

DERIVATIVE DISPERSION RELATIONS FOR THE AMPLITUDE SLOPES IN pp AND $\bar{p}p$ SCATTERING

ERASMO FERREIRA

Universidade Federal do Rio de Janeiro,

P.O.Box 68528 Rio de Janeiro,

RJ 22461-200, Brazil

erasmo@if.ufrj.br

Abstract

We extend the use of derivative dispersion relations to the study of slopes of the real and imaginary amplitudes in pp and $\bar{p}p$ elastic scattering. The new relations are tested against the solutions for the amplitudes obtained in the analysis of the high energy data. Extensions beyond the forward direction are investigated.

I. INTRODUCTION

Derivative Dispersion Relations (DDR) for $|t| = 0$ have received much interest [1, 2], but their extensions to general momentum transfers $|t|$ have been very limited [3], due, in the practical aspects, to the absence of knowledge on the imaginary and real hadronic amplitudes for arbitrary t . However, a treatment of the pp and $\bar{p}p$ data has proposed a solution for the amplitudes [4, 5], which is likely realistic as a phenomenological description. This solution can be tested through DDR written for arbitrary $|t|$, and this is the purpose of the present work.

The momentum transfer t enters as a parameter in the s -channel dispersion relations. Thus in a simplest form of DDR, to be applied to pp and $\bar{p}p$ scattering at high energies, we write [1, 2], for the even and odd combinations

$$\frac{\text{Re}F_+(s, t)}{s} = \frac{K}{s} + \left[\tan \left(\frac{\pi}{2} \frac{d}{d \log s} \right) \right] \left[\frac{\text{Im}F_+(s, t)}{s} \right], \quad (1.1)$$

$$\frac{\pi}{2} \frac{d}{d \log s} \left[\frac{\text{Re}F_-(s, t)}{s} \right] = - \left[\left(\frac{\pi}{2} \frac{d}{d \log s} \right) \cot \left(\frac{\pi}{2} \frac{d}{d \log s} \right) \right] \left[\frac{\text{Im}F_-(s, t)}{s} \right]. \quad (1.2)$$

The amplitudes for the pp and $\bar{p}p$ channels are $F_{pp} = F_+ + F_-$ and $F_{\bar{p}p} = F_+ - F_-$. The normalization for each channel (pp or $\bar{p}p$) is defined by the optical theorem $\sigma(s) = \text{Im}F(s, t=0)/s$. The ratio $\rho(s) = \text{Re}F(s, t=0)/\text{Im}F(s, t=0)$ of real to imaginary amplitude at $t=0$ and the exponential slope are characteristic parameters of elastic scattering. With amplitudes described at low $|t|$ by exponential slopes, we write for each channel, $\text{Re}F(s, t) = \text{Re}F(s, 0) \exp(-B^R|t|/2)$, $\text{Im}F(s, t) = \text{Im}F(s, 0) \exp(-B^I|t|/2)$.

II. DDR FOR $t=0$

In terms of experimentally measured quantities the DDR for the even and odd amplitudes with $t=0$ are written respectively

$$\frac{1}{2} \left(\sigma_{pp} \rho_{pp} + \sigma_{\bar{p}p} \rho_{\bar{p}p} \right) = \frac{K}{s} + \frac{1}{2} \left[\frac{\pi}{2} \frac{d}{d \log s} + \frac{1}{3} \left(\frac{\pi}{2} \frac{d}{d \log s} \right)^3 + \dots \right] \left[\sigma_{pp} + \sigma_{\bar{p}p} \right], \quad (2.1)$$

$$\frac{1}{2} \frac{\pi}{2} \frac{d}{d \log s} \left[\sigma_{pp} \rho_{pp} - \sigma_{\bar{p}p} \rho_{\bar{p}p} \right] = - \frac{1}{2} \left[1 - \frac{1}{3} \left(\frac{\pi}{2} \frac{d}{d \log s} \right)^2 - \dots \right] \left[\sigma_{pp} - \sigma_{\bar{p}p} \right]. \quad (2.2)$$

We parametrize the total cross-sections with two alternative forms

$$\sigma = D + d_0 \log^2(s/s_0) + d_1 s^{-\mu_1} - \tau a_2 s^{-\eta_2}, \quad (2.3)$$

$$\text{and} \quad \sigma = a_0 s^\epsilon + a_1 s^{-\eta_1} - \tau a_2 s^{-\eta_2} . \quad (2.4)$$

where $\tau = +1$ and -1 for pp and $\bar{\text{p}}\text{p}$ respectively, s is in GeV^2 , and $s_0 = 25 \text{ GeV}^2$.

Using these representations for σ , we use $d^n s^\lambda / d \log s^n = \lambda^n s^\lambda$, and may write in closed forms the RHS terms of Eqs. (2.1), (2.2). We thus have for the even-DDR

$$\frac{1}{2} \left(\sigma_{\text{pp}} \rho_{\text{pp}} + \sigma_{\bar{\text{p}}\text{p}} \rho_{\bar{\text{p}}\text{p}} \right) = \frac{K}{s} + 2d_0 \left(\frac{\pi}{2} \right) \log(s/s_0) - d_1 \tan \left(\frac{\pi}{2} \mu_1 \right) s^{-\mu_1} , \quad (2.5)$$

$$\frac{1}{2} \left(\sigma_{\text{pp}} \rho_{\text{pp}} + \sigma_{\bar{\text{p}}\text{p}} \rho_{\bar{\text{p}}\text{p}} \right) = \frac{K}{s} + a_0 \tan \left(\frac{\pi}{2} \epsilon \right) s^\epsilon - a_1 \tan \left(\frac{\pi}{2} \eta_1 \right) s^{-\eta_1} , \quad (2.6)$$

respectively for the squared log and power representations of the cross sections. The series would not converge for non-integer powers of $\log s$.

The RHS of the odd-DDR is the same for both representations,

$$\text{RHS(odd)} = a_2 \left[1 - \frac{1}{3} \left(\frac{\pi}{2} \eta_2 \right)^2 - \dots \right] s^{-\eta_2} = a_2 \left(\frac{\pi}{2} \eta_2 \right) \cot \left(\frac{\pi}{2} \eta_2 \right) s^{-\eta_2} . \quad (2.7)$$

Then the whole odd-DDR in Eq.(2.2) can be integrated (from infinity to s), giving

$$\frac{1}{2} \left[\sigma_{\text{pp}} \rho_{\text{pp}} - \sigma_{\bar{\text{p}}\text{p}} \rho_{\bar{\text{p}}\text{p}} \right] = -a_2 \cot \left(\frac{\pi}{2} \eta_2 \right) s^{-\eta_2} = \frac{1}{2} \cot \left(\frac{\pi}{2} \eta_2 \right) \left[\sigma_{\text{pp}} - \sigma_{\bar{\text{p}}\text{p}} \right] . \quad (2.8)$$

This relation connects observable quantities, without derivative operations. These DDR for $|t| = 0$ have been tested against experimental values of ρ_{pp} and $\rho_{\bar{\text{p}}\text{p}}$.

III. DDR FOR AMPLITUDE SLOPES

The purpose of the present work is to examine the validity of DDR beyond the forward direction. We here present results for the amplitude slopes. Taking the exponential forms for the amplitudes into Eq.(1.1), expanding for small $|t|$, and taking into account that DDR at $|t| = 0$ are valid, we obtain from the even DDR, to first order in $|t|$,

$$B_{\text{pp}}^R \sigma_{\text{pp}} \rho_{\text{pp}} + B_{\bar{\text{p}}\text{p}}^R \sigma_{\bar{\text{p}}\text{p}} \rho_{\bar{\text{p}}\text{p}} = \tan \left[\frac{\pi}{2} \frac{d}{d \log s} \right] [B_{\text{pp}}^I \sigma_{\text{pp}} + B_{\bar{\text{p}}\text{p}}^I \sigma_{\bar{\text{p}}\text{p}}] . \quad (3.1)$$

Analogously from the odd DDR we obtain

$$\frac{d}{d \log s} \left[B_{\text{pp}}^R \rho_{\text{pp}} \sigma_{\text{pp}} - B_{\bar{\text{p}}\text{p}}^R \rho_{\bar{\text{p}}\text{p}} \sigma_{\bar{\text{p}}\text{p}} \right] = - \left[\left(\frac{d}{d \log s} \right) \cot \left(\frac{\pi}{2} \frac{d}{d \log s} \right) \right] [B_{\text{pp}}^I \sigma_{\text{pp}} - B_{\bar{\text{p}}\text{p}}^I \sigma_{\bar{\text{p}}\text{p}}] . \quad (3.2)$$

To evaluate these expressions we need to know the amplitude slopes and their energy dependences. Following the results obtained in the analysis of data [5], we assume that the

imaginary slopes are the same for the pp and $\bar{p}p$ channels, with linear dependences in $\log s$.
Thus

$$B_{pp}^I = B_{\bar{p}p}^I = B^I(s) = c_1^I + c_2^I \log s . \quad (3.3)$$

Using the relations

$$\frac{d^n}{d(ax)^n} [xZ(x)] = \frac{n}{a} \frac{d^{n-1}}{d(ax)^{n-1}} [Z(x)] + x \frac{d^n}{d(ax)^n} [Z(x)]$$

we can operate with the series expansions and obtain closed forms for the slope DDR. The expressions that we need are

$$\tan\left(\frac{\pi}{2} \frac{d}{d \log s}\right) [\log s \ Z(s)] = \log s \ \tan\left(\frac{\pi}{2} \frac{d}{d \log s}\right) [Z(s)] + \frac{\pi}{2} \sec^2\left(\frac{\pi}{2} \frac{d}{d \log s}\right) [Z(s)] ,$$

and

$$\begin{aligned} & \frac{\pi}{2} \frac{d}{d \log s} \cot\left(\frac{\pi}{2} \frac{d}{d \log s}\right) [\log s \ Z(s)] = \\ & \log s \ \frac{\pi}{2} \frac{d}{d \log s} \cot\left(\frac{\pi}{2} \frac{d}{d \log s}\right) [Z(s)] + \frac{\pi}{2} \left[\cot\left(\frac{\pi}{2} \frac{d}{d \log s}\right) - \frac{\pi}{2} \frac{d}{d \log s} \operatorname{cosec}^2\left(\frac{\pi}{2} \frac{d}{d \log s}\right) \right] [Z(s)] . \end{aligned}$$

To study the odd DDR, we use the parametrizations of σ , and write

$$\begin{aligned} & \frac{\pi}{2} \frac{d}{d \log s} \left[B_{pp}^R \rho_{pp} \sigma_{pp} - B_{\bar{p}p}^R \rho_{\bar{p}p} \sigma_{\bar{p}p} \right] = \\ & - \left(\frac{\pi}{2} \frac{d}{d \log s} \right) \cot\left(\frac{\pi}{2} \frac{d}{d \log s}\right) \left[(c_1^I + c_2^I \log(s)) (\sigma_{pp} - \sigma_{\bar{p}p}) \right] = \\ & 2a_2 \ s^{-\eta_2} \left[B^I \left[\frac{\pi}{2} \eta_2 \cot\left(\frac{\pi}{2} \eta_2\right) \right] + c_2^I \frac{\pi}{2} \left[-\cot\left(\frac{\pi}{2} \eta_2\right) + \frac{\pi}{2} \eta_2 \operatorname{cosec}^2\left(\frac{\pi}{2} \eta_2\right) \right] \right] . \end{aligned} \quad (3.4)$$

Integrating both sides from infinity to s we have for the odd DDR for slopes

$$B_{pp}^R \rho_{pp} \sigma_{pp} - B_{\bar{p}p}^R \rho_{\bar{p}p} \sigma_{\bar{p}p} = -2a_2 \ s^{-\eta_2} \left[B^I \cot\left(\frac{\pi}{2} \eta_2\right) + c_2^I \frac{\pi}{2} \operatorname{cosec}^2\left(\frac{\pi}{2} \eta_2\right) \right] . \quad (3.5)$$

For the even DDR for slopes we have to consider two cases separately.

I- σ of $\log^2(s)$ kind, Eq.(2.3). We obtain

$$\begin{aligned} & B_{pp}^R \sigma_{pp} \rho_{pp} + B_{\bar{p}p}^R \sigma_{\bar{p}p} \rho_{\bar{p}p} = B^I [2\pi d_0 \log(s/s_0) - 2d_1 \tan\left(\frac{\pi}{2} \mu_1\right) s^{-\mu_1}] \\ & + c_2^I \pi [d_0 \log^2(s/s_0) + d_0 \frac{\pi^2}{2} + D + d_1 \sec^2\left(\frac{\pi}{2} \mu_1\right) s^{-\mu_1}] . \end{aligned} \quad (3.6)$$

II- σ of s^ϵ kind, Eq. (2.4). We here obtain

$$\begin{aligned} & B_{pp}^R \sigma_{pp} \rho_{pp} + B_{\bar{p}p}^R \sigma_{\bar{p}p} \rho_{\bar{p}p} = B^I [2a_0 \tan\left(\frac{\pi}{2} \epsilon\right) s^\epsilon - 2a_1 \tan\left(\frac{\pi}{2} \eta_1\right) s^{-\eta_1}] \\ & + c_2^I \pi [a_0 \sec^2\left(\frac{\pi}{2} \epsilon\right) s^\epsilon + a_1 \sec^2\left(\frac{\pi}{2} \eta_1\right) s^{-\eta_1}] . \end{aligned} \quad (3.7)$$

Knowing the imaginary slope we may draw lines representing the RHS of the DDR for slopes. The LHS is given by the data, using B^R slopes of the pp and $\bar{p}p$ amplitudes [5]. The results are shown in Fig. III, where we observe compatibility, confirming both the values of the slopes and the adequacy of the new dispersion relations.

FIG. 1: The experimental points (full circles and error bars) represent the LHS of the even and odd DDR for slopes. The lines represent the RHS of Eqs. (3.6), (3.7) and (3.5), with (for the even case) full line for σ of form $\log^2(s/s_0)$ and dashed line for the form with s^ϵ .

Acknowledgements

The author is grateful to CNPq (Brazil) for support of his scientific research.

-
- [1] R.F. Ávila and M.J. Menon, Nucl. Phys. **A744** (2004), 249; M.J. Menon, A.E. Motter and B.M. Pimentel, Phys. Lett. **B451** (1999), 207.
 - [2] K. Kand and B. Nicolescu, Phys. Rev. **D11** (1975), 2461 .
 - [3] J.B. Bronzan, G.L. Kane and U.P. Sukhatme, Phys. Lett. **B49** (1974), 272.
 - [4] F. Pereira and E. Ferreira, Phys. Rev. **D59** (1999), 014008 ; Phys. Rev. **D61**(2000), 077507.
 - [5] E. Ferreira and F. Pereira, "Amplitudes in pp and $\bar{p}p$ scattering", in this volume, Int. Jour. Mod. Phys. E , 2007.



