

On sampling theorem with sparse decimated samples

Nikolai Dokuchaev

Submitted: May 2, 2016. Revised: June 3, 2016

Abstract

The classical sampling Nyquist-Shannon-Kotelnikov theorem states that a band-limited continuous time function is uniquely defined by infinite two-sided sampling series taken with a sufficient frequency. The paper shows that these band-limited functions allows an arbitrarily close uniform approximation by functions that are uniquely defined by their extremely sparse subsamples representing arbitrarily small fractions of one-sided equidistant sample series with fixed oversampling parameter. In particular, an arbitrarily small adjustment of a band-limited underlying function makes redundant every $(m-1)$ members of any set of m samples for an arbitrarily large m . This allows to bypass, in a certain sense, the restriction on the sampling rate defined by the critical Nyquist rate.

Keywords: sampling, bandlimitness, missing values, one-sided sequences, sparse samples.

MSC 2010 classification : 94A20, 94A12, 93E10

1 Introduction

The paper suggests a modification of the classical sampling theorem that is also known as Nyquist-Shannon theorem, Nyquist-Shannon-Kotelnikov theorem, Whittaker-Shannon-Kotelnikov theorem, Whittaker-Nyquist-Kotelnikov-Shannon theorem, which is one of the most basic results in the theory of signal processing and information science. This theorem states that any band-limited function can be uniquely recovered without error from a infinite two-sided equidistant sampling sequence taken with sufficient frequency. This result was obtained independently by four authors [21, 11, 10, 14]. The theorem imposes a restriction on the sampling rate defined by the critical Nyquist rate as the lower boundary of the sampling rate allowing recovery of the underlying function. Numerous extensions of this theorem were obtained, including the case of nonuniform sampling and restoration of the signal with mixed samples; see some recent literature review in [1, 8, 17, 19, 22]. There were many works

The author is with Department of Mathematics and Statistics, Curtin University, GPO Box U1987, Perth, Western Australia, 6845 (email N.Dokuchaev@curtin.edu.au).

devoted to reducing the set of sampling points required for restoration of the underlying functions. In particular, it is known that a bandlimited function can be recovered without error from an oversampling sample sequence if a finite number of sample values is unknown. It is known [18] that the function can be recovered without error with a missing one-sided half of any oversampling sample sequence. It is also known [7] that the function can be recovered without error with a missing equidistant infinite subsequence consistent of n th member of the original sample sequence, i.e. that each n th member is redundant, under some additional constraints on the oversampling parameter. The constraints are such that the oversampling parameter is increasing if $n \geq 2$ is decreasing.

The present paper readdress the problem of reducing the sample required for reconstruction of the underlying continuous time band-limited function. We show that an arbitrarily small adjustment of a band-limited underlying function makes redundant every $(m - 1)$ members of any subset of m samples from an one-sided equidistant sample (Theorem 1 and Corollary 1). This m can be selected arbitrarily large, without increasing of oversampling parameter for the underlying sampling points. This allows to bypass, in a certain sense, the restriction on the sampling rate described by the critical Nyquist rate. The corresponding recovery algorithm is based on a pathwise predicting algorithm (Proposition 2). In addition, we establish the robustness of recovering algorithm with respect to the noise contamination.

2 Some definitions

We denote by $L_2(D)$ the usual Hilbert space of complex valued square integrable functions $x : D \rightarrow \mathbf{C}$, where D is a domain.

For $f \in L_2(\mathbf{R})$, we denote by $F = \mathcal{F}f$ the function defined on $i\mathbf{R}$ as the Fourier transform of f ;

$$F(i\omega) = (\mathcal{F}f)(i\omega) = \int_{-\infty}^{\infty} e^{-i\omega t} f(t) dt, \quad \omega \in \mathbf{R}.$$

Here $i = \sqrt{-1}$ is the imaginary unit. For $f \in L_2(\mathbf{R})$, the Fourier transform F is defined as an element of $L_2(i\mathbf{R})$, i.e. $F(i\cdot) \in L_2(\mathbf{R})$.

For $\Omega > 0$, let $L_2^{BL,\Omega}(\mathbf{R})$ be the subset of $L_2(\mathbf{R})$ consisting of functions f such that $f(t) = (\mathcal{F}^{-1}F)(t)$, where $F(i\omega) \in L_2(i\mathbf{R})$ and $F(i\omega) = 0$ for $|\omega| > \Omega$.

We denote by \mathbb{Z} the set of all integers. Let $\mathbb{Z}^+ = \{m \in \mathbb{Z} : m > 0\}$.

3 The main results

Let us formulate first an one-sided modification of Nyquist-Shannon-Kotelnikov Theorem; this modification is known and follows from the result [18].

Lemma 1 Let $\Omega > 0$ and $\tau \in (0, \pi/\Omega)$ be given. Let $\{t_k\}_{k \in \mathbb{Z}} \subset \mathbf{R}$ be a sequence such that $t_k = \tau k$, $k \in \mathbb{Z}$. Then, for any $s \in \mathbb{Z}$, a band-limited function $f \in L_2^{BL, \Omega}(\mathbf{R})$ is uniquely defined by the values $\{f(t_k)\}_{k \leq s}$.

In particular, Lemma 1 implies that, for any finite set S , $f \in L_2^{BL, \Omega}(\mathbf{R})$ is uniquely defined by the values $\{f(t_k)\}_{k \in \mathbb{Z} \setminus S}$; this was established in [6] by a different method. We cannot claim the same for some infinite sets of missing values. For example, it may happen that $f \in L_2^{BL, \Omega}(\mathbf{R})$ is not uniquely defined by the values $\{f(t_{2k})\}_{k \in \mathbb{Z}}$, if the sampling rate for this sample $\{f(t_{2k})\}_{k \in \mathbb{Z}}$ is lower than is required by the Nyquist-Shannon-Kotelnikov Theorem; see more examples in [7].

The main result of the present paper is given by the following theorem.

Theorem 1 Let $m \in \mathbb{Z}^+$ be given, and let $m \geq 2$. Let $\Omega > 0$ and $\tau \in (0, \pi/\Omega)$ be given. Let

$$s_k = \frac{2\pi k - \pi}{\tau m}, \quad k = 0, 1, \dots, m-1.$$

For $\delta > 0$, let

$$\mathcal{I}_\delta = \{\omega \in \mathbf{R} : \min_{k=0,1,\dots,m-1} |\omega - s_k| \leq \delta\}. \quad (1)$$

Let $f \in L_2^{BL, \Omega}(\mathbf{R})$ be such that there exists $\delta > 0$ such that

$$F(i\omega) = 0 \quad \text{for } \omega \in \mathcal{I}_\delta, \quad (2)$$

where $F = \mathcal{F}^{-1}f$. Let $\{t_k\}_{k \in \mathbb{Z}} \subset \mathbf{R}$ be a sequence of sampling points defined as $t_k = \tau k$. Then, for any $s \in \mathbb{Z}$, a band-limited function $f \in L_2^{BL, \Omega}(\mathbf{R})$ is uniquely defined by the values $\{f(t_{mk-1})\}_{k \leq s}$.

Corollary 1 Let $\Omega > 0$, $f \in L_2^{BL, \Omega}(\mathbf{R})$, and $\tau \in (0, \pi/\Omega)$, be given. Then for any $\varepsilon > 0$ there exists $\delta = \delta(\varepsilon) > 0$ such that $\sup_{t \in \mathbf{R}} |f(t) - f_\delta(t)| \leq \varepsilon$, where $f_\delta \triangleq \mathcal{F}^{-1}(F \mathbb{I}_{\mathcal{I}_\delta})$, $F = \mathcal{F}f$. This f_δ satisfies assumptions of Theorem 1 and is uniquely defined by the values $\{f_\delta(t_{mk-1})\}_{k \leq s}$.

Remark 1 In Theorem 1 and Corollary 1, the values δ and ε can be selected arbitrarily small, and m can be selected arbitrarily large. This means that selection of a large m and an arbitrarily small adjustment of a band-limited function f (i.e. replacement f by f_δ defined in Corollary 1) makes redundant every $(m-1)$ members among any set of m samples. Since m can be arbitrarily large, the fraction of remaining samples that we need for recovery can be arbitrarily small.

Remark 2 The value $\tau = \pi/\Omega$ is excluded in Lemma 1 and Theorem 1, meaning that the series $\{t_k\}$ oversamples f ; this is essential for the proof. This value is allowed in the classical Nyquist-Shannon-Kotelnikov Theorem with two-sided sampling series that states that $f \in L_2^{BL, \Omega}(\mathbf{R})$ is uniquely defined by the values $\{f(t_k)\}_{k \in \mathbb{Z}}$ if $\tau \in (0, \Omega/\pi]$.

Remark 3 In the proof given below, we suggest an algorithm of calculation of the complete sample $\{f(t_k)\}_{k \in \mathbb{Z}}$ from the set of values $\{f(t_{2m+1})\}_{k \leq s}$. This leads to recovery of f by standard methods.

Remark 4 Theorem 1 consider a subsequence of the left hand half of the sampling series; it is convenient for representation of past historical observations, for instance, for predicting problems. However, a similar statement can be formulated for a subsequence of the right hand half of the sampling series.

4 Proofs

Some preliminary definitions and results

Let us introduce some additional notations first.

For $r \in [1, +\infty]$, we denote by ℓ_r the set of all sequences $x = \{x(k)\}_{k \in \mathbb{Z}} \subset \mathbf{C}$, such that $\|x\|_{\ell_r} = (\sum_{k=-\infty}^{\infty} |x(k)|^r)^{1/r} < +\infty$ for $r \in [1, \infty)$ or $\|x\|_{\ell_\infty} = \sup_{k \in \mathbb{Z}} |x(k)| < +\infty$ for $r = +\infty$.

We denote by $L_r(-\pi, \pi)$ the usual Banach space of complex valued L_r -integrable functions $x : [-\pi, \pi] \rightarrow \mathbf{C}$.

Let $D^c \triangleq \{z \in \mathbf{C} : |z| > 1\}$, and let $\mathbb{T} = \{z \in \mathbf{C} : |z| = 1\}$.

For $x \in \ell_2$, we denote by $X = \mathcal{Z}x$ the Z-transform

$$X(z) = \sum_{k=-\infty}^{\infty} x(k)z^{-k}, \quad z \in \mathbb{T}.$$

Respectively, the inverse Z-transform $x = \mathcal{Z}^{-1}X$ is defined as

$$x(k) = \frac{1}{2\pi} \int_{-\pi}^{\pi} X(e^{i\omega}) e^{i\omega k} d\omega, \quad k = 0, \pm 1, \pm 2, \dots$$

For $x \in \ell_2$, the trace $X|_{\mathbb{T}}$ is defined as an element of $L_2(\mathbb{T})$.

Let $H^r(D^c)$ be the Hardy space of functions that are holomorphic on D^c including the point at infinity with finite norm $\|h\|_{H^2(D^c)} = \sup_{\rho > 1} \|h(\rho e^{i\omega})\|_{L_r(-\pi, \pi)}$, $r \in [1, +\infty]$.

For $W \in (0, \pi)$, let $\mathbb{L}^W(\mathbb{T})$ be the set of all mappings $X : \mathbb{T} \rightarrow \mathbf{C}$ such that $X(e^{i\omega}) \in L_2(-\pi, \pi)$ and $X(e^{i\omega}) = 0$ for $|\omega| > W$. We will call the corresponding processes $x = \mathcal{Z}^{-1}X$ *band-limited*.

For $s \in \mathbb{Z}$, we denote by $\ell_2(-\infty, s)$ the set of all sequences $x = \{x(k)\}_{k \leq s} \subset \mathbf{C}$, such that $\sum_{k=-\infty}^s |x(k)|^2 < +\infty$.

Let ℓ_2^{BL} be the subset of ℓ_2 consisting of sequences $\{x(k)\}_{k \in \mathbb{Z}}$ such that $x = \mathcal{Z}^{-1}X$ for some $X(e^{i\omega}) \in \cup_{W \in (0, \pi)} \mathbb{L}^W(\mathbb{T})$. Let $\ell_2^{BL}(-\infty, s)$ be the subset of $\ell_2(-\infty, s)$ consisting of traces $\{x(k)\}_{k \leq s}$ of all $x \in \ell_2^{BL}$.

Proposition 1 For any $x \in \ell_2^{BL}(-\infty, s)$, there exists an unique $X \in \cup_{W \in (0, \pi)} \mathbb{L}^W(\mathbb{T})$ such that $x(k) = (\mathcal{Z}^{-1}X)(k)$ for $k \leq s$.

By Lemma 1, the future $\{x(k)\}_{k>s}$ of a band-limited process $x = \mathcal{Z}^{-1}X$, $X \in \mathbb{L}^W(\mathbb{T})$, is uniquely defined by its history $\{x(k)\}_{k \leq s}$. This statement represent a reformulation in the deterministic setting of the classical Szegő-Kolmogorov Theorem for stationary Gaussian processes [9, 15, 16, 20].

Proof of Proposition 1. The proof follows from predictability results for band-limited discrete time processes obtained in [2, 3]. For completeness, we will provide a direct and independent proof. (This proof can be found in [4]). Let $D \triangleq \{z \in \mathbb{C} : |z| < 1\}$. It suffices to prove that if $x(\cdot) \in \ell_2^{BL}$ is such that $x(k) = 0$ for $k \leq s$, then either $x(k) = 0$ for $k > s$ or $x \notin \ell_2^{BL}$. If $x(k) = 0$ for $k > s$, then $X = \mathcal{Z}x = z^s Y(z)$, where $Y \in H^2(D^c)$. Hence, by the property of the Hardy space, $Y \notin \cup_{W \in (0, \pi)} \mathbb{L}^W(\mathbb{T})$; see e.g. Theorem 17.18 from [13]. This completes the proof of Proposition 1. \square

Proof of Lemma 1

The result of the lemma is known [18]. We provide a different proof since we will use this proof for the proof of Theorem 1.

Consider a sequence of samples

$$x(k) = f(t_k) = \frac{1}{2\pi} \int_{-\Omega}^{\Omega} F(i\omega) e^{i\omega t_k} d\omega, \quad k = 0, \pm 1, \pm 2, \dots$$

Since $t_k = k\tau$, we have that

$$x(k) = \frac{1}{2\pi\tau} \int_{-\tau\Omega}^{\tau\Omega} F(i\nu/\tau) e^{i\nu k} d\nu = \frac{1}{2\pi} \int_{-\tau\Omega}^{\tau\Omega} G(e^{i\nu}) e^{i\nu k} d\nu.$$

Here G is such that $G(e^{i\nu}) = \tau^{-1}F(i\nu/\tau)$. We used here a change of variables $\nu = \omega\tau$. Since $F(i\nu/\tau) \in L_2(i\mathbb{R})$, it follows that $G(e^{i\nu}) \in L_2(\mathbb{T})$. By the assumption that $\tau < \pi/\Omega$, it follows that $\tau\Omega < \pi$ and $x \in \ell_2^{BL}$. By the Nyquist-Shannon-Kotelnikov Theorem, it follows that the function f is uniquely defined by the two-sided sequence $\{x(k)\}_{k \in \mathbb{Z}} = \{f(t_k)\}_{k \in \mathbb{Z}}$. Further, Lemma 1 implies that a sequence from ℓ_2^{BL} is uniquely defined by its trace on the set $\{k \leq 0\}$. Hence the sequence $\{x(k)\}_{k \leq 0}$ defined uniquely the sequence $\{x(k)\}_{k \in \mathbb{Z}}$, and this sequence defines uniquely G as well as F and f . This completes the proof of Lemma 1. \square

Proof of Theorem 1

It suffices to proof the theorem for $s = 0$ only; the extension on $s \neq 0$ is straightforward.

Let \mathcal{V} be the set of all $x \in \ell_2$ such that $\|x\|_{\ell_2} \leq 1$ and

$$X(e^{i\omega}) = 0 \quad \text{for } \omega \in J_\delta, \tag{3}$$

where $X = \mathcal{Z}^{-1}x$,

$$J_\delta = \{\omega \in (-\pi, \pi] : \min_{k=0,1,\dots,m-1} |\omega - \tau s_k| \leq \delta\tau\}. \quad (4)$$

Let \mathcal{H} be the set of all $h \in \ell_\infty$ such that the following holds:

- (i) $h = \mathcal{Z}^{-1}H$ for some $H \in H^\infty(D^c)$;
- (ii) $h(d) = 0$ if $(d+1)/m \notin \mathbb{Z}$, $d \in \mathbb{Z}$,
- (iii) $h(d) = 0$ for all negative $d \in \mathbb{Z}$.

Proposition 2 *The class \mathcal{V} is predictable in the following sense: for any $\varepsilon > 0$, there exists $\hat{h} \in \mathcal{H}$ such that*

$$\|y(k) - \hat{y}(k)\|_{\ell_\infty} \leq \varepsilon \quad (5)$$

for any $x \in \mathcal{V}$, where

$$y(k) = x(k+1), \quad \hat{y}(k) \triangleq \sum_{d=-\infty}^k \hat{h}(k-d)x(d). \quad (6)$$

In (6), $\hat{y} = \hat{h} \circ x$; we use the sign \circ for the convolution in ℓ_2 . The process \hat{y} is the output of a linear predictor defined by the kernel \hat{h} .

Proof of Proposition 2. We will prove that the predicting can be ensured by kernels $\hat{h} = \mathcal{Z}^{-1}\hat{H}$, where

$$\hat{H}(z) \triangleq zV(z^m), \quad (7)$$

and where

$$V(z) \triangleq 1 - \exp\left[-\frac{\gamma}{z+\alpha}\right], \quad (8)$$

where $\alpha = 1 - \gamma^{-r}$ and where $r > 0$ and $\gamma > 0$ are parameters. This function V was introduced in [2]. (In the notations from [2], $r = 2\mu/(q-1)$, where $\mu > 1$, $q > 1$ are the parameters). This predictor produces the process $\hat{y}(t)$ approximating $y(t) = x(t+1)$ as $\gamma \rightarrow +\infty$ for all inputs $x \in \mathcal{V}$.

Let $W(\alpha) = \arccos(-\alpha)$, let $D_+(\alpha) = (-W(\alpha), W(\alpha))$, and let $D(\alpha) \triangleq [-\pi, \pi] \setminus D_+(\alpha)$. We have that $\cos(W(\alpha)) + \alpha = 0$, $\cos(\omega) + \alpha > 0$ for $\omega \in D_+(\alpha)$, and $\cos(\omega) + \alpha < 0$ for $\omega \in D(\alpha)$.

Note that $\alpha = \alpha(\gamma) \rightarrow 1$ as $\gamma \rightarrow +\infty$.

It was shown in [2] that the following holds:

- (i) $V(z) \in H^\infty(D^c)$ and $zV(z) \in H^\infty(D^c)$.

(ii) $V(e^{i\omega}) \rightarrow 1$ for all $\omega \in (-\pi, \pi)$ as $\gamma \rightarrow +\infty$.

(iii) If $\omega \in D_+(\alpha)$ then $\operatorname{Re} \left(\frac{\gamma}{e^{i\omega} + \alpha} \right) > 0$ and $|V(e^{i\omega}) - 1| \leq 1$.

The definitions imply that there exists $\gamma_0 > 0$ such that for any $\gamma \geq \gamma_0$ and for V selected with $\alpha = \alpha(\gamma)$ we have $\sup_{\omega \in (-\pi, \pi] \setminus J_\delta} |V(e^{i\omega}) - 1| \leq 1$.

Let

$$Q(\alpha) = \cup_{k=0}^{m-1} \left(\frac{W(\alpha) + 2\pi k}{m}, \frac{2\pi - W(\alpha) + 2\pi k}{m} \right), \quad Q_+(\alpha) = [-\pi, \pi] \setminus Q(\alpha).$$

From the properties of V , it follows that the following holds.

(i) $V(z^m) \in H^\infty(D^c)$ and $\widehat{H}(z) = zV(z^m) \in H^\infty(D^c)$.

(ii) $V(e^{im\omega}) \rightarrow 1$ for all $\omega \in (-\pi, \pi] \setminus \{\tau s_k\}_{k=0}^{m-1}$ as $\gamma \rightarrow +\infty$.

(iii) If $\omega \in Q_+(\alpha)$ then $\operatorname{Re} \left(\frac{\gamma}{e^{im\omega} + \alpha} \right) > 0$ and $|V(e^{im\omega}) - 1| \leq 1$.

In addition, we have that $v = \mathcal{Z}^{-1}V$ is such that $v(0) = 0$. It follows that $V(z^m) = z^{-m}v(1) + z^{-2m}v(2) + z^{-3m}v(3) \dots$. Hence $\widehat{H}(z) = zV(z^m)$ belongs to the class \mathcal{H} .

Suppose that we are given $x \in \mathcal{V}$, $\widehat{h} = \mathcal{Z}^{-1}\widehat{H}$, $X \triangleq \mathcal{Z}x$, and

$$y(t) \triangleq x(t+1), \quad \widehat{y}(t) \triangleq \sum_{s=-\infty}^t \widehat{h}(t-s)x(s).$$

This means that $Y(z) = zX(z)$, $\widehat{Y} = \mathcal{Z}\widehat{y} = \widehat{H}X$.

Suppose that $\gamma \rightarrow +\infty$. Let us show that this implies that

$$\sup_{t \in \mathbb{Z}} |x(k+1) - y(k)| \rightarrow 0.$$

We have that $\|Y(e^{i\omega}) - \widehat{Y}(e^{i\omega})\|_{L_1(-\pi, \pi)} = I_1 + I_2$, where

$$I_1 = \int_{Q(\alpha)} |Y(e^{i\omega}) - \widehat{Y}(e^{i\omega})| d\omega, \quad I_2 = \int_{Q_+(\alpha)} |Y(e^{i\omega}) - \widehat{Y}(e^{i\omega})| d\omega.$$

By the definitions, there exists $\gamma_0 > 0$ such that, for all $\gamma > \gamma_0$, we have that

$$Q(\alpha) \subset \mathcal{I}_\delta, \tag{9}$$

and $I_1 = 0$. It follows that $I_1 \rightarrow 0$ as $\gamma \rightarrow +\infty$ uniformly over $x \in \mathcal{V}$.

Let us estimate I_2 . By the known properties of V , we have that $|V(e^{im\omega}) - 1| \leq 1$ for all $\omega \in Q_+(\alpha)$. We have that

$$I_2 = \int_{Q(\alpha)} |e^{i\omega}(1 - V(e^{im\omega}))X(e^{i\omega})| d\omega \leq \|1 - V(e^{im\omega})\|_{L_2(Q_+(\alpha))} \|X(e^{i\omega})\|_{L_2(-\pi, \pi)}.$$

We have that $\mathbb{I}_{Q_+(\alpha)}(\omega)|1 - V(e^{2i\omega})| \rightarrow 0$ a.e. as $\gamma \rightarrow +\infty$, where \mathbb{I} is the indicator function. We have that

$$\mathbb{I}_{Q_+(\alpha)}(\omega)|1 - V(e^{im\omega})| \leq 1.$$

From Lebesgue Dominance Theorem, it follows that $\|1 - V(e^{im\omega})\|_{L_2(Q_+(\alpha))} \rightarrow 0$ as $\gamma \rightarrow +\infty$. It follows that $I_1 + I_2 \rightarrow 0$ uniformly over $x \in \mathcal{V}$. Hence $\|\hat{y} - y\|_{\ell_\infty} \rightarrow 0$ as $\gamma \rightarrow +\infty$ uniformly over $x \in \mathcal{V}$. It follows that the predicting kernels $\hat{h}(\cdot) = \mathcal{Z}^{-1}\hat{H}$ are such as required. This completes the proof of Proposition 2. \square

Corollary 2 *For any $x \in \mathcal{V}$ and any $s \in \mathbb{Z}$, the sequence $\{x(mk - 1)\}_{k \leq s}$ uniquely defines x .*

Proof of Corollary 2. It suffices to prove that if x is such that $x(k) = 0$ for $k \leq s$, then $x(k) = 0$ for $k > s$. Let us apply predictability established above to a process $x \in \mathcal{V}$ such that $x(k) = 0$ for $k \leq s$. Let $y(k) \triangleq \sum_{d=-\infty}^k \hat{h}(k-d)x(d)$, where \hat{h} are selected as above, with $\gamma \rightarrow +\infty$. Clearly, $y(k) = 0$ if $k \leq s$. It follows from the predictability of x established in Proposition 2 that $x(1) = 0$.

Further, let us apply the proof given above to the process $x_1(k) = x(k+1)$. Clearly, $x_1 \in \mathcal{V}$ and $x_1(k) = 0$ for $k < s$. Similarly, we obtain that $x_1(k) = 0$ for all $k \leq s+1$. Repeating this procedure n times, we obtain that $x(k) = 0$ for all $k < s+n$ for all n . This completes the proof of Corollary 2. \square

We are now in the position to complete Theorem 1. Let $x(k) = f(t_k)$, $k \in \mathbb{Z}$. In the notations of the proofs of Lemma 1 and Proposition 2, we have that the function $G : \mathbb{T} \rightarrow \mathbb{C}$ is such that $G(e^{i\omega}) = 0$ if either $|\omega| > \bar{W} = \tau\Omega$ or $\omega \in J_\delta$. By Proposition 2, the sequence $\{x(k)\}_{k \in \mathbb{Z}}$ is uniquely defined by the sequence $\{f(t_{mk-1})\}_{k \leq s}$. Hence G is uniquely defined by the sequence $\{f(t_{mk-1})\}_{k \leq s}$. Since $F = \mathcal{F}f$ is uniquely defined by G , it follows that the function $f = \mathcal{F}^{-1}F$ is uniquely defined by the sequence $\{f(t_{mk-1})\}_{k \leq s}$. This completes the proof of Theorem 1. \square

Proof of Corollary 1. It suffices to observe that $\|F(i\cdot) - F_\delta(i\cdot)\|_{L_2(\mathbf{R})} \rightarrow 0$ as $\delta \rightarrow 0$, where $F_\delta = \mathcal{F}f_\delta$. Since the support of $F(i\omega) = 0$ and $F_\delta(i\omega) = 0$ if $|\omega| > \Omega$, it follows that $\|F(i\cdot) - F_\delta(i\cdot)\|_{L_1(\mathbf{R})} \rightarrow 0$ as $\delta \rightarrow 0$. Hence $\|f - f_\delta\|_{L_\infty(\mathbf{R})} \rightarrow 0$ as $\delta \rightarrow 0$. This completes the proof. \square

It can be noted that the choice of predicting kernels presented in the proof is not unique.

5 An algorithm of recovery of f from a decimated sample

The present paper targets the theoretical aspects of possibility of recovering functions from decimated samples rather than numerical methods. However, the proofs are based on construction of a recovering algorithm that still may have a potential for practical applications.

To apply the classical Nyquist-Shannon-Kotelnikov Theorem for the data recovery, one has to restore the Fourier transform $F = \mathcal{F}f$ from the two-sided sampling series $\{f(t_k)\}_{k \in \mathbb{Z}}$. This procedure is

relatively straightforward. The algorithm used in the proof of Theorem 1 requires to restore Z-transform $G(e^{i\omega}) = F(i\omega/\tau)$ from sparse subsequences using predicting algorithms such as the one described in Proposition 2. This task is feasible but numerically challenging.

Let us summarize the steps implied by Theorem 1 for recovery of f from the sample $\{f(t_{mk-1})\}_{k \leq s}$ under the assumptions of Theorem 1 with a fixed δ . The algorithm requires the following steps:

- (i) For a given $\varepsilon > 0$, find γ that ensures that (5) holds for \hat{h} constructed as described above with this γ .
- (ii) Find \hat{y} presented in (5). Accept the values $\hat{y}(t_d)$ as estimates of the values $f(t_d)$ that are missing for $d \notin \{km + 1 : k \in \mathbb{Z}, k \leq s\}$.
- (iii) Restore f from the full oversampling series $\{f(t_d)\}_{d \in \mathbb{Z}}$.

It can be noted that the choice of ε controls the size of the error for normalized complete sequence $x = \{x(k)\}_{k \in \mathbb{Z}} = \{f(t_k)\}_{k \in \mathbb{Z}}$ such that $\|x\|_{\ell_2} \leq 1$. However, the complete sequences are unknown a priori. It may happen that the norm $\|x\|_{\ell_2}$ of the calculated x will be large; in this case, the error will be larger than ε . To achieve higher precision, one may need to repeat the listed steps with a smaller ε .

Some examples of applications of related predicting algorithms can be found in [5].

On robustness of recovery of the sample with respect to noise contamination

Let us discuss the presence of the contaminating noise on recovering the complete sampling sequences $\{x(k)\}_{k \in \mathbb{Z}} = \{f(t_k)\}_{k \in \mathbb{Z}}$ from a decimated sequence.

The predicting algorithm uses the transfer function $\hat{H}(e^{i\omega})$ defined by (7) that approximates the function $e^{i\omega}$ representing the forward one-step shift in the time domain; the value $|\hat{H}(e^{i\omega}) - e^{i\omega}|$ is small outside of $Q_+(\alpha)$. Therefore, the process $y(t)$ represents an one step prediction of $x(t + 1)$ if $X(e^{i\omega})$ vanishes on $Q_+(\alpha)$. This is illustrated by Figures 1 and 2 showing the shape of error curves for approximation of the forward one step shift operator. More precisely, it shows the shape of $|\hat{H}(e^{i\omega}) - e^{i\omega}|$ for the transfer function (7), and the shape of the corresponding predicting kernel wh with different parameters. As can be seen, the values of transfer functions rise sharply as $\text{mes } Q_+(\alpha) \rightarrow 2\pi$, i.e., if $\varepsilon \rightarrow 0$ or $\gamma \rightarrow +\infty$ in Proposition 2 or $\delta \rightarrow 0$ in Corollary 1. This means that the presence of noise, i.e., $F(i\omega) \neq 0$ for $\omega \in \mathcal{I}_\delta$, can imply a significant error for large γ or small δ .

Let us show that the algorithm still features some robustness if $\delta > 0$ is fixed or separated from zero.

Assume that the assumptions of Theorem 1 are satisfied with some $\delta > 0$. Suppose that the kernels \hat{h} described in the proof of Proposition 2 are applied to a sequence with a noise contamination. Let us

consider an input sequence $x \in \ell_2$ such that $x = x_0 + \eta$, where $x_0 \in \mathcal{V}$, and where $\eta \in \ell_2$ represents a noise. Let $X = \mathcal{Z}x$, $X_0 = \mathcal{Z}x_0$, and $N = \mathcal{Z}\eta$. We assume that $\|N(e^{i\omega})\|_{L_1(-\pi, \pi)} = \sigma$; the parameter $\sigma \geq 0$ represents the intensity of the noise.

In the proof of Theorem 1, we found that, for an arbitrarily small $\varepsilon > 0$, there exists a predicting kernel $\hat{h} \in \mathcal{H}$ such that

$$\int_{-\pi}^{\pi} |(\hat{H}(e^{i\omega}) - 1)X_0(e^{i\omega})| d\omega \leq 2\pi\varepsilon \quad \forall x_0 \in \mathcal{V},$$

where $\hat{H} = \mathcal{Z}\hat{h}$. This kernel is such that $\hat{y}_0 = \hat{h} \circ x_0$ approximated the process $x_0^+(t) \triangleq x_0(t+1)$ such that

$$\|\hat{y}_0 - x_0^+\|_{\ell_\infty} \leq \varepsilon.$$

Let us estimate the prediction error for the case where $\sigma > 0$. For $\hat{y} = \hat{h} \circ x$ and $x^+(t) \triangleq x(t+1)$, we have that

$$\|\hat{y} - x^+\|_{\ell_\infty} \leq E_0 + E_\eta,$$

where

$$E_0 = \frac{1}{2\pi} \|(\hat{H}(e^{i\omega}) - 1)X_0(e^{i\omega})\|_{L_1(-\pi, \pi)} \leq \varepsilon, \quad E_\eta = \frac{1}{2\pi} \|(\hat{H}(e^{i\omega}) - 1)N(e^{i\omega})\|_{L_1(-\pi, \pi)}.$$

The value E_η represents the additional error caused by the presence of unexpected high-frequency noise (when $\sigma > 0$). It follows that

$$\|\hat{y} - x^+\|_{\ell_\infty} \leq \varepsilon + \sigma(\kappa + 1), \tag{10}$$

where

$$\kappa = \sup_{\omega \in [-\pi, \pi]} |\hat{H}(e^{i\omega})|.$$

Therefore, it can be concluded that the prediction is robust with respect to noise contamination for any given ε .

However, we have that

$$\kappa \rightarrow +\infty \quad \text{as} \quad \gamma \rightarrow +\infty. \tag{11}$$

This implies that error (10) is increasing as $\varepsilon \rightarrow 0$ for any given $\sigma > 0$. This happens when the predictor is targeting too small a size of the error for the sequences from \mathcal{V} , i.e. under the assumption that $\sigma = 0$.

In particular, this implies that the assumptions of Theorem 1 cannot be bypassed via approximation described in Corollary 1 with $f_\delta \triangleq \mathcal{F}^{-1}(F\mathbb{I}_{\mathcal{I}_\delta})$, $F = \mathcal{F}f$. The problem is that the values $f_\delta(t_{mk-1})$ are not observable directly; the error $f(t_{mk-1}) - f_\delta(t_{mk-1}) \rightarrow 0$ as $\delta \rightarrow 0$. However, if $\delta \rightarrow 0$, then we need $\gamma \rightarrow +\infty$ to ensure (9). In this case, (10) and (11) imply that the error is increasing.

6 Discussion and future developments

- (i) It could be interesting to find non-equidistant infinite sets that can be redundant for recoverability of the underlying function. In particular, it could be interesting to investigate if recovery of f suggested in Theorem 1 is robust with respect to errors in location of the sampling points t_k .
- (ii) It is unclear if our approach based on predictability of discrete time processes is applicable to processes defined on multidimensional lattices. It could be interesting to extend this approach on functions $f : \mathbf{R}^2 \rightarrow \mathbf{R}$, using the setting from [12].
- (iii) We used a predicting algorithm based on [2]. Instead, we could use a predicting algorithm based on [3].
- (iv) Since we used a predicting algorithm [2] that does not require that the spectrum of an underlying process is actually vanishing on an arc of \mathbb{T} , we can relax conditions of Theorem 1. Instead of processes vanishing on open sets \mathcal{I}_δ , we can consider processes that vanish only at the middle points of the intervals forming \mathcal{I}_δ ; however, the rate of vanishing has to be sufficient, similarly to [2].
- (v) In theorem 1, we could replace the set $\{f(t_{mk-1})\}_{k \leq s}$ by the set $\{f(t_{mk+1})\}_{k \geq s}$. This would require to replace the predicting algorithm on its backward version which is rather technical. In addition, Theorem 1 applied to f transformed by a simple time shift allows to use sets $\{f(t_{mk-d})\}_{k \leq s}$ for any $d \in \mathbb{Z}$.

Acknowledgment

This work was supported by ARC grant of Australia DP120100928 to the author.

References

- [1] T. Cai, G. Xu, and J. Zhang. (2009), On recovery of sparse signals via ℓ_1 minimization, *IEEE Trans. Inf. Theory*, vol. 55, no. 7, pp. 3388-3397.
- [2] Dokuchaev, N. (2012). Predictors for discrete time processes with energy decay on higher frequencies. *IEEE Transactions on Signal Processing* **60**, No. 11, 6027-6030.
- [3] Dokuchaev, N. (2012). On predictors for band-limited and high-frequency time series. *Signal Processing* **92**, iss. 10, 2571-2575.

- [4] Dokuchaev, N. (2012). Causal band-limited approximation and forecasting for discrete time processes. arXiv 1208.3278.
- [5] Dokuchaev, N. (2016). Near-ideal causal smoothing filters for the real sequences. *Signal Processing* **118**, iss. 1, pp. 285-293.
- [6] Ferreira P. G. S. G.. (1992). Incomplete sampling series and the recovery of missing samples from oversampled bandlimited signals. *IEEE Trans. Signal Processing* **40**, iss. 1, 225-227.
- [7] Ferreira P. G. S. G.. (1995). Sampling Series With An Infinite Number Of Unknown Samples. In: *SampTA'95, 1995 Workshop on Sampling Theory and Applications*, 268-271.
- [8] Jerri, A. (1977). The Shannon sampling theorem - its various extensions and applications: A tutorial review. *Proc. IEEE* **65**, 11, 1565–1596.
- [9] Kolmogorov, A.N. (1941). Interpolation and extrapolation of stationary stochastic series. *Izv. Akad. Nauk SSSR Ser. Mat.*, 5:1, 3–14.
- [10] Kotelnikov, V.A. (1933). On the carrying capacity of the ether and wire in telecommunications. *Material for the First All-Union Conference on Questions of Communication, Izd. Red. Upr. Svyazi RKKA, Moscow*, 1933.
- [11] Nyquist, H. (1928). Certain topics in telegraph transmission theory, *Trans. AIEE*, Trans., vol. 47, pp. 617-644.
- [12] Petersen, D.P. and Middleton D. (1962). Sampling and reconstruction of wave-number-limited functions in N-dimensional Euclidean spaces. *Information and Control*, vol. 5, pp. 279-323.
- [13] Rudin, W. *Real and Complex Analysis*. 3rd ed. Boston: McGraw-Hill, 1987.
- [14] Shannon, C.E. (1949). Communications in the presence of noise, *Proc. Institute of Radio Engineers*, vol. 37, no.1, pp. 1021.
- [15] Szegő, G. (1920). Beiträge zur Theorie der Toeplitzschen Formen. *Math. Z.* 6, 167–202.
- [16] Szegő, G. (1921). Beiträge zur Theorie der Toeplitzschen Formen, II. *Math. Z.* 9, 167-190.
- [17] Unser, M. (2000). Sampling 50 years after Shannon, *Proceedings of the IEEE*, vol. 88, pp. 569-587.,
- [18] Vaidyanathan P. P. (1987). On predicting a band-limited signal based on past sample values, in *Proceedings of the IEEE*, vol. 75, no. 8, pp. 1125-1127.

- [19] Vaidyanathan, P.P. (2001). Generalizations of the Sampling Theorem: Seven Decades After Nyquist. *IEEE Transactions on circuits and systemsI: fundamental theory and applications*, v. 48, NO. 9,
- [20] Verblunsky, S. (1936). On positive harmonic functions (second paper). *Proc. London Math. Soc.* 40, 290–320.
- [21] Whittaker, E.T. (1915). On the Functions Which are Represented by the Expansions of the Interpolation Theory. *Proc. Royal Soc. Edinburgh, Sec. A*, vol.35, pp. 181194.
- [22] Zayed A. (1993). *Advances in Shannon's Sampling Theory*. Boca Raton, CRC Press, N.Y, London, Tokyo.

%% [error,errorF]=decimated(100,2.5,0.4,0.3,0,0.8,0.7,30,1,3,2,1,2)




Figure 1: Approximation of the one-step forward shift operator: the values $|K(e^{i\omega}) - e^{i\omega}|$ for the transfer function of the predictor (7) and the values of the corresponding kernel \hat{h} with $\gamma = 2.5$, $r = 0.4$, $m = 2$.




Figure 2: Approximation of the one-step forward shift operator: the values $|K(e^{i\omega}) - e^{i\omega}|$ for the transfer function of the predictor (7) and the values of the corresponding kernel \hat{h} with $\gamma = 4$, $r = 0.4$, $m = 4$.