

A General Bidirectional Controlled/Uncontrolled Quantum Teleportation Protocol

Moein Sarvaghad-Moghaddam¹ & Negin Fatahi^{2*}

¹Young Researchers and Elite Club, Mashhad Branch, Islamic Azad University, Mashhad, Iran. .

²Department of Physics, Kermanshah Branch, Islamic Azad University, Kermanshah, Iran.

E-mail: *n83fatahi@yahoo.com

Abstract. In this paper, different from the other existing methods that only the special and limited numbers of qubits transmit between Alice and Bob, a general method is proposed to implement Bidirectional Quantum Controlled/uncontrolled Teleportation (BQCT/BQT) that Alice and Bob can transmit each type of arbitrary n and m -qubits to each other, simultaneously. This protocol is based on Controlled-NOT (CNOT) operation, appropriate single-qubit unitary operations and single-qubit measurement in the Z-basis and X-basis. Also, quantum channel can be created by using Hadamard and CNOT operations. One of the advantages of this method is using the single-qubit measurements which are more efficient than two-qubit measurements.

Keywords: Bidirectional quantum teleportation, n -qubit state, Bidirectional quantum controlled teleportation, entanglement state.

1. Introduction

Quantum teleportation (QT) is one of the communication protocols in Quantum information theory where an unknown quantum state can be transmitted to a receiver by using the shared entanglement state as quantum channel and some auxiliary classical communications [1].

Rapidly, safe and secret communication has been caused QT to become a very interesting topic of researches and plays an important role in many applications in recent years [2-8]. In 1993, Bennett et.al.[2], introduced idea of QT by using an Einstein-Podolsky-Rosen (EPR) pair as a quantum channel. After that, modified versions of QT are introduced by using EPR pair, Greenberger- Horne-Zeilinger (GHZ) state, W state and other entangled states as a quantum channel [9-14].

In 1993, Karlsson et al.[15], proposed another version of QT named as Controlled Quantum Teleportation (CQT). This protocol is same as QT with presence of third

user (Charlie) as controller or supervisor. Later, in [16-23] several protocols of CQT were proposed with one or more controller. In 2013, Zha et al. [24] demonstrated a new version of QT named as Bidirectional Controlled Quantum Teleportation (BCQT) via five-qubit cluster state as quantum channel. In BCQT or BQT protocol, both authorized users transmit unknown quantum states to each other, simultaneously. In [25, 26], BCQT protocols are proposed with various channels such as six-qubit cluster state, six-qubit entangled state and five-qubit composite. Also, Chen [27], Hassanpour [28], Hong [29] and Sang [30], proposed various BCQT protocols by using channels of six-qubit genuine, six-qubit entangled state and seven-qubit entangled state, respectively. In proposed protocol in [29, 30] Bob and Alice can transmit arbitrary two and one qubit together by using a seven-qubit entangled state as quantum channel. In [31], a pure EPR state can be transmitted by Alice and Bob to each other by using six-qubit GHZ as quantum channel. In proposed protocol by Li et al. [32], an arbitrary two and one-qubit can be transmitted by Alice and Bob via six-qubit cluster state simultaneously. In 2017, Sadeghi Zadeh et al. [33] proposed a BQT protocol which the users can transmit an arbitrary two-qubit state to each other by using eight-qubit quantum channel. In this paper, a new general protocol of Bidirectional Quantum Teleportation (BQT) and Bidirectional Quantum Controlled Teleportation (BQCT) are proposed for transmitting each number of unknown qubits between Alice and Bob with supervisor Charlie or without it. This method can covers the transmitting of each arbitrary type of qubits such as entanglement states or pure states. In this protocol, users only perform single-qubit measurements.

The remainder of this paper is organized as follows. In Section 2, proposed method for general BQT protocol is introduced in details. In Section 3, the comparison between reported channels in previous works and our method is discussed. Finally, Section 4 concludes the paper.

2. General BQT protocol

In this section, firstly the general Bidirectional Quantum Teleportation (BQT) protocol is proposed for transmitting n and m -qubits between Alice and Bob. Then this proposed method generalized for transmitting the n - qubit entanglement state between one or two users to each other. Finally, a general method is proposed for Bidirectional Controlled Quantum Teleportation (BQCT) protocol with presence of Charlie as a controller or supervisor.

2.1. Transmitting the n and m qubits state

In this section, a general method for BQT protocol is proposed. By using this protocol Alice and Bob can transmit an arbitrary n and m -qubit state to each other. The general schematic of this protocol is shown in Fig. 1.

Consider the n -qubit general state that Alice wants to teleport to Bob and the




Figure 1. General schematic of proposed BQT protocol for transmitting the arbitrary n and m -qubit states between Alice and Bob.

m -qubit general state that Bob wants to teleport to Alice. This states are given by

$$|\phi_a\rangle = \sum_{i=0}^{2^n-1} \alpha_i |i\rangle \quad \alpha_i \in c_z, \quad \sum_{i=0}^{2^n-1} \alpha_i^2 = 1 \quad (1)$$

$$|\phi_b\rangle = \sum_{i=0}^{2^m-1} b_i |i\rangle \quad b_i \in c_z, \quad \sum_{i=0}^{2^m-1} b_i^2 = 1 \quad (2)$$

Where variable i is binary number. As shown in Fig. 1, the qubits that used in channel are divided into two parts: Main qubits and Control qubits. Duty of main qubits is creating the number of required qubits for sending information between Alice and Bob ($|0\dots0\rangle_a |0\dots0\rangle_b$ that a, b stand to belong to Alice and Bob respectively). Sending qubits show the number of qubits transmitted by Alice and Bob to each other. The numbers of Main qubits are dependent on the sum of the Sending qubits by Alice and Bob. If the number of Sending qubits by Alice is n and the number of Sending qubits by Bob is m , so the number of Main qubits is $m + n$. The number of Control qubits are same as Main qubits and n -qubit is belong to Alice and m qubit belong to Bob. In the other words, the number of Control qubits for each of Alice and Bob are equivalent to the number of the Sending qubits. These additional qubits are used for communicating with Sending qubits. The placing of Control qubits is arbitrary. We place them after than Main qubits. The protocol consists the following steps:

Step1:

In this step, quantum channel is created. As shown in Fig. 1, the first Main qubits and Control qubits are created as stated in above. Also, the arrangement of the Main qubits are inverses of Sending qubits. But, the arrangement of the Control qubits is same as Sending qubits. For example, if the arrangement of Sending qubits are as $|\phi_{bm}\rangle |\phi_{an}\rangle$ then, the arrangement of Main qubits and Control qubits are $|0\dots0\rangle_{am} |0\dots0\rangle_{bn} |0\dots0\rangle_{cbm} |0\dots0\rangle_{can}$ where a, b and c stand to belong to Alice, Bob

and Control qubits, respectively. Also, the index n and m is the number of qubits that transferred by Alice and Bob. Then, Hadamard gate is applied to the Main qubits and create a superposition from this qubits and after that CNOT gate is applied, respectively. So that, Main qubits are used as Control Lines and Control qubits are used as target lines. For example, the first qubit $|0\rangle_{a0}$ (that belongs to Alice) is used as Control line for target line $|0\rangle_{c_{b0}}$ (the first Control qubit that belongs to Bob) and so on. So, generally same states of Main qubits are multiplied as a tensor product with control qubits. Thus, the general state can be written as:

$$\frac{1}{\sqrt{n}} \left(\sum_{i=0}^{2^{n+m}-1} |i\rangle_{ab} |i\rangle_{c_b} |i\rangle_{c_a} \right) \otimes |\phi\rangle_b |\phi\rangle_a \quad (3)$$

where, n and m are the number of Sending qubits by Alice and Bob, respectively. Also, the index a and b belong to Alice and Bob and c_b, c_a show the Control qubits belong to Bob and Alice. $|\phi\rangle_b$ and $|\phi\rangle_a$ denote Sending qubits by Bob and Alice.

Step2:

Control NOT operator is applied by Alice and Bob so that, Sending qubits are as Control lines and Control qubits are as target lines. For example, consider the Sending qubits belong to Bob and Alice as $|\phi\rangle_b = |\phi\rangle_{b0}, |\phi\rangle_{b1}, \dots, |\phi\rangle_{bn}$, and $|\phi\rangle_a = |\phi\rangle_{a0}, |\phi\rangle_{a1}, \dots, |\phi\rangle_{am}$, for instance, CNOT gate can be used by Bob (Alice) as $|\phi\rangle_{b0}$ ($|\phi\rangle_{a0}$) as control line and line of c_{b0} (c_{a0}) is used as target line and so on.

Step 3:

In this step, Alice and Bob measure the single qubit of the control qubits in the Z-basis. The unmeasured qubits collapse into the one of the $2^{(n+m)}$ possible states with equal probability.

Step 4:

Alice and Bob share the measurement results that obtained from previous step, on classical channel. Then, they apply X unitary operator to their unmeasured qubits. If for each qubit in control line, 1 is obtained then, the X unitary operation applied to equivalent qubit in the main qubits. For example, if c_{a0} be 1, Then X operator is applied to equivalent qubit in Main qubits i.e. $a0$ line.

Step 5:

In this step, Alice and Bob measure the single-qubit of Sending qubits in the X -basis. The unmeasured qubits collapse into one of the $2^{(n+m)}$ possible states with equal probability.

Step 6:

After that the users tell their measurement results to each other, they apply Z unitary operator to their unmeasured qubits. After that, if for each Sending qubits, the value of one is obtained then, for the equivalent qubit in the Main qubits, Z unitary operator is applied. For example, if after that measurement the value of $|\phi\rangle_{a0}$ equal $|-\rangle$, then, Z operator is applied to equivalent qubit in the Main qubits i.e. $a0$ line. Finally, all of the states will be in the same form.

Step 7:

Users reconstruct the n and m -qubit states and the BQT is successfully finished. See the following example in order to explain this method in more details.

Example:

Consider a two-qubit state that Alice wants to teleport to Bob and a one-qubit state that Bob want to teleport to Alice, that are given by:

$$|\phi\rangle_{A_0A_1} = \alpha_{00}|00\rangle + \alpha_{01}|01\rangle + \alpha_{10}|10\rangle + \alpha_{11}|11\rangle \quad (4)$$

$$|\phi\rangle_{B_0} = b_0|0\rangle + b_1|1\rangle \quad (5)$$

This protocol consists of the following steps:

Step 1: For creating channel, two qubit belong to Bob and one qubit belong to Alice are considered as Main qubits. Then, two qubit for Alice and one qubit for Bob are considered as Control qubits. So, the number of qubits is as following:

$$|000\rangle_{b_0b_1a_0} |000\rangle_{c_{a0}c_{a1}c_{b0}} \quad (6)$$

By applying the Hadamard gate to the Main qubits we have:

$$\begin{aligned} & \frac{1}{\sqrt{8}}(|000\rangle + |001\rangle + |010\rangle + |100\rangle + |011\rangle + |110\rangle + \\ & |101\rangle + |111\rangle)_{b_0b_1a_0} |000\rangle_{c_{a0}c_{a1}c_{b0}} \end{aligned} \quad (7)$$

Then, by applying CNOT gate to the Control qubits, the structure of the channel is created as the following:

$$\begin{aligned} |\psi\rangle_{(b_0)(b_1)(a_0)(c_{a0})(c_{a1})(c_{b0})} = & \frac{1}{\sqrt{8}}(|000000\rangle + |001001\rangle + |010010\rangle \\ & + |011011\rangle + |100100\rangle + |101101\rangle + |110110\rangle + |111111\rangle \end{aligned} \quad (8)$$

The state of the whole system can be expressed as :

$$|\phi\rangle_{(b_0)(b_1)(a_0)(c_{a0})(c_{a1})(c_{b0})A_0A_1B_0} = |\psi\rangle_{(b_0)(b_1)(a_0)(c_{a0})(c_{a1})(c_{b0})} \otimes |\Phi\rangle_{(A_0A_1)} \otimes |\Phi\rangle_{(B_0)} \quad (9)$$

Step 2: In this step, Alice and Bob applied Controlled NOT (CNOT) operator so that A_0, A_1 and B_0 as control line and c_{a0}, c_{a1} and c_{b0} (Control Qubits) as target line, respectively. Then the state of the whole system is shown as:

$$\begin{aligned} & |\phi\rangle_{(b_0)(a_0)(a_1)(c_{a0})(c_{a1})(c_{b0})A_0A_1B_0} = \\ & \frac{1}{\sqrt{8}}[\alpha_{00}b_0(|000\rangle|000\rangle + |001\rangle|001\rangle + |010\rangle|010\rangle + |011\rangle|011\rangle + |100\rangle|100\rangle \\ & + |101\rangle|101\rangle + |110\rangle|110\rangle + |111\rangle|111\rangle)|000\rangle + \\ & \alpha_{00}b_1(|000\rangle|001\rangle + |001\rangle|000\rangle + |010\rangle|011\rangle + |011\rangle|010\rangle + |100\rangle|101\rangle \\ & + |101\rangle|100\rangle + |110\rangle|111\rangle + |111\rangle|110\rangle)|001\rangle + \\ & \alpha_{01}b_0(|000\rangle|010\rangle + |001\rangle|011\rangle + |010\rangle|000\rangle + |011\rangle|001\rangle + |100\rangle|110\rangle \\ & + |101\rangle|111\rangle + |110\rangle|100\rangle + |111\rangle|101\rangle)|010\rangle + \end{aligned} \quad (10)$$

$$\begin{aligned}
 & \alpha_{01}b_1(|000\rangle + |011\rangle + |001\rangle + |010\rangle + |010\rangle + |001\rangle + |011\rangle + |000\rangle + |100\rangle + |111\rangle \\
 & + |101\rangle + |110\rangle + |110\rangle + |101\rangle + |111\rangle + |100\rangle)|011\rangle + \\
 & \alpha_{10}b_0(|000\rangle + |100\rangle + |001\rangle + |101\rangle + |010\rangle + |110\rangle + |011\rangle + |111\rangle + |100\rangle + |000\rangle \\
 & + |101\rangle + |001\rangle + |110\rangle + |010\rangle + |111\rangle + |011\rangle)|100\rangle + \\
 & \alpha_{10}b_1(|000\rangle + |101\rangle + |001\rangle + |100\rangle + |010\rangle + |111\rangle + |011\rangle + |110\rangle + |100\rangle + |001\rangle \\
 & + |101\rangle + |000\rangle + |110\rangle + |011\rangle + |111\rangle + |010\rangle)|101\rangle + \\
 & \alpha_{11}b_0(|000\rangle + |110\rangle + |001\rangle + |111\rangle + |010\rangle + |100\rangle + |011\rangle + |101\rangle + |100\rangle + |010\rangle \\
 & + |101\rangle + |011\rangle + |110\rangle + |000\rangle + |111\rangle + |001\rangle)|110\rangle + \\
 & \alpha_{11}b_1(|000\rangle + |111\rangle + |001\rangle + |001\rangle + |010\rangle + |101\rangle + |011\rangle + |100\rangle + |100\rangle + |011\rangle \\
 & + |101\rangle + |010\rangle + |110\rangle + |001\rangle + |111\rangle + |000\rangle)|111\rangle]
 \end{aligned}$$

Step3: Single-qubit measurement is applied on qubits c_{a0}, c_{a1} and c_{b0} (Control Qubits) by Alice and Bob, respectively. As shown in Table 1, the unmeasured qubits collapse into the one of the 8 possible states with equal probability.

Table 1. measurement results based on Z done by Alice and Bob on Control Qubits

Alice's Result	Bob's Result	The collapsed state of qubits (b_0)(b_1)(a_0)A0A1B0 encoding algorithm
00	0	$\alpha_{00}b_0 000\rangle + 000\rangle + \alpha_{00}b_1 001\rangle + 001\rangle + \alpha_{01}b_0 010\rangle + 010\rangle + \alpha_{01}b_1 011\rangle + 011\rangle + \alpha_{10}b_0 100\rangle + 100\rangle + \alpha_{10}b_1 101\rangle + 101\rangle + \alpha_{11}b_0 110\rangle + 110\rangle + \alpha_{11}b_1 111\rangle + 111\rangle$
00	1	$\alpha_{00}b_0 001\rangle + 000\rangle + \alpha_{00}b_1 000\rangle + 001\rangle + \alpha_{01}b_0 011\rangle + 010\rangle + \alpha_{01}b_1 010\rangle + 011\rangle + \alpha_{10}b_0 101\rangle + 100\rangle + \alpha_{10}b_1 100\rangle + 101\rangle + \alpha_{11}b_0 111\rangle + 110\rangle + \alpha_{11}b_1 110\rangle + 111\rangle$
01	0	$\alpha_{00}b_0 010\rangle + 000\rangle + \alpha_{00}b_1 011\rangle + 001\rangle + \alpha_{01}b_0 000\rangle + 010\rangle + \alpha_{01}b_1 001\rangle + 011\rangle + \alpha_{10}b_0 110\rangle + 100\rangle + \alpha_{10}b_1 111\rangle + 101\rangle + \alpha_{11}b_0 100\rangle + 110\rangle + \alpha_{11}b_1 101\rangle + 111\rangle$
01	1	$\alpha_{00}b_0 011\rangle + 000\rangle + \alpha_{00}b_1 010\rangle + 001\rangle + \alpha_{01}b_0 001\rangle + 010\rangle + \alpha_{01}b_1 000\rangle + 011\rangle + \alpha_{10}b_0 111\rangle + 100\rangle + \alpha_{10}b_1 110\rangle + 101\rangle + \alpha_{11}b_0 101\rangle + 110\rangle + \alpha_{11}b_1 100\rangle + 111\rangle$
10	0	$\alpha_{00}b_0 100\rangle + 000\rangle + \alpha_{00}b_1 101\rangle + 001\rangle + \alpha_{01}b_0 110\rangle + 010\rangle + \alpha_{01}b_1 111\rangle + 011\rangle + \alpha_{10}b_0 000\rangle + 100\rangle + \alpha_{10}b_1 001\rangle + 101\rangle + \alpha_{11}b_0 010\rangle + 110\rangle + \alpha_{11}b_1 011\rangle + 111\rangle$
10	1	$\alpha_{00}b_0 101\rangle + 000\rangle + \alpha_{00}b_1 100\rangle + 001\rangle + \alpha_{01}b_0 111\rangle + 010\rangle + \alpha_{01}b_1 110\rangle + 011\rangle + \alpha_{10}b_0 001\rangle + 100\rangle + \alpha_{10}b_1 000\rangle + 101\rangle + \alpha_{11}b_0 011\rangle + 110\rangle + \alpha_{11}b_1 010\rangle + 111\rangle$
11	0	$\alpha_{00}b_0 110\rangle + 000\rangle + \alpha_{00}b_1 111\rangle + 001\rangle + \alpha_{01}b_0 100\rangle + 010\rangle + \alpha_{01}b_1 101\rangle + 011\rangle + \alpha_{10}b_0 010\rangle + 100\rangle + \alpha_{10}b_1 011\rangle + 101\rangle + \alpha_{11}b_0 000\rangle + 110\rangle + \alpha_{11}b_1 001\rangle + 111\rangle$
11	1	$\alpha_{00}b_0 111\rangle + 000\rangle + \alpha_{00}b_1 110\rangle + 001\rangle + \alpha_{01}b_0 101\rangle + 010\rangle + \alpha_{01}b_1 100\rangle + 011\rangle + \alpha_{10}b_0 011\rangle + 100\rangle + \alpha_{10}b_1 010\rangle + 101\rangle + \alpha_{11}b_0 001\rangle + 110\rangle + \alpha_{11}b_1 000\rangle + 111\rangle$

Step 4: The measurement results that obtained from previous step are notified by Alice and Bob to each other. Then, they apply the unitary X operator to their

unmeasured qubits (Main q qubits) according to the Table 2. As a result, the state of the whole system will be converted in the form as follow:

$$\begin{aligned}
 |\phi\rangle_{(b0)(a0)(a1)(c_{a0})(c_{a1})(c_{b0})A0A1B0} = & \quad (11) \\
 & \alpha_{00}b_0|000\rangle + \alpha_{00}b_1|001\rangle + \alpha_{01}b_0|010\rangle + \alpha_{01}b_1|011\rangle + \\
 & + \alpha_{10}b_0|100\rangle + \alpha_{10}b_1|101\rangle + \alpha_{11}b_0|110\rangle + \alpha_{11}b_1|111\rangle
 \end{aligned}$$

Table 2. local unitary transformations performed by Alice and Bob

Alices Result	Bobs Result	Unitary Operator on $(b0)(b1)(a0)$
00	0	$I \otimes I \otimes I$
00	1	$I \otimes I \otimes X$
01	0	$I \otimes X \otimes I$
01	1	$I \otimes X \otimes X$
10	0	$X \otimes I \otimes I$
10	1	$X \otimes I \otimes X$
11	0	$X \otimes X \otimes I$
11	1	$X \otimes X \otimes X$

Step 5: in this step, single-qubit measurements are applied on the Sending Qubits (A_0, A_1 and B_0) by Alice and Bob in the X-basis, respectively. As shown in the Table 3, the unmeasured qubits (Main qubits) collapse into the one of the 8 possible states with equal probability.

Step 6: After that users announced the results of the measurement to each other, they apply Z unitary operator to their unmeasured qubits (Main qubits) according to Table 4. Therefore, the state of the Main qubits will be converted as:

$$\begin{aligned}
 \text{Main qubit} = & \alpha_{00}b_0|000\rangle + \alpha_{00}b_1|001\rangle + \alpha_{01}b_0|010\rangle + \alpha_{01}b_1|011\rangle + \\
 & + \alpha_{10}b_0|100\rangle + \alpha_{10}b_1|101\rangle + \alpha_{11}b_0|110\rangle + \alpha_{11}b_1|111\rangle
 \end{aligned} \quad (12)$$

Step 7: Alice and Bob reconstruct the one and two-qubit states according to the bellow equation and the BQT is successfully finished.

$$\begin{aligned}
 |\phi\rangle_{A0} &= (b_0|0\rangle + b_1|1\rangle)_{a0} \\
 |\phi\rangle_{B0B1} &= (\alpha_{00}|00\rangle + \alpha_{01}|01\rangle + \alpha_{10}|10\rangle + \alpha_{11}|11\rangle)_{b0b1}
 \end{aligned} \quad (13)$$

2.2. Transmitting of n and m qubits by Alice and Bob with entanglement state

Suppose that one of the states or each two states transmitted by Alice and Bob are entangled. In this case that the state is entanglement, only the Step 1 of the protocol (channel structure) is changed. For example, suppose Alice wants transmit n -qubit entanglement state to Bob and Bob wants transmit a m -qubit state to Alice as shown in below equation (and Fig. 2 (a))

$$|\phi\rangle_{an} = \alpha_0|0\dots 0\rangle + \alpha_1|1\dots 1\rangle \quad \alpha_0, \alpha_1 \in C_z, |\alpha_0|^2 + |\alpha_1|^2 = 1 \quad (14)$$

Table 3. measurement results based on X done by Alice and Bob on Main qubits

Alice's Result	Bob's Result	The collapsed state of qubits (b0)(b1)(a0)
++	+	$\alpha_{00}b_0 000\rangle + \alpha_{00}b_1 001\rangle + \alpha_{01}b_0 010\rangle + \alpha_{01}b_1 011\rangle + \alpha_{10}b_0 100\rangle + \alpha_{10}b_1 101\rangle + \alpha_{11}b_0 110\rangle + \alpha_{11}b_1 111\rangle$
++	-	$\alpha_{00}b_0 000\rangle - \alpha_{00}b_1 001\rangle + \alpha_{01}b_0 010\rangle - \alpha_{01}b_1 011\rangle + \alpha_{10}b_0 100\rangle - \alpha_{10}b_1 101\rangle + \alpha_{11}b_0 110\rangle - \alpha_{11}b_1 111\rangle$
+-	+	$\alpha_{00}b_0 000\rangle + \alpha_{00}b_1 001\rangle - \alpha_{01}b_0 010\rangle - \alpha_{01}b_1 011\rangle + \alpha_{10}b_0 100\rangle + \alpha_{10}b_1 101\rangle - \alpha_{11}b_0 110\rangle - \alpha_{11}b_1 111\rangle$
+-	-	$\alpha_{00}b_0 000\rangle - \alpha_{00}b_1 001\rangle - \alpha_{01}b_0 010\rangle + \alpha_{01}b_1 011\rangle + \alpha_{10}b_0 100\rangle - \alpha_{10}b_1 101\rangle - \alpha_{11}b_0 110\rangle + \alpha_{11}b_1 111\rangle$
-+	+	$\alpha_{00}b_0 000\rangle + \alpha_{00}b_1 001\rangle + \alpha_{01}b_0 010\rangle + \alpha_{01}b_1 011\rangle - \alpha_{10}b_0 100\rangle - \alpha_{10}b_1 101\rangle - \alpha_{11}b_0 110\rangle - \alpha_{11}b_1 111\rangle$
-+	-	$\alpha_{00}b_0 000\rangle - \alpha_{00}b_1 001\rangle + \alpha_{01}b_0 010\rangle - \alpha_{01}b_1 011\rangle - \alpha_{10}b_0 100\rangle + \alpha_{10}b_1 101\rangle - \alpha_{11}b_0 110\rangle + \alpha_{11}b_1 111\rangle$
--	+	$\alpha_{00}b_0 000\rangle + \alpha_{00}b_1 001\rangle - \alpha_{01}b_0 010\rangle - \alpha_{01}b_1 011\rangle - \alpha_{10}b_0 100\rangle - \alpha_{10}b_1 101\rangle + \alpha_{11}b_0 110\rangle + \alpha_{11}b_1 111\rangle$
--	-	$\alpha_{00}b_0 000\rangle - \alpha_{00}b_1 001\rangle - \alpha_{01}b_0 010\rangle + \alpha_{01}b_1 011\rangle - \alpha_{10}b_0 100\rangle + \alpha_{10}b_1 101\rangle + \alpha_{11}b_0 110\rangle - \alpha_{11}b_1 111\rangle$

Table 4. local unitary transformations performed by Alice and Bob

Alices Result	Bobs Result	Unitary Operation on (b0)(b1)(a0)
++	+	$I \otimes I \otimes I$
++	-	$I \otimes I \otimes Z$
+-	+	$I \otimes Z \otimes I$
+-	-	$I \otimes Z \otimes Z$
-+	+	$Z \otimes I \otimes I$
-+	-	$Z \otimes I \otimes Z$
--	+	$Z \otimes Z \otimes I$
--	-	$Z \otimes Z \otimes Z$

$$|\phi\rangle_{bm} = \sum_{i=0}^{2^m-1} b_i|i\rangle \quad b_i \in C_z, \quad \sum_{i=0}^{2^n-1} b_i^2 = 1 \quad (15)$$

As shown in Fig. 2 (a), Main qubit is constructed from m-qubit for Alice and n-qubit for Bob as $|0\rangle_{a0} \dots |0\rangle_{am} |0\rangle_{b0} \dots |0\rangle_{bn}$. This n-qubit has been supposed as entanglement state. So, in the Main qubit, the operator that introduced in previous section applied on the Alice's m-qubit and for n-qubit of Bob, the following operator is applied. Hadamard gate applied on the first qubit then CNOT operator applied. So that the first qubit is considered as control lines and other qubits as target lines. For control qubits of $|0\rangle_{(cb0)} \dots |0\rangle_{(cbm)}$, CNOT gates are applied as described in the




Figure 2. Channel structural. a)The n-qubit entanglement state as a sending qubits by Alice. b)The n and m qubits entanglement state as a sending qubits by Alice and Bob.

previous section. But, the number of control-qubits for a n-qubit entanglement state is one. So, a CNOT gate is applied to the state of $|0\rangle_{(c_{a0})}$. So that, the first qubit of Bob in main qubits is considered as control line and c_{a0} line is as target line.

Fig. 2 (b) shows conditions that Alice and Bob transmit n and m qubit entanglement states to each other. So, it need to two control qubits and structure implemented for Alice in Fig. 2 (a) is considered for each of Alice and Bob. The other steps of protocol are same as before. Only in the Step 2 of protocol, for applying CNOT gates to Control qubits, each of Sending qubits by Alice and Bob are as entanglement state. So, the first it's qubit only is considered as control line for related Control qubits.

Example 2: consider a two-qubit entanglement state that Alice wants teleport to Bob and a one-qubit state that Bob wants to teleport to Alice are given by :

$$|\phi\rangle_{A0A1} = \alpha_0|00\rangle + \alpha_1|11\rangle \quad (16)$$

$$|\phi\rangle_B = b_0|0\rangle + b_1|1\rangle \quad (17)$$

For creating the channel, two qubits are considered for Bob and one qubit is considered for Alice. Also, one qubit for Alice and one qubit for Bob as Control Qubits

are considered. Then, the general state is as the following:

$$|000\rangle_{b0b1a0} |00\rangle_{(c_a)(c_b)} \quad (18)$$

Then, for main qubits Hadamard gate is applied to the first Bobs qubit (because it is entanglement) and Alice qubits ($a0$). The created state is

$$(|000\rangle + |001\rangle + |100\rangle + |101\rangle)_{b0b1a0} |00\rangle_{(c_a)(c_b)} \quad (19)$$

Then, CNOT gates are applied to Bob's qubits in the Main qubits so that, the first Bob's qubit ($b0$) is considered as control line and other qubits ($b1$) belong to Bob are considered as target lines. Therefore the created state is as following:

$$\frac{1}{2}(|000\rangle + |001\rangle + |110\rangle + |111\rangle)_{b0b1a0} |00\rangle_{(c_a)(c_b)} \quad (20)$$

Then, for control qubits CNOT gates are applied so that, $b0$ and $a0$ are considered as control lines. c_a and c_b are considered as target lines. Therefore, the created channel is as following:

$$|\psi\rangle_{(b0)(b1)(a0)(c_a)(c_b)} = \frac{1}{2}(|000\rangle |00\rangle + |001\rangle |01\rangle + |110\rangle |10\rangle + |111\rangle |11\rangle) \quad (21)$$

The general state of the system is

$$|\phi\rangle_{(b0)(b1)(a0)(c_a)(c_b)A_0A_1B_0} = |\psi\rangle_{(b0)(b1)(a0)(c_a)(c_b)} \otimes |\phi\rangle_{(A_0A_1)} \otimes |\phi\rangle_{(B_0)} \quad (22)$$

For Step 2 of this protocol, CNOT operators are applied by Alice and Bob so that, A_0 and B_0 are as control lines and c_a and c_b are as target lines, respectively. The other Steps of the protocol are same as with previous protocol.

2.3. Bidirectional Quantum Controlled Teleportation

For transmitting n and m qubit by Alice and Bob to each other the presence of a controller Charlie, the proposed methods in the previous section can be used but, a qubit belong to Charlie is added to the last Main qubits (Placing of Charlie's qubit is arbitrary). Also, after that all previous operators applying in creating channels, only CNOT gates is applied on it. Therefore each combination of Control Qubits can be considered as control lines and Charlie's qubit is as target line. So, Charlie can create $2^{(\text{thenumberofControlQubits})}$ quantum channel that in each quantum channel, the distribution of charlie's qubit is different. Then Charlie can encode each type of channel with classical bit and notify the type of creating a channel to Alice and Bob in the final step. Thus by doing this, the probability of estimation of Charlie's qubit by eavesdropper is $\frac{1}{2^{(\text{thenumberofControlQubits})}}$. For example, channel created in Example 1 can be converted to a bidirectional controlled quantum teleportation protocol, thus the first, initial state is created as the following:

$$|0000\rangle_{b0b1a0C} |000\rangle_{(c_{a0}c_{a1}c_{b0})} \quad (23)$$

Where, C denote belong to Charlie. Then, Applying of Hadamard gate to main qubits have:

$$\frac{1}{\sqrt{8}}(|0000\rangle + |0010\rangle + |0100\rangle + |0110\rangle + |1000\rangle + |1010\rangle + |1100\rangle + |1110\rangle) \quad (24)$$

$$+|1100\rangle + |1110\rangle)_{b_0b_1a_0C}(|000\rangle)_{(c_{a0}c_{a1}c_{b0})}$$

Then, by applying CNOT gate to control qubits we have:

$$\frac{1}{\sqrt{8}}(|0000\rangle + |000\rangle + |0010\rangle + |001\rangle + |0100\rangle + |010\rangle + |0110\rangle + |011\rangle +$$

$$+ |1000\rangle + |100\rangle + |1010\rangle + |101\rangle + |1100\rangle + |110\rangle + |1110\rangle + |111\rangle)_{((b_0)(b_1)(a_0)(C)(c_{a0})(c_{a1})(c_{b0}))}$$

Finally, a CNOT gate is applied to Charlie's qubit (C) according to combination of Control qubits as control lines and Charlie's qubit as target line. So, channels are created as shown in Table 5.

Table 5. measurement results based on X done by Alice and Bob on Main Qubits

Encoding of the various distributions of Charlies qubit	The proposed channel $ \Psi\rangle_{(b_0)(b_1)(a_0)(C)(C_{a0})(C_{a1})(C_{b0})}$	Charlies Results	Unitary Operation on b_0, b_1, a_0
000	$\frac{1}{\sqrt{8}}(0000\rangle + 000\rangle + 0010\rangle + 001\rangle + 0100\rangle + 010\rangle + 0110\rangle + 011\rangle + 1000\rangle + 100\rangle + 1010\rangle + 101\rangle + 1100\rangle + 110\rangle + 1110\rangle + 111\rangle)$	$ +\rangle$ $ -\rangle$	$I \otimes I \otimes I$ $I \otimes I \otimes I$
001	$\frac{1}{\sqrt{8}}(0000\rangle + 000\rangle + 0011\rangle + 001\rangle + 0100\rangle + 010\rangle + 0111\rangle + 011\rangle + 1000\rangle + 100\rangle + 1011\rangle + 101\rangle + 1100\rangle + 110\rangle + 1111\rangle + 111\rangle)$	$ +\rangle$ $ -\rangle$	$I \otimes I \otimes I$ $I \otimes I \otimes Z$
010	$\frac{1}{\sqrt{8}}(0000\rangle + 000\rangle + 0010\rangle + 001\rangle + 0101\rangle + 010\rangle + 0111\rangle + 011\rangle + 1000\rangle + 100\rangle + 1010\rangle + 101\rangle + 1101\rangle + 110\rangle + 1111\rangle + 111\rangle)$	$ +\rangle$ $ -\rangle$	$I \otimes I \otimes I$ $I \otimes Z \otimes I$
011	$\frac{1}{\sqrt{8}}(0000\rangle + 000\rangle + 0011\rangle + 001\rangle + 0101\rangle + 010\rangle + 0110\rangle + 011\rangle + 1000\rangle + 100\rangle + 1011\rangle + 101\rangle + 1101\rangle + 110\rangle + 1110\rangle + 111\rangle)$	$ +\rangle$ $ -\rangle$	$I \otimes I \otimes I$ $I \otimes Z \otimes Z$
100	$\frac{1}{\sqrt{8}}(0000\rangle + 000\rangle + 0010\rangle + 001\rangle + 0100\rangle + 010\rangle + 0110\rangle + 011\rangle + 1001\rangle + 100\rangle + 1011\rangle + 101\rangle + 1101\rangle + 110\rangle + 1111\rangle + 111\rangle)$	$ +\rangle$ $ -\rangle$	$I \otimes I \otimes I$ $Z \otimes I \otimes I$
101	$\frac{1}{\sqrt{8}}(0000\rangle + 000\rangle + 0011\rangle + 001\rangle + 0100\rangle + 010\rangle + 0111\rangle + 011\rangle + 1001\rangle + 100\rangle + 1010\rangle + 101\rangle + 1101\rangle + 110\rangle + 1110\rangle + 111\rangle)$	$ +\rangle$ $ -\rangle$	$I \otimes I \otimes I$ $Z \otimes I \otimes Z$
110	$\frac{1}{\sqrt{8}}(0000\rangle + 000\rangle + 0010\rangle + 001\rangle + 0101\rangle + 010\rangle + 0111\rangle + 011\rangle + 1001\rangle + 100\rangle + 1011\rangle + 101\rangle + 1100\rangle + 110\rangle + 1110\rangle + 111\rangle)$	$ +\rangle$ $ -\rangle$	$I \otimes I \otimes I$ $Z \otimes Z \otimes I$
111	$\frac{1}{\sqrt{8}}(0000\rangle + 000\rangle + 0011\rangle + 001\rangle + 0101\rangle + 010\rangle + 0110\rangle + 011\rangle + 1001\rangle + 100\rangle + 1010\rangle + 101\rangle + 1100\rangle + 110\rangle + 1111\rangle + 111\rangle)$	$ +\rangle$ $ -\rangle$	$I \otimes I \otimes I$ $Z \otimes Z \otimes Z$

Suppose channel created by the controller (Charlie) be encoded channel by classical

bits 001 shown as

$$\begin{aligned}
 |\Psi\rangle_{((b0)(b1)(a0)(C)(c_{a0})(c_{a1})(c_{b0}))} = & \frac{1}{\sqrt{8}}(|0000\rangle + |000\rangle + |0011\rangle + |001\rangle + |0100\rangle + |010\rangle + \\
 & + |0111\rangle + |011\rangle + |0100\rangle + |010\rangle + |0111\rangle + |011\rangle + |0111\rangle + |011\rangle + \\
 & + |1000\rangle + |100\rangle + |1011\rangle + |101\rangle + |1100\rangle + |110\rangle + |1111\rangle + |111\rangle)
 \end{aligned} \quad (26)$$

Then, the other steps of the protocol are same as the proposed protocol in previous sections. Only, after than the Step 6, Charlie must allow Bob and Alice for reconstructing the initial unknown state (Equation that written in below shows the wholes state of the system after than Step 6.). Thus, he needs to apply single qubit measurement in the X-basis on its qubit and tells to receivers his result and also, he must tell them about creating a channel by encoding bits. Therefore, we create Step 6-1 and Step 6-2 for it as the following:

$$\begin{aligned}
 & (\alpha_{00}b_0|0000\rangle + \alpha_{00}b_1|0011\rangle + \alpha_{01}b_0|0100\rangle + \alpha_{01}b_1|0111\rangle + \alpha_{10}b_0|1000\rangle + \\
 & + \alpha_{10}b_1|1011\rangle + \alpha_{11}b_0|1100\rangle + \alpha_{11}b_1|1111\rangle)_{(b0)(b1)(a0)(C)}
 \end{aligned} \quad (27)$$

Step 6-1: For reconstructing the initial state by Alice and Bob, Charlie must allow them by measuring in the X-basis on its qubit and tells to Alice and Bob his result. Also, he tells the type of created channel to them by encoding bits 001. If Charlies measured result is $|+\rangle$ ($|-\rangle$), then the state of other qubits is

$$\begin{aligned}
 & (\alpha_{00}b_0|000\rangle + \alpha_{00}b_1|001\rangle + \alpha_{01}b_0|010\rangle + \alpha_{01}b_1|011\rangle + \\
 & \alpha_{10}b_0|100\rangle + \alpha_{10}b_1|101\rangle + \alpha_{11}b_0|110\rangle + \alpha_{11}b_1|111\rangle)
 \end{aligned} \quad (28)$$

$$\begin{aligned}
 & (\alpha_{00}b_0|000\rangle - \alpha_{00}b_1|001\rangle + \alpha_{01}b_0|010\rangle - \alpha_{01}b_1|011\rangle + \\
 & \alpha_{10}b_0|100\rangle - \alpha_{10}b_1|101\rangle + \alpha_{11}b_0|110\rangle - \alpha_{11}b_1|111\rangle)
 \end{aligned} \quad (29)$$

Step 6-2: After than Charlie tells its measurement result and type of the created channel to Alice and Bob. Then, they need to apply local unitary operator as showed in the last column of Table 5.

Then, In Step 7, Alice and Bob can reconstruct transmitted states again and the BQCT is successfully finished.

3. Comparison

In this section, a comparison between quantum channels introduced in previous works and our proposed method for creating BQT protocol are presented as shown in Table 6 for many of the best previous works with various Sending qubits. In this table, columns of NUM Alice and NUM Bob stand for numbers of transmitted qubits between Alice and Bob, respectively. Also, Channel column shows introduced channel by previous works

and our method. In addition, final column express analogy between channel created by our method and previous works. As shown in this table, many of channels introduced in the previous works are same as with channels in proposed method with difference in moving of Control qubits or Charlies qubit [29, 31, 32, 34] where as stated in Section 1, placing of these qubits are arbitrary and can place everywhere. But, in many of previous works [27, 30], channel created by previous works are different from our method. These differences are due to that in these works two-qubit measurement are used such as measurement based on Bell state while in our method one-qubit measurement is used for creating channel that it is more efficient from previous works. Also, our method is a protocol with the numbers of Fewer qubits in channel than many previous works such as [27, 28].

4. Conclusion

In this paper, we presented a new general protocol of Bidirectional Quantum Teleportation (BQT) and Bidirectional Quantum Controlled Teleportation (BQCT) to transmit the arbitrary numbers of qubits between Alice and Bob with or without supervisor Charlie. This method can cover transmitting of each arbitrary types of qubits such as entanglement states or pure states simultaneously. The users can teleport each type state by using a $2(n + m)$ -qubit channel for the not entanglement states(pure states), $(n + 2m + 1)$ -qubit channel when one of the states is entanglement (for exp. State belong to Alice) and $(n + m + 2)$ -qubit channel for transmitting the entanglement states. Where n and m denote the number of Sending qubits between Alice and Bob, respectively. Also, for BQCT protocol, due to presence of Charlie, one qubit is added to the number of Main qubits. For creating channels, CNOT operator and Hadamard gate are used. In addition, this protocol uses single-qubit measurement based on Z or X which are more efficient than two-qubit measurements [34]. We hope that such BQT and BQCT protocols can be realized experimentally in the future.

Table 6. measurement results based on X done by Alice and Bob on Main qubits

Reference	Protocol type	NUM Alice	NUM Bob	Channel	Analogy between proposed channel and previous one
[33] method	BQT	2	2	$\frac{1}{4}[00000000\rangle + 00010001\rangle + 00100010\rangle + 00110011\rangle + 01000100\rangle + 01010101\rangle + 01100110\rangle + 01110111\rangle + 10001000\rangle + 10011001\rangle + 10101010\rangle + 10111011\rangle + 11001100\rangle + 11011101\rangle + 11101110\rangle + 11111111\rangle]$ _{a1b1a2b2b3b4a3a4}	Moving of Control Qubits
our method	BQT	2	2	$\frac{1}{4}[00000000\rangle + 00010001\rangle + 00100010\rangle + 00110011\rangle + 01000100\rangle + 01010101\rangle + 01100110\rangle + 01110111\rangle + 10001000\rangle + 10011001\rangle + 10101010\rangle + 10111011\rangle + 11001100\rangle + 11011101\rangle + 11101110\rangle + 11111111\rangle]$ _{b0b1a0a1Ca0Ca1Cb0Cb1}	Moving of Control Qubits
[32] method	BCQT	2 entanglement	1	$\frac{1}{2}[000000\rangle + 000111\rangle + 111000\rangle - 111111\rangle]$ ₁₂₃₄₅₆	Moving of control qubits and Charlie qubits
our method	BCQT	2 entanglement	1	$\frac{1}{2}[000000\rangle + 001101\rangle + 110010\rangle + 111111\rangle]$ _{b0b1a0cca0cb0}	Moving of Control Qubits and Charlie qubits
[31] method	BQT	2 entanglement	2 entanglement	$\frac{1}{2}[000000\rangle + 000111\rangle + 111000\rangle + 111111\rangle]$ _{a1b1b2a2a3b3}	Moving of Control Qubits
our method	BQT	2 entanglement	2 entanglement	$\frac{1}{2}[000000\rangle + 001101\rangle + 110010\rangle + 111111\rangle]$ _{b0b1a0a1ca0cb0}	Moving of Control Qubits
[30] method	BCQT	1	2	$\frac{\sqrt{2}}{4}[00000000\rangle + 00000011\rangle + 00011010\rangle + 00011110\rangle + 11100001\rangle + 11100010\rangle + 11111000\rangle + 11111100\rangle + 11111111\rangle]$ ₁₂₃₄₅₆₇	Moving of Control Qubits
our method	BCQT	1	2	$\frac{\sqrt{2}}{4}[00000000\rangle + 0011001\rangle + 0100010\rangle + 0111011\rangle + 1000100\rangle + 1011101\rangle + 1100110\rangle + 1111111\rangle]$ _{b0a0a1cca0cb0cb1}	Moving of Control Qubits
[29] method	BCQT	1	2	$\frac{\sqrt{2}}{4}[00000000\rangle + 0010010\rangle + 0100100\rangle + 0110110\rangle + 1001001\rangle + 1011011\rangle + 1101101\rangle + 1111111\rangle]$ ₁₂₃₄₅₆₇	Moving of Charli Qubits and difference in variations of Charlie's Qubits this qubit change according to qubit b0
our method	BCQT	1	2	$\frac{\sqrt{2}}{4}[00000000\rangle + 0011001\rangle + 0100010\rangle + 0111011\rangle + 1000100\rangle + 1011101\rangle + 1100110\rangle + 1111111\rangle]$ _{b0a0a1cca0cb0cb1}	in our method change according qubit cb1
[28] method	BCQT	1	1	$\frac{1}{2\sqrt{2}}[000000\rangle + 000011\rangle + 001100\rangle + 001111\rangle + 110000\rangle + 110011\rangle + 111100\rangle + 111111\rangle]$ _{a1b1c1a2c2b2}	Moving of Contorol Qubits by 6 qubit channel
our method	BCQT	1	1	$\frac{1}{2}[000000\rangle + 01101\rangle + 10010\rangle + 11111\rangle]$ _{b0a0cca0cb0}	in our method 5 qubit channel used
[27] method	BCQT	1	1	$\frac{\sqrt{2}}{4}[000000\rangle + 011100\rangle + 111000\rangle + 100100\rangle + 001111\rangle + 010011\rangle + 110111\rangle + 101011\rangle]$ ₁₂₃₄₅₆	Moving of Contorol Qubits by 6 qubit channel
our method	BCQT	1	1	$\frac{1}{2}[000000\rangle + 01101\rangle + 10010\rangle + 11111\rangle]$ _{b0a0cca0cb0}	in our method 5 qubit channel used

5. Acknowledgement

This work is supported by Kermanshah Branch, Islamic Azad University, Kermanshah, IRAN.

6. References

- [1] Nielsen. M.A., Chuang, I.L., *Quantum Computation and Quantum Information*, Cambridge University Press, (2010).
- [2] Bennett. C.H., Brassard. G., Crepeau. C., Jozsa. R., Peres. A., Wootters. W.K., *Teleporting an Unknown Quantum State via Dual Classical and Einstein-Podolsky-Rosen Channels*, Physical Review Letters 70(13), 1895-1899 (1993).
- [3] Li. X.H., Deng. F.G., Zhou. H.Y., *Efficient quantum key distribution over a collective noise channel*, Physical Review A 78(2), 022321 (2008).
- [4] Grudka. A., Wjck. A., *Symmetric scheme for superdense coding between multiparties*, Physical Review A 66(1), 014301 (2002).
- [5] Xiao. L., Long. G.L., Deng. F.G., Pan. J.W., *Efficient multiparty quantum-secret-sharing schemes*, Physical Review A 69(5), 052307 (2004).
- [6] Zhang. Q.n., Li. C.c., Li. Y.h., Nie. Y.y., *Quantum secure direct communication based on four-qubit cluster states*, International Journal of Theoretical Physics 52(1), 22-27 (2013).
- [7] Lance. A.M., Symul. T., Bowen. W.P., Sanders. B.C., Lam. P.K., *Tripartite quantum state sharing*, Physical review letters 92(17), 177903 (2004).
- [8] Ren. B.C., Du. F.F., Deng. F.G., *Two-step hyperentanglement purification with the quantum-state-joining method*, Physical Review A 90(5), 052309 (2014).
- [9] Cardoso. W., *Teleportation of GHZ-states in QED-cavities without the explicit Bell-state measurement*, International Journal of Theoretical Physics 47(4), 977-982 (2008).
- [10] Shi. B.S., Tomita. A., *Teleportation of an unknown state by W state*, Physics Letters A 296(4), 161-164 (2002).
- [11] Yang. K., Huang. L., Yang. W., Song. F., *Quantum teleportation via GHZ-like state*, Int. J. Theor. Phys. 48(2), 516-521 (2009).
- [12] Tian. D., Tao. Y., Qin. M., *Teleportation of an arbitrary two-qudit state based on the non-maximally four-qudit cluster state*, Science in China Series G: Physics Mechanics and Astronomy 51(10), 1523-1528 (2008).
- [13] Tang. S.Q., Shan. C.J., Zhang. X.X., *Quantum teleportation of an unknown two-atom entangled state using four-atom cluster state*, Int. J. Theor. Phys 49(8), 1899-1903 (2010).
- [14] Nandi. K., Mazumdar. C., *Quantum teleportation of a two qubit state using GHZ-like state*, Int. J. Theor. Phys 53(4), 1322-1324 (2014).
- [15] Karlsson. A., Bourennane. M., *Quantum teleportation using three-particle entanglement*, Physical Review A 58(6), 4394 (1998).
- [16] Yang. C.P., Han. S., *A scheme for the teleportation of multiqubit quantum information via the control of many agents in a network*, Physics Letters A 343(4), 267-273 (2005).
- [17] Deng. F.G., Li. C.Y., Li. Y.S., Zhou. H.Y., Wang. Y., *Symmetric multiparty-controlled teleportation of an arbitrary two-particle entanglement*, Physical Review A 72(2), 022338 (2005).
- [18] Wang. Y.H., Song. H.S., *Preparation of partially entangled W state and deterministic multi-controlled teleportation*, Optics Communications 281(3), 489-493 (2008).
- [19] Wang. X.W., Su. Y.H., Yang. G.J., *Controlled teleportation against uncooperation of part of supervisors*, Quantum Information Processing 8(4), 319-330 (2009).
- [20] Tian-Yin. W., Qiao-Yan. W., *Controlled quantum teleportation with Bell states*, Chinese Physics B 20(4), 040307 (2011).

- [21] Fatahi. N., Naseri. M., Gong. L.H., Liao. Q.H., *High-Efficient Arbitrated Quantum Signature Scheme Based on Cluster States*, Int J Theor Phys, 55, pp.1-8(2016).
- [22] Fatahi. N., Naseri. M., *Quantum Watermarking Using Entanglement Swapping*, Int. J. Theor. Phys. 51, 2094 (2012).
- [23] Naseri. M., Heidari. S., Baghfalaki. M., Fatahi. N., Gheibi. R., Batle. J., Farouk. A., Habibi. A., *A new secure quantum watermarking scheme*, Optik-Int. J. Light Electron Opt. 139, 77 86 (2017).
- [24] Zha. X.W., Zou. Z.C., Qi. J.X., Song. H.Y., *Bidirectional quantum controlled teleportation via five-qubit cluster state*. Int. J. Theor. Phys. 52(6), 1740-1744 (2013).
- [25] Yan. A., *Bidirectional controlled teleportation via six-qubit cluster state*, Int. J. Theor. Phys. 52(11), 3870-3873 (2013).
- [26] Sun. X., Zha. X., *A scheme of bidirectional quantum controlled teleportation via six-qubit maximally entangled state*, Acta Photonica Sin 48, 1052-1056 (2013).
- [27] Chen. Y., *Bidirectional quantum controlled teleportation by using a genuine six-qubit entangled state*, Int. J. Theor. Phys. 54(1), 269-272 (2015).
- [28] Hassanpour. S., Houshmand. M., *Bidirectional quantum controlled teleportation by using EPR states and entanglement swapping*, arXiv preprint arXiv:1502.03551 (2015).
- [29] Hong. W.q., *Asymmetric bidirectional controlled teleportation by using a seven-qubit entangled state*, Int. J. Theor. Phys. 55(1), 384-387 (2016).
- [30] Sang. M.h., *Bidirectional Quantum Controlled Teleportation by using a Seven-qubit Entangled State*, Int. J. Theor. Phys. 55(1), 380-383 (2016).
- [31] Hassanpour. S., Houshmand. M., *Bidirectional teleportation of a pure EPR state by using GHZ states*, Quantum Information Processing 15(2), 905-912 (2016).
- [32] Li. Y.h., Nie. L.p., Li. X.l., Sang. M.h., *Asymmetric Bidirectional Controlled Teleportation by Using Six-qubit Cluster State*, Int. J. Theor. Phys. 55(6), 3008-3016 (2016).
- [33] Zadeh. M.S.S., Houshmand. M., Aghababa. H., *Bidirectional Teleportation of a Two-Qubit State by Using Eight-Qubit Entangled State as a Quantum Channel*, Int. J. Theor. Phys., 1-12 (2017).
- [34] Deng. F.G., Li. X.H., Li. C.Y., Zhou. P., Zhou. H.Y., *Quantum state sharing of an arbitrary two-qubit state with two-photon entanglements and Bell-state measurements*, The European Physical Journal D-Atomic, Molecular, Optical and Plasma Physics 39(3), 459-464 (2006).