

# Channels, Remote Estimation and Queueing Systems With A Utilization-Dependent Component: A Unifying Survey Of Recent Results

Varun Jog, Richard J. La, Michael Lin, and Nuno C. Martins

**Abstract**—In this article, we survey the main models, techniques, concepts, and results centered on the design and performance evaluation of engineered systems that rely on a utilization-dependent component (UDC) whose operation may depend on its usage history or assigned workload. Specifically, we report on research themes concentrating on the characterization of the capacity of channels and the design with performance guarantees of remote estimation and queueing systems. Causes for the dependency of a UDC on past utilization include the use of replenishable energy sources to power the transmission of information among the sub-components of a networked system, and the assistance of a human operator for servicing a queue. Our analysis unveils the similarity of the UDC models typically adopted in each of the research themes, and it reveals the differences in the objectives and technical approaches employed. We also identify new challenges and future research directions inspired by the cross-pollination among the central concepts, techniques and problem formulations of the research themes discussed.

**Index Terms**—Channel capacity, task scheduling, remote estimation, queueing, energy harvesting, human factors, age of information, security.

## I. INTRODUCTION

As new technologies and applications emerge, the algorithms that determine the functionality and regulate the operation of engineered systems have to contend with unexampled constraints and nonstandard problems. This evolution has been evident for communication [1], cyber-physical [2], [3], human-assisted [4], networked estimation [5] and control [6] systems, which are now designed for maximal performance subject to restrictions that are more intricate than the conventional limits on reliability and power usage. In this article, we provide a partial account of such advances by surveying models, concepts and results on the characterization of channel capacity, and the design and performance analysis of queueing and remote estimation systems, all of which have in common the unconventional attribute of relying on a component whose performance may be constrained by its usage history and possibly also be affected by the workload assigned to it. We refer succinctly to this class of components as **UDC**, which

stands for utilization-dependent component. We do not aim at a comprehensive survey; instead, we will cite a selection of published work relevant to each key concept, problem formulation or technique on an as-needed basis for illustration.

A primary goal of this article is to highlight the commonalities in the presented studies and describe some of existing tools available to investigate challenging problems in these and other related fields. Our hope is that this survey article will serve as a good starting point for those who are interested in conducting research in these areas and foster future research that builds on the cross-pollination among the methods and problem formulations originally developed and employed on each of the research themes broached.

**Paper structure:** After the Introduction, in Section II we define a class of UDCs that is general enough to model the performance restrictions imposed by the reliance on the energy harvested from stochastic sources, human-assisted decision-making, or human labor. In Section III, we introduce widely-used models quantifying certain performance-limiting factors, such as mental workload, queueing workload and the state of charge of the battery of an energy harvesting module. Subsequently, in Sections IV - VI, we employ these definitions as a unifying framework to discuss research on methods to design and analyze the performance of systems comprising a UDC in the context of communication, remote estimation, and queueing respectively. In Section VII, we discuss recent work that addresses a class of problems that combines models, concepts and metrics from Sections V and VI, and, hence, serves as an example of the sort of research this survey intends to foster, and the UDC framework may facilitate. This article ends with the conclusions and future directions proposed in Section VIII.

**Notation** Throughout the article, we use  $\mathbb{N}$  and  $\mathbb{N}_+$  to denote the set of non-negative integers and positive integers, respectively. When appropriate, we assume that all random variables and stochastic processes are defined on a common probability space. In addition, for notational simplicity, we use  $\mathcal{P}_{R_1|R_2}(r_1|r_2)$  to denote the conditional probability  $\mathbf{P}(R_1 = r_1|R_2 = r_2)$ , where  $R_1, R_2$  are random variables/vectors defined on the same probability space.

## II. A GENERAL UTILIZATION-DEPENDENT COMPONENT (UDC) MODEL

We start by presenting a model that is general enough to describe all types of UDC considered throughout this article.

The authors are listed according to the lexicographical order of their last names. Varun Jog is with the Electrical and Computer Engineering Department at UW-Madison. Richard J. La, Michael Lin, and Nuno Miguel Lara Cintra Martins are with the Department of Electrical and Computer Engineering and the Institute for Systems Research, University of Maryland, College Park, MD, 20742 USA. E-mails: vjog@wisc.edu, {hyongla, mlin1025, nmartins}@umd.edu. Work writing this article was supported by AFOSR grant FA95501510367, NSF grant ECCS 1446785 and NIST grant 70NANB16H024

Without loss of generality, we limit our discussion to discrete-time processes and models. Namely, time takes values in the set of non-negative integers  $\mathbb{N}$ .

**Definition 1. (UDC Model)** *The following describes the two main sub-components of the UDC model (see Fig. 1).*

- The first sub-component is a partially-observed controlled Markov chain (POCMC),<sup>1</sup> whose state is represented as  $S := \{S(k) : k \in \mathbb{N}\}$ . It has two inputs denoted as  $Y := \{Y(k) : k \in \mathbb{N}\}$  and  $U := \{U(k) : k \in \mathbb{N}\}$ , where the latter is an external control process. The outputs are indicated as  $O := \{O(k) : k \in \mathbb{N}\}$  and  $W := \{W(k) : k \in \mathbb{N}\}$ . The former is characterized by an output kernel and is available to the policy that generates  $U$ , while the latter is a deterministic function of  $S$  that we refer to as the performance process. The processes  $U$ ,  $Y$ ,  $S$  and  $W$  take values in given alphabets  $\mathbb{U}$ ,  $\mathbb{Y}$ ,  $\mathbb{S}$  and  $\mathbb{W}$ , respectively, which are subsets of real coordinate spaces. The POCMC is specified by maps  $\mathcal{S} : \mathbb{S}^2 \times \mathbb{U} \times \mathbb{Y} \rightarrow [0, 1]$ ,  $\mathcal{O} : \mathbb{O} \times \mathbb{S} \times \mathbb{U} \rightarrow [0, 1]$  and  $\mathcal{W} : \mathbb{U} \times \mathbb{S} \rightarrow \mathbb{W}$ . The first two determine the state transition probability and the output kernel as follows:

$$\mathcal{S}(s^+|s, u, y) := \mathcal{P}_{S(k+1)|S(k), U(k), Y(k)}(s^+|s, u, y),$$

$$s, s^+ \in \mathbb{S}, u \in \mathbb{U}, y \in \mathbb{Y}$$

$$\mathcal{O}(o|s, u) := \mathcal{P}_{O(k)|S(k), U(k)}(o|s, u),$$

$$o \in \mathbb{O}, s \in \mathbb{S}, u \in \mathbb{U}$$

The performance process is determined as  $\mathcal{W} : (U(k), S(k)) \mapsto W(k)$ .

- The second sub-component is an action kernel that models the functionality whose performance is affected by the process  $W$ . Specifically, the output of the action kernel is  $Y$  and the inputs are  $W$  and an external source or command signal denoted as  $X := \{X(k) : k \in \mathbb{N}\}$ . The processes  $X$  and  $Y$  take values in given alphabets  $\mathbb{X}$  and  $\mathbb{Y}$ , respectively, which are subsets of real coordinate spaces. A map  $\mathcal{A} : \mathbb{X} \times \mathbb{W} \rightarrow [0, 1]$  specifies probabilistically  $Y$  in terms of  $X$  and  $W$  as follows:

$$\mathcal{A}(y|x, w) := \mathcal{P}_{Y(k)|X(k), W(k)}(y|x, w),$$

$$y \in \mathbb{Y}, x \in \mathbb{X}, w \in \mathbb{W}$$

Since  $X$  and  $U$  are both inputs of the overall UDC model, we allow causal policies that determine them in terms of  $O$ .

The definition of the UDC model is not complete until we specify the probabilistic dependence among the implicit sources of randomness of the state recursion and the output kernels. These will be particularized throughout the text on an as-needed basis. Typically,  $S(k+1)$  and  $O(k)$  are conditionally independent given  $S(k)$ ,  $U(k)$  and  $Y(k)$ ; and  $Y(k)$  and  $O(k)$  are conditionally independent given  $S(k)$ ,  $U(k)$  and  $X(k)$ .

<sup>1</sup>Here, we consider a POCMC in the model, rather than a controlled Markov chain (CMC), to allow scenarios where the states are partially observed. However, this assumption is not critical for the purpose of this article.




Fig. 1. Basic overall structure of the utilization-dependent component (UDC) model.

Although most existing work adopts variations of the models discussed in Section III, we opted to define a UDC model that is general enough to be used as a common framework to facilitate our presentation in this article and also for future work.

### III. COMMONLY USED POCMC MODELS

We proceed with defining a few common POCMC models, which we will invoke later appropriately altered to suit a specific application. In Sections III-A and III-B, we will specify  $W$  as a function of  $U$  and we will explicitly describe a state recursion in cases when it is clearer to do so. Because the output kernel is application dependent, we will defer its specification on an as-needed basis to Sections IV-V. Typical cases include when  $O$  equals  $S$  or when additive measurement noise is present.

To be concise, when the POCMC is deterministic, we specify it via the functional recursion that governs the state update in terms of the inputs, and we express each output as a function of the current state and inputs. In the stochastic case, the probabilistic state recursion and output kernel can always be specified by the conditional probabilities associated with  $\mathcal{S}$  and  $\mathcal{O}$ , respectively. The action kernel is specified in an analogous manner.

In order to appropriately indicate the dependence on certain parameters, or to discern which model is associated with a given internal process, such as  $S$  and  $W$ , we often annotate them with a self-descriptive superscript.

#### A. Utilization ratio and workload models

The concept of *mental workload* [4], in human-assisted systems, refers broadly to the burden imposed on a human operator by the difficulty of tasks and the frequency with which they are assigned. Hence, considering that it is known to influence the performance of a human operator [7], quantifying workload is important for the design of task assignment policies. In spite of having a rather simple structure, [8, Chapter 11] explains why the utilization ratio defined below is a pertinent mental workload metric. Here, the UDC is a human operator who has to service tasks from a queue. The types of services carried out by an operator include classification, supervision [9], [10] or assembly jobs within a production system [11].

**Definition 2. Utilization ratio:** The utilization ratio POCMC for a given positive averaging horizon  $T$  is defined as:

$$W^{r,T}(k) = \frac{1}{T} \sum_{i=1}^{\min\{T,k\}} U(k-i), \quad k \in \mathbb{N}_+ \quad (1)$$

where we adopt the convention that  $\mathbb{W}^{r,T} = \mathbb{R}_+$ ,  $W^{r,T}(0) = 0$  and  $U$  is a scalar non-negative process that governs the level of utilization.

In its simplest and most prevalent form, the set of utilization levels  $\mathbb{U}$  would be  $\{0, 1\}$ , and  $U(k) = 1$  and  $U(k) = 0$  would indicate whether the component is being used or not, respectively, at time  $k$ . The research on intelligent task management reported in [12], also uses  $\mathbb{U} = \{0, 1\}$  for the following alternative mental workload metric quantifying utilization ratio with a forgetting factor.

**Definition 3. Utilization ratio with forgetting factor:** Given a forgetting factor  $\alpha$  in  $(0, 1)$ , the associated utilization ratio POCMC is defined as:

$$S^{f,\alpha}(k+1) = \alpha S^{f,\alpha}(k) + U(k), \quad k \in \mathbb{N}, \quad S^{f,\alpha}(0) = 0 \quad (2)$$

$$W^{f,\alpha}(k) = (1 - \alpha) S^{f,\alpha}(k), \quad k \in \mathbb{N} \quad (3)$$

where we adopt the convention that  $\mathbb{W}^{f,\alpha}$  and  $\mathbb{S}^{f,\alpha}$  are  $\mathbb{R}_+$  and  $U$  is a scalar non-negative process that governs the level of utilization. Notice that the performance process can be computed directly for  $k$  greater than or equal to 1 as  $W^{f,\alpha}(k) = (1 - \alpha) \sum_{i=0}^{k-1} \alpha^{k-i-1} U(i)$ .

The authors of [13] also adopt the utilization ratio with forgetting factor to model the dynamics of the temperature of the circuitry of the transmitter that broadcasts information across an additive noise link, subject to a transmission power process  $U$ . In this context,  $\mathbb{U}$  is  $\mathbb{R}_+$  and the UDC is the resulting communication channel whose performance is adversely affected by the thermal noise that intensifies with increasing temperature. Related work on allocation of energy harvested from a stochastic source for wireless transmission subject to constraints on temperature is reported in [14], while thermal effects were considered in [15] in the context of distributed estimation.

In contrast to the concept of mental workload, in the queueing literature the workload affecting the performance of the server quantifies the *effort* needed to complete the tasks apportioned to the server, but not yet completed. The following is a discrete-time approximation of the continuous-time model governing the workload process analyzed in [16].

**Definition 4. Queueing Workload:** The following defines the queueing workload POCMC for a component acting as a server:

$$S^w(k+1) = S^w(k) + U(k) - \check{Y}(k), \quad k \in \mathbb{N}, \quad S^w(0) = 0 \quad (4)$$

$$W^w(k) = S^w(k) \quad (5)$$

where  $\mathbb{S}^w$ ,  $\mathbb{U}$  and  $\mathbb{Y}$  are  $\mathbb{N}$ . Here,  $U(k)$  and  $\check{Y}(k)$  may represent the number of work quanta, or effort, associated with the incoming and completed tasks at time  $k$ , respectively. Notice

that, given the structure in Fig. 1,  $\check{Y}(k)$  must be determined as a function of  $Y(k)$ . We assume that  $\check{Y}(k)$  must be zero when  $S^w(k)$  and  $U(k)$  are zero, which requires a properly defined action kernel<sup>2</sup>.

### B. Energy harvesting models

We also consider cases in which the state of the POCMC is governed not only by utilization but, unlike the models covered in Section III-A, also by extrinsic stochastic processes. Prime examples of these, include models of the so-called state of charge (SOC) quantifying the energy stored in a battery that is repeatedly recharged using energy harvested from unsteady sources. We propose the following model that is both a generalization and an adaptation to our discrete-time framework of ubiquitous models, such as those used in [17], [18]. Our model is general enough to capture the effects described in [19, Part IV] for microbatteries that are often used in small devices powered by energy harvesting, including implanted medical devices [20].

### Definition 5. Energy harvesting (EH) model

Let  $S^A := \{S^A(k) : k \in \mathbb{N}\}$  be a given homogeneous Markovian process that quantifies not only the energy harvested over time but possibly also other stochastic phenomena that influence the operation of the battery and its recharging subsystems. This process takes values in a subset  $\mathbb{S}^A$  of a real coordinate space. A given map  $\Delta^E : \mathbb{S}^{soc} \times \mathbb{S}^A \times \mathbb{R}_+ \rightarrow \mathbb{R}_+$  governs the dynamics of the energy harvesting POCMC according to following recursion:

$$S^{soc}(k+1) = S^{soc}(k) + \Delta^E(S^{soc}(k), S^A(k), W^E(k)), \quad k \in \mathbb{N}$$

where we assume that  $S^{soc}(k)$ , which quantifies the SOC at time  $k$ , is in  $\mathbb{S}^{soc} := [0, \bar{s}^{soc}]$  and  $\bar{s}^{soc}$  denotes the maximum SOC. The initial SOC is quantified by  $S^{soc}(0)$ . Here,  $W^E$  takes values in  $\mathbb{R}_+$  and quantifies the energy effectively extracted from the battery for use by the action kernel. The map  $\Delta^E$  quantifies the net change in the battery charge resulting from the difference between the effect of  $W^E(k)$  and the energy harvested. The state of the POCMC can be chosen as  $S^E := \{(S^{soc}(k), S^A(k)) : k \in \mathbb{N}\}$ . The map  $W^E$  that determines  $W^E$  in terms of  $S^E$  and  $U$  is described below in Remark 1.

The map  $\Delta^E$  is characteristic of each battery and it must satisfy the following consistency conditions:

$$\Delta^E(s^{soc}, s^A, w^E) \leq \bar{s}^{soc} - s^{soc}, \quad (6)$$

$$\Delta^E(s^{soc}, s^A, w^E) \geq -s^{soc}, \quad (7)$$

for all  $s^{soc}$ ,  $s^A$  and  $w^E$  in  $\mathbb{S}^{soc}$ ,  $\mathbb{S}^A$  and  $\mathbb{R}_+$ , respectively. We also assume that  $\Delta^E(s^{soc}, s^A, w^E)$  is continuous with respect to  $w^E$ .

### Remark 1. (Description of $W^E$ )

As is known since the early work in [21], each battery type has a discharge curve that characterizes the voltage in terms of the SOC. Invariably, even for modern batteries [22], the voltage decreases as the SOC drops, which leads to the following constraints:

<sup>2</sup>In particular, this will require that  $Y(k)$  carries enough information to determine when  $U(k)$  is zero.

- The maximum energy that can be delivered by the battery at any time  $k$  is a decreasing function of the SOC, which we represent as  $\mathcal{D} : \mathbb{S}^{\text{SOC}} \rightarrow \mathbb{R}_+$ . More concretely, the constraint is given by:

$$W^E(k) \leq \mathcal{D}(S^{\text{SOC}}(k)), \quad k \in \mathbb{N} \quad (8)$$

- There is a positive minimum SOC, denoted as  $\underline{s}^{\text{SOC}}$ , below which the voltage is too low to power the component. This leads to the following constraint that must be satisfied for every  $k$  in  $\mathbb{N}$ :

$$(\Delta^E(S^{\text{SOC}}(k), S^A(k), W^E(k)) + S^{\text{SOC}}(k) - \underline{s}^{\text{SOC}}) W^E(k) \geq 0 \quad (9)$$

Consequently,  $U$ , which represents the energy requested by the control policy, may differ from  $W^E$ . To be more specific, the energy extracted from the battery is determined in terms of  $U$  and the state of the EH model via the map  $\mathcal{W}^E : (s^E, u) \mapsto w^E$  specified as follows:

$$w^E = \max \left\{ \tilde{w}^E \geq 0 \mid \tilde{w}^E \leq u, \tilde{w}^E \leq \mathcal{D}(s^{\text{SOC}}), \right. \\ \left. (\Delta^E(s^{\text{SOC}}, s^A, \tilde{w}^E) + s^{\text{SOC}} - \underline{s}^{\text{SOC}}) \tilde{w}^E \geq 0 \right\}$$

The following is a simplified version of the EH model that is characterized by  $\Delta^E$  with a linear range in which it quantifies the difference between the energy used and harvested, and it also implements a saturation that restricts the SOC to the interval  $\mathbb{S}^{\text{SOC}}$ .

**Definition 6. (Linear-saturated EH model)**

The linear-saturated EH model is specified as follows for every  $k$  in  $\mathbb{N}$ :

$$S^{\text{SOC}}(k+1) = \min\{S^{\text{SOC}}(k) + S^A(k) - W^E(k), \bar{s}^{\text{SOC}}\} \quad (10a)$$

$$W^E(k) = \begin{cases} U(k) & \text{if } U(k) \leq S^{\text{SOC}}(k) + S^A(k) \\ S^{\text{SOC}}(k) + S^A(k) & \text{otherwise} \end{cases} \quad (10b)$$

where  $S^A(k)$ , in this simplified model, represents the energy harvested at time  $k$ .

The linear-saturated EH model does not capture the effects of the discharge curve and the changes that the mechanisms of charge and discharge go through as the SOC varies. The following is another simplified model in which the SOC takes values in a finite set and evolves as a controlled Markov chain (CMC).

**Definition 7. (Finite-state EH model)**

The SOC evolves according to a CMC whose state  $S^E := \{S^E(k) : k \in \mathbb{N}\}$  takes values in  $\mathbb{S}^E := \{0, 1, \dots, \bar{s}^E\}$ . The following map determines the probability transition map for  $S^E$  in terms of  $U$ :

$$S^E(s^+ | s, u, y) = \begin{cases} \hat{\Gamma}_s(u) & \text{if } s^+ = s + 1, s < \bar{s}^E \\ \check{\Gamma}_s(u) & \text{if } s^+ = s - 1, s > 0 \\ 1 - \hat{\Gamma}_s(u) - \check{\Gamma}_s(u) & \text{if } s^+ = s \end{cases}, \\ s^+, s \in \mathbb{S}^E, u \in \mathbb{U}, y \in \mathbb{Y}$$

where  $\hat{\Gamma}_s : \mathbb{U} \rightarrow [0, 1]$  and  $\check{\Gamma}_s : \mathbb{U} \rightarrow [0, 1]$  are given maps satisfying  $\check{\Gamma}_0(u) = 0$ ,  $\hat{\Gamma}_{\bar{s}^E}(u) = 0$  and  $\hat{\Gamma}_s(u) + \check{\Gamma}_s(u) \leq 1$ . Here, we assume that  $S^E(k+1)$  is independent of  $Y(k)$  when conditioned on  $S^E(k)$  and  $U(k)$  taking values  $s$  and  $u$ , respectively. In this case, a given map  $\mathcal{W}^E : \mathbb{S}^E \times \mathbb{U} \rightarrow \mathbb{R}_+$  determines the energy used by the action kernel as  $\mathcal{W}^E : (S^E(k), U(k)) \mapsto W^E(k)$ .

#### IV. COMMUNICATION CHANNELS

In recent years, there has been a tremendous amount of research focused on energy harvesting wireless communication systems. For a comprehensive survey, we refer the reader to survey articles [23], [24], [25]. As detailed above, an energy harvesting transmitter is a UDC with a state that indicates the amount of charge available for usage. In what follows, we provide a brief survey of two key areas: determining channel capacities and optimal scheduling policies in energy harvesting systems.

From an information-theoretic perspective, a key problem is identifying the capacity of an energy harvesting communication channel. The capacity of an additive white Gaussian noise (AWGN) channel with an energy harvesting transmitter was analyzed in references [26] and [27], for the infinite battery case and the no-battery case, respectively. Various upper and lower bounds on capacities have been studied in [28], [29], [30], [31], [32]. A general formula for the capacity of a point-to-point energy harvesting channel was established in [33]. Reference [33] also established a novel connection between the channel capacity and the optimal throughput (discussed below) for an energy harvesting transmitter. Beyond point-to-point channels, the capacity of energy harvesting multiple access channels (MACs) has been analyzed in [34], [35], where a general capacity formula is derived, along with lower and upper bounds on capacity.

A significant amount of research has focused on the problem of scheduling for an energy harvesting transmitter. In this case, the transmitter has an energy queue as well as a data queue, and the goal is to transmit data to the recipients in the least amount of time, or equivalently transmit the maximum amount of data until a certain time. This problem has been studied in the offline setting, where the energy arrivals are non-causally known, as well as the online setting where the transmitter has causal information about energy and data arrival [24], [25]. For the offline case, a variety of channel models have been investigated including point-to-point channels, broadcast channels [36], [37], interference channels [38], and MAC channels [39]. The online case has also been studied for the point-to-point channel [40], the broadcast channel [41], and the MAC channel [42]. We refer to [42] for a thorough list of references concerning online and offline scheduling in energy harvesting channels. In all the models described so far, the transmitter utilizes energy for the sole purpose of transmission. Energy harvesting transmitters which expend energy on sensing, computing, communicating, and possessing imperfect batteries have been surveyed in [25].

### A. Channels with evolving power constraints

In addition to energy harvesting systems, we show that the UDC framework may also be used to analyze more general communication channels with time evolving power constraints. We describe these constraints below. The AWGN channel is one of the most popular channel models in information theory due to its relevance in practical applications. Evaluating the capacity of the AWGN channel under a variety of power constraints is a problem that has received much attention in the literature. The classical constraint studied by Shannon [43] involved an average power constraint of  $P_{avg}$ . In other words, if  $(X(1), X(2), \dots, X(n))$  is the input to a channel, then it must satisfy

$$\frac{1}{n} \sum_{k=1}^n \|X(k)\|^2 \leq P_{avg}.$$

Shannon showed that the capacity of this channel is achieved using a random Gaussian codebook. In addition to the average power constraint, another practically relevant power constraint is the peak power constraint. A peak power constraint of  $P_{peak}$  stipulates that every input  $X$  to the channel should satisfy  $\|X\|^2 \leq P_{peak}$ . Finding the capacity of this channel in the scalar case was first studied by Smith [44]. Smith showed that, although it is not possible to express the capacity in a closed-form expression, it may be calculated efficiently. The key observation in [44] was that the capacity is achieved by a *discrete* input distribution that is supported on a finite number of atoms in  $[-\sqrt{P_{peak}}, \sqrt{P_{peak}}]$ .

The flexible UDC framework allows us to model a variety of power-constrained channels. For example, the average power and peak power constraint may be restated as

$$\|X(k)\|^2 \leq \min \left\{ kP_{avg} - \sum_{j=1}^{k-1} \|X(j)\|^2, P_{peak} \right\}, \quad k \in \mathbb{N}_+.$$

It is evident that the power constraint on the  $k$ -th channel use depends not only on  $P_{avg}$  and  $P_{peak}$  but also on the symbols transmitted prior to time  $k$ . Therefore, this power constraint is *utilization dependent*. We now provide a description of the UDC framework used for modeling a large class of power-constrained communication channels.

**Definition 8** (Evolving power constraints). *An evolving power constraint is defined via a sequence of functions  $\{P_k : k \in \mathbb{N}\}$ , where  $P_k : \mathbb{R}_+^k \rightarrow \mathbb{R}_+$  such that  $P_k(u_1, u_2, \dots, u_k)$  determines the power constraint on the  $(k+1)$ -th transmission  $X(k+1)$ , where  $u_l$  is the power of the  $l$ -th transmitted symbol, i.e.,  $u_l = \|X(l)\|^2$ ,  $l \geq 1$ .*

**Definition 9** (Evolving power constraint with state). *An evolving power constraint with a state is characterized by three sequences of functions: (i)  $\{f_k : k \in \mathbb{N}\}$  with  $f_k : \mathbb{R}^k \rightarrow \mathbb{R}$ , (ii)  $\{\tilde{f}_k : k \in \mathbb{N}\}$ , where  $\tilde{f}_k : \mathbb{R}^2 \rightarrow \mathbb{R}$ , and (iii)  $\{p_k : k \in \mathbb{N}\}$  such that  $p_k : \mathbb{R} \rightarrow \mathbb{R}$ . These functions satisfy the property that  $f_k(u_1, \dots, u_k) = \tilde{f}_k(f_{k-1}(u_1, \dots, u_{k-1}), u_k)$ , i.e., the value of function  $f_k$  at time  $k$  can be computed from that of function  $f_{k-1}$  at time  $k-1$  and  $u_k$ .*

*An evolving power constraint is said to have a state  $f_k(u_1, \dots, u_k)$  at time  $k+1$  if the sequence of functions*

$P_k$  in Definition 8 may be written as  $P_k(u_1, \dots, u_k) = p_k(f_k(u_1, \dots, u_k))$ . Thus, the power constraint on the  $k$ -th symbol depends on the history of transmitted symbols up to time  $k-1$  through the state at time  $k$ .

Evolving power constraints may be used to describe several power constraints studied in the literature. We provide a few examples below:

**Example 1.** *Consider the standard average power constrained communication channel. Here, the constraint on the  $k$ -th symbol  $X(k)$  is given by*

$$\|X(k)\|^2 \leq kP_{avg} - \sum_{j=1}^{k-1} \|X(j)\|^2,$$

for some fixed  $P_{avg} > 0$ . This power constraint may be characterized as an evolving power constraint with state, as follows: For  $k \in \mathbb{N}$ , define  $f_k(x_1, \dots, x_k) = \sum_{j=1}^k \|x_j\|^2$ . This definition satisfies the property that  $f_{k+1}(x_1, \dots, x_{k+1})$  can be calculated using  $f_k(x_1, \dots, x_k)$  and  $x_{k+1}$ ; in particular,  $\tilde{f}_{k+1}(u, v) = u + v$ . The power constraint functions  $P_k$  as  $P_k(x_1, \dots, x_k) = (k+1)P_{avg} - f_k(x_1, \dots, x_k)$  for every  $k \in \mathbb{N}$ .

**Example 2.** *For an average power constraint of  $P_{avg}$  coupled with a peak power constraint of  $P_{peak}$ , the only change from above is that  $P_k(x_1, \dots, x_k) = \min(P_{peak}, (k+1)P_{avg} - f_k(x_1, \dots, x_k))$ .*

**Example 3.** *For a windowed-average power constraint over a window  $T$ , the state is the total energy expended over the last  $T-1$  transmitted symbols. By allowing states to be vector valued in  $\mathbb{R}^{T-1}$ , this constraint is easily accommodated in Definition 9.*

**Example 4.** *A  $(\sigma, \rho)$ -power constraint is found to be relevant in energy harvesting applications as well as neuroscience. The  $(\sigma, \rho)$ -power constraint is defined as follows: Let  $\sigma, \rho \geq 0$ . A codeword  $(x_1, x_2, \dots, x_n)$  is said to satisfy a  $(\sigma, \rho)$ -power constraint if*

$$\sum_{j=k+1}^l x_j^2 \leq \sigma + (l-k)\rho \quad \text{for all } 0 \leq k < l \leq n. \quad (11)$$

*The  $(\sigma, \rho)$ -power constraint essentially imposes a restriction on how bursty the transmit power can be, by constraining the total energy consumed over every interval to be approximately linear in the length of the interval. In energy harvesting communication systems, a  $(\sigma, \rho)$ -power constraint may be used to model a transmitter that harvests  $\rho$  units of energy per unit time, and is equipped with a battery with capacity of  $\sigma$  units, which is used to store unused energy for future transmissions. The  $(\sigma, \rho)$ -power constraints can be expressed equivalently by tracking a state parameter  $\sigma_k$ , that keeps track of the tightest constraint among the  $k+1$  inequalities for  $x_{k+1}$ . The state function  $\sigma_k$  evolves as follows:*

$$\sigma_k(x_1, \dots, x_k) = \min(\sigma, \sigma_{k-1}(x_1, \dots, x_{k-1}) + \rho - x_k^2).$$

*The power constraint function  $P_k$  is defined as  $P_k(x_1, \dots, x_k) = \sigma_k(x_1, \dots, x_k) + \rho$ . Note that  $\rho$  need*

not be constant over time, and such dependence or variability with respect to time is useful in modeling energy harvesting with arbitrary amounts of energy  $\rho_k$  harvested at time  $k$ .

We define a UDC model that imposes evolving power constraints on an action kernel that is a communication channel.

**Definition 10** (POCMC component). *Let  $\{(P_k, f_k, \tilde{f}_k) : k \in \mathbb{N}\}$  be an evolving power constraint with state. The POCMC component has state  $S(k)$  that tracks the state of the power constraint at time  $k$ , i.e.  $S(k) = f_{k-1}(u_1, \dots, u_{k-1})$ . An input  $U(k)$  indicates the desired power output for time  $k$ , i.e. the energy required to send symbol  $X(k)$ . The performance process  $W(k)$  is equal to the power constraint imposed on  $X(k)$ . In other words,  $W(k) = P_{k-1}(u_1, \dots, u_{k-1}) = p_{k-1}(S(k))$  is a deterministic function of  $S(k)$ . The state at time  $k+1$  satisfies  $S(k+1) = \tilde{f}_k(S(k), u_k)$ .*

**Definition 11** (Action kernel). *The action kernel is a communication channel with input  $X$  and output  $Y$ . At time  $k$ , the  $k$ -th symbol  $X(k)$  is scheduled to be transmitted. The output of the channel  $Y(k)$  depends on the input  $X(k)$ , the noise in the channel, as well as the performance process  $W(k)$ . Two natural cases to consider are:*

- 1) *If  $U(k) \leq W(k)$ , then  $X(k)$  is transmitted unaltered. Otherwise,  $X(k)$  is rescaled to have power  $W(k)$ , i.e.  $X'(k)$  is transmitted across the channel where  $X'(k) = X(k) \times \sqrt{\frac{W(k)}{U(k)}}$ .*
- 2) *If  $U(k) > W(k)$ , then  $X(k)$  is transmitted unaltered. Otherwise, there is no transmission, i.e.  $X'(k)$  is transmitted across the channel where  $X'(k) = 0$ .*

Note that since these are deterministic power constraints, the transmitter can calculate the power constraints on the  $k$ -th symbol in advance and ensure that  $X(k)$  satisfies these power constraints. However, this is not possible when the power constraints are random. An example of random power constraint is the following. Consider a stochastic process  $E := \{E(k) : k \in \mathbb{N}\}$ , where  $E(k)$ 's are independent and identically distributed random variables. We may now define the state as  $(S(k), E(k))$ , and the power constraint on the  $k$ -th symbol is computed via  $p_k(S(k), E(k))$ . The state evolution proceeds as  $S(k+1) = \tilde{f}_k(S(k), u_k, E(k))$ . This particular formulation is relevant to energy harvesting communication systems, discussed in Section III-B. In the absence of any output  $O(k)$ , the transmitter has no way of modifying its  $k$ -th symbol to satisfy the power constraints. A variety of feedback settings are worth considering:  $O(k) = S(k)$  or  $O(k) = (S(k), E(k))$ . Additionally, the transmitter may also receive feedback from the receiver, i.e.,  $O(k)$  contains  $Y(k)$ . The capacity of energy harvesting systems with feedback has also been investigated in recent years, and it has been found that feedback increases capacity [45]. In addition to random  $E(k)$ , yet another setting to consider is when the sequence of  $E(k)$  is completely arbitrary, but is known to lie in some set. This is analogous to arbitrarily varying channels [46], [47] and may also be modeled using the UDC framework.

## B. Additional channel models

Point-to-point communication under memoryless channels is widely studied and well-understood. However, there are several settings where this simple channel model is not sufficient. For example, we may consider channels that change with time, channels with memory, or channels that are simply unknown such as arbitrarily varying channels [46], [47]. We observe that many channel models of interest may be cast in the UDC framework by interpreting the channel as a utilization dependent channel. Such a reinterpretation suggests generalizations that may be harder to arrive at directly. We briefly describe three examples of interest below: interference channels, finite-state Markov channels [48], and channels with action dependent states [49].

**Inter-symbol interference:** Consider a discrete-time Gaussian inter-symbol interference channel as found in [50]. For an input  $X(k)$  at time  $k$  in  $\mathbb{N}_+$ , the output  $Y(k)$  of this channel is given by

$$Y(k) = \sum_{i=0}^{k-1} \alpha^i X(k-i) + N(k), \quad (12)$$

where  $N(k)$  is AWGN, and  $\alpha \in (0, 1)$ . Define the state of the channel at time  $k$  to be  $S(k) := \sum_{i=1}^{k-1} \alpha^i X(k-i)$ , and let  $U(k) = X(k)$  and  $W(k) = S(k)$ . Then, we have

$$\begin{aligned} S(k+1) &= \alpha(S(k) + U(k)) \quad \text{and} \\ Y(k) &= X(k) + W(k) + N(k). \end{aligned}$$

The first equation shows how the channel state  $S(k)$  depends on the channel usage via previous inputs to the channel. The second equation highlights the effect of the performance process  $W(k)$  on the action kernel, which is the communication channel from the input  $X$  to the output  $Y$ .

**Channels with action-dependent states:** Weissman [49] proposed a communication channel model with a state  $S(k)$  at time  $k$  which may be altered via an action  $U(k)$ . This model includes communication settings where the channel state is known to the encoder and allows for novel settings, such as channels with a “rewrite” option. Effective communication over such a channel involves manipulating the channel state via actions and then coding for the channel. Let the state of the channel  $S(k+1)$  at time  $k+1$  depend on the input  $U(k)$  according to the kernel  $\mathcal{P}_{S(k+1)|S(k), U(k)}$ . The action kernel is simply the communication channel where the output  $Y(k)$  depends on the input  $X(k)$  and the performance process  $W(k)$ , which is simply the channel state  $S(k)$  in this case (i.e.,  $W(k) = S(k)$ ), according to the kernel  $\mathcal{P}_{Y(k)|X(k), W(k)}$ . This setup completely captures the model in [49].

**Finite-state Markov channels:** The finite-state Markov channel, which was introduced in [48], consists of a channel with state  $S(k)$  that evolves according to a Markov process, independently of channel inputs and outputs. This may be thought of as a utilization-independent channel where the state evolves according to a Markov kernel  $\mathcal{P}_{S(k+1)|S(k)}$ . A simple generalization allows us to model utilization-dependent channels using a CMC: the channel state  $S(k)$  evolves as a CMC with an input  $U(k) = X(k)$  in accordance with a transition kernel  $\mathcal{P}_{S(k+1)|S(k), U(k)}$ . The channel input is also

$X(k)$ , and the channel output is  $Y(k)$  that is generated as per  $\mathcal{P}_{Y(k)|X(k),W(k)}$  with  $W(k) = S(k)$ . There are a number of open problems concerning such channels: Is it possible to calculate channel capacity in closed-form? If the input  $X = \{X(k) : k \in \mathbb{N}\}$  is fixed to be Markovian, what is the maximum achievable channel capacity?

## V. REMOTE ESTIMATION ACROSS A PACKET-DROP LINK POWERED BY ENERGY HARVESTING

We begin this section by describing a UDC consisting of a packet-drop link powered by energy harvested and stored according to the models delineated in Section III-B. The apportionment of energy for transmission of information across the link over time is governed by a control process. We then proceed to discussing a few research themes in which the link is used in a remote estimation context.

### A. Packet-drop links powered by energy harvesting

At each time  $k$ , the link can either convey unerringly a symbol in  $\mathbb{X}$  or a packet drop occurs. Implementation of the packet-drop link using wireless communication requires, for each  $k$ , that a codeword appropriately encoding  $X(k)$  is placed for transmission across one or more physical channels. The transmission of a codeword will, in general, require multiple uses of each channel. A decoder at the receiver attempts to recover  $X(k)$  and a packet drop occurs when it fails due to an outage caused by fading, interference or other detrimental effects. If  $\mathbb{X}$  is infinite, such as when it is a real coordinate space, we assume that the codeword length is large enough to encode  $X(k)$  with negligible quantization error.

**Definition 12. (EH packet-drop link)** A packet-drop link comprises an action kernel whose output alphabet is  $\mathbb{Y} := \mathbb{X} \cup \{\mathfrak{E}\}$ , where  $\mathfrak{E}$  indicates a packet drop. The input-output relationship is specified as follows:

$$Y(k) = \begin{cases} X(k) & \text{if } L(k) = 1 \\ \mathfrak{E} & \text{if } L(k) = 0 \end{cases} \quad (13)$$

where the link process  $L$  indicates that there is a successful transmission when  $L(k) = 1$  and the packet is dropped otherwise. We assume that a map  $\mathcal{L} : \mathbb{W}^E \rightarrow [0, 1]$  characterizes  $L$  probabilistically as follows:

$$\mathcal{P}_{L(k)|S^E(k),U(K)}(0|s^E, u) = \mathcal{L}(w^E), \quad k \in \mathbb{N}, \quad s^E \in \mathbb{S}^E, \quad u \in \mathbb{U} \quad (14)$$

which quantifies the probability of packet drop. Here,  $W^E$  and  $S^E$  are obtained from the EH model described in Definition 5 or a simplified version, such as the one specified in Definition 7. In addition, we assume that  $L(k)$ ,  $S^E(k+1)$  and  $O(k)$  are conditionally independent given  $S^E(k)$  and  $U(k)$ .

In a wireless communication setting, an outage causing a packet drop occurs when fading, which is stochastic in general, attenuates the transmitted signal to a point that the received power is below a threshold needed for decoding [51], [52]. The threshold depends on the codeword length, noise, interference characteristics [53] and it may also be stochastic. Here, we assume that fading and the transmission power are constant




Fig. 2. Basic overall structure of the remote estimation system considered.

during the transmission of the codeword encoding  $X(k)$ . Moreover,  $W^E(k)$  represents the total energy used attempting to transmit  $X(k)$ . Hence,  $\mathcal{L}$ , which quantifies the probability of outage given the transmission power as in (14), is a non-increasing function that can be determined on a case-by-case basis, such as in [54].

### B. Design of remote estimation systems: problem definitions

Henceforth, we prioritize the discussion of research on the design of remote estimation systems. Our choice is motivated not only by applications, such as monitoring of physical processes, but also by relevance for the design of control systems.

We consider the configuration depicted in Fig. 2 in which an estimator  $\mathcal{E}$  is a causal map that is possibly time-varying, and seeks to reconstruct a process  $V$  based on information sent to it via a packet-drop link according to  $\mathcal{E} : y(1:k) \mapsto v^E(k)$ , for  $k$  in  $\mathbb{N}$ . A transmitter is a causal map  $\mathcal{T}$  that is possibly time-varying, and uses  $V^T$  and  $O$  to produce  $X$  and  $U$  according to  $\mathcal{T} : (V^T(1:k), O(1:k)) \mapsto (X(k), U(k))$ , for  $k$  in  $\mathbb{N}$ . In most cases of interest  $V^T$  is either  $V$  itself, or a causal function of  $V$  possibly disrupted by additive or multiplicative noise. We refer to the pair  $(\mathcal{T}, \mathcal{E})$  in conjunction with the UDC that specifies the EH packet-drop link as a remote estimation system.

#### Remark 2. Synchronization between $\mathcal{T}$ and $\mathcal{E}$

Notice that one-step delayed feedback from the output of the link can be made available to  $\mathcal{T}$  through  $O$  by augmenting the state of the POCMC so as to include  $Y(k-1)$ . When such a feedback is present, a copy of the estimate  $V^E(k-1)$  can be replicated by  $\mathcal{T}$  at time  $k$ . This synchronization often simplifies the joint design of  $\mathcal{T}$  and  $\mathcal{E}$  to meet stability or optimality conditions.

We proceed with discussing the chronology of research on the design of remote estimation systems and control, with emphasis on the former.

#### Problem 1. (Optimal remote estimation system design)

Let an EH packet-drop link, the joint probabilistic description of  $V^T(1:k)$  and  $V(1:k)$  for all  $k$  in  $\mathbb{N}$  be given. For predetermined sets  $\mathbb{T}$  and  $\mathbb{E}$  of allowable transmitters and remote estimators, respectively, determine whether a pair  $(\mathcal{T}, \mathcal{E})$  exists that is optimal with respect to a given figure of merit  $\mathcal{J} : \mathbb{T} \times \mathbb{E} \rightarrow \mathbb{R}_+$  that should assess the quality of  $V^E$  relative to  $V$  and can include additional costs. If such a pair exists, determine one.

Unless stated otherwise, we assume the following widely-used covariance-based cost structure:

$$\mathcal{J}^{(2q, K)}(\mathcal{T}, \mathcal{E}) := \frac{1}{K} \sum_{k=1}^K \mathbb{E} \left[ \left( (V^{\mathcal{T}}(k) - V(k))^T (V^{\mathcal{T}}(k) - V(k)) \right)^q \right] \quad (15)$$

where  $q$  is a positive integer and  $K$  indicates the length of the optimization horizon.

Stabilizability in the  $m$ -th moment sense, as defined below, is another relevant design objective.

**Problem 2. ( $m$ -th moment stabilizability)**

Let an EH packet-drop link, the joint probabilistic description of  $V^{\mathcal{T}}(1:k)$  and  $V(1:k)$  for all  $k$  in  $\mathbb{N}$  be given. Consider that the  $m$ -th moment of  $V$  is unbounded. Determine whether a pair  $(\mathcal{T}, \mathcal{E})$  exists for which the  $m$ -th moment of  $V(k) - V^{\mathcal{E}}(k)$  is bounded for all  $k$  in  $\mathbb{N}$ . If such a pair exists, determine one.

Notice that the existence of a solution that is optimal for  $\mathcal{J}^{(2q, K)}(\mathcal{T}, \mathcal{E})$  in the limit when  $K$  tends to infinity may imply, under certain conditions,  $2q$ -th moment stabilizability.

When either  $\mathbb{T}$  or  $\mathbb{E}$  is a singleton in Problems 1 or 2, we say that the associated design problem is of the single-block type, and we qualify it as two-block otherwise.

**Remark 3. (Relevance of remote estimation for control systems)** There are at least two scenarios for which Problems 1 or 2 are relevant in the context of control systems. The first is when a packet-drop link connects the sensors that access the output of the plant to the controller. In this case, the transmitter is collocated with the sensors and the remote estimator is typically a component of the controller. The second setting is when the controller includes a transmitter to send its command signals to a remote estimator that is collocated with the actuator. A combination of both cases is also possible.

*C. Uncontrolled transmission: optimal policies*

As is surveyed in [6], the design of stabilizing and, whenever possible, optimal estimation and control systems whose components communicate via packet-drop links has been an active research topic for at least fifteen years. Early work assumed that the link process  $L$  was an uncontrolled time-homogeneous Markov chain. This assumption is realistic when the fading process, as indexed by  $k$ , is a real-valued time-homogeneous Harris chain and  $\mathcal{T}$  does not have the authority to select the transmission power, which may be kept constant thanks to a dependable energy supply.

Henceforth, we limit our discussion to remote estimation systems in which  $V$  and  $V^{\mathcal{T}}$  are obtained as follows:

$$V(k+1) = \mathbf{A}V(k) + N(k), \quad k \in \mathbb{N} \quad (16a)$$

$$V^{\mathcal{T}}(k) = \mathbf{C}V(k) + N^{\mathcal{T}}(k), \quad k \in \mathbb{N} \quad (16b)$$

where  $\mathbf{A}$  and  $\mathbf{C}$  are real matrices of appropriate dimensions and the noise processes  $N$  and  $N^{\mathcal{T}}$  are independent and white with nonsingular covariance. In the context of control systems,

an additional input term may be present in the right hand side of (16a) and (16b).

At first, the effect of uncontrolled packet drops was modeled as multiplicative noise [55], [56], which makes the analysis of stability and second moment optimal design amenable to techniques inspired on Markovian jump linear system theory [57]. Typically the noise process would be Bernoulli, which would take value 0 when a drop occurs. In a control systems setting, these multiplicative noises could affect the links carrying sensor measurements to the controller and control signals to the actuator. Most approaches focused on single-block design, which, depending on which links suffer packet drops, would be either a component at the sensors that processes measurements prior to transmission, a controller [58] or a remote estimator. As a consequence of the simplicity of the single-block framework, optimal policies and tight stabilizability conditions for state estimation and control can be obtained even when there is no link output feedback [59], [60], which can be viewed as a form of user datagram protocol (UDP).

The two-block remote estimation system formulated in [61] was the first to consider the simultaneous design of  $\mathcal{T}$  and  $\mathcal{E}$ . When (16) is detectable [62], [63] the approach in [61], which is specified in continuous-time, can be immediately adapted to our discrete-time framework. In such a case, when  $L$  is a Bernoulli process, the remote estimation system is  $m$ -th moment stabilizable if and only if the following condition holds:

$$p^{\text{outage}} \rho(\mathbf{A})^m < 1 \quad (17)$$

where  $p^{\text{outage}} := \mathcal{P}_{L(k)}(0)$  is the probability of drop and  $\rho(\mathbf{A})$  is the spectral radius of  $\mathbf{A}$ . As is shown in [61], a stabilizing solution is obtained by selecting  $\mathcal{T}$  as a Kalman filter and  $X$  as its state followed by a properly designed estimator  $\mathcal{E}$ . Subsequent work in [64] showed that the scheme in [61] is optimal with respect to a quadratic cost when  $N$  and  $N^{\mathcal{T}}$  are independent white Gaussian processes. Stabilizability in a control systems context was characterized in [65] using similar techniques for the case in which measurements are conveyed to the controller using two packet-drop links, with each having a distinct transmitter block. The setting in which a packet-drop link conveys command signals from the controller to the actuator was investigated in [66].

Interestingly, (17) can be obtained as the limiting case [67] when  $r$  tends to infinity of the condition in [68], [69], [70] that characterizes stabilizability when a  $r$ -ary erasure channel<sup>3</sup> connects the transmitter to the remote estimator.

*D. Controlled transmissions without packet drops*

We now consider the case in which transmissions may be controlled through  $U$ , while  $V$  and  $V^{\mathcal{T}}$  are modeled by (16). When restricted to the remote estimation framework adopted here, in which  $\mathcal{T}$  must be designed to appropriately generate both  $X$  and  $U$ , controlled transmissions were first studied in a stabilizability context in [61].

<sup>3</sup>We refer the reader to the comprehensive overviews in [71], [6] that describe the most important classical results on control subject to data-rate constraints.



In [61],  $\mathcal{T}$  incorporates a Kalman filter that uses  $V^\mathcal{T}$  to generate a local estimate  $\hat{V}$  of  $V$ . In addition, it implements policies that use the magnitude of  $\hat{V} - V^\mathcal{E}$  to determine the likelihood that a transmission is requested, which requires synchronization between  $\mathcal{T}$  and  $\mathcal{E}$  so that  $V^\mathcal{E}$  can be reconstructed at the transmitter. Notice that, in the absence of packet drops,  $\mathcal{T}$  and  $\mathcal{E}$  can be synchronized without the need for feedback through  $O$  since  $Y$  can be causally computed at the transmitter based on  $U$  and  $X$ . In this context, when  $V$  is scalar and the noises  $N$  and  $N^\mathcal{T}$  are Gaussian, a policy that requests a transmission when the magnitude of  $\hat{V} - V^\mathcal{E}$  exceeds a threshold was later shown<sup>4</sup> in [72] to be optimal jointly with a Kalman-like estimator, with respect to a cost that linearly combines the expected squared estimation error and the time-averaged probability of transmission. As reported in [74], threshold-type policies remain optimal when  $V$  has dimension two or higher, provided that  $A$  is a scaled orthogonal matrix. Although [75] shows that a jointly optimal transmitter and estimator pair exists for the aforementioned setting even when  $A$  is any real-valued matrix, the question of whether there is a jointly optimal pair admitting threshold-type policies for transmission remains an open problem. Certainty equivalence properties for these estimators, which are relevant for the design of optimal controllers, are investigated in [76]. Optimal strategies subject to restrictions on the total number of transmissions were determined in [58]. Results reported in [77] show that threshold-based schemes can be adapted to guarantee stabilizability of a system formed by a network of plants and controllers connected by multiple packet-drop links.

The framework in [74] was the first, in the context of remote estimation considered here, to allow for transmission policies that account for energy harvesting. Notably, it considers that  $U$  is generated based not only on  $V^\mathcal{T}$  but also on  $S^{\text{soc}}$ , as determined by the linear-saturated EH model (10a) for which the arrival process  $S^A$  is assumed i.i.d. and  $S^{\text{soc}}$  is normalized so that each transmission at time  $k$  requires  $W^E(k) = 1$ . In this context, the following theorem, which follows from [74, Theorems 3 and 4], establishes an important structural result.

**Theorem 1.** *When the noises in (16) are zero-mean white Gaussian, and there are no packet drops, there are transmission and estimation policies with the structure in (18) and (19), respectively, that are jointly optimal for the scalar case.*

$$V^\mathcal{E}(k) = \begin{cases} AV^\mathcal{E}(k-1) & \text{if } Y(k) = \mathfrak{E} \\ X(k) & \text{if } Y(k) \neq \mathfrak{E} \end{cases}, \quad k \in \mathbb{N} \quad (18)$$

$$U(k+1) = \begin{cases} 1 & \text{if } |\hat{V}(k+1) - AV^\mathcal{E}(k)| > \mathcal{G}(k, S^{\text{soc}}(k+1)) \\ 0 & \text{otherwise} \end{cases} \quad (19a)$$

$$X(k) = \hat{V}(k), \quad k \in \mathbb{N} \quad (19b)$$

Here,  $\mathcal{G}$  is a threshold that depends on time and the state of charge  $S^{\text{soc}}(k)$ . The threshold determines when  $U(k)$  is 1, in

<sup>4</sup>The techniques and results in [72] are to a significant extent equivalent to the research reported in [73] for paging and registration policies.

which case a transmission setting  $Y(k)$  to  $X(k)$  is requested at time  $k$ .

Methods to determine  $\mathcal{G}$  are described in [74]. It is remarkable that a policy pair with the simple structure in (18) and (19) is jointly optimal, which also guarantees that it accomplishes the *best* trade-off between transmitting at time  $k$  or saving energy to transmit later.

It is important to note that, barring the dependence of the thresholds for transmission on  $S^{\text{soc}}(k)$ , (18) and (19) are akin to the optimal policies in [72], [73]. As is explained in [74], one way to obtain these results is to establish that there is a jointly optimal policy pair whose estimator has the structure (18), after which the problem of finding a corresponding optimal transmission policy can be cast as an MDP [78] whose state is finite dimensional because  $\mathcal{T}$  and  $\mathcal{E}$  are synchronized. Subsequently, well-known results can be invoked to prove that restricting transmission policies to be memoryless functions of the state of the MDP incurs no loss of optimality. Properties of the probability distributions of the noises, such as symmetry and unimodality, are used to show that there is no optimality loss when these policies are further restricted to be of the form (19).

#### E. Controlled transmissions with packet drops and perfect feedback

In this subsection, we discuss recent work for the framework that extends of that of Section V-D by allowing packet drops in the link that connects the transmitter to the remote estimator.

**Assumption 1.** *Unless noted otherwise, here we assume that there is a causal map with which  $Y(k)$  can be recovered unerringly from  $O(1:k+1)$ , for all  $k$  in  $\mathbb{N}$ , which also implies that  $\mathcal{T}$  and  $\mathcal{E}$  can be synchronized.*

**Assumption 2.** *We also assume that  $S^{\text{soc}}(k)$  and  $S^A(k)$  can be recovered from  $O(1:k)$ , for all  $k$  in  $\mathbb{N}$ .*

We proceed to defining and subsequently discussing advantages and properties of a class of covariance-based transmission policies, which has been adopted in [79], [80], [81], [82], to list a few.

A transmission policy is classified as covariance-based when the dependence of  $U$  on  $V^\mathcal{T}$  and  $O$  can be recast in terms of a matrix-valued process  $\mathbf{P}^\mathcal{T}$  that is determined from  $Y$  as follows, for  $k$  in  $\mathbb{N}$ :

$$\mathbf{P}^\mathcal{T}(k) := \mathbb{E} \left[ (V(k) - V^\mathcal{E}(k))^T (V(k) - V^\mathcal{E}(k)) \mid Y(1:k) \right] \quad (20)$$

where  $\mathbf{P}^\mathcal{T}(0)$  is predetermined.

There is a recursive time-update mechanism [79] for  $\mathbf{P}^\mathcal{T}$  that guarantees that it is an information state [83], which, as we discuss below, may be used to recast the underlying optimization as an MDP, subject to the following set of policies.

**Definition 13. ( $\mathbb{T}^c$  - Memoryless covariance-based transmission policy set)** *We use  $\mathbb{T}^c$  to denote the set of transmitters for which there is a map  $\mathcal{T}^u$  determining  $U$  according to  $\mathcal{T}^u : (P^\mathcal{T}(k-1), S^{\text{soc}}(k), S^A(k)) \mapsto U(k)$ .*

Now, consider the formulation in [79], in which, for each  $k$ ,  $\mathcal{T}$  selects  $X(k)$  equal to  $\hat{V}(k)$ , and  $U(k)$  is either zero (no transmission) or a pre-selected energy quantum, as opposed to allowing two or more energy levels. A transmitter that seeks to convey  $X(k) = \hat{V}(k)$  to the estimator is often labeled *smart sensor* to distinguish it from the scheme in [81], which attempts to forward the *unprocessed* measurements by setting  $X(k)$  equal to  $V^{\mathcal{S}}(k)$ . The following theorem establishing an important structural property for the estimator is a consequence of the analysis in [79, Section 2].

**Theorem 2.** *Assume that  $N$  and  $N^{\mathcal{S}}$  are Gaussian and that we seek to solve Problem 1 subject to the additional constraint that the transmitter is in  $\mathbb{T}^c$ . In this context, restricting the set of estimators to be of the form (18) incurs no loss of optimality.*

Consequently, Problem 1 becomes more tractable in exchange for the possible loss of optimality that results from restricting the transmitter structure to  $\mathbb{T}^c$ . Notably, Theorem 2 allowed the authors of [79] to show that there are coordinate-wise threshold transmission policies that are optimal among those in  $\mathbb{T}^c$ . In spite of these advantages, there is no known bound on the performance loss incurred by this method.

The authors of [80] investigated methods to determine optimal power selection policies when the probability of outage depends exponentially on the transmission power, which in their framework is allowed to vary among two or more levels. Notably, short of allowing for varying transmission power levels, the formulation of [80] is analogous to the one in [79]. Notwithstanding their similarities, the analysis in the former demonstrates why allowing the transmitter to select among multiple power levels complicates significantly the search and characterization of optimal policies. In order to contend with the complexity of the problem, work in [80] includes useful approximations and tractable methods. The analysis and framework in [84], which also examines a control problem, provides suboptimal policies and numerical methods to address the case in which Assumptions 1 and 2 are not satisfied.

Related work in [85], [86] extends [87] to the case in which information is sent from the sensor to the estimator across a noisy channel whose quality depends on an internal state and the transmission power. The research reported in these articles sought to solve Problem 1, in the absence of energy harvesting considerations, with respect to transmission policies that determine the transmission power  $U$  and the transmitted signal  $X$ , and for a cost that combines the transmission power and the estimation error.

Tight necessary and sufficient conditions for the existence of a transmission policy that stabilizes the estimation error in the second-moment sense have been recently determined in [88]. When adapted to our current formulation, assuming the finite-state EH model (Definition 7), the framework in [88] would consider memoryless policies that use the state of charge  $S^E(k)$  to decide, at each time  $k$ , whether a transmission should be attempted. More precisely, the probability that a transmission is requested at time  $k$  is a function of  $S^E(k)$  represented as  $\mathcal{L}^{\theta} : \mathbb{S}^E \rightarrow [0, 1]$ , which is denoted as  $\theta$  in [88]. In order to employ the stabilizability conditions of [88] in the current

context, we assume that a map  $\mathcal{L}^d : \mathbb{S}^E \rightarrow [0, 1]$  is given which represents the probability of outage at time  $k$  in terms of  $S^E(k)$  when a transmission is requested at time  $k$ . Consequently, the map  $\mathcal{L}^d$ , which is represented with  $d$  in [88], must account for the combined effect of the pre-selected policy that governs  $U(K)$  in terms of  $S^E(k)$  when a transmission is requested,  $\mathcal{W}^E$  and  $\mathcal{L}(W^E(k))$ , which quantifies the outage probability according to (14). Finally, we can restate [88, Theorem 3.1] in our context as follows.

**Theorem 3.** *Given  $\mathcal{L}^d$ , there is a stabilizing transmission-request policy  $\mathcal{L}^{\theta}$  if and only if the following inequality holds:*

$$\lambda^s \rho(A)^2 \leq 1 \quad (21)$$

where the nonnegative real constant  $\lambda^s$  is a function of  $\mathcal{L}^d$  and  $S^E$ .

In addition, it is stated in [88, Theorem 3.1] that it suffices to consider deterministic transmission-request policies and according to [88, Theorem 3.2] the search can be further narrowed to threshold policies when  $\mathcal{L}^{\theta}$  is non-increasing.

Notice that (21) is a generalization of (17) and the two conditions coincide when  $\mathcal{L}^d$  is constant and equal to  $p^{\text{outage}}$ .

## VI. SCHEDULING: QUEUEING SYSTEMS WITH TIME-VARYING PARAMETERS, AND WIRELESS ENERGY TRANSFER

The UDC model constitutes a natural framework for studying the scheduling problem in a wide range of applications. In this section, we consider two specific applications – queueing systems with time-varying parameters and wireless systems with devices powered by wireless energy transfer – and discuss how the UDC framework can be used to study interesting and challenging problems in these areas.

### A. Queueing systems with time varying parameters

There exists a large volume of literature on queueing systems with time-varying parameters, dating back to the studies by Conway and Maxwell [89], Jackson [90], Yadin and Naor [91], Gupta [92] and Harris [93], most of which focused on the state-dependent service rates. We refer a reader interested in a summary of earlier studies on queues with state-dependent parameters to [94] and references therein. Although many, if not most, of these studies can be carried out using the UDC framework or its variant, here we focus on a more recent development in this area.

The performance and management of humans has been the subject of many studies in the past, e.g., [95], [96], [97], [98]. Recently, with rapid advances in information and sensor technologies, human supervisory control (HSC) became an active research area [10], [99]. In HSC, human supervisors play a crucial role in the systems (e.g., supervisory control and data acquisition (SCADA)) and at times are required to process a large amount of information in a short period in order to make critical decisions (e.g., a possible imminent nuclear meltdown due to a malfunction of cooling system), potentially causing information overload. For this reason, there is a resurging interest in modeling and understanding the performance

of humans under widely varying settings. Although this is still an active research area, it is well documented that the performance of humans depends on many factors, including arousal and perceived workload [96], [98], [99], [100], [101]. For example, the well-known Yerkes-Dodson law suggests that moderate levels of arousal are beneficial, leading to the inverted-U model [95]. Moreover, the performance of a human for varying types of tasks (e.g., easy tasks vs. difficult tasks) changes differently as a function of the level of arousal [102].

Savla and Frazzoli proposed a dynamical queue approach to studying task management with human operators, using a differential system model [12]. The service time of a task is equal to the product of (i) its workload and (ii) the value of service time function, which depends on the utilization level of the human operator at the time of task assignment. The utilization level in their study is the continuous-time counterpart of the utilization ratio with forgetting factor defined in Section III-A. The service time function determines the service time per unit workload as a function of the utilization level.

Their key results include the following:

- SF1. Suppose that the service time function is convex and all tasks bring the same workload. Then, there is a maximally stabilizing task release policy that applies a threshold to the utilization level (Theorems III.1 and III.2 of [12]): when the human operator is idle at time  $t$ , the policy assigns a new task if and only if its utilization level at time  $t$  is less than or equal to some threshold.
- SF2. When tasks bring heterogeneous workloads, the maximum throughput that can be achieved does not decrease compared to the case with homogeneous workload of tasks (Theorem IV.1 of [12]). Thus, the heterogeneity of workload does not diminish the maximum throughput that can be achieved.

1) *UDC framework for a Utilization-Dependent Server*: To the best of our knowledge, the work of Savla and Frazzoli is the first to study the task scheduling problem for servers whose efficiency varies with an internal state that summarizes its (recent) utilization. Recently, Lin et al. [103], [104] extended this work by adopting the UDC framework. Here we briefly summarize the work. A more detailed treatment is provided in Section VII.

The authors of [103], [104] introduced an internal state of the server, which is modeled using a finite-state CMC and approximates the utilization ratio with forgetting factor. However, unlike in the model adopted in [12] where the service time depends only on the utilization level at the time of task assignment, the service rate of the server is not assumed fixed during the service time of a task; instead, it continues to change as the utilization level of the server evolves over time in accordance with a CMC. Their key findings include the following:

- LF1. Their study characterizes the maximum task arrival rate  $\lambda^*$ , for which there exists a stabilizing task scheduling policy (see Theorem 4 in Section VII). Moreover, the study provides a computationally efficient method for computing  $\lambda^*$ , by proving that this maximum task arrival

rate is equal to the maximum throughput we can achieve using a threshold policy on the utilization level.

- LF2. In addition, the study shows that there exists a task scheduling policy with simple structure which can stabilize the system for any task arrival rate smaller than  $\lambda^*$ . Specifically, a throughput-optimal task scheduling policy is a threshold policy (see Theorem 5 in Section VII); there exists some threshold  $\tau^*$  on the utilization level so that the policy assigns a new task to the server if and only if the queue is non-empty and the utilization level is below the threshold.
- LF3. Finally, for a fixed task arrival rate, the study proposes a method for finding a task scheduling policy that not only stabilizes the system, but also aims to minimize the proportion of time the server is requested to work on tasks, which the authors call the “utilization rate” of the policy. In particular, they demonstrate that the proposed method can produce a task scheduling policy whose utilization rate can be made arbitrarily close to the minimum utilization rate achievable subject to the stability constraint (see Theorems 6 and 7 in Section VII).

## B. Wireless energy transfer

Wireless energy transfer (WET) has emerged as a potential solution to powering small devices that have low-capacity batteries or cannot be easily recharged, e.g., Internet-of-Things (IoTs) devices [105], [106], [107], [108]. Since the devices need to collect sufficient energy before they can transmit and the transmission rate is a function of transmit power, a transmitter has to decide (i) when to harvest energy and (ii) when to transmit and what transmission rate it should use.

For example, the studies reported in [109], [110], [111] examined the problem of maximizing throughput in wireless networks in which communication devices are powered by hybrid access points (H-APs) via WET. In a related study, Shanet al. [112] studied the problem of minimizing the total transmission delay or completion time of a given set of packets. In [113], Rezaei et al. investigated how to maximize the sum secrecy throughput among devices wirelessly powered by a base station and how to achieve max-min fair or proportionally fair secrecy throughput.

In spite of recent efforts, there are many interesting open problems. For example, what are the packet arrival rates at the devices powered by WET for which we can find a scheduling policy that stabilizes the queues at the devices, subject to an energy expenditure rate or average power constraint, while capturing the battery discharge curve explained in Section III-B? Another related question is: how do we minimize the energy expenditure rate at an H-AP or a base station, while maintaining stable queues at the wireless devices and honoring (average) packet delay requirements?

Here, we describe a model based on the UDC framework, which can be employed to study these problems. For the simplicity of illustration, we focus on a scenario where two devices are powered by a single H-AP and communicate on the uplink to the H-AP, and packets of fixed-size  $K$  arrive at the devices according to two independent Bernoulli processes with parameters  $\lambda = (\lambda_0, \lambda_1)$ .

1) *UDC framework for WET*: Let  $S^{soc} := \{S^{soc}(k) : k \in \mathbb{N}\}$ , where  $S^{soc}(k) = (S_0^{soc}(k), S_1^{soc}(k)) \in \mathbb{S}^{soc2}$ ,  $S_i^{soc}(k)$  represents the battery SOC of device  $i$  at time  $k$ , and  $\mathbb{S}^{soc}$  is the set of possible SOC (defined in Section III-B). Similarly,  $Q = \{Q(k) : k \in \mathbb{N}\}$ , where  $Q(k) = (Q_0(k), Q_1(k)) \in \mathbb{N}^2$  and  $Q_i(k)$  is the number of backlogged bytes in the queue of device  $i$ . The packets of size  $K$  can be segmented for transmission on the uplink from the devices to the H-AP.

A scheduling policy is described by a mapping  $\theta : \mathbb{S}^{soc2} \times \mathbb{N}^2 \rightarrow \{H, 0, 1\} \times \mathbb{T}_{HAP} \times \mathbb{T}_D$ , where  $\mathbb{T}_{HAP}$  and  $\mathbb{T}_D$  are the set of admissible transmit powers for the H-AP and the devices, respectively, with associated modulation and coding schemes. For a given pair  $(s^{soc}, \mathbf{q}) \in \mathbb{S}^{soc2} \times \mathbb{N}^2$ ,  $\theta_1(s^{soc}, \mathbf{q}) \in \{H, 0, 1\}$  indicates who will transmit, and  $\theta_2(s^{soc}, \mathbf{q}) \in \mathbb{T}_{HAP}$  and  $\theta_3(s^{soc}, \mathbf{q}) \in \mathbb{T}_D$  represent the selected transmit power:  $\theta_1(s^{soc}, \mathbf{q}) = H$  means that the H-AP charges the devices using transmit power  $\theta_2(s^{soc}, \mathbf{q})$ . On the other hand,  $\theta_1(s^{soc}, \mathbf{q}) = i$  ( $i = 0, 1$ ) informs device  $i$  to transmit on the uplink using transmit power  $\theta_3(s^{soc}, \mathbf{q})$ .

When the H-AP transmits with power  $p_H \in \mathbb{T}_{HAP}$ , device  $i$  receives energy at the rate  $h_i \cdot p_H$  (per scheduling block duration), where  $h_i$  is the transfer gain. The scenario in which the amount of transferred power is governed by a stochastic process can be handled analogously. In addition, when device  $i$  is asked to transmit at power  $p_D$ , it transmits  $g_i(p_D)$  bytes with transmit power  $\xi(p_D, s_i^{soc})$ , where  $s_i^{soc}$  is the SOC of device  $i$  at the time. Here,  $\xi(p_D, s_i^{soc})$  models the power that can be delivered by the battery as a function of requested power and its SOC. The probability that the transmission from device  $i$  will be unsuccessful is determined by an error function  $e_i(g_i(p_D), \xi(p_D, s_i^{soc}))$ .

Let  $U = \{U(k) : k \in \mathbb{N}\}$ , where  $U(k)$  is the scheduling decision at time  $k$ . The performance process is given by  $W = \{W(k) : k \in \mathbb{N}\}$ , where  $W(k) = 1 - e_i(g_i(p_D), \xi(p_D, s_i^{soc}))$  if  $U(k) = (i, \cdot, p_D)$  with  $i \in \{0, 1\}$ , and  $W(k) = 0$  if  $U_1(k) = H$ . The output process of the UDC action kernel is  $Y = \{Y(k) : k \in \mathbb{N}\}$  with  $Y(k) \sim \text{Bernoulli}(W(k))$ .

The SOC and queue size of device  $i$  ( $i = 0, 1$ ) evolve as follows:

$$\begin{aligned} S_i^{soc}(k+1) &= \begin{cases} S_i^{soc}(k) - \xi(U_3(k), S_i^{soc}(k)) & \text{if } U_1(k) = i \\ S_i^{soc}(k) + h_i \cdot U_2(k) & \text{if } U_1(k) = H \\ S_i^{soc}(k) & \text{if } U_1(k) = 1 - i \end{cases} \end{aligned} \quad (22)$$

and

$$Q_i(k+1) = Q_i(k) + K \cdot B_i(k) - \tilde{Y}_i(k)$$

where  $B_i(k) \sim \text{Bernoulli}(\lambda_i)$  and indicates whether or not there is a new packet arrival at device  $i$  at time  $k$ , and  $\tilde{Y}_i(k)$  is the number of bytes successfully transmitted from device  $i$  to the H-AP at time  $k$  and is given by

$$\tilde{Y}_i(k) = \begin{cases} g_i(U_3(k))Y(k) & \text{if } U_1(k) = i, \\ 0 & \text{otherwise.} \end{cases}$$

Here, we do not consider battery charge leakage, which may be an issue with cheap low-power remote sensing devices or IoT devices. However, this can be handled by modifying equation

(22). For more details on battery charge leakage, we refer to Section VIII-G.

**Remark 4.** We note that the problem of designing a scheduling policy that can stabilize the queues at the wireless devices subject to constraints is similar to the problem investigated by Lin et al. in [103]. Moreover, finding a scheduling policy that minimizes the energy expenditure rate at the H-AP is closely related to the problem of minimizing the utilization rate with utilization-dependent server, which is studied in [104] using the UDC framework. For these reasons, we expect that the UDC framework and tools used by Lin et al. in [103], [104] will prove to be instrumental to studying the wireless systems with WET. We refer a reader interested in more detail to Section VII.

As discussed in Sections IV and V (more specifically Section V-A), there is already extensive literature on wireless systems with energy harvesting, including many studies that adopt an MDP formulation. For example, Kashef and Ephremides [114] studied the problem of maximizing the average number of successfully transmitted packets over a time-varying channel by a wireless device with EH. In their study, the channel state is modeled using a simple two-state time-homogeneous Markov chain (so-called Gilbert-Elliot model), and they derived structural properties of optimal policies. In [115], Mao et al. examined a similar problem of maximizing the average amount of successfully transmitted data over the course of a sensor life, where the sensor life is modeled using a geometric random variable. They proposed an optimal energy allocation algorithm using the value iteration. Ahmed et al. [116] investigated the problem of maximizing the data arrival rate that can handled by the system, subject to delay constraints, where data arrive with a fixed constant rate at each time. They considered two different delay constraints – average and statistical delay constraints – provided some structural properties of optimal policies and an online algorithm.

Even though these studies are closely related to those in WET in that, in both cases, device batteries need recharging through either EH or WET, and adopt a similar MDP formulation, there is also a key difference between them. In the literature with EH, energy is often assumed to arrive according to a deterministic process or a random process, which is beyond the control of decision makers. On the other hand, in the problem of WET, the energy delivery via WET is a part of decision making process. Thus, the scheduling policy must carry out a suitable trade-off between recharging device batteries and scheduling data/packet transmissions in accordance with the objective of the designer.

## VII. MOTIVATING EXAMPLE: A SINGLE SERVER WITH UTILIZATION-DEPENDENT SERVICE RATE

In many cases of interest, the instantaneous performance or service rate of a server depends on their (recent) utilization. For example, as mentioned before, the efficiency of human operators is not constant and varies with several factors, such as arousal and fatigue [95], [101]. Thus, in many applications with human operators making critical decisions (e.g., air traffic

control and nuclear plant monitoring), it is important to take into account their alertness and (instantaneous) efficiency, in order to improve the performance of overall systems. The setting in which the service rate of a server varies as a function of its recent utilization has been studied by Savla and Frazzoli in [12], using a continuous-time differential system model, and their main findings are summarized in Section VI-A.

In this section, we use the recent work by Lin et al. [103], [104] on a single server system to illustrate how the UDC framework was successfully used to facilitate the study of a similar system and help them extend the results in [12]. In particular, the UDC framework is leveraged to expedite the computation of the maximum average task completion rate or throughput that can be achieved by any stationary task scheduling policy (TSP) and to design effective TSPs [103], [104].

To this end, they examine following two problems: in the first problem, they are interested in designing a simple TSP that can stabilize the queue for any task arrival rate for which there exists a stabilizing TSP. In the second problem, given a fixed task arrival rate, they aim to devise a TSP that not only stabilizes the queue, but also minimizes the long-term proportion of time the server is requested to work on tasks.

#### A. Setup: a UDC model

Consider a queueing system with a single server and an infinite first-in-first-out queue. The server is assumed non-preemptive; once it starts servicing a task, it continues until the task is completed before taking on a new task or resting.

New tasks arrive according to a Bernoulli process  $B := \{B(k) : k \in \mathbb{N}\}$  with parameter  $\lambda \in (0, 1]$ :  $B(k) = 1$  if there is a new task arrival at time  $k$ , the probability of which is equal to  $\lambda$ , and  $B(k) = 0$  otherwise. The Bernoulli random variables  $B(k)$ ,  $k \in \mathbb{N}$ , are mutually independent. Although Bernoulli arrivals are assumed to simplify our discussion, more general arrival distributions (e.g., Poisson distributions) can be handled with appropriate changes.

A new task that arrives at time  $k$  becomes eligible for service, beginning at time  $k + 1$ , and is put in the queue until the server is ready to service it. Each new task brings a (random) workload, which is the amount of service that the server needs to provide in order to complete the task. They make a simplifying assumption that the workloads of tasks are modeled using independent and identically distributed exponential random variables. Thus, the residual workload of a task that is currently being serviced has the same distribution as the workload of a queued task waiting for service.

The control input at time  $k$ , namely  $U(k)$ , is the scheduling decision chosen by the employed TSP:  $U(k) = 1$  means that the scheduler requests the server to work on a task at time  $k$ , and  $U(k) = 0$  otherwise, i.e., the server rests at time  $k$ . The control input process  $\{U(k) : k \in \mathbb{N}\}$  determines the evolution of the server utilization over time, which in turn affects its instantaneous and long-term performance in the manner explained below.

Let  $S^u := \{S^u(k) : k \in \mathbb{N}\}$  be the process that tracks the utilization level of the server. For instance,  $S^u(k)$  could




Fig. 3. The UDC framework for the study by Lin et al. in [103], [104].

represent the utilization ratio or the utilization ratio with forgetting factor  $\alpha$  of the server (provided in Definitions 2 and 3 of Section III-A). In [103], [104], the authors model  $S^u$  using a CMC taking values in a finite set  $\mathbb{S}^u := \{1, 2, \dots, s_{\max}\}$ . The dynamics of  $S^u$  will be explained shortly.

The instantaneous performance or efficiency of the server at time  $k$  depends on its current utilization level  $S^u(k)$ . This is modeled using a service rate function  $\mu^u : \mathbb{S}^u \rightarrow (0, 1)$ , where  $\mu^u(s^u)$  is the probability that the server will complete a task within a unit time. The memoryless property of an exponential distribution assumed for task workloads implies that this probability does not depend on the amount of service that a task in service received in the past.

The transition probabilities of the utilization level  $S^u(k) = s^u$  at time  $k$  depend on (i) the current value of utilization,  $s^u$ , and (ii) the control input  $U(k)$ , and are governed by the following mapping:

$$S^u(\bar{s}^u | s^u, a) := \mathcal{P}(S^u(k+1) = \bar{s}^u | S^u(k) = s^u, U(k) = a) = \begin{cases} \eta_{s^u}^+ & \text{if } a = 1, \bar{s}^u = \min(s_{\max}, s^u + 1) \\ 1 - \eta_{s^u}^+ & \text{if } a = 1, \bar{s}^u = s^u \\ \eta_{s^u}^- & \text{if } a = 0, \bar{s}^u = \max(1, s^u - 1) \\ 1 - \eta_{s^u}^- & \text{if } a = 0, \bar{s}^u = s^u \end{cases}$$

It is clear from the given transition probabilities that if the server works on a task (resp. rests) at time  $k$ , the utilization level either remains at  $s^u$  with probability  $1 - \eta_{s^u}^+$  (resp.  $1 - \eta_{s^u}^-$ ) or goes up by one with probability  $\eta_{s^u}^+$  if  $s^u < s_{\max}$  (resp. goes down by one with probability  $\eta_{s^u}^-$  if  $s^u > 1$ ) with the convention  $\eta_1^- = \eta_{s_{\max}}^+ = 0$ .

The overall system dynamics are described by a CMC  $S^U = \{(S^u(k), S^a(k), Q(k)) : k \in \mathbb{N}\}$ , where  $Q(k)$  is the number of backlogged tasks in the queue at time  $k$ , and  $S^a(k)$  indicates the availability of the server to take on a new task. In other words,  $S^a(k) = 1$  if the server is available to service a new task at time  $k$  (either after completing a task or resting at time  $k - 1$ ), and  $S^a(k) = 0$  otherwise. The CMC  $S^U$  takes values in the state space of the system, which is given by  $\mathbb{S}^U := \mathbb{S}^u \times ((\{0, 1\} \times \mathbb{N}) \setminus \{0, 0\})$ .

In [103], [104], they consider the following class of stationary TSPs that map the current state of CMC,  $S^U(k)$ , to the probability of scheduling a task at each time  $k$  in  $\mathbb{N}$ .

**Definition 14.** An *admissible stationary randomized TSP (SRTSP)* is a mapping  $\theta : \mathbb{S}^U \rightarrow [0, 1]$  such that (i) for all  $(s^u, s^a, q) \in \mathbb{S}^U$ ,  $\theta(s^u, s^a, q)$  is the probability that the server is asked to work on a task when the CMC state is  $(s^u, s^a, q)$ , and (ii)  $\theta(s^u, 0, q) = 1$  for all  $q > 0$  and  $s^u \in \mathbb{S}^u$ .

Obviously, the second requirement reflects the assumption that the server is non-preemptive. Also, under a fixed SRTSP  $\theta$ , the CMC  $S^U$  is a discrete-time Markov chain with a countable state space.

**Threshold scheduling policies:** In practice, oftentimes a simple TSP is preferred as long as it does not cause a significant degradation in performance. One class of simple TSPs that are of interest is the set of threshold TSPs: fix a threshold  $\tau \in \mathbb{S}_+^u := \{1, \dots, s_{\max} + 1\}$ . A threshold (task scheduling) policy with threshold  $\tau$  is a deterministic TSP given by a mapping  $\theta_\tau : \mathbb{S}^U \rightarrow \{0, 1\}$ , where

$$\theta_\tau(s^u, s^a, q) := \begin{cases} 0 & \text{if (i) } s^u \geq \tau \text{ and } s^a = 1 \\ & \text{or (ii) } q = 0, \\ 1 & \text{otherwise.} \end{cases} \quad (23)$$

Clearly, when the server is available to service a new task, the threshold policy  $\theta_\tau$  assigns a new task if and only if the queue is non-empty and the utilization level is less than the threshold  $\tau$ . Threshold policies are easy to implement in practice and require little information for making scheduling decisions.

When studying a queueing system, one of the most important properties of interest is its stability; an unstable system will lead to poor performance in terms of the average number of completed tasks per unit time or the (mean) sojourn times experienced by tasks. For the study, they adopt the following notion of stability.

**Definition 15.** For a fixed task arrival rate  $\lambda > 0$ , the CMC  $S^U$  under a chosen SRTSP  $\theta$ , denoted by  $S_\theta^U$ , is said to be *stable* if

- 1) there exists at least one recurrent communicating class of  $S_\theta^U$ ;
- 2) all recurrent communicating classes are positive recurrent; and
- 3) the number of transient states is finite.

In addition,  $\theta$  is said to *stabilize* the CMC  $S^U$  for the given task arrival rate  $\lambda$ .

It is shown in [103, Lemma 1] that if  $S_\theta^U$  is stable under some SRTSP  $\theta$ , there is a unique aperiodic, positive recurrent communicating class. As a result, we can find a unique stationary distribution of  $S_\theta^U$ .

### B. Throughput-optimal task scheduling policies

As stated earlier, the stability of a system is a fundamental property of a queueing system of interest. Therefore, a natural question that arises is: *how can we design an effective TSP that stabilizes the system whenever it is possible to do so, when the instantaneous performance of the server is affected by the very scheduling decisions it has made in the past?*

1) *Reduced process:* In order to find an answer to this question, Lin et al. investigated the problem of designing a throughput-optimal TSP that stabilizes  $S^U$  for any arrival rate  $\lambda$  for which there exists a stabilizing TSP [103]. To this end, they first study a system in which there are infinitely many backlogged tasks at the beginning, i.e.,  $Q(0) = \infty$ . In this system, there is always a task waiting for service in the queue when the server becomes available.

Consider the process  $\tilde{S}^U = ((S^u(k), S^a(k)) : k \in \mathbb{N})$  that describes the utilization level and availability of the server. It turns out that this reduced process  $\tilde{S}^U$  plays a critical role in their studies. For example, when a threshold policy  $\theta_\tau$  is adopted with some threshold  $\tau > 1$ , the resulting CMC  $\tilde{S}^U$  can be modeled using a finite-state Markov chain with a unique stationary distribution  $\tilde{\pi}_\tau$  concentrated on the set

$$\tilde{\mathbb{S}}_\tau := \{(s^u, s^a) | s^u \in \{\tau - 1, \dots, s_{\max}\}, s^a \in \{0, 1\}\}.$$

As detailed in [104] and summarized below, this approach allows them to transform the problem of designing a throughput-optimal TSP for  $S^U$  to a more manageable MDP with a finite state space: the problem becomes one of finding a TSP for the reduced process  $\tilde{S}^U$  which maximizes the task completion rate of  $\tilde{S}^U$ . To tackle this problem, they leverage many well known results in the MDP literature, some of which are explained in Section VII-D.

Define

$$\lambda^* := \max_{\tau \in \mathbb{S}_+^u} \left( \sum_{(s^u, s^a) \in \tilde{\mathbb{S}}_\tau} \tilde{\pi}_\tau(s^u, s^a) \theta_\tau(s^u, s^a, 1) \mu^u(s^u) \right). \quad (24)$$

Note that  $\lambda^*$  is the maximum average task completion rate among all threshold policies of the form in (23) when the queue is never empty. Let  $\tau^*$  be a maximizer of the right-hand side of (24).

Clearly, threshold policies of the form in (23) constitute a small subset of the family of SRTSPs. Hence, without any additional assumptions, for instance, on the service rate function  $\mu^u$  as done in [12], one may suspect that we can find an SRTSP that achieves a higher average task completion rate than  $\lambda^*$  and such an SRTSP will likely be able to stabilize the system for a task arrival rate larger than  $\lambda^*$ .

Somewhat surprisingly, this is not the case and  $\lambda^*$ , which can be computed efficiently by solving the optimization in (24) over a finite set, serves as an upper bound on the task arrival rate for which we can find a stabilizing SRTSP. This is formally stated by the following theorem.

**Theorem 4.** Suppose that there exists a stabilizing SRTSP for some task arrival rate  $\lambda > 0$ . Then,  $\lambda \leq \lambda^*$ .

From the definition of  $\lambda^*$  in (24), it is reasonable to expect that when the task arrival rate  $\lambda$  is smaller than  $\lambda^*$ , we should be able to find a threshold policy that can stabilize the system, with  $\theta_{\tau^*}$  being a natural candidate. This is illustrated by the next theorem.

**Theorem 5.** Suppose that the task arrival rate satisfies  $\lambda < \lambda^*$ . Then, the CMC  $S^U$  under the deterministic threshold policy  $\theta_{\tau^*}$  is stable.

An important implication of Theorems 4 and 5 is that there is a throughput-optimal threshold TSP we can find efficiently.

### C. Utilization rate minimizing task scheduling policies

In some cases, in addition to keeping the system stable, it may be desirable to minimize the proportion of time a server is required to work. For instance, in the case of battery-powered wireless sensors sustained by renewable energy or WET, we may wish to minimize the number of wireless transmissions over a long period, while keeping the queue stable (assuming that the measurements are not delay-sensitive). Similarly, when dealing with human operators, it may be of interest to minimize the amount of time a human operator is required to work on tasks.

In a complementary study to [103], Lin et al. investigated the problem of designing a TSP that minimizes the utilization rate of the server, which is defined to be the long-term proportion of time the server works on tasks. This problem is considerably more challenging than the first problem as the design requires maintaining system stability, while trying to minimize the utilization rate.

For a given task arrival rate  $\lambda \in (0, \lambda^*)$ , let  $\Theta(\lambda)$  be the set of stabilizing SRTSPs for  $S^U$ . Recall that, if a TSP  $\theta$  stabilizes  $S^U$ , there is a unique stationary distribution of  $S_\theta^U$ , which we denote by  $\pi^\theta$ . The corresponding utilization rate of the server in  $S_\theta^U$  is equal to

$$\mathcal{U}(\lambda; \theta) := \sum_{s \in \mathbb{S}^U} \pi^\theta(s) \theta(s).$$

There are two questions of interest. First, given a task arrival rate  $\lambda$  in  $(0, \lambda^*)$ , what is the minimum utilization rate we can achieve using a stabilizing TSP? Denote this minimum utilization rate by

$$\mathcal{U}^*(\lambda) := \inf \{ \mathcal{U}(\lambda; \theta) \mid \theta \in \Theta(\lambda) \}.$$

Second, how do we find a stabilizing TSP that achieves a utilization rate arbitrarily close to  $\mathcal{U}^*(\lambda)$ ? In other words, given any constant  $\delta > 0$ , can we systematically find a stabilizing TSP  $\theta^*$  such that  $\mathcal{U}(\lambda; \theta^*) \leq \mathcal{U}^*(\lambda) + \delta$ ?

The authors of [104] once again turned to the reduced process  $\tilde{S}^U$  for answers: consider the problem of designing a TSP that makes a decision on the basis of the utilization level and the availability of the server, assuming that the queue is always non-empty (which is true when  $Q(0) = \infty$ ). Such a TSP is given by a mapping  $\phi : \tilde{\mathbb{S}}^U \rightarrow [0, 1]$ , where  $\tilde{\mathbb{S}}^U := \mathbb{S}^u \times \{0, 1\}$ . As before,  $\phi(s^u, s^a)$  represents the probability with which the scheduler requests the server to work on a task. We denote the CMC  $\tilde{S}^U$  under a TSP  $\phi$  by  $\tilde{S}_\phi^U$ .

They showed that, for every TSP  $\phi$  satisfying  $\phi(1, 1) > 0$ , there is a unique stationary distribution of  $\tilde{S}_\phi^U$ . Denote this unique stationary distribution by  $\tilde{\pi}^\phi$ .<sup>5</sup> Define  $\Phi_+$  to be the set

<sup>5</sup>For a TSP  $\phi$  with  $\phi(1, 1) = 0$ , there are two positive recurrent communicating classes of  $\tilde{S}_\phi^U$  with one positive recurrent communicating class being  $\{(1, 1)\}$ .

of TSPs  $\phi$  satisfying  $\phi(1, 1) > 0$ . The utilization rate of  $\phi$  in  $\Phi_+$  is given by

$$\bar{\mathcal{U}}_\phi = \sum_{(s^u, s^a) \in \tilde{\mathbb{S}}^U} (\phi(s^u, s^a) \tilde{\pi}^\phi(s^u, s^a)),$$

and the average task completion rate is equal to

$$\bar{\nu}_\phi = \sum_{(s^u, s^a) \in \tilde{\mathbb{S}}^U} (\phi(s^u, s^a) \tilde{\pi}^\phi(s^u, s^a) \mu^u(s^u)).$$

Let  $\Phi_+(\lambda) := \{\phi \in \Phi_+ \mid \bar{\nu}_\phi = \lambda\}$ .

**Theorem 6.** We have  $\mathcal{U}^*(\lambda) = \bar{\mathcal{U}}_+(\lambda)$ , where

$$\bar{\mathcal{U}}_+(\lambda) := \inf \{ \bar{\mathcal{U}}_\phi \mid \phi \in \Phi_+(\lambda) \}.$$

Although Theorem 6 reveals an interesting relation and a potential means of computing  $\mathcal{U}^*(\lambda)$ , it does not explicitly tell us how to find an SRTSP that can achieve a utilization rate close to  $\mathcal{U}^*(\lambda)$ . The following theorem sheds some light on this issue.

**Theorem 7.** Fix a task arrival rate  $\lambda$  in  $(0, \lambda^*)$  and positive  $\delta$ . (i) We can find a pair  $(\bar{\nu}^{(\lambda, \delta)}, \epsilon^{(\lambda, \delta)})$ , where  $\bar{\nu}^{(\lambda, \delta)} \in (\lambda, \lambda^*)$  and  $\epsilon^{(\lambda, \delta)} \in (0, 1]$  such that

$$\Phi_\epsilon(\bar{\nu}^{(\lambda, \delta)}) := \{ \phi \in \Phi_+(\bar{\nu}^{(\lambda, \delta)}) \mid \phi(1, 1) \geq \epsilon^{(\lambda, \delta)} \}$$

is non-empty. (ii) Suppose  $\phi^* \in \Phi_\epsilon(\bar{\nu}^{(\lambda, \delta)})$ . Then, an SRTSP  $\theta^*$  with

$$\theta^*(s^u, s^a, q) = \begin{cases} \phi^*(s^u, s^a) & \text{if } q > 0 \\ 0 & \text{otherwise} \end{cases}$$

belongs to  $\Theta(\lambda)$ , and  $\mathcal{U}(\lambda, \theta^*) \leq \mathcal{U}^*(\lambda) + \delta$ .

Theorem 7 indicates that if we find a policy in  $\Phi_\epsilon(\bar{\nu}^{(\lambda, \delta)})$ , we can construct a stabilizing SRTSP whose utilization rate lies within  $\delta$  of  $\mathcal{U}^*(\lambda)$ . Hence, we can get arbitrarily close to  $\mathcal{U}^*(\lambda)$  by reducing  $\delta$ . Furthermore, they demonstrated in [104] that the problem of finding a policy in  $\Phi_\epsilon(\bar{\nu}^{(\lambda, \delta)})$  can be formulated as a simple linear optimization problem. Therefore, their study offers a systematic way of constructing a suitable stabilizing SRTSP whose utilization rate can be made arbitrarily close to the minimum utilization rate.

### D. Discussion

In this section, we first discuss the key differences between the studies by Lin et al. [103], [104] and that of Salva and Frazzoli [12]. Then, we outline how the UDC framework was vital in obtaining the new results in [103], [104].

1) *Key differences between the studies by Savla and Frazzoli [12] and by Lin et al. [103], [104]:* There are two key differences between these two studies. First, the authors of [12] assume that the service time function is convex, which is analogous to the service rate function  $\mu^u$  being unimodal [103], [104]. But, Lin et al. do not impose any assumptions on the service rate function. In particular,  $\mu^u$  is not assumed to be monotonic or unimodal and can be an arbitrary function taking values in  $(0, 1)$ . Moreover, the model in [12] assumes that the server efficiency during the service time of a task depends only on the value of the service time function at the

time the task was assigned to the server and is fixed during the service time of the task. In contrast, the model employed in [103], [104] allows the server efficiency captured by the service rate function to evolve while the server works on a task.

Relaxing the assumptions introduced in [12] and allowing a general service rate function is important to optimizing the performance of servers with time-varying service rates, such as human operators, whose performance is shown to be non-monotonic in arousal or fatigue and its dependence on arousal varies with the difficulty level or types of tasks, e.g., its performance tends to be monotonically increasing in arousal for easy tasks, whereas it is not the case for difficult tasks.

Second, in [12], a threshold policy is proved to be maximally stabilizing only for the case with identical task workload. In the study by Lin et al., however, the workloads of tasks are modeled using i.i.d. random variables. Although they assume an exponential distribution for the workload to facilitate the analysis, similar results can be obtained with more general workload distributions with appropriate changes to their model.

In addition to these key differences, there is another important aspect of the results by Lin et al. which should be emphasized. Even though the results of [12] are interesting, unfortunately they do not shed much light on a key practical question: *how do we identify a throughput-optimal policy in a computationally efficient manner?* In contrast, the study by Lin et al. offers a systematic, computationally efficient method of finding a throughput-optimal policy.

#### 2) Integral role of the UDC framework in [103], [104]:

It is noteworthy that the answers to several key questions by Lin et al. are obtained by relating the original problems to an MDP on a reduced, finite state space. This greatly simplifies their analysis and, more importantly, enables them to leverage an extensive set of tools available for (constrained) MDPs.

First, finding a throughput-optimal TSP in the UDC framework becomes straightforward; an optimal threshold  $\tau^*$  can be computed as a solution to the optimization problem in (24) by searching through the finite set  $\mathbb{S}^{u+}$  with  $s_{\max} + 1$  elements. Note that, for each  $\tau$  in  $\mathbb{S}_+^u$ , the stationary distribution  $\tilde{\pi}_\tau$  has a finite support  $\tilde{\mathbb{S}}_\tau$  and can be computed efficiently as explained in [103].

Second, the proofs of Theorems 4 through 7 rely heavily on the tools available for MDPs. For example, a well-known result for constrained MDPs [117, Theorem 4.4] states that, for a constrained MDP, there is an optimal policy that requires at most  $n_C$  randomizations, where  $n_C$  is the number of constraints in the corresponding constrained optimization problem. Lin et al. formulate the problem of designing a throughput-optimal TSP as an unconstrained MDP. Thus, they can infer from Theorem 4.4 of [117] that there is an optimal deterministic TSP (which is not necessarily a threshold TSP).<sup>6</sup>

<sup>6</sup>Although it is not discussed in this article to keep our discussion limited to single-queue scenarios, this observation plays an even more important role in an extension of their work, where they consider multiple types of tasks. The problem of designing a stabilizing policy with, for example, two types of tasks can be viewed as one of maximizing the throughput of one type of tasks subject to a constraint on the throughput for the other type.

In addition, the proof of Theorem 7 requires computing an optimal policy for the MDP with a finite state space, which achieves the minimum utilization rate among the policies in  $\Phi_\epsilon(\nu)$  for some  $\nu$  in  $(\lambda, \lambda^*)$ . As this is an MDP on a finite state space, they are able to formulate an appropriate linear optimization problem, the solution of which can be obtained efficiently and is used to construct an optimal policy that they seek.

Third, we explain how the UDC framework was central in bringing the synergy from two different research fields in findings answers to their questions. Identifying near-optimal TSPs for the problem of minimizing the utilization rate demands expertise from optimization, queueing theory and stochastic control; finding such near-optimal TSPs calls for many structural results needed to prove the main findings on stability. Their proofs borrow advanced tools from stochastic processes. These structural results are crucial to identifying optimal policies for MDPs on the reduced state space via a linear optimization problem, which are then used to construct near-optimal policies for the problem. Therefore, the UDC framework is indispensable to carrying out the study at the intersection of these areas and obtaining the results. Finally, we point out that the problem studied in [88] by the same authors, was in part motivated by the UDC framework and, as a result, shares a similar methodology.

## VIII. CONCLUSIONS AND FUTURE DIRECTIONS

Our overview of the concepts, formulations, and methods utilized on the research themes expounded in Sections IV - V evinces not only the similarities elicited by the presence of a UDC, but it also unveils a clear distinction among the objectives, techniques and assumptions adopted in each theme. This disconnection creates new research opportunities and challenges that would benefit from the fusion of the techniques and approaches that hitherto have been routinely employed by the information theory, wireless communication, operations research, networking and control theory communities. Notably, we concluded that the research challenges described in Sections VIII-A-VIII-C are currently not fully addressed, and constitute significant opportunities for future work that would also lead to methods for tackling problems specified by more realistic models and assumptions. Subsequently, in Sections VIII-D - VIII-G, we proceed with suggesting additional future research directions that broach aspects of security and secrecy, effective methods to cope with systems comprising multiple UDCs, UDC in learning and more realistic battery models, respectively.

### A. Noisy channels for remote estimation

Most work discussed in Section V presumes that, in the absence of an outage, an EH packet-drop link can convey a real vector unerringly from the sensor to the estimator when a transmission is requested. Future progress on new causal encoding and decoding schemes, possibly inspired on modifications of those discussed in Section IV, may lead to effective methods to tackle the unidealized case in which a noisy channel links the sensor to the estimator. Introducing



channel encoding and decoding, and possibly lossy source compression, as was done in [118] for an independent Gaussian source would expand the set of policies to include high and low fidelity solutions whose implementation may consume more or less energy [119], respectively, in addition to that required for transmission. Obtaining methods for the design of such policies with stability and performance guarantees is, therefore, an important open challenge.

The case in which the UDC would depend not only on the energy available but also on the state of a physical system, such as the position and velocity vectors of a mobile agent, would be an interesting extension of this framework. In this setting, the UDC could be a communication channel between the agent and a base station whose outage likelihood would increase with distance for each transmission power level. The scenario in which the UDC would be a global positioning module (GPS) whose accuracy would depend on the location and power level, with higher fidelity consuming more power, would be an example relevant to autonomous navigation [120] of unmanned assets. In these cases, one needs to consider policies that not only allocate power for the UDC but also govern the control action that steers the agent. As is discussed in [121], many active sensing problems could be formulated similarly once energy harvesting constraints are included.

#### B. Queueing, remote estimation and age of information

According to the optimality principle used in [64], for the framework adopted in Section V-C, if a sensor has access to the state  $V$  or is able to compute the optimal state estimate  $\hat{V}$  - cases we refer to as *full-information* sensor or *smart sensor*, respectively - then it should always attempt to transmit the latest one to the remote estimator. Hence, given a choice, it is optimal to discard state estimates corresponding to failed transmission attempts in favor of the most recent one - a principle we term as *most-recent-only optimality*<sup>7</sup>. In fact, this most-recent-only optimality principle for a full-information/smart sensor remains valid even in the controlled transmission setting described in Section V-E. Hence, these observations suggest that introducing a packet management layer, such as establishing a queue, prior to transmission is not necessary and may even be counterproductive when the sensor is full-state/smart.

However, when using an existing transmission system one may be left with no option but to deal with a pre-existing first-in-first-out queue-based non-preemptive management system in which a packet leaves the queue only when it is successfully conveyed to the remote estimator. Notably, as is proved in [123], [124] for the aforementioned scenario, for the case in which the source is a Wiener or Ornstein-Uhlenbeck process and the sensor is full-state, it is never optimal to submit a measurement for transmission when the queue is non-empty, and when a new measurement is inserted in the empty queue for transmission it must be the current state of the process, which can be viewed as a version of the *most-recent-only optimality* principle for the case when pre-emption is not allowed.

Interestingly, the optimal rule proposed in [124] to determine whether to submit the latest measurement for transmission, subject to the queue being empty, follows an event-based threshold policy that is analogous to the one found to be optimal for the closely-related case analyzed in [87]<sup>8</sup>. The fact that the most-recent-only optimality principle may no longer hold when the sensor is neither full-state nor smart [81] raises the question of whether, if the sensor in the framework of [124] could transmit only noisy output measurements  $V^{\mathcal{T}}$ , there would be optimal policies for which a transmission would be scheduled even when the queue is non-empty. Furthermore, if the queue is served by a channel powered by energy harvested from stochastic sources then we are left with the currently unsolved problem of designing policies that determine not only when and which estimates or measurements should be placed in the queue for transmission but also allocate the energy used for each transmission attempt. A typical approach would be to characterize stabilizing policies first, perhaps within an appropriately parametrized class, followed by the characterization of structural properties that could facilitate the computation of optimal policies using tractable methods. The stability problem may require the integration of techniques such as the ones used in [103] and [88], which were discussed in Sections VI and V in the context of queueing and remote estimation, respectively. Devising methods to design optimal policies may involve fusing the techniques adopted in Section V-E and [123], [124], and possibly leveraging the fact that our UDC model is amenable to existing methodologies [83], [78] for POCMCs. Since the fidelity of the estimate constructed at the remote estimator depends on the recency of the information received by the remote estimator, both the stability and the optimization problems are related to recent work seeking to analyze and design data-transmission systems that effectively regulate the age of information [125], [126]. In fact, it has been suggested in [127], [128] that the remote estimation and age of information problems are inextricably tied.

#### C. Feasible region and trade-off among performance metrics

Most existing studies in which queue length, utilization or workload affects the performance of servers, including those mentioned in Sections VI and VII, examine the effects on a single aspect of server performance, oftentimes their service rates being the choice. In another example, the study by Chatterjee et al. [129] takes into account the service quality (which is modeled as channel condition in their study) as a function of queue length and examines the information-theoretic capacity of such systems.

In many cases of interest, however, including human supervisors [99], several performance aspects, including service rate and service quality (e.g., reliability or frequency of mistakes or poor decisions), can be affected at the same time by work history via server state. Moreover, the requirements (e.g., service rate vs. reliability) in different applications are likely to vary considerably based on the types of tasks that need to be processed.

<sup>7</sup>See [122] for an overview of scheduling techniques for networked control systems, where most-recent-only scheduling is also discussed.

<sup>8</sup>The techniques used in [87] are analogous to the ones adopted for the case without packet drops in [72].

From this viewpoint, it is important to develop a comprehensive theory for these systems, including their fundamental limits. Regrettably, to the best of our knowledge, little is known about the feasible region of multiple performance metrics which can be achieved simultaneously and how to design suitable policies for carrying out a desired trade-off among various performance metrics in the feasible region, in particular on the Pareto frontier.

#### *D. Secure remote estimation powered by energy-harvesting*

Preventing, or at the very least mitigating the effect of, attacks on the channels connecting the sensors to every component relying on remotely constructed state estimates is critical to ensure the safe operation [130] of networked cyber-physical systems. While clever encoding and decoding schemes [131], some of which may be implemented efficiently using event-based algorithms, may thwart or curb the effect [132] of certain types of attacks, a relentless surreptitious Man-in-the-Middle (MitM) attack injecting false data [133] may significantly degrade the performance of any remote estimation system. The case-study in [134] illustrates that by employing message authentication codes (MACs), even if infrequently, may afford performance guarantees against MitM attacks. It further demonstrates that although MAC are known to substantially increase communication overhead, which is particularly critical when using bandwidth-limited networks such as the ones found in automobiles, its parsimonious use may suffice for practical purposes. A promising new research avenue is to investigate estimation-oriented encoding and decoding schemes and MAC scheduling policies that would jointly provide stability and performance guarantees, or would even be jointly optimal with respect to a given estimation error metric, in the presence of MitM attacks. Realistic problem formulations, in which information transmission is powered by an energy harvesting module, would have to account for the additional energy required for the transmission of MAC. A new type of EH link<sup>9</sup> that would account not only for packet-drop events, but also MitM attacks whose likelihood and severity would depend on the power employed in each transmission for the inclusion of MAC could be a useful abstraction to design and evaluate the performance of such systems. The open problems discussed here would also be relevant for distributed function calculation [135] in the cases in which information would be wirelessly disseminated among the agents via such security-threatened EH links.

Finally, it would be important to investigate all of these problems in light of other security threats [136], including denial-of-service attacks [137].

#### *E. Systems with multiple UDCs and development of a new theory for large systems with many UDCs*

In many situations of practical interest, there are a set of servers working on tasks (e.g., emergency rooms at hospitals). Furthermore, the availability of servers may be affected by some exogenous processes (e.g., schedules of doctors and

nurses at hospitals). For example, data centers comprise a large number of server racks that are connected by high-speed networks and are sometimes subject to power constraints. Also, because the reliability of hardware components, such as CPUs, GPUs and memory modules, degrades when the temperature exceeds some threshold, they need to be cooled for stable operation, for instance, via direct-to-chip liquid cooling. Moreover, because new server racks are added over time to meet increasing demands and old or failed racks are replaced at different times, the computational capabilities offered by various computational resources, which are designed for different types of tasks (e.g., CPUs vs. GPUs), can vary significantly.

Another class of problems well suited for the UDC framework with multiple UDCs, which is also related to those in Sections VIII-B and VIII-D, is information collection from multiple sources over time. These sources may be distributed sensors in wireless sensor networks (WSNs), which are powered by renewable energy or WET, or “friends” in social networks who prefer not to be bothered constantly for the latest information. One can view the “usefulness” of the information collected from each sensor or friend as the reward. Such usefulness of information from a sensor or a friend will likely be stochastic. However, there are certain factors that would affect the usefulness of the information. These include (i) the accuracy or quality of the sensors or the importance of the friends in social networks (which are often measured using their “centralities” in social networks [138]) and (ii) the age-of-information from each sensor or friend introduced in Section VIII-B as well as the frequency of information requests.

Unfortunately, the quality of sensors and the importance of friends may not be known in advance. In addition, in many practical scenarios, we may be able to poll or collect information from only a limited number of sensors or friends at any given time and only so often. In WSNs, for instance, the number of available channels or timeslots in a frame may constrain the number of measurements we can collect at each time and, when the sensors are powered by renewable energy or WET, they may not be able to report measurements even when they are polled, as their availability for reporting measurements will be governed by a stochastic process.

Despite their prevalence, not much is known about their fundamental performance limits and efficient resource management in such systems with many UDCs. This calls for the development of a new theory, especially for offering a guideline for effective resource allocations in large systems with many UDCs. Only recently research has demonstrated the benefits of task-aware scheduling at data centers (e.g. [139]). Consequently, there is a rich set of open problems in related domains. For instance, when heterogeneous servers are designed/optimized for different types of tasks and their efficiency is utilization-dependent, how should we schedule arriving tasks so that both the (mean) sojourn time of the tasks and the utilization rates of the servers are minimized while maintaining the stability of the queues? These are some of questions, the answer to which can have significant impact on many areas, including crucial applications involving HSC

<sup>9</sup>Possibly based on a modification of Definition 12.

(e.g., air traffic control and nuclear power plant monitoring). A useful approach for studying these problems, especially when some of the parameters are unknown, is the restless multi-armed bandit model, which has been previously applied to stochastic scheduling [140], [141].

#### F. UDC in learning

In recent years, information-theoretic techniques have emerged as effective tools to study optimization procedures in machine learning problems [142], [143], [144], [145], [146]. Iterative and noisy optimization procedures such as the stochastic gradient descent or stochastic gradient Langevin dynamics have been hypothesized to be efficient due to their inherent noisy nature [144], [147], [148], [149]. It is not hard to describe such iterative optimization techniques using the UDC framework, but such a reformulation leads to some novel adversarial models of learning that may be of interest. For example, the controlled Markov process may be current hypothesis  $S(k)$  that is being optimized in an iterative fashion. The action kernel may be used to generate the additive update  $Y(k)$  that modifies  $S(k)$  to  $S(k+1) = S(k) + Y(k)$ . In general, this update is simply a derivative (or a noisy version thereof). In an adversarial setting, these updates may be influenced by an adversary via an input  $X(k)$  to the action kernel. Such a scenario generalizes data-poisoning attacks studied in [150], [151], [152] or gradient-based attacks [153], [154].

#### G. More realistic battery models for energy harvesting: leakage and nonlinearities

Although, as we discussed in Section III-B, the batteries used in energy harvesting modules have a rather complex behavior, the existing work discussed throughout this article adopts either the linear-saturated or the finite-state approximations. These simplified models do not capture a host of issues that could possibly require new methods and abstractions. This is illustrated by the following two features that could be captured by our general model of Definition 5:

a) *Leakage*: The chemistry of every battery and the operation of its auxiliary circuitry will cause charge to leak, even when it is not supplying power. Hence, the charge that is stored in a battery may be partially lost unless it is used quickly or the leakage is offset by harvesting. This is a relevant problem for low-power remote sensing devices that operate over long periods of time.

b) *Nonlinearities*: In Section III-B we mentioned the fact that, due to the discharge curve, in general there is a state of charge threshold below which the voltage of the battery does not suffice to power the other components. Consequently, if the voltage is near the required minimum then leakage effects may drain the state of charge below the aforesaid threshold, after which enough energy must be harvested before the battery can function again. The fact that the state of charge also governs the portion of the energy harvested that is effectively stored constitutes another important nonlinearity. Notably, as the state of charge nears its maximum and minimum the ability of the battery to store energy varies considerably.

Although these detrimental battery features have been taken into account in the design of transmitters that seek to maximize wireless transmission rate subject to energy harvesting [155], [156], they have yet to be addressed in the context of remote estimation systems.

#### ACKNOWLEDGEMENT

The authors would like to thank Sennur Ulukus (UMD), Yasser Shoukry (UMD) and Vijay Gupta (UND) for helpful discussions and suggestions.

#### REFERENCES

- [1] S. Ulukus, A. Yener, E. Erkip, O. Simeone, M. Zorzi, P. Grover, and K. Huang, "Energy harvesting wireless communications: a review of recent advances," *IEEE Journal on Selected Areas in Communications*, vol. 33, pp. 360–381, March 2015.
- [2] K.-D. Kim and P. R. Kumar, "Cyber-physical systems: a perspective at the centennial," *Proceedings of the IEEE*, pp. 1287–1308, May 2012.
- [3] R. Baheti and H. Gill, *The impact of control technology*, ch. Cyber-physical systems, pp. 161–166. IEEE Control Systems Society, 2011.
- [4] M. A. Staal, "Stress, cognition and human performance: A literature review and conceptual framework," Tech. Rep. NASA/TM-2004-212824, NASA, August 2004.
- [5] A. S. Leong, D. E. Quevedo, and S. Dey, *Optimal control of energy resources for state estimation over wireless channels*. Briefs in electrical and computer engineering, Springer, 2018.
- [6] J. P. Hespanha, P. Naghshtabrizi, and Y. Xu, "A survey of recent results in networked control systems," *Proceedings of the IEEE*, vol. 95, no. 1, pp. 138–162, 2007.
- [7] K. H. Teigen, "Yerkes-Dodson: a law for all seasons," *Theory & Psychology*, vol. 4, no. 4, pp. 525–547, 1994.
- [8] C. D. Wickens and J. G. Hollands, *Engineering psychology and human performance*. Prentice Hall, third edition ed., 2000.
- [9] M. L. Cummings and C. E. Nehme, "Modeling the impact of workload in network centric supervisory control settings," in *Proceedings of the 2nd Annual Sustaining Performance Under Stress Symposium*, February 2009.
- [10] J. R. Peters, V. Srivastava, G. S. Taylor, A. Surana, M. P. Eckstein, and F. Bullo, "Human supervisory control of robotic teams: Integrating cognitive modeling with engineering design," *IEEE Control Systems Magazine*, vol. 35, pp. 57–80, December 2015.
- [11] H. P. G. van Ooijen and J. W. M. Bertrand, "The effects of a simple arrival rate control policy on throughput and work-in-process in production systems with workload dependent processing rates," *International Journal of Production Economics*, vol. 85, pp. 61–68, 2003.
- [12] K. Savla and E. Frazzoli, "A dynamical queue approach to intelligent task management for human operators," *Proceedings of the IEEE*, vol. 100, pp. 672–686, March 2012.
- [13] T. Koch, A. Lapidot, and P. P. Sotiriadis, "Channels that heat up," *IEEE Transactions on Information Theory*, vol. 55, pp. 3594–3612, August 2009.
- [14] A. Baknina, O. Ozel, and S. Ulukus, "Energy harvesting communications under explicit and implicit temperature constraints," *IEEE Transactions on Wireless Communications*, vol. 17, pp. 6680–6692, October 2018.
- [15] D. Forte and A. Srivastava, "Thermal-aware sensor scheduling for distributed estimation," *ACM Transactions on Sensor Networks*, vol. 9, pp. 53:1–53:31, July 2013.
- [16] F. Baccelli and P. Brémaud, *Elements of queueing theory*. Springer, second edition ed., 2003.
- [17] S. Sudevalayam and P. Kulkarni, "Energy harvesting sensor nodes: Survey and implications," *IEEE Communications Surveys and Tutorials*, vol. 13, no. 3, pp. 443–461, 2011.
- [18] A. Kansal, J. Hsu, S. Zahedi, and M. B. Srivastava, "Power management in energy harvesting sensor networks," *ACM Transactions on Embedded Computing Systems*, vol. 6, September 2007.
- [19] S. Priya and D. J. Inman, eds., *Energy Harvesting Technologies*. Springer, 2009.

- [20] B. E. Lewandowski, K. L. Kilgore, and K. J. Gustafson, "Feasibility of an implantable, stimulated muscle-powered piezoelectric generator as a power source for implanted medical devices," in *Energy Harvesting Technologies* (S. Priya and D. J. Inman, eds.), ch. 15, pp. 389–404, Springer, 2009.
- [21] C. M. Shepherd, "Design of primary and secondary cells ii. an equation describing battery discharge.," *J. Electrochem. Soc.*, vol. 112, no. 7, pp. 657–664, 1965.
- [22] M. Chen and G. A. Ricón-Mora, "Accurate electrical battery model capable of predicting runtime and i-v performance," *IEEE Transactions on Energy Conversion*, vol. 21, pp. 504–511, June 2006.
- [23] S. Sudevalayam and P. Kulkarni, "Energy harvesting sensor nodes: Survey and implications," *IEEE Communications Surveys & Tutorials*, vol. 13, no. 3, pp. 443–461, 2011.
- [24] D. Gunduz, K. Stamatiou, N. Michelusi, and M. Zorzi, "Designing intelligent energy harvesting communication systems," *IEEE communications magazine*, vol. 52, no. 1, pp. 210–216, 2014.
- [25] S. Ulukus, A. Yener, E. Erkip, O. Simeone, M. Zorzi, P. Grover, and K. Huang, "Energy harvesting wireless communications: A review of recent advances," *IEEE Journal on Selected Areas in Communications*, vol. 33, no. 3, pp. 360–381, 2015.
- [26] O. Ozel and S. Ulukus, "Achieving AWGN capacity under stochastic energy harvesting," *IEEE Transactions on Information Theory*, vol. 58, no. 10, pp. 6471–6483, 2012.
- [27] O. Ozel and S. Ulukus, "AWGN channel under time-varying amplitude constraints with causal information at the transmitter," in *2011 Conference Record of the Forty Fifth Asilomar Conference on Signals, Systems and Computers (ASILOMAR)*, pp. 373–377, IEEE, 2011.
- [28] Y. Dong and A. Özgür, "Approximate capacity of energy harvesting communication with finite battery," in *2014 IEEE International Symposium on Information Theory*, pp. 801–805, IEEE, 2014.
- [29] V. Jog and V. Anantharam, "An energy harvesting AWGN channel with a finite battery," in *2014 IEEE International Symposium on Information Theory*, pp. 806–810, IEEE, 2014.
- [30] K. Tutuncuoglu, O. Ozel, A. Yener, and S. Ulukus, "Improved capacity bounds for the binary energy harvesting channel," in *2014 IEEE International Symposium on Information Theory*, pp. 976–980, IEEE, 2014.
- [31] Y. Dong, F. Farnia, and A. Özgür, "Near optimal energy control and approximate capacity of energy harvesting communication," *IEEE Journal on Selected Areas in Communications*, vol. 33, no. 3, pp. 540–557, 2015.
- [32] O. Ozel, K. Tutuncuoglu, S. Ulukus, and A. Yener, "Fundamental limits of energy harvesting communications," *IEEE Communications Magazine*, vol. 53, no. 4, pp. 126–132, 2015.
- [33] D. Shaviv, P. Nguyen, and A. Özgür, "Capacity of the energy-harvesting channel with a finite battery," *IEEE Transactions on Information Theory*, vol. 62, no. 11, pp. 6436–6458, 2016.
- [34] O. Ozel and S. Ulukus, "On the capacity region of the Gaussian MAC with batteryless energy harvesting transmitters," in *2012 IEEE Global Communications Conference (GLOBECOM)*, pp. 2385–2390, IEEE, 2012.
- [35] H. Inan, D. Shaviv, and A. Özgür, "Capacity of the energy harvesting Gaussian MAC," *IEEE Transactions on Information Theory*, vol. 64, no. 4, pp. 2347–2360, 2018.
- [36] O. Ozel, J. Yang, and S. Ulukus, "Optimal scheduling over fading broadcast channels with an energy harvesting transmitter," in *2011 4th IEEE International Workshop on Computational Advances in Multi-Sensor Adaptive Processing (CAMSAP)*, pp. 193–196, IEEE, 2011.
- [37] O. Ozel, J. Yang, and S. Ulukus, "Optimal broadcast scheduling for an energy harvesting rechargeable transmitter with a finite capacity battery," *IEEE Transactions on Wireless Communications*, vol. 11, no. 6, pp. 2193–2203, 2012.
- [38] K. Tutuncuoglu and A. Yener, "Sum-rate optimal power policies for energy harvesting transmitters in an interference channel," *Journal of Communications and Networks*, vol. 14, no. 2, pp. 151–161, 2012.
- [39] J. Yang and S. Ulukus, "Optimal packet scheduling in a multiple access channel with energy harvesting transmitters," *Journal of Communications and Networks*, vol. 14, no. 2, pp. 140–150, 2012.
- [40] D. Shaviv and A. Özgür, "Universally near optimal online power control for energy harvesting nodes," *IEEE Journal on Selected Areas in Communications*, vol. 34, no. 12, pp. 3620–3631, 2016.
- [41] A. Baknina and S. Ulukus, "Optimal and near-optimal online strategies for energy harvesting broadcast channels," *IEEE Journal on Selected Areas in Communications*, vol. 34, no. 12, pp. 3696–3708, 2016.
- [42] A. Baknina and S. Ulukus, "Energy harvesting multiple access channels: Optimal and near-optimal online policies," *IEEE Transactions on Communications*, vol. 66, no. 7, pp. 2904–2917, 2018.
- [43] C. E. Shannon, "A mathematical theory of communication, I and II," *Bell Syst. Tech. J.*, vol. 27, pp. 379–423, 1948.
- [44] J. G. Smith, "The information capacity of amplitude-and variance-constrained scalar Gaussian channels," *Information and Control*, vol. 18, no. 3, pp. 203–219, 1971.
- [45] D. Shaviv, A. Özgür, and H. Permuter, "Can feedback increase the capacity of the energy harvesting channel?," in *IEEE Information Theory Workshop (ITW)*, 2015, pp. 1–5, IEEE, 2015.
- [46] D. Blackwell, L. Breiman, and A. J. Thomasian, "The capacities of certain channel classes under random coding," *The Annals of Mathematical Statistics*, vol. 31, no. 3, pp. 558–567, 1960.
- [47] I. Csiszar and J. Körner, *Information theory: coding theorems for discrete memoryless systems*. Cambridge University Press, 2011.
- [48] A. J. Goldsmith and P. P. Varaiya, "Capacity, mutual information, and coding for finite-state Markov channels," *IEEE Transactions on Information Theory*, vol. 42, no. 3, pp. 868–886, 1996.
- [49] T. Weissman, "Capacity of channels with action-dependent states," *IEEE Transactions on Information Theory*, vol. 56, no. 11, pp. 5396–5411, 2010.
- [50] W. Hirt and J. L. Massey, "Capacity of the discrete-time Gaussian channel with intersymbol interference," *IEEE Transactions on Information Theory*, vol. 34, no. 3, pp. 38–38, 1988.
- [51] A. Goldsmith, *Wireless communications*. Cambridge University Press, 1 ed., 2005.
- [52] D. Tse and P. Viswanath, *Fundamentals of Wireless Communication*. Cambridge University Press, 1 ed., 2005.
- [53] L. H. Ozarow, S. Shamai, and A. D. Wyner, "Information theoretic considerations for cellular mobile radio," *IEEE Transactions on Vehicular Technology*, vol. 43, no. 2, pp. 359–378, 1994.
- [54] N. C. Beaulieu and J. Hu, "A closed-form expression for the outage probability of decode-and-forward relaying in dissimilar rayleigh fading channels," *IEEE Communications Letters*, vol. 10, pp. 813–815, December 2006.
- [55] C. N. Hadjisostis and R. Touri, "Feedback control utilizing packet dropping links," in *Proceedings of the IEEE Conference on Decision and Control*, pp. 1205–1210, 2002.
- [56] B. Sinopoli, L. Schenato, M. Franceschetti, K. Poola, M. I. Jordan, and S. S. Sastry, "Kalman filtering with intermittent observations," *IEEE Transactions on Automatic Control*, vol. 49, no. 9, pp. 1453–1464, 2004.
- [57] O. L. V. Costa and M. D. Fragoso, "Stability results for discrete-time linear systems with markovian jumping parameters," *Journal of Mathematical Analysis and Applications*, vol. 179, pp. 154–178, 1993.
- [58] O. C. Imer, S. Yüksel, and T. Basar, "Optimal control of lti systems over unreliable communication links," *Automatica*, vol. 42, pp. 1429–1439, 2006.
- [59] O. C. Imer and T. Basar, "Optimal estimation with limited measurements," *International Journal of Systems, Control and Communications*, vol. 2, pp. 5–29, 2010.
- [60] L. Schenato, B. Sinopoli, M. Franceschetti, K. Poola, and S. S. Sastry, "Foundations of control and estimation over lossy networks," *Proceedings of the IEEE*, vol. 95, pp. 163–187, January 2007.
- [61] Y. Xu and J. P. Hespanha, "Estimation under uncontrolled and controlled communications in networked control systems," in *Proceedings of the IEEE Conference on Decision and Control*, pp. 842–847, December 2005.
- [62] W. J. Rugh, *Linear system theory*. Prentice Hall, 2 ed., 1996.
- [63] J. P. Hespanha, *Linear systems theory*. Princeton University Press, 2 ed., 2018.
- [64] V. Gupta, B. Hassibi, and R. M. Murray, "Optimal lqg control across packet-dropping links," *Systems and Control Letters*, vol. 56, pp. 439–446, 2007.
- [65] V. Gupta, N. C. Martins, and J. S. Baras, "Optimal output feedback control using two remote sensors over erasure channels," *IEEE Transactions on Automatic Control*, vol. 54, pp. 1463–1476, July 2009.
- [66] V. Gupta and N. C. Martins, "On stability in the presence of analog erasure channel between the controller and the actuator," *IEEE Transactions on Automatic Control*, vol. 55, no. 1, pp. 175–179, 2010.
- [67] P. Minero, M. Franceschetti, S. Dey, and G. N. Nair, "Data rate theorem for stabilization over time-varying feedback channels," *IEEE Transactions on Automatic Control*, vol. 54, no. 2, pp. 243–255, 2009.
- [68] W. S. Wong and R. Brockett, "Systems with finite communication bandwidth constraints—part i: State estimation problems," *IEEE Transactions on Automatic Control*, vol. 42, no. 9, 1997.

- [69] N. C. Martins, M. A. Dahleh, and N. Elia, "Feedback stabilization of uncertain systems in the presence of a direct link," *IEEE Transactions on Automatic Control*, vol. 51, no. 3, pp. 438–447, 2006.
- [70] A. Sahai and S. Mitter, "The necessity and sufficiency of anytime capacity for stabilization of a linear system over a noisy communication link - part i: scalar systems," *IEEE Transactions on Information Theory*, vol. 52, pp. 3369–3395, August 2006.
- [71] A. S. Matveev and A. Savkin, *Estimation and Control Over Communication Networks*. Birkauer Boston, 2009.
- [72] G. M. Lipsa and N. C. Martins, "Remote state estimation with communication costs for first-order lti systems," *IEEE Transactions on Automatic Control*, vol. 56, pp. 2013–2025, September 2011.
- [73] B. Hajek, K. Mitzel, and S. Yang, "Paging and registration in cellular networks: jointly optimal policies and an iterative algorithm," *IEEE Transactions on Information Theory*, vol. 54, pp. 608–622, February 2008.
- [74] A. Nayyar, T. Basar, D. Teneketzis, and V. V. Veeravalli, "Optimal strategies for communication and remote estimation with an energy harvesting sensor," *IEEE Transactions on Automatic Control*, vol. 58, pp. 2246–2260, September 2013.
- [75] S. Park and N. C. Martins, "Individually optimal solutions to a remote state estimation problem with communication costs," in *Proceedings of the IEEE Conference on Decision and Control*, pp. 4014–4019, 2018.
- [76] A. Molin and S. Hirche, "On the optimality of certainty equivalence for event-triggered control systems," *IEEE Transactions on Automatic Control*, vol. 58, no. 2, pp. 470–474, 2013.
- [77] X. Wang and M. Lemmon, "Event-triggering in distributed networked control systems," *IEEE Transactions on Automatic Control*, vol. 56, pp. 586 – 601, March 2011.
- [78] M. L. Puterman, *Markov decision processes: discrete stochastic dynamic programming*. Wiley, 2005.
- [79] A. S. Leong, S. Dey, and D. E. Quevedo, "Transmission scheduling for remote state estimation and control with an energy harvesting sensor," *Automatica*, vol. 91, pp. 54–60, 2018.
- [80] Y. Li, F. Zhang, D. E. Quevedo, V. Lau, S. Dey, and L. Shi, "Power control of an energy harvesting sensor for remote state estimation," *IEEE Transactions on Automatic Control*, vol. 62, pp. 277–290, January 2017.
- [81] M. Nourian, A. S. Leong, and S. Dey, "Optimal energy allocation for kalman filtering over packet dropping links with imperfect acknowledgements and energy harvesting constraints," *IEEE Transactions on Automatic Control*, vol. 59, pp. 2128–2143, August 2014.
- [82] S. Trimpe and R. D'Andrea, "Event-based state estimation with variance-based triggering," *IEEE Transactions on Automatic Control*, vol. 59, pp. 3266–3281, December 2014.
- [83] P. R. Kumar and P. Varayia, *Stochastic Systems: Estimation, Identification and Adaptive Control*. SIAM, 2015.
- [84] S. Knorn and S. Dey, "Optimal energy allocation for linear control with packet loss under energy harvesting constraints," *Automatica*, vol. 77, pp. 259–267, 2017.
- [85] X. Ren, J. Wu, K. H. Johansson, G. Shi, and L. Shi, "Infinite horizon optimal transmission power control for remote state estimation over fading channels," *IEEE Transactions on Automatic Control*, vol. 63, pp. 85–100, January 2018.
- [86] J. Chakravorty and A. Mahajan, "Remote estimation over a packet-drop channel with markovian state," *IEEE Transactions on Automatic Control (in press)*, 2019.
- [87] G. M. Lipsa and N. C. Martins, "Optimal state estimation in the presence of communication costs and packet drops," in *Proceedings of Allerton Conference on Communication, Control and Computing*, pp. 160–169, 2009.
- [88] M. Lin, R. J. La, and N. C. Martins, "Remote state estimation across an action-dependent packet-drop link," in *Proceedings of the IEEE Conference on Decision and Control*, 2018.
- [89] R. W. Conway and W. L. Maxwell, "A queueing model with state dependent service rates," *Journal of Industrial Engineering*, vol. 12, pp. 132–136, 1962.
- [90] J. R. Jackson, "Jobshop-like queueing systems," *Management Science*, vol. 10, no. 1, pp. 131–142, 1963.
- [91] M. Yadin and P. Naor, "Queueing systems with a removable service station," *Operational Research Society*, vol. 14, pp. 393–405, December 1963.
- [92] S. Gupta, "On bulk queues with state dependent parameters," *Journal of the Operations Research Society of Japan*, vol. 9, pp. 69–82, April 1967.
- [93] C. M. Harris, "Queues with state-dependent stochastic service rates," *Operations Research*, vol. 15, pp. 117–130, February 1967.
- [94] J. H. Dshalalow, "Queueing systems with state dependent parameters," in *Frontiers in Queueing: Models and Applications in Science and Engineering, Probability and Stochastics Series* (J. H. Dshalalow, ed.), ch. 4, pp. 132–136, CRC, 1997.
- [95] R. M. Yerkes and J. D. Dodson, "The relation of strength of stimulus to rapidity of habit-formation," *Journal of Comparative Neurology and Psychology*, vol. 18, pp. 459–482, November 1908.
- [96] L. C. Edie, "Traffic delays at toll booths," *Journal of the Operations Research Society of America*, vol. 2, pp. 107–138, May 1954.
- [97] G. Borghini, L. Astolfi, G. Vecchiato, D. Mattia, and F. Babiloni, "Measuring neurophysiological signals in aircraft pilots and car drivers for the assessment of mental workload, fatigue and drowsiness," *Neuroscience & Biobehavioral Reviews*, vol. 44, pp. 58–75, July 2014.
- [98] M. Shunko, J. Niederhoff, and Y. Rosokha, "Humans are not machines: the behavioral impact of queueing on service time," *Management Science*, vol. 64, pp. 57–80, December 2017.
- [99] T. S. Sheridan, "Supervisory control," in *Handbook of Human Factors and Ergonomics, second edition* (G. Salvendy, ed.), pp. 1295–1327, John Wiley & Sons, 1997.
- [100] P. V. Asaro, L. M. Lewis, and S. B. Boxerman, "The impact of input and output factors on emergency department throughput," *Academic Emergency Medicine*, vol. 14, pp. 235–242, April 2007.
- [101] D. S. Kc and C. Terwiesch, "Impact of workload on service time and patient safety: an economic analysis of hospital operations," *Management Science*, vol. 55, pp. 1486–1498, September 2009.
- [102] D. M. Diamond, A. M. Campbell, C. R. Park, J. Halonen, and P. R. Zoladz, "The temporal dynamics model of emotional memory processing: a synthesis on the neurobiological basis of stress-induced amnesia, flashbulb and traumatic memories, and the yerkes-dodson law," *Neural Plasticity*, 2017.
- [103] M. Lin, R. J. La, and N. C. Martins, "Stability of a single queue subject to action-dependent server performance." preprint available at <https://arxiv.org/abs/1903.00135>, 2019.
- [104] M. Lin, N. C. Martins, and R. J. La, "Queueing subject to action-dependent server performance: utilization rate reduction." preprint available at <https://arxiv.org/abs/2002.08514>, 2020.
- [105] S. Bi, Y. Zeng, and R. Zhang, "Wireless powered communication networks: An overview," *IEEE Wireless Communications*, vol. 23, pp. 10–18, April 2016.
- [106] D. Niyato, D. I. Kim, M. Maso, and Z. Han, "Wireless powered communication networks: Research directions and technological approaches," *IEEE Wireless Communications*, vol. 24, pp. 88–97, December 2017.
- [107] Z. Chu, F. Zhou, Z. Zhu, R. Q. Hu, and P. Xiao, "Wireless powered sensor networks for internet of things: Maximum throughput and optimal power allocation," *IEEE Internet of Things Journal*, vol. 5, pp. 310–321, February 2018.
- [108] B. Lyu, T. Qi, H. Guo, and Z. Yang, "Throughput maximization in full-duplex dual-hop wireless powered communication networks," *IEEE Access*, vol. 7, pp. 158584–158593, 2019.
- [109] H. Ju and R. Zhang, "Throughput maximization in wireless powered communication networks," *IEEE Transactions on Wireless Communications*, vol. 13, pp. 418–428, January 2014.
- [110] Y. L. Che, L. Duan, and R. Zhang, "Spatial throughput maximization of wireless powered communication networks," *IEEE Journal on Selected Areas in Communications*, vol. 33, pp. 1534–1548, August 2015.
- [111] G. Yang, C. K. Ho, R. Zhang, and Y. L. Guan, "Throughput maximization for massive MIMO systems powered by wireless energy transfer," *IEEE Journal on Selected Areas in Communications*, vol. 33, pp. 1640–1650, August 2015.
- [112] F. Shan, J. Luo, W. Wu, and X. Shen, "Optimal wireless power transfer scheduling for delay minimization," in *Proceedings of the IEEE INFOCOM*, 2016.
- [113] R. Rezaei, S. Sum, X. Kang, Y. L. Guan, and M. R. Pakravan, "Secrecy throughput maximization for full-duplex wireless powered iot networks under fairness constraints," *IEEE Internet of Things Journal*, vol. 6, pp. 6964–6976, August 2019.
- [114] M. Kashaf and A. Ephremides, "Optimal packet scheduling for energy harvesting sources on time varying wireless channels," *Journal of Communications and Networks*, vol. 14, pp. 121–129, April 2012.
- [115] S. Mao, M. H. Cheung, and V. W. Wong, "Joint energy allocation for sensing and transmission in rechargeable wireless sensor networks," *IEEE Transactions on Vehicular Technology*, vol. 63, pp. 2862–2875, July 2014.
- [116] I. Ahmed, K. T. Phan, and T. Le-Ngoc, "Optimal stochastic power control for energy harvesting systems with delay constraints," *IEEE*

- Journal on Selected Areas In Communications*, vol. 34, pp. 3512–3527, December 2016.
- [117] E. Altman, *Constrained Markov Decision Processes*. CRC Press, 1 ed., 1999.
  - [118] O. Orhan, D. Gündüz, and E. Erkip, “Source-channel coding under energy, delay and buffer constraints,” *IEEE Transactions on Wireless Communications*, vol. 14, no. 7, pp. 3836–3849, 2015.
  - [119] P. Grover, K. Woyach, and A. Sahai, “Towards a communication-theoretic understanding of system-level power consumption,” *IEEE Journal on Selected Areas in Communications*, vol. 29, September 2011.
  - [120] D. O. Wheeler, D. P. Koch, J. S. Jackson, T. W. McLain, and R. W. Beard, “Relative navigation: a keyframe-based approach for observable gps-degraded navigation,” *IEEE Control Systems Magazine*, vol. 38, pp. 30–48, July 2018.
  - [121] C. Kreucher, K. Kastella, and A. O. Hero III, “Sensor management using an active sensing approach,” *Signal Processing*, vol. 85, pp. 607–624, 2005.
  - [122] G. C. Walsh and H. Ye, “Scheduling of networked control systems,” *IEEE Control Systems Magazine*, vol. 21, no. 1, pp. 57–65, 2001.
  - [123] Y. Sun, Y. Polyanskiy, and E. Uysal-Biyikoglu, “Sampling of the wiener process for remote estimation over a channel with random delay,” *ArXiv*, 2018.
  - [124] Y. Sun, Y. Polyanskiy, and E. Uysal-Biyikoglu, “Remote estimation of the wiener process over a channel with random delay,” *ArXiv*, 2018.
  - [125] Y. Sun, E. Uysal-Biyikoglu, R. D. Yates, C. E. Koksal, and N. B. Shroff, “Update or wait: how to keep your data fresh,” *IEEE Transactions on Information Theory*, vol. 63, pp. 7492–7508, November 2017.
  - [126] A. Arafa, J. Yang, S. Ulukus, and H. V. Poor, “Age-minimal transmission for energy harvesting sensors with finite batteries: online policies,” *ArXiv*, 2018.
  - [127] C. Kam, S. Kompela, G. D. Nguyen, J. E. Wieselthier, and A. Ephremides, “Towards an effective age of information: remote estimation of a Markov source,” in *Proceedings of the IEEE Conference on Computer Communication Workshops: AoI Workshop*, pp. 367–372, 2018.
  - [128] T. Z. Ornee and Y. Sun, “Sampling for remote estimation through queues: age of information and beyond,” *ArXiv*, February 2019.
  - [129] A. Chatterjee, D. Seo, and L. R. Varshney, “Capacity of systems with queue-length dependent service quality,” *IEEE Transactions on Information Theory*, vol. 63, pp. 3950–3963, June 2017.
  - [130] M. Pajic, J. Weimer, N. Bezzo, O. Sokolsky, G. J. Pappas, and I. Lee, “Design and implementation of attack-resilient cyberphysical systems,” *IEEE Control Systems Magazine*, pp. 66–81, April 2017.
  - [131] H. Fawzi, P. Tabuada, and S. Diggavi, “Secure estimation and control for cyber-physical systems under adversarial attacks,” *IEEE Transactions on Automatic Control*, vol. 59, no. 6, pp. 1454–1467, 2014.
  - [132] Y. Shoukry and P. Tabuada, “Event-triggered state observers for sparse sensor noise/attacks,” *IEEE Transactions on Automatic Control*, vol. 61, pp. 2079–2091, August 2016.
  - [133] Y. Mo, E. Garone, A. Casavola, and B. Sinopoli, “False data injection attacks against state estimation in wireless sensor networks,” in *Proceedings of the IEEE Conference on Decision and Control*, pp. 5967–5972, 2010.
  - [134] I. Jovanov and M. Pajic, “Secure state estimation with cumulative message authentication,” in *Proceedings of the IEEE Conference on Decision and Control*, pp. 2074–2079, 2018.
  - [135] S. Sundaram and C. N. Hadjicostis, “Distributed function calculation via linear iterative strategies in the presence of malicious agents,” *IEEE Transactions on Automatic Control*, vol. 56, pp. 1495–1508, July 2011.
  - [136] D. I. Urbina, J. Giraldo, A. A. Cardenas, J. Valente, M. Faisal, N. O. Tippenhauer, J. Ruths, R. Candell, and H. Sandberg, “Survey and new directions for physics-based attack detection in control systems,” Tech. Rep. NIST GCR 16-010, NIST, U.S. Department of Commerce, November 2016.
  - [137] A. Cetinkaya, H. Ishii, and T. Hayakawa, “An overview on denial-of-service attacks in control systems: attack models and security analyses,” *Entropy*, vol. 21, pp. 1–29, February 2019.
  - [138] D. Easley and J. Kleinberg, *Networks, Crowds and Markets*. Cambridge University Press, 1 ed., 2010.
  - [139] F. R. Dogar, T. Karagiannis, H. Ballani, and A. Rowstron, “Decentralized task-aware scheduling for data center networks,” in *Proceedings of ACM SIGCOMM*, pp. 431–442, August 2014.
  - [140] A. Mahajan and D. Teneketzis, *Multi-armed bandit problems*, ch. Multi-armed bandit problems, pp. 121–151. Springer, 2008.
  - [141] P. Whittle, “Restless bandits: activity allocation in a changing world,” *Journal of Applied Probability*, vol. 25, pp. 287–298, 1988.
  - [142] D. Russo and J. Zou, “Controlling bias in adaptive data analysis using information theory,” in *Proceedings of the 19th International Conference on Artificial Intelligence and Statistics* (A. Gretton and C. C. Robert, eds.), vol. 51 of *Proceedings of Machine Learning Research*, pp. 1232–1240, PMLR, 09–11 May 2016.
  - [143] A. Xu and M. Raginsky, “Information-theoretic analysis of generalization capability of learning algorithms,” in *Advances in Neural Information Processing Systems* (I. Guyon, U. V. Luxburg, S. Bengio, H. Wallach, R. Fergus, S. Vishwanathan, and R. Garnett, eds.), pp. 2521–2530, Curran Associates, Inc., 2017.
  - [144] A. Pensia, V. Jog, and P. Loh, “Generalization error bounds for noisy, iterative algorithms,” in *2018 IEEE International Symposium on Information Theory (ISIT)*, pp. 546–550, June 2018.
  - [145] J. Negrea, M. Haghifam, G. K. Dziugaite, A. Khisti, and D. M. Roy, “Information-theoretic generalization bounds for SGLD via data-dependent estimates,” in *Advances in Neural Information Processing Systems*, pp. 11013–11023, 2019.
  - [146] T. Steinke and L. Zakynthinou, “Reasoning about generalization via conditional mutual information,” *arXiv preprint arXiv:2001.09122*, 2020.
  - [147] R. Ge, F. Huang, C. Jin, and Y. Yuan, “Escaping from saddle points—Online stochastic gradient for tensor decomposition,” in *Conference on Learning Theory*, pp. 797–842, 2015.
  - [148] C. Jin, R. Ge, P. Netrapalli, S. M. Kakade, and M. I. Jordan, “How to escape saddle points efficiently,” *arXiv preprint:1703.00887*, 2017.
  - [149] E. Abbe and C. Sandon, “Poly-time universality and limitations of deep learning,” *arXiv preprint arXiv:2001.02992*, 2020.
  - [150] B. Biggio, B. Nelson, and P. Laskov, “Poisoning attacks against support vector machines,” in *Proceedings of the 29th International Conference on Machine Learning*, pp. 1467–1474, Omnipress, 2012.
  - [151] S. Mei and X. Zhu, “Using machine teaching to identify optimal training-set attacks on machine learners,” in *AAAI*, pp. 2871–2877, 2015.
  - [152] P. Koh and P. Liang, “Understanding black-box predictions via influence functions,” *arXiv preprint arXiv:1703.04730*, 2017.
  - [153] P. Blanchard, R. Guerraoui, J. Stainer, et al., “Machine learning with adversaries: Byzantine tolerant gradient descent,” in *Advances in Neural Information Processing Systems*, pp. 119–129, 2017.
  - [154] Y. Chen, L. Su, and J. Xu, “Distributed statistical machine learning in adversarial settings: Byzantine gradient descent,” *ACM SIGMETRICS Performance Evaluation Review*, vol. 46, no. 1, pp. 96–96, 2019.
  - [155] B. Devillers and D. Gündüz, “A general framework for the optimization of energy harvesting communication systems with battery imperfections,” *Journal of Communications and Networks*, vol. 14, no. 2, pp. 130–139, 2012.
  - [156] K. Tutuncoglu, A. Yener, and S. Ulukus, “Optimum policies for an energy harvesting transmitter under energy storage losses,” *IEEE Journal on Selected Areas in Communications*, vol. 33, no. 3, pp. 467–481, 2015.