

Julia Lieb, Raquel Pinto and Joachim Rosenthal

Convolutional Codes



Chapter 1

Convolutional Codes

1.1	Introduction	3
1.2	Foundational Aspects of Convolutional Codes	4
1.2.1	Definition of Convolutional Codes via Generator and Parity-check Matrices	4
1.2.2	Distances of Convolutional Codes	10
1.3	Constructions of Codes with Optimal Distance	16
1.3.1	Constructions of MDS convolutional codes	16
1.3.2	Constructions of MDP convolutional codes	17
1.4	Connection to Systems Theory	20
1.5	Decoding of Convolutional Codes	23
1.5.1	Decoding over the erasure channel	24
1.5.1.1	The case $\delta = 0$	24
1.5.1.2	The general case	24
1.5.2	The Viterbi decoding algorithm	27
1.6	Two-dimensional Convolutional Codes	28
1.6.1	Definition of 2D Convolutional Codes via Generator and Parity-check Matrices	29
1.6.2	ISO representations	32
1.7	Connections of convolutional codes to symbolic dynamics	35
1.8	Acknowledgements	37

1.1 Introduction

Convolutional codes were introduced by Peter Elias [6] in 1955. They can be seen as a generalization of block codes. In order to motivate this generalization consider a $k \times n$ generator matrix G whose row space generates an $[n, k]$ block code \mathcal{C} . Denote by \mathbb{F}_q the finite field with q elements. In case a sequence of message words $m_i \in \mathbb{F}_q^k, i = 1, \dots, N$ has to be encoded one would transmit the sequence of codewords $c_i = m_i G \in \mathbb{F}_q^n, i = 1, \dots, N$. Using polynomial notation and defining

$$m(z) := \sum_{i=1}^N m_i z^i \in \mathbb{F}_q[z]^k, \quad c(z) := \sum_{i=1}^N c_i z^i \in \mathbb{F}_q[z]^n$$

the whole encoding process using the block code \mathcal{C} would be compactly described as

$$m(z) \mapsto c(z) = m(z)G.$$

Instead of using the constant matrix G as an encoding map Elias suggested using more general polynomial matrices of the form $G(z)$ whose entries consists of elements of the polynomial ring $\mathbb{F}_q[z]$.

There are natural connections to automata theory and systems theory and this was first recognized by Massey and Sain in 1967 [26]. These connections have always been fruitful in the development of the theory on convolutional codes and the reader might also consult the survey [33].

Forney developed in the seventies [9, 10, 11] a mathematical theory which allowed the processing of an infinite set of message blocks having the form $m(z) := \sum_{i=1}^{\infty} m_i z^i \in \mathbb{F}_q[[z]]^k$. Note that the quotient field of the ring of formal power series $\mathbb{F}_q[[z]]$ is the field of formal Laurent series $\mathbb{F}_q((z))$ and in the theory of Forney convolutional codes were defined as k -dimensional linear subspaces of the n -dimensional vector space $\mathbb{F}_q((z))^n$ which also possess a $k \times n$ polynomial generator matrix $G(z) \in \mathbb{F}_q[z]^{k \times n}$.

The theory of convolutional codes as first developed by Forney can also be found in the monograph by Piret [31] and in the textbook by Johansson and Zigangirov [17] and McEliece provides also a survey [27].

In this survey article our starting point is message words of finite length, i.e. polynomial vectors of the form $m(z) := \sum_{i=0}^N m_i z^i \in \mathbb{F}_q[z]^k$ which get processed by a polynomial matrix $G(z) \in \mathbb{F}_q[z]^{k \times n}$. The resulting code becomes then in a natural way a rank k module over the polynomial ring $\mathbb{F}_q[z]$. The connection to discrete time linear systems by duality is then also natural as first shown by Rosenthal, Schumacher and York [34].

1.2 Foundational Aspects of Convolutional Codes

1.2.1 Definition of Convolutional Codes via Generator and Parity-check Matrices

Let $R = \mathbb{F}_q[z]$ be the ring of polynomials with coefficients in the field \mathbb{F}_q , and denote by $\mathbb{F}_q(z)$ the field of rational functions with coefficients in \mathbb{F}_q . R is a Principal Ideal Domain (PID). Modules over a PID admit a basis and two different bases have the same number of elements, called the **rank** of the module.

Throughout this chapter, three notations will be used for vectors of polynomials in R_n . The usual n -tuple notation for $c(z) \in R_n$ will be used: $c(z) = (c_1(z), c_2(z), \dots, c_n(z))$ where $c_i(z) \in R$ for $1 \leq i \leq n$. Related, $c(z)$ will be written as the $1 \times n$ matrix $c(z) = [c_1(z) \ c_2(z) \ \cdots \ c_n(z)]$. The **degree** of

$c(z)$ is defined as $\deg(c(z)) = \max_{1 \leq i \leq n} \deg(c_i(z))$. The third more compact notation will be $c(z) = \sum_{i=0}^{\deg(c(z))} c_i z^i$ where $c_i \in \mathbb{F}_q^n$.

A **convolutional code** \mathcal{C} of **rate** k/n is an R -submodule of R^n of rank k . A $k \times n$ matrix $G(z)$ with entries in R whose rows constitute a basis of \mathcal{C} is called a **generator matrix** for \mathcal{C} .

Recall that a $k \times k$ matrix $U(z)$ with entries in R is called a **unimodular matrix** if there is a $k \times k$ matrix $V(z)$ with entries in R such that

$$U(z)V(z) = V(z)U(z) = I_k.$$

By Cramer's rule and elementary properties of determinants it follows that $U(z)$ is unimodular if and only if $\det(U(z)) \in \mathbb{F}_q^* := \mathbb{F}_q \setminus \{0\}$.

Assume that $G(z)$ and $\tilde{G}(z)$ are both generator matrices of the same code $\mathcal{C} = \text{rowspace}_R(G(z)) = \text{rowspace}_R(\tilde{G}(z))$. Then we immediately show that there is a unimodular matrix U such that

$$\tilde{G}(z) = U(z)G(z).$$

Note that this induces an equivalence relation on the set of the $k \times k$ generator matrices: $G(z)$ and $\tilde{G}(z)$ are **equivalent** if $\tilde{G}(z) = U(z)G(z)$ for some unimodular matrix $U(z)$. A canonical form for such an equivalence relation is the column Hermite form.

Definition 1.2.1 [12, 19] Let $G(z) \in \text{Mat}_{k,n}(R)$, with $k \leq n$. Then there exists a unimodular matrix $U(z) \in \text{Mat}_{k,k}(R)$ such that

$$\begin{aligned} H(z) &= U(z)G(z) \\ &= \begin{bmatrix} h_{11}(z) & h_{12}(z) & \cdots & h_{1k}(z) & h_{1,k+1}(z) & \cdots & h_{1n}(z) \\ & h_{22}(z) & \cdots & h_{2k}(z) & h_{2,k+1}(z) & \cdots & h_{2n}(z) \\ & & \ddots & \vdots & \vdots & & \vdots \\ & & & h_{kk}(z) & h_{k,k+1}(z) & \cdots & h_{kn}(z) \end{bmatrix} \end{aligned}$$

where $h_{ii}(z)$, $i = 1, 2, \dots, k$, are monic polynomials such that $\deg h_{ii} > \deg h_{ji}$, $j < i$. $H(z)$ is the (unique) **column Hermite form** of $G(z)$.

Other equivalence relations are induced by right multiplication with a unimodular matrix or by right and left multiplication with unimodular matrices. Canonical forms of such equivalence relations are the row Hermite form and the Smith form, respectively.

Definition 1.2.2 [12, 19] Let $G(z) \in \text{Mat}_{k,n}(R)$, with $k \leq n$. Then there exists a unimodular matrix $U(z) \in \text{Mat}_{n,n}(R)$ such that

$$\begin{aligned} H(z) &= G(z)U(z) \\ &= \begin{bmatrix} h_{11}(z) & & & 0 & 0 \\ h_{21}(z) & h_{22}(z) & & \vdots & \vdots \\ \vdots & \vdots & \ddots & \vdots & \vdots \\ h_{k1}(z) & h_{k2}(z) & \cdots & h_{kk}(z) & 0 \cdots 0 \end{bmatrix} \end{aligned}$$

where $h_{ii}(z)$, $i = 1, 2, \dots, k$, are monic polynomials such that $\deg h_{ii} > \deg h_{ij}$, $j < i$. $H(z)$ is the (unique) **row Hermite form** of $G(z)$.

Definition 1.2.3 [12, 19] Let $G(z) \in \text{Mat}_{k,n}(R)$, with $k \leq n$. Then there exist unimodular matrices $U(z) \in \text{Mat}_{k,k}(R)$ and $V(z) \in \text{Mat}_{n,n}(R)$ such that

$$\begin{aligned} S(z) &= U(z)G(z)V(z) \\ &= \begin{bmatrix} \gamma_1(z) & & & 0 & \cdots & 0 \\ & \gamma_2(z) & & \vdots & & \vdots \\ & & \ddots & \vdots & & \vdots \\ & & & \gamma_k(z) & 0 & 0 \end{bmatrix} \end{aligned}$$

where $\gamma_i(z)$, $i = 1, 2, \dots, k$, are monic polynomials such that $\gamma_{i+1}(z) | \gamma_i(z)$, $i = 1, 2, \dots, k-1$. These polynomials are uniquely determined by $G(z)$ and are called **invariant polynomials** of $G(z)$. $S(z)$ is the **Smith form** of $G(z)$.

Since two equivalent generator matrices differ by left multiplication with a unimodular matrix, they have equal $k \times k$ (full size) minors, up to multiplication by a constant. The maximal degree of the full size minors of a generator matrix (called its **internal degree**) of a convolutional code \mathcal{C} is called the **degree** (or **complexity**) of \mathcal{C} , and it is usually denoted by δ . A convolutional code of rate k/n and degree δ is also called an (n, k, δ) convolutional code. **Throughout this chapter** $L := \lfloor \frac{\delta}{k} \rfloor + \lfloor \frac{\delta}{n-k} \rfloor$.

For $i = 1, \dots, k$, the largest degree of any entry in row i of a matrix $G(z) \in \text{Mat}_{k,n}(R)$ is called the i -th **row degree** ν_i . It is obvious that if $G(z)$ is a generator matrix and $\nu_1, \nu_2, \dots, \nu_k$ are the row degrees of $G(z)$, then $\delta \leq \nu_1 + \nu_2 + \dots + \nu_k$. The sum of the row degrees of $G(z)$ is called its external degree. If the internal degree and the external degree coincide, $G(z)$ is said to be **row reduced** and it is called a **minimal** generator matrix. Thus, the degree of the code can be equivalently defined as the external degree of a minimal generator matrix of \mathcal{C} .

Lemma 1.2.4 [8, 19] Let $G(z) = [g_{ij}(z)] \in \text{Mat}_{k,n}(R)$ with row degrees $\nu_1, \nu_2, \dots, \nu_k$ and $[G]_{hr}$ be the highest row degree coefficient matrix defined as the matrix with the i -th row consisting of the coefficients of z^{ν_i} in the i -th row of $G(z)$. Then $\delta = \nu_1 + \nu_2 + \dots + \nu_k$ if and only if $[G]_{hr}$ is full row rank.

Let $G(z)$ be a row reduced generator matrix with row degrees $\nu_1, \nu_2, \dots, \nu_k$ and $c(z) = u(z)G(z)$ where $u(z) = \begin{bmatrix} u_1(z) & u_2(z) & \cdots & u_k(z) \end{bmatrix} \in R^k$. Obviously, $\deg c(z) \leq \max_{i: u_i(z) \neq 0} \{\nu_i + \deg u_i(z)\}$. Let $\Lambda = \max_{i: u_i(z) \neq 0} \{\nu_i + \deg u_i(z)\}$ and write $u_i(z) = \alpha_i z^{\Lambda - \nu_i} + r_i(z)$ with $\deg r_i(z) < \Lambda - \nu_i$, $i = 1, 2, \dots, k$. Then

$$c(z) = \left(\begin{bmatrix} \alpha_1 z^{\Lambda-\nu_1} & \alpha_2 z^{\Lambda-\nu_2} & \cdots & \alpha_k z^{\Lambda-\nu_k} \end{bmatrix} + \begin{bmatrix} r_1(z) & r_2(z) & \cdots & r_k(z) \end{bmatrix} \right) \times \left(\begin{bmatrix} z^{\nu_1} & & & \\ & z^{\nu_2} & & \\ & & \ddots & \\ & & & z^{\nu_k} \end{bmatrix} [G]_{hr} + G_{rem}(z) \right),$$

where $G_{rem}(z) \in Mat_{k,n}(R)$ has the i -th row degree smaller than ν_i , $i = 1, 2, \dots, k$. The coefficient of $c(z)$ of degree Λ is given by $c_\Lambda = \begin{bmatrix} \alpha_1 & \alpha_2 & \cdots & \alpha_k \end{bmatrix} [G]_{hr}$ which is different from zero since $\alpha_i \neq 0$ for some $i \in \{1, 2, \dots, k\}$ and $[G]_{hr}$ is full row rank, i.e.,

$$\deg c(z) = \max_{i: u_i(z) \neq 0} \{\nu_i + \deg u_i(z)\}. \quad (1.1)$$

Equality (1.1) is called the **predictable degree property** and it is an equivalent characterization of the row reduced matrices [8, 19].

Given a generator matrix $G(z)$, there always exists a row reduced generator matrix equivalent to $G(z)$ [19]. That is, all convolutional codes admit minimal generator matrices. If $G_1(z)$ and $G_2(z)$ are two equivalent generator matrices, each row of $G_1(z)$ belongs to the image of $G_2(z)$ and vice-versa. Then, if $G_1(z)$ and $G_2(z)$ are row reduced matrices, the predictable degree property implies that $G_1(z)$ and $G_2(z)$ have the same row degrees, up to row permutation.

Another important property of polynomial matrices is left (or right) primeness.

Definition 1.2.5 A polynomial matrix $G(z) \in Mat_{k,n}(R)$, with $k \leq n$ is **left prime** if in all factorizations

$$G(z) = \Delta(z) \overline{G}(z), \text{ with } \Delta(z) \in Mat_{k,k}(R), \text{ and } \overline{G}(z) \in Mat_{k,n}(R),$$

the left factor $\Delta(z)$ is unimodular.

Left prime matrices admit several very useful characterizations. Some of these characterizations are presented in the next theorem.

Theorem 1.2.6 [19] Let $G(z) \in Mat_{k,n}(R)$, with $k \leq n$. The following are equivalent:

1. $G(z)$ is left prime;
2. the Smith form of $G(z)$ is $[I_k \ 0]$;
3. the row Hermite form of $G(z)$ is $[I_k \ 0]$;
4. $G(z)$ admits a right $n \times k$ polynomial inverse;

5. $G(z)$ can be completed to a unimodular matrix, i.e., there exists $L(z) \in \text{Mat}_{n-k,n}(R)$ such that $\begin{bmatrix} G(z) \\ L(z) \end{bmatrix}$ is unimodular.
6. the ideal generated by all the k -th order minors of $G(z)$ is R .
7. for all $u(z) \in \mathbb{F}_q(z)^k$, $u(z)G(z) \in R^n$ implies that $u(z) \in R^k$.
8. $\text{rank } G(\lambda) = k$ for all $\lambda \in \overline{\mathbb{F}}_q$, where $\overline{\mathbb{F}}_q$ denotes the algebraic closure of \mathbb{F}_q .

Since generator matrices of a convolutional code \mathcal{C} differ by left multiplication with a unimodular matrix, it follows that if a convolutional code admits a left prime generator matrix then all its generator matrices are also left prime. We call such codes **noncatastrophic** convolutional codes.

Example 1.2.7 Let us consider the binary field, i.e., $q = 2$. The convolutional code \mathcal{C} of rate $2/3$ with generator matrix

$$G(z) = \begin{bmatrix} 1 & 1 & z \\ z^2 & 1 & z+1 \end{bmatrix}$$

is noncatastrophic, since $G(z)$ is left prime. In fact, $G(z)$ admits the right polynomial inverse $\begin{bmatrix} 0 & 0 \\ z+1 & z \\ 1 & 1 \end{bmatrix}$. The highest coefficient matrix of $G(z)$, $[G]_{hr}$, is full row rank and, consequently, $G(z)$ is row reduced. The degree of \mathcal{C} is then equal to the sum of the row degrees of $G(z)$, which is 3. Therefore \mathcal{C} is a $(3, 2, 3)$ binary convolutional code.

On the other hand, the convolutional code $\tilde{\mathcal{C}}$ with generator matrix

$$\tilde{G}(z) = \begin{bmatrix} 1+z & 1 \\ 0 & 1 \end{bmatrix} G(z) = \begin{bmatrix} 1+z+z^2 & z & 1+z^2 \\ z^2 & 1 & z+1 \end{bmatrix}$$

is a catastrophic convolutional code contained in \mathcal{C} as the first equality of the preceding equation implies $\text{rowspan}_R \tilde{G}(z) \subset \text{rowspan}_R G(z)$. The matrix $[\tilde{G}]_{hr} = \begin{bmatrix} 1 & 0 & 1 \\ 1 & 0 & 0 \end{bmatrix}$ has full row rank 2, making $\tilde{G}(z)$ row reduced, and implying that the degree of $\tilde{\mathcal{C}}$ is $2+2=4$. Hence $\tilde{\mathcal{C}}$ is $(3, 2, 4)$ convolutional subcode of \mathcal{C} .

Let \mathcal{C} be a noncatastrophic convolutional code and $G(z) \in \text{Mat}_{k,n}(R)$ be a generator matrix of \mathcal{C} . By Theorem 1.2.6, there exists a polynomial matrix $N(z) \in \text{Mat}_{n-k,n}(R)$ such that $\begin{bmatrix} G(z) \\ N(z) \end{bmatrix}$ is unimodular. Let $L(z) \in \text{Mat}_{k,n}(R)$ and $H(z) \in \text{Mat}_{n-k,n}(R)$ such that

$$\begin{bmatrix} G(z) \\ N(z) \end{bmatrix} \begin{bmatrix} L(z)^T & H(z)^T \end{bmatrix} = I_n. \quad (1.2)$$

One immediately sees that

$$c(z) \in \mathcal{C} \Leftrightarrow H(z)c(z)^T = \mathbf{0}.$$

$H(z)$ is called a **parity-check matrix** of \mathcal{C} , analogous to the block code case.

It was shown that if a convolutional code is noncatastrophic, then it admits a parity-check matrix. But the converse is also true.

Theorem 1.2.8 [44] Let \mathcal{C} be a convolutional code of rate k/n . Then there exists a full row rank polynomial matrix $H(z) \in \text{Mat}_{n-k,n}(R)$ such that

$$\begin{aligned} \mathcal{C} &= \ker H(z) \\ &= \{c(z) \in R^n : H(z)c(z)^T = \mathbf{0}\}, \end{aligned}$$

i.e. a **parity-check matrix** of \mathcal{C} , if and only if \mathcal{C} is noncatastrophic.

Proof: Let us assume that \mathcal{C} admits a parity-check matrix $H(z) \in \text{Mat}_{n-k,n}(R)$ and let us write $H(z) = X(z)\tilde{H}(z)$, where $X(z) \in \text{Mat}_{n-k,n-k}(R)$ is full rank and $\tilde{H}(z) \in \text{Mat}_{n-k,n}(R)$ is left prime. Then there exists a matrix $L(z) \in \text{Mat}_{k,n}(R)$ such that $\begin{bmatrix} L(z)^T & \tilde{H}(z)^T \end{bmatrix}$ is unimodular and therefore

$$\begin{bmatrix} G(z) \\ N(z) \end{bmatrix} \begin{bmatrix} L(z)^T & \tilde{H}(z)^T \end{bmatrix} = I_n,$$

for some left prime matrices $N(z) \in \text{Mat}_{n-k,n}(R)$ and $G(z) \in \text{Mat}_{k,n}(R)$. Then $\tilde{H}(z)G(z)^T = 0$ and consequently also $H(z)G(z)^T = 0$. It is clear that $\mathcal{C} = \text{rowspace}_R G(z)$ and therefore \mathcal{C} is noncatastrophic. \square

Remark 1.2.9 If $\tilde{\mathcal{C}}$ is catastrophic (i.e., its generator matrices are not left prime), we can still obtain a right prime matrix $H(z) \in \text{Mat}_{n-k,n}(R)$ such that $\tilde{\mathcal{C}} \subsetneq \ker_R H(z)$. If $\tilde{G}(z)$ is a generator matrix of $\tilde{\mathcal{C}}$, we can write $\tilde{G}(z) = [\Delta(z) \ 0]U(z)$ with $\Delta(z) \in \text{Mat}_{k,k}(R)$ and where $[\Delta(z) \ 0]$, is the row Hermite form of $\tilde{G}(z)$ and $U(z)$ is a unimodular matrix. Then $\tilde{G}(z) = \Delta(z)U_1(z)$, where $U_1(z)$ is the submatrix of $U(z)$ constituted by its first k rows. This means, by Theorem 1.2.6, that $U_1(z)$ is left prime. The matrix $H(z)$ is a parity-check matrix of the convolutional code $\tilde{\mathcal{C}} = \text{rowspace}_R U_1(z)$ and $\tilde{\mathcal{C}} \subsetneq \mathcal{C}$.

Example 1.2.10 Consider the convolutional codes \mathcal{C} and $\tilde{\mathcal{C}}$ considered in Example 1.2.7. The matrix $H(z) = \begin{bmatrix} 1 & 1+z+z^3 & 1+z^2 \end{bmatrix}$ is a parity-check matrix of \mathcal{C} .

Since $\tilde{\mathcal{C}}$ is catastrophic, it does not admit a parity-check matrix. However, since $\tilde{\mathcal{C}} \subsetneq \mathcal{C}$, it follows that $\tilde{\mathcal{C}} \subsetneq \ker H(z)$.

Given a noncatastrophic code \mathcal{C} , we define the **dual** of \mathcal{C} as

$$\mathcal{C}^\perp = \{y(z) \in R^n : y(z)c(z)^T = 0 \text{ for all } c(z) \in \mathcal{C}\}.$$

The dual of a noncatastrophic convolutional code is also noncatastrophic. The left prime parity-check matrices of \mathcal{C} are the generator matrices of \mathcal{C}^\perp and vice-versa. The degree of a noncatastrophic code and its dual are the same. This result is a consequence of the following lemma and Theorem 1.2.6, part 6.

Lemma 1.2.11 [8] Let $H(z) \in \text{Mat}_{n-k,k}(R)$ and $G(z) \in \text{Mat}_{k,n}(R)$ be a left prime parity-check matrix and a generator matrix of a noncatastrophic convolutional code, respectively. Given a full size minor of $G(z)$ constituted by the columns i_1, i_2, \dots, i_k , let us define the complementary full size minor of $H(z)$ as the minor constituted by the complementary columns i.e., by the columns $\{1, 2, \dots, n\} \setminus \{i_1, i_2, \dots, i_k\}$.

Then the full size minors of $G(z)$ are equal to the complementary full size minors of $H(z)$, up to multiplication by a nonzero constant.

Proof: For simplicity, let us consider $i_1 = 1, i_2 = 2, \dots, i_k = k$ i.e., the full size minor of $G(z)$, $M_1(G)$, constituted by the first k columns:

$$M_1(G) = \det \begin{bmatrix} G(z) \\ \mathbf{0}_{n-k,k} & I_{n-k} \end{bmatrix}.$$

Then, considering $L(z)$ as in (1.2), we have that

$$\begin{bmatrix} G(z) \\ \mathbf{0}_{n-k,k} & I_{n-k} \end{bmatrix} \begin{bmatrix} L^T(z) & H^T(z) \end{bmatrix} = \begin{bmatrix} I_k & \mathbf{0}_{k,n-k} \\ Q(z) & \tilde{H}(z) \end{bmatrix} \quad (1.3)$$

where $Q(z) \in \text{Mat}_{n-k,k}(R)$ and $\tilde{H}(z)$ is the submatrix of $H(z)$ constituted by its last $n - k$ columns, i.e., $\overline{M}_1(H) = \det \tilde{H}(z)$ is the complementary minor to $M_1(G)$ and from (1.3) we conclude that $M_1(G) = \alpha \overline{M}_1(H)$, where $\alpha = \det \begin{bmatrix} L^T(z) & H^T(z) \end{bmatrix}$ belongs to \mathbb{F}_q^* . Applying the same reasoning we conclude that all the full size minors of $G(z)$ are equal to α times the complementary full size minors of $H(z)$. \square

Therefore if $G(z)$ is a generator matrix and $H(z)$ is a parity-check matrix of a noncatastrophic convolutional code \mathcal{C} , they have the same maximal degree of the full size minors, which means that \mathcal{C} and \mathcal{C}^\perp have the same degree.

1.2.2 Distances of Convolutional Codes

The distance of a code is an important measure of robustness of the code since it provides a means to assess its capability to protect data from errors. Several types of distance can be defined for convolutional codes. We will consider the free distance and the column distances. To define these notions, one first has to define the distance between polynomial vectors.

Definition 1.2.12 The **(Hamming) weight** $wt(c)$ of $c \in \mathbb{F}_q^n$ is defined as the number of nonzero components of c and the **weight** of a polynomial

vector $c(z) = \sum_{t=0}^{\deg(c(z))} c_t z^t \in R^n$ is defined as $wt(c(z)) = \sum_{t=0}^{\deg(c(z))} wt(c_t)$. The **(Hamming) distance** between $c_1, c_2 \in \mathbb{F}_q^n$ is defined as $d(c_1, c_2) = wt(c_1 - c_2)$; correspondingly the **distance** between $c_1(z), c_2(z) \in R^n$ is defined as $d(c_1(z), c_2(z)) = wt(c_1(z) - c_2(z))$,

Definition 1.2.13 The **free distance** of a convolutional code \mathcal{C} is given by

$$d_{free}(\mathcal{C}) := \min_{c_1(z), c_2(z) \in \mathcal{C}} \{d(c_1(z), c_2(z)) \mid c_1(z) \neq c_2(z)\}$$

During transmission of information over a q -ary symmetric channel, errors may occur, i.e. information symbols can be exchanged by other symbols in \mathbb{F}_q in a symmetric way.

After channel transmission, a convolutional code \mathcal{C} can detect up to s errors in any received word $w(z)$ if $d_{free}(\mathcal{C}) \geq s + 1$ and can correct up to t errors in $w(z)$ if $d_{free}(\mathcal{C}) \geq 2t + 1$, which gives the following theorem.

Theorem 1.2.14 Let \mathcal{C} be a convolutional code with free distance d . Then \mathcal{C} can always detect $d - 1$ errors and correct $\lfloor \frac{d-1}{2} \rfloor$ errors.

As convolutional codes are linear, the difference between two codewords is also a codeword which gives the following equivalent definition of free distance.

Lemma 1.2.15 The free distance of a convolutional code \mathcal{C} is given by

$$d_{free}(\mathcal{C}) := \min_{c(z) \in \mathcal{C}} \left\{ \sum_{t=0}^{\deg(c(z))} wt(c_t) \mid c(z) \neq \mathbf{0} \right\}.$$

Example 1.2.16 Consider the convolutional code \mathcal{C} defined in Example 1.2.7. Since $\begin{bmatrix} 1 & 1 & z \end{bmatrix}$ is a codeword of \mathcal{C} with weight 3, it follows that

$d_{free}(\mathcal{C}) \leq 3$. On the other hand any nonzero codeword of \mathcal{C} , $w(z) = \sum_{i=\ell_0}^{\ell_1} w_i z^i$,

with $\ell_0, \ell_1 \in \mathbb{N}_0$ such that $w_{\ell_0} \neq 0$ and $w_{\ell_1} \neq 0$, is such that $w_{\ell_0} \in \text{rowspace}_R G(0)$ and consequently it has weight 2 or 3. Moreover, the predictable degree property of $G(z)$ implies that $\ell_1 > \ell_0$ and therefore $w(z)$ must have weight greater or equal than 3. Hence, we conclude that \mathcal{C} has free distance 3.

Besides the free distance, convolutional codes also possess another notion of distance, the so-called column distances. These distances have an important role for transmission of information over an erasure channel, which is a suitable model for many communication channels, in particular packet switched networks such as the internet. In this kind of channel, each symbol either arrives correctly or does not arrive at all, and it is called an erasure. In Section 1.5.1 the decoding over these type of channels will be analyzed in detail.

Column distances have important characterizations in terms of the generator matrices of the code, but also in terms of its parity-check matrices if the code is noncatastrophic. For this reason, we will consider throughout this section noncatastrophic convolutional codes.

Definition 1.2.17 For $c(z) \in R^n$ with $\deg(c(z)) = \gamma$, write $c(z) = c_0 + \cdots + c_\gamma z^\gamma$ with $c_t \in \mathbb{F}_q^n$ for $t = 0, \dots, \gamma$ and set $c_t = \mathbf{0} \in \mathbb{F}_q^n$ for $t \geq \gamma + 1$. We define the **j-th truncation** of $c(z)$ as $c_{[0,j]}(z) = c_0 + c_1 z + \cdots + c_j z^j$.

Definition 1.2.18 [14] For $j \in \mathbb{N}_0$, the **j-th column distance** of a convolutional code \mathcal{C} is defined as

$$d_j^c(\mathcal{C}) := \min_{c(z) \in \mathcal{C}} \{wt(c_{[0,j]}(z)) \mid c_0 \neq \mathbf{0}\}.$$

Let $G(z) = \sum_{i=0}^{\mu} G_i z^i \in \text{Mat}_{k,n}(R)$ and $H(z) = \sum_{i=0}^{\nu} H_i z^i \in \text{Mat}_{n-k,n}(R)$ be a generator matrix and a parity-check matrix, respectively, of the convolutional code \mathcal{C} . Note that $G_i \in \text{Mat}_{k,n}(\mathbb{F}_q)$ and $H_i \in \text{Mat}_{n-k,n}(\mathbb{F}_q)$. For $j \in \mathbb{N}_0$, define the **truncated sliding generator matrices** $G_j^c \in \text{Mat}_{(j+1)k, (j+1)n}(\mathbb{F}_q)$ and the **truncated sliding parity-check matrices** $H_j^c \in \text{Mat}_{(j+1)(n-k), (j+1)n}(\mathbb{F}_q)$ as

$$G_j^c := \begin{bmatrix} G_0 & G_1 & \cdots & G_j \\ & G_0 & \cdots & G_{j-1} \\ & & \ddots & \vdots \\ & & & G_0 \end{bmatrix} \quad \text{and} \quad H_j^c := \begin{bmatrix} H_0 & & & \\ H_1 & H_0 & & \\ \vdots & \vdots & \ddots & \\ H_j & H_{j-1} & \cdots & H_0 \end{bmatrix}.$$

Then if $c(z) = \sum_{i \in \mathbb{N}_0} c_i z^i$ is a codeword of \mathcal{C} , it follows that

$$[c_0 \ c_1 \ \cdots \ c_j] = [u_0 \ u_1 \ \cdots \ u_j] G_j^c \quad \text{for some } u_0, u_1, \dots, u_j \in \mathbb{F}_q^k \quad (1.4)$$

$$\text{and} \quad H_j^c [c_0 \ \dots \ c_j]^\top = \mathbf{0}.$$

Note that since $G(z)$ is left prime, G_0 has full row rank and therefore, $c_0 \neq \mathbf{0}$ in (1.4) if and only if $u_0 \neq \mathbf{0}$. Consequently,

$$d_j^c(\mathcal{C}) = \min_{u_0 \neq \mathbf{0}} \{wt([u_0 \ \cdots \ u_j] G_j^c)\} = \min_{c_0 \neq \mathbf{0}} \{wt(c_{[0,j]}(z)) \mid H_j^c [c_0 \ \dots \ c_j]^\top = \mathbf{0}\}$$

and one has the following theorem.

Theorem 1.2.19 [14] For $d \in \mathbb{N}$ the following statements are equivalent:

- (a) $d_j^c(\mathcal{C}) = d$
- (b) None of the first n columns of H_j^c is contained in the span of any other $d-2$ columns and one of the first n columns is contained in the span of some other $d-1$ columns of that matrix.

Example 1.2.20 The convolutional code \mathcal{C} defined in Example 1.2.7 has column distances $d_0^c(\mathcal{C}) = \min_{u_0 \neq \mathbf{0}} \{wt(u_0 G_0^c)\} = 2$ and, for $j \geq 1$,

$$\begin{aligned} d_j^c(\mathcal{C}) &= \min_{u_0 \neq \mathbf{0}} \{wt([u_0 \cdots u_j] G_j^c)\} \\ &= wt([u_0 \cdots u_j] G_j^c) = 3, \text{ for } u_0 = [1 \ 0], u_1 = u_2 = \cdots = u_j = 0. \end{aligned}$$

As for block codes, there exist upper bounds for the distances of convolutional codes.

Theorem 1.2.21 [35][14] Let \mathcal{C} be an (n, k, δ) convolutional code. Then,

- (i) $d_{free}(\mathcal{C}) \leq (n - k) \left(\left\lfloor \frac{\delta}{k} \right\rfloor + 1 \right) + \delta + 1$
- (ii) $d_j^c(\mathcal{C}) \leq (n - k)(j + 1) + 1$ for all $j \in \mathbb{N}_0$

The bound in (i) of the preceding theorem is called the **generalized Singleton bound** since for $\delta = 0$ one gets the Singleton bound for block codes.

An (n, k, δ) convolutional code \mathcal{C} such that

$$d_{free}(\mathcal{C}) = (n - k) \left(\left\lfloor \frac{\delta}{k} \right\rfloor + 1 \right) + \delta + 1$$

is called a **maximum distance separable (MDS)** code [35]. In [35] it was proved that an (n, k, δ) convolutional code always exist over a sufficiently large field. In Section 1.3.1, constructions of such codes are presented.

The generalized Singleton bound has implications on the values that the column distances can achieve. Note that $0 \leq d_0 \leq d_1 \leq \cdots \leq d_{free}$ and $d_{free}(\mathcal{C}) = \lim_{j \rightarrow \infty} d_j^c(\mathcal{C})$, which implies $d_j^c(\mathcal{C}) \leq (n - k) \left(\left\lfloor \frac{\delta}{k} \right\rfloor + 1 \right) + \delta + 1$ for all $j \in \mathbb{N}_0$. Hence $j = L := \left\lfloor \frac{\delta}{k} \right\rfloor + \left\lfloor \frac{\delta}{n - k} \right\rfloor$ is the largest possible value of j for which $d_j^c(\mathcal{C})$ can attain the upper bound in (ii) of the preceding theorem. Moreover, the following lemma shows that maximal j -th column distance implies maximal column distance of all previous ones.

Lemma 1.2.22 [14] Let \mathcal{C} be an (n, k, δ) convolutional code. If $d_j^c(\mathcal{C}) = (n - k)(j + 1) + 1$ for some $j \in \{1, \dots, L\}$, then $d_i^c(\mathcal{C}) = (n - k)(i + 1) + 1$ for all $i \leq j$.

Definition 1.2.23 [14] An (n, k, δ) convolutional code \mathcal{C} is said to be **maximum distance profile (MDP)** if

$$d_j^c(\mathcal{C}) = (n - k)(j + 1) + 1 \quad \text{for } j = 0, \dots, L = \left\lfloor \frac{\delta}{k} \right\rfloor + \left\lfloor \frac{\delta}{n - k} \right\rfloor.$$

Lemma 1.2.22 shows that it is sufficient to have equality for $j = L$ in part (ii) of Theorem 1.2.21 to get an MDP convolutional code.

A convolutional code \mathcal{C} where $d_j^c(\mathcal{C})$ meets the generalized Singleton bound

for the smallest possible value of j is called **strongly maximum distance separable (sMDS)**. Note that either $j = L$ or $j = L + 1$. More precisely, an (n, k, δ) convolutional code is sMDS if

$$d_M^c(\mathcal{C}) = (n - k) \left(\left\lfloor \frac{\delta}{k} \right\rfloor + 1 \right) + \delta + 1 \quad \text{where} \quad M := \left\lfloor \frac{\delta}{k} \right\rfloor + \left\lceil \frac{\delta}{n - k} \right\rceil.$$

The next remark points out the relationship between MDP, MDS and strongly MDS convolutional codes.

Remark 1.2.24 [16] (i) Each sMDS code is an MDS code.
(ii) If $n - k$ divides δ , an (n, k, δ) convolutional code \mathcal{C} is MDP if and only if it is sMDS.

In the following, we will provide criteria to check whether a convolutional code is MDP.

Theorem 1.2.25 [14] Let \mathcal{C} be a convolutional code with generator matrix $G(z) = \sum_{i=0}^{\mu} G_i z^i \in \text{Mat}_{k,n}(R)$ and with left prime parity-check matrix $H(z) = \sum_{i=0}^{\nu} H_i z^i \in \text{Mat}_{n-k,n}(R)$. The following statements are equivalent:

(a) \mathcal{C} is MDP.

(b) $\mathcal{G}_L := \begin{bmatrix} G_0 & \dots & G_L \\ & \ddots & \vdots \\ 0 & & G_0 \end{bmatrix}$ where $G_i = 0$ for $i > \mu$ has the property that every full size minor that is formed by rows with indices $1 \leq j_1 < \dots < j_{(L+1)k} \leq (L+1)n$ which fulfill $j_{sk} \leq sn$ for $s = 1, \dots, L$ is nonzero.

(c) $\mathcal{H}_L := \begin{bmatrix} H_0 & & 0 \\ \vdots & \ddots & \\ H_L & \dots & H_0 \end{bmatrix}$ where $H_i = 0$ for $i > \nu$ has the property that every full size minor that is formed by columns with indices $1 \leq j_1 < \dots < j_{(L+1)(n-k)} \leq (L+1)n$ which fulfill $j_{s(n-k)} \leq sn$ for $s = 1, \dots, L$ is nonzero.

The property of being an MDP convolutional code is invariant under duality as shown in the following theorem.

Theorem 1.2.26 [14] An (n, k, δ) convolutional code is MDP if and only if its dual code, which is an $(n, n - k, \delta)$ convolutional code, is MDP.

MDP convolutional codes are very efficient for decoding over the erasure channel. Next we introduce two special classes of MDP convolutional codes, the reverse MDP convolutional codes and the complete MDP convolutional codes, which are specially suited to deal with particular patterns of erasures. Section 1.5.1 is devoted to decoding over this channel, and the decoding capabilities of these codes will be analyzed in more detail.

Definition 1.2.27 [15] Let \mathcal{C} be an (n, k, δ) convolutional code with left prime row reduced generator matrix $G(z)$, which has entries $g_{ij}(z)$. Set $\bar{g}_{ij}(z) := z^{\nu_i} g_{ij}(z^{-1})$ where ν_i is the i -th row degree of $G(z)$. Then, the code $\bar{\mathcal{C}}$ with generator matrix $\bar{G}(z)$, which has $\bar{g}_{ij}(z)$ as entries, is also an (n, k, δ) convolutional code, which is called the **reverse code** to \mathcal{C} . It holds: $v_0 + \dots + v_d z^d \in \bar{\mathcal{C}} \Leftrightarrow v_d + \dots + v_0 z^d \in \mathcal{C}$.

Definition 1.2.28 [39] Let \mathcal{C} be an MDP convolutional code. If $\bar{\mathcal{C}}$ is also MDP, \mathcal{C} is called a **reverse MDP** convolutional code.

Remark 1.2.29 [39] Let \mathcal{C} be an (n, k, δ) MDP convolutional code such that $(n - k) \mid \delta$ and $H(z) = H_0 + \dots + H_\nu z^\nu$, with $H_\nu \neq 0$, be a left prime and row reduced parity-check matrix of \mathcal{C} . Then the reverse code $\bar{\mathcal{C}}$ has parity-check matrix $\bar{H}(z) = H_\nu + \dots + H_0 z^\nu$. Moreover, \mathcal{C} is reverse MDP if and only if every full size minor of the matrix

$$\mathfrak{H}_L := \begin{bmatrix} H_\nu & \cdots & H_{\nu-L} \\ & \ddots & \vdots \\ 0 & & H_\nu \end{bmatrix}$$

formed from the columns with indices $j_1, \dots, j_{(L+1)(n-k)}$ with $j_{s(n-k)+1} > sn$, for $s = 1, \dots, L$ is nonzero.

Theorem 1.2.30 [39] An (n, k, δ) reverse MDP convolutional code exists over a sufficiently large base field.

Definition 1.2.31 [39] Let $H(z) = H_0 + H_1 z + \dots + H_\nu z^\nu \in \text{Mat}_{n-k, n}(R)$, with $H_\nu \neq 0$, be a left prime and row reduced parity-check matrix of the (n, k, δ) convolutional code \mathcal{C} . Set $L = \lfloor \frac{\delta}{n-k} \rfloor + \lfloor \frac{\delta}{k} \rfloor$. Then

$$\mathfrak{H} := \begin{pmatrix} H_\nu & \cdots & H_0 & & 0 \\ & \ddots & & \ddots & \\ 0 & & H_\nu & \cdots & H_0 \end{pmatrix} \in \text{Mat}_{(L+1)(n-k), (\nu+L+1)n}(\mathbb{F}_q) \quad (1.5)$$

is called a **partial parity check matrix** of the code. Moreover, \mathcal{C} is called a **complete MDP** convolutional code if every full size minor of \mathfrak{H} that is formed by columns $j_1, \dots, j_{(L+1)(n-k)}$ with $j_{(n-k)s+1} > sn$ and $j_{(n-k)s} \leq sn + \nu n$ for $s = 1, \dots, L$ is nonzero.

Remark 1.2.32 (i) Every complete MDP convolutional code is a reverse MDP convolutional code. [39]

(ii) A complete (n, k, δ) MDP convolutional code exists over a sufficiently large base field if and only if $(n - k) \mid \delta$. [22]

1.3 Constructions of Codes with Optimal Distance

1.3.1 Constructions of MDS convolutional codes

In this section, we will present the most important known constructions for MDS convolutional codes. They differ in the constraints on the parameters and the necessary field size. The first two constructions that will be considered are for convolutional codes with rate $1/n$. The following theorem gives the first construction of MDS convolutional codes.

Theorem 1.3.1 [18] For $n \geq 2$ and $|\mathbb{F}_q| \geq n+1$, set $s_j := \lceil (j-1)(|\mathbb{F}_q|-1)/n \rceil$ for $j = 2, \dots, n$ and $\delta := \begin{cases} \lfloor \frac{2}{9} |\mathbb{F}_q| \rfloor, & n = 2 \\ \lfloor \frac{1}{3} |\mathbb{F}_q| \rfloor, & 3 \leq n \leq 5 \\ \lfloor \frac{1}{2} |\mathbb{F}_q| \rfloor, & n \geq 6 \end{cases}$. Moreover, let α be a primitive element of \mathbb{F}_q and set $g_1(x) := \prod_{k=1}^{\delta} (x - \alpha^k)$, $g_j(x) := g_1(x\alpha^{-s_j})$. Then $G(z) = [g_1(z) \cdots g_n(z)]$ is the generator matrix of an $(n, 1, \delta)$ MDS convolutional code with free distance equal to $n(\delta + 1)$.

The second construction works for the same field size as the first one but contains a restriction on the degree of the code, which is different from the restriction on the degree in the first construction.

Theorem 1.3.2 [13] Let $|\mathbb{F}_q| \geq n+1$, $0 \leq \delta \leq n-1$ and α be an element of \mathbb{F}_q with order at least n . Then $G(z) := \sum_{i=0}^{\delta} z^i [1 \ \alpha \ \alpha^2 \cdots \alpha^{(n-1)i}]$ generates an $(n, 1, \delta)$ MDS convolutional code.

Finally, we present a construction that works for arbitrary parameters but has a stronger restriction on the field size.

Theorem 1.3.3 [37] Let a, r be integers such that $a \geq \lfloor \frac{\delta}{k} \rfloor + 1 + \frac{\delta}{n-k}$ and $an = p^r - 1$. Let α be a primitive element of \mathbb{F}_{p^r} . Set $N = an$, $K = N - (n-k)(\lfloor \frac{\delta}{k} \rfloor + 1) - \delta$, $g(z) = (z - \alpha^0)(z - \alpha^1) \cdots (z - \alpha^{N-K-1})$ and write $g(z) = g_0(z^n) + g_1(z^n)z + \cdots + g_{n-1}(z^n)z^{n-1}$. Then

$$G(z) = \begin{bmatrix} g_0(z) & g_1(z) & \cdots & g_{n-1}(z) \\ zg_{n-1}(z) & g_0(z) & \cdots & g_{n-2}(z) \\ \vdots & \ddots & & \vdots \\ zg_{n-k}(z) & \cdots & \cdots & g_{n-k}(z) \end{bmatrix}$$

is the generator matrix of an (n, k, δ) MDS convolutional code.

1.3.2 Constructions of MDP convolutional codes

MDP convolutional codes can be constructed by selecting appropriate columns and rows of so-called superregular matrices, which we define in the following.

Definition 1.3.4 (i) Let $l \in \mathbb{N}$ and $A = [a_{ij}]$ be a matrix in $\text{Mat}_{l,l}(\mathbb{F}_q)$. Define $\bar{a} = [\bar{a}_{ij}]$ where $\bar{a}_{ij} = 0$ if $a_{ij} = 0$ and $\bar{a}_{ij} = x_{ij}$ if $a_{ij} \neq 0$ and consider the determinant of \bar{A} as an element of the ring of polynomials in the variables x_{ij} , $i, j \in \{1, \dots, l\}$ and with coefficients in \mathbb{F}_q . One calls the determinant of A **trivially zero** if the determinant of \bar{A} is equal to the zero polynomial.

A is called **superregular** if all its not trivially zero minors are nonzero.

(ii) A Toeplitz matrix of the form $\begin{pmatrix} a_1 & & 0 \\ \vdots & \ddots & \\ a_l & \dots & a_1 \end{pmatrix}$ with $a_i \in \mathbb{F}_q$ for $i = 1, \dots, l$ that is superregular is called a **lower triangular superregular matrix**.

In the following, we present two constructions for (n, k, δ) MDP convolutional codes using superregular matrices of different shapes.

For the first construction, which is presented in the following theorem, it is required to have $(n - k) \mid \delta$ and $k > \delta$, i.e. $L = \frac{\delta}{n-k}$.

Theorem 1.3.5 [39] Let $(n - k) \mid \delta$, $k > \delta$ and T be an $r \times r$ lower triangular superregular matrix with $r = (L + 1)(2n - k - 1)$.

For $j = 0, \dots, L$, let I_j and J_j be the following sets:

$$I_j = \{(j + 1)n + j(n - k - 1), \dots, (j + 1)(2n - k - 1)\},$$

$$J_j = \{jn + j(n - k - 1) + 1, \dots, (j + 1)n + j(n - k - 1)\},$$

and let $I = \bigcup_{j=0}^L I_j$ and $J = \bigcup_{j=0}^L J_j$. Form $\mathcal{H}_L = \begin{bmatrix} H_0 & & 0 \\ \vdots & \ddots & \\ H_L & \dots & H_0 \end{bmatrix}$ taking

the rows and columns of T with indices in I and J , respectively. Then $H(z) = \sum_{i=0}^L H_i z^i$ is the parity check matrix of an MDP convolutional code.

The construction of the preceding theorem could be explained in the following way:

Step 1: Construct the lower triangular superregular matrix T .

Step 2: Partition T in $L + 1$ blocks with $2n - k - 1$ rows each and delete the first $n - 1$ rows in each block. Define \hat{T} as the matrix consisting of the remaining rows.

Step 3: Partition \hat{T} in $L + 1$ blocks with $2n - k - 1$ columns each and delete the first $n - k - 1$ columns in each block. Define \mathcal{H}_L as the matrix consisting of the remaining columns.

The following theorem provides a general construction for such a superregular matrix if the characteristic of the underlying field is sufficiently large.

Theorem 1.3.6 [14] For every $b \in \mathbb{N}$ the not trivially zero minors of the

$$\text{Toeplitz matrix} \begin{bmatrix} 1 & 0 & \cdots & \cdots & 0 \\ \binom{b}{1} & \ddots & \ddots & & \vdots \\ \vdots & \ddots & \ddots & \ddots & \vdots \\ \binom{b}{b-1} & & \ddots & \ddots & 0 \\ 1 & \binom{b}{b-1} & \cdots & \binom{b}{1} & 1 \end{bmatrix} \in \text{Mat}_{b,b}(\mathbb{Z}) \text{ are all positive.}$$

Hence for each $b \in \mathbb{N}$ there exists a smallest prime number p_b such that this matrix is superregular over the prime field \mathbb{F}_{p_b} .

The second construction for MDP convolutional code also requires large field sizes but has the advantage that it works for arbitrary characteristic of the underlying field as well as for arbitrary code parameters.

Theorem 1.3.7 [1] Let n, k, δ be given integers and $m := \max\{n - k, k\}$. Let α be a primitive element of a finite field \mathbb{F}_{p^N} , where p is prime and N is

$$\text{an integer, and define } T_i := \begin{pmatrix} \alpha^{2^{im}} & \alpha^{2^{im+1}} & \cdots & \alpha^{2^{(i+1)m-1}} \\ \alpha^{2^{im+1}} & \alpha^{2^{im+2}} & & \alpha^{2^{(i+1)m}} \\ \vdots & & \ddots & \vdots \\ \alpha^{2^{(i+1)m-1}} & \alpha^{2^{(i+1)m}} & \cdots & \alpha^{2^{(i+2)m-2}} \end{pmatrix} \text{ for}$$

$i = 1, \dots, L = \lfloor \frac{\delta}{k} \rfloor + \lfloor \frac{\delta}{n-k} \rfloor$. Define

$$\mathcal{T}(T_0, \dots, T_L) := \begin{pmatrix} T_0 & & 0 \\ \vdots & \ddots & \\ T_L & \cdots & T_0 \end{pmatrix} \in \text{Mat}_{(L+1)m, (L+1)m}(\mathbb{F}_{p^N}).$$

If $N \geq 2^{m(L+2)-1}$ then the matrix $\mathcal{T}(T_0, T_1, \dots, T_L)$ is superregular (over \mathbb{F}_{p^N}).

The following theorem provides a construction for (n, k, δ) MDP convolutional codes with $(n-k) \mid \delta$ using the superregular matrices from the preceding theorem.

Theorem 1.3.8 [1] Let n, k, δ be given integers such that $(n-k) \mid \delta$ and let $T_l = [t_{ij}^l]$, $i, j = 1, 2, \dots, m$ and $l = 0, 1, 2, \dots, L$ be the entries of the matrix T_l as in the preceding theorem. Define $\overline{H}_l = [t_{ij}^l]$ for $i = 1, 2, \dots, n-k$, $j = 1, 2, \dots, k$ and $l = 0, 1, 2, \dots, L$.

If $q = p^N$ for $N \in \mathbb{N}$ and $|\mathbb{F}_q| \geq p^{2m(L+1)+n-2}$, then the convolutional code $\mathcal{C} = \ker_R[A(z)B(z)]$ where $A(z) = \sum_{i=0}^{\nu} A_i z^i \in \text{Mat}_{n-k, n-k}(R)$ and $B(z) = \sum_{i=0}^{\nu} B_i z^i \in \text{Mat}_{n-k, k}(R)$, with $\nu = \frac{\delta}{n-k}$, $A_0 = I_{n-k}$, $A_i \in \text{Mat}_{n-k, n-k}(\mathbb{F}_q)$, $i = 1, \dots, \nu$ obtained by solving the equations

$$[A_\nu \cdots A_1] \begin{bmatrix} \overline{H}_{l-\nu} & \cdots & \overline{H}_1 \\ \vdots & & \vdots \\ \overline{H}_{L-1} & \cdots & \overline{H}_\nu \end{bmatrix} = -[\overline{H}_L \cdots \overline{H}_{\nu+1}], \text{ and } B_i = A_0 \overline{H}_i +$$

$A_1 \overline{H}_{i-1} + \cdots + A_i \overline{H}_0$, $i = 0, \dots, \nu$, is an (n, k, δ) MDP convolutional code.

In [30] this construction was generalized to arbitrary code parameters, where not necessarily $(n - k) \mid \delta$. In this way, the authors of [30] obtained constructions of (n, k, δ) convolutional codes that are both MDP and sMDS convolutional codes. Other constructions for convolutional codes can be found in [14]. There are two general constructions of complete MDP convolutional codes, similar to the constructions for MDP convolutional codes given in Theorem 1.3.5 and Theorem 1.3.8, presented in the following two theorems.

Theorem 1.3.9 [22] Let $n, k, \delta \in \mathbb{N}$ with $k < n$ and $(n - k) \mid \delta$ and $\nu = \frac{\delta}{n - k}$. Then $H(z) = \sum_{i=0}^{\nu} H_i z^i$ with

$$H_0 = \begin{bmatrix} \binom{\nu n + k}{k} & \cdots & 1 & & 0 \\ \vdots & & & \ddots & \\ \binom{\nu n + k}{n-1} & & \cdots & & 1 \end{bmatrix}$$

$$H_i = \begin{bmatrix} \binom{\nu n + k}{in + k} & \cdots & \binom{\nu n + k}{(i-1)n + k + 1} \\ \vdots & & \vdots \\ \binom{\nu n + k}{(i+1)n-1} & \cdots & \binom{\nu n + k}{in} \end{bmatrix} \text{ for } i = 1, \dots, \nu - 1$$

$$H_{\nu} = \begin{bmatrix} 1 & \cdots & \binom{\nu n + k}{n-1} \\ & \ddots & \vdots \\ 0 & 1 & \cdots & \binom{\nu n + k}{k} \end{bmatrix}$$

is the parity-check matrix of an (n, k, δ) complete MDP convolutional code if the characteristic of the base field is greater than $\binom{\nu n + k}{\lfloor (\nu n + k)/2 \rfloor}^{(n-k)(L+1)} \cdot ((n-k)(L+1))^{(n-k)(L+1)/2}$ where $L = \lfloor \frac{\delta}{k} \rfloor + \lfloor \frac{\delta}{n-k} \rfloor$.

Theorem 1.3.10 [22] Let $n, k, \delta \in \mathbb{N}$ with $k < n$ and $(n - k) \mid \delta$ and $L = \lfloor \frac{\delta}{k} \rfloor + \lfloor \frac{\delta}{n-k} \rfloor$ and let α be a primitive element of a finite field \mathbb{F}_{p^N} where p is a prime and $N > (L + 1) \cdot 2^{(\nu+2)n-k-1}$. Then $H(z) = \sum_{i=0}^{\nu} H_i z^i$ with

$$H_i = \begin{bmatrix} \alpha^{2^{in}} & \cdots & \alpha^{2^{(i+1)n-1}} \\ \vdots & & \vdots \\ \alpha^{2^{(i+1)n-k-1}} & \cdots & \alpha^{2^{(i+2)n-k-2}} \end{bmatrix} \text{ for } i = 0, \dots, \nu = \frac{\delta}{n-k} \text{ is the parity-}$$

check matrix of an (n, k, δ) complete MDP convolutional code.

1.4 Connection to Systems Theory

The aim of this section is to explain the correspondence between convolutional codes and discrete-time linear systems [36] of the form

$$\begin{aligned} x_{t+1} &= x_t A + u_t B \\ y_t &= x_t C + u_t D \\ c_t &= [y_t \ u_t] \end{aligned} \quad (1.6)$$

with $(A, B, C, D) \in \text{Mat}_{s,s}(\mathbb{F}_q) \times \text{Mat}_{k,s}(\mathbb{F}_q) \times \text{Mat}_{s,n-k}(\mathbb{F}_q) \times \text{Mat}_{k,n-k}(\mathbb{F}_q)$, $t \in \mathbb{N}_0$ and $s, k, n \in \mathbb{N}$ with $n > k$. The system (1.6) will be represented by $\Sigma = (A, B, C, D)$, and the integer s is called its **dimension**. We call $x_t \in \mathbb{F}_q^s$ the **state vector**, $u_t \in \mathbb{F}_q^k$ the **information vector**, $y_t \in \mathbb{F}_q^{n-k}$ the **parity vector** and $c_t \in \mathbb{F}_q^n$ the **code vector**. We consider that the initial state is the zero vector, i.e., $x_0 = 0$.

The input, state and output sequences (trajectories), $\{u_t\}_{t \in \mathbb{N}_0}$, $\{x_t\}_{t \in \mathbb{N}_0}$, $\{y_t\}_{t \in \mathbb{N}_0}$, respectively, can be represented as formal power series:

$$u(z) = \sum_{t \in \mathbb{N}_0} u_t z^t \in \mathbb{F}_q[[z]]^k$$

$$x(z) = \sum_{t \in \mathbb{N}_0} x_t z^t \in \mathbb{F}_q[[z]]^s$$

$$y(z) = \sum_{t \in \mathbb{N}_0} y_t z^t \in \mathbb{F}_q[[z]]^{n-k}$$

A trajectory $\{x(t), u(t), y(t)\}_{t \in \mathbb{N}_0}$ satisfies the first two equations of (1.6) if and only if

$$\begin{bmatrix} x(z) & u(z) & y(z) \end{bmatrix} E(z) = \mathbf{0}, \quad (1.7)$$

where

$$E(z) := \begin{bmatrix} I - Az & -C \\ -Bz & -D \\ \mathbf{0}_{(n-k) \times s} & I_{n-k} \end{bmatrix}. \quad (1.8)$$

In order to obtain the codewords of a convolutional code by means of the system (1.6) we must only consider the polynomial input-output trajectories $c(z) = [u(z) \ y(z)]$ of the system. Moreover, we discard the input-output trajectories $c(z)$ with corresponding state trajectory $x(z)$ having infinite weight, since this would make the system remain indefinitely excited. Thus, we restrict to polynomial input-output trajectories with corresponding state trajectory also polynomial. We will call these input-output trajectories, **finite-weight input-output trajectories**. The set of finite-weight input-output trajectories of the system (1.6) forms a submodule of R^n of rank k and thus, it is a convolutional code of rate $\frac{k}{n}$, denoted by $\mathcal{C}(A, B, C, D)$. The system

$\Sigma = (A, B, C, D)$ is said to be an **input-state-output (ISO) representation** of the code.

Since $\mathcal{C}(A, B, C, D)$ is a submodule of rank k , there exists a matrix $G(z) \in \text{Mat}_{k,n}(R)$ such that $\mathcal{C}(A, B, C, D) = \text{rowspan}_R G(z)$. In fact, if $X(z) \in \text{Mat}_{k,s}(R)$ and $G(z) \in \text{Mat}_{k,n}(R)$ are such that $[X(z) \ G(z)]E(z) = 0$ and $[X(z) \ G(z)]$ is left prime, then $G(z)$ is a generator matrix for \mathcal{C} .

Conversely, for each convolutional code \mathcal{C} of rate $\frac{k}{n}$, there exists $(A, B, C, D) \in \text{Mat}_{s,s}(\mathbb{F}_q) \times \text{Mat}_{k,s}(\mathbb{F}_q) \times \text{Mat}_{s,n-k}(\mathbb{F}_q) \times \text{Mat}_{k,n-k}(\mathbb{F}_q)$ such that $\mathcal{C} = \mathcal{C}(A, B, C, D)$, if one allows permutation of the coordinates of the codewords.

If S is an invertible $s \times s$ constant matrix, the change of basis on the state vector, $x'(t) = x(t)S$, produces the algebraic equivalent system $\tilde{\Sigma} = (S^{-1}AS, BS, S^{-1}C, D)$ with the same input-output trajectories as the system Σ . $\tilde{\Sigma} = (S^{-1}AS, BS, S^{-1}C, D)$ is another ISO representation of $\mathcal{C}(A, B, C, D)$ of the same dimension.

However there are other ISO representations of the code with different dimension. We are interested in characterizing the ISO representations of the code with minimal dimension. These ISO representations will be called **minimal ISO representations**. The following properties of the system (1.6) have an important role not only on the characterization of the minimal ISO representations of the code, but also reflect on the properties of the code.

Given $A \in \text{Mat}_{s,s}(\mathbb{F}_q)$, $B \in \text{Mat}_{k,s}(\mathbb{F}_q)$ and $C \in \text{Mat}_{s,n-k}(\mathbb{F}_q)$, define the matrices

$$\Phi(A, B) = \begin{bmatrix} B \\ BA \\ \vdots \\ BA^{s-1} \end{bmatrix} \quad \text{and} \quad \Omega(A, C) = [C \quad AC \quad \cdots \quad A^{s-1}C]$$

Definition 1.4.1 [19] Let $A \in \text{Mat}_{s,s}(\mathbb{F}_q)$, $B \in \text{Mat}_{k,s}(\mathbb{F}_q)$ and $C \in \text{Mat}_{s,n-k}(\mathbb{F}_q)$.

1. the pair (A, B) is called **reachable** if $\text{rank } \Phi(A, B) = s$;
2. the pair (A, C) is called **observable** if $\text{rank } \Omega(A, C) = s$.

The following lemma gives equivalent conditions for reachability and observability and it is called the **Popov, Belevitch and Hautus (PBH) criterion**.

Lemma 1.4.2 [19] Let $A \in \text{Mat}_{s,s}(\mathbb{F}_q)$, $B \in \text{Mat}_{k,s}(\mathbb{F}_q)$ and $C \in \text{Mat}_{s,n-k}(\mathbb{F}_q)$.

1. (A, B) is reachable if and only if $\begin{bmatrix} z^{-1}I_s - A \\ B \end{bmatrix}$ is right prime in the indeterminate z^{-1} ;

2. (A, C) is observable if and only if $[z^{-1}I_s - A \quad C]$ is left prime in the indeterminate z^{-1} .

If $\Sigma = (A, B, C, D)$ is not reachable, then $\text{rank } \Phi(A, B) = \delta < s$ and there exists an invertible matrix $S \in \text{Mat}_{s,s}(\mathbb{F}_q)$ such that $\Phi(A, B)S = \begin{bmatrix} \tilde{\Phi} \\ \mathbf{0} \end{bmatrix}$ where $\tilde{\Phi} \in \text{Mat}_{sk,\delta}(\mathbb{F}_q)$ is a full row rank matrix. Then

$$S^{-1}AS = \begin{bmatrix} A_1 & \mathbf{0} \\ A_2 & A_3 \end{bmatrix}, BS = [B_1 \quad \mathbf{0}], S^{-1}C = \begin{bmatrix} C_1 \\ C_2 \end{bmatrix} \quad (1.9)$$

where $A_1 \in \text{Mat}_{\delta,\delta}(\mathbb{F}_q)$, $B_1 \in \text{Mat}_{k,\delta}(\mathbb{F}_q)$ and $C_1 \in \text{Mat}_{\delta,n-k}(\mathbb{F}_q)$ and $\Phi(A_1, B_1)$ has rank δ , i.e., the system $\Sigma_1 = (A_1, B_1, C_1, D)$ is reachable. The partitioning (1.9) is called the **Kalman (controllable) canonical form** [19].

The system $\tilde{\Sigma} = (S^{-1}AS, BS, S^{-1}C, D)$ has updating equations

$$\begin{aligned} x_{t+1}^{(1)} &= x_t^{(1)} A_1 + x_t^{(2)} A_2 + u_t B_1 \\ x_{t+1}^{(2)} &= x_t^{(2)} A_3 \\ y_t &= x_t^{(1)} C_1 + x_t^{(2)} C_2 + u_t D \end{aligned} \quad (1.10)$$

where $x_t = [x_t^{(1)} \quad x_t^{(2)}]$, with $x_t^{(1)} \in \mathbb{F}_q^\delta$ and $x_t^{(2)} \in \mathbb{F}_q^{s-\delta}$. Since $x_0 = 0$ then $x_t^{(2)} = 0$ for all $t \in \mathbb{N}_0$. Therefore the system

$$x_{t+1}^{(1)} = x_t^{(1)} A_1 + u_t B_1 \quad (1.11)$$

$$y_t = x_t^{(1)} C_1 + u_t D \quad (1.12)$$

has the same finite-weight input-output trajectories and therefore $\mathcal{C}(A, B, C, D) = \mathcal{C}(A_1, B_1, C_1, D)$. i.e, $\Sigma_1 = (A_1, B_1, C_1, D)$ is another ISO representation of the code with smaller dimension. This means that a minimal ISO representation of a convolutional code must be necessarily reachable. But the converse is also true as it is stated in the next theorem.

Theorem 1.4.3 [36] Let $\Sigma = (A, B, C, D)$ be an ISO representation of a convolutional code \mathcal{C} of degree δ . Then Σ is a minimal ISO representation of \mathcal{C} if and only if it is reachable.

Moreover, if Σ is a minimal ISO representation of \mathcal{C} , then it has dimension δ and all the minimal ISO representation of \mathcal{C} are of the form $\tilde{\Sigma} = (\tilde{S}^{-1}A\tilde{S}, B\tilde{S}, \tilde{S}^{-1}C, D)$, where $\tilde{S} \in \mathbb{F}_q^{\delta \times \delta}$ is invertible.

The reachability together with the observability of the system influence the properties of the corresponding code as the next theorem shows.

Theorem 1.4.4 [36] Let $\Sigma = (A, B, C, D)$ be a reachable system. The convolutional code $\mathcal{C}(A, B, C, D)$ is noncatastrophic if and only if $\Sigma = (A, B, C, D)$ is observable.

If $\Sigma = (A, B, C, D)$ is an ISO representation of a code \mathcal{C} which is reachable and observable, then the polynomial input-output trajectories of the system coincide with the finite-weight input-output trajectories, which means that \mathcal{C} is the set of the polynomial input-output trajectories of $\Sigma = (A, B, C, D)$.

The correspondence between linear systems and convolutional codes allows one to obtain further constructions of convolutional codes with good distance properties. The following theorem presents a construction for MDS convolutional codes with rate $1/n$ and arbitrary degree.

Theorem 1.4.5 [38] Let $|\mathbb{F}_q| \geq n\delta + 1$ and α be a primitive element of

\mathbb{F}_q . Set $A = \begin{bmatrix} \alpha & & & 0 \\ & \alpha^2 & & \\ & & \ddots & \\ 0 & & & \alpha^\delta \end{bmatrix} \in \text{Mat}_{\delta, \delta}(\mathbb{F}_q)$, $B = [1 \cdots 1] \in \mathbb{F}_q^\delta$, $D = [1 \cdots 1] \in \mathbb{F}_q^{n-1}$ and $C \in \text{Mat}_{\delta, n-1}(\mathbb{F}_q)$ where the columns c_1, c_2, \dots, c_{n-1} of the matrix C are chosen such that $\det(sI - (A - c_i B)) = \prod_{k=1}^{\delta} (s - \alpha^{r_i+k})$ and $r_i, i = 1, \dots, \delta$, are chosen such that $\{\alpha^{r_i+1}, \alpha^{r_i+2}, \dots, \alpha^{r_i+\delta}\} \cap \{\alpha^{r_j+1}, \alpha^{r_j+2}, \dots, \alpha^{r_j+\delta}\} = \emptyset$ for $i \neq j$. Then $\mathcal{C}(A, B, C, D)$ is an MDS convolutional code.

ISO-representations could also be helpful for the construction of MDP convolutional codes, using the following criterion for being MDP.

Theorem 1.4.6 [16, Corollary 1.1] The matrices (A, B, C, D) generate an MDP convolutional code if and only if the matrix $\mathcal{F}_L :=$

$\begin{bmatrix} D & BC & \dots & BA^{L-1}C \\ 0 & \ddots & \ddots & \vdots \\ \vdots & \ddots & \ddots & BC \\ 0 & \dots & 0 & D \end{bmatrix}$ with $L = \lfloor \frac{\delta}{k} \rfloor + \lfloor \frac{\delta}{n-k} \rfloor$ has the property that every minor which is not trivially zero is nonzero.

1.5 Decoding of Convolutional Codes

In this section, we will present decoding techniques for convolutional codes. The first part of this section describes the decoding of convolutional codes over the erasure channel (see Section 1.2.2), where simple linear algebra techniques are applied. The second part presents the most famous decoding algorithm for convolutional codes over the q -ary symmetric channel, the Viterbi algorithm. Other decoding principles for this kind of channel such as sequential decoding, list decoding, iterative decoding and majority-logic decoding are explained in e.g. [17] or [23].

1.5.1 Decoding over the erasure channel

To make it easier to follow, the decoding over an erasure channel will be explained first for $\delta = 0$ and afterwards the general case.

1.5.1.1 The case $\delta = 0$

Convolutional codes of degree zero are block codes. The only column distance that is defined for a block code \mathcal{C} of rate k/n is the 0-th column distance, which coincides with its minimal distance $d(\mathcal{C}) = \min_{c \in \mathcal{C}} \{wt(c) \mid c \neq 0\}$.

The minimal distance of a block code can be characterized by its parity-check matrices.

Lemma 1.5.1 Let \mathcal{C} be a block code of rate k/n and let $H_0 \in \text{Mat}_{n-k,n}(\mathbb{F}_q)$ be a parity-check matrix of \mathcal{C} . Then \mathcal{C} has minimal distance d if and only if all the sets of $d - 1$ columns of H_0 are linearly independent and there exist d linearly dependent columns of H_0 .

The next theorem establishes the number of erasures that can be corrected by a block code.

Theorem 1.5.2 Let \mathcal{C} be a block code with minimal distance d . Then \mathcal{C} can correct at most $d - 1$ erasures.

Let \mathcal{C} be a block code of rate k/n and minimal distance d and $H_0 \in \text{Mat}_{n-k,n}(\mathbb{F}_q)$ be a parity-check matrix of \mathcal{C} . Let $c \in \mathbb{F}_q^n$ be a received codeword of \mathcal{C} after transmission over an erasure channel with at most $d - 1$ erasures. Then, $H_0 c^\top = 0$. Denote by $c^{(e)}$ the vector consisting of the components of c that are erased during transmission and by $c^{(r)}$ the vectors consisting of the components of c that are received (correctly). Moreover, denote by $H_0^{(e)}$ the matrix consisting of the columns of H_0 whose indices correspond to the indices of the erased components of c and by $H_0^{(r)}$ the matrix consisting of the other columns of H_0 . Then, the equation $H_0 c^\top = 0$ is equivalent to the system of linear equations $H_0^{(e)} c^{(e)} = -H_0^{(r)} c^{(r)}$ with the erased components as unknowns. Since $H_0^{(e)}$ is full column rank, the system $H_0^{(e)} c^{(e)} = -H_0^{(r)} c^{(r)}$ has a unique solution and the erasures are recovered.

Clearly, the decoding is optimal if as many of these linear equations as possible are linearly independent for as many as possible erasure patterns. This is the case if all full size minors of H_0 are nonzero, which is true if and only if \mathcal{C} is MDS, and the maximal number of erasures that a block code of rate k/n can correct is $n - k$.

1.5.1.2 The general case

In this subsection, the considerations of the preceding subsection are generalized to noncatastrophic convolutional codes of rate k/n and arbitrary degree

δ [39]. Moreover, it will be seen that convolutional codes have a better performance than block codes in the decoding over the erasure channel. This is due to the capability of considering particular parts (windows) of the sequence, of different sizes, through the decoding process and slide along this sequence to choose the window to start decoding. Such capability is called the sliding window property and it allows the decoder to adapt the process to the erasure pattern.

Let \mathcal{C} be an (n, k, δ) noncatastrophic convolutional code and assume that for a codeword $c(z) = \sum_{i \in \mathbb{N}_0} c_i z^i$ of \mathcal{C} , the coefficients c_0, \dots, c_{t-1} are known for some $t \in \mathbb{N}_0$ and that there exists at least one erasure in c_t . Let $H(z) = \sum_{i=0}^{\nu} H_i z^i$ with $H_i \in \text{Mat}_{n-k, n}(\mathbb{F}_q)$ be a left prime parity-check matrix of \mathcal{C} . Then, for each $j \in \mathbb{N}_0$ and

$$\mathfrak{H}_j := \begin{pmatrix} H_\nu & \cdots & H_0 & & 0 \\ & \ddots & & \ddots & \\ 0 & & H_\nu & \cdots & H_0 \end{pmatrix} \in \text{Mat}_{(j+1)(n-k), (\nu+j+1)n}(\mathbb{F}_q),$$

one has $\mathfrak{H}_j[c_{t-\nu}, \dots, c_{t+j}]^\top = \mathbf{0}$, where $c_i = 0$ for $i \notin \{0, \dots, \deg(c)\}$. Denote by $\mathfrak{H}_j^{(1)}$ the matrix consisting of the first νn columns of \mathfrak{H}_j . Then, $\mathfrak{H}_j = [\mathfrak{H}_j^{(1)} \ H_j^c]$ and consequently, to recover the erasures in c_t, \dots, c_{t+j} , one has to consider the window $[c_{t-\nu}, \dots, c_{t+j}]$ and solve the linear system

$$H_j^{(e)}[c_t^{(e)}, \dots, c_{t+j}^{(e)}]^\top = -H_j^{(r)}[c_t^{(r)}, \dots, c_{t+j}^{(r)}]^\top - \mathfrak{H}_j^{(1)}[c_{t-\nu}, \dots, c_{t-1}],$$

where $c_i^{(e)}$ and $c_i^{(r)}$ denote the erased and received components of c_i , respectively, and $H_j^{(e)}$ and $H_j^{(r)}$ denote the corresponding columns of H_j^c . The erasures are recovered if and only if the system has a unique solution, i.e. if and only if $H_j^{(e)}$ has full column rank.

Hence, bearing in mind Theorem 1.2.19, one obtains the following theorem, which relates the capability to correct erasures by forward decoding (i.e., decoding from left to right) with the column distances of the convolutional code.

Theorem 1.5.3 [39] If for an (n, k, δ) convolutional code \mathcal{C} , in any sliding window of length $(j+1)n$ at most $d_j^c(\mathcal{C}) - 1$ erasures occur, then full error correction from left to right is possible.

Clearly, the best situation is if one has an MDP convolutional code, i.e. $d_j^c(\mathcal{C}) - 1 = (j+1)(n-k)$ for $j = 0, \dots, L$. Define the **recovery rate** as the ratio of the number of erasures and the total number of symbols in a window. In [39], it has been shown that the recovery rate $\frac{n-k}{n}$ of an MDP convolutional code is the maximal recovery rate one could get over an erasure channel.

Reverse MDP convolutional codes have the MDP property forward and backward and hence also the erasure correcting capability described in Theorem 1.5.3 from left to right and from right to left, and therefore they can

recover even more situations than MDP convolutional codes [39]. There are bursts of erasures that cannot be forward decoded but could be skipped and afterwards be decoded from right to left (backward); see [39] for examples.

If patterns of erasures occur that do not fulfill the conditions of Theorem 1.5.3, neither forward nor backward, one has a block that could not be recovered and gets lost in the recovering process. In order to continue recovering, one needs to find a block of νn correct symbols, a so-called guard space, preceding a block that fulfills the conditions of Theorem 1.5.3. Complete MDP convolutional codes have the additional advantage that to compute a guard space, it is not necessary to have a large sequence of correct symbols [39]. Instead it suffices to have a window with a certain percentage of correct symbols as the following theorem states.

Theorem 1.5.4 [39] Let \mathcal{C} be an (n, k, δ) complete MDP convolutional code and $L = \lfloor \frac{\delta}{k} \rfloor + \lfloor \frac{\delta}{n-k} \rfloor$. If in a window of size $(L + \nu + 1)n$ there are not more than $(L + 1)(n - k)$ erasures, and if they are distributed in such a way that between position 1 and sn and between positions $(L + \nu + 1)n$ and $(L + \nu + 1)n - sn + 1$, for $s = 1, \dots, L + 1$, there are not more than $s(n - k)$ erasures, then full correction of all symbols in this interval will be possible. In particular a new guard space can be computed.

The way of decoding over the erasure channel described here could be used for any convolutional code. However, to correct as many erasures as possible it is optimal to use MDP or even complete MDP convolutional codes. For algorithms to do that we refer to [39].

Remark 1.5.5 If $\tilde{\mathcal{C}}$ is a catastrophic convolutional code, it is possible to find a noncatastrophic convolutional code \mathcal{C} with $\tilde{\mathcal{C}} \subset \mathcal{C}$ (see Remark 1.2.9). Let $H(z)$ be a left prime parity-check matrix for \mathcal{C} . Then, $H(z)c(z)^\top = \mathbf{0}$ for all $c(z) \in \tilde{\mathcal{C}}$. Hence, the decoding procedure described in this subsection could be applied to $\tilde{\mathcal{C}}$ by using $H(z)$.

MDP convolutional codes are able to recover patterns of erasures that MDS block codes, with the same recovering rate, cannot recover, as illustrated in the next example.

Example 1.5.6 [39] Let us consider the received sequence

$$w = (w_0, w_1, \dots, w_{100})$$

with $w_i \in \mathbb{F}_q^2$ and with 120 erasures in w_i , $i \in \{0, 1, \dots, 29\} \cup \{70, 71, \dots, 99\}$.

Let us assume that w is a received word of an MDS block code of rate $101/202$. Such a code can correct up to 101 symbols in a sequence of 202 symbols, i.e., it has a recovering rate of 50%. Thus, since w has 120 erasures it cannot be recovered.

Let us assume now that $w(z) = \sum_{i=0}^{100} w_i z^i$ is a received word of a $(2, 1, 50)$

MDP convolutional code \mathcal{C} . \mathcal{C} has the same recovering rate, but it is able to correct the erasures in $w(z)$. Note that $d_j^c(\mathcal{C}) = j + 1$, for $j = 0, 1, \dots, L$ with $L = 100$. To recover the whole sequence one can consider a window with the first 120 symbols (i.e., the sequence constituted by w_0, w_1, \dots, w_{59}). Since $d_{59}^c(\mathcal{C}) = 60$, then the first 60 symbols can be recovered by applying the decoding algorithm described in this section. Afterwards, take another window with the symbols $w_{41}, w_{42}, \dots, w_{100}$. Similarly, this window has 120 symbols and 60 erasures, which means that also these erasures can be recovered and the whole corrected sequence is obtained.

1.5.2 The Viterbi decoding algorithm

The most commonly used error-correction decoding algorithm for convolutional codes is the Viterbi decoding algorithm, which was proposed by Viterbi in 1967 [41]. It is a minimum-distance decoder, i.e. it computes all codewords of a certain length and compares the received word to each of them. Then, the codeword closest to the received word is selected (maximum-likelihood decoding). It could be understood as applying techniques from dynamic programming to the linear systems representation of the convolutional code, as explained next.

A state-transition diagram for the convolutional code can be defined from a minimal ISO representation of the code, $\Sigma = (A, B, C, D)$ of dimension δ , as a labeled directed graph with set of nodes $X = \mathbb{F}_q^\delta$ and such that (x_1, x_2) , with $x_1, x_2 \in X$, is an arc (transition) of the graph if there exists $u \in \mathbb{F}_q^k$ such that $x_2 = x_1 A + u B$. In this case we assign the label (u, y) to the arc (x_1, x_2) , where $y = x_1 C + u D$. The codewords of the code are obtained considering all closed walks on the state-transition diagram that start at the node $x = 0$ and end at the same node, and a codeword corresponding to such a walk is the sequence of the labels of the arcs that constitute this walk.

When we introduce the dimension of time, this state-transition diagram, can be represented as a trellis diagram by considering a different copy of the set of nodes (states) of the state-transition diagram at each time instant (also called depth). For every $t \in \mathbb{N}_0$, we consider an arc e from a state x_1 in time instant t to another state x_2 at time instant $t + 1$, if there exists the arc (x_1, x_2) in the state-transition diagram. The label of the arc e is taken to be the same as the label of (x_1, x_2) in the state-transition diagram. The codewords of the code correspond to the paths on the trellis diagram that start and end at the zero state [5].

If $c^r(z) \in \mathbb{F}_q[z]^n$ is a received word, the Viterbi algorithm searches the paths of the trellis diagram starting at the state $x = 0$ and ending at the same state, $x = 0$, such that the corresponding codeword has minimal distance to

$c^r(z)$. The decoding progress is simplified by breaking it down into a sequence of steps using the recursive relation given by the equations defining the linear system. In each step, the distance between the received word and the estimated word is minimized.

In the following, this process should be explained in detail.

Algorithm:

Assume that a convolutional code \mathcal{C} and a received word $c^r(z) = \sum_{i \in \mathbb{N}_0} c_i^r z^i$, which should be decoded, are given. Take a minimal ISO representation $\Sigma = (A, B, C, D)$ of dimension δ of \mathcal{C} and set $x_0 = \mathbf{0}$.

Step 1: set $t = 0$, $d_{min} = \infty$ and $sp_{min} = \emptyset$, and assign to the initial node the label $(d = 0, sp = \emptyset)$. Go to Step 2.

Step 2: for each node x_2 at time instant $t + 1$ do: for each of the predecessors x_1 at time instant t with label (d, sp) and $d < d_{min}$, compute the sum $d + d((u, y), c_t)$, where (u, y) is the label of the arc (x_1, x_2) in the state-transition diagram, determine the minimum of these sums, \bar{d} and assign to x_2 the label (\bar{d}, \bar{sp}) , where \bar{sp} is the shortest path from $x = 0$, at time instant zero, to x_2 (if there are several sums with the minimal value, then there are several paths from $x = 0$, at time instant zero, to x_2 with distance \bar{d} : in this case select randomly one of these paths). If $x_2 = 0$ and $\bar{d} < d_{min}$ then set $d_{min} = \bar{d}$ and $sp_{min} = \bar{sp}$. Go to Step 3.

Step 3: if at time instant $t + 1$, all the nodes x with label (\bar{d}, \bar{sp}) are such that $\bar{d} \geq d_{min}$, then STOP and the result of the decoding is the codeword corresponding to the path sp_{min} . Otherwise set $t = t + 1$ and go to Step 2.

The complexity of this algorithm grows with the number of states, at each time instant, in the trellis diagram. The set of states is $X = \mathbb{F}_q^\delta$ and therefore it has q^δ elements. This algorithm is practical only for codes with small degree and defined in fields of very small size.

Instead of using the linear systems representation, the Viterbi algorithm could also be operated using the trellis of the convolutional code; see e.g. [5].

1.6 Two-dimensional Convolutional Codes

In this section we consider convolutional codes of higher dimension, namely the two-dimensional (2D) convolutional codes. Let $R = \mathbb{F}_q[z_1, z_2]$ be the ring of polynomials in the indeterminates z_1 and z_2 , $\mathbb{F}_q(z_1, z_2)$ the field of rational functions in z_1 and z_2 with coefficients in \mathbb{F}_q and $\mathbb{F}_q[[z_1, z_2]]$ the ring of formal power series in z_1 and z_2 with coefficients in \mathbb{F}_q .

1.6.1 Definition of 2D Convolutional Codes via Generator and Parity-check Matrices

A **two-dimensional (2D) convolutional code** \mathcal{C} of **rate** k/n is a free R -submodule of R^n of rank k . A **generator matrix** of \mathcal{C} is a full row rank matrix $G(z_1, z_2)$ whose rows constitute a basis of \mathcal{C} , and it induces an injective map between R^k and R^n . This is the main reason of the restriction of the definition of 2D convolutional codes to free submodules of R^n .

Analogously as defined in the 1D case, a matrix $U(z_1, z_2) \in \text{Mat}_{k,k}(R)$ is unimodular if there exists a $k \times k$ matrix over R such that

$$U(z_1, z_2)V(z_1, z_2) = V(z_1, z_2)U(z_1, z_2) = I_k,$$

or equivalently, if $\det(U(z_1, z_2)) \in \mathbb{F}_q^*$. Using the same reasoning as in section 1.2.1 for one-dimensional (1D) convolutional codes, the matrices $G(z_1, z_2)$ and $\tilde{G}(z_1, z_2)$ in $\text{Mat}_{k,n}(R)$ are said to be equivalent if they are generator matrices of the same code, which happens if and only if

$$\tilde{G}(z_1, z_2) = U(z_1, z_2)G(z_1, z_2),$$

for some unimodular matrix $U(z_1, z_2) \in \text{Mat}_{k,k}(R)$.

Complexity and degree are equivalent and important notions of 1D convolutional codes. They are one of the parameters of the generalized Singleton bound on the distance of these codes and they also provide a lower bound on the dimension of their ISO representations. To define similar notions for 2D convolutional codes, we consider the usual notion of (total) degree of a polynomial in two indeterminates $p(z_1, z_2) = \sum_{(i,j) \in \mathbb{N}_0} p_{ij} z_1^i z_2^j$ with $p_{ij} \in \mathbb{F}_q$ as

$\deg(p(z_1, z_2)) = \max\{i + j : p_{ij} \neq 0\}$. We also define the **internal degree** of a polynomial matrix $G(z_1, z_2)$, denoted by $\delta_i(G)$, as the maximal degree of the full size minors of $G(z_1, z_2)$ and its **external degree**, denoted by $\delta_e(G)$, as $\sum_{i=1}^k \nu_i$, where ν_i is the maximum degree of the entries of the i -th row of $G(z_1, z_2)$. Obviously $\delta_i(G) \leq \delta_e(G)$.

Since two generator matrices of a 2D convolutional code \mathcal{C} differ by a unimodular matrix, their full size minors are equal, up to multiplication by a nonzero constant. The **complexity** of \mathcal{C} is defined as the internal degree of any generator matrix of \mathcal{C} and it is represented by δ_c . The **degree** of \mathcal{C} is the minimum external degree of all generator matrices of \mathcal{C} and it is represented by δ_d . Clearly the internal degree of any generator matrix is less than or equal to the corresponding external degree, and therefore $\delta_c \leq \delta_d$ [29, 3].

The row reduced generator matrices of 1D convolutional codes are the ones for which the corresponding notions of internal degree and external degree coincide, and this is why the complexity and degree of a 1D convolutional code are the same. However, 2D convolutional codes do not always admit such generator matrices and there are 2D convolutional codes such that $\delta_c < \delta_d$, as is illustrated in the following simple example.

Example 1.6.1 For any finite field, the 2D convolutional code with generator matrix

$$G(z_1, z_2) = \begin{bmatrix} 1 & z_1 & 0 \\ 1 & z_2 & 1 \end{bmatrix}$$

has complexity 1 and degree 2.

Another important property of a 1D convolutional code is the existence (or not) of prime generator matrices. When we consider polynomial matrices in two indeterminates, there are two different notions of primeness, factor-primeness and zero-primeness [28, 21, 45, 32].

Definition 1.6.2 A matrix $G(z_1, z_2) \in \text{Mat}_{k,n}(R)$, with $n \geq k$ is

(a) **left factor-prime** (ℓFP) if for every factorization

$$G(z_1, z_2) = T(z_1, z_2)\overline{G}(z_1, z_2),$$

with $\overline{G}(z_1, z_2) \in \text{Mat}_{k,n}(R)$ and $T(z_1, z_2) \in \text{Mat}_{k,k}(R)$, $T(z_1, z_2)$ is unimodular;

(b) **left zero-prime** (ℓZP) if the ideal generated by the $k \times k$ minors of $G(z_1, z_2)$ is $\mathbb{F}_q[z_1, z_2]$.

A matrix $G(z) \in \text{Mat}_{k,n}(R)$, with $k \geq n$, is **right factor-prime** (rFP) / **right zero-prime** (rZP) if its transpose is ℓFP / ℓZP , respectively. The notions (a) and (b) of the above definition are equivalent for polynomial matrices in one indeterminate (see Theorem 1.2.6). However, for polynomial matrices in two indeterminates, zero-primeness implies factor-primeness, but the contrary does not happen, as is illustrated in the following example.

Example 1.6.3 The matrix $\begin{bmatrix} z_1 & z_2 \end{bmatrix}$ is left factor-prime but it is not left zero-prime.

The following lemmas give characterizations of left factor-primeness and left zero-primeness.

Lemma 1.6.4 Let $G(z_1, z_2) \in \text{Mat}_{k,n}(R)$, with $n \geq k$. Then the following are equivalent:

(a) $G(z_1, z_2)$ is ℓFP ;

(b) there exist polynomial matrices $X_i(z_1, z_2)$ such that

$$X_i(z_1, z_2)G(z_1, z_2) = d_i(z_i)I_k,$$

with $d_i(z_i) \in \mathbb{F}_q[z_i] \setminus \{0\}$, for $i = 1, 2$;

(c) for all $u(z_1, z_2) \in \mathbb{F}_q(z_1, z_2)^k$, $u(z_1, z_2)G(z_1, z_2) \in R^n$ implies that $u(z_1, z_2) \in R^k$.

(d) the $k \times k$ minors of $G(z_1, z_2)$ have no common factor.

Lemma 1.6.5 Let $G(z_1, z_2) \in \text{Mat}_{k,n}(R)$, with $n \geq k$. Then the following are equivalent:

- (a) $G(z_1, z_2)$ is ℓZP ;
- (b) $G(z_1, z_2)$ admits a polynomial right inverse;
- (c) $G(\lambda_1, \lambda_2)$ is full column rank, for all $\lambda_1, \lambda_2 \in \overline{\mathbb{F}_q}$, where $\overline{\mathbb{F}_q}$ denotes the algebraic closure of \mathbb{F}_q .

From the above lemmas, it immediately follows that if a 2D convolutional code admits a left factor-prime (left zero-prime) generator matrix then all its generator matrices are also left factor-prime (left zero-prime). 2D convolutional codes with left factor-prime generator matrices are called **noncatastrophic** and if they admit left zero-prime generator matrices, they are called **basic**.

A **parity-check matrix** of a 2D convolutional code \mathcal{C} is a full row rank matrix $H(z_1, z_2) \in \text{Mat}_{n-k,n}(R)$ such that

$$c(z_1, z_2) \in \mathcal{C} \Leftrightarrow H(z_1, z_2)c(z_1, z_2)^T = 0.$$

As for 1D convolutional codes, the existence of parity-check matrices for a 2D convolutional code is connected with primeness properties of its generator matrices as stated in the following theorem.

Theorem 1.6.6 [40] A 2D convolutional code \mathcal{C} admits a parity-check matrix $H(z_1, z_2)$ if and only if it is noncatastrophic.

The free distance of a 2D convolutional code was first defined in [42], and it is a generalization of the free distance defined in the 1D case. The weight of a polynomial vector $c(z_1, z_2) = \sum_{(i,j) \in \mathbb{N}_0^2} c_{ij} z_1^i z_2^j$ is given by $wt(c(z_1, z_2)) =$

$\sum_{(i,j) \in \mathbb{N}_0^2} wt(c_{ij})$ and the **free distance** of \mathcal{C} is defined as

$$\begin{aligned} d_{free}(\mathcal{C}) &= \min\{wt(c_1(z_1, z_2) - c_2(z_1, z_2)) : c_1(z_1, z_2), c_2(z_1, z_2) \in \mathcal{C}, c_1(z_1, z_2) \neq c_2(z_1, z_2)\} \\ &= \min\{wt(c(z_1, z_2)) : c(z_1, z_2) \in \mathcal{C} \setminus \{\mathbf{0}\}\}. \end{aligned}$$

The degree of a 2D convolutional code \mathcal{C} is an important parameter for establishing an upper bound on the distance of \mathcal{C} .

Theorem 1.6.7 [3] Let \mathcal{C} be a 2D convolutional code of rate k/n and degree δ . Then

$$d_{free}(\mathcal{C}) \leq n \frac{(\lfloor \frac{\delta}{k} \rfloor + 1)(\lfloor \frac{\delta}{k} \rfloor + 2)}{2} - k \left(\left\lfloor \frac{\delta}{k} \right\rfloor + 1 \right) + \delta + 1.$$

This upper bound is the extension to 2D convolutional codes of the generalized Singleton bound for 1D convolutional codes [35] and it is called the **2D generalized Singleton bound**. Moreover, a 2D convolutional code of rate k/n and degree δ is said to be a **maximum distance deparable** (MDS) 2D convolutional code if its distance equals the 2D generalized Singleton bound. Constructions of MDS 2D convolutional codes can be found in [2, 3].

1.6.2 ISO representations

Two-dimensional convolutional codes can also be represented by a linear system. Unlike the 1D case, there exist several state-space models of a 2D linear system, namely the Roesser model, the Attasi model and the Fornasini-Marchesini model. The ISO representations of 2D convolutional codes investigated in the literature consider the Fornasini-Marchesini model [7]. In this model a first quarter plane 2D linear system is given by the updating equations

$$\begin{aligned} x_{i+1,j+1} &= x_{i,j+1}A_1 + x_{i+1,j}A_2 + u_{i,j+1}B_1 + u_{i+1,j}B_2 \\ y_{ij} &= x_{ij}C + u_{ij}D \\ c_{ij} &= \begin{bmatrix} y_{ij} & u_{ij} \end{bmatrix} \end{aligned} \quad (1.13)$$

with $(A_1, A_2, B_1, B_2, C, D) \in \text{Mat}_{s,s}(\mathbb{F}_q) \times \text{Mat}_{s,s}(\mathbb{F}_q) \times \text{Mat}_{k,s}(\mathbb{F}_q) \times \text{Mat}_{k,s}(\mathbb{F}_q) \times \text{Mat}_{s,n-k}(\mathbb{F}_q) \times \text{Mat}_{k,n-k}(\mathbb{F}_q)$, $i, j \in \mathbb{N}_0$ and $s, k, n \in \mathbb{N}$ with $n > k$. The system (1.13) will be represented by $\Sigma = (A_1, A_2, B_1, B_2, C, D)$, and the integer s is called its **dimension**. We call $x_{ij} \in \mathbb{F}_q^s$ the **local state vector**, $u_{ij} \in \mathbb{F}_q^k$ the **information vector**, $y_{ij} \in \mathbb{F}_q^{n-k}$ the **parity vector** and $c_{ij} \in \mathbb{F}_q^n$ the **code vector**. Moreover, the input and the local state have past finite support, i.e., $u_{ij} = 0$ and $x_{ij} = 0$, for $i < 0$ or $j < 0$ and we consider zero initial conditions, i.e., $x_{00} = 0$.

The input, local state and output 2D sequences (trajectories) of the system, $\{u_{ij}\}_{(i,j) \in \mathbb{N}_0^2}$, $\{x_{ij}\}_{(i,j) \in \mathbb{N}_0^2}$, $\{y_{ij}\}_{(i,j) \in \mathbb{N}_0^2}$, respectively, can be represented as formal power series in the indeterminates z_1, z_2 :

$$\begin{aligned} u(z_1, z_2) &= \sum_{(i,j) \in \mathbb{N}_0^2} u_{ij} z_1^i z_2^j \in \mathbb{F}_q[[z_1, z_2]]^k \\ x(z_1, z_2) &= \sum_{(i,j) \in \mathbb{N}_0^2} x_{ij} z_1^i z_2^j \in \mathbb{F}_q[[z_1, z_2]]^s \\ y(z_1, z_2) &= \sum_{(i,j) \in \mathbb{N}_0^2} y_{ij} z_1^i z_2^j \in \mathbb{F}_q[[z_1, z_2]]^{n-k}. \end{aligned}$$

The $\mathbb{F}_q[[z_1, z_2]]$ -kernel of the matrix

$$E(z_1, z_2) = \begin{bmatrix} I_s - A_1 z_1 - A_2 z_2 & -C \\ -B_1 z_1 - B_2 z_2 & -D \\ 0 & I_{n-k} \end{bmatrix} \quad (1.14)$$

consists of the $(x(z_1, z_2), u(z_1, z_2), y(z_1, z_2))$ trajectories of the system, and we say that an input-output trajectory has corresponding state trajectory $x(z_1, z_2)$ if $[x(z_1, z_2) u(z_1, z_2) y(z_1, z_2)]E(z_1, z_2) = 0$.

For the same reasons stated for 1D convolutional codes in Section 1.4, we only consider the finite-weight input-output trajectories of the system (1.13) to obtain a 2D convolutional code, i.e, the polynomial trajectories $(u(z_1, z_2), y(z_1, z_2))$ with corresponding state trajectory $x(z_1, z_2)$ also polynomial.

Theorem 1.6.8 [29] The set of finite-weight input-output trajectories of the system (1.13) is a 2D convolutional code of rate k/n .

The 2D convolutional code whose codewords are the finite-weight input-output trajectories of the system (1.13) is denoted by $\mathcal{C}(A_1, A_2, B_1, B_2, C, D)$. The system $\Sigma = (A_1, A_2, B_1, B_2, C, D)$ is called an **input-state-output (ISO) representation** of the code $\mathcal{C}(A_1, A_2, B_1, B_2, C, D)$.

If $L(z_1, z_2) \in \text{Mat}_{k,s}(R)$ and $G(z_1, z_2) \in \text{Mat}_{k,n}(R)$ are such that

$$\begin{bmatrix} L(z_1, z_2) & G(z_1, z_2) \end{bmatrix} E(z_1, z_2) = 0$$

where $\begin{bmatrix} L(z_1, z_2) & G(z_1, z_2) \end{bmatrix}$ is left factor-prime, then $G(z_1, z_2)$ is a generator matrix of $\mathcal{C}(A_1, A_2, B_1, B_2, C, D)$.

Reachability and observability are properties of a linear system that also reflect on the corresponding convolutional code. However, 2D linear systems as in (1.13) admit different types of reachability and observability notions.

Definition 1.6.9 [7] Let $\Sigma = (A_1, A_2, B_1, B_2, C, D)$ be a 2D linear system with dimension s and define the following matrices

$$A_1 {}^r\Delta^t A_2 = A_1(A_1 {}^{r-1}\Delta^t A_2) + A_2(A_1 {}^r\Delta^{t-1} A_2), \text{ for } r, t \geq 1,$$

$$A_1 {}^r\Delta^0 A_2 = A_1^r, \quad A_1 {}^0\Delta^t A_2 = A_2^t, \text{ for } r, t \geq 0,$$

$$A_1 {}^r\Delta^t A_2 = 0, \text{ when either } r \text{ or } t \text{ is negative.}$$

1. Σ is **locally reachable** if the reachability matrix

$$\mathcal{R} = \begin{bmatrix} R_1 \\ R_2 \\ R_3 \\ \vdots \end{bmatrix}$$

is full row rank, where R_k is the block matrix constituted by all

$$B_1(A_1 {}^{i-1}\Delta^j A_2) + B_2(A_1 {}^i\Delta^{j-1} A_2),$$

with $i + j = k$, for $i, j \geq 0$, i.e.,

$$R_k = \begin{bmatrix} B_1 A_1^{k-1} \\ B_1(A_1^{k-2} \Delta^1 A_2) + B_2(A_1^{k-1} \Delta^0 A_2) \\ B_1(A_1^{k-3} \Delta^2 A_2) + B_2(A_1^{k-2} \Delta^1 A_2) \\ \vdots \\ B_1(A_1^0 \Delta^{k-1} A_2) + B_2(A_1^1 \Delta^{k-2} A_2) \\ B_2 A_2^{k-1} \end{bmatrix}.$$

2. Σ is **modally reachable** if the matrix

$$\begin{bmatrix} I_s - A_1 z_1 - A_2 z_2 \\ B_1 z_1 + B_2 z_2 \end{bmatrix}$$

is right factor-prime.

3. Σ is **modally observable** if the matrix

$$\begin{bmatrix} I_s - A_1 z_1 - A_2 z_2 & C \end{bmatrix}$$

is left factor-prime.

There also exists a notion of local observability that will not be considered here. There are 2D systems that are locally reachable (observable) but not modally reachable (observable) and vice-versa [7]. The next lemma shows the influence of these properties on the corresponding convolutional code.

Lemma 1.6.10 [29, 4] Let $\Sigma = (A_1, A_2, B_1, B_2, C, D)$ be a modally reachable 2D linear system. Then Σ is modally observable if and only if $\mathcal{C}(A_1, A_2, B_1, B_2, C, D)$ is noncatastrophic.

If $\Sigma = (A_1, A_2, B_1, B_2, C, D)$ is an ISO representation of a 2D convolutional code of dimension s , and S is an invertible $s \times s$ constant matrix, the algebraically equivalent system $\tilde{\Sigma} = (S^{-1}A_1S, S^{-1}A_2S, B_1S, B_2S, S^{-1}C, D)$ is also an ISO representation of the code, i.e., $\mathcal{C}(A_1, A_2, B_1, B_2, C, D) = \mathcal{C}(S^{-1}A_1S, S^{-1}A_2S, B_1S, B_2S, S^{-1}C, D)$ [29]. Among the algebraically equivalent ISO representation of a code there exists the Kalman canonical form considered in the next definition.

Definition 1.6.11 [7] A 2D linear system $\Sigma = (A_1, A_2, B_1, B_2, C, D)$ with dimension s , k inputs and $n - k$ outputs is in **Kalman canonical form** if

$$A_1 = \begin{bmatrix} A_{11}^{(1)} & 0 \\ A_{21}^{(1)} & A_{22}^{(1)} \end{bmatrix}, A_2 = \begin{bmatrix} A_{11}^{(2)} & 0 \\ A_{21}^{(2)} & A_{22}^{(2)} \end{bmatrix},$$

$$B_1 = \begin{bmatrix} B_1^{(1)} & 0 \end{bmatrix}, B_2 = \begin{bmatrix} B_1^{(2)} & 0 \end{bmatrix}, C = \begin{bmatrix} C_1 \\ C_2 \end{bmatrix},$$

where $A_{11}^{(1)}, A_{11}^{(2)} \in \text{Mat}_{\delta, \delta}(\mathbb{F}_q)$, $B_1^{(1)}, B_1^{(2)} \in \text{Mat}_{k, \delta}(\mathbb{F}_q)$, $C_1 \in \text{Mat}_{\delta, n-k}(\mathbb{F}_q)$, with $s \geq \delta$ and the remaining matrices of suitable dimensions, and $\Sigma_1 = (A_{11}^{(1)}, A_{11}^{(2)}, B_1^{(1)}, B_1^{(2)}, C_1, D)$ a locally reachable system. Σ_1 is called the **largest locally reachable subsystem** of Σ .

Theorem 1.6.12 [29] Let $\Sigma = (A_1, A_2, B_1, B_2, C, D)$ be an ISO representation of a 2D convolutional code \mathcal{C} . Let S be an invertible constant matrix such that

$$\tilde{\Sigma} = (S^{-1}A_1S, S^{-1}A_2S, B_1S, B_2S, S^{-1}C, D)$$

is in Kalman reachability canonical form and let

$$\Sigma_1 = (A_{11}^{(1)}, A_{11}^{(2)}, B_1^{(1)}, B_1^{(2)}, C_1, D)$$

be the largest locally reachable subsystem of $\tilde{\Sigma}$. Then we have that $\mathcal{C} = \mathcal{C}(A_{11}^{(1)}, A_{11}^{(2)}, B_1^{(1)}, B_1^{(2)}, C_1, D)$.

Unlike 1D convolutional codes, there are no characterizations of minimal ISO representations of a 2D convolutional code. However, Theorem 1.6.12 allows one to obtain a necessary condition for minimality; i.e., a minimal ISO representation of a 2D convolutional code must be locally reachable.

1.7 Connections of convolutional codes to symbolic dynamics

We already explained in detail a close connection between convolutional codes and linear systems. Concepts closely connected to convolutional codes appear also in automata theory and in the theory of symbolic dynamics. The survey article of Marcus [25] provides details. In this section we describe the connection to symbolic dynamics. The reader will find more details on this topic in [20, 24, 33]. In the sequel we closely follow [33].

In symbolic dynamics one often works with a finite alphabet $\mathcal{A} := \mathbb{F}_q^n$ and then considers sequence spaces such as $\mathcal{A}^{\mathbb{Z}}$, $\mathcal{A}^{\mathbb{N}}$, or $\mathcal{A}^{\mathbb{N}_0}$. In the order to be consistent with the rest of the chapter we will work in the sequel with $\mathcal{A}^{\mathbb{N}_0}$, i.e., with the 'non-negative time axis' \mathbb{N}_0 .

Let k be a natural number. A **block** over the alphabet \mathcal{A} is defined as a finite string $\beta = x_1x_2 \dots x_k$ consisting of the k elements $x_i \in \mathcal{A}$, $i = 1, \dots, k$. If $w(z) = \sum_i w_i z^i \in \mathcal{A}[[z]]$ is a sequence, one says that the block β occurs in w if there is some integer j such that $\beta = w_j w_{j+1} \dots w_{k+j-1}$. If $X \subset \mathcal{A}[[z]]$ is any subset, we denote by $\mathcal{B}(X)$ the set of blocks which occur in some element of X .

As we will explain in this section one can view observable convolutional codes as the dual of linear, compact, irreducible and shift-invariant subsets

of $\mathbb{F}_q^n[[z]]$. In order to establish this result we will have to explain the basic definitions from symbolic dynamics.

For this consider a set \mathcal{F} of blocks. It is possible that this set is infinite.

Definition 1.7.1 The subset $X \subset \mathcal{A}[[z]]$ consisting of all sequences $w(z)$ which do not contain any of the (forbidden) blocks of \mathcal{F} is called a **shift space**.

The left-shift operator is the \mathbb{F}_q -linear map

$$\sigma : \mathbb{F}_q[[z]] \longrightarrow \mathbb{F}_q[[z]], \quad w(z) \longmapsto z^{-1}(w(z) - w(0)). \quad (1.15)$$

Let I_n be the $n \times n$ identity matrix acting on $\mathcal{A} = \mathbb{F}_q^n$. The shift map σ extends to the **shift map**

$$\sigma I_n : \mathcal{A}[[z]] \longrightarrow \mathcal{A}[[z]].$$

One says that $X \subset \mathcal{A}[[z]]$ is a **shift-invariant set** if $(\sigma I_n)(X) \subset X$.

Shift spaces can be characterized in a topological manner:

Definition 1.7.2 Let $v(z) = \sum_i v_i z^i$ and $w(z) = \sum_i w_i z^i$ be elements of $\mathcal{A}[[z]]$. Let $d_H(x, y)$ be the Hamming distance between elements in \mathcal{A} . One defines the distance between the sequences $v(z)$ and $w(z)$ through:

$$d(v(z), w(z)) := \sum_{i \in \mathbb{N}_0} 2^{-i} d_H(v_i, w_i). \quad (1.16)$$

Note that in this metric two elements $v(z), w(z)$ are ‘close’ if they coincide in a large number of elements in the beginning of the sequence. The function $d(\cdot, \cdot)$ defines a metric on the sequence space $\mathcal{A}^{\mathbb{N}_0}$. The metric introduced in Definition 1.7.2 is equivalent to the metric described in [24, Example 6.1.10]. The following result can be found in [24, Theorem 6.1.21].

Theorem 1.7.3 A subset of $\mathcal{A}[[z]]$ is a shift space if and only if it is shift-invariant and compact.

Next we need the notion of irreducibility:

Definition 1.7.4 A shift space $X \subset \mathcal{A}[[z]]$ is called **irreducible** if for every ordered pair of blocks β, γ of $\mathcal{B}(X)$ there is a block μ such that the concatenated block $\beta\mu\gamma$ is in $\mathcal{B}(X)$.

Of particular interest are shift spaces which have a ‘kernel representation’. For this let $P(z)$ be an $r \times n$ matrix having entries in the polynomial ring $\mathbb{F}_q[z]$. Define the set

$$\mathcal{B} = \{ w(z) \in \mathcal{A}[[z]] \mid P(\sigma)w(z) = 0 \}. \quad (1.17)$$

Subsets $\mathcal{B} \subseteq \mathcal{A}[[z]]$ having the particular form (1.17) can be characterized in a purely topological manner.

Theorem 1.7.5 A subset $\mathcal{B} \subseteq \mathcal{A}[[z]]$ has a kernel representation of the form (1.17) if and only if \mathcal{B} is a linear, irreducible, compact and shift invariant subset of $\mathcal{A}[[z]]$.

Subsets of the form (1.17) appear also prominently in the behavioral theory of linear system championed by Jan Willems. The following theorem was proven by Willems [43, Theorem 5]. Note that a metric space is called complete if every Cauchy sequence converges in this space.

Theorem 1.7.6 A subset $\mathcal{B} \subset \mathbb{F}_q^n[[z]]$ is linear, time-invariant and complete if and only if \mathcal{B} has a representation of the form (1.17).

There is a small difference in above notions as a subset $\mathcal{B} \subset \mathcal{A}[[z]]$ which is linear, irreducible, compact and shift invariant is automatically also a 'controllable behavior' in the sense of Willems.

We are now in a position to connect to convolutional codes (polynomial modules) using Pontryagin duality. For this consider the bilinear form:

$$\begin{aligned} (,) : \mathbb{F}_q^n[[z]] \times \mathbb{F}_q^n[z] &\longrightarrow \mathbb{F}_q \\ (w, v) &\mapsto \sum_{i=0}^{\infty} \langle w_i, v_i \rangle, \end{aligned} \quad (1.18)$$

where \langle , \rangle represents the standard dot product on $\mathcal{A} = \mathbb{F}_q^n$. As the sum has only finite many nonzero terms the bilinear form $(,)$ is well defined and nondegenerate. Using this bilinear form one defines for a subset \mathcal{C} of $\mathbb{F}_q^n[z]$ the **annihilator**

$$\mathcal{C}^\perp = \{w \in \mathbb{F}_q^n[[z]] \mid (w, v) = 0, \forall v \in \mathcal{C}\} \quad (1.19)$$

and the **annihilator** of a subset \mathcal{B} of $\mathbb{F}_q^n[[z]]$ is

$$\mathcal{B}^\perp = \{v \in \mathbb{F}_q^n[z] \mid (w, v) = 0, \forall w \in \mathcal{B}\}. \quad (1.20)$$

The relation between these two annihilator operations is given by the following theorem which was derived and proven in [34].

Theorem 1.7.7 If $\mathcal{C} \subseteq \mathbb{F}_q^n[z]$ is a convolutional code with generator matrix $G(z)$, then \mathcal{C}^\perp is a linear, left-shift-invariant and complete behavior with kernel representation $P(z) = G^t(z)$. Conversely, if $\mathcal{B} \subseteq \mathbb{F}_q^n[[z]]$ is a linear, left-shift-invariant and complete behavior with kernel representation $P(z)$, then \mathcal{B}^\perp is a convolutional code with generator matrix $G(z) = P^t(z)$. Moreover $\mathcal{C} \subseteq \mathbb{F}_q^n[z]$ is noncatastrophic if and only if \mathcal{C}^\perp is a controllable behavior.

1.8 Acknowledgements

This work is supported by The Center for Research and Development in Mathematics and Applications (CIDMA) through the Portuguese Foundation

for Science and Technology (FCT - Fundação para a Ciência e a Tecnologia), references UIDB/04106/2020 and UIDP/04106/2020, by the Swiss National Science Foundation grant n. 188430 and the German Research Foundation grant LI 3101/1-1. It will appear as a chapter in "A Concise Encyclopedia of Coding Theory" to be published by CRC Press.

Bibliography

- [1] P. Almeida, D. Napp, and R. Pinto. A new class of superregular matrices and MDP convolutional codes. *Linear Algebra and its Applications*, 439(7):2145–2157, 2013.
- [2] J.-J. Climent, D. Napp, C. Perea, and R. Pinto. A construction of mds 2d convolutional codes of rate $1/n$ based on superregular matrices. *Linear Algebra and its Applications*, 437(3):766–780, 2012.
- [3] J.-J. Climent, D. Napp, C. Perea, and R. Pinto. Maximum distance separable 2d convolutional codes. *IEEE Transactions on Information Theory*, 62(2):669–680, 2016.
- [4] J.-J. Climent, D. Napp, R. Pinto, and R. Simões. Series concatenation of 2d convolutional codes. *Proceedings IEEE 9th International Workshop on Multidimensional (nD) Systems (nDS), Vila Real, Portugal*, 2015.
- [5] A. Dholakia. *Introduction to Convolutional Codes with Applications*. Kluwer Academic Publishers, Boston, 1994.
- [6] P. Elias. Coding for noisy channels. *IRE Conv. Rec.*, 4:37–46, 1955.
- [7] E. Fornasini and G. Marchesini. Structure and properties of two-dimensional systems. *Multidimensional Systems, Techniques and Applications*, editor: S. G. Tzafestas, *Electrical and Computer Engineering*, 9:37–88, 1986.
- [8] G. Forney. Convolutional codes i: Algebraic structure. *IEEE Trans. Inform. Theory. Correction Ibid.*, IT-17, pp. 360, 1071, IT-16(6):720–738, 1970.
- [9] G. D. Forney, Jr. Convolutional codes I: Algebraic structure. *IEEE Trans. Inform. Theory*, IT-16(5):720–738, 1970.
- [10] G. D. Forney, Jr. Structural analysis of convolutional codes via dual codes. *IEEE Trans. Inform. Theory*, IT-19(5):512–518, 1973.
- [11] G. D. Forney, Jr. Convolutional codes II: Maximum likelihood decoding. *Inform. Control*, 25:222–266, 1974.
- [12] F.R. Gantmacher. *The Theory of Matrices, vol. I*. Chelsea Publishing Company, New York, 1977.

- [13] H. Gluesing-Luerssen and B. Langfeld. A class of one-dimensional mds convolutional codes. *Journal of Algebra and Its Applications*, 5(4):505–520, 2006.
- [14] H. Gluesing-Luerssen, J. Rosenthal, and R. Smarandache. Strongly MDS convolutional codes. *IEEE Trans. Inform. Theory*, 52(2):584–598, 2006.
- [15] R. Hutchinson. The existence of strongly MDS convolutional codes. *SIAM J. Control Optim.*, 47(6):2812–2826, 2008.
- [16] R. Hutchinson, J. Rosenthal, and R. Smarandache. Convolutional codes with maximum distance profile. *Systems & Control Letters*, 54(1):53–63, 2005.
- [17] R. Johannesson and K. Sh. Zigangirov. *Fundamentals of Convolutional Coding*. IEEE Press, New York, 1999.
- [18] J. Justesen. An algebraic construction of rate $1/\nu$ convolutional codes. *IEEE Trans. Inform. Theory*, IT-21(1):577–580, 1975.
- [19] T. Kailath. *Linear Systems*. Englewood Cliffs, N.J.: Prentice Hall, 1980.
- [20] B. Kitchens. Symbolic dynamics and convolutional codes. In *Codes, systems, and graphical models (Minneapolis, MN, 1999)*, volume 123 of *IMA Vol. Math. Appl.*, pages 347–360. Springer, New York, 2001.
- [21] B.C. Lévy. *2-D Polynomial and Rational Matrices, and their Applications for the Modeling of 2-D Dynamical Systems*. Ph.D. dissertation, Stanford University, 1981.
- [22] J. Lieb. Complete MDP convolutional codes. *Journal of Algebra and Its Applications*, 2018.
- [23] S. Lin and D. Costello. *Error Control Coding: Fundamentals and Applications*. Prentice Hall Professional Technical Reference, 1994.
- [24] D. Lind and B. Marcus. *An Introduction to Symbolic Dynamics and Coding*. Cambridge University Press, 1995.
- [25] B. Marcus. Symbolic dynamics and connections to coding theory, automata theory and system theory. In *Different aspects of coding theory (San Francisco, CA, 1995)*, volume 50 of *Proc. Sympos. Appl. Math.*, pages 95–108. Amer. Math. Soc., Providence, RI, 1995.
- [26] J. L. Massey and M. K. Sain. Codes, automata, and continuous systems: Explicit interconnections. *IEEE Trans. Automat. Contr.*, AC-12(6):644–650, 1967.

- [27] Robert J. McEliece. The algebraic theory of convolutional codes. In V. Pless and W.C. Huffman, editors, *Handbook of Coding Theory*, volume 1, pages 1065–1138. Elsevier Science Publishers, Amsterdam, The Netherlands, 1998.
- [28] M. Morf, B.C. Lévy, S.Y. Kung, and T. Kailath. New results in 2d systems theory: Part i and ii. *Proc. IEEE*, 65:861–872 and 945–961, 1977.
- [29] D. Napp, C. Perea, and R. Pinto. Input-state-output representations and constructions of finite-support 2d convolutional codes. *Advances in Mathematics of Communications AMC*, 4(4):533–545, 2010.
- [30] D. Napp and R. Smarandache. Constructing strongly-mds convolutional codes with maximum distance profile. *Advances in Mathematics of Communications AMC*, 10(2):275–290, 2016.
- [31] Ph. Piret. Structure and constructions of cyclic convolutional codes. *IEEE Trans. Inform. Theory*, IT-22(2):147–155, 1976.
- [32] P. Rocha. *Structure and Representation of 2-D Systems*. Ph.D. dissertation, University of Groningen, 1990.
- [33] J. Rosenthal. Connections between linear systems and convolutional codes. In B. Marcus and J. Rosenthal, editors, *Codes, Systems and Graphical Models*, IMA Vol. 123, pages 39–66. Springer-Verlag, 2001.
- [34] J. Rosenthal, J. M. Schumacher, and E. V. York. On behaviors and convolutional codes. *IEEE Trans. Inform. Theory*, 42(6, part 1):1881–1891, 1996.
- [35] J. Rosenthal and R. Smarandache. Maximum distance separable convolutional codes. *Appl. Algebra Engrg. Comm. Comput.*, 10(1):15–32, 1999.
- [36] J. Rosenthal and E. V. York. BCH convolutional codes. *IEEE Trans. Inform. Theory*, 45(6):1833–1844, 1999.
- [37] R. Smarandache, H. Gluesing-Luerssen, and J. Rosenthal. Constructions for MDS-convolutional codes. *IEEE Trans. Inform. Theory*, 47(5):2045–2049, 2001.
- [38] R. Smarandache and J. Rosenthal. A state space approach for constructing MDS rate $1/n$ convolutional codes. In *Proceedings of the 1998 IEEE Information Theory Workshop on Information Theory*, pages 116–117, Killarney, Kerry, Ireland, June 1998.
- [39] V. Tomás, J. Rosenthal, and R. Smarandache. Decoding of convolutional codes over the erasure channel. *IEEE Trans. Inform. Theory*, 58(1):90–108, January 2012.

- [40] M.E. Valcher and E. Fornasini. On 2d finite support convolutional codes: an algebraic approach. *Multidimensional Systes and Signal Processing*, 5:231–243, 1994.
- [41] A.J. Viterbi. Error bounds for convolutional codes and an asymptotically optimum decoding algorithm. *IEEE Transactions on Information Theory*, IT-13(2):260–269, 1967.
- [42] P. Weiner. *Multidimensional Convolutional Codes*. Ph.D. dissertation, University of Notre Dame, 1998.
- [43] J. C. Willems. From time series to linear system. Part I: Finite dimensional linear time invariant systems. *Automatica*, 22:561–580, 1986.
- [44] E.V. York. *Algebraic Description and Construction of Error Correcting Codes: A Linear Systems Point of View*. Ph.D. dissertation, University of Notre Dame, 1997.
- [45] D.C. Youla and P.F. Pickel. The quillen-suslin theorem. *IEEE Trans. Ck. Svst.*, pages 513–518, 1984.