arXiv:2002.09296v1 [physics.class-ph] 20 Feb 2020

Stabilization of a Time Dependent Hamiltonian System

Asher Yahalom[a,b] & Natalia Puzanov[a]
[a]Ariel University, Ariel 40700, Israel
[b]Princeton University, Princeton, New Jersey 08543, USA

Abstract

In this paper we consider the unstable chaotic attractor of the Toda potential and stabilize it by a control in integral form. In order to obtain stability results, we propose a special technique which is based on the idea of reduction of integro-differential equations to ordinary differential equations system.

1 Introduction.

The presence of chaos in physical systems has been extensively demonstrated and is very common. In practice, however, it is often desired that chaos should be avoided and that the performance of system should be stabilized. A review of various methods of controlling chaos is presented in [1].

Various stabilization approaches are based on a delayed feedback control scheme [18]. This scheme involves a control signal $u(t)$ generated by the difference between the current state $x(t)$ and the previous state $x(t-\tau)$ of the system. Examples of the use of this method can be found in electronic chaos oscillators [19], magnetoelastic chaos [8], lasers [3], the low-dimensional chaos arising from the nonlinear interaction between the two different types of ionization waves [12], chemical systems [14], [10], plasma [6], [16], Lorenz attractor [17]. Various modifications of this method have been proposed in [21], where an extended delayed feedback controller, using information about many previous states of the system, was suggested. More examples can be found in a review by M.A.F. Sanjuan and C. Grebogi [20].

Consider, for example, the unstable system of ordinary differential equations

$$X'(t) - A(t)X(t) = 0, \tag{1}$$

where $A(t)$ is $n \times n$ matrix and $X(t) = col\left\{x_1(t), ..., x_n(t)\right\}$. Adding a small external force $u(t)$ in the right hand side of this system, we try to obtain various types of regular behavior of the process $X(t)$. This force $u(t)$ can be considered as a control. It is clear that $u(t)$ should depend on the process $X(t)$. We thus obtain the system:

$$X'(t) - A(t)X(t) + Ku(t) = 0, \tag{2}$$

where K is a corresponding $n \times n$ matrix. Usually the control $u(t)$ depends on the values of the process $X(s)$ for $0 \leq s \leq t - \tau$, where $\tau > 0$ is a time of a possible reaction, typical to real systems. One of the simple ideas to achieve a stabilization is to choose the control $u(t)$ in the form $u(t) = X(t - \tau)$. The stabilization is achieved only in the case when the system:

$$X'(t) - A(t)X(t) + KX(t - \tau) = 0, \tag{3}$$

is stable. Describing existing approaches to the study of stability, we consider an autonomous systems i.e. with the case when all the coefficients and delays in system (3) are constants.

Another approach to cope with delays is a reduction model approach, also denoted the finite spectrum assignment technique, which originated in the works of [2, 9, 11, 15]. Recent developments of this concept are discussed in [13] (see also the references therein). A development of this idea is to choose $u(t)$ in the form of the sum:

$$u(t) = \sum_{i=1}^{m} K_i X(t - \tau_i). \tag{4}$$

It looks very natural to choose the control $u(t)$ in the form:

$$u(t) = \int_0^t k(t, s)X(s)ds. \tag{5}$$

in which all the history of the process $X(t)$ is taken into account. It will be convenient for our stabilization purpose to choose:

$$k(t, s) = e^{-\beta(t-s)}. \tag{6}$$

There are two strong objections against the use of the control in integral form. The first one is the following: we have "to remember" all the values of a solution $X(s)$ for $s \in [0, t]$ for computing simulations. The second one is connected with the fact that integral terms accumulate calculation errors. The method we suggest avoids these objections. Using the exponential kernels, we reduce the study of integro-differential system of the order n to analysis of $(n+m)$-th order system of ordinary differential equations [5, 7].

Example. Consider the following scalar equation

$$x'(t) = a_1 x(t) \tag{7}$$

a_1 is a constant. If $a_1 > 0$, then solution of equation (7): $x = 0$ is unstable. Let us use the control $u(t)$ in the form (5), where $k(t, s) = e^{-\beta(t-s)}$ and consider the integro-differential equation:

$$x'(t) - a_1 x(t) + \alpha u(t) = x'(t) - a_1 x(t) + \alpha \int_0^t e^{-\beta(t-s)} x(s)ds = 0, \ t \in [0, +\infty). \tag{8}$$

where α and β are control parameters.

In accordance with the Leibnitz rule of differentiation under the sigh of an integral depending on a parameter and limits of integration depend on the differentiation variable:

$$\frac{d}{dy} \int_{a(y)}^{b(y)} f(x, y)dt = \int_{a(y)}^{b(y)} \frac{\partial}{\partial y} f(x, y)dx + b'(y)f(y, b(y)) - a'(y)f(y, a(y)) \tag{9}$$

we obtain:

$$u'(t) = -\beta \int_0^t e^{-\beta(t-s)} x(s) ds + e^{-\beta(t-t)} x(t) - 0 = -\beta u(t) + x(t) \tag{10}$$

Using Leibnitz rule, we can write the corresponding system in the form:

$$\begin{cases} x'(t) = a_1 x(t) - \alpha u(t), \\ u'(t) = -\beta u(t) + x(t) = 0, \quad t \in [0, +\infty) \\ u(0) = 0 \end{cases} \tag{11}$$

Its characteristic equation is the following:

$$\lambda^2 + (\beta - a_1)\lambda + \alpha - \beta a_1 = 0. \tag{12}$$

The condition:

$$\beta - a_1 > 0 \ \text{ and } \ \alpha - \beta a_1 > 0 \tag{13}$$

is necessary and sufficient for the exponential stability of the system (11). If condition (13) is fulfilled, then the solution $x(t) = 0$ of the equation (8) is exponentially stable.

2 Stabilization of Hamiltonian system by feedback control in integral form.

The state of a Hamiltonian system can be described by N generalized momenta $p \equiv (p_1, ..., p_N)$ and the same number N generalized coordinates $q \equiv (q_1, ..., q_N)$. Here N designates the number of a system's degrees of freedom. The evolution of p and q in time is determined by the equations of motion:

$$\dot{p_i} = -\frac{\partial H}{\partial q_i}; \quad \dot{q_i} = \frac{\partial H}{\partial p_i}; \quad (i = 1, ..., N), \tag{14}$$

which become concrete only with the Hamiltonian:

$$H = (H, p, q, t). \tag{15}$$

The Hamiltonian is given in $2N$ - dimensional phase space (p, q) and may also be an explicit function of time. Pairs of variables (p_i, q_i) are called canonically conjugate pairs and the equations (14) are canonical equations. We consider the two-dimensional motion may be defined by the Hamiltonian

$$H = \frac{p_x^2}{2m} + \frac{p_y^2}{2m} + V(x, y), \quad m = 1, \tag{16}$$

where $V(x, y)$ is Toda lattice potential:

$$V(x, y) = \frac{1}{2}(x^2 + y^2) + x^2 y - \frac{1}{3}y^3 + \frac{3}{2}x^4 + \frac{1}{2}y^4. \tag{17}$$

We rewrite system (14) in the form:

$$\begin{cases} \dot{x} = p_x \\ \dot{y} = p_y \\ \dot{p_x} = -\frac{\partial H}{\partial x} \\ \dot{p_y} = -\frac{\partial H}{\partial y}. \end{cases} \tag{18}$$

or in more concrete form:

$$\begin{cases} \dot{x} = p_x \\ \dot{y} = p_y \\ \dot{p_x} = -x - 2xy - 6x^3 \\ \dot{p_y} = -y - x^2 + y^2 - 2y^3. \end{cases} \tag{19}$$

We represent this system in the time dependent explicit form:

$$\begin{cases} x'(t) = p(t) \\ p'(t) = -x(t) - 2x(t)y(t) - 6x^3(t) \\ y'(t) = q(t) \\ q'(t) = -y(t) - x^2(t) + y^2(t) - 2y^3(t). \end{cases} \tag{20}$$

System (20) is autonomous and homogeneous. Studying the stability of this system, we consider its linear approximation of the original nonlinear system at the equilibrium point: $x = 0, y = 0, p = 0, q = 0$ according to Lyapunov's linearization method:

$$\begin{cases} x'(t) = p(t) \\ p'(t) = -x(t) \\ y'(t) = q(t) \\ q'(t) = -y(t). \end{cases} \tag{21}$$

We rewrite system (21) in the vector form

$$\begin{bmatrix} x'(t) \\ p'(t) \\ y'(t) \\ q'(t) \end{bmatrix} = \begin{bmatrix} 0 & 1 & 0 & 0 \\ -1 & 0 & 0 & 0 \\ 0 & 0 & 0 & 1 \\ 0 & 0 & -1 & 0 \end{bmatrix} \begin{bmatrix} x(t) \\ p(t) \\ y(t) \\ q(t) \end{bmatrix} \tag{22}$$

let us designate:

$$A = \begin{bmatrix} 0 & 1 & 0 & 0 \\ -1 & 0 & 0 & 0 \\ 0 & 0 & 0 & 1 \\ 0 & 0 & -1 & 0 \end{bmatrix} \tag{23}$$

as the (constant) matrix of system (22). The determinant:

$$det(A - \lambda I) = \begin{vmatrix} -\lambda & 1 & 0 & 0 \\ -1 & -\lambda & 0 & 0 \\ 0 & 0 & -\lambda & 1 \\ 0 & 0 & -1 & -\lambda \end{vmatrix} \tag{24}$$

leads to the characteristic equation $det(A - \lambda I) = 0$ which will take the form:

$$\lambda^4 + 2\lambda^2 + 1 = (\lambda^2 + 1)^2 = (\lambda - i)^2(\lambda + i)^2 = 0 \tag{25}$$

and its characteristic roots are

$$\lambda_1 = \lambda_2 = i, \quad \lambda_3 = \lambda_4 = -i. \tag{26}$$

Now if:

$$det(A - \lambda I) = (\lambda - \lambda_1)^{m_1}(\lambda - \lambda_2)^{m_2}...(\lambda - \lambda_i)^{m_i}...(\lambda - \lambda_n)^{m_n} \tag{27}$$

then elementary divisors are $(\lambda-\lambda_1)^{m_1}$, . . . , $(\lambda-\lambda_i)^{m_i}$, ... Their number is the same as the number of the Jordan blocks of A and the elementary divisor $(\lambda - \lambda_i)^{m_i}$ corresponds to a Jordan blocks of oder m_i. If $m_i = 1$ then $(\lambda - \lambda_i)$ is a simple elementary divisor. It follows that the Jordan form of (23) consists of two blocks corresponding to each of the characteristic roots.

In accordance with the theorem, which was proved in the monograph [4], a linear homogeneous system with constant matrix A is stable if and only if all of its eigenvalues have nonpositive real parts, and the eigenvalues with zero real part may have only simple elementary divisors. That is, the corresponding Jordan cells are reduced to one element.

So the linear system (21) is chaotic behavior and hence also the nonlinear system (20) is chaotic. The chaotic behaviour is demonstrated in Figure 1 where one can easily see than trajectories filling the area (see also [23]).




Figure 1. The phase portrait of the solution of system (20) in the (y, q) plane for a) $E = 0.214$, b) $E = 3.0$ and c) $E = 5.0$ with initial conditions: $x(0) = 0,\ y(0) = 0,\ p(0) = \sqrt{2E}\sin\left(\frac{a\pi}{2}\right),\ q(0) = \sqrt{2E}\cos\left(\frac{a\pi}{2}\right),$ For $a = 0$ (gray), $a = 0.1$ (green), $a = 0.2$ (pink), $a = 0.3$ (yellow), $a = 0.4$ (red), $a = 0.5$ (brown), $a = 0.6$ (magenta), $a = 0.7$ (auqamarine), $a = 0.8$ (blue), $a = 0.9$ (cyan), $a = 1.0$ (black)

3 Stabilization of Hamiltonian system by feedback control in integral form

Let us use the control $u(t)$ in the form [22]:

$$u(t) = \int_0^t e^{-\beta(t-s)} q(s) ds, \tag{28}$$

in which all the history of the process q(t) is taken into account [5]. We apply stabilization to the second equation of system (20) by feedback delay control, because for a mechanical system control is normally applied to acceleration.

$$\begin{cases} x'(t) = p(t) \\ p'(t) = -x(t) - 2x(t)y(t) - 6x^3(t) - \alpha \int_0^t e^{-\beta(t-s)} p(s) ds \\ y'(t) = q(t) \\ q'(t) = -y(t) - x^2(t) + y^2(t) - 2y^3(t) \end{cases} \tag{29}$$

where α and β are control parameters. We can rewrite the system (29) in a form of the system of ordinary differential equations according to Leibnitz rule (21):

$$\begin{cases} x'(t) = p(t), \\ p'(t) = -x(t) - 2x(t)y(t) - 6x^3(t) - \alpha u(t) \\ y'(t) = q(t) \\ q'(t) = -y(t) - x^2(t) + y^2(t) - 2y^3(t) \\ u'(t) = p(t) - \beta u(t). \end{cases} \tag{30}$$

System (30) is autonomous and homogeneous. Studying the stability of this system, we consider its linear approximation of the original nonlinear system at the equilibrium point $x = 0, y = 0, p = 0, q = 0, u = 0$:

$$\begin{cases} x'(t) = p(t), \\ p'(t) = -x(t) - \alpha u(t) \\ y'(t) = q(t) \\ q'(t) = -y(t) \\ u'(t) = p(t) - \beta u(t) \end{cases} \tag{31}$$

The constant matrix of the system (31) is:

$$A = \begin{bmatrix} 0 & 1 & 0 & 0 & 0 \\ -1 & 0 & 0 & 0 & -\alpha \\ 0 & 0 & 0 & 1 & 0 \\ 0 & 0 & -1 & 0 & 0 \\ 0 & 1 & 0 & 0 & -\beta \end{bmatrix} \tag{32}$$

Which leads to the characteristic equation:

$$det(A - \lambda I) = \begin{vmatrix} -\lambda & 1 & 0 & 0 & 0 \\ -1 & -\lambda & 0 & 0 & -\alpha \\ 0 & 0 & -\lambda & 1 & 0 \\ 0 & 0 & -1 & -\lambda & 0 \\ 0 & 1 & 0 & 0 & -\lambda - \beta \end{vmatrix} = 0 \tag{33}$$

The characteristic equation can be also written in the form:

$$\begin{gathered} -\left(\lambda^5+\lambda^4\beta+(\alpha+2)\lambda^3+2\beta\lambda^2+(\alpha+1)\lambda+\beta\right)= \\ -\left(\lambda^3+\lambda^2\beta+\lambda(1+\alpha)+\beta\right)\left(\lambda^2+1\right)=0 \end{gathered} \tag{34}$$

and

$$\lambda_1=\frac{C}{6}-\frac{2D}{C}-\frac{\beta}{3};\quad \lambda_{2,3}=-\frac{C}{12}+\frac{D}{C}-\frac{\beta}{3}\pm i\sqrt{3}\left(\frac{C}{6}+\frac{2D}{C}\right);\quad \lambda_{4,5}=\pm i. \tag{35}$$

where

$$\begin{gathered} A=12+36\alpha+24\beta^2+36\alpha^2-60\alpha\beta^2+12\beta^4+12\alpha^3-3\alpha^2\beta^2; \\ B=-72\beta+36\alpha\beta-8\beta^3; C=\left(B+12\sqrt{A}\right)^{\frac{1}{3}};\ D=\frac{1}{3}\left(1+\alpha-\frac{\beta}{3}\right). \end{gathered} \tag{36}$$

For $\alpha>0$, $\beta>0$ λ_1 and real parts of λ_2 and λ_3 are negative. According to J. L. Massera's theorem, this is a stability indication for nonlinear ODE systems [4]. Massera's theorem states that given a nonlinear homogeneous system:

$$\frac{dy}{dt}=A(t)y+f(t,y);\ f(t,0)\equiv 0, \tag{37}$$

the function y is limited, If:

1)

$$\|f(t,y)\|\le\psi(t)\|y\|^m,\qquad (m>1) \tag{38}$$

where $\psi(t)$ is a positive function such that:

$$\lim_{x\to\infty}\frac{1}{t}ln|\psi(t)|=0 \tag{39}$$

2) for Lyapunov characteristic exponents $a_1,...a_n$ of the linear approximation of a nonlinear system:

$$\frac{dy}{dt}=A(t)y \tag{40}$$

the inequality:

$$max_k(a_k)<-\frac{\kappa}{m-1}\le 0 \tag{41}$$

is fulfilled, where:

$$\kappa=\sum_{k=1}^{n}a_k-\lim_{x\to\infty}\frac{1}{t}\int_0^t tr\{A(t_1)\}dt_1 \tag{42}$$

then the solution $y\equiv 0$ of a nonlinear system is asymptotically stable (Lyapunov) for $t\to\infty$. In the neighborhood of $y=0$, which is the equilibrium position of the system (30), nonlinear terms are smaller then linear ones. System (30) is a system with constant coefficients (autonomous), therefore conditions (38) and (39) are satisfied, i.e. condition **1)** fulfilled.

Since the characteristic exponents $a_j(j=1,...,n)$ of solutions of a linear system

$$\frac{dy}{dt}=Ay(t) \tag{43}$$

with a constant matrix A are the real parts of the characteristic roots of the matrix A, i.e.

$$a_j = Re\lambda_j(A) \quad (j = 1, ..., n) \tag{44}$$

where $\lambda_j = \lambda_j(A)$ are roots of the equation $det(A - \lambda E) = 0$ [4] then condition **2)** is fulfilled as

$$max_k(a_k) = max(\lambda_1, Re\lambda_{2,3}) < 0, \tag{45}$$

$$\sum_{k=1}^{3} a_k = \lambda_1 + 2Re\lambda_{2,3} = -\beta \tag{46}$$

and

$$\lim_{x\to\infty} \frac{1}{t} \int_0^t tr\{A\}dt_1 = -\beta. \tag{47}$$

Thus

$$\kappa = \sum_{k=1}^{3} a_k - \lim_{x\to\infty} \frac{1}{t} \int_0^t tr\{A\}dt_1 = 0 \tag{48}$$

and inequality (41) is fulfilled. The stabilized solution is demonstrated in figure 2 where the trajectories are periodic and are not surface filling.




Figure 2. The phase portrait of the solution of system (19) in the (y, q) plane for a) $E = 0.214$, b) $E = 3.0$ and c) $E = 5.0$ with initial conditions:
$x(0) = 0,\ y(0) = 0,\ p(0) = \sqrt{2E}\sin\left(\frac{a\pi}{2}\right),\ q(0) = \sqrt{2E}\cos\left(\frac{a\pi}{2}\right),$
$\alpha = 2.0, \beta = 1.0, \quad 40 \le t \le 300$
For $a = 0$ (gray), $a = 0.1$ (green), $a = 0.2$ (pink), $a = 0.3$ (yellow), $a = 0.4$ (red), $a = 0.5$ (brown), $a = 0.6$ (magenta), $a = 0.7$ (auqamarine), $a = 0.8$ (blue), $a = 0.9$ (cyan), $a = 1.0$ (black)

4 Conclusion

This model satisfies the rapid convergence of the process to a limit cycle with a small control function $u(t)$.




Figure 3. The control function $u(t)$ (red) as compared to the stabilized process $p(t)$ (blue). $E = 5.0, \alpha = 2.0, \beta = 1.0, a = 0.5$

This model differs from the methods described in publications of other authors by the absence of an adjustable parameters and rough approximations in determining of the control function.

It should be noted that the period of limit cycle obtained by above-described method is not associated with the "period" of a chaotic motion but is automatically obtained by the substitution of the values of the control parameters α and β to the nonlinear differential equations system.

References

[1] B.R. Andrievskii, A.L. Fradkov, Control of chaos: Methods and applications. I. Methods. Autom. and Rem. Control. v.64, pp.3-45. (2003); B.R. Andrievskii, A.L. Fradkov, Control of chaos: Methods and applications. II.Applications. Automation and Remote Control, v.65, pp.505-533. (2004).

[2] Z.Artstein, Linear systems with delayed controls: a reduction, *IEEE Transactions on Automatic Control,* 1982, AC-27, 869-879.

[3] S.Bielawski, B.Bouazaoui, D.Derozier and P.Glorieux. Stabilization and characterization of unstable steady states . Phys. Rev. A 47, pp 3276-3279, (1993).

[4] B.P. Demidovich, Lectures on the Mathematical Theory of Stability, Nauka, Moskow, (1967).

[5] A.Domoshnitsky, Ya.Goltser. One approach to study stability ofintegro-differential equations, Nonlinear Analysis: TMA, 47 (2001),3885-3896.

[6] T. Fukuyama, H. Shirahama, and Y. Kawai. Dynamical control of the chaotic state of the current-driven ion acoustic instability in a laboratory plasma using delayed feedback. Physics of Plasmas, 9, 4525 (2002).

[7] Ya.Goltser and A.Domoshnitsky. Bifurcation and stability of integro-differential equations, Nonlinear Analysis.Theory, Methods and Applications, 47 (2001), pp.953-967.

[8] T.Hikihara and T.Kawagoshi. An experimental study on stabilization of unstable periodic motion in magnetoelastic chaos. Phys. Lett. A 211, 29 (1996).

[9] W.H.Kwon and A.E.Pearson, feedback stabilization of linear sustems with delayed control, *IEEE Transactions on Automatic Control,* 1980, AC-25 (2), 266-269.

[10] A. Lekebusch, A. Foerster, and F. W. Schneider, Chaos Control in an Enzymatic Reaction. J. Phys. Chem., 99, 681 (1995).

[11] A.Manitius and A.Olbrot, Finite spectrum assignment problem for systems with delays, *IEEE Transactions on Automatic Control,* 1979, 24, 541-553.

[12] Th.Mausbach, T.Klinger, A.Piel, A.Atipo, Th.Pierre, G.Bonhomme, Continuous control of ionization wave chaos by spatially derived feedback signals. Phys. Lett. A 228 (1997) 373.

[13] F.Mazenc and S-I.Niculescu, Generating positive and stable solutrions through delayed state feedback, Automatica 2011, doi:10.10.16/j.automatica.2011.01.029.

[14] P.Parmananda, R.Madrigal M.Rivera, L.Nyikos, Z.Kissand V.Gaspar. Stabilization of unstable steady states and periodic orbits in an electrochemical system using delayed-feedback control. Phys. Rev. E 59, 5266 (1999).

[15] A.Olbrot, Stabilizability, detectability and spectrum assignment for linear autonomous systems with general tome delays, *IEEE Transactions on Automatic Control,* 1978, 23, 605-618.

[16] Th. Pierre, G. Bonhomme and A. Atipo. Controlling the Chaotic Regime of Nonlinear Ionization Waves using the Time-Delay Autosynchronization Method Phys. Rev. Lett., 76, 2290 (1996).

[17] Claire M. Postlethwaite and Mary Silber. Stabilizing unstable periodic orbits in the Lorenz equations using time-delayed feedback control. Engineering Sciences and Applied Mathematics, Northwestern University, Evanston, IL, 60208, USA.

[18] K.Pyragas. Control of chaos via an unstable delayed feedback controller, Phys. Rev. Lett., vol.86, No 11, March 2001, pp.2265-2268;

[19] K.Pyragas and A.Tamasevicius. Experimental control of chaos by delayed self-controlling feedback. Phys. Lett. A 180, 99 (1993).

[20] M.A.F. Sanjuan, C. Grebogi : Recent Progress in Controlling Chaos, Vol.16, Word Scientific Publishing Co.Pte. Ltd., Singapure (2010)

[21] J.E.S. Socolar, D.W. Sukow and D.J. Gauthier. Stabilizing unstable periodic orbits in fast dynamical systems. Phys. Rev. E50, 3245, (1994).

[22] A Domoshnitsky and A Maghakyan and N Puzanov. About Stabilization by Feedback Control in Integral Form. Georgian Math 19:665-685, 2012.

[23] A. Yahalom, M. Lewkowicz, J. Levitan, G. Elgressy, L.P. Horwitz and Y. Ben-Zion, "Uncertainty Relation for Chaos" International Journal of Geometric Methods in Modern Physics. DOI: 10.1142/S0219887815500930. Vol. 12 (2015) 1550093 (12 pages), ©World Scientific Publishing Company.