

OVERDETERMINED INDEPENDENT VECTOR ANALYSIS

Rintaro Ikeshita, Tomohiro Nakatani, Shoko Araki

NTT Communication Science Laboratories, NTT Corporation, Kyoto, Japan

ABSTRACT

We address the convolutive blind source separation problem for the (over-)determined case where (i) the number of nonstationary target-sources K is less than that of microphones M , and (ii) there are up to $M - K$ stationary Gaussian noises that need not to be extracted. Independent vector analysis (IVA) can solve the problem by separating into M sources and selecting the top K highly nonstationary signals among them, but this approach suffers from a waste of computation especially when $K \ll M$. Channel reductions in preprocessing of IVA by, e.g., principle component analysis have the risk of removing the target signals. We here extend IVA to resolve these issues. One such extension has been attained by assuming the orthogonality constraint (OC) that the sample correlation between the target and noise signals is to be zero. The proposed IVA, on the other hand, does not rely on OC and exploits only the independence between sources and the stationarity of the noises. This enables us to develop several efficient algorithms based on block coordinate descent methods with a problem specific acceleration. We clarify that one such algorithm exactly coincides with the conventional IVA with OC, and also explain that the other newly developed algorithms are faster than it. Experimental results show the improved computational load of the new algorithms compared to the conventional methods. In particular, a new algorithm specialized for $K = 1$ outperforms the others.

Index Terms— Blind source separation, overdetermined, independent vector analysis, block coordinate descent method, generalized eigenvalue problem

1. INTRODUCTION

Blind source separation (BSS) is a problem of estimating the source signals from their observed mixtures [1, 2]. In this paper, we focus on the (over-)determined BSS where the number of nonstationary signals K is less than that of microphones M , i.e., $K < M$. There can be up to $M - K$ stationary Gaussian noises as long as the problem remains (over-)determined.¹ The goal is to extract K nonstationary signals efficiently. We do not care about separating the noises.

If the mixture is convolutive, *independent vector analysis* (IVA [3, 4]) is one of the most fundamental methods to solve BSS. As a straightforward way, we can apply IVA as if there are M nonstationary sources and select the top $K (< M)$ highly nonstationary signals among the M separated signals. This method is, however, computationally intensive and does not run in realtime if M is large. To improve the computational efficiency, in preprocessing of IVA, we can reduce the number of channels up to K by using principle component analysis or picking up K channels with high SNR. These channel reductions, however, have the risk of removing the target signals and often degrade the separation performance [5].

¹The assumption that there are at most $M - K$ noises is for the sake of developing efficient algorithms rigorously and can be violated to some extent (see Section 6).

BSS methods for efficiently extracting just one or several target signals with specific properties such as non-Gaussianity has already been studied [6–11]. Among them, we only focus on methods in which the demixing filters can be optimized by using an *iterative projection (IP)* [12–14] technique. IP is a class of *block coordinate descent (BCD)* methods specialized for optimizing the maximum-likelihood-based IVA, with the advantages of high computational efficiency and no hyperparameters. Recently proposed *OverIVA* [5] (IVA for the overdetermined case), which is a multi-target-source extension of independent component/vector extraction (ICE/IVE [15, 16]), takes the advantages of IP, resulting in significantly improved computational cost of IVA. In addition to IP, OverIVA as well as ICE/IVE also relies on the orthogonality constraint (OC) that the sample correlation between the separated target and noise signals is to be zero. As OC is a heuristic assumption for developing efficient algorithms, the open problems here are (i) to theoretically clarify the validity of OC, and (ii) to further accelerate OverIVA.

In this paper, we propose a different approach for BSS, which we call OverIVA as well. It does not employ OC and exploits only the independence between sources and the stationarity of the Gaussian noises (see Section 3). For this model, we develop several efficient optimization algorithms based on BCD, all of which can be viewed as extensions of IP (see Section 4). We then prove that one such algorithm exactly coincides with OverIVA with OC [5], meaning that the stationarity of the Gaussian noises implicitly implies OC (see Section 5). We also describe that the other newly developed algorithms are expected to be faster than OverIVA with OC (see Section 5), and confirm their effectiveness in the experiment (see Section 6).

2. PROBLEM FORMULATION

Suppose that K nonstationary source signals are mixed with a stationary noise, or possibly a silent signal, of dimension $M - K$ and observed with M microphones, where $1 \leq K \leq M - 1$. In the time-frequency domain, the mixture signal, $\mathbf{x}(f, t)$, is modeled by

$$\mathbf{x}(f, t) = A_s(f)\mathbf{s}(f, t) + A_z(f)\mathbf{z}(f, t) \in \mathbb{C}^M, \quad (1)$$

$$A_s(f) = [\mathbf{a}_1(f), \dots, \mathbf{a}_K(f)] \in \mathbb{C}^{M \times K}, \quad A_z(f) \in \mathbb{C}^{M \times (M-K)},$$

$$\mathbf{s}(f, t) = [s_1(f, t), \dots, s_K(f, t)]^\top \in \mathbb{C}^K, \quad \mathbf{z}(f, t) \in \mathbb{C}^{M-K},$$

where $f \in \{1, \dots, F\}$ and $t \in \{1, \dots, T\}$ denote the frequency bin and time-frame indexes, respectively, $^\top$ is the transpose, $\mathbf{a}_k(f)$ and $s_k(f, t)$ are the transfer function and signal for the target source k , respectively, and $A_z(f)$ and $\mathbf{z}(f, t)$ are those for the noise source.

The demixing matrix $W(f) = [\mathbf{w}_1(f), \dots, \mathbf{w}_M(f)] \in \mathbb{C}^{M \times M}$ satisfying $W(f)^\text{H}[A_s(f), A_z(f)] = I_M$ translates (1) into

$$s_k(f, t) = \mathbf{w}_k(f)^\text{H} \mathbf{x}(f, t) \in \mathbb{C}, \quad k \in \{1, \dots, K\}, \quad (2)$$

$$\mathbf{z}(f, t) = W_z(f)^\text{H} \mathbf{x}(f, t) \in \mathbb{C}^{M-K}, \quad (3)$$

$$W_z(f) = [\mathbf{w}_{K+1}(f), \dots, \mathbf{w}_M(f)] \in \mathbb{C}^{M \times (M-K)}, \quad (4)$$

where I_M is the identity matrix and H is the Hermitian transpose.

The BSS problem dealt with in this paper is to recover the spatial images of the target nonstationary sources, $\{\mathbf{a}_k(f)s_k(f, t)\}_{k,f,t}$ under the assumption that K is given and the source signals are independent of each other. Once the demixing matrices $\{W_z(f)\}_f$ are obtained, we can estimate the spatial images using projection back technique [17] as follows (here $\mathbf{e}_k \in \mathbb{C}^M$ denotes the unit vector whose k th element is equal to one and the others zero):

$$\mathbf{a}_k(f)s_k(f, t) = (W(f)^{-H}\mathbf{e}_k)(\mathbf{w}_k(f)^H\mathbf{x}(f, t)) \in \mathbb{C}^M. \quad (5)$$

3. PROBABILISTIC MODEL

We present the probabilistic model of the proposed OverIVA, which is almost identical to that of the ordinary IVA [3, 4]. The only difference is in the model of the stationary noise that we do not need to estimate. In fact, the proposed model is defined by (2)–(4) and the following (6)–(8): $\mathbf{s}_k(t) := [s_k(1, t), \dots, s_k(F, t)]^T \in \mathbb{C}^F$, and

$$p(\{\mathbf{s}_k(t), \mathbf{z}(f, t)\}_{k,f,t}) = \prod_{k,t} p(\mathbf{s}_k(t)) \cdot \prod_{f,t} p(\mathbf{z}(f, t)), \quad (6)$$

$$\mathbf{s}_k(t) \sim \mathcal{CN}(\mathbf{0}, \lambda_k(t)I_F), \quad k \in \{1, \dots, K\}, \quad (7)$$

$$\mathbf{z}(f, t) \sim \mathcal{CN}(\mathbf{0}, I_{M-K}), \quad (8)$$

where $\{\lambda_k(t)\}_t$ are frequency-independent time-varying variances modeling the power spectrum for source k . The parameters to be optimized in the model are the demixing matrix $\mathbf{W} := \{W(f)\}_f$ and power spectra $\boldsymbol{\lambda} := \{\lambda_k(t)\}_{k,t}$.

Note that the noise model (8) with the constant covariance matrix does not sacrifice generality. At first glance, it seems better to employ $\mathbf{z}(f, t) \sim \mathcal{CN}(\mathbf{0}, R(f))$ with a general $R(f)$ being a parameter to be optimized. However, as we are not interested in the noise components, we can freely change the variables to satisfy (8) using the ambiguity between $A_z(f)$ and $\{\mathbf{z}(f, t)\}_{t=1}^T$ as follows:

$$A_z(f)\mathbf{z}(f, t) = (A_z(f)R(f)^{\frac{1}{2}})(R(f)^{-\frac{1}{2}}\mathbf{z}(f, t)).$$

4. OPTIMIZATION

We develop an algorithm for the maximum likelihood (ML) estimation of the parameters $\mathbf{W}$ and $\boldsymbol{\lambda}$. The ML estimation is attained by minimizing the negative log-likelihood J , which is computed as

$$J = \sum_{k,t} \left[\frac{\|\mathbf{s}_k(t)\|^2}{\lambda_k(t)} + F \log \lambda_k(t) \right] + \sum_{f,t} \|\mathbf{z}(f, t)\|^2 - 2T \sum_f \log |\det W(f)| + C,$$

where C is a constant independent of the parameters.

As is often the case with IVA, the proposed algorithm updates $\mathbf{W}$ and $\boldsymbol{\lambda}$ alternately. When $\mathbf{W}$ is kept fixed, $\boldsymbol{\lambda}$ can be globally optimized by $\lambda_k(t) = \frac{1}{F} \|\mathbf{s}_k(t)\|^2$.

In what follows, we will develop several computationally efficient algorithms that optimize $\mathbf{W}$, keeping $\boldsymbol{\lambda}$ fixed. The objective function J with respect to $\mathbf{W} = \{W(f)\}_{f=1}^F$ is additively separable for each frequency bin f . This enables us to split the problem into F independent problems, each of which is described as (P1) below. We hereafter abbreviate the frequency bin index f to simplify the notation without mentioning it.

$$\underset{\mathbf{W}}{\text{minimize}} J_W, \quad (\text{P1})$$

$$J_W = \sum_{k=1}^K \mathbf{w}_k^H G_k \mathbf{w}_k + \text{tr}(W_z^H G_z W_z) - 2 \log |\det W|,$$

$$G_k = \frac{1}{T} \sum_{t=1}^T \frac{\mathbf{x}(t)\mathbf{x}(t)^H}{\lambda_k(t)} \in \mathbb{C}^{M \times M}, \quad k \in \{1, \dots, K\},$$

$$G_z = \frac{1}{T} \sum_{t=1}^T \mathbf{x}(t)\mathbf{x}(t)^H \in \mathbb{C}^{M \times M}.$$

Table 1. Optimization procedure for each method

Method	Procedure
IP-0 (§4.1.1 [13])	Optimize $\mathbf{w}_1, \dots, \mathbf{w}_K, \dots, \mathbf{w}_M$ cyclically.
IP-1 (§4.1.2)	Optimize $\mathbf{w}_1, \dots, \mathbf{w}_K, W_z$ cyclically.
IP-2 (§4.1.3)	Optimize $\mathbf{w}_1$ and W_z simultaneously (when $K = 1$).
IP-3 (§5 [5])	Optimize $\mathbf{w}_1, W_z, \mathbf{w}_2, W_z, \dots, \mathbf{w}_K, W_z$ cyclically.

4.1. The algorithms to optimize $\mathbf{W}$

If $K = M$ and the noise component does not exist, the problem (P1) is known as the ML based ICA [18–21]. Block coordinate descent (BCD) methods have been proposed to solve it [12–14, 22, 23] and reported to be faster and to give higher separation performance than other algorithms such as the natural gradient method [24] and FastICA [8, 9] (see, e.g., [12]). The family of these BCD algorithms specialized to solve the ML based ICA is currently called an *iterative projection (IP) method* [25]. Even when $K < M$, IP can directly be applied to the problem (P1) by translating the second term of J_W as $\text{tr}(W_z^H G_z W_z) = \sum_{k=K+1}^M \mathbf{w}_k^H G_z \mathbf{w}_k$. The problem is, however, a huge wasted computational cost especially in the case of $K \ll M$.

We therefore propose two different computationally efficient algorithms based on BCD to solve the problem (P1). We call them IP-1 and IP-2, respectively, because they can be viewed as extensions of the conventional IP, named IP-0 in this paper. All algorithms exactly optimize one or several columns of $\mathbf{W}$ in each iteration while keeping all other columns fixed. The procedures of IP-1 and IP-2 as well as IP-0, are summarized in Table 1. As we will clarify in Section 5, that the conventional OverIVA [5] can be obtained from the proposed OverIVA by selecting IP-3 in Table 1 as an optimization procedure of BCD. To make the algorithms work properly, we need to introduce two technical but essential conditions (C1) and (C2):²

(C1) $G_1, \dots, G_K, G_z$ are positive definite.

(C2) Estimates of $\mathbf{W}$ are always nonsingular during optimization.

As we will see, the algorithms are developed by exploiting the first order necessary optimality (stationary) conditions of the problem (P1) with respect to $\mathbf{w}_k$ ($k = 1, \dots, K$) and W_z , which are expressed as follows (see, e.g., [20, 21]):

$$\frac{\partial J_W}{\partial \mathbf{w}_k^*} = \mathbf{0}_M \iff W^H G_k \mathbf{w}_k = \mathbf{e}_k \in \mathbb{C}^M, \quad (9)$$

$$\frac{\partial J_W}{\partial W_z^*} = \mathbf{0} \iff W^H G_z W_z = E_z \in \mathbb{C}^{M \times (M-K)}, \quad (10)$$

where $*$ denotes the element-wise conjugate, $\mathbf{0}_M \in \mathbb{C}^M$ means the zero vector while $\mathbf{0} \in \mathbb{C}^{M \times (M-K)}$ denotes the zero matrix, and we define $E_z := [\mathbf{e}_{K+1}, \dots, \mathbf{e}_M] \in \mathbb{C}^{M \times (M-K)}$.

4.1.1. The review of the conventional IP: IP-0

We review IP-0 for solving the problem (P1) (see [13] for the details). In each iteration, IP-0 updates $\mathbf{w}_k$ for some $k = 1, \dots, M$ ($> K$) so that it globally minimizes J_W with respect to $\mathbf{w}_k$ while keeping all other variables fixed. This is achieved under (C1)–(C2) by

$$\mathbf{u}_k \leftarrow (W^H G_k)^{-1} \mathbf{e}_k \in \mathbb{C}^M, \quad (11)$$

$$\mathbf{w}_k \leftarrow \mathbf{u}_k \left(\mathbf{u}_k^H G_k \mathbf{u}_k \right)^{-\frac{1}{2}} \in \mathbb{C}^M. \quad (12)$$

²If (C1) is violated, the problem (P1) has no optimal solutions and the algorithms diverge to infinity (see [26, Proposition 1] for the proof). In practice, we can always guarantee (C1) by adding small εI_M heuristically (see Algorithm 1). The condition (C2) is satisfied automatically if we initialize $\mathbf{W}$ as nonsingular. Intuitively, a singular $\mathbf{W}$ implies $-\log |\det \mathbf{W}| = +\infty$, which will never occur during optimization.

Here, $G_k := G_z$ ($k = K + 1, \dots, M$), and the k th column of W in (11), w_k , is set to the current estimate before update. It is guaranteed that updating w_k with (11)–(12) will not increase the value of J_W .

4.1.2. The derivation of IP-1

We derive IP-1 that updates $w_1, \dots, w_K, W_z$ cyclically. The update rules for $w_1, \dots, w_K$ are given by (11)–(12) while that for W_z is defined by (17) below. To begin with, we enumerate all global solutions for the problem of minimizing J_W with respect to W_z when keeping $w_1, \dots, w_K$ fixed.

Proposition 1. Suppose (C1) and (C2). A matrix W_z satisfies the stationary condition (10) if and only if

$$U_z \leftarrow (W^H G_z)^{-1} E_z, \quad (13)$$

$$W_z \leftarrow U_z \left(U_z^H G_z U_z \right)^{-\frac{1}{2}} Q, \quad Q \in \mathcal{U}_{M-K}, \quad (14)$$

where $\mathcal{U}_{M-K}$ is the set of all unitary matrices of size $M - K$, and the last $M - K$ columns of W in (13), W_z , are set to the current estimate before update.

Moreover, (13)–(14) with an arbitrary $Q \in \mathcal{U}_{M-K}$ globally minimizes J_W if $w_1, \dots, w_K$ are kept fixed.

Proof. The first K rows of (10) are linear with respect to W_z and solved as $W_z = U_z B$, where U_z is defined by (13) and $B \in \mathbb{C}^{(M-K) \times (M-K)}$ is a free parameter. The remaining $M - K$ rows of (10) constrain B and we obtain (13)–(14), which certainly satisfies the stationary condition (10).

We next prove the latter statement. As (13)–(14) satisfies (10), $\text{tr}(W_z^H G_z W_z) = M - K$ holds. It also holds that $|\det W| = |\det[W_s, W_z Q^{-1}]|$ for any $Q \in \mathcal{U}_{M-K}$. Hence, J_W takes the same value on all stationary points. On the other hand, by Proposition 4, J_W attains its minimum at some W_z , and this W_z must satisfy the stationary condition (10). $\square$

From Proposition 1, as an update formula of W_z , we can use (13)–(14) with $Q = I_{M-K}$. Although this formula guarantees the monotonic nonincrease of the cost function, the computation of (14) is not efficient. We therefore propose an acceleration of (13)–(14), resulting in (17) below.

We now show that we can adopt (17) below as an update formula for W_z if we do not need to separate the noise to satisfy (8). Let U_z and W_z be defined by (13) and (14), respectively. Let also $W'_z \in \mathbb{C}^{M \times (M-K)}$ be a matrix satisfying $\text{Im } W'_z = \text{Im } U_z (= \text{Im } W_z)$, i.e., $W'_z = W_z R$ for some $R \in \mathbb{C}^{(M-K) \times (M-K)}$. Then, concerning (11) and (13), we have

$$(W'^H G_k)^{-1} e_k = (W^H G_k)^{-1} e_k, \quad k = 1, \dots, K, \quad (15)$$

$$\text{Im} \left((W'^H G_z)^{-1} E_z \right) = \text{Im} \left((W^H G_z)^{-1} E_z \right), \quad (16)$$

where $W' := [W_s, W'_z]$. The equality (15) implies that using W' instead of W does not affect the resultant w_k obtained from (11)–(12) for each $k = 1, \dots, K$. Also, (16) means that $\text{Im } U_z$ is updated to the same subspace in (13) regardless of whether we use W or W' on the right hand side of (13). Hence, it turns out that we only have to update W_z so as to satisfy $\text{Im } W_z = \text{Im } U_z$, unless we care about the noise components. Such update of W_z can be attained simply by $W_z \leftarrow U_z := (W^H G_z)^{-1} E_z$. In this paper, inspired by [5], we propose a more efficient update:

$$W_z \leftarrow \begin{pmatrix} -(W_s^H G_z E_s)^{-1} (W_s^H G_z E_z) \\ I_{M-K} \end{pmatrix} \in \mathbb{C}^{M \times (M-K)}, \quad (17)$$

where $E_s := [e_1, \dots, e_K]$ and $W_s := [w_1, \dots, w_K] = W E_s$. We can check using the block matrix inversion that W_z obtained by (17) satisfies $\text{Im } W_z = \text{Im } U_z$, where U_z is given by (13). This concludes the derivation of IP-1 and the procedure of IP-1 is summarized in Algorithm 2.

4.1.3. The derivation of IP-2 only for $K = 1$

When $K = M = 2$ (or $K = 1$ and $M = 2$), it is known that the problem (P1) can be solved directly through a generalized eigenvalue problem [14, 23, 25]. We here extend this direct method to the case where $K = 1$ and $M \geq 2$, which is summarized in Proposition 2.

Proposition 2. Suppose (C1) and (C2), and let $K = 1$ and $M \geq 2$. Then, a matrix $W = [w_1, W_z]$ satisfies the stationary condition (9)–(10) if and only if

$$u_1 \in \mathbb{C}^M \text{ satisfying } G_z u_1 = \lambda G_1 u_1, \quad (18)$$

$$U_z \in \mathbb{C}^{M \times (M-1)} \text{ satisfying } U_z^H G_z u_1 = \mathbf{0}_{M-1}, \quad (19)$$

$$w_1 = u_1 \left(u_1^H G_1 u_1 \right)^{-\frac{1}{2}} e^{\sqrt{-1}\theta}, \quad \theta \in \mathbb{R}, \quad (20)$$

$$W_z = U_z \left(U_z^H G_z U_z \right)^{-\frac{1}{2}} Q, \quad Q \in \mathcal{U}_{M-1}, \quad (21)$$

where (18) is the generalized eigenvalue problem with u_1 and $\lambda \in \mathbb{R}$ being a generalized eigenvector and the corresponding eigenvalue.

Moreover, if λ in (18) is chosen as the largest generalized eigenvalue, then any W obtained by (18)–(21) globally minimizes J_W .

Proof. The “if” part is obvious and we prove the “only if” part. The equations (9)–(10) imply $w_1^H G_1 w_1 = 1$ and that $G_1 w_1$ and $G_z w_1$ are orthogonal to the subspace $\text{Im } W_z$ of dimension $M - 1$. Hence, (18) and (20) are necessary. Also, the equations (9)–(10) together with (20) imply $W_z^H G_z W_z = I_{M-1}$ and that $G_z u_1$ are orthogonal to $\text{Im } W_z$. Thus, (19) and (21) are necessary.

We next prove the latter statement. As (18)–(21) satisfy (9)–(10), the sum of the first and second terms of J_W becomes M . On the other hand, as for the log det term, it holds that

$$\begin{aligned} |\det W| &= \left(u_1^H G_1 u_1 \right)^{-\frac{1}{2}} \cdot \det \left(U_z^H G_z U_z \right)^{-\frac{1}{2}} \cdot |\det U| \\ &= \sqrt{\lambda} \det \left(U^H G_z U \right)^{-\frac{1}{2}} \cdot |\det U| = \sqrt{\lambda} \det(G_z)^{-\frac{1}{2}}, \end{aligned}$$

where $U := [u_1, U_z]$ and we use $U_z^H G_z u_1 = \mathbf{0}_{M-1}$ in the second equality. Hence, the largest λ leads to the smallest J_W . $\square$

From Proposition 2, we can update $W = [w_1, W_z]$ using (18)–(21) with $\theta = 0$ and $Q = I_{M-1}$, minimizing J_W globally. Note that updating w_1 by (18) and (20) is independent of W_z since G_1 and G_z are independent of W_z . We can thus simplify the procedure of IP-2, which is summarized in Algorithm 3. Interestingly, because G_z and G_1 can be viewed as the covariance matrices of the mixture and noise signals, IP-2 turns out to be a MaxSNR beamformer [27, 28]. In other words, OverIVA with IP-2 is a method that alternately updates the target-source power spectrum and MaxSNR beamformer.

5. RELATION TO PRIOR WORKS

The conventional OverIVA [5], denoted as OverIVA-OC, is an acceleration of IVA. It exploits not only the independence of sources but also the orthogonality constraint (OC [5, 15, 16]): the sample correlation (or inner product) between the target sources and the noise

Algorithm 1 OverIVA

```

1: Set  $\varepsilon_1, \varepsilon_2 \in \mathbb{R}_{\geq 0}$  (we set  $\varepsilon_1 = 10^{-5}$  and  $\varepsilon_2 = 10^{-1}$  in §6).
2: Initialization:  $W(f) = I_M$  for all  $f = 1, \dots, F$ .
3:  $G_z(f) \leftarrow \frac{1}{T} \sum_{t=1}^T \mathbf{x}(f, t) \mathbf{x}(f, t)^H$  for all  $f$ .
4: repeat
5:    $s_k(f, t) \leftarrow \mathbf{w}_k(f)^H \mathbf{x}(f, t)$  for all  $k, f, t$ .
6:    $\lambda_k(t) \leftarrow \max\{\frac{1}{F} \|\mathbf{s}_k(t)\|^2, \varepsilon_1\}$  for all  $k, t$ .
7:    $G_k(f) \leftarrow \frac{1}{T} \sum_{t=1}^T \frac{\mathbf{x}(f, t) \mathbf{x}(f, t)^H}{\lambda_k(f, t)} + \varepsilon_2 I_M$  for all  $k, f$ .
8:   Update  $W(f)$  using IP-1, IP-2, or IP-3 for all  $f$ .
9:   Normalization for numerical stability:  $c_k := \frac{1}{T} \sum_t \lambda_k(t)$ ,
       $\lambda_k(t) \leftarrow \lambda_k(t) c_k^{-1}$  and  $\mathbf{w}_k(f) \leftarrow \mathbf{w}_k(f) c_k^{-1/2}$  for all  $k, f, t$ .
10: until convergence
11: In the case of IP-2, update  $W_z(f)$  using (17) for all  $f$ .
12: The separation result is obtained by (5).

```

Algorithm 2 IP-1

```

1: for  $k = 1, \dots, K$  do
2:    $\mathbf{u}_k(f) \leftarrow (W(f)^H G_k(f))^{-1} \mathbf{e}_k$ 
3:    $\mathbf{w}_k(f) \leftarrow \mathbf{u}_k(f) (\mathbf{u}_k(f)^H G_k(f) \mathbf{u}_k(f))^{-\frac{1}{2}}$ 
4: end for
5:  $W_z(f) \leftarrow \begin{pmatrix} -(W_s(f)^H G_z(f) E_s)^{-1} (W_s(f)^H G_z(f) E_z) \\ I_{M-K} \end{pmatrix}$ 

```

is to be zero, i.e., $W_s^H G_z W_z = O$. This constraint is nothing but the first K rows in (10), meaning that the stationarity of the Gaussian noise implicitly implies OC. In this subsection, we clarify that OverIVA-OC can also be obtained from the proposed OverIVA.

OverIVA-OC restricts W_z to the form $W_z = \begin{pmatrix} -B_z \\ I_{M-K} \end{pmatrix}$, which

together with OC imply $B_z = -(W_s^H G_z E_s)^{-1} (W_s^H G_z E_z)$. This relation between B_z and W_s gives an update rule of W_z . The procedure of OverIVA-OC is summarized in Algorithm 4. Note that the update of W_z has to be done immediately after optimizing any other variables $\mathbf{w}_1, \dots, \mathbf{w}_K$ so as to always enforce OC in the model.

It is easy to see that Algorithm 4 can also be obtained from the proposed OverIVA by selecting IP-3 as the optimization procedure of BCD. Hence, OverIVA-OC can be viewed as a special case of our OverIVA. The main advantage of our approach is that, by removing OC, we can develop several algorithms including IP-1 and IP-2 that are expected to be more efficient than IP-3. In fact, the computational cost of IP-1 per iteration is slightly less than IP-3. Also, the convergence speed of IP-2 is much faster than IP-3. The advantages of IP-1 and IP-2 are shown experimentally (see Section 6).

6. EXPERIMENTS

We carried out experiments to compare the separation and runtime performances of the following four methods:

AuxIVA [13]: The conventional auxiliary-function-based IVA [13], followed by picking the K signals with largest powers.

OverIVA-OC [5]: It is OverIVA(IP-3). See Algorithms 1 and 4.

OverIVA(IP-1) and OverIVA(IP-2): See Algorithms 1, 2, and 3.

As evaluation data, we generated synthesized convolutive mixtures of target speech and untarget white-noise signals. To this end, we used point-source speech signals from SiSEC2008 [29] and selected a set of room impulse responses (RIR) recorded in the room E2A from RWCP Sound Scene Database [30]. Then, for a given numbers of speakers K , white noises L , and microphones M , (i) we

Algorithm 3 IP-2 (only for $K = 1$)

```

1: Solve the generalized eigenvalue problem  $G_z(f) \mathbf{u} = \lambda G_1(f) \mathbf{u}$  to obtain the eigenvector  $\mathbf{u}$  corresponding to the largest eigenvalue.
2:  $\mathbf{w}_1(f) \leftarrow \mathbf{u} (\mathbf{u}^H G_1(f) \mathbf{u})^{-\frac{1}{2}}$ 

```

Algorithm 4 IP-3 (The conventional OverIVA with OC [5] is equivalent to the proposed OverIVA with IP-3 as shown in §5)

```

1: for  $k = 1, \dots, K$  do
2:   Execute lines 2, 3, and 5 in Algorithm 2 to update  $\mathbf{w}_k(f)$  and  $W_z(f)$ .
3: end for

```

randomly picked K speech signals and $K + L$ RIRs, (ii) generated L white noises, (iii) convolved these $K + L$ point-source signals using the RIRs, and (iv) added the obtained $K + L$ spatial images so that $\text{SINR} := 10 \log_{10} \frac{\frac{1}{K} \sum_{k=1}^K \sigma_k^2}{\sum_{l=1}^L \sigma_l^2}$ [dB] becomes a specified value,

where σ_k^2 and σ_l^2 denote the variances of speech and white noise signals, respectively. We generated 10 mixtures for each condition.

We initialized $W(f) = I_M$, and set the number of optimization iterations to 50 except set it to three in OverIVA(IP-2). The sampling rate was 16 kHz, the reverberation time was 300 ms, the frame length was 4096 (256 ms), and the frame shift was 1/4 of the frame length.

Table 2 shows the BSS performance averaged over 10 samples in terms of SDR [31] and real time factor (RTF) calculated as “the total computation time [sec] divided by the signal length (10 sec).” As expected, the proposed OverIVA is faster than the other methods while providing the comparable SDR. In particular, OverIVA(IP-2) specialized for $K = 1$ significantly outperforms the other methods.

Table 2. The resultant SDR [dB] and real time factor (RTF)

#speeches & #noises SINR [dB] #channels (M)		$K = 1, L = 5$ 0 dB			$K = 2, L = 1$ 10 dB			
		3	5	7	3	4	5	6
Mixture	SDR	0.0	0.0	0.0	-0.4	-0.4	-0.5	-0.4
	RTF							
AuxIVA [12]	SDR	3.9	3.5	4.1	5.7	7.2	7.6	7.3
	RTF	0.26	0.80	3.23	0.25	0.48	0.80	1.84
OverIVA-OC [5]	SDR	4.5	5.6	6.6	6.3	7.6	5.8	6.1
	RTF	0.10	0.22	0.73	0.19	0.27	0.41	0.81
OverIVA(IP-1)	SDR	4.5	5.6	6.6	6.1	7.5	6.0	6.2
	RTF	0.10	0.22	0.73	0.18	0.25	0.38	0.76
OverIVA(IP-2)	SDR	5.3	7.0	8.6	-	-	-	-
	RTF	0.017	0.046	0.10	-	-	-	-

Note that OverIVA-OC and OverIVA(IP-1) are the same when $K = 1$. All algorithms were implemented in Python 3.7 and run on a laptop PC with 2.6 GHz Intel Core i7.

7. CONCLUSION

We proposed a computationally efficient IVA for overdetermined BSS, called OverIVA. Unlike the previous OverIVA [5] relying on the orthogonality constraint, our approach exploits only the independence of sources and the stationarity of the Gaussian noise. We verified the effectiveness of the proposed OverIVA in the experiment.

8. APPENDIX

To give a proof of Proposition 1, we need Proposition 4 below, which is a modification of Proposition 3 provided in [20–23]. The proofs of Propositions 3 and 4 are almost the same and so we omit it.

Proposition 3 (see, e.g., [20–23]). Suppose (C1). Then, J_W is lower bounded and attains its minimum.

Proposition 4. Suppose (C1) and let $W := [W_s, W_z] \in \mathbb{C}^{M \times M}$ be a matrix. If the submatrix W_s is full column rank and W_z is a variable, then the function $J(W_z) := \text{tr}(W_z^H G_z W_z) - 2 \log |\det W|$ is lower bounded and attains its minimum.

9. REFERENCES

- [1] P. Comon, "Independent component analysis, a new concept?," *Signal processing*, vol. 36, no. 3, pp. 287–314, 1994.
- [2] J.-F. Cardoso, "Blind signal separation: statistical principles," *Proceedings of the IEEE*, vol. 86, no. 10, pp. 2009–2025, 1998.
- [3] T. Kim, H. T. Attias, S.-Y. Lee, and T.-W. Lee, "Blind source separation exploiting higher-order frequency dependencies," *IEEE Transactions on Audio, Speech, and Language Processing*, vol. 15, no. 1, pp. 70–79, 2007.
- [4] A. Hiroe, "Solution of permutation problem in frequency domain ICA, using multivariate probability density functions," in *Proc. ICA*, 2006, pp. 601–608.
- [5] R. Scheibler and N. Ono, "Independent vector analysis with more microphones than sources," in *Proc. WASPAA*, 2019.
- [6] J. H. Friedman and J. W. Tukey, "A projection pursuit algorithm for exploratory data analysis," *IEEE Transactions on Computers*, vol. 100, no. 9, pp. 881–890, 1974.
- [7] P. J. Huber, "Projection pursuit," *The annals of Statistics*, pp. 435–475, 1985.
- [8] A. Hyvärinen and E. Oja, "A fast fixed-point algorithm for independent component analysis," *Neural computation*, vol. 9, no. 7, pp. 1483–1492, 1997.
- [9] A. Hyvärinen, "Fast and robust fixed-point algorithms for independent component analysis," *IEEE transactions on Neural Networks*, vol. 10, no. 3, pp. 626–634, 1999.
- [10] T. Wei, "A convergence and asymptotic analysis of the generalized symmetric FastICA algorithm," *IEEE Transactions on Signal Processing*, vol. 63, no. 24, pp. 6445–6458, 2015.
- [11] S. A. Cruces-Alvarez, A. Cichocki, and S. Amari, "From blind signal extraction to blind instantaneous signal separation: criteria, algorithms, and stability," *IEEE Transactions on Neural Networks*, vol. 15, no. 4, pp. 859–873, 2004.
- [12] N. Ono and S. Miyabe, "Auxiliary-function-based independent component analysis for super-Gaussian sources," in *Proc. LVA/ICA*, 2010, pp. 165–172.
- [13] N. Ono, "Stable and fast update rules for independent vector analysis based on auxiliary function technique," in *Proc. WASPAA*, 2011, pp. 189–192.
- [14] N. Ono, "Fast stereo independent vector analysis and its implementation on mobile phone," in *Proc. IWAENC*, 2012, pp. 1–4.
- [15] Z. Koldovský, P. Tichavský, and V. Kautský, "Orthogonally constrained independent component extraction: Blind mpdr beamforming," in *Proc. EUSIPCO*, 2017, pp. 1155–1159.
- [16] Z. Koldovský and P. Tichavský, "Gradient algorithms for complex non-gaussian independent component/vector extraction, question of convergence," *IEEE Transactions on Signal Processing*, vol. 67, no. 4, pp. 1050–1064, 2018.
- [17] N. Murata, S. Ikeda, and A. Ziehe, "An approach to blind source separation based on temporal structure of speech signals," *Neurocomputing*, vol. 41, no. 1–4, pp. 1–24, 2001.
- [18] D. T. Pham, "Blind separation of instantaneous mixture of sources via an independent component analysis," *IEEE Transactions on Signal Processing*, vol. 44, no. 11, pp. 2768–2779, 1996.
- [19] D.-T. Pham and J.-F. Cardoso, "Blind separation of instantaneous mixtures of nonstationary sources," *IEEE Transactions on Signal Processing*, vol. 49, no. 9, pp. 1837–1848, 2001.
- [20] A. Yeredor, B. Song, F. Roemer, and M. Haardt, "A sequentially drilled joint congruence (SeDJoCo) transformation with applications in blind source separation and multiuser MIMO systems," *IEEE Transactions on Signal Processing*, vol. 60, no. 6, pp. 2744–2757, 2012.
- [21] A. Yeredor, "On hybrid exact-approximate joint diagonalization," in *Proc. CAMSAP*, 2009, pp. 312–315.
- [22] S. Dégerine and A. Zaïdi, "Separation of an instantaneous mixture of Gaussian autoregressive sources by the exact maximum likelihood approach," *IEEE Transactions on Signal Processing*, vol. 52, no. 6, pp. 1499–1512, 2004.
- [23] S. Dégerine and A. Zaïdi, "Determinant maximization of a nonsymmetric matrix with quadratic constraints," *SIAM Journal on Optimization*, vol. 17, no. 4, pp. 997–1014, 2006.
- [24] S. Amari, A. Cichocki, and H. H. Yang, "A new learning algorithm for blind signal separation," in *Proc. NIPS*, 1996, pp. 757–763.
- [25] N. Ono, "Fast algorithm for independent component/vector/low-rank matrix analysis with three or more sources," in *Proc. ASJ Spring Meeting*, 2018, (in Japanese).
- [26] R. Ikeshita, N. Ito, T. Nakatani, and H. Sawada, "Independent low-rank matrix analysis with decorrelation learning," in *Proc. WASPAA*, 2019.
- [27] H. L. Van Trees, *Optimum array processing: Part IV of detection, estimation, and modulation theory*, John Wiley & Sons, 2004.
- [28] E. Warsitz and R. Haeb-Umbach, "Blind acoustic beamforming based on generalized eigenvalue decomposition," *IEEE Transactions on Audio, Speech, and Language Processing*, vol. 15, no. 5, pp. 1529–1539, 2007.
- [29] E. Vincent, S. Araki, and P. Bofill, "The 2008 signal separation evaluation campaign: A community-based approach to large-scale evaluation," in *Proc. ICA*, 2009, pp. 734–741.
- [30] S. Nakamura, K. Hiyane, F. Asano, T. Nishiura, and T. Yamada, "Acoustical sound database in real environments for sound scene understanding and hands-free speech recognition," in *LREC*, 2000.
- [31] E. Vincent, R. Gribonval, and C. Févotte, "Performance measurement in blind audio source separation," *IEEE Transactions on Audio, Speech, and Language Processing*, vol. 14, no. 4, pp. 1462–1469, 2006.