

This work has been submitted to the IEEE for possible publication.  
Copyright may be transferred without notice, after which this version may no longer be accessible.

# On decoding of a specific type of self-dual codes

Radinka Yorgova  
TU Delft, The Netherlands  
radinka.yorgova@gmail.com

## Abstract

This work introduces a decoding strategy for binary self-dual codes possessing an automorphism of a specific type. The proposed algorithm is a hard decision iterative decoding scheme. The enclosed experiments show that the new decoding concept performs error correction beyond the upper bound for the code correction capability. Moreover, we prove that the requirements for the new algorithm hold for any binary self-dual code having an automorphism of the specific type, which makes decoding of this large group of codes possible.

## Index Terms

Decoding, Self-dual codes.

## I. INTRODUCTION

THE existing general decoding schemes as the nearest neighbor decoding or the syndrome decoding are only applicable for short-length self-dual codes [1, p.41]<sup>1</sup>. When increasing the size of the code, the required memory for each of these algorithms limits their practical applications. For several particular self-dual codes, there exist decoding schemes. For example, decoding by hand the [24, 12, 8] binary extended Golay code by Pless [2] or decoding binary extremal self-dual code of length 40 by Kim and Lee [3]. Moreover, Gaborit et al. presented decoding schemes for few binary doubly-even self-dual codes of length 32 [5].

There is no efficient general decoding algorithm for self-dual codes or for a large family of such codes to the best of our knowledge. This was defined by Pless and Huffman in 2003 as a research problem [1, Research Problem 9.7.8].

Here, we propose a decoding algorithm for a large group of binary self-dual codes, namely self-dual codes having an automorphism of odd order. The algorithm is a hard decision iterative decoding scheme and can be used for any code of this group regardless of its length and minimum distance.

We first provide preliminaries with definitions and results used further in this work. Then the idea in our decoding scheme is introduced. Further, we prove that the proposed algorithm is a valid algorithm for any self-dual code possessing an automorphism of odd order. Next, three examples of extremal and optimal self-dual codes are presented together with the simulation results for our decoding scheme. Two of these codes are known, whereas the third one is new and constructed to illustrate that the codes, which can benefit from the new decoding scheme, are a large group. At last, we discuss some open questions, possible applications, and limitations of the proposed decoding scheme.

## II. PRELIMINARIES

In this section, we present first the terminology related to self-dual codes in general and afterward related to self-dual codes with automorphisms of odd order.

### A. Self-dual Codes

Let  $\mathbb{F}_2^n$  be the standard  $n$ -dimensional vector space over the binary field  $\mathbb{F}_2$  and  $\mathcal{C}$  be a  $k$ -dimensional subspace of  $\mathbb{F}_2^n$ . Then  $\mathcal{C}$  is a binary  $[n, k]$  code. The *Hamming weight*  $wt(v)$  of a vector  $v \in \mathbb{F}_2^n$  is the number of the nonzero coordinates of  $v$ . If  $d$  is the minimum weight of all the nonzero codewords of  $\mathcal{C}$ , then  $\mathcal{C}$  is called a binary  $[n, k, d]$  code and  $d$  - minimum weight of the code. *Hamming distance* between two vectors in  $\mathbb{F}_2^n$  is the number of coordinates where they differ.

The inner product in  $\mathbb{F}_2^n$  is given by  $u \cdot v = u_1v_1 + u_2v_2 + \dots + u_nv_n$  for  $u, v \in \mathbb{F}_2^n$ . Two vectors are orthogonal if their inner product equals to 0. Then, the orthogonal of the code  $\mathcal{C}$  is  $\mathcal{C}^\perp = \{v \in \mathbb{F}_2^n \mid u \cdot v = 0, \forall u \in \mathcal{C}\}$ .

If  $\mathcal{C} \subset \mathcal{C}^\perp$ , the code  $\mathcal{C}$  is called *self-orthogonal* and if  $\mathcal{C} = \mathcal{C}^\perp$ ,  $\mathcal{C}$  is called *self-dual*. It is known that the weight of any codeword of a self-dual code is even. A binary self-dual code  $\mathcal{C}$  is called *doubly-even* if the weight of every codeword is divisible by four, and *singly-even* if there is at least one codeword of even weight not divisible by 4, i.e.,  $\text{weight} \equiv 2 \pmod{4}$  [1, p.11].

<sup>1</sup>In the optimal case, for a binary  $[n, k]$  code both decoding schemes could use a lookup table with  $2^{n-k}$  elements in  $\mathbb{F}_2^n$ .

Upper bounds for the minimum weight of a self-dual  $[n, n/2, d]$  code are given in [?]:

$$d \leq 4\lfloor \frac{n}{24} \rfloor + 4, \quad \text{if } n \not\equiv 22 \pmod{24}, \quad (1)$$

and

$$d \leq 4\lfloor \frac{n}{24} \rfloor + 6, \quad \text{if } n \equiv 22 \pmod{24}. \quad (2)$$

Stricter bounds are known for some specific lengths, like for  $n = 78$  the maximum  $d$  is 14 instead of 16 [6]. Self-dual codes which reach the minimum weight bounds are called *extremal* whereas self-dual codes with the highest minimum weight for a given length among the known such are called *optimal*. In [7], it is proven that binary extremal double-even self-dual codes do not exist for lengths  $n > 3928$ .

Two binary codes are equivalent if one can be obtained from the other by a permutation of coordinates. That is, if there exist a permutation  $\sigma$ ,  $\sigma \in S_n$  ( $S_n$ - the symmetric group of degree  $n$ ), such that  $\sigma(\mathcal{C}) = \mathcal{C}'$ . If  $\sigma(\mathcal{C}) = \mathcal{C}$  for some  $\sigma \in S_n$ , then the permutation  $\sigma$  is an automorphism of the code  $\mathcal{C}$ .

### B. Self-dual Codes and Automorphisms of Odd Order

Following the notations in [8], a permutation of order  $\mathcal{L}$ , having  $f$  fixed points and  $t_1$  cycles of length  $a_1$ ,  $t_2$  cycles of length  $a_2$ ,  $\dots$ ,  $t_h$  cycles of length  $a_h$ , with  $1 < a_1 < a_2 < \dots < a_h$ , is called a *permutation of type  $\mathcal{L}-(t_1, t_2, \dots, t_h; f)$* .

In this work, we only consider permutations of type  $\mathcal{L}-(t_1; 0)$ , where  $\mathcal{L} = pr$ , for  $p$  and  $r$  being odd primes. That is,  $\sigma$  is of order  $pr$  and has only cycles of length  $pr$  and no fixed points. Thus, without loss of generality  $\sigma$  can be represented as:

$$\sigma = \Omega_1 \Omega_2 \dots \Omega_{t_1}, \quad (3)$$

where  $\Omega_s$  is a cycle of length  $pr$  for  $1 \leq s \leq t_1$ .

Let further  $\mathcal{C}$  be a binary self-dual  $[n, n/2, d]$  code with a generator matrix  $G$  and  $\sigma$  be an automorphism of  $\mathcal{C}$ .

If  $v \in \mathcal{C}$ , then  $v$  can be presented as

$$v = (v|_{\Omega_1}, v|_{\Omega_2}, \dots, v|_{\Omega_{t_1}}),$$

where  $v|_{\Omega_i} = (v_0, v_1, \dots, v_{pr-1})$  denotes the coordinates of  $v$  in the  $i$ -th cycle of  $\sigma$ . Then, the image of  $v$ ,  $\sigma(v)$ , is a vector obtained from  $v$  by cyclic shift in each of  $v|_{\Omega_i}$ . From another side  $\sigma(v) \in \mathcal{C}$  since  $\sigma$  is an automorphism of  $\mathcal{C}$ . Thus, all vectors obtained from  $v$  by cyclic shifts of the coordinates in each  $\Omega_i$  are also codewords. Therefore, a matrix in the form

$$\begin{pmatrix} G_1 & G_2 & \dots & G_{t_1} \end{pmatrix}, \quad (4)$$

where  $G_j$  is a circulant matrix of length  $pr$ , generates codewords and then it can be considered as a sub-matrix of  $G$ .

Further, we follow the notations in [8] adjusted to our particular type of automorphism (Eq. (3)). The sets  $F_\sigma(\mathcal{C})$  and  $E_\sigma(\mathcal{C})$  are defined as:

$$F_\sigma(\mathcal{C}) = \{v \in \mathcal{C} \mid v\sigma = v\} \quad (5)$$

and

$$E_\sigma(\mathcal{C}) = \{v \in \mathcal{C} \mid wt(v|_{\Omega_i}) \equiv 0 \pmod{2}, 1 \leq i \leq t_1\}, \quad (6)$$

where  $v|_{\Omega_i}$  is the restriction of  $v$  on  $\Omega_i$ .

It is known that  $F_\sigma(\mathcal{C})$  and  $E_\sigma(\mathcal{C})$  are subcodes of  $\mathcal{C}$ . Moreover,  $\mathcal{C} = F_\sigma(\mathcal{C}) \oplus E_\sigma(\mathcal{C})$ , where  $\oplus$  stands for the direct sum of linear subspaces [9]. Then a generator matrix of our self-dual code  $\mathcal{C}$  can be decomposed as:

$$G = \begin{pmatrix} X \\ Y \end{pmatrix}, \quad (7)$$

where  $X$  is a generator matrices of  $F_\sigma(\mathcal{C})$  and  $Y$  is a generator matrix of  $E_\sigma(\mathcal{C})$ .

If a map  $\pi$  for our particular type of automorphism is defined as

$$\pi : F_\sigma(\mathcal{C}) \rightarrow \mathbb{F}_2^{t_1}, \quad \pi(v|_{\Omega_i}) = v_j, \quad (8)$$

for some  $j \in \Omega_i$ ,  $i = 1, \dots, t_1$ , then the image  $\pi(F_\sigma(\mathcal{C}))$  is a binary  $[t_1, t_1/2]$  self-dual code [9].

Let  $\mathcal{P}$  denote the set of even-weight polynomials in  $\mathcal{R} = \mathbb{F}_2[x]/(x^{pr} - 1)$  and map  $\varphi$  be the following:

$$\varphi : E_\sigma(\mathcal{C}) \rightarrow \mathcal{P}^{t_1},$$

where  $v|_{\Omega_i} = (v_0, v_1, \dots, v_{pr-1})$  is identified with the polynomial  $\varphi(v|_{\Omega_i})(x) = v_0 + v_1x + \dots + v_{pr-1}x^{pr-1}$  in  $\mathcal{P}$  for  $1 \leq i \leq t_1$ .

An inner product in  $\mathcal{P}^{t_1}$  is defined as:

$$\langle g, h \rangle = g_1(x)h_1(x^{-1}) + \dots + g_{t_1}(x)h_{t_1}(x^{-1}) \quad (9)$$

for every  $g, h \in \mathcal{P}^{t_1}$ .

The image  $\varphi(E_\sigma(\mathcal{C}))$  is a self-orthogonal code [8, Lemma 1], i.e.,

$$u_1(x)v_1(x^{-1}) + \dots + u_{t_1}(x)v_{t_1}(x^{-1}) = 0, \quad (10)$$

for  $\forall u, v \in \varphi(E_\sigma(\mathcal{C}))$ .

This orthogonality and the cyclic structure of  $G_i$  in Eq. (4) are used in the decoding strategy described next.

### III. HARD-DECISION ITERATIVE DECODING ALGORITHM

Let  $\mathcal{C}$  and  $\sigma$  be defined as before. Let also a codeword  $c \in \mathcal{C}$  be transmitted and  $r = c + e$  be received where  $e$  is the error vector. In polynomial representation this is:  $(r_1(x), r_2(x), \dots, r_{t_1}(x)) = (c_1(x), c_2(x), \dots, c_{t_1}(x)) + (e_1(x), e_2(x), \dots, e_{t_1}(x))$ , where  $r_i(x)$ ,  $c_i(x)$ ,  $e_i(x)$  are in  $\mathcal{R} = \mathbb{F}_2[x]/(x^{pr} - 1)$ .

We denote by  $w$  the inner product of the received  $r$  with any minimum weight codeword  $b \in \mathcal{C}$ :

$$w(x) = \langle r, b \rangle = \sum_{i=1}^{t_1} r_i(x)b_i(x^{-1}) \mod(x^{pr} - 1)$$

Since  $r = c + e$  it follows that:

$$w(x) = \langle r, b \rangle = \sum_{i=1}^{t_1} c_i(x)b_i(x^{-1}) + \sum_{i=1}^{t_1} e_i(x)b_i(x^{-1}).$$

The term  $\sum_{i=1}^{t_1} c_i(x)b_i(x^{-1})$  is equal to zero if  $c, b \in \varphi(E_\sigma(\mathcal{C}))$ . In Section IV, we prove that this term is zero for any two codewords. Here, we only formulate the statement.

**Lemma 1.** *Let  $\mathcal{C}$  be a binary  $[n, n/2, d]$  self-dual code possessing an automorphism  $\sigma$  of type  $pr$ -( $t_1; 0$ ), where  $p$  and  $r$  are odd primes and  $n = prt_1$ . Then, Eq. (10) holds for every  $u, v \in \mathcal{C}$ .*

Thus, in the expression for  $w$  only the last term remains:

$$w(x) = \langle r, b \rangle = \sum_{i=1}^{t_1} e_i(x)b_i(x^{-1}) \mod(x^{pr} - 1).$$

It is clear that if the error vector  $r$  is zero, i.e.,  $e_i(x) = 0$  for  $1 \leq i \leq t_1$ , then  $w$  is also zero.

Let the support of  $b_1(x)$ ,  $\text{supp}(b_1(x))$ , be the set  $\{\beta_1, \beta_2, \dots, \beta_d\}$  which means that  $b_1(x) = x^{\beta_1} + x^{\beta_2} + \dots + x^{\beta_d}$ . Then  $w$  can be written as:

$$\begin{aligned} w(x) &= \sum_{i=1}^{t_1} e_i(x)b_i(x^{-1}) \mod(x^{pr} - 1) \\ &= e_1(x)b_1(x^{-1}) + \sum_{i=2}^{t_1} e_i(x)b_i(x^{-1}) \mod(x^{pr} - 1) \\ &= e_1(x)x^{-\beta_1} + e_1(x)x^{-\beta_2} + \dots + e_1(x)x^{-\beta_d} + \\ &\quad + \sum_{i=2}^{t_1} e_i(x)b_i(x^{-1}) \mod(x^{pr} - 1) \end{aligned}$$

If  $e_1(x) = x^{\epsilon_1} + x^{\epsilon_2} + \dots + x^{\epsilon_r}$ , then the expression for  $w$  can be further reorganized as:

$$\begin{aligned} w(x) &= x^{\epsilon_1 - \beta_1} + x^{\epsilon_2 - \beta_1} + \dots + x^{\epsilon_r - \beta_1} + \\ &\quad x^{\epsilon_1 - \beta_2} + x^{\epsilon_2 - \beta_2} + \dots + x^{\epsilon_r - \beta_2} + \\ &\quad x^{\epsilon_1 - \beta_3} + x^{\epsilon_2 - \beta_3} + \dots + x^{\epsilon_r - \beta_3} + \\ &\quad \vdots \\ &\quad x^{\epsilon_1 - \beta_d} + x^{\epsilon_2 - \beta_d} + \dots + x^{\epsilon_r - \beta_d} + \\ &\quad + \sum_{i=2}^{t_1} e_i(x)b_i(x^{-1}) \mod(x^{pr} - 1), \end{aligned} \quad (11)$$

where all  $\epsilon_i - \beta_j$  are in  $\text{mod}(pr)$ .

Eq. (11) can be seen as: the first row contains all error positions of  $e_1(x)$  shifted by  $-\beta_1$  positions; the second row - all error positions of  $e_1(x)$  shifted by  $-\beta_2$  positions and so on, the  $d^{\text{th}}$  row - all error positions of  $e_1(x)$  shifted by  $-\beta_d$  positions. The rest can be considered by the same way regarding the error positions of  $e_2, e_3, \dots, e_{t_1}$  with shifts corresponding to the

supports of  $b_2, b_3, \dots, b_{t_1}$ . Note that many of these terms can be canceled out since these shifted error positions can be the same for different  $e_i b_i$ .

If we multiply  $w$  by  $x^{\beta_1}$ , the first row of  $x^{\beta_1} w(x)$  in Eq. (11) will become exactly  $e_1(x)$ . Multiplying  $w$  with  $x^{\beta_2}$ , the second row in Eq. (11) will become exactly  $e_1(x)$  and so on.

Thus, each of the polynomials:

$$x^{\beta_1} w(x), x^{\beta_2} w(x), \dots, x^{\beta_d} w(x) \mod(x^{pr} - 1) \quad (12)$$

contains  $e_1(x)$ ,  $x^{\beta_j - \beta_s} e_1(x)$ , and  $x^{\beta_j} \sum_{i=2}^{t_1} e_i(x) b_i(x^{-1}) \mod(x^{pr} - 1)$ , which are the original and shifted error positions of  $e_1(x)$  and shifted error positions of  $e_i(x)$ ,  $i = 2, 3, \dots, t_1$ . Some of the original or shifted error positions of  $e_1(x)$  can be canceled out with some of the shifted error positions of  $e_2(x), e_3(x), \dots, e_{t_1}(x)$ . If in all polynomials  $x^{\beta_s} w(x)$  in Eq. (12), we count the number of 1s in each position  $1, 2, \dots, pr$ , it is expected some of the error positions to have higher frequency than the rest of the positions. The same process can be repeated for

$$e_2(x) b_2(x^{-1}), e_3(x) b_3(x^{-1}), \dots, e_{t_1}(x) b_{t_1}(x^{-1}).$$

In general, if we consider  $e_s(x) b_s(x^{-1})$ , where  $\text{supp}(b_s(x)) = \{\beta_1^{(s)}, \beta_2^{(s)}, \dots, \beta_d^{(s)}\}$ , then the polynomials:

$$x^{\beta_1^{(s)}} w(x), x^{\beta_2^{(s)}} w(x), \dots, x^{\beta_d^{(s)}} w(x) \mod(x^{pr} - 1) \quad (13)$$

contain error positions and shifted error positions of  $e_s(x)$  and shifted error positions of  $e_i(x)$ ,  $i = 1, 2, \dots, t_1, i \neq s$ . Therefore, when counting the number of 1s in each position from 1 till  $pr$  in the polynomials in Eq. (13), a higher number of 1s will be an indicator for an error in this position. The polynomials in Eq. (13) are created for every  $s$ ,  $1 \leq s \leq t_1$  and the number of 1s in each position included in  $\Phi_j^{(s)}$  defined latter.

Let  $\mathcal{C}$  has  $L$  cyclicly different minimum weight codewords. In our case *cyclicly different* codewords means that one cannot be obtained from the other by applying  $\sigma^t$ , for some  $t$ , that is,  $b \neq \sigma^t(c)$  for  $1 \leq t \leq pr - 1, \forall b, c \in \mathcal{C}$ . The counting of 1s in each position from 1 till  $pr$  in the cycles  $\Omega_j$  is repeated for the polynomials in Eq. (13) for all cyclicly different minimum weight codewords  $b$ . The number is denoted by  $\Phi_j^{(s)}$ :

$$\Phi_j^{(s)} = \sum_{l=1}^L \sum_{i \in \text{supp}(b_s^{(l)}(x))} w_{i+j \mod pr}^{(l)} \quad (14)$$

$$j = 0, 1, 2, \dots, pr - 1, \quad s = 1, 2, \dots, t_1,$$

where  $w_{i+j \mod pr}^{(l)}$  is counted in position  $j$  since the shift of  $w(x)$  by  $-i$  moves the position  $i + j \mod pr$  into  $j$ .

As it was mentioned, a higher number of 1s in a position from 1 till  $pr$  in the polynomials in Eq. (13) is an indicator for an error in this position. Thus, an error is expected in the  $j$ -th position in cycle  $\Omega_s$  if  $\Phi_j^{(s)}$  has a higher value than the sum for any other position in the same cycle  $\Omega_s$  and than the sum on any position in the other cycles.

Note that the idea of shifting and counting 1s in each coordinate position is introduced in [10], and it is specifically and only for cyclic codes. The presence of the cyclic cells in the generator matrix of the code  $\mathcal{C}$  and moreover, the orthogonality in polynomial representation of each two codewords make it possible to use shifting and counting in a similar way.

Since  $w(x) = \langle r, b \rangle = \sum_{i=1}^{t_1} r_i(x) b_i(x^{-1}) \mod(x^{pr} - 1)$ , one can determine the coefficients  $w_i$  of the polynomial  $w(x)$  as linear combinations of the coefficients  $r_i^{(t)}$  of  $r_i(x)$  and the supports of  $b_i(x)$  for  $1 \leq i \leq t_1$ .

Here, we define our decoding strategy. We suppose that  $\mathcal{C}$  and  $\sigma$  are defined as before and  $G$  is a generator matrix of  $\mathcal{C}$ . As noted above, a high value of  $\Phi_j^{(s)}$  indicates an error in position  $j$  of  $\Omega_s$ .

## Decoding Scheme <sup>2</sup>

1) generate all or almost all cyclicly different codewords of weight  $d$  or  $d + o$  for some small  $o$ , for example 2 or 4 or 6. Denote the set by  $D_1$ ;

<sup>2</sup>A pseudocode of the decoding scheme is provided in Appendix A.

- 2) for the received vector  $r$  compute  $rG$ . If  $rG = 0$ , then  $r$  belongs to the code  $\mathcal{C} \rightarrow$  end, otherwise  $\rightarrow$  3);
- 3) split  $r$  into  $t_1$  polynomials of  $\mathbb{F}_2[x]/(x^{pr} - 1)$ , i.e.,  $r = (r_1(x), r_2(x), \dots, r_{t_1}(x))$ ;
- 4) for  $r = (r_1(x), r_2(x), \dots, r_{t_1}(x))$  compute:
  - $w(x) = \langle r, b \rangle = r_1(x)b_1(x^{-1}) + r_2(x)b_2(x^{-1}) + \dots + r_{t_1}(x)b_{t_1}(x^{-1}) \pmod{x^{pr} - 1}$   
for  $\forall b \in D_1, b = (b_1(x), b_2(x), \dots, b_{t_1}(x))$
  - $x^{\beta_i^{(1)}} w(x) \pmod{x^{pr} - 1}$  for  $\forall \beta_i^{(1)} \in \text{supp}(b_1(x))$   
 $x^{\beta_i^{(2)}} w(x) \pmod{x^{pr} - 1}$  for  $\forall \beta_i^{(2)} \in \text{supp}(b_2(x))$   
 $\vdots$   
 $x^{\beta_i^{(t_1)}} w(x) \pmod{x^{pr} - 1}$  for  $\forall \beta_i^{(t_1)} \in \text{supp}(b_{t_1}(x))$
- Note first that, for the chosen code  $\mathcal{C}$  if  $r \in \mathcal{C}$ , then  $w(x) = 0$  and second, the products  $x^{\beta_i^{(s)}} w(x)$  are cyclic shifts of  $w$  with number of positions which values are from the support of  $b_s(x)$ .
- 5) compute  $\Phi_j^{(s)}$  defined in Eq. (14) for  $j = 0, 1, \dots, pr - 1, s = 1, 2, \dots, t_1$ ;
- 6) determine  $\Phi_{max} = \max\{\Phi_j^{(s)} \mid j = 0, 1, \dots, pr - 1, s = 1, 2, \dots, t_1\}$  and find the position with the value  $\Phi_{max}$ , i.e., find the cycle  $s_1$  and position(s)  $j_1$  such that  $\Phi_{j_1}^{(s_1)} = \Phi_{max}$ ;
- 7) flip the coordinate of  $r_{s_1}(x)$  by adding  $x^{j_1}$  to  $r_{s_1}(x)$ , i.e.,  $r_{s_1}(x)$  becomes  $r_{s_1}(x) + x^{j_1}$ ;
- 8) for the modified  $r$  repeat from 2).

In this algorithm, we could use set of cyclically different codewords of weight  $d$  or weight slightly higher than  $d$ . It is because if in the first set the codewords have only 0 coordinates in some of the cycles of  $\sigma$ , it is clear that no error in this cycle can be corrected. Also, if the first set is very small, the algorithm does not perform error correction close to the error-correction capability of the code. Therefore, experiments are required for finding a suitable number of low weight codewords that have good decoding performance. In Section V we give three examples and the decoding performance of different sets of codewords.

#### IV. PROOF OF LEMMA 1

To prove Lemma 1, we first prove that Eq. (10) holds for every  $u, v \in F_\sigma(\mathcal{C})$ , then for every  $u \in F_\sigma(\mathcal{C})$  and every  $v \in E_\sigma(\mathcal{C})$ , and at last, the statement in the lemma, for  $\forall u, v \in \mathcal{C}$ .

**Proposition 1.** *Let  $\mathcal{C}$  be a binary self-dual code having an automorphism  $\sigma$  of type  $pr - (t_1; 0)$ . Let each  $u \in F_\sigma(\mathcal{C})$  be presented as  $u = (u_1(x), u_2(x), \dots, u_{t_1}(x))$ . Then, for  $u, v \in F_\sigma(\mathcal{C})$  it follows:*

$$u_1(x)v_1(x^{-1}) + \dots + u_{t_1}(x)v_{t_1}(x^{-1}) = 0. \quad (15)$$

*Proof.* The codewords of the subcode  $F_\sigma(\mathcal{C})$  can be seen as one row circulant matrices in Eq. (4). Moreover, the coordinates of a fixed codeword are constant in each  $pr$  cycle, i.e.,  $v|\Omega_i = (0, 0, \dots, 0)$  or  $v|\Omega_i = (1, 1, \dots, 1)$  for  $v \in F_\sigma(\mathcal{C}), 1 \leq i \leq t_1$ . If a map  $\pi$  is defined as in Eq. (8), then  $\pi(F_\sigma(\mathcal{C}))$  is a binary  $[t_1, t_1/2]$  self-dual code.

Therefore,  $t_1$  must be even and the weight of each element in  $\pi(F_\sigma(\mathcal{C}))$  must also be even. Thus, each fixed codeword in  $\mathcal{C}$  has an even number of  $v|\Omega_i = (1, 1, \dots, 1)$ . This written in polynomials in  $\mathbb{F}_2[x]/(x^{pr} - 1)$  is:

each  $g = (g_1(x), g_2(x), \dots, g_{t_1}(x)) \in F_\sigma(\mathcal{C})$  has an even number of coordinates  $g_s(x)$  of the form  $1 + x + x^2 + \dots + x^{pr-1}$ .

If  $1 + x + x^2 + \dots + x^{pr-1}$  is denoted by  $g_0(x)$ , then it is clear that  $g_0(x^{-1}) = g_0(x) \pmod{x^{pr} - 1}$  and  $g_0(x)g_0(x^{-1}) = g_0(x) \pmod{x^{pr} - 1}$ .

Thus, we can conclude that Eq. (15) holds for two codewords in  $F_\sigma(\mathcal{C})$  if they intersect in even positive number of cycle positions with full one vector or, they intersect in 0 cycle positions with full one vector.

Let we assume that there exist two codewords  $v, v' \in F_\sigma(\mathcal{C})$  that intersect in odd number of cycle positions with full one vector and this odd number is  $z$ . Since the length of the cycles is  $pr$ , then the regular inner product of  $v$  and  $v'$ ,  $v.v' = v_1v'_1 + v_2v'_2 + \dots + v_{prt_1}v'_{prt_1} \pmod{2}$ , will be equal to  $zpr$ , where  $z$  is odd and  $p$  and  $r$  are odd primes. Thus,

$v.v' = zpr \equiv 1 \pmod{2}$ , which is a contradiction to  $\mathcal{C}$  being a self-dual code. Therefore, Eq. (10) holds for any two codewords in  $F_\sigma(\mathcal{C})$ .  $\square$

Let now  $u \in F_\sigma(\mathcal{C})$  and  $v \in E_\sigma(\mathcal{C})$ , where  $u = (u_1(x), u_2(x), \dots, u_{t_1}(x))$  with coordinates  $u_i(x) = 0$  or  $u_i(x) = 1 + x + x^2 + \dots + x^{pr-1}$ , and  $v = (v_1(x), v_2(x), \dots, v_{t_1}(x))$ , where  $v_i(x) \in \mathcal{P}$ .

Since the weight of  $\pi(u)$  is even, then  $u$  contains even number of coordinates equal to  $1 + x + x^2 + \dots + x^{pr-1}$ . Let  $u_i(x) = 1 + x + x^2 + \dots + x^{pr-1}$  for  $i \in \{\alpha_1, \alpha_2, \dots, \alpha_{2s}\}$ . Then,  $\langle u, v \rangle$  and  $\langle v, u \rangle$  are:

$$\begin{aligned} \langle u, v \rangle &= \sum_{i=1}^{t_3} u_i(x) v_i(x^{-1}) = \\ &= \sum_{i \in \{\alpha_1, \dots, \alpha_{2s}\}} (1 + x + x^2 + \dots + x^{pr-1}) v_i(x^{-1}) = \\ &= \sum_{i \in \{\alpha_1, \alpha_2, \dots, \alpha_{2s}\}} \frac{x^{pr}-1}{x-1} v_i(x^{-1}) = \\ &= \frac{x^{pr}-1}{x-1} \sum_{i \in \{\alpha_1, \alpha_2, \dots, \alpha_{2s}\}} v_i(x^{-1}) \\ \langle v, u \rangle &= \sum_{i=1}^{t_3} v_i(x) u_i(x^{-1}) = \\ &= \sum_{i=1}^{t_3} v_i(x) u_i(x) = \\ &= \frac{x^{pr}-1}{x-1} \sum_{i \in \{\alpha_1, \alpha_2, \dots, \alpha_{2s}\}} v_i(x) \end{aligned}$$

Thus,

$$\begin{aligned} \langle u, v \rangle &\equiv 0 \pmod{x^{pr}-1} \text{ if and only if} \\ \sum_{i \in \{\alpha_1, \alpha_2, \dots, \alpha_{2s}\}} v_i(x^{-1}) &\equiv 0 \pmod{x-1} \\ &\text{and} \end{aligned} \tag{16}$$

$$\begin{aligned} \langle v, u \rangle &\equiv 0 \pmod{x^{pr}-1} \text{ if and only if} \\ \sum_{i \in \{\alpha_1, \alpha_2, \dots, \alpha_{2s}\}} v_i(x) &\equiv 0 \pmod{x-1}. \end{aligned}$$

Let us discuss the coordinates  $v_i(x)$  of  $v \in E_\sigma(\mathcal{C})$ . By definition  $E_\sigma(\mathcal{C}) = \{v \in \mathcal{C} \mid \text{wt}(v|_{\Omega_i}) \equiv 0 \pmod{2}, i = 1, \dots, t_1\}$ , which implies that the weight of  $v_i(x)$  is even for  $1 \leq i \leq t_1$ . When  $v_i(x)$  has even number of nonzero coefficients, then  $v_i(1) = 0$  in  $\mathbb{F}_2$ , which means 1 is a root of  $v_i(x)$ . Therefore,  $x-1$  divides  $v_i(x)$  for  $1 \leq i \leq t_1$ .

From this one can conclude that

$$\sum_i v_i(x) \equiv 0 \pmod{x-1}$$

for any  $i$  and in particular, this will also be satisfied for  $i \in \{\alpha_1, \alpha_2, \dots, \alpha_{2s}\}$ , which means that

$$\sum_{i \in \{\alpha_1, \alpha_2, \dots, \alpha_{2s}\}} v_i(x) \equiv 0 \pmod{x-1}. \tag{17}$$

Is  $\sum_{i \in \{\alpha_1, \alpha_2, \dots, \alpha_{2s}\}} v_i(x^{-1}) \equiv 0 \pmod{x-1}$  also true?

The polynomial  $v_i(x^{-1}) \equiv v_i(x^{pr-1}) \in \mathbb{F}_2[x]/(x^{pr}-1)$ .

Since  $x \equiv 1 \pmod{x-1}$  it follows that  $x^{pr-1} \equiv 1 \pmod{x-1}$  and then,  $x^{pr-1} - 1 \equiv 0 \pmod{x-1}$ .

From above,  $x - 1$  divides  $v_i(x)$  for  $1 \leq i \leq t_1$ . Thus,

$$v_i(x) = (x - 1)v'_i(x)$$

and then,

$$\begin{aligned} v_i(x^{-1}) &= v_i(x^{pr-1}) = \\ &= (x^{pr-1} - 1) v'_i(x^{pr-1}) \equiv 0 \pmod{x - 1} \end{aligned}$$

for  $1 \leq i \leq t_1$ .

In particular, it also holds for  $i \in \{\alpha_1, \alpha_2, \dots, \alpha_{2s}\}$  and therefore

$$\sum_{i \in \{\alpha_1, \alpha_2, \dots, \alpha_{2s}\}} v_i(x^{-1}) \equiv 0 \pmod{x - 1}. \quad (18)$$

Combining Eqs. (16), (17), and (18), we derive the following proposition.

**Proposition 2.** *Let  $\mathcal{C}$  be a binary self-dual code having an automorphism  $\sigma$  of type  $pr - (t_1; 0)$ . Then  $u \in F_\sigma(\mathcal{C})$ ,  $v \in E_\sigma(\mathcal{C})$  are orthogonal, namely  $\langle u, v \rangle \equiv 0 \pmod{x^{pr} - 1}$  and  $\langle v, u \rangle \equiv 0 \pmod{x^{pr} - 1}$ .*

Summarizing Proposition 1, Proposition 2, and [8, Lemma 1], we can prove Lemma 1.

*Proof.* Let  $u, v \in \mathcal{C}$ , where  $\mathcal{C} = F_\sigma(\mathcal{C}) \oplus E_\sigma(\mathcal{C})$ . Then,

$$u = u' + u'', \quad v = v' + v'',$$

where  $u', v' \in F_\sigma(\mathcal{C})$  and  $u'', v'' \in E_\sigma(\mathcal{C})$ . The inner product of  $u$  and  $v$  is

$$\begin{aligned} \langle u, v \rangle &= \langle u' + u'', v' + v'' \rangle = \\ &= \langle u', v' \rangle + \langle u', v'' \rangle + \langle u'', v' \rangle + \langle u'', v'' \rangle. \end{aligned}$$

The first term  $\langle u', v' \rangle = 0$  according to Proposition 1. The next two terms are also 0 because of Proposition 2. The last term  $\langle u'', v'' \rangle$  is also 0 because  $\varphi(E_\sigma(\mathcal{C}))$  is a self-orthogonal code [8, Lemma 1]. Therefore,  $\langle u, v \rangle = 0$  for any  $u, v \in \mathcal{C}$ .  $\square$

**Remark 1.** *In case the binary self-dual code  $\mathcal{C}$  has an automorphism  $\gamma$  of odd prime order  $p$  with  $c$  cycles and no fixed points (type  $p - (c, 0)$ ), the fixed subcode  $F_\gamma(\mathcal{C})$  is also self-dual [11] and, the image  $\varphi(E_\gamma(\mathcal{C}))$  of the even subcode  $E_\gamma(\mathcal{C})$  is also self-orthogonal [12]. Following the proofs of Proposition 1 and Proposition 2, one can conclude that they also hold for  $p$  instead of  $pr$ . Therefore, Lemma 1 is also a valid statement for self-dual codes with an automorphism of type  $p - (c, 0)$ . With this, the group of the self-dual codes that can be decoded by the new decoding scheme is expanded.*

## V. EXAMPLES

The decoding algorithm is applied on three examples of self-dual code with the required structure, where two of the codes are known, whereas the third one is new. The last is constructed to demonstrate that self-dual codes with automorphism of the particular type exist and it is not hard to generate them when their minimum weight is not close to its upper bound Eq. (1) and Eq. (2).

### A. Decoding of a Binary [90,45,14] Self-dual Code

**Example 1.** *Let  $\mathcal{D}$  be a binary [90,45,14] self-dual code with an automorphism  $\phi$  of type  $15 - (6; 0)$ . Note that it is an optimal code since the upper bound for the minimum distance is 16. The code  $\mathcal{D}$  holds the conditions in Lemma 1 and therefore, the decoding Algorithm 1 is applicable to it. The number of errors which  $\mathcal{D}$  is capable to correct is  $t \leq \lfloor \frac{d-1}{2} \rfloor$  errors, i.e., maximum 6 errors.*

In Appendix B, the construction of the generator matrix of the code  $\mathcal{D}$ , defined in Eq. (7) is included.

The code  $\mathcal{D}$  has 375 codewords of weight 14, 11 745 of weight 16 and 215 915 of weight 18. The rank of these sets is 45, 44, and 45, respectively. The cyclically different codewords are isolated and the sets are denoted by  $B_{14}$ ,  $B_{16}$ , and  $B_{18}$ , where  $|B_{14}| = 25$ ,  $|B_{16}| = 783$  and  $|B_{18}| = 14\,399$  (Table I).



TABLE I  
SETS OF CODEWORDS IN THE  $[90, 45, 14]$  S-D CODE  $\mathcal{D}$

weight $i$	$A_i$	rank	cyclically different	in simulations
14	375	45	$B_{14},  B_{14}  = 25$	$D_1,  D_1  = 25$
16	11 745	44	$B_{16},  B_{16}  = 783$	$D_2,  D_2  = 450$
18	215 915	45	$B_{18},  B_{18}  = 14 399$	$D_3,  D_3  = 340$

In simulations, we use three different sets of cyclically different codewords and compare their performance. The sets are  $D_1$ ,  $D_2$ , and  $D_3$ , which are also given in Table I.

We perform simulations on 2000 random error vectors and random encoded messages for each number of errors  $t$ , for  $t = 1, 2, \dots, 8$ . The simulation steps are:

- generate a random error vector  $e$  of length 90 and weight  $t$ ;
- generate a random message vector  $m$  of length 45;
- encode the message vector  $m$  into  $c = mG$ ;
- compute  $r = e + c$ ;
- decode the received vector  $r$  using the iteration steps 2 till 8 of Algorithm 1;

The results of the simulations are presented in Table II. They show that the set  $D_1$  of the cyclically different codewords of weight 14 is too small for a good decoding performance. The decoding algorithm, using each of the other two sets,  $D_2$  and  $D_3$ , reaches the error correcting capability of the code and corrects 100% of the errors, where errors are in the range up to 6. Moreover, these two sets in the experiments correct 99.95% and 95.35% of the cases with 7 errors, and 96.8% and 60.35% of the cases with 8 errors.

The results of the experiments indicate a high error-correcting capability of our new algorithm, a capability beyond the upper bound for  $t$ .

Note that the rank of the set of weight 16 codewords is 44 which means that it is possible in step 4) to obtain a vector  $r(x)$  such that the corresponding  $w(x) = 0$  but  $rG \neq 0$ . That is the reason we consider also the set  $D_3$  that has rank 45, and the described exception is not possible.

TABLE II  
DECODING PERFORMANCE OF THE  $[90, 45, 14]$  SELF-DUAL CODE  $\mathcal{D}$

Decoding set $D_1,  D_1  = 25$				Decoding set $D_2,  D_2  = 450$				Decoding set $D_3,  D_3  = 340$			
$t$	tested	corrected	%	$t$	tested	corrected	%	$t$	tested	corrected	%
1	90	90	100	1	90	90	100	1	90	90	100
2	2 000	1 932	96.6	2	2 000	2 000	100	2	2 000	2 000	100
3	2 000	1 928	96.4	3	2 000	2 000	100	3	2 000	2 000	100
4	2 000	1 955	97.75	4	2 000	2 000	100	4	2 000	2 000	100
5	2 000	1 930	96.5	5	2 000	2 000	100	5	2 000	2 000	100
6	2 000	1 829	91.45	6	2 000	2 000	100	6	2 000	2 000	100
7	2 000	1 268	63.4	7	2 000	1 999	99.95	7	2 000	1 907	95.35
8	2 000	560	28	8	2 000	1 936	96.8	8	2 000	1 207	60.35

### B. Decoding of a Binary $[78, 39, 14]$ Self-dual Code

**Example 2.** Let  $\mathcal{T}$  be a binary  $[78, 39, 14]$  self-dual code with an automorphism  $\phi_1$  of type  $39 - (2; 0)$ . Note that  $\mathcal{T}$  is an extremal code [6]. Since  $d = 14$ , the number of errors which  $\mathcal{T}$  is capable to correct is up to 6. As in the previous example, the conditions in Lemma 1 are satisfied for the code  $\mathcal{T}$  and therefore, the decoding Algorithm 1 is applicable to  $\mathcal{T}$ .

A generator matrix of  $\mathcal{T}$  is available in Appendix B.

This particular example has 3 081 minimum weight codewords and 46 116 codewords of weight 16. The rank of the sets is 39 and 38, respectively. Among them the cyclically different are 79 with weight 14 and 1 644 with weight 16.

The set of 79 elements is denoted by  $T_1$  and the set of 79 elements of weight 14 together with 244 elements of weight 16 is denoted by  $T_2$  (Table III). The sets  $T_1$  and  $T_2$  are used in the decoding simulations.



TABLE III  
SETS OF CODEWORDS IN THE  $[78, 39, 14]$  SELF-DUAL CODE  $\mathcal{T}$

weight $i$	$A_i$	rank	cyclically different	in simulations
14	3 081	39	$B_{14},  B_{14}  = 79$	$T_1,  T_1  = 79$
16	46 116	38	$B_{16},  B_{16}  = 1\,644$	$T'_2,  T'_2  = 244$
14,16	49 197	39	$B_{14} \cup B_{16}$	$T_2 = T_1 \cup T'_2$

Similarly to the first decoding example, for both sets  $T_1$  and  $T_2$ , for each  $t$ ,  $1 \leq t \leq 8$ , we perform simulations on 2000 random error vectors and random encoded messages. The simulation steps are the same. The results are included in Table IV.

TABLE IV  
DECODING PERFORMANCE OF THE  $[78, 39, 14]$  SELF-DUAL CODE  $\mathcal{T}$

Decoding set $T_1,  T_1  = 79$				Decoding set $T_2,  T_2  = 323$			
$t$	tested	corrected	%	$t$	tested	corrected	%
1	78	78	100	1	78	78	100
2	2 000	2 000	100	2	2 000	2 000	100
3	2 000	2 000	100	3	2 000	2 000	100
4	2 000	2 000	100	4	2 000	2 000	100
5	2 000	2 000	100	5	2 000	2 000	100
6	2 000	2 000	100	6	2 000	2 000	100
7	2 000	1 974	98.7	7	2 000	1 995	99.75
8	2 000	1 530	76.5	8	2 000	1 725	86.25

The values in Table IV show that the set of 14 weight codewords are sufficient for the complete decoding of 6 errors which is the upper bound for the error capability of this code example. Differently from the first code, here both, the set  $T_1$  and  $T_2$ , have a high error-correcting performance beyond the upper bound for  $t$ .

In both decoding examples, the complete set of 16 (or 16 and 18) weight cyclically different codewords is not considered. There is a trade-off between the speed and memory of the decoder from one side and the decoding performance of the algorithm from another side. To achieve decoding up to  $\frac{d-1}{2}$  errors for the first example it is sufficient to use set  $D_3$  with 340 codewords and for the second example, set  $T_1$  with 79 codewords.

### C. Decoding of a Binary $[266, 133, 36]$ Self-dual Code

**Example 3.** Let  $B$  be a binary  $[266, 133, 36]$  self-dual code with an automorphism  $\phi_2$  of type  $133 - (2; 0)$ . It is an optimal code since the upper bound for  $d$  is 48 (Eq. (1)) and, to the best of our knowledge, there is no example of a self-dual  $[266, 133, d \geq 36]$ . The code  $B$  has error correcting capability of 17 errors. Since the code possesses the specific automorphism of type  $pr - (t_1; 0)$ , then the conditions in Lemma 1 are satisfied and the decoding Algorithm 1 is applicable to  $B$ .

First, the construction of the code is presented and then the decoding experiments.

The code  $B$  possesses an automorphism  $\phi_2$  of type  $133 - (2; 0)$ . Then:

- 1)  $B = F_{\phi_2}(B) \oplus E_{\phi_2}(B)$ ;
- 2) the fixed subcode  $\pi(F_{\phi_2}(B))$  is a binary  $[2, 1]$  self-dual code, and
- 3) the vectors of the image  $\varphi(E_{\phi_2}(B))$  are from  $\mathcal{P}^2$ , where  $\mathcal{P} \subset \mathbb{F}_2/(x^{133} - 1)$ .

From 2) it follows that the generator matrix of  $F_{\phi_2}(B)$  is  $X = \begin{pmatrix} l & l \end{pmatrix}$ , where  $l = (1, 1, \dots, 1)$  is the full one vector in  $\mathbb{F}_2^{133}$ .

Applying 3) by computer check an example for the generator matrix  $Y$  of  $F_{\phi_2}(B)$  is obtained:

$$Y = \begin{pmatrix} y_{1,1} & y_{1,2} \\ \vdots & \vdots \\ y_{9,1} & y_{9,2} \end{pmatrix},$$

where  $y_{i,j}$  are right-circulant  $3 \times 133$  cells for the first 2 rows in  $Y$  and  $y_{i,j}$  are right-circulant  $18 \times 133$  cells for the next 7 rows. The first rows of these circulant matrices are given in Table IX in Appendix B.

For the code  $B$  only part of the codewords with weight 36, 38 and 40 are generated. They are denoted by  $L_{36}$ ,  $L_{38}$  and  $L_{40}$ , respectively (Table V). For decoding of code  $B$  we use two sets,  $M_1$  and  $M_2$ , of cyclically different codewords. Both of them contain elements of  $L_{36}$ ,  $L_{38}$  and  $L_{40}$ . Details are given in Table V.

TABLE V  
SETS OF CODEWORDS IN THE  $[266, 133, 36]$  S-D CODE  $B$

weight $i$	cyclically different	rank
36	$L_{36},  L_{36}  = 16$	16
38	$L_{38},  L_{38}  = 58$	58
40	$L_{40},  L_{40}  = 2\,616$	132
36	$M_{1,36} \subset L_{36},  M_{1,36}  = 13$	13
38	$M_{1,38} \subset L_{38},  M_{1,38}  = 22$	22
40	$M_{1,40} \subset L_{40},  M_{1,40}  = 1\,455$	132
40	$M_{2,40} \subset L_{40},  M_{2,40}  = 2\,594$	132
36,38,40	$M_1 = M_{1,36} \cup M_{1,38} \cup M_{1,40}$	133
36,38,40	$M_2 = L_{36} \cup L_{38} \cup M_{2,40}$	133

As in the previous two examples, for the sets  $M_1$  and  $M_2$  and each number of errors  $t$ , in this case  $13 \leq t \leq 18$ , we perform a decoding experiment on 2 000 received encoded messages with  $t$  errors. The simulation steps described in V-A are followed, where the length of the error vector is 266 and the length of the message is 133. The results of the simulations are provided in Table VI.

TABLE VI  
DECODING PERFORMANCE OF THE  $[266, 133, 36]$  SELF-DUAL CODE  $B$

Decoding set $M_1,  M_1  = 1\,490$				Decoding set $M_2,  M_2  = 2\,614$			
$t$	tested	corrected	%	$t$	tested	corrected	%
13	2 000	2 000	100	13	2 000	2 000	100
14	2 000	1 945	97.25	14	2 000	2 000	100
15	2 000	1 635	81.75	15	2 000	2 000	100
16	2 000	1 075	53.75	16	2 000	1 476	73.8
17	2 000	543	27.15	17	2 000	1 040	52
18	2 000	350	17.5	18	2 000	404	20.2

Code  $B$  has error-correcting capability of 17 errors. The results in Table VI show that set  $M_1$  is too small for decoding via the new algorithm since only 13 errors are 100% corrected whereas 17 errors are corrected in only 27.15% of the cases. When using the set  $M_2$  the new decoding Algorithm 1 corrects the errors upto 15 in 100% of the cases and 16 errors in almost 74%. The algorithm reaches the error-correcting capability of the code  $B$  in only 52% of the cases. To increase the error-correction performance, a larger number of cyclically different codewords of weight 36 and close to 36 have to be generated and included in the decoding set. Note that  $L_{36}$ ,  $L_{38}$  and  $L_{40}$  are only part of the sets of codewords with weight 36, 38 and 40. We expect that if the decoding Algorithm 1 uses all the cyclically different codewords of weight 36 and 38 together with a subset of  $L_{40}$ , then it will reach the error-correction capability of the code in 100% of the cases.

## VI. OPEN QUESTIONS AND LIMITATIONS

The proposed decoding algorithm opens some questions about its possible applications. One of those questions is if a programming implementation can reach the speed requirements for any of the current decoding applications. Is an efficient hardware implementation possible, for example an efficient very large scale integrated (VLSI) implementations of en/decoder? Another open question is if this algorithm is suitable for use in the decryption process of Code-based cryptosystems.

Since the algorithm uses a subset of the minimum weight, or close to the minimum weight codewords, it implies a limitation for a large length extremal or optimal self-dual codes. This is because this set of codewords first has to be generated, which is computationally expensive (infeasible) for a large length and minimum distance. Moreover, extremal self-dual codes are only known for a length up to 130.

Regardless of the questions above, we proposed an efficient decoding algorithm for a large family of self-dual codes.

Moreover, it is well known that the automorphism groups of one of the best self-dual codes have a very large order. For example, the extended Golay code  $G_{24}$  - Mathieu group  $M_{24}$  of order  $2^{10} \cdot 3^3 \cdot 5 \cdot 7 \cdot 11 \cdot 23 = 244\,823\,040$  or extended quadratic residue code  $QR_{80}$  -  $PSL(2, 79)$  of order  $2^4 \cdot 3 \cdot 5 \cdot 13 \cdot 79 = 246\,480$ . This is an indicator that the new decoding scheme would be applicable for a large set of self-dual codes with as high as possible error correcting capability.

## REFERENCES

- [1] V. Pless, W. Huffman, *Fundamentals of Error-Correcting Codes*, Amsterdam, The Netherlands: Cambridge University Press, 2003.
- [2] V. Pless, *Decoding the Golay codes*, IEEE Transactions on Information Theory, vol. 32, no. 4, pp. 561-567, July 1986, doi:10.1109/TIT.1986.1057197.
- [3] J. Kim, N. Lee, *A projection decoding of a binary extremal self-dual code of length 40*, Des. Codes Cryptogr., vol. 83, p. 589-609, 2017.
- [4] P. Gaborit, J. Kim, V. Pless, *Decoding binary  $R(2,5)$  by hand*, Discrete Mathematics, vol. 264, p. 55 - 73, 2003.

- [5] E. M. Rains, *Shadow bounds for self-dual codes*, IEEE Trans. Inform. Theory, vol. 44, pp. 134–139, 1998.
- [6] S. Dougherty, T. Gulliver, and M. Harada, *Extremal binary self-dual codes*, IEEE Transactions on Information Theory, vol. 43, no. 6, pp. 2036–2047, 1997.
- [7] S. Zhang, *On the nonexistence of extremal self-dual codes*, Discrete Applied Math., vol. 91, pp. 277–286, 1999.
- [8] R. Yorgova, *On binary self-dual codes with automorphisms*, IEEE Trans. of Inf. Theory, vol. 54, no. 7, pp. 3345–3351, 2008.
- [9] R. Dontcheva, A. Zanten, and S. M. Dodunekov, *Binary self-dual codes with automorphisms of composite order*, IEEE Trans. of Inf. Theory, vol. 50, no. 2, pp. 311–318, 2004.
- [10] M. Bossert, *On decoding using codewords of the dual code*, CoRR (Computing Research Repository), Jan 2020. <http://arxiv.org/abs/2001.02956>
- [11] W. Huffman, “Automorphisms of codes with applications to extremal doubly even codes of length 48,” IEEE Transactions on Information Theory, vol. 28, no. 3, pp. 511–521, 1982.
- [12] V. Yorgova, *Binary self-dual codes with automorphisms of odd order*, Problems Inform. Transmission, vol. 19, no. 4, p. 260–270, 1983.
- [13] R. Yorgova, *Binary self-dual extremal codes of length 92*, in 2006 IEEE International Symposium on Information Theory, 2006, pp. 1292–1295.

## APPENDIX A DECODING ALGORITHM

Algorithm 1 gives the pseudocode of how to decode self-dual codes having an automorphism.

---

### Algorithm 1: Decoding self-dual codes having an automorphism

---

- 1 Generate the set  $D_1$  of all or almost all cyclically different codewords of weight  $d$  or  $d + o$  for some small  $o$  (2, 4, or 6)
  - 2 Compute  $rG$ .  
If  $rG = 0$  ( $r \in \mathcal{C}$ )  $\rightarrow$  end,  
else  $\rightarrow$  3);
  - 3 Split  $r$  into  $t_1$  polynomials of  $\mathbb{F}_2[x]/(x^{pr} - 1)$ , i.e.,  $r = (r_1(x), r_2(x), \dots, r_{t_1}(x))$
  - 4 Compute:
    - $w(x) = \langle r, b \rangle = r_1(x)b_1(x^{-1}) + r_2(x)b_2(x^{-1}) + \dots + r_{t_1}(x)b_{t_1}(x^{-1}) \bmod (x^{pr} - 1)$
    - for  $\forall b \in D_1$ ,  $b = (b_1(x), b_2(x), \dots, b_{t_1}(x))$
    - $x^{\beta_i^{(1)}} w(x) \bmod (x^{pr} - 1)$  for  $\forall \beta_i^{(1)} \in \text{supp}(b_1)$
    - $x^{\beta_i^{(2)}} w(x) \bmod (x^{pr} - 1)$  for  $\forall \beta_i^{(2)} \in \text{supp}(b_2)$
    - $\vdots$
    - $x^{\beta_i^{(t_1)}} w(x) \bmod (x^{pr} - 1)$  for  $\forall \beta_i^{(t_1)} \in \text{supp}(b_{t_1})$
  - 5 Compute  $\Phi_j^{(s)}$  defined in Eq. (14) for  $j = 0, 1, \dots, pr - 1$ ,  $s = 1, 2, \dots, t_1$ ;
  - 6 Determine  $\Phi_{max} = \max\{\Phi_j^{(s)}\}$  and, the cycle  $s_1$  and position(s)  $j_1$  such that  $\Phi_{j_1}^{(s_1)} = \Phi_{max}$
  - 7 Compute  $r_{s_1}(x) + x^{j_1}$ .  
 $r_{s_1}(x) \leftarrow r_{s_1}(x) + x^{j_1}$
  - 8 Repeat from 2) for the modified  $r$ .
- 

## APPENDIX B GENERATOR MATRICES FOR THE EXAMPLES

This section provides generator matrices for the examples as discussed in Section V.

### A. Example V-A

Let  $\mathcal{D}$  be the binary [90, 45, 14] self-dual code of Example V-A. The generator matrix of  $\mathcal{D}$  defined in Eq. (7) requires the matrices  $X$  and  $Y$  generating the subcodes  $F_\phi(\mathcal{D})$  and  $E_\phi(\mathcal{D})$ , respectively.

For  $X$  a possible choice is

$$X = \begin{pmatrix} l & o & l & o & o & o \\ o & l & o & l & o & o \\ o & o & o & o & l & l \end{pmatrix},$$

where  $l = (1, 1, \dots, 1)$ ,  $o = (0, 0, \dots, 0)$ , i.e., the full one vector and the zero vector in  $\mathbb{F}_2^{15}$ .

The subcode  $E_\phi(\mathcal{D})$  is generated via its image  $\varphi(E_\phi(\mathcal{D}))$ . A full description of how the subcode  $\varphi(E_\phi(\mathcal{D}))$  is constructed is available in [13]. Here, we present one example of generator matrix of  $\varphi(E_\phi(\mathcal{D}))$ , namely:

$$A' = \begin{pmatrix} e_1(x) & 0 & 0 & 0 & \mu_1(x) & \mu_1^2(x) \\ 0 & e_1(x) & 0 & \mu_1(x) & \mu_1(x) & \mu_1^{12}(x) \\ 0 & 0 & e_1(x) & \mu_1^2(x) & \mu_1^{12}(x) & \mu_1^8(x) \\ e_2(x) & 0 & 0 & 0 & \mu_2(x) & \mu_2(x) \\ 0 & e_2(x) & 0 & \mu_2(x) & \mu_2(x) & 0 \\ 0 & 0 & e_2(x) & \mu_2(x) & \mu_2(x) & \mu_2(x) \\ 0 & \mu_3(x) & \mu_3(x) & e_3(x) & 0 & 0 \\ \mu_3(x) & \mu_3(x) & \mu_3(x) & 0 & e_3(x) & 0 \\ \mu_3(x) & 0 & \mu_3(x) & 0 & 0 & e_3(x) \\ e_4(x) & 0 & 0 & 0 & 0 & \mu_4(x) \\ 0 & e_4(x) & 0 & 0 & \mu_4^2(x) & 0 \\ 0 & 0 & e_4(x) & \mu_4^2(x) & 0 & 0 \end{pmatrix},$$

where  $e_i, \mu_i$  for  $1 \leq i \leq 4$  are given in Table VII. All the polynomials in  $A'$  are even weight polynomials of  $\mathbb{F}_2[x]/(x^{15} - 1)$ .

TABLE VII  
ELEMENTS OF  $\mathbb{F}_2[x]/(x^{15} - 1)$

$e_1$	$x^{14} + x^{13} + x^{12} + x^{11} + x^9 + x^8 + x^7 + x^6 + x^4 + x^3 + x^2 + x$
$e_2$	$x^{14} + x^{13} + x^{12} + x^{11} + x^9 + x^7 + x^6 + x^3$
$e_3$	$x^{12} + x^9 + x^8 + x^6 + x^4 + x^3 + x^2 + x$
$e_4$	$x^{14} + x^{13} + x^{11} + x^{10} + x^8 + x^7 + x^5 + x^4 + x^2 + x$
$\mu_1$	$x^{11} + x^{10} + x^6 + x^5 + x + 1$
$\mu_2$	$x^{14} + x^{13} + x^{11} + x^9 + x^8 + x^5 + x + 1$
$\mu_3$	$x^{14} + x^{10} + x^7 + x^6 + x^4 + x^2 + x + 1$
$\mu_4$	$x^{13} + x^{12} + x^{10} + x^9 + x^7 + x^6 + x^4 + x^3 + x + 1$

The corresponding generator matrix of the subcode  $E_\phi(\mathcal{D})$  is

$$Y = \begin{pmatrix} y_{1,1} & \cdots & y_{1,6} \\ \vdots & \ddots & \vdots \\ y_{12,1} & \cdots & y_{12,6} \end{pmatrix},$$

where  $y_{i,j}$  are right-circulant  $4 \times 15$  cells for the first 9 rows in  $Y$  and  $y_{i,j}$  are right-circulant  $2 \times 15$  cells for the last 3 rows. The first rows of these circulant matrices are corresponding to the given polynomials in matrix  $A'$ .

### B. Example 2

Let  $\mathcal{T}$  be the binary  $[78, 39, 14]$  self-dual code with an automorphism  $\phi_1$  of type  $39 - (2; 0)$  considered in V-B.

The matrices  $X$  and  $Y$  of the generator matrix of  $\mathcal{T}$  defined in Eq. (7) are:

$$X = \begin{pmatrix} l & l \end{pmatrix},$$

where  $l = (1, 1, \dots, 1)$  is the full one vector in  $\mathbb{F}_2^{39}$  and

$$Y = \begin{pmatrix} y_{1,1} & y_{1,2} \\ y_{2,1} & y_{2,2} \\ y_{3,1} & y_{3,2} \\ y_{4,1} & y_{4,2} \end{pmatrix},$$

where  $y_{i,j}$  are right-circulant  $12 \times 38$  cells for the first 3 rows in  $Y$  and  $y_{i,j}$  are right-circulant  $2 \times 39$  cells for the last row. The first rows of these circulant matrices are given in Table VIII.

TABLE VIII  
COEFFICIENTS OF POLYNOMIALS IN  $\mathbb{F}_2[x]/(x^{39} - 1)$

$y_{1,1}$	00010011010010110111010110011111011111
$y_{1,2}$	110011010100011111000101000011010111100
$y_{2,1}$	100111101011000010100011111000101011001
$y_{2,2}$	011111101111100110101110110100101100100
$y_{3,1}$	011010000010001101000001000110100000100
$y_{3,2}$	01111111111101111111111111011111111111
$y_{4,1}$	011011011011011011011011011011011011011
$y_{4,2}$	011011011011011011011011011011011011011

## C. Example 3

TABLE IX  
COEFFICIENTS OF POLYNOMIALS IN  $\mathbb{F}_2[x]/(x^{133} - 1)$

$y_{1,1}$	111010011101001110100111010011101001110100111010011 1010011101001110100111010011101001110100111010011101001110 1001110100111010011101001110100
$y_{1,2}$	000 000 000
$y_{2,1}$	000 000 000
$y_{2,2}$	100101110010111001011100101110010111001011100101110 010111001011100101110010111001011100101110010111001 0111001011100101110010111001011
$y_{3,1}$	00010011010111100110011110101001001110010111111110 11001100101110000101111010110001010111111010111000 1111000011100100110010101000000
$y_{3,2}$	000 000 000
$y_{4,1}$	1001110111001101110101010100101001111010000100000 100100001111001100100101010010110010111011010011011 1010110010010000101110010000011
$y_{4,2}$	000000010101001100100111000011110001110101111111010 10001101011110100001110100110011011111111010011100 1001010111100110011110101100100
$y_{5,1}$	011110111000111111000100111011101011010000100000111 011001011100111011010011101010100110000010100101110 0111110100110010111101001110100
$y_{5,2}$	1001110111001101110101010100101001111010000100000 100100001111001100100101010010110010111011010011011 1010110010010000101110010000011
$y_{6,1}$	111000001001110100001001001101011101100101101110100 110100101010010011001111000010010000010000101111001 0100101010101011101100111011100
$y_{6,2}$	000101110010111101001100101111100111010010100000110 010101011100101101110011101001101110000010000101101 0111011100100011111100011101111
$y_{7,1}$	011011011010001010001100010110011101000011100101011 001111000011110110110000001011011100101110110011011 0001101011110101010011111011011
$y_{7,2}$	100011011100010100100111010101000000100000101010011 11111010110111011001010110011000000111111001011110 111111010101100001110101101011
$y_{8,1}$	1111010110101110000110101011111011110100111111000 00011001101010011011101101011111100101010000010000 0010101011100100101000111011000
$y_{8,2}$	011011011111001010101111010110001101100110111010011 10110100000011011011100001111001101010011100001011 1001101000110001010001011011011
$y_{9,1}$	011111111111111110111111111111111110111111111111111 111111011 11111111111011111111111111111111
$y_{9,2}$	100110111000010111010011011100001011101001101110000 101110100110111000010111010011011100001011101001101 1100001011101001101110000101110