

Multivariable Super-Twisting Algorithm for Systems with Uncertain Input Matrix and Perturbations^{*}

Jaime A. Moreno[†], Héctor Ríos^{‡*}, Luis Ovalle[§] and Leonid Fridman[§]

Abstract

This paper proposes a Lyapunov approach to the design of a multivariable generalized Super-Twisting algorithm (MGSTA), which is able to control a system with perturbations and uncertain control matrix, both depending on time and the system states. The presented procedure shows that, under reasonable assumptions for the uncertainties, it is always possible to find a set of constant gains for the MGSTA in order to ensure global and robust finite-time stability of the system's outputs. Simulation results on an omnidirectional mobile robot illustrate the performance of the MGSTA.

Index Terms

Sliding-mode control, Super-Twisting algorithm, Robust control, Uncertain systems.

I. INTRODUCTION

The Super-Twisting algorithm (STA) (see [1] and [2]) is one of the most cited non-linear controllers of the last two decades. The STA yields finite-time stabilization for a perturbed system with relative degree one using only output information. The STA achieves a second-order sliding motion providing a continuous control signal.

In the first stage of development, the convergence analysis of the STA was made based on a geometric approach (see [1] and [2]) considering the effect of time-varying uncertain control gains and perturbations. It took fifteen years until the first *strict* Lyapunov function ensuring finite-time convergence for the STA, was presented in [3] (see also [4]). The design of the Lyapunov functions in [3] and [4], pushed forward the analysis of the properties of STA and its applications.

Recently for the scalar case, in [5] and [6], the most general conditions for the gain selection of the STA have been found. Different approaches to estimate the convergence time for STA are summarized in [7] and [8]. Moreover, in [9] some new gain conditions for the STA are provided to guarantee the stability of an uncertain system with actuator saturation. A modified version of the STA has been proposed by [10] in order to ensure a saturated control signal. Similarly, in [11] and [12] some modifications to the structure of the STA are made to ensure the saturation of the control signal. In [13], a generalization of the STA has been presented to deal with a larger class of perturbations. In [14] the STA gains have been designed to minimize the amplitude of chattering or the energy needed to maintain the real second-order sliding-mode. The previously mentioned approaches gave way for the usage of the STA in different applications: wind turbines [15], pneumatic actuators [16], fuel cells [17], quadrotor helicopters [18] and [19] and many others. Applications of [1] – [14] clarify two main restrictions of these results:

- 1) The perturbations are assumed to have an *a priori* known Lipschitz constant, preventing them to grow with the states.
- 2) The presence of state-dependent uncertainty in the control gain is not considered.

These two problems have been solved in [20] adding linear terms to the discontinuous control law. However, since the previous results allow only for a scalar control input, a major problem remains: only systems with multiple inputs can be taken into account if they can be decoupled into scalar subsystems that can be treated independently. This restricts considerably the possible applications, since uncertain couplings between control channels cannot be considered.

[†]Universidad Nacional Autónoma de México (UNAM), Instituto de Ingeniería, 04510, Mexico City, Mexico. Email: JMorenoP@ii.unam.mx

[‡]Tecnológico Nacional de México/I.T. La Laguna, División de Estudios de Posgrado e Investigación, Blvd. Revolución y Cuauhtémoc S/N, C.P. 27000, Torreón, Coahuila, Mexico.

[§]Universidad Nacional Autónoma de México (UNAM), Facultad de Ingeniería, 04510, Mexico City, Mexico.

*Cátedras CONACYT, Av. Insurgentes Sur 1582, C.P. 03940, Mexico City, Mexico. Email: hriosb@correo.itlalaguna.edu.mx

*The authors gratefully acknowledge the financial support from CONACYT project 282013, PAPIIT-UNAM projects IN115419 and IN102121, Cátedras CONACYT CVU 270504 project 922, and TECNM research projects.

This paper has been submitted for possible publication to IEEE Transactions on Automatic Control.

To deal with multiple-input systems some multivariable generalized Super-Twisting algorithms (MGSTA) have been developed. The Super-Twisting algorithm is a second-order sliding-mode controller and its structure is given by

$$\begin{bmatrix} u \\ \dot{v} \end{bmatrix} = \begin{bmatrix} -k_1\phi_1(x) + v \\ -k_2\phi_2(x) \end{bmatrix},$$

where $x \in \mathbb{R}^n$ is the variable to control, $u \in \mathbb{R}^n$ is the control signal, $v \in \mathbb{R}^n$ is an internal state of the algorithm and $k_1, k_2 \in \mathbb{R}$ represent the algorithm gains. The functions ϕ_1 and ϕ_2 are considered to be of the form $\phi_1(x) = (\alpha\|x\|^{-p} + \beta)x$ and $\phi_2(x) = [\alpha(1-p)\|x\|^{-p} + \beta](\alpha\|x\|^{-p} + \beta)x$. The first MGSTA design was proposed in [21], based on the Lyapunov function suggested in [4], with a Lipschitz perturbation. However, the presence of an uncertain input matrix is not considered. Two kinds of MGSTAs were introduced in [22] and [23], including the one proposed by [21] that is termed *unitary* (or quasi-continuous), since the control terms are divided by the norm of the states. In [24] conditions on the (unitary) MGSTA gains are given to ensure the global finite-time convergence despite of an unknown but **constant** and symmetric input matrix and Lipschitz perturbations. In [25] a (unitary) MGSTA with time and state-dependent gains is proposed for systems with known input matrix and state-dependent perturbations. However, they have not taken into account the main problem appearing in this case: in the derivative of the state-varying perturbation, the control signal appears once more (see the motivation example in [20] and Section II), causing an algebraic loop that requires special treatment.

In synthesis, the existing MGSTA designs cannot ensure the convergence of the trajectories of the system in three very important situations:

- Systems with a state- and time-dependent uncertain input matrix, *e.g.*, mechanical systems with parametric uncertainties in the inertia matrix.
- Systems with state- and time-dependent perturbations, *e.g.*, the tracking problem of any uncertain mechanical system.
- Systems with state- and time-dependent actuator faults.

In this paper a unitary MGSTA for the control of a system with state- and time-dependent uncertain control matrix and perturbations is proposed. It is shown that under reasonable assumptions for the uncertainties, it is always possible to find a set of constant gains to ensure global and robust finite-time stability of the closed-loop system. Furthermore, a procedure to choose a set of gains is proposed. Moreover, the structure presented in [21], [24] and [25] is generalized by allowing not only discontinuous terms in the algorithm, adding an extra degree of freedom in the design.

The tracking control problem for an omnidirectional mobile robot is considered as a motivation example. In this example it is shown that the conditions given by [21], [24] and [25] cannot be satisfied. On the other hand, the proposed methodology ensures the global finite-time stability of the closed-loop system for a larger class of dynamical systems. The simulation results illustrate the effectiveness of the proposed methodology.

This paper is structured as follows: Section II presents a motivational example, while Section III states the problem to be solved and working assumptions. In Section IV the main result of the paper is announced. Section V shows a simulation study illustrating the results and Section VI furnishes some concluding remarks. The stability proof of the main result is provided in the Appendix.

Notation: For a matrix $M \in \mathbb{R}^{n \times n}$, the symmetric component is $\text{Sym}\{M\} = \frac{1}{2}(M + M^T)$, while $\text{Gram}\{M\} = M^T M$ is the Gramian matrix. Recall that $\|M\|_2^2 = \sigma_{\max}^2\{M\} = \lambda_{\max}\{\text{Gram}\{M\}\}$, where $\sigma_{\max}\{M\}$ represents the largest singular value of matrix M and $\mathbb{R}_+ = \{x \in \mathbb{R} \mid x \geq 0\}$.

II. MOTIVATION EXAMPLE

Consider the dynamics of a four-wheeled omnidirectional mobile robot (for more details, see [26] and [27]):

$$\ddot{q} = M^{-1} \left[\frac{k_a r_e}{r_a} R^T(\theta) E \nu - C(\dot{q}) \dot{q} - f_r(\dot{q}) + w(t, q, \dot{q}) \right], \quad (1)$$

where $q = [x, y, \theta]^T \in \mathbb{R}^3$ is a vector containing the configuration variables in the task space, $\nu \in \mathbb{R}^4$ is a vector with the motor armature voltages while $w : \mathbb{R} \times \mathbb{R}^3 \times \mathbb{R}^3 \rightarrow \mathbb{R}^3$ represents some external disturbances. The matrices $M \in \mathbb{R}^{3 \times 3}$, $R(\theta) \in \mathbb{R}^{3 \times 3}$, $E \in \mathbb{R}^{3 \times 4}$, and $C(\dot{q}) \in \mathbb{R}^{3 \times 3}$ are the inertia matrix, the rotation matrix for a planar motion, the transpose of the Jacobian matrix and the Coriolis/centrifugal matrix, respectively; while $f_r : \mathbb{R}^3 \rightarrow \mathbb{R}^3$ is a friction force vector containing viscous and dry friction.

The structure of the system matrices is given by:

$$\begin{aligned}
M &= \text{diag}\{M_1, M_2, M_3\} + (J_2 + J_m r_e^2)EE^T, \\
R(\theta) &= \begin{bmatrix} \cos \theta & \sin \theta & 0 \\ -\sin \theta & \cos \theta & 0 \\ 0 & 0 & 1 \end{bmatrix}, \\
E &= \frac{1}{r} \begin{bmatrix} 1 & 1 & 1 & 1 \\ 1 & -1 & 1 & -1 \\ L & -L & -L & L \end{bmatrix}, \\
C(\dot{q}) &= \frac{4}{r^2}(J_2 + J_m r_e^2) \tanh(\dot{\theta})B, \quad B = \begin{bmatrix} 0 & 1 & 0 \\ -1 & 0 & 0 \\ 0 & 0 & 0 \end{bmatrix}, \\
f_r(\dot{q}) &= f_v(\dot{q}) + f_d(\dot{q}), \\
f_v(\dot{q}) &= \begin{bmatrix} f_{vx}\dot{x} \\ f_{vy}\dot{y} \\ f_{v\theta}\dot{\theta} \end{bmatrix}, \quad f_d(\dot{q}) = \begin{bmatrix} f_{dx} \tanh(\dot{x}) \\ f_{dy} \tanh(\dot{y}) \\ f_{d\theta} \tanh(\dot{\theta}) \end{bmatrix},
\end{aligned}$$

where $M_1 = M_2 = m_1 + 4m_2$, $M_3 = 4m_2(l_1^2 + l_2^2) + J_1 + 4J_3$, with m_1 being the mass of the body, m_2 the mass of each wheel, J_1 the inertia of the body, J_2 and J_3 the inertia of the wheels over and perpendicular to the motor shaft, respectively; l_1 and l_2 the length from the robot center to the robot front and robot side, respectively; r the wheels radius, L the distance from the robot center to the wheels, J_m the inertia of the motor shaft, k_a the torque constant, r_a the armature resistance and r_e the gear ratio.

Let us consider the tracking problem; thus, the tracking error is defined as $\tilde{q} = q - q_d(t)$, where $q_d(t)$ is a reference signal to be tracked. Then, in order to control system (1) via the MGSTA a sliding variable is designed as

$$s = \Theta \tilde{q} + \dot{\tilde{q}},$$

where $\Theta \in \mathbb{R}^{3 \times 3}$ is a positive definite matrix to be designed. Suppose that only nominal values for M , k_a , r_a and r_e are available. Thus, the dynamics for s can be written as

$$\begin{aligned}
\dot{s} &= \Theta \dot{\tilde{q}} - \ddot{q}_d + \bar{M}(q)u + M^{-1}[-C(\dot{q})\dot{q} \\
&\quad - f_r(\dot{q}) + w(t, q, \dot{q})],
\end{aligned}$$

where $u = E\nu$ and $\bar{M}(q) = k_a r_e M^{-1} R^T(\theta)/r_a$. Taking into account that the friction forces f_v and f_c are unknown; then, they represent some additional uncertainties/perturbations on the system. Additionally, the matrix $\bar{M}(q)$ is uncertain in the sense that there exist some matrices $M_0(q)$ and $\Delta_M(q)$ such that $\bar{M}(q) = (I + \Delta_M(q))M_0(q)$, where $M_0(q)$ and $\Delta_M(q)$ represent a nominal known and an unknown part of the matrix $\bar{M}(q)$, respectively. Note that, when $\Delta_M(q) = 0$, the nominal case is recovered, and for $M_0(q) = I$ and $\Delta_M(q) = \bar{M}(q) - I$, the case with no available knowledge is considered. This representation becomes meaningful in contexts where the inertial parameters may vary, *e.g.*, when the robot changes mass due to the task, or in tasks where actuator faults may be present, to list only a few examples.

Thus, if the control law $u = u_{st}$ is considered, with u_{st} representing any MGSTA; then, the closed-loop system dynamics can be rewritten as

$$\begin{aligned}
\dot{s} &= \Theta \dot{\tilde{q}} - \ddot{q}_d + (I + \Delta_M(q))M_0(q)u_{st} \\
&\quad + M^{-1}[-C(\dot{q})\dot{q} - f_r(\dot{q}) + w(t, q, \dot{q})]. \quad (2)
\end{aligned}$$

Note that the term $\Delta_M(q)M_0(q)u_{st}$ cannot be canceled; thus, such a term needs to be considered as a part of the perturbation. This issue presents a challenge since the perturbation would depend directly on the control law and the gain selection cannot be made without assuming the boundedness of the trajectories of the closed-loop system *a priori*.

Furthermore, under the assumptions made in [23] and [25], which represent the most general conditions presented on the literature, the only way to deal with the dry friction model is to assume that it has a bounded time derivative, *i.e.*, that

$$\frac{d}{dt} f_d(\dot{q}) = \begin{bmatrix} f_{dx}(1 - \tanh^2(\dot{x}))\ddot{x} \\ f_{dy}(1 - \tanh^2(\dot{y}))\ddot{y} \\ f_{d\theta}(1 - \tanh^2(\dot{\theta}))\ddot{\theta} \end{bmatrix},$$

is bounded. However, note that this term depends linearly on the control signal. Therefore, to design the controller gains, the bounds of the accelerations need to be known *a priori*. It is important to remark that the works presented in [21], [23]–[25] do not consider this algebraic loop.

III. PROBLEM STATEMENT

Consider the following dynamical system

$$\dot{x} = f(t, x) + G(t, x)u, \quad (3)$$

where $x \in \mathbb{R}^n$ represents the state vector, $u \in \mathbb{R}^n$ is the control input, $f(t, x) \in \mathbb{R}^n$ is an uncertain vector field containing uncertainties and/or perturbations, and $G(t, x) \in \mathbb{R}^{n \times n}$ is the uncertain control (or input) matrix.

The uncertain input matrix $G(t, x)$ will be represented as

$$G(t, x) = (I + \Delta_G(t, x))G_0(t, x), \quad (4)$$

where $G_0 : \mathbb{R}_+ \times \mathbb{R}^n \rightarrow \mathbb{R}^{n \times n}$ corresponds to the nominal part, which is assumed to be invertible, and $\Delta_G : \mathbb{R}_+ \times \mathbb{R}^n \rightarrow \mathbb{R}^{n \times n}$ is the uncertain term.

In order to control (3), following [21] and [23], an MGSTA in the form

$$u = -k_1\phi_1(x) + bG_0^{-1}(t, x)v, \quad (5a)$$

$$\dot{v} = -k_2\phi_2(x), \quad (5b)$$

is proposed. The non-linear functions $\phi_i : \mathbb{R}^n \rightarrow \mathbb{R}^n$ are monotonically increasing, ϕ_1 is continuous everywhere and ϕ_2 is continuous everywhere except possibly at $x = 0$. We consider them as given by

$$\phi_1(x) = (\alpha \|x\|^{-p} + \beta)x, \quad (6)$$

$$\phi_2(x) = J(x)\phi_1(x) = c(x)\phi_1(x), \quad (7)$$

where $J(x)$ is the Jacobian matrix of $\phi_1(x)$ and $c(x)$ is a scalar function, which are defined in $\mathbb{R}^n \setminus \{0\}$, i.e.,

$$J(x) = \frac{\partial \phi_1(x)}{\partial x} = (\alpha \|x\|^{-p} + \beta)I - \alpha p \frac{\|x\|^{-p}}{\|x\|^2} xx^T, \quad (8)$$

$$c(x) = \alpha(1-p)\|x\|^{-p} + \beta. \quad (9)$$

The (positive) constant scalar gains $k_1, k_2 \in \mathbb{R}_+$ have to be designed, while the control coefficient gain $b > 0$, the internal positive gains $\alpha > 0, \beta > 0$ and the power $p \in (0, \frac{1}{2}]$ can be freely chosen by the designer. Note that the relation $\phi_2(x) = J(x)\phi_1(x)$ in (7) is an extension to the multivariable case of the scalar relation $\phi_2(x) = \phi_1'(x)\phi_1(x)$ (see [4] and [23] for further details).

Remark 1. The properties of matrix $\mathcal{J}(x) \triangleq \frac{1}{c(x)}J(x)$ are important. It is easily seen that it is symmetric since $J(x) = J^T(x)$. It is continuous in $\mathbb{R}^n \setminus \{0\}$, and in contrast to $J(x)$ it is bounded in \mathbb{R}^n , although its limit for $x = 0$ does not exist. Moreover, it has one eigenvalue at $\lambda = 1$, with eigenvector x . It has also $(n-1)$ repeated eigenvalues with value $1 \leq \lambda = \frac{\alpha + \beta \|x\|^p}{\alpha(1-p) + \beta \|x\|^p} < \frac{1}{1-p}$, with corresponding linearly independent eigenvectors in each of the $(n-1)$ different directions orthogonal to the vector x . Since \mathcal{J} is symmetric and all eigenvalues are positive and upper and lower bounded, it follows that $\mathcal{J}(x)$ is positive definite for all $x \in \mathbb{R}^n$, i.e.,

$$I \leq \mathcal{J}(x) \triangleq \frac{1}{c(x)}J(x) \leq \frac{\alpha + \beta \|x\|^p}{\alpha(1-p) + \beta \|x\|^p} I.$$

It is well-known [21], [23]–[25] that in the absence of input matrix uncertainty, i.e., $\Delta_G \equiv 0$, and for some bounds on the perturbation terms in $f(t, x)$ the origin of the closed-loop system (3)-(5) is finite-time stable by an appropriate selection of the gains k_1, k_2 . The objective of this paper is to find conditions on the uncertainty of the input matrix and on $f(t, x)$ such that the robust finite-time stability of the closed-loop system is assured.

For this, the uncertain term $f(t, x)$ is assumed to be decomposed as

$$f(t, x) = f_1(t, x) + f_2(t, x) = \Delta_1(t, x)\phi_1(x) + f_2(t, x), \quad (10)$$

where $f_2(t, x)$ is such that

$$\frac{d}{dt} \left[(I + \Delta_G)^{-1} f_2 \right] = \Delta_2(t, x)\phi_2(x) + \Delta_3(t, x)\dot{x}. \quad (11)$$

Moreover, introduce the following assumptions on the input matrix and the perturbations.

Assumption 1. For the dynamical system (3) and controller (6)-(7), the following conditions hold for all $t \geq 0$ and $x \in \mathbb{R}^n$:

1) There exist some positive constants $0 < g_m^\Delta \leq g_M^\Delta$ such that

$$g_m^\Delta I \leq G(t, x) + G^T(t, x) \leq g_M^\Delta I. \quad (12)$$

2) Matrices Δ_i , $i = 1, 2, 3$, in (10) and (11), are bounded, i.e., there exist $\delta_i \geq 0$ such that

$$\|\Delta_i(t, x)\| \leq \delta_i, \quad i = 1, 2, 3.$$

3) There exist some positive constants $0 < \gamma_1^\Delta \leq \gamma_2^\Delta$ such that

$$0 < \gamma_1^\Delta I \leq 2\text{Sym}\{\mathcal{J}(x)(I + \Delta_G)\} \leq \gamma_2^\Delta I. \quad (13)$$

For future reference, note that as a consequence of the previous assumptions there also exist non-negative constants $\gamma_3, \gamma_4, \gamma_5$ such that

$$\text{Gram}\{\mathcal{J}G\} \leq \gamma_3 I, \quad (14a)$$

$$2\text{Sym}\{\Delta_G \mathcal{J}G\} \leq \gamma_4 I, \quad (14b)$$

$$\text{Gram}\{\Delta_G^T\} \leq \gamma_5 I. \quad (14c)$$

Some comments on Assumption 1 are in order.

- Conditions 1) and 3) refer to the size of Δ_G . They require G_0 to have a positive definite symmetric part, and Δ_G to be sufficiently small not to destroy this property either for G nor for \mathcal{J} . These conditions are clearly weaker than those considered in the previous papers [21], [24], [25] and [23].
- Condition 2) implies that the term $f_1(t, x)$ contains vanishing perturbations, while $f_2(t, x)$ can have non-vanishing disturbances. Moreover, condition 2) considers that the derivative of the perturbation depends on \dot{x} and thus of the control signal. This term needs to be considered to properly manage the algebraic loop mentioned in the motivational example and in [20].
- Note that the depending on the class of perturbations, an appropriate value of p needs to be selected. If *e.g.*, the derivative of f_2 has terms not vanishing at zero, then $p = \frac{1}{2}$ will be suitable, as is considered in [21], [24] and [25]. Other values of p can be considered though.

IV. MAIN RESULT

In this section sufficient conditions for the stability of the closed-loop system (3)-(5) are derived. Moreover, a procedure to find gains k_1, k_2 assuring the stability is provided.

For convenience, we drop the arguments of the functions, when this does not lead to confusion. Defining the variable $z = v + b^{-1}(I + \Delta_G)^{-1}f_2$ the closed-loop system (3)-(5) can be written as

$$\dot{x} = f_1 + (I + \Delta_G)(-G_0 k_1 \phi_1 + bz), \quad (15)$$

$$\dot{z} = -k_2 \phi_2 + \Delta_2 \phi_2 + \Delta_3 \dot{x}. \quad (16)$$

The following theorem is the main result of the paper and ensures the global and robust finite-time stability of the closed-loop system (15)-(16).

Theorem 1. *Select $\alpha > 0$, $\beta > 0$, $b > 0$ and $p \in (0, \frac{1}{2}]$ and let Assumption 1 be satisfied. Assume further that the inequality*

$$\gamma_1^\Delta g_m^\Delta > \gamma_4 + 2\sqrt{\gamma_3 \gamma_5}, \quad (17)$$

is satisfied. Then, for arbitrary values of $\delta_1, \delta_2, \delta_3$, there exist positive constant controller gains k_1, k_2 such that $[x^T, z^T]^T = 0$ is globally robust finite-time stable.

The proof of the Theorem is given in the Appendix, using a (non-smooth) Lyapunov function. Note that the key condition (17) depends only on the size of the uncertainty of the control matrix Δ_G . If $\Delta_G \equiv 0$ then (17) is satisfied, since $\gamma_4 = \gamma_5 = 0$. So we come to the rather surprising conclusion that if the closed-loop can be stabilized for $f \equiv 0$ in presence of the uncertainty Δ_G , it can be stabilized for arbitrary large f satisfying Assumption 1.

Theorem 1 generalizes the results presented in [21], [24], [25] and [23] by considering the presence of an uncertain time- and state-dependent input matrix. Moreover, the algebraic loop caused by the presence of \dot{x} in the perturbation, and discussed in detail in [20], have been appropriately taken into account.

Note that after a finite time $z \equiv 0$, so that $v(t) \equiv -b^{-1}(I + \Delta_G(t, x))^{-1}f_2(t, x)$. This shows that the term v of the MGSTA (5) estimates exactly the (negative) value of the perturbation, and can therefore compensate for it.

To complete the paper, a procedure to select stabilizing gains k_1, k_2 will be given. Assumption 1 assures the existence of constants μ_1, \dots, μ_4 and $\theta_1, \dots, \theta_{12}$ such that the following bounds are satisfied:

$$2\text{Sym}\{\Delta_1\} \leq \mu_1 I, \quad (18a)$$

$$2\text{Sym}\{AG\} \leq \mu_2 I, \quad (18b)$$

$$2\text{Sym}\{A\Delta_1 + \Delta_2\} \leq \mu_3 I, \quad (18c)$$

$$2\text{Sym}\{A(I + \Delta_G)\} \leq \mu_4 I, \quad (18d)$$

with $A = \frac{\Delta_3}{c}$, and

$$\theta_1 I \geq 2\text{Sym}\{G^T \mathcal{J} A G\}, \quad (19a)$$

$$\theta_2 I \geq \text{Gram}\{AG\}, \quad (19b)$$

$$\theta_3 I \geq 2\text{Sym}\{[A(I + \Delta_G)b + \Delta_1^T \mathcal{J}] \mathcal{J} G\}, \quad (19c)$$

$$\theta_4 I \geq 2\text{Sym}\{(\Delta_2^T + \Delta_1^T A^T) \mathcal{J} G\}, \quad (19d)$$

$$\theta_5 I \geq 2\text{Sym}\{[A(I + \Delta_G)b + \Delta_1^T \mathcal{J}] A G\}, \quad (19e)$$

$$\theta_6 I \geq 2\text{Sym}\{\Delta_G A G\}, \quad (19f)$$

$$\theta_7 I \geq 2\text{Sym}\{(\Delta_2^T + \Delta_1^T A^T) A G\}, \quad (19g)$$

$$\theta_8 I \geq 2\text{Sym}\{\Delta_G [(I + \Delta_G^T) A^T b + \mathcal{J} \Delta_1]\}, \quad (19h)$$

$$\theta_9 I \geq 2\text{Sym}\{\Delta_G (\Delta_2 + A \Delta_1)\}, \quad (19i)$$

$$\theta_{10} I \geq 2\text{Sym}\{(\Delta_2^T + \Delta_1^T A^T) [(I + \Delta_G^T) A^T b + \mathcal{J} \Delta_1]\}, \quad (19j)$$

$$\theta_{11} I \geq \text{Gram}\{\Delta_2 + A \Delta_1\}, \quad (19k)$$

$$\theta_{12} I \geq \text{Gram}\{(I + \Delta_G^T) A^T b + \mathcal{J} \Delta_1\}. \quad (19l)$$

For positive $p_1 > 0$ and $p_2 > 0$, define the functions

$$\Xi_1(p_1, p_2) = \theta_8 + \theta_9 p_2 + \theta_{10} \frac{p_2}{b p_1} + \theta_{11} \frac{p_2^2}{b p_1} + \theta_{12} \frac{1}{b p_1},$$

$$\Xi_2(p_2) = \frac{1}{b} (\theta_3 + (\theta_4 + \theta_5) p_2 + \theta_7 p_2^2),$$

$$\Xi_3(p_2) = \frac{1}{b} (\gamma_3 + \theta_1 p_2 + \theta_2 p_2^2),$$

$$\Gamma_0(p_1, p_2) = \left(\Xi_2 + \left(\gamma_1^\Delta - p_2 \mu_4 \right) \mu_2 \right) \frac{1}{p_1} + \left(\theta_6 + \mu_4 g_m^\Delta \right) p_2,$$

$$\Gamma_1(p_1, p_2) = \left(\Gamma_0 + \gamma_4 - \gamma_1^\Delta g_m^\Delta \right)^2 - 4b \Xi_3 \gamma_5,$$

$$\Gamma_2(p_1, p_2) = 4\Xi_3 \left\{ \left(\frac{2b}{p_2} + \mu_1 + \frac{\mu_3}{p_1} \right) \left(\gamma_1^\Delta - p_2 \mu_4 \right) + \Xi_1 \right\},$$

and also

$$\alpha_2 = \frac{1}{\tilde{\gamma}_1^\Delta} \Xi_3(p_2), \quad (20a)$$

$$\alpha_1 = \frac{1}{\tilde{\gamma}_1^\Delta} (\Xi_2 + \gamma_4 p_1 + \theta_6 p_1 p_2) + \mu_2 - g_m^\Delta p_1, \quad (20b)$$

$$\alpha_0 = 2b \frac{p_1}{p_2} + \mu_1 p_1 + \mu_3 + \frac{1}{b \tilde{\gamma}_1^\Delta} (\gamma_5 b p_1 + \Xi_1) b p_1, \quad (20c)$$

with $\tilde{\gamma}_1^\Delta = \gamma_1^\Delta - p_2 \mu_4$. The design of the gains follows the following algorithm, which is derived from the proof of Theorem 1 in Appendix.

Algorithm 1. In order to ensure a proper selection of the gains k_1 and k_2 in (5), consider the following steps:

- 1) Select $\alpha > 0$, $\beta > 0$, $b > 0$ and $p \in (0, \frac{1}{2}]$. The parameter p should be selected depending on the size of the perturbations.
- 2) Find a value of $p_2 = p_2^*$ and a value of $p_1 = p_1^*$ such that

$$\gamma_1^\Delta > p_2 \mu_4, \quad (21)$$

and

$$\gamma_1^\Delta g_m^\Delta - \gamma_4 - \Gamma_0(p_1, p_2) > 0, \quad (22)$$

are satisfied for $p_2 = p_2^*$ and $p_1 \geq p_1^*$. These values always exist.

3) Find a value $p_1^\#$ of p_1 such that $p_1^\# \geq p_1^*$ and that the following inequality

$$\Gamma_1(p_1, p_2) p_1 > \Gamma_2(p_1, p_2), \quad (23)$$

is satisfied for every $p_1 \geq p_1^\#$. This is also always feasible.

4) Fix $p_2 = p_2^*$, $p_1 \geq p_1^\#$ and $p_1 p_2 > 1$, choose

$$k_2 = b \frac{p_1}{p_2}, \quad (24)$$

and

$$k_1 \in \left(\frac{-\alpha_1 - \bar{\alpha}}{2\alpha_2}, \frac{-\alpha_1 + \bar{\alpha}}{2\alpha_2} \right), \quad (25)$$

with $\bar{\alpha} = \sqrt{\alpha_1^2 - 4\alpha_2\alpha_0}$.

V. EXAMPLES

A. An Academic Example

Consider a simple situation with $n = 2$ and in (4)

$$G_0 = I_2, \Delta_G = \begin{bmatrix} 0 & g(t) \\ g(t) & 0 \end{bmatrix},$$

with $g(t)$ an arbitrary time-varying signal with $|g(t)| \leq \bar{g}$, that represents the coupling between the two control channels. We calculate the value of \bar{g} such that the key condition (17) is satisfied, *i.e.*, there exist stabilizing gains. Unfortunately, even in this simple case, it seems to be impossible to obtain an analytical expression for the condition, due to the discontinuous nature of \mathcal{J} . However, a good approximation can be computed numerically. For $\alpha = \beta = 1$, $p = 1/2$, $g_m^\Delta = 2(1 - \bar{g})$, $\gamma_5 = \bar{g}^2$, and for $\bar{g} = 0.23$ condition (17) is still fulfilled. This is possibly a conservative estimation of the true value, and so are also the gains calculated by the Algorithm 1.

B. The Motivation Example

For the four-wheeled omnidirectional mobile robot closed-loop dynamics (2), the representation in (3) is given as follows:

$$\begin{aligned} f(t, s) &= \Theta \dot{\tilde{q}} - \ddot{q}_d + M^{-1}[-C(\dot{q})\dot{q} - f_r(\dot{q}) + w(t, q, \dot{q})], \\ G(t, s) &= (I + \Delta_M(q))M_0(q). \end{aligned}$$

Recalling that $s = \Theta \tilde{q} + \dot{\tilde{q}}$, that the friction forces f_v and f_d are unknown, and that the matrix $\bar{M}(q)$ is uncertain, it follows that

$$\begin{aligned} f_1(t, s) &= M^{-1}[M\Theta - C(\dot{q}) - \bar{f}_v]s + w_1(t, s), \\ f_2(t, s) &= M^{-1}[C(\dot{q})\Theta + \bar{f}_v - M\Theta^2]\tilde{q} - \ddot{q}_d \\ &\quad - M^{-1}[C(\dot{q}) + \bar{f}_v]\dot{q}_d - M^{-1}f_d(\dot{q}) + w_2(t, s), \\ \Delta_M(q) &= [\bar{M}(q) - M_0(q)]M_0^{-1}(q), \\ M_0(q) &= \frac{k_{an}r_{en}}{r_{an}}M_n^{-1}R^T(\theta), \quad \bar{M}(q) = \frac{k_a r_e}{r_a}M^{-1}R^T(\theta), \end{aligned}$$

where $\bar{f}_v = \text{diag}\{f_{vx}, f_{vy}, f_{v\theta}\}$ is a viscous friction matrix; M_n , k_{an} , r_{an} and r_{en} are nominal values for M , k_a , r_a and r_e , respectively; and the external disturbances w_1 and w_2 are such that $w(t, s) = w_1(t, s) + w_2(t, s)$.

Therefore, one can verify that, for all $\theta \in (-\pi/2, \pi/2)$, condition 1) of Assumption 1 holds for some $g_m^\Delta, g_M^\Delta > 0$. Additionally, f_1 satisfies

$$\begin{aligned} f_1(t, s) &= \Delta_1(t, s)(\alpha \|s\|^{-p} s + \beta s), \\ \Delta_1(t, s) &= M^{-1}[M\Theta - C(\dot{q}) - \bar{f}_v], \\ w_1(t, s) &= \alpha \Delta_1(t, s) \|s\|^{-p} s, \end{aligned}$$

with $\alpha > 0$ and $\beta = 1$. Then, due to the properties of the omnidirectional mobile robot, one could assume that $\|f_1(t, s)\| \leq \delta_1 \|\phi_1(s)\|$, for some $\delta_1 > 0$.

Table I
SYSTEM PARAMETERS

| Parameter | Value | Parameter | Value |
|-----------|----------------------------------|-----------|---------------------------------|
| m_1 | 2.8[kg] | r | 0.042[m] |
| m_2 | 0.38[kg] | J_m | $5.7e^{-7}$ [kgm ²] |
| J_1 | 0.0608[kgm ²] | k_a | 0.013[Nm/A] |
| J_2 | $3.24e^{-4}$ [kgm ²] | r_a | 1.9[Ω] |
| J_3 | $4.69e^{-4}$ [kgm ²] | r_e | 58 |
| L | 0.1100[m] | f_v | $1e^{-4}I$ |
| l_1 | 0.1524[m] | f_d | $1e^{-4}I$ |
| l_2 | 0.1505[m] | - | - |

On the other hand, assuming that $\dot{q}_d(t) = cte.$, and $M_n = \lambda_M I$ with some $\lambda_M > 0$; after some calculations, $\bar{f}_2(t, s) = (I + \Delta_M(q))^{-1} f_2(t, s)$ satisfies

$$\begin{aligned} \frac{d}{dt} \bar{f}_2(t, s) &= \Delta_2(t, s) [\alpha^2 (1-p) \|s\|^{-2p} s \\ &\quad + \alpha \beta (2-p) \|s\|^{-p} s + \beta^2 s] + \Delta_3(t, s) \dot{s}, \\ \Delta_2(t, s) &= (I + \Delta_M(q))^{-1} M^{-1} [C(\dot{q}) \Theta + \bar{f}_v - M \Theta^2], \\ \Delta_3(t, s) &= (I + \Delta_M(q))^{-1} M^{-1} \left[\frac{4}{r^2} (J_2 + J_m r_e^2) B \times \right. \\ &\quad \left. (1 - \tanh^2(\dot{\theta})) (\Theta \tilde{q} - \dot{q}_d) \bar{\mathbf{I}} - \bar{f}_d (I - \tanh^2(\dot{q})) \right], \\ \frac{d}{dt} w_2(t, s) &= \alpha \Delta_2(t, s) [\alpha (1-p) \|s\|^{-2p} + \beta (2-p) \|s\|^{-p}] s, \end{aligned}$$

with $\bar{\mathbf{I}} = [0, 0, 1]$, $\bar{f}_d = \text{diag}\{f_{dx}, f_{dy}, f_{d\theta}\}$ is a dry friction matrix; $\alpha > 0$ and $\beta = 1$. Thus, due to the properties of the omnidirectional mobile robot, one could assume that $\|d\bar{f}_2(t, s)/dt\| \leq \delta_2 \|\phi_2(s)\| + \delta_3 \|\dot{s}\|$, for some $\delta_2, \delta_3 > 0$. Hence, condition 2) of Assumption 1 is satisfied.

Finally, due to the fact that $\mathcal{J}(s)$ is positive definite and $\theta \in (-\pi/2, \pi/2)$, condition 3) of Assumption 1 holds for some $\gamma_1^\Delta, \gamma_2^\Delta > 0$.

In order to illustrate the performance of the MGSTA (5), some simulations are carried out in Matlab with Euler explicit discretization method and sampling time equal to 1×10^{-3} . The parameters of the mobile robot are given in Table I. The units for f_{vx} , f_{vy} and $f_{v\theta}$ are [kg/s], [kg/s] and [kgm²/s], respectively; while for f_{dx} , f_{dy} and $f_{d\theta}$ are [kgm/s²], [kgm/s²] and [kgrad/s²], respectively. The nominal values for M , k_a , r_a and r_e are taken as $M_n = 7.7341I$, $k_{an} = 0.0130$, $r_{an} = 1.9$ and $r_{en} = 57$.

Using some numerical calculations, it is possible to obtain that $g_m^\Delta = 0.0714$, $g_M^\Delta = 5.2696$, $\delta_1 = 2$, $\delta_2 = 4.0080$, $\delta_3 = 1.3434$, $\gamma_1^\Delta = 1.9957$, $\gamma_2^\Delta = 3.2688$, $\gamma_3 = 18.4838$, $\gamma_4 = 2.5907e^{-4}$ and $\gamma_5 = 4.6706e^{-6}$. Therefore, it is easy to verify that condition (17), in Theorem 1, is satisfied; and thus, there exist positive gains k_1 and k_2 such that $[s^T, z^T]^T = 0$ is globally robust finite-time stable.

It is worth mentioning that one could compute the controller gains following Algorithm 1. However, due to the fact that such an Algorithm is based on conservative estimations given in (18) and (19), it is natural that the obtained gains are also conservative, as in this particular example, where very large values are computed.

For these simulation results, the controller gains are chosen as $k_1 = 42$ and $k_2 = 13$, while $\alpha = 1$, $\beta = 1$, $b = 3$ $p = 0.4$ and $\Theta = 2I$, ensuring finite-time convergence for s . The desired trajectory has been chosen as $q_d(t) = [0.5t, 0.5t, \pi/4]^T$. The obtained results are illustrated by Figs. 1, 2 and 3.

Fig. 1 shows the behavior of the sliding variables. Note that such variables vanish in a finite time, which illustrates the main result given in Theorem 1.

Fig. 2 depicts the configuration variables of the omnidirectional mobile robot. It can be seen that the mobile robot exponentially tracks the desired reference even when there exists state-dependent uncertainty in the input matrix and unknown friction forces. This results highlight the effectiveness of the proposed approach.

Finally, Fig. 3 shows the of the control inputs. Note that in this case such inputs are given by the armature voltages, which are directly applied to each wheel motor through the relation $\nu = E^+ u$, with E^+ the right pseudo-inverse of E and u the current control signals designed based on the MGSTA. Note that the control signals do not seem to be excessive for a real omnidirectional mobile robot. Moreover, it is worth saying that, under ideal conditions, the MGSTA provides an excellent solution to the chattering problem, if no actuator dynamics is considered.




Figure 1. Sliding Variables




Figure 2. Configuration Variables

VI. CONCLUSIONS

This paper presents a Lyapunov approach to the design of the MGSTA to control systems with perturbations and an uncertain input matrix, both depending on time and system states. The proposed procedure provides sufficient conditions for the MGSTA gains selection ensuring global finite-time stability of the system's outputs. The simulation results illustrate the effectiveness of the proposed version of the MGSTA for a four-wheeled omnidirectional mobile robot even when the conditions of [21], [24] and [25] cannot be satisfied.

Future research can be devoted to obtain less conservative estimations for the uncertainties of the system and provide better algorithms for the controller gains design.




Figure 3. Armature Voltages

APPENDIX
PROOF OF THE MAIN RESULT

In this section, following usual ideas for the Super-Twisting [3], [4], [21], [23]–[25] and [28], a quadratic non-smooth Lyapunov function is used to prove the main result Theorem 1, from which Algorithm 1 is derived.

Lyapunov Function Candidate and its Derivative: Consider the closed-loop system given by (15) and (16). The Lyapunov function candidate is the quadratic form

$$V(\zeta) = \frac{1}{2}\zeta^T P \zeta = \frac{1}{2}\zeta^T \begin{bmatrix} p_1 I & -I \\ -I & p_2 I \end{bmatrix} \zeta, \quad (26)$$

in the variable $\zeta = [\zeta_1^T, \zeta_2^T]^T = [\xi^T, z^T]^T$, where $\xi = \phi_1(x)$ and $z = v + b^{-1}(I + \Delta_G)^{-1} f_2$. If the positive constants $p_1, p_2 > 0$ are such that $p_1 p_2 > 1$, then the function $V(\zeta)$ is positive definite, radially unbounded and differentiable almost everywhere, *i.e.*, it is not differentiable whenever $\xi = x = 0$.

To calculate its derivative, we require $\dot{\zeta}$. From the definition of $J(x)$ in (8) it follows that $\dot{\xi} = J(x)\dot{x}$. Using the shorthand notations

$$\tilde{K}_1 = k_1 I - G^{-1} \Delta_1, \quad \tilde{K}_2 = k_2 I - \Delta_2, \quad A = \frac{\Delta_1}{c},$$

it follows that $\dot{\zeta}$ is given almost everywhere by

$$\dot{\zeta} = S(t, x) \zeta, \quad (27)$$

with the square matrix $S(t, x)$ given as

$$S(t, x) = \begin{bmatrix} -JG\tilde{K}_1 & J(I + \Delta_G)b \\ -c\tilde{K}_2 - \Delta_1 G\tilde{K}_1 & \Delta_1(I + \Delta_G)b \end{bmatrix}.$$

The derivative of the Lyapunov function along the trajectories of (15)–(16), and using the relation $J\zeta_1 = c\zeta_1$ given in (7), can be written as

$$\dot{V} = -c\zeta^T Q \zeta = -c \begin{bmatrix} Q_{11} & Q_{12} \\ Q_{12}^T & Q_{22} \end{bmatrix} \zeta,$$

where

$$Q_{11} = \text{Sym} \left\{ p_1 G \tilde{K}_1 - \left(\tilde{K}_2 + A G \tilde{K}_1 \right) \right\}, \quad (28a)$$

$$Q_{21} = -JG\tilde{K}_1 + p_2 \left(\tilde{K}_2 + A G \tilde{K}_1 \right) + b \left(I + \Delta_G^T \right) \left(A^T - p_1 I \right), \quad (28b)$$

$$Q_{22} = b \text{Sym} \left\{ J \left(I + \Delta_G \right) - p_2 A \left(I + \Delta_G \right) \right\}. \quad (28c)$$

Positive Definiteness of Q: The negative definiteness of \dot{V} and the global finite-time stability of the origin $x = 0, z = 0$ follows from usual arguments for the Super-Twisting (see, *e.g.*, [23] and [28]) if the bounded matrix $Q(t, x)$ is positive definite for all values of (t, x) . For Q to be positive definite it is necessary that Q_{22} is also positive definite. Using (18) and assuming that $p_2 > 0$ is chosen sufficiently small so that (21) is satisfied, it is readily obtained that

$$0 < b\tilde{\gamma}_1^\Delta I \leq Q_{22}, \quad (29)$$

where $\tilde{\gamma}_1^\Delta = \gamma_1^\Delta - p_2 \mu_4$, showing that Q_{22} is positive definite. Moreover, Q is positive definite if so is the Schur Complement, *i.e.*,

$$Q_{11} > Q_{21}^T Q_{22}^{-1} Q_{21}. \quad (30)$$

Note that

$$Q_{11} = \text{Sym} \left\{ k_1 p_1 G - k_2 I - p_1 \Delta_1 - k_1 A G + \Delta_2 + A \Delta_1 \right\},$$

so that the use of (12) and (18) in (28a) leads to

$$Q_{11} > g_m^\Delta p_1 k_1 I - 2k_2 I - (p_1 \mu_1 + k_1 \mu_2 + \mu_3) I. \quad (31)$$

From (29) it easily follows that $Q_{21}^T Q_{22}^{-1} Q_{21} \leq \frac{1}{b\gamma_1^{\Delta}} Q_{21}^T Q_{21}$. Then, selecting k_2 as in (24), in order to cancel some known terms in Q_{21} , from its expression in (28b) and with the help of (19), after a simple but lengthy calculation, the following inequality is attained

$$\begin{aligned} Q_{21}^T Q_{22}^{-1} Q_{21} \leq & \frac{1}{b\gamma_1^{\Delta}} (\gamma_3 k_1^2 + \theta_1 p_2 k_1^2 + \theta_2 p_2^2 k_1^2 + \theta_3 k_1 \\ & + \gamma_4 b p_1 k_1 + \theta_4 p_2 k_1 + \theta_5 p_2 k_1 + \theta_6 b p_1 p_2 k_1 \\ & \theta_7 p_2^2 k_1 + \gamma_5 b^2 p_1^2 + \theta_8 b p_1 + \theta_9 b p_1 p_2 \\ & + \theta_{10} p_2 + \theta_{11} p_2^2 + \theta_{12}) I. \end{aligned} \quad (32)$$

Using (31) and (32) in (30), and rearranging the terms as a polynomial in k_1 , it is concluded that the inequality

$$\alpha_2 k_1^2 + \alpha_1 k_1 + \alpha_0 < 0, \quad (33)$$

where α_i , with $i = 0, 1, 2$, are defined in (20), implies the positive definiteness of Q . The existence of positive values of the gain k_1 such that inequality (33) is fulfilled requires the polynomial to have two positive real roots (since $\alpha_0 > 0$), *i.e.*, $\alpha_1^2 - 4\alpha_2\alpha_0 > 0$ and $\alpha_1 < 0$. These two inequalities are equivalent to (22) and (23). To conclude the proof, we need to show that the main condition (17) implies (21)-(23), which are the inequalities used up to this point. In order to show that, fix $b > 0$ and note that (22) is $\gamma_1^{\Delta} g_m^{\Delta} - \gamma_4 - \Gamma_0(p_1, p_2) > 0$, with Γ_0 a continuous function, and $\lim_{p_1 \rightarrow 0} \{\lim_{p_2 \rightarrow \infty} \Gamma_0(p_1, p_2)\} = 0$. As a consequence, (17) implies that (22) is satisfied for values of (p_1, p_2) with p_1 large and p_2 small. Note that p_2 sufficiently small also implies (21).

A similar reasoning shows that $\Gamma_1(p_1, p_2)$, the coefficient of p_1 in (23), is positive for large values of p_1 and small values of p_2 . Fixing the value of p_2 , it is easy to see that $\Gamma_1(p_1, p_2) p_1$ in (23) grows unboundedly and strictly monotonically with p_1 (for p_1 sufficiently large), while $\Gamma_2(p_1, p_2)$ is bounded. This implies that, for all sufficiently large values of p_1 , (23) will be satisfied. Moreover, p_1 can be selected sufficiently large so that $p_1 p_2 > 1$, and thus $V > 0$. Therefore, there exist appropriate values of k_1 to render $Q > 0$, *i.e.*, $\dot{V} < 0$, so that the system is asymptotically stable. Due to the dominance of the negative homogeneity degree, finite-time convergence is obtained. This concludes the proof.

REFERENCES

- [1] A. Levant, "Sliding order and sliding accuracy in sliding mode control," *International Journal of Control*, vol. 58, no. 6, pp. 1247–1263, 1993.
- [2] A. Levant, "Robust exact differentiation via sliding mode technique," *Automatica*, vol. 34, no. 3, pp. 379 – 384, 1998.
- [3] J. A. Moreno and M. Osorio, "A Lyapunov approach to second-order sliding mode controllers and observers," in *The 47th IEEE Conference on Decision and Control*, pp. 2856–2861, Dec 2008.
- [4] J. A. Moreno, *Sliding Modes after the First Decade of the 21st Century*, ch. Lyapunov Approach for Analysis and Design of Second Order Sliding Mode Algorithms. Springer-Verlag, 2011.
- [5] R. Seeber and M. Horn, "Necessary and sufficient stability criterion for the super-twisting algorithm," in *2018 15th International Workshop on Variable Structure Systems (VSS)*, pp. 120–125, 2018.
- [6] R. Seeber and M. Horn, "Stability proof for a well-established super-twisting parameter setting," *Automatica*, vol. 84, pp. 241 – 243, 2017.
- [7] R. Seeber, M. Horn, and L. Fridman, "A novel method to estimate the reaching time of the super-twisting algorithm," *IEEE Transactions on Automatic Control*, vol. 63, pp. 4301–4308, Dec 2018.
- [8] R. Seeber, "Computing and estimating the reaching time of the super-twisting algorithm," in *Variable Structure Systems and Sliding-Mode Control*, Springer, 2020.
- [9] A. K. Behera, A. Chalanga, and B. Bandyopadhyay, "A new geometric proof of super-twisting control with actuator saturation," *Automatica*, vol. 87, pp. 437 – 441, 2018.
- [10] R. Seeber and M. Reichhartinger, "Conditioned super-twisting algorithm for systems with saturated control action," *Automatica*, vol. 116, p. 108921, 2020.
- [11] I. Castillo, M. Steinberger, L. Fridman, J. Moreno, and M. Horn, "Saturated super-twisting algorithm based on perturbation estimator," in *The 55th IEEE Conference on Decision and Control*, (Las Vegas, USA), pp. 7325–7328, 2016.
- [12] M. A. Golkani, S. Koch, M. Reichhartinger, and M. Horn, "A novel saturated super-twisting algorithm," *Systems & Control Letters*, vol. 119, pp. 52 – 56, 2018.
- [13] H. Haimovich and H. De Battista, "Disturbance-tailored super-twisting algorithms: Properties and design framework," *Automatica*, vol. 101, pp. 318 – 329, 2019.
- [14] U. Pérez-Ventura and L. Fridman, "Design of super-twisting control gains: A describing function based methodology," *Automatica*, vol. 99, pp. 175 – 180, 2019.
- [15] C. Evangelista, P. Puleston, F. Valenciaga, and L. Fridman, "Lyapunov-designed super-twisting sliding mode control for wind energy conversion optimization," *IEEE Transactions on Industrial Electronics*, vol. 60, pp. 538–545, Feb 2013.
- [16] F. Plestan, X. Yan, M. Taleb, and A. Estrada, "Adaptive solutions for robust control of electropneumatic actuators," in *Recent Trends in Sliding Mode Control*, Herts: The Institution of Engineering and Technology, 2016.
- [17] C. Kunusch, P. F. Puleston, M. A. Mayosky, and L. Fridman, "Experimental results applying second order sliding mode control to a pem fuel cell based system," *Control Engineering Practice*, vol. 21, no. 5, pp. 719–726, 2013.
- [18] D. Efimov, G. Perozzi, J.-M. Biannic, and L. Planckaert, "Trajectory tracking for a quadrotor under wind perturbations: sliding mode control with state-dependent gains," *Journal of the Franklin Institute*, vol. 355, no. 12, pp. 4809 – 4838, 2018.
- [19] M. You, Q. Zong, L. Zuo, X. Wang, and X. Zhao, "Multivariable supertwisting fixed-time approach for rlv re-entry attitude control," *International Journal of Robust and Nonlinear Control*, vol. 29, no. 4, pp. 973–989, 2019.

- [20] I. Castillo, L. Fridman, and J. A. Moreno, "Super-twisting algorithm in presence of time and state dependent perturbations," *International Journal of Control*, vol. 91, no. 11, pp. 2535–2548, 2018.
- [21] I. Nagesh and C. Edwards, "A multivariable super-twisting sliding mode approach," *Automatica*, vol. 50, no. 3, pp. 984 – 988, 2014.
- [22] F. López-Caamal and J. A. Moreno, "Qualitative differences of two classes of multivariable super-twisting algorithms," in *54th IEEE Conference on Decision and Control*, pp. 5414–5419, Dec 2015.
- [23] F. López-Caamal and J. A. Moreno, "Generalised multivariable supertwisting algorithm," *International Journal of Robust and Nonlinear Control*, vol. 29, no. 3, pp. 634–660, 2019.
- [24] P. V. N. M. Vidal, E. V. L. Nunes, and L. Hsu, "Multivariable super-twisting algorithm for a class of systems with uncertain input matrix," in *2016 American Control Conference (ACC)*, pp. 7201–7206, July 2016.
- [25] P. V. N. M. Vidal, E. V. L. Nunes, and L. Hsu, "Output-feedback multivariable global variable gain super-twisting algorithm," *IEEE Transactions on Automatic Control*, vol. 62, pp. 2999–3005, June 2017.
- [26] G. Campion, G. Bastin, and B. D'Andrea-Novet, "Structural properties and classification of kinematic and dynamic models of wheeled mobile robots," *IEEE Transactions on Robotics and Automation*, vol. 12, no. 1, pp. 47–62, 1996.
- [27] R. Kelly, V. Santibáñez, and J. A. Loría, *Control of robot manipulators in joint space*. Springer Science & Business Media, 2006.
- [28] J. A. Moreno and M. Osorio, "Strict Lyapunov functions for the Super-Twisting algorithm," *IEEE Transactions on Automatic Control*, vol. 57, no. 4, pp. 1035–1040, 2012.