

Invariant and Dual Invariant Subspaces of k -valued Networks[★]

Daizhan Cheng^{a,b}, Hongsheng Qi^a, Xiao Zhang^{a,c}, Zhengping Ji^a

^aKey Laboratory of Systems and Control, Academy of Mathematics and Systems Science, Chinese Academy of Sciences

^bResearch Center of Semi-tensor Product of Matrices: Theory and Applications, Liaocheng 252026, P.R. China

^cNational Center for Mathematics and Interdisciplinary Sciences, Academy of Mathematics and Systems Science, Chinese Academy of Sciences

Abstract

Consider a k -valued network. Two kinds of (control) invariant subspaces, called state and dual invariant subspaces, are proposed, which are subspaces of state space and dual space respectively. Algorithms are presented to verify whether a dual subspace is a dual or dual control invariant subspace. The bearing space of k -valued (control) networks is introduced. Using the structure of bearing space, the universal invariant subspace is introduced, which is independent of the dynamics of particular networks. Finally, the relationship between state invariant subspace and dual invariant subspace of a network is investigated. A duality property shows that if a dual subspace is invariant then its perpendicular state subspace is also invariant and vice versa.

Key words: k -valued (control) network; state (or dual) invariant subspace; bearing space; finite ring; finite lattice.

1 Introduction

Since the state-space approach proposed by Kalman in 1960 [26], the (control) invariant subspace became one of the most important concepts in modern control theory. Consider a linear control system

$$\dot{x} = Ax + Bu, \quad x \in \mathbb{R}^n, u \in \mathbb{R}^m. \quad (1)$$

A subspace $V \subset \mathbb{R}^n$ is called an (A, B) -invariant (or control-invariant) subspace, if $AV \subset V + \mathcal{B}$, where \mathcal{B} is a subspace spanned by $\text{Col}(B)$ [42]. It is clear that this concept is a generalization of A invariant subspace from linear algebra when there is no control. That is, a subspace V is A -invariant if $AV \subset V$.

This concept has then been extended to non-linear control systems. Consider an affine non-linear control sys-

tem

$$\dot{x} = f(x) + \sum_{i=1}^m g_i(x)u_i, \quad x \in M, u \in \mathbb{R}^m, \quad (2)$$

where M is an n -dimensional manifold. Then a distribution \mathcal{D} is called an (f, g) -invariant distribution, if $L_f \mathcal{D} \subset \mathcal{D} + \mathcal{G}$, where $L_f \mathcal{D} = \{L_f(X) \mid X \in \mathcal{D}\}$ is the set of Lie derivatives of X with respect to f , \mathcal{G} is the distribution generated by $\{g_i \mid i = 1, \dots, m\}$ [23]. It is also clear that without control, \mathcal{D} becomes f -invariant.

It is well known that V is the control-invariant subspace of (1), if and only if, there exists a state-feedback control $U = Fx$, such that V is $A + BF$ invariant [42]. Similar result is also true for (2) [23]. Roughly speaking, a control-invariant subspace is an invariant subspace for a controlled (or closed-loop) system. Hence, the invariant subspace and control-invariant subspace are essentially the same and can be discussed simultaneously.

In general, the invariant subspace plays a fundamental role in system analysis and control design. In most cases, an invariant subspace is established to represent specific properties of a dynamic system. Hence, it is used for solving various control problems, such as decomposition and disturbance decoupling problems; stability and stabilization problems; output tracking problems, etc.

[★] This work is supported partly by the National Natural Science Foundation of China (NSFC) under Grants 62073315 and 61733018, and the China Postdoctoral Science Foundation 2021M703423 and 2022T150686.

Email addresses: dcheng@iss.ac.cn (Daizhan Cheng), qihongsh@amss.ac.cn (Hongsheng Qi), xiaozhang@amss.ac.cn (Xiao Zhang), zpji@amss.ac.cn (Zhengping Ji).

The Boolean network (BN) was firstly proposed by Kauffman to formulate and analyze the genetic regulation networks [27]. Many biological systems have exogenous inputs. To deal with them or to manipulate BNs, the Boolean control networks (BCNs) have then been investigated [22,13]. In the light of the semi-tensor product (STP) of matrices, the BNs and BCNs have been formulated into the framework of the linear and bi-linear state space model, called the algebraic state space representation (ASSR) [6,8]. The last decade or more has witnessed unprecedented progress in the investigation of BNs and BCNs, stimulated by STP.

When the state space approach was introduced to formulate BNs and BCNs, the (control) invariant subspace becomes a useful tool for analyzing the structure and properties of BNs and the control design of BCNs. Under the regularity assumption, the invariant subspace has been introduced to BNs to solve the disturbance decoupling problem [7]. Then a new concept about invariant subspace, which removed the assumption of regularity has been proposed and used to solve decomposition problem [46] and disturbance decoupling problem [45]. State feedback invariant subspace has also been proposed and used for designing controls for BCNs [18,33].

A recent work [11] investigates the realization of BNs using their invariant subspace. It reveals that for a BN with n nodes, since the state variables $X_i(t) \in \mathcal{D} := \{0, 1\}$, $i \in [1, n]$, the state space should be $\mathcal{X} = \mathcal{D}^n$. The set of logical functions, denoted by $\mathcal{X}^* := \mathcal{F}_\ell(X_1, X_2, \dots, X_n)$, is then called the dual space of \mathcal{X} . It follows that $|\mathcal{X}^*| = 2^{2^n}$, hence the dual space is much larger than the original state space.

Based on this observation, it is easy to find that all the (control) invariant subspaces considered in the literature (precisely speaking, in previously mentioned papers) are subspaces of dual spaces. Hereafter, they should be correctly called the dual (control) invariant subspaces.

A Boolean network approach is the approximation of the active levels of nodes (cells) by quantizing them to $\{0, 1\}$. To improve the accuracy of approximation, k -valued network is a natural solution [1,2,25]. Using the STP, the ASSR approach for BNs can easily be extended to multi-valued networks [28].

The multi-valued network approach is not only useful for biological networks but also very useful for other finite-valued problems such as finite games [17,9]. To see more applications of the multi-valued ASSR approach to finite (networked) games, you are referred to the survey paper [10]. In fact, the multi-valued ASSR approach can be used for many other finite-value-based problems, such as intelligent problems [43], circuit design [4], etc. Hence, it is worth paying more attention to k -valued networks.

When a dynamic system is considered, the state vari-

ables take values from a preassigned set. We call it the bearing space. For instance, when linear control system (1) or nonlinear control system (2) are considered, the bearing space is \mathbb{R} . When a BN is considered, the bearing space is the Boolean set $\mathcal{D} := \{0, 1\}$.

The structures and properties of the bearing space do affect the properties of a dynamic system over the space. For BNs, Boolean algebra has been developed to describe the bearing space of BNs [39]. Similarly, a k -valued algebra, proposed firstly by Post and then named by Post algebra, has been developed to describe the bearing space of k -valued networks [36,14,37,38,41].

Post lattice (or Post algebra) is not the only structure for bearing space of k -valued networks. Recently, when the multi-valued networks are deeply investigated, people started to pay more attention to the structure of bearing spaces of the networks, and various bearing spaces are proposed. For instance, the networks over finite fields have been studied by several authors [40,35,29,30,31,34]. It follows that the networks over finite rings and networks over finite lattices have also been investigated [11,24].

Exploring some bearing spaces of k -valued networks, we found some state invariant subspaces appear naturally and these state invariant subspaces play a fundamental role in both structure analysis and control design for k -valued networks. This is the motivation for us to investigate both dual and state (control) invariant subspaces of k -valued (control) networks.

The main work and contribution of this paper consist of the following:

- (i) Though the concept of (control) invariant subspaces has been used for a considerable long time, they have been classified clearly into two kinds of invariant subspaces for the first time, which clarified some confusing points in the past use.
- (ii) An algorithm is presented to verify whether a dual subspace of a k -valued network is a dual control-invariant subspace. If the answer is “yes”, the algorithm can also produce the state-feedback controls to make the subspace a dual invariant subspace for the closed-loop network. The algorithm can also be used for BCNs. To our best knowledge, there was no known algorithm for BCNs.
- (iii) By investigating bearing space and its bearing subspace, the concept of universal state invariant subspace is proposed. Correspondingly, a universal cascading normal form is obtained. Here “universal” means that the invariant subspace and the normal form are independent of the dynamics of individual networks, while they depend on the structure of bearing spaces only.
- (iv) The duality relationship of state subspaces with their perpendicular dual subspaces is revealed, which shows

that if a state subspace is invariant then its perpendicular dual subspace is also invariant, and vice versa. This relationship leads to the discovery of universal dual invariant subspaces.

The rest of this paper is outlined as follows: Section 2 investigates dual (control) invariant subspace. Necessary and sufficient conditions are obtained for dual control invariant subspaces. Two algorithms are proposed to numerically verify whether a subspace is a dual (or a dual control) invariant subspace. As a special kind of dual (control) subspaces, the node invariant subspaces are also studied. Section 3 considers the state invariant subspaces, including the attractor-based state invariant subspaces and the bearing space-based invariant subspaces. The universal state invariant subspace is investigated in Section 4. Using universal state invariant subspace the universal cascading normal form is obtained. Section 5 reveals the duality of state invariant subspace with dual invariant subspace. Using duality, the universal dual invariant subspace is also discovered. Section 6 is a brief summary. Finally, an appendix is attached, which consists of two parts: Part 1 is a quick survey on the STP of matrices and the ASSR of networks. Part 2 is a brief introduction to some bearing spaces, including field, ring, and lattice.

Before ending this section, we give a list of notations:

- (1) $\mathcal{M}_{m \times n}$: the set of $m \times n$ real matrices.
- (2) $\text{Col}(M)$ ($\text{Row}(M)$): the set of columns (rows) of M .
 $\text{Col}_i(M)$ ($\text{Row}_i(M)$): the i -th column (row) of M .
- (3) $\mathcal{D}_k := \{1, 2, \dots, k\}$, $k \geq 2$.
- (4) δ_n^i : the i -th column of the identity matrix I_n .
- (5) $\Delta_n := \{\delta_n^i | i = 1, \dots, n\}$.
- (6) $\mathbf{1}_\ell = \underbrace{(1, 1, \dots, 1)}_\ell^T$.
- (7) $\mathbf{0}_{p \times q}$: a $p \times q$ matrix with zero entries.
- (8) A matrix $L \in \mathcal{M}_{m \times n}$ is called a logical matrix if the columns of L are of the form of δ_m^k . That is, $\text{Col}(L) \subset \Delta_m$. Denote by $\mathcal{L}_{m \times n}$ the set of $m \times n$ logical matrices.
- (9) $L = [\delta_n^{i_1}, \delta_n^{i_2}, \dots, \delta_n^{i_r}] \in \mathcal{L}_{n \times r}$ is briefly denoted as $L = \delta_n[i_1, i_2, \dots, i_r]$.
- (10) \ltimes : the semi-tensor product of matrices.
- (11) $*$: Khatri-Rao product of matrices.
- (12) $PR_k := \text{diag}(\delta_k^1, \delta_k^2, \dots, \delta_k^k)$ is called the k -th power-reducing matrix.
- (13) $W_{[m, n]} := [I_n \otimes \delta_m^1, I_n \otimes \delta_m^2, \dots, I_n \otimes \delta_m^m]$ is called the (m, n) -th swap matrix.
- (14) \wedge, \vee, \neg : The conjunction, disjunction, negation operators.

2 Two Kinds of Invariant Subspaces

2.1 Invariant Dual Subspace

Consider a k -valued network

$$\begin{cases} X_1(t+1) = f_1(X_1(t), \dots, X_n(t)), \\ X_2(t+1) = f_2(X_1(t), \dots, X_n(t)), \\ \vdots \\ X_n(t+1) = f_n(X_1(t), \dots, X_n(t)), \end{cases} \quad (3)$$

where $X_i \in \mathcal{D}_k$, $f_i : \mathcal{D}_k^n \rightarrow \mathcal{D}_k$ are k -valued logical functions, $i \in [1, n]$.

Its control version is

$$\begin{cases} X_1(t+1) = f_1(X_1(t), \dots, X_n(t), U_1(t), \dots, U_m(t)), \\ X_2(t+1) = f_2(X_1(t), \dots, X_n(t), U_1(t), \dots, U_m(t)), \\ \vdots \\ X_n(t+1) = f_n(X_1(t), \dots, X_n(t), U_1(t), \dots, U_m(t)), \end{cases} \quad (4)$$

where $U_j \in \mathcal{D}_k$, $j = 1, 2, \dots, m$ are controls.

Assume $X_i = j \in [1, k]$, its vector form expression is denoted by

$$x_i = \vec{X}_i := \delta_k^j.$$

Using vector form expression, k -valued network (3) can be expressed by its component-wise ASSR as

$$x_i(t+1) = M_i x(t), \quad i \in [1, n], \quad (5)$$

where $x(t) = \ltimes_{j=1}^n x_j(t)$, $M_i \in \mathcal{L}_{k \times k^n}$ is the structure matrix of f_i . Moreover, the overall ASSR of (3) is

$$x(t+1) = Mx(t), \quad (6)$$

where $M = M_1 * M_2 * \dots * M_n \in \mathcal{L}_{k^n \times k^n}$.

Similarly, the k -valued control network (4) can be expressed by its component-wise ASSR as

$$x_i(t+1) = L_i u(t) x(t), \quad i \in [1, n], \quad (7)$$

where $u(t) = \ltimes_{j=1}^m u_j(t)$, $L_i \in \mathcal{L}_{k \times k^{n+m}}$ is the structure matrix of f_i . Moreover, the overall ASSR of (4) is

$$x(t+1) = Lu(t)x(t), \quad (8)$$

where $L = L_1 * L_2 * \dots * L_n \in \mathcal{L}_{k^n \times k^{n+m}}$.

The invariant subspace of network (3) or control networks (4) is generated by some k -valued logical functions. In a recent work [11], the concept of invariant subspace for Boolean (control) networks has been

clearly stated and certain fundamental properties have also been provided. This concept and properties can be easily extended to k -valued networks. So we just state them in the k -valued version.

Denote by $\mathcal{X} = \{X_1, X_2, \dots, X_n\}$ the state space of the networks; $\mathcal{F}_\ell(X_1, X_2, \dots, X_n)$ the set of k -valued logical functions with arguments X_1, X_2, \dots, X_n ; $\mathcal{X}^* := \mathcal{F}_\ell(X_1, X_2, \dots, X_n)$ the dual space of \mathcal{X} . Then we have the following definition.

Definition 1 Consider the k -valued network (3). Let $\{Z_1, Z_2, \dots, Z_r\} \subset \mathcal{X}^*$ be a set of logical functions. Define $\mathcal{Z} := \mathcal{F}_\ell(Z_1, Z_2, \dots, Z_r)$ the subspace generated by $\{Z_1, Z_2, \dots, Z_r\}$. \mathcal{Z} is said to be an invariant (dual) subspace of (3) if $Z(0) = (Z_1(0), Z_2(0), \dots, Z_r(0)) \in \mathcal{Z}$ implies $Z(t) \in \mathcal{Z}, \forall t \in \mathbb{Z}_+$.

Let $Z_i = g_i(X_1, X_2, \dots, X_n)$ with $z_i = \vec{Z}_i$ and the structure matrix of g_i be $G_i \in \mathcal{L}_{k \times k^n}$. Then

$$z := \times_{i=1}^r z_i = Gx, \quad (9)$$

where $G = G_1 * G_2 * \dots * G_r \in \mathcal{L}_{k^r \times k^n}$.

Now we have the following conclusion, which is an immediate extension of the corresponding result in [11]:

Proposition 2 [11] \mathcal{Z} is an invariant dual subspace of (3), if and only if, there exists a logical matrix $H \in \mathcal{L}_{k^r \times k^r}$ such that

$$GM = HG. \quad (10)$$

Moreover, let $z(t) = Gx(t)$. Then the dynamics of $z(t)$ is determined by

$$z(t+1) = Hz(t). \quad (11)$$

\mathcal{Z} is also called the M -invariant dual subspace.

Definition 3 Consider the k -valued control network (4). Let $\{Z_1, Z_2, \dots, Z_r\} \subset \mathcal{X}^*$ be a set of logical functions. Define $\mathcal{Z} := \mathcal{F}_\ell(Z_1, Z_2, \dots, Z_r)$ the subspace generated by $\{Z_1, Z_2, \dots, Z_r\}$. \mathcal{Z} is said to be control-invariant dual subspace of (4) if for any $X(0) = (X_1(0), X_2(0), \dots, X_n(0)) \in \mathcal{Z}$ there exists a control sequence $\{U(t) \mid t \geq 0\}$ such that \mathcal{Z} is invariant to the controlled network. In other words, the controlled network satisfies $X(t) \in \mathcal{Z}$.

Splitting L into k^m equal blocks as

$$L = [M_1, M_2, \dots, M_{k^m}],$$

where $M_i = L\delta_{k^m}^i \in \mathcal{L}_{k^n \times k^n}, i \in [1, k^m]$.

For a fixed $H \in \mathcal{L}_{k^r \times k^r}$, we define a set of index sets as follows:

$$J_j := \{i \mid \text{Col}_j(GM_i) = \text{Col}_j(HG)\}, \quad j \in [1, k^n]. \quad (12)$$

Theorem 4 Consider the k -valued control network (4). $\mathcal{Z} := \mathcal{F}_\ell(Z_1, Z_2, \dots, Z_r)$ is a dual control-invariant subspace of (4), if and only if, one of the following two equivalent conditions is satisfied.

(i) There exists an $H \in \mathcal{L}_{k^r \times k^r}$, such that $\forall j \in [1, k^n]$,

$$J_j \neq \emptyset. \quad (13)$$

(ii) There exists a state feedback control

$$u(t) = Fx(t), \quad (14)$$

where $F \in \mathcal{L}_{k^m \times k^n}$, such that \mathcal{Z} is M -invariant, where $M := LFPR_{k^n}$.

Proof: (Necessity) According to Proposition 2, at each time t there must exist a $u(t)$ and an $H \in \mathcal{L}_{k^r \times k^r}$, such that for the controlled system,

$$z(t+1) = Hz(t). \quad (15)$$

Assume $u(t) = \delta_{k^m}^i$, then (15) leads to

$$GM_i x(t) = HGx(t). \quad (16)$$

Assume $x(t) = \delta_{k^n}^j$, then (16) implies $i \in J_j$, that is, $J_j \neq \emptyset$.

Next, from (13) we know that for each $x(t) = \delta_{k^n}^j$ we can find that $u(t) = \delta_{k^m}^i$, where $i \in J_j$ may not be unique, such that (15) holds. Then the state-feedback matrix F exists.

(Sufficiency) Assume (13) holds. We can construct state feedback control as aforementioned. Using this state feedback control, (16) ensures $x(t+1) \in \mathcal{Z}$ as long as $x(t) \in \mathcal{Z}$. \square

Next, we look for numerical algorithms to verify whether a dual subspace is (control) invariant.

To begin with, observing condition (10), one can search H as follows: Assume $\text{Col}_j(G) = \delta_{k^r}^{\ell_j}$, then $\text{Col}_j(HG) = \text{Col}_{\ell_j}(H)$. Hence, to satisfy (10), it is enough to choose

$$\text{Col}_{\ell_j}(H) = \text{Col}_j(GM), \quad j \in [1, k^n]. \quad (17)$$

The following corollary is obvious:

Corollary 5 Consider the k -valued network (3). Define a set of index sets as

$$S_i := \{j \mid \text{Col}_j(G) = \delta_{k^r}^i\}, \quad i \in [1, k^r]. \quad (18)$$

Then \mathcal{Z} is M -invariant, if and only if,

$$\text{Col}_j(GM) = \text{const.}, \quad j \in S_i. \quad (19)$$

Proof: Necessity comes from the fact that (18) forces (19) to be true. As for the sufficiency, as long as (19) holds, we can simply set

$$\text{Col}_i(H) := \text{Col}_j(GM), \quad i \in [1, k^r], \quad (20)$$

which verifies (10). \square

Remark 6 If $S_i = \emptyset$, Eq. (19) is automatically true. Then the corresponding $\text{Col}_i(H)$ can be chosen arbitrarily.

The algorithm follows immediately.

Algorithm 1 Let \mathcal{Z} be a dual subspace of (3) and its structure matrix be $G \in L_{k^r \times k^n}$.

- Step 1: Construct S_i , $i \in [1, k^r]$ by (18).
- Step 2: Check if (19) holds.
If the answer is “yes”, \mathcal{Z} is M -invariant. (H can be constructed by (20).)
Otherwise, \mathcal{Z} is not M -invariant.

Consider the control network (4).

Observing condition (13) one can search H as follows: Assume $\text{Col}_j(G) = \delta_{k^r}^{\ell_j}$, then $\text{Col}_j(HG) = \text{Col}_{\ell_j}(H)$. According to (16), there exists at least one i such that (18) holds for $M = M_i$. It follows that

$$\text{Col}_{\ell_j}(H) \in \bigcup_{i=1}^{k^m} \text{Col}_j(GM_i), \quad j \in [1, k^n]. \quad (21)$$

Hence, we have the following conclusion.

Corollary 7 Consider the control network (4). \mathcal{Z} is control invariant, if and only if,

$$\bigcap_{j \in S_i} \left(\bigcup_{\ell=1}^{k^m} \text{Col}_j(GM_\ell) \right) \neq \emptyset, \quad i \in [1, k^r]. \quad (22)$$

Then the corresponding algorithm can be obtained as follows:

Algorithm 2 Let \mathcal{Z} be a dual subspace of (4) and its structure matrix be $G \in L_{k^r \times k^n}$.

- Step 1: Construct S_i , $i \in [1, k^r]$ by (18).
- Step 2: Check if (22) holds.
If the answer is “yes”, \mathcal{Z} is the control invariant. Go to Step 3.
Otherwise, \mathcal{Z} is not control invariant. Stop.
- Step 3: (Construct state feed control) For each $i \in [1, k^r]$, choose a (anyone)

$$\xi_i \in \bigcap_{j \in S_i} \left(\bigcup_{\ell=1}^{k^m} \text{Col}_j(GM_\ell) \right)$$

Then for each j , there is (at least) a $\ell_j \in [1, k^m]$, such that

$$\xi_i = \text{Col}_j(GM_{\ell_j}).$$

Set

$$u = \delta_{k^m}^{\ell_j}, \quad x = \delta_{k^n}^j, \quad j \in S_i. \quad (23)$$

Note that Remark 6 remain true. That is, if $S_i = \emptyset$, then ξ_i can be arbitrary.

Remark 8 Using (23), the state feedback matrix F as in (14) is obtained. By construction, it is ready to verify that \mathcal{Z} is $M = LFPR_{k^n}$ invariant. That is, control invariant.

Example 9 Consider the 3-valued control network

$$\begin{cases} X_1(t+1) = X_2(t) \vee U(t), \\ X_2(t+1) = X_1(t) \wedge U(t). \end{cases} \quad (24)$$

Assume $\mathcal{Z} = \mathcal{F}_\ell\{Z\}$, where

$$z = \vec{Z} = \delta_3[1, 2, 1, 1, 3, 3, 2, 3, 2]x := Gx.$$

Check whether \mathcal{Z} is a control dual invariant subspace.

The structure matrices of \vee and \wedge are as follows:

$$\begin{aligned} M_d &:= M_\vee = \delta_3[1, 1, 1, 1, 2, 2, 1, 2, 3], \\ M_c &:= M_\wedge = \delta_3[1, 2, 3, 2, 2, 3, 3, 3, 3]. \end{aligned}$$

Then the component-wise ASSR is

$$\begin{cases} x_1(t+1) = M_d u(t) x_2(t) \\ \quad = M_d (I_3 \otimes \mathbf{1}_3^T \otimes I_3) u(t) x(t) \\ \quad := L_1 u(t) x(t), \\ x_2(t+1) = M_c u(t) x_1(t) \\ \quad = M_c (I_9 \otimes \mathbf{1}_3^T) u(t) x(t) \\ \quad := L_2 u(t) x(t), \end{cases} \quad (25)$$

where

$$L_1 = \delta_3[1, 1, 1, 1, 1, 1, 1, 1, 1, 1, 2, 2, 1, 2, 2, 1, 2, 2, 1, 2, 3, 1, 2, 3, 1, 2, 3].$$

$$L_2 = \delta_3[1, 1, 1, 2, 2, 2, 3, 3, 3, 2, 2, 2, 2, 2, 2, 3, 3, 3, 3, 3, 3, 3, 3, 3, 3, 3].$$

Then

$$L = L_1 * L_2$$

$$= \delta_9[1, 1, 1, 2, 2, 2, 3, 3, 3, 2, 5, 5, 2, 5, 5, 3, 6, 6, 3, 6, 9, 3, 6, 9, 3, 6, 9].$$

Next, we calculate GM_i , where $M_i = L\delta_3^i$, $i = 1, 2, 3$. Put them into Table 1.

Table 1
Searching Common Vectors in GM_i

j	1	2	3	4	5	6	7	8	9
$\text{Col}_j(GM_1)$	δ_3^1	$\underline{\delta_3^1}$	δ_3^1	δ_3^2	δ_3^2	δ_3^2	δ_3^1	δ_3^1	$\underline{\delta_3^1}$
$\text{Col}_j(GM_2)$	$\underline{\delta_3^2}$	δ_3^3	δ_3^3	$\underline{\delta_3^2}$	δ_3^3	$\underline{\delta_3^3}$	δ_3^1	δ_3^3	δ_3^3
$\text{Col}_j(GM_3)$	δ_3^1	δ_3^3	$\underline{\delta_3^2}$	δ_3^1	$\underline{\delta_3^3}$	δ_3^2	$\underline{\delta_3^1}$	$\underline{\delta_3^3}$	δ_3^2

Now we search for possible $H = [h_1, h_2, h_3]$:

Since

$$G = \delta_3[1, 2, 1, 1, 3, 3, 2, 3, 2],$$

we have

$$S_1 = \{1, 3, 4\},$$

$$S_2 = \{2, 7, 9\},$$

$$S_3 = \{5, 6, 8\}.$$

Consider S_1 , we have

$$h_1 \in \bigcap_{j=1,3,4} \{\text{Col}_j(GM_1) \cup \text{Col}_j(GM_2) \cup \text{Col}_j(GM_3)\}.$$

Then we can have $h_1 \in \{\delta_3^1, \delta_3^2\}$. We choose, say, $h_1 = \delta_3^2$. Correspondingly, for $j = 1$ we can choose M_2 , for $j = 3$ we can choose M_3 , for $j = 4$ we can choose either M_1 or M_2 , say, we choose M_2 . Then we underline the corresponding M_i in Table 1.

Similarly, considering S_2 , we have

$$h_2 \in \bigcap_{j=2,7,9} \{\text{Col}_j(GM_1) \cup \text{Col}_j(GM_2) \cup \text{Col}_j(GM_3)\}.$$

Then we have $h_2 = \delta_3^1$. Corresponding M_i are also underlined in the Table.

Finally, for S_3 we have

$$h_3 \in \bigcap_{j=5,6,8} \{\text{Col}_i(GM_1) \cup \text{Col}_j(GM_2) \cup \text{Col}_j(GM_3)\}.$$

Then we have $h_3 = \delta_3^3$. Corresponding M_i are also underlined in the Table.

According to Theorem 4, we conclude that \mathcal{Z} is a control-invariant dual subspace. Moreover, using (23), the state feedback can be constructed as

$$u(x) = \begin{cases} \delta_3^1, & x = \delta_9^2, \delta_9^9, \\ \delta_3^2, & x = \delta_9^1, \delta_9^4, \delta_9^6, \\ \delta_3^3, & x = \delta_9^3, \delta_9^5, \delta_9^7, \delta_9^8. \end{cases}$$

Equivalently,

$$u(x) = Fx,$$

where $F = \delta_3[2, 1, 3, 2, 3, 2, 3, 3, 1]$.

A straightforward verification shows that

$$GLFPR_9 = HG,$$

where $H = \delta_3[2, 1, 3]$.

From the above process, one sees easily that the state feedback control is not unique.

2.2 Node Invariant Subspace

Definition 10(i) Assume the k -valued network (3) can be expressed by

$$\begin{cases} X^1(t+1) = F_1(X^1(t)), \\ X^2(t+1) = F_2(X^1(t), X^2(t)), \end{cases} \quad (26)$$

where (X^1, X^2) is a partition of $\{X_1, X_2, \dots, X_n\}$. Then X^1 is called a node invariant subspace. *

(ii) Consider the k -valued control network (4). Assume under a suitable (state feedback) control $U(t) = GX(t)$, the closed-loop network of (4) can be expressed into the form of (26), then X^1 is called a node control-invariant subspace.

Both node invariant subspace and node control-invariant subspace are particularly useful in decoupling problems and has been discussed in detail by [7] under the name of regular subspace.

To verify whether a subspace is a node invariant subspace the key issue is to know when a subspace is a node subspace. The following result is fundamental.

* The node-invariant subspace was called a regular invariant subspace in previous literature, e.g., [7]




Fig. 1. Node Subspace \mathcal{H}^*

Proposition 11 [7] Consider the k -valued network (3) with its ASSR (6). Let $\mathcal{H}^* = \{h_1, h_2, \dots, h_s\} \subset \mathcal{X}^*$ be a dual subspace, and H is the structure matrix of \mathcal{H}^* . \mathcal{H} is a node (or regular) subspace, if and only if,

$$|\{j \mid \text{Col}_j(H) = \delta_{k^s}^i\}| = k^{n-s}, \quad \forall i \in [1, k^s]. \quad (27)$$

Remark 12(i) Both node invariant subspace and node control-invariant subspace are special cases of dual invariant subspace and dual control-invariant subspace respectively. The only special point of node invariant subspaces lies in that the subspaces are generated by a set of coordinate functions.

- (ii) To get the decomposed form (26) a coordinate change may be required.
- (iii) Intuitively, a node invariant subspace \mathcal{H}^* is a set of nodes, which form a subgraph in the network graph. Moreover, the in-degree of the subgraph is zero. (Refer to Fig. 1).
- (iv) For a control network, to verify the node control-invariant subspace the method provided for the dual invariant subspace is also applicable. The only difference lies in verifying whether the subspace is a node (or regular) one.

3 State Invariant Subspace

Definition 13(i) Consider the k -valued network (3). Assume $V \subset \mathcal{D}_k^n$ is a subset of the state space \mathcal{X} . Let $X(0) = \{X_1(0), X_2(0), \dots, X_n(0)\} \in V$. If the trajectory $X(t, X(0)) \in V, t \geq 0$, then V is called a state invariant subspace of (3).

- (ii) Consider the k -valued control network (4). Assume $V \subset \mathcal{D}_k^n$ be a subset of the state space \mathcal{X} . Let $X(0) = \{X_1(0), X_2(0), \dots, X_n(0)\} \in V$. Assume there is a control sequence $\{U(t) \mid t \geq 0\}$. If the trajectory $X(t, U(0), X(0)) \in V, t \geq 0$, then V is called a state control-invariant subspace of (4).

Proposition 14 Let $V \subset \mathcal{X}$ with $|V| = r$.

- (i) V is invariant with respect to network (3) (or M -invariant), if and only if, there exists a logical matrix $E \in \mathcal{L}_{r \times r}$ such that

$$MV = VE. \quad (28)$$

- (ii) V is control-invariant to the control network (4), if and only if, there exists a state feedback

$$u(t) = Gx(t), \quad (29)$$

where $G \in \mathcal{L}_{k^m \times k^n}$, such that V is $LGPR_{k^n}$ -invariant.

Proof:

- (i) The existence of a real matrix E is well known in linear algebra. Since each column of MV is a logical vector, it must be a column of V , which ensures E to be a logical matrix.
- (ii) The argument is similar to the proof of Theorem 4. □

State invariant subspace is closely related to the topological structure of networks. The normal form of Boolean networks was firstly revealed by [15]. The following form comes from [15,32], which is for Boolean networks. It is also true for k -valued networks:

Proposition 15 Consider the k -valued network (3). Under a suitable coordinate frame $z = Tx$, its ASSR can be expressed as

$$z(t+1) = \tilde{M}z(t), \quad (30)$$

where

$$\tilde{M} = \text{diag}(\tilde{M}_1, \tilde{M}_2, \dots, \tilde{M}_k),$$

and each block can be expressed as

$$\tilde{M}_j = \begin{bmatrix} C_j & D_j \\ 0 & N_j \end{bmatrix}, \quad j \in [1, k],$$

where C_j is a cyclic matrix, that is,

$$C_j = \delta_{n_j}[2, 3, \dots, n, 1],$$

corresponding to a cycle of length n_j ; N_j is a nilpotent matrix, that is, there exists an $s_j > 0$ such that $(N_j)^{s_j} = 0$, corresponding to the basin of attraction of C_j .

Since a coordinate transformation of networks is only a state rename, it does not change the topological structure (including attractors and their basins of attraction), the structure of normal form represents general forms. From the normal form, it is clear that a state invariant subspace of a network consists of several attractors with (might be a subset of) their basins of attraction. This is the only form of state invariant subspaces.

State (control) invariant subspaces have been applied to set reachability [47], set stability [19,?], output regulation [44], etc. under terminologies of ‘‘invariant set’’ and ‘‘control invariant set’’. We omit further discussion here.

$$M_{\wedge} M_{\vee} x_1 x_2 x_3 = M_{\wedge} M_{\vee} (\mathbf{1}_5^T \otimes I_{125}) u x$$

$$:= L_3 u x,$$

where

$$L_3 = M_{\wedge} M_{\vee} (\mathbf{1}_5^T \otimes I_{125})$$

$$= \delta_5 [1, 2, 3, 4, 5, 1, 2, 3, 4, 5, 1, 2, 3, 4, 5, 1, 2, 3, 4, 5,$$

$$\dots$$

$$2, 2, 4, 4, 5, 3, 4, 3, 4, 5, 4, 4, 4, 4, 5, 5, 5, 5, 5, 5].$$

It follows that

$$L = L_1 * L_2 * L_3$$

$$= \delta_{125} [1, 2, 3, 4, 5, 1, 2, 3, 4, 5, 1, 2, 3, 4, 5,$$

$$\dots, 47, 47, 49, 49, 50, 73, 74, 73, 74, 75,$$

$$99, 99, 99, 99, 100, 125, 125, 125, 125, 125].$$

Finally, since $J = \{\delta_5^4, \delta_5^5\}$ is a sub-lattice of L (precisely speaking, J is an ideal of L), when all the state variables (i.e., x_1, x_2, x_3), take values from J , the corresponding states form an invariant subspace. Denote it by V . That is,

$$V = \{x = x_1 x_2 x_3 \mid x_1, x_2, x_3 \in \{\delta_5^4, \delta_5^5\}\}$$

$$= \{\delta_5^4 \delta_5^4 \delta_5^4, \delta_5^4 \delta_5^4 \delta_5^5, \dots, \delta_5^5 \delta_5^5 \delta_5^5\}$$

$$= \delta_{125} [94, 95, 99, 100, 119, 120, 124, 125]$$

$$\in \mathcal{L}_{125 \times 8}.$$

If the control $u = \delta_5^4 \in J$, we have

$$M_4 = L \delta_5^4 \in \mathcal{L}_{125 \times 125}.$$

Then V is M_4 -invariant. A straightforward computation shows that

$$M_4 V = V E_1,$$

where $E_1 = \delta_8 [1, 4, 1, 4, 3, 4, 4, 4]$.

If the control $u = \delta_5^5 \in J$, we have

$$M_5 = L \delta_5^5 \in \mathcal{L}_{125 \times 125}.$$

Then V is M_5 -invariant. It is also easy to show that

$$M_5 V = V E_2,$$

where $E_2 = \delta_8 [1, 4, 5, 8, 3, 4, 8, 8]$.

Remark 18 In both Example 16 and Example 17 the invariant subspaces come from the “subspace” structure of the bearing spaces, from which the nodes of networks take values. Such invariant subspaces are independent of the particular networks.

4 Universal Cascading Form

4.1 Universal Invariant Subspace

Definition 19 Assume B is the bearing space of a network with its operators $t_i, i = 1, 2, \dots, s$. $H \subset B$ and the restrictions of $t_i|_H, i = 1, 2, \dots, s$ are properly defined, then H is called a bearing subspace of B .*

Example 20(i) Consider a ring \mathbb{Z}_6 , assume $H = \{0, 3\}$ which is a sub-ring of \mathbb{Z}_6 . Then the operators $\oplus|_H$ and $\odot|_H$ are properly defined. So, if \mathbb{Z}_6 is a bearing space of a network, then H is a bearing subspace of the network.

(ii) Consider a lattice L with its Hasse diagram as in Fig. ???. If L is a bearing space of a network, Then $H_0 = \{D\}$, $H_1 = \{B, D\}$, $H_2 = \{A, B, D\}$, as sub-lattices of L , are all bearing subspaces.

Consider k -valued network (3) (or k -valued control network (4)). Assume its bearing space is B and $H \subset B$ is a bearing subspace. The state subspace corresponding to H is defined by

$$\mathcal{X}|_H = \{(X_1, X_2, \dots, X_n) \in \mathcal{X} \mid X_i \in H, i \in [1, n]\}.$$

The following proposition comes from the definition of bearing space.

Proposition 21 Assume k -valued network (3) (or k -valued control network (4)) has its bearing space B , and $H \subset B$ is a bearing subspace. Then the $\mathcal{X}|_H$ is the state invariant subspace of (3). It is also a control-invariant subspace of (4). Moreover, $\mathcal{X}|_H$ is independent of a particular network. It is, therefore, called the universal state invariant subspace.

Remark 22(i) Assume

$$H = \{\delta_k^{r_1}, \delta_k^{r_2}, \dots, \delta_k^{r_s}\}.$$

Then

$$\mathcal{X}|_H = \left\{ \times_{i=1}^n \delta_k^{j_i} \mid j_i \subset \{r_1, r_2, \dots, r_s\}, i \in [1, n] \right\}. \quad (35)$$

(ii) To see $\mathcal{X}|_H$ is also a control-invariant state subspace, we simply set $u_j \in H, j \in [1, m]$, the conclusion follows.

* In fact, H is a subuniverse of the universal algebra B [3].

4.2 Cascading Normal Form

Proposition 23 Let $H_1 \subset H_2 \subset \dots \subset H_s = B$ be a set of nested bearing subspaces.

- (i) Consider k -valued network (3) with B as its bearing space. Then there exists a coordinate transformation $Z = T(X)$, such that under the coordinate frame Z , the ASSR of (3) becomes

$$z(t+1) = Mz(t), \quad (36)$$

where M has the cascading form (upper block triangular form) as

$$M = \begin{bmatrix} D_{1,1} & D_{1,2} & \dots & D_{1,s} \\ 0 & D_{2,2} & \dots & D_{2,s} \\ \vdots & & & \\ 0 & 0 & \dots & D_{ss} \end{bmatrix}, \quad (37)$$

where the nested diagonal square blocks

$$D_{1,1}, \begin{bmatrix} D_{1,1} & D_{1,2} \\ 0 & D_{2,2} \end{bmatrix}, \dots, M$$

correspond to the nested $H_1 \subset H_2 \subset \dots \subset H_s$ respectively.

- (ii) Consider k -valued control network (4) with B as its bearing space, and assume $u \in H_r$. Then there exists a coordinate transformation $Z = T(X)$, such that under the coordinate frame Z , the ASSR of (4) becomes

$$z(t+1) = \tilde{L}(u)z(t), \quad (38)$$

$$\tilde{L}(u) = \begin{bmatrix} L_{1,1} & L_{1,2} \\ 0 & L_{2,2} \end{bmatrix}, \quad (39)$$

where $L_{1,1}$ corresponds to H_r .

Proof:

- (i) We give constructive proof. Define

$$T_i := \{\times_{j=1}^n x_j^i \mid x_j^i \in H_i\}.$$

It follows from the construction that if $X \in T_i$, $Y \in T_j \mathfrak{I}_i$, $j > i$, then

$$\langle X, Y \rangle = 0. \quad (40)$$

Then we construct a $k^n \times k^n$ matrix as

$$T := [T_1 \mid T_2 \setminus T_1 \mid T_3 \setminus T_2 \mid \dots \mid T_s \setminus T_{s-1}]. \quad (41)$$

Using some properties of the STP, a straightforward computation verifies that T is a coordinate transformation, and

$$T^{-1} = T^T.$$

Moreover, set $x = Tz$, then it is easy to verify that T_i and $T_j \setminus T_i$ are orthogonal, where $j > i$.

$\cdot MT_i \subset T_i$.

These two facts lead to the conclusion that under the coordinate frame z the transition matrix $T^T MT$ has the form (37).

- (ii) Since $u \in H_r$, H_r is $L(u)$ invariant. The conclusion becomes a special case of (i). \square

Example 24 Consider a 4-valued network

$$\begin{cases} X_1(t+1) = X_1(t) \wedge X_2(t), \\ X_2(t+1) = X_1(t) \vee X_2(t). \end{cases} \quad (42)$$

Assume its bearing space is a lattice L with its Hasse diagram as in Fig. ???. Denote by $A = \delta_4^1$, $B = \delta_4^2$, $C = \delta_4^3$, and $D = \delta_4^4$. Skipping the tedious calculation, which is similar to Example 17, the ASSR form of (41) can be obtained as

$$x(t+1) = Mx(t), \quad (43)$$

where

$$M = \delta_{16}[1, 5, 9, 13, 5, 6, 13, 14, 9, 13, 11, 15, 13, 14, 15, 16].$$

It is easy to calculate that

$$\begin{aligned} T_1 &= \{\delta_4^4 \delta_4^4\}, \\ T_2 \setminus T_1 &= \{\delta_4^4 \delta_4^2, \delta_4^2 \delta_4^4, \delta_4^2 \delta_4^2\}, \\ T_3 \setminus T_2 &= \{\delta_4^4 \delta_4^1, \delta_4^1 \delta_4^4, \delta_4^2 \delta_4^1, \delta_4^1 \delta_4^2\}, \\ T_4 \setminus T_3 &= \{\delta_4^1 \delta_4^1, \delta_4^1 \delta_4^3, \delta_4^3 \delta_4^4, \delta_4^2 \delta_4^3, \\ &\quad \delta_4^3 \delta_4^2, \delta_4^1 \delta_4^3, \delta_4^3 \delta_4^1, \delta_4^3 \delta_4^3\}. \end{aligned}$$

Then we got

$$\begin{aligned} T &= [T_1, T_2 \setminus T_1, T_3 \setminus T_2, T_4 \setminus T_3] \\ &= \delta_{16}[16, 14, 8, 6, 13, 4, 5, 2, 1, 15, 12, 7, 10, 3, 9, 11]; \end{aligned}$$

Finally, we set $x = Tz$ and calculate the transition matrix under the z coordinate frame as

$$z(t+1) = T^T MTz(t) := \tilde{M}z(t), \quad (44)$$

where

$$\tilde{M} = \delta_{16}[1, 2, 2, 4, 5, 5, 7, 7, 9, 10, 10, 5, 5, 15, 15, 16], \quad (45)$$

which is in cascading form with

$$\begin{aligned} [1] & \rightarrow H_1, \\ \delta_4[1, 2, 2, 4] & \rightarrow H_2, \\ \delta_8[1, 2, 2, 4, 5, 5, 7, 7] & \rightarrow H_3, \\ \tilde{M} & \rightarrow B. \end{aligned}$$

Remark 25 Precisely speaking, bearing subspaces depend also on network dynamics in certain sense. For instance, in Example 24, only \wedge and \vee are used in dynamic equation (42), hence all the sun-lattices of the lattice L in Fig. ?? are its bearing subspaces.

- (i) Since L is a complementation lattice, each element a has its complement $\neg a$. Now if \neg is used in the dynamic equation (42), then only the complementation sub-lattice can be considered as a bearing subspace. That is, we have only $H_1 = \{A, D\} \subset L$ as its bearing subspace.
- (ii) If we consider conjunctive networks over L , which are similar to conjunctive Boolean networks [16], since (L, \wedge) is a semi-lattice, any sub-semi-lattices can be considered as its bearing subspace. For instance, a nested bearing subspaces can be $H_1 = \{D\}$, $H_2 = \{B, D\}$, $H_3 = \{D, B, C\}$, $H_4 = L$.

5 Duality of Invariant Subspaces

5.1 Invariant Subspace vs Dual Invariant Subspace

Assuming the bearing space B of a finite-valued network has a “zero”, then we consider the duality of invariant subspaces with invariant dual subspaces. We give a precise definition.

Definition 26 Given a bearing space B of a finite-valued network Σ , as described by (3) with its ASSR (6). Assume there is a $\theta \in B$, and a binary operator \odot over B , such that

$$b \odot \theta = \theta \odot b = \theta, \quad \forall b \in B,$$

then B is said to have a zero element θ , and the operator \odot is considered as a product over B .

Example 27(i) Assume B is a finite ring (including finite field), then B is with zero, where $\theta = 0$ and \odot is the product of the ring.

* A lattice is called a complementation lattice if L has a maximum element $\mathbf{1}$ and minimum element $\mathbf{0}$ such that for each element $a \in L$ there is an element, called the complement of a and denoted by $\neg a$, such that

$$a \vee \neg a = \mathbf{1}, \quad a \wedge \neg a = \mathbf{0}.$$

- (ii) Assume B is a k -valued logic (including Boolean logic), then B is with zero, where $\theta = 0$ with product \wedge . (If you wish, you can also set $\theta = 1$ with product \vee .)
- (iii) Assume B is a finite lattice, then B is with zero, where $\theta = \min$ (smallest element) with product \inf .

Definition 28 Given a bearing space B of a finite-valued network Σ , as described by (3), and assume B has zero θ .

- (i) Let $\mathcal{G}^* = \mathcal{F}_\ell(g_1, g_2, \dots, g_r)$ be a dual subspace of \mathcal{X}^* . Then

$$\mathcal{G}^{*\perp} := \{X \in \mathcal{X} \mid g_i(X) = \theta, i \in [1, r]\} \quad (46)$$

is called the state space perpendicular to \mathcal{G}^* .

- (ii) Let $\mathcal{V} = \{X_1, X_2, \dots, X_s\}$ be a subspace of \mathcal{X} . Then

$$\mathcal{V}^\perp := \{f \in \mathcal{X}^* \mid f(X_i) = \theta, i \in [1, s]\} \quad (47)$$

is called the dual state space perpendicular to \mathcal{V} .

The following result shows the relationship between invariant subspace and invariant dual subspace.

Theorem 29 Consider k -valued network (3) with its ASSR (6) and assume its bearing space B has zero element θ .

- (i) Assume \mathcal{G}^* is an M -invariant dual subspace. Then its perpendicular subspace $\mathcal{V} = \mathcal{G}^{*\perp}$ is an M -invariant subspace.
- (ii) Assume \mathcal{V} is an M -invariant subspace. Then its perpendicular dual subspace $\mathcal{G}^* = \mathcal{V}^\perp$ is an M -invariant dual subspace.

Proof: We prove (i) only, the proof of (ii) is similar.

Let $x \in \mathcal{G}^{*\perp}$. Consider Mx : Since $G \in \mathcal{L}_{k^r \times k^n}$ is M -invariant, there exists H such that

$$GMx = HGx.$$

Now since $HG \subset \text{Span}\{\text{Row}(G)\}$, $HGx = \theta^r$. Hence $Mx \in \mathcal{G}^{*\perp}$. \square

The following is an immediate consequence.

Corollary 30 Given a bearing space B of a finite control network Σ , as described by the k -valued control network (4) with its ASSR (6) and assume its bearing space B has zero element θ .

- (i) Assume \mathcal{G}^* is a control-invariant dual subspace. Then its perpendicular subspace $\mathcal{V} = \mathcal{G}^{*\perp}$ is a control-invariant subspace.

(ii) Assume \mathcal{V} is a control-invariant subspace. Then its perpendicular dual subspace $\mathcal{G}^* = \mathcal{V}^\perp$ is a control-invariant dual subspace.

We use a simple example to verify Theorem 29.

Example 31 Consider a Boolean network

$$\begin{cases} X_1(t+1) = X_1(t) \vee X_2(t), \\ X_2(t+1) = X_1(t) \wedge X_2(t), \\ X_3(t+1) = X_1(t) \leftrightarrow X_3(t). \end{cases} \quad (48)$$

Then it is obvious that $\mathcal{G}^* = \mathcal{F}_\ell(X_1, X_2)$ is a node invariant subspace. The ASSR of (48) can easily be calculated as

$$x(t+1) = Mx(t), \quad (49)$$

where $M = \delta_8[1, 2, 3, 4, 4, 3, 8, 7]$.

Let the structure matrix of \mathcal{G}^* be G . Then it is easy to calculate that

$$G = \delta_4[1, 1, 2, 2, 2, 2, 4, 4].$$

A straightforward verification shows that

$$GM = HG,$$

where $H = I_4$.

Consider $E := \mathcal{G}^{*\perp}$. Then

$$\begin{aligned} E &= \{\delta_2^2 \delta_2^2 x_3 \mid x_3 \in \Delta_2\} \\ &= \{\delta_8^7, \delta_8^8\}. \end{aligned}$$

It is ready to verify that

$$ME = E\delta_2[2, 1] \subset E.$$

5.2 Universal Dual Invariant Subspace

Using the duality of invariant subspaces with dual invariant subspaces, one sees easily that the universal invariant subspaces also have their corresponding (perpendicular) dual invariant subspaces. According to Theorem 29, it is obvious that the dual invariant subspaces are also independent of the particular network dynamics. Hence we have the following result.

Proposition 32 Consider the k -valued network (3). Assume its bearing space B has zero θ . If \mathcal{V} is a universal invariant subspace, then $\mathcal{G}^* = \mathcal{V}^\perp$ is also universal. That is, it is independent of particular network dynamics.

Example 33 Recall Example 24 and observe Fig.???. There is a sequence of universal invariant subspaces:

$$H_1 \subset H_2 \subset H_3 \subset H_4 = L,$$

where H_i corresponds to T_i , $i = 1, 2, 3, 4$.

Then we have a sequence of universal dual invariant subspaces as

$$\mathcal{G}_4^* \subset \mathcal{G}_3^* \subset \mathcal{G}_2^* \subset \mathcal{G}_1^*,$$

where $\mathcal{G}_i^* = H_i^\perp$, $i = 1, 2, 3, 4$.

Then it is clear that the elements of \mathcal{G}_i^* , denoted their vector forms by g_i , $i = 1, 2, 3, 4$, are

$$\begin{aligned} g_4 &= \delta_4[4, 4, 4, 4, 4, 4, 4, 4, 4, 4, 4, 4, 4, 4], \\ g_3 &= \delta_4[4, 4, *, 4, 4, 4, *, 4, *, *, *, *, 4, 4, *, 4], \\ g_2 &= \delta_4[*, *, *, *, *, 4, *, 4, *, *, *, *, *, 4, *, 4], \\ g_1 &= \delta_4[*, *, *, *, *, *, *, *, *, *, *, *, *, *, 4], \end{aligned}$$

where $*$ $\in \{1, 2, 3, 4\}$ stands for arbitrary value.

Using the coordinate transformation

$$\begin{aligned} T &= \delta_{16}[16, 14, 8, 6, 13, 4, 5, 2, 1, 15, 12, 7, 10, 3, 9, 11], \\ \tilde{g}_4 &:= g_4 T = \delta_4[4, 4, 4, 4, 4, 4, 4, 4, 4, 4, 4, 4, 4, 4, 4, 4], \\ \tilde{g}_3 &:= g_3 T = \delta_4[4, 4, 4, 4, 4, 4, 4, 4, *, *, *, *, *, *], \\ \tilde{g}_2 &:= g_2 T = \delta_4[4, 4, 4, 4, *, *, *, *, *, *, *, *, *, *], \\ \tilde{g}_1 &:= g_1 T = \delta_4[4, *, *, *, *, *, *, *, *, *, *, *, *, *, *]. \end{aligned}$$

It is ready to verify that $\mathcal{G}_i^* = \{\tilde{g}_i\}$ $i = 1, 2, 3, 4$ are \tilde{M} -invariant, where \tilde{M} is given in (45).

6 Conclusion

Though the concept of ‘‘invariant subspace’’ has been used in the STP-based study of Boolean (control) networks for a considerable long time, it has not been clearly defined and there are some unclear or murky issues. In this paper, the two kinds of (control) invariant subspaces of k -valued networks have been clearly defined. They are the state invariant and dual invariant subspaces of the state space and the dual space respectively. Then their properties have been investigated.

First, for invariant dual subspaces, two algorithms have been proposed to verify if a dual subspace of a network is an invariant subspace and a dual subspace of a control network is a dual control invariant subspace respectively. Second, for state invariant subspaces, the relationship between the topological structure and the state invariant subspaces is revealed. Then a special kind of

state invariant subspaces, called universal subspaces, are considered. They are caused by the structure of bearing space and are independent of the dynamics of individual networks. Based on universal invariant subspaces the universal normal form is revealed. Finally, the duality of state invariant subspaces and dual invariant subspaces is obtained, which shows that if a dual subspace is invariant, then its perpendicular state subspace is also invariant, and vice versa.

Since invariant subspace is a fundamental concept and a useful tool in many control problems of networks, this paper may help to build a solid theoretical foundation for further investigation and applications.

References

- [1] A. Adamatzky, On dynamically non-trivial three-valued logics: oscillatory and bifurcatory spaces, *Chaos Solitons Fractals*, Vol. 18, 917-936, 2003.
- [2] T. Akutsi, M. Hayashida, W. Ching, M. Ng, Control of Boolean networks: hardness results and algorithms for three structured networks, *J. Theor. Biol.*, Vol. 244, No. 4, 670-769, 2007.
- [3] S. Burris, H.H. Sankappanavar, *A Course in Universal Algebra*, Springer-verlag, New York, 1981.
- [4] R.E. Bryant, A switch-level model and simulator for MOS digital systems, *IEEE Trans. Comput.*, Vol. C-33, No. 2, 160-177, 1984.
- [5] D. Cheng, H. Qi, State space analysis of Boolean networks, *IEEE Trans. Neural Netw.*, Vol. 21, No. 4, 584-594, 2010.
- [6] D. Cheng, H. Qi, Z. Li, *Analysis and Control of Boolean Networks: A Semi-tensor Product Approach*, Springer, London, 2011.
- [7] D. Cheng, Disturbance decoupling of Boolean control networks, *IEEE Trans. Aut. Contr.*, Vol. 56, No. 1, 2-10, 2011.
- [8] D. Cheng, H. Qi, Y. Zhao, *An Introduction to Semi-tensor Product of Matrices and Its Applications*, World Scientific, Singapore, 2012.
- [9] D. Cheng, F. He, H. Qi, T. Xu, Modeling analysis and control of networked evolutionary games, *IEEE Trans. Aut. Contr.*, Vol. 60, No. 9, 2402-2415, 2015.
- [10] D. Cheng, Y. Wu, G. Zhao, S. Fu, A comprehensive survey on STP approach to finite games, *J. Sys. Sci. Compl.*, Vol. 34, No. 5, 1666-1680, 2021.
- [11] D. Cheng, L. Zhang, D. Bi, Invariant subspace approach to Boolean (control) networks, *IEEE Trans. Aut. Contr.*, (on line) ieeexplore.ieee.org/document/9775567, 2022.
- [12] D. Cheng, Z. Ji, On networks over finite rings, *J. Franklin Inst.*, Vol. 359, No. 14, 7562-7599, 2022.
- [13] A. Datta, A. Choudhary, M.L. Bittner, E.R. Dougherty, External control in Markovian genetic regulatory networks, *Mach. Learn.*, Vol. 52, 169-191, 2003.
- [14] G. Epstein, The lattice theory of Post algebras, *Trans. Am. Soc.*, Vol. 95, 300-317, 1960.
- [15] E. Fornasini, M.E. Valcher, Observability, reconstructibility and state observers of Boolean control networks, *IEEE Trans. Aut. Contr.*, Vol. 58, No. 6, 1390-1401, 2013.
- [16] Z. Gao, X. Chen, T. Başar, Stability structures of conjunctive Boolean networks, *Automatica*, Vol. 89, 8-20, 2018.
- [17] P. Guo, Y. Wang, H. Li, Algebraic formulation and strategy optimization for a class of evolutionary networked games via semi-tensor product method, *Automatica*, Vol. 49, 3384-3389, 2013.
- [18] Y. Guo, P. Wang, W. Gui, C. Yang, Set stability and set stabilization of Boolean control networks based on invariant subsets, *Automatica*, Vol. 61, 106,112, 2015.
- [19] Y. Guo, Y. Ding, D. Xie, Invariant subset and set stability of Boolean networks under arbitrary switching signals, *IEEE Trans. Aut. Contr.*, Vol. 62, No. 8, 4209-4214, 2017.
- [20] Y. Guo, R. Zhou, Y. Wu, W. Gui, C. Yang, Stability and set stability in distribution of probabilistic Boolean networks, *IEEE Trans. Aut. Contr.*, Vol. 64, No. 2, 736-742, 2019.
- [21] T.W. Hungerford, *Algebra*, Springer-Verlag, Now York, 1974.
- [22] T. Ideker, T. Galitski, L. Hood, A new approach to decoding life: systems biology, *Annu. Rev. Genom. Hum. Genet.*, Vol. 2, 343-372, 2001.
- [23] A. Isidori, *Non-linear Control Systems*, 3rd ed., Springer-Verlag, New York, 1995.
- [24] Z. Ji, D. Cheng, Control networks over finite lattices, preprint, arXiv:2208.03716, 2022.
- [25] J. de Jong, Modeling and simulation of genetic regulatory systems: a literature review, *J. Comput. Biol.*, Vol. 9, No. 1, 67-103, 2012.
- [26] R.E. Kalman, On the general theory of control systems, in Automatic and Remote control (Proc. 1st Int. Congr. Internat. Fed. Aut. Contr., Moscow, 1960), Butterworths, London, Vol. 1, 481-492, 1961.
- [27] S.A. Kauffman, Metabolic stability and epigenesis in randomly constructed genetic nets, *J. Theoret. Biol.*, Vol. 22, 437-467, 1969.
- [28] Z. Li, D. Cheng, Algebraic approach to dynamics of multi-valued networks, *Int. J. Bifurc. Chaos*, Vol. 20, No. 3, 561-582, 2010.
- [29] X. Li, M. Chen, H. Su, C. Li, Consensus networks with switching topology and time-delays over finite fields, *Automatica* 68 (2016) 39-43.
- [30] H. Li, G. Zhao, P. Guo, Analysis and Control of Finite-Valued Systems, CRC Press, 2018.
- [31] Y. Li, H. Li, X. Ding, G. Zhao, Leader-follower consensus of multiagent systems with time delays over finite fields, *IEEE Trans. Cyb.* 49 (8) (2019) 3203-3208.
- [32] Z. Liu, D. Cheng, Canonical form of Boolean networks, *Proc. 38th CCC*, 1801-1806, 2019.
- [33] A. Liu, H. Li, On feedback invariant subspace of Boolean control networks, *Sci. China Inf. Sci.*, 63, 229201, 2020.
- [34] M. Meng, X. Li, G. Xiao, Synchronization of networks over finite fields, *Automatica* 115 (2020) 108877.
- [35] F. Pasqualetri, D. Borra, F. Bullo, Consensus networks over finite fields, *Automatica* 50 (2) (2014) 349-358.
- [36] E.L. Post, Introduction to a general theory of elementary propositions, *AM.J. Math.*, Vol. 43, 163-185, 1921.
- [37] E. Remy, P. Ruet, D. Thieffry, Positive or negative regulatory circuit inference from multilevel dynamics, in *Positive Systems: Theory and Applications*, Lecture Notes in Control and Information Science, Vol. 341, Springer, Berlin, 263-270, 2006.
- [38] A. Richard, J.P. Comet, Necessary conditions for multistationarity in discrete dynamical systems, *Disc. Appl. Math.*, Vol. 155, 2403-2413, 2007.

- [39] K.A. Ross, C.R.B. Wright, *Discrete Mathematics*, 5th Ed., Prentice Hall, New Jersey, 2003.
- [40] S. Sundaram, C.N. Hadjicostis, Structural controllability and observability of linear systems over finite fields with applications to multi-agent systems, *IEEE Trans. Aut. Contr.* 58 (1) (2012) 60-73.
- [41] R. Thomas, M. Kaufman, Multistationarity, the basis of cell differentiation and memory, I& II, *Chaos*, Vol. 11, 170-195, 2001.
- [42] W.M. Wonham, *Linear Multivariable Control, A Geometric Approach*, Springer-Verlag, Berlin, 1974.
- [43] X. Zhang, Y. Wang, D. Cheng, Incomplete logical control system and its application to some intellectual problems, *Asian J. Contr.*, Vol. 20, No. 2, 697-706, 2018.
- [44] X. Zhang, Y. Wang, D. Cheng, Output tracking of Boolean control networks, *IEEE Trans. Aut. Contr.*, Vol. 65, No. 6, 2730-2735, 2020.
- [45] J. Zhu, P. Lü, Regular subspaces and invariant subspaces, *IET Contr. Theory Appl.*, Vol. 10, No. 5, 504-508, 2016.
- [46] Y. Zou, J. Zhu, Kalman decomposition for Boolean control networks, *Automatica*, Vol. 54, 65-71, 2015.
- [47] R. Zhou, Y. Guo, Set reachability and observability of probabilistic Boolean networks, *Automatica*, Vol. 106, 230-241, 2019.

A Semi-tensor Product of Matrices

The semi-tensor product of matrices is defined as follows [6,8]:

Definition 34 Let $M \in \mathcal{M}_{m \times n}$, $N \in \mathcal{M}_{p \times q}$, and $t = \text{lcm}\{n, p\}$ be the least common multiple of n and p . The semi-tensor product (STP) of M and N is defined as

$$M \times N := (M \otimes I_{t/n}) (N \otimes I_{t/p}) \in \mathcal{M}_{mt/n \times qt/p}, \quad (\text{A.1})$$

where \otimes is the Kronecker product.

The STP of matrices is a generalization of the conventional matrix product, and all the computational properties of the conventional matrix product remain available. Throughout this paper, the default matrix product is STP, so the product of two arbitrary matrices is well defined, and the symbol \times is mostly omitted.

The following properties will be used in the sequel:

Proposition 35 Let $X \in \mathbb{R}^t$. Then for a given matrix A we have

$$XA = (I_t \otimes A)X. \quad (\text{A.2})$$

A swap matrix $W_{[m,n]} \in \mathcal{M}_{mn \times mn}$ is defined as

$$W_{[m,n]} := [I_n \otimes \delta_m^1, I_n \otimes \delta_m^2, \dots, I_n \otimes \delta_m^m]. \quad (\text{A.3})$$

It is used to swap two vectors.

Proposition 36 Let $X \in \mathbb{R}^m$, $Y \in \mathbb{R}^n$ be two column vectors. Then

$$W_{[m,n]}XY = YX. \quad (\text{A.4})$$

A power reducing matrix $PR_k \in \mathcal{M}_{k^2 \times k}$ is defined as

$$PR_k := \text{diag}(\delta_k^1, \delta_k^2, \dots, \delta_k^k). \quad (\text{A.5})$$

It is used to reduce the power of a vector.

Proposition 37 Let $X \in \mathbb{R}^k$. Then

$$PR_k X = X^2. \quad (\text{A.6})$$

Using STP to k -valued logical mappings, we have the following result.

Proposition 38 Let $f : \Delta_k^n \rightarrow \Delta_k$. Then there exists a unique matrix, called the structure matrix of f and denoted by $M_f \in \mathcal{L}_{k \times k^n}$, such that

$$f(x_1, x_2, \dots, x_n) = M_f \times_{i=1}^n x_i, \quad x_i \in \Delta_k, i \in [1, n]. \quad (\text{A.7})$$

Definition 39 Let $A \in \mathcal{M}_{p \times n}$ and $B \in \mathcal{M}_{q \times n}$. The Khatri-Rao product of A and B , denoted by $A * B$, is defined as follows.

$$A * B = [\text{Col}_1(A) \text{Col}_1(B), \text{Col}_2(A) \text{Col}_2(B), \dots, \text{Col}_n(A) \text{Col}_n(B)] \in \mathcal{M}_{pq \times n}. \quad (\text{A.8})$$

B Some Bearing Spaces

In this section, we give a brief introduction to some basic algebraic structures, which are used to describe structures of some commonly used bearing spaces of k -valued networks.

Definition 40 [21] A set $G \neq \emptyset$ with a binary operator $*$: $G \times G$ is a group, if

- (i) $a * (b * c) = (a * b) * c, \quad a, b, c \in G;$
- (ii) there exists an identity $e \in G$, such that

$$a * e = e * a = a, \quad \forall a \in G;$$

- (iii) for each $a \in G$ there exists a inverse a^{-1} , such that

$$a * a^{-1} = a^{-1} * a = e.$$

If only (i) is satisfied, G is a semi-group. If only (i) and (ii) are satisfied, G is a monoid (or semi-group with identity).

In addition, if a group satisfies

$$a * b = b * a, \quad a, b \in G,$$

then G is called an Abelian group.

Definition 41 [21] A set $R \neq \emptyset$ with two binary operators $+$ and $*$ is called a ring, denoted by $(R, +, *)$, if

- (i) $(R, +)$ is an Abelian group with identity $\mathbf{0}$,
- (ii) $(R, *)$ is a semi-group,
- (iii) the following distributive rule is satisfied:

$$(a + b) * c = a * c + b * c,$$

$$c * (a + b) = c * a + c * b, \quad a, b, c \in R.$$

When $(R, *)$ is with identity $\mathbf{1}$, it is called a ring with identity. If $a * b = b * a$ for $a, b \in R$, R is called a commutative ring. If $E \subset R$ and $(E, +, *)$ is also a ring, E is said to be a sub-ring of R . If E is a sub-ring of R and for any $r \in R$ and $e \in E$

$$r * e, e * r \in E,$$

then E is called an ideal of R .

Definition 42 [21] A set $(F, +, *)$ is a field, if it is a ring, and $(F \setminus \{\mathbf{0}\}, *)$ is also an Abelian group.

Definition 43 [3] A partial ordered set (L, \prec) is called a lattice, if for any two elements $a, b \in L$, there exists a least upper bound, denoted by $\sup(a, b) = a \vee b$, and a greatest lower bound, denoted by $\inf(a, b) = a \wedge b$.

If (L, \prec) is a lattice, $H \subset L$ and (H, \prec) is also a lattice, then H is said to be a sub-lattice of L . A sub-lattice H is called an ideal, if for any $a \in L$ there exists an $h \in H$ such that $a \prec h$ implies $a \in H$.

A lattice can be described by a figure called the Hasse diagram. For instance, Fig. B.1 shows a lattice L , where $L = \{A, B, C, D\}$. It is easy to verify that $A \vee B = A$, $A \wedge B = B$, $B \vee C = A$, $B \wedge C = D$, etc.




Fig. B.1. Hasse Diagram of L