

Correcting one error in channels with feedback

Ilya Vorobyev, Alexey Lebedev, Vladimir Lebedev, Christian Deppe

Abstract

We address the problem of correcting a single error in an arbitrary discrete memoryless channel with error-free instantaneous feedback. For the case of a one-time feedback, we propose a method for constructing optimal transmission strategies. The obtained result allows us to prove that for a binary channel, two feedbacks are sufficient to transmit the same number of messages as in the case of complete feedback. We also apply the developed techniques to a binary asymmetric channel to construct transmission strategies for small lengths.

I. INTRODUCTION

We analyze the problem of correcting a single error in an arbitrary discrete memoryless channel with instantaneous error-free feedback. In what follows we always assume all these conditions—memoryless channel and error-free instantaneous feedback—to be fulfilled. The most attention is paid to binary symmetric and asymmetric channels. In a binary symmetric channel, any symbol can be transmitted erroneously, for example, 0 instead of 1, or vice versa. The word *symmetric* is usually omitted, and such a channel is simply referred to as a binary channel. In a binary asymmetric channel, 0 can be received instead of a transmitted symbol 1, but the symbol 0 is always transmitted without errors. We consider a combinatorial model of such a channel with feedback and a single transmission error.

It is known that the problem of correcting t errors in a binary channel with complete feedback is equivalent to the following combinatorial search problem. It is required to find an element $x \in \mathcal{M}$ using n questions of the following type: “Does an element x belong to a subset A of a set $\mathcal{M}$?” Questions are asked in succession, i.e., each next question may depend on answers to the preceding ones. The opponent who answers the questions knows x and is allowed to lie at most t times. This problem was first formulated by Rényi [1]. For a linear number of errors in a binary channel with complete feedback, the optimal transmission rate was computed by Berlekamp [2] and Zigangirov [3]. This problem became popular after Ulam in his biography [4] asked a similar question for $M = 10^6$. Optimal strategies for all M have been found in [5] for $t = 1$, in [6] for $t = 2$, and in [7] for $t = 3$. Tables of optimal strategies for various values of t and $M \leq 2^{20}$ are presented in [8].

Error correction in a binary asymmetric channel with complete feedback is equivalent to a version of Ulam’s problem with halfie first described in [9]. The difference from the original problem is that lying is allowed only when the true answer is affirmative. A good survey of results on this problem can be found in [10]. For a fixed number t of errors, the maximum cardinality of $\mathcal{M}$ is asymptotically equivalent to $2^{n+t} / \binom{n}{t}$. For $t = 1$, this was proved in [11], and for an arbitrary t , in [12], [13].

Note that for a fixed number of errors, even one-time feedback is sufficient to transmit asymptotically the same number of messages as in the case of complete feedback. For a nonbinary symmetric channel, this was proved in [14], and for an arbitrary discrete channel, in [15].

A key result of the present paper is the description of optimal strategies with one-time feedback and a single error for an arbitrary discrete channel. The developed technique is applied to construct single-error-correcting transmission strategies for a binary channel with one- or two-time feedback, and also to construct single-error-correcting strategies in a binary asymmetric channel with one-time feedback. The most interesting of the obtained results, in our opinion, is constructing a strategy with two feedbacks

Ilya Vorobyev and Christian Deppe are with Institute of Communications Engineering, Technical University of Munich, Munich, Germany. (email: ilya.vorobyev@tum.ru, christian.deppe@tum.de)

Alexey Lebedev and Vladimir Lebedev are with Kharkevich Institute for Information Transmission Problems, Moscow, Russia. (email: al_lebed95@mail.ru, lebedev37@mail.ru)

that corrects a single error in a binary channel and transmits as many messages as a completely adaptive strategy.

The rest of the paper is organized as follows. In Section II we give basic definitions. In Section III we formulate and prove a theorem describing the structure of optimal strategies with a single error and one-time feedback. In Section IV the main theorem is applied to construct a single-error-correcting transmission strategy in a binary channel with two feedbacks that allows to transmit as many messages as in the case of complete feedback. In the last section, the developed technique is applied to find good strategies for a binary asymmetric channel with a single error and one-time feedback.

II. BASIC DEFINITIONS

Consider a channel with q -ary input alphabet $\mathcal{X} = \{0, \dots, q-1\}$ and output alphabet $\mathcal{Y} = \mathcal{X}$. The encoder transmits a message $\mathbf{x} \in \mathcal{X}^n$, and the decoder receives a message $\mathbf{y} \in \mathcal{Y}^n$. The prefix of length p of a vector $\mathbf{y}$ will be denoted by $\mathbf{y}_{\overline{p}}$. By an error we mean replacing a symbol q_1 of a sequence $\mathbf{x}$ by a symbol q_2 , $q_1 \neq q_2$. We define a bipartite graph G with the left-hand part corresponding to elements from $\mathcal{X}$, and the right-hand part, to elements from $\mathcal{Y}$. We connect $q_1 \in \mathcal{X}$ and $q_2 \in \mathcal{Y}$, $q_1 \neq q_2$, by an edge if an error may change the symbol q_1 to q_2 . An example of such a graph for a one-way ternary channel is shown in Fig. 1.




Figure 1. Error graph for a one-way ternary channel.

In this paper we consider transmission over a channel with k feedbacks. Let the codeword length n be divided into $k+1$ parts:

$$n = n_1 + n_2 + \dots + n_{k+1}.$$

The encoder transmits a message $m \in [M]$. The first n_1 transmitted symbols $x_1, \dots, x_{n_1}$ depend on the message m only. After $N_{i-1} := n_1 + \dots + n_{i-1}$, $i \geq 2$, symbols are transmitted, the encoder has values of the received symbols $\mathbf{y}_{\overline{N_{i-1}}}$ from the feedback channel. The encoder sends the i th block of n_i symbols, which is a function of the message m and of the symbols $\mathbf{y}_{\overline{N_{i-1}}}$ received by the encoder. The case of $k=0$ corresponds to a channel without feedback, and the case of $k=n-1$, to a channel with complete feedback.

We define the cloud $B_t(m)$ (or $B(m)$ for $t=1$) for a message m to be the set of sequences $\mathbf{y}$ that can be obtained at the output of the channel with at most t errors during the transmission of this message. We refer to the collection of disjoint clouds $B_t(m)$, $m \in [M]$, as a t -error-correcting code $\mathcal{C}$. Points of the space that do not belong to any cloud will be referred to as free points and will be denoted by $\mathcal{F}(\mathcal{C})$. Codes that do not use feedback will be called nonadaptive.

Note that for a symmetric channel without feedback, clouds are spheres of radius t in the Hamming metric. For a symmetric channel, sizes of all clouds are the same, but for an arbitrary error graph this is not the case. For constructions proposed in the present paper, it makes sense to find codes with the maximum number of free points for each length and each cardinality. Such codes will be called F -optimal.

As an example, let us describe the structure of clouds for a binary channel with a single error and complete feedback. Every cloud $B(m)$ contains a sequence $\mathbf{y}$ which will be transmitted if there are no errors in the channel. We call it a root sequence. For any coordinate i , the cloud contains a sequence $\mathbf{y}(i)$ which coincides with $\mathbf{y}$ in the first $i - 1$ positions, differs from it in the i th position, and has arbitrary symbols in all other positions. Hence it is seen that each cloud consists of at least $n + 1$ sequences. In particular, this yields the Hamming bound on the maximum number of transmitted messages.

III. ONE-TIME FEEDBACK

In this section we propose a transmission strategy for the case of a single error and one-time feedback. We divide the codeword length n into two parts, n_1 and n_2 , with $n = n_1 + n_2$. We define a bipartite graph $H = (U \sqcup V, E)$ as follows. The left- and right-hand parts consist of q^{n_1} vertices corresponding to the sets of input and output sequences. Vertices u and v are connected by an edge if the sequence corresponding to v can be obtained from the sequence corresponding to u as a result of a single error. Note that we do not connect vertices corresponding to identical sequences (this corresponds to the case of no error).

Theorem 1. *Let a graph $H = (U \sqcup V, E)$ be given. A strategy allowing to transmit*

$$M = \sum_{u \in U} M(u) \quad (1)$$

messages exists if and only if there exists a family of single-error-correcting codes $C(u)$ of length n_2 and cardinality $M(u)$ with $F(u)$ free points that satisfy the condition

$$\sum_{u: (u,v) \in E} M(u) \leq F(v) \quad (2)$$

for any $v \in V$.

Proof. Let us describe an arbitrary coding strategy. First, a sequence $\mathbf{u}$ of length n_1 is transmitted, which corresponds to a vertex u in the left-hand part U of the graph H . Let the number of messages such that transmitting them begins with the sequence $\mathbf{u}$ be $M(u)$. Consider the case of no error in the first n_1 symbols. On the remaining n_2 symbols, we need to transmit $M(u)$ different messages, and one error may occur. Therefore, we need to use a single-error-correcting code $C(u)$ of length n_2 and cardinality $M(u)$. Denote by $F(u)$ the number of free points of $C(u)$.

If there was an error in the first n_1 symbols and instead of $\mathbf{u}$ a sequence $\mathbf{v}$ was received, to transmit $M(u)$ messages that start with $\mathbf{u}$ we need $M(u)$ points, which must be free points of $C(v)$.

Thus, for each message $\mathbf{v}$ there should exist a code $C(v)$ with free points distributed among the sequences $\mathbf{u}$ from which the sequence $\mathbf{v}$ can be reached, and every such sequence $\mathbf{u}$ must get at least $M(u)$ free points, which is possible if and only if condition (2) is satisfied.

Now we describe the decoding algorithm. Let a sequence of the first n_1 received symbols correspond to a vertex $v \in V$; denote the sequence of the last n_2 symbols by $\mathbf{a}$. If $\mathbf{a}$ is not a free point of $C(v)$, this means that an error occurred in the second part of the message. In this case, the second part of the message corresponds to the center of the sphere to which the point $\mathbf{a}$ belongs.

If the sequence $\mathbf{a}$ is a free point of $C(v)$, then it corresponds to some sequence $\mathbf{u}$ from which $\mathbf{v}$ can be obtained. Then precisely this sequence $\mathbf{u}$ has been transmitted at the first encoding stage. The second part of the message is recovered based on which point $\mathbf{a}$ out of at least $M(u)$ points corresponding to $\mathbf{u}$ was used. $\square$

We are not aware of any efficient (polynomial in the code length) method to find an optimal family of codes satisfying (2). However, even choosing identical codes for all sequences $\mathbf{u} \in \mathcal{X}^{n_1}$ can provide a good result, as is shown in Corollary 1.

For an example showing that choosing identical codes for a binary channel is not optimal, consider the case of $n_1 = 2$ and $n_2 = 1$. When identical codes are chosen, the maximum number of messages is

always divisible by 2^{n_1} , and in this case it is 0, since even adaptively, no more than two messages can be transmitted on length 3. If we choose two different codes, we can transmit two messages.

The following statement for a binary symmetric channel will be used below to construct an optimal strategy with two feedbacks.

Corollary 1. *Let $n_2 = 2^k - 1$, $n_1 = n - n_2$, $k \geq 1$. Then in a symmetric channel with a single error and one-time feedback we can transmit*

$$M_1(n) = 2^{n_1} \left\lfloor \frac{2^{n_2}}{n_1 + n_2 + 1} \right\rfloor$$

messages.

Proof. To each point $\mathbf{u}$, assign as $\mathcal{C}(u)$ the Hamming code of length n_2 with x codewords deleted. We choose x so that to satisfy the constraints (2). This is equivalent to the inequality

$$x2^k \geq n_1(2^{n_2-k} - x),$$

whence we obtain

$$x \geq \frac{n_1 2^{n_2-k}}{n_1 + 2^k}.$$

Then we may take $x = \left\lceil \frac{n_1 2^{n_2-k}}{n_1 + 2^k} \right\rceil$. The number of remaining words in the chosen codes is

$$2^{n_2-k} - \left\lceil \frac{n_1 2^{n_2-k}}{n_1 + 2^k} \right\rceil = \left\lfloor \frac{2^{n_2}}{n_1 + 2^k} \right\rfloor = \left\lfloor \frac{2^{n_2}}{n_1 + n_2 + 1} \right\rfloor$$

The total number of transmitted messages is

$$M_1(n) = 2^{n_1} \left\lfloor \frac{2^{n_2}}{n_1 + n_2 + 1} \right\rfloor.$$

□

IV. BINARY SYMMETRIC CHANNEL WITH FEEDBACK

Denote by $Alg_k(n)$ a transmission strategy in a channel of length n with a single error and k feedbacks. Now we describe an algorithm to construct a strategy $Alg_k(n)$ given $Alg_{k-1}(n-1)$, which will be used in what follows.

DADA (Double and Delete Algorithm) algorithm for constructing a strategy $Alg_k(n)$ given $Alg_{k-1}(n-1)$.

Recall that every cloud in a binary symmetric channel of length $n-1$ contains a root message and $n-1$ additional messages that coincide with the root in the first $i-1$ symbols and differ from it in the i th symbol, $i = 1, 2, \dots, n-1$. From each cloud of messages of length $n-1$, we construct two sets of messages of length n by adding to each message the prefix 0 for the first set and 1 for the second. To make a cloud on length n from the first (second) set, it suffices to add any message beginning with 1 (0). We will refer to such sets as incomplete clouds. Next, from each free point we make two free points by adding a prefix 0 or 1. We use up all available free sequences to turn some number of incomplete clouds into clouds. If the number of incomplete clouds is not greater than the number of free sequences of length n , by the end of this procedure we will have $2M(n-1)$ clouds and some number of free points, where $M(n-1)$ is the number of messages transmitted by the $Alg_{k-1}(n-1)$ algorithm. In this case, the DADA algorithm is completed.

Otherwise, by the end of this procedure we will have some number of clouds and some number of incomplete clouds completely covering the space.

After that, we will take one incomplete cloud of sequences beginning with 1 and one incomplete cloud of sequences beginning with 0 and eliminate them by turning all their elements into free points. This

operation yields $2n$ free points. Then free points are used to turn incomplete clouds into clouds. The operation is repeated until the incomplete clouds are over.

At the end of the procedure, there remain an even number of clouds and at most $2n$ free points. If the number of free points is $2n$, this means that these free points have been obtained just now from two incomplete clouds. Then we reconstruct one of these incomplete clouds back and turn it into a cloud by adding one free point. As a result, we obtain an additional cloud.

Thus, we have proved the following.

Theorem 2. *Assume that on length $n-1$ we have constructed $M(n-1)$ clouds for transmitting messages with a single error and $k-1$ feedbacks, $k = 1, \dots, n-1$. Let*

$$U(n) = 2 \left\lfloor \frac{2^n}{2(n+1)} \right\rfloor, \quad r(n) = 2^n - (n+1)U(n).$$

Then the DADA algorithm constructs a strategy $Alg_k(n)$ transmitting $M(n)$ messages, where

$$M(n) = \begin{cases} 2M(n-1) & \text{if } 2M(n-1) \leq \frac{2^n}{n+1}, \\ U(n) & \text{if } 2M(n-1) > \frac{2^n}{n+1} \text{ and } r(n) < 2n, \\ U(n) + 1 & \text{if } 2M(n-1) > \frac{2^n}{n+1} \text{ and } r(n) \geq 2n. \end{cases}$$

In the complete feedback case, the optimum number of messages that can be transmitted with a single error has been computed in [5]. In Theorem 3 we present a new simpler proof of this result.

Theorem 3. *Let*

$$U(n) = 2 \left\lfloor \frac{2^n}{2(n+1)} \right\rfloor, \quad r(n) = 2^n - (n+1)U(n).$$

Then one can transmit $M_{ad}(n)$ messages through a channel with a single error, where

$$M_{ad}(n) = \begin{cases} U(n) & \text{if } r(n) < 2n, \\ U(n) + 1 & \text{if } r(n) \geq 2n. \end{cases} \quad (3)$$

Moreover, this number of messages is optimal.

Remark 1. *In fact, r is always even and is less than $2n+2$; therefore, the condition $r \geq 2n$ in the last line of (3) can be replaced with $r = 2n$. Note that the second case is realized very rarely. Namely, the code cardinality is $U(n) + 1$ for $n = 1, 2$, and the next length for which this happens is 49 736. Thus, the optimum number of messages is most often the largest even number that does not exceed the Hamming bound.*

Proof. We will construct a transmission strategy inductively. For $n \leq 8$, the formula can be verified by hand.

Now assume that for length $n-1$, $n \geq 9$, we have constructed $M_{ad}(n-1)$ clouds. Note that the number of incomplete clouds is at least

$$2M_{ad}(n-1) \geq \frac{2^n}{n} - 4 > \frac{2^n}{n+1}$$

for $n \geq 9$. We use the DADA algorithm to construct an adaptive strategy on length n from the strategy on length $n-1$. Since

$$2M_{ad}(n-1) > \frac{2^n}{n+1},$$

we conclude that $M_{ad}(n)$ equals either $U(n)$ or $U(n) + 1$ depending on $r(n)$, as required. $\square$

Theorem 4. *In a binary channel with two feedbacks and a single error, $M_{ad}(n)$ messages can be transmitted, i.e., the same number as for the transmission with complete feedback.*

n	3	4	5	6	7	8	9	10	11	12	13	14	15	16
M_1	2	2	4	8	16	28	50	90	168	312	580	1088	2048	3854
M_{ad}	2	2	4	8	16	28	50	92	170	314	584	1092	2048	3854

Table I

MAXIMUM NUMBERS TRANSMITTED MESSAGES IN A BINARY SYMMETRIC CHANNEL WITH A SINGLE ERROR, WITH ONE-TIME FEEDBACK AND WITH COMPLETE FEEDBACK.

Note that one-time feedback is not sufficient for that, which is seen from Table I.

Proof. We use the DADA algorithm to construct $Alg_2(n)$ given $Alg_1(n-1)$. For $Alg_1(n-1)$ we take the strategy constructed in Corollary 1 with

$$M_1(n-1) = \left\lfloor \frac{2^{n_2}}{n_1 + n_2 + 1} \right\rfloor 2^{n_1},$$

where $n_2 = 2^k - 1$ and $n_1 = n - 1 - n_2$.

Notice (see Table I) that for $n \leq 9$ even one-time feedback is sufficient to transmit the same number of messages as for coding with complete feedback. Therefore, it suffices to prove the statement for $n \geq 10$. Let us show that

$$2M_1(n-1) > \frac{2^n}{n+1}$$

for $n \geq 10$.

This is equivalent to the inequality

$$2^{n_1+1} \left\lfloor \frac{2^{n_2}}{n_1 + n_2 + 1} \right\rfloor > \frac{2^{n_1+n_2+1}}{n_1 + n_2 + 2}.$$

Reducing by 2^{n_1+1} and using the inequality $\lfloor x \rfloor > x - 1$, we obtain

$$\left\lfloor \frac{2^{n_2}}{n_1 + n_2 + 1} \right\rfloor > \frac{2^{n_2}}{n_1 + n_2 + 1} - 1 \geq \frac{2^{n_2}}{n_1 + n_2 + 2}.$$

The latter inequality is equivalent to

$$2^{n_2} \geq (n_1 + n_2 + 1)(n_1 + n_2 + 2).$$

Recalling that $n_2 \geq n_1$ and $n_2 = 2^k - 1$, we conclude that the inequality holds for $n_2 \geq 15$.

Thus, we have proved the inequality $2M_1(n-1) > \frac{2^n}{n+1}$ for $n \geq 16$. For $n \in [10, 15]$, the inequality can be checked by hand using Table I. Applying Theorems 2 and 3 yields the desired result. $\square$

V. BINARY ASYMMETRIC CHANNEL

In this section we apply the theorems obtained above to the binary asymmetric channel. To this end, we need to compose tables of codes with many free points. To find such codes, we use the linear programming method.

In [16]–[18], linear programming was used to prove upper bounds on the cardinality of nonadaptive codes correcting asymmetric errors. We modify the methods from those papers to obtain upper bounds on the number of free points in a code of fixed length and cardinality.

Denote by $M_Z(n, t)$ the maximum cardinality of a t -error-correcting asymmetric code of length n . Also, denote by $L(n, d, w)$ and $U(n, d, w)$ the lower and upper bounds on the cardinality of a constant-weight code with weight w , length n , and distance d .

Theorem 5. Let $n \geq 2t \geq 2$, $1 \leq M \leq M_Z(n, t)$. Define

$$\overline{F}(n, M, t) = \max \left(2^n - \sum_{i=0}^n \left(z_i \sum_{j=0}^t \binom{i}{i-j} \right) \right),$$

where the maximum is over all z_i satisfying the following conditions:

- 1) z_i are nonnegative integers;
- 2) $z_0 = 1, z_1 = z_2 = \dots = z_t = 0$;
- 3) $\sum_{i=1}^s \binom{n-w+i}{i} z_{w-i} + \sum_{j=0}^{t-s} \binom{w+j}{j} z_{w+j} \leq \binom{n}{w}$ for $0 \leq s \leq t < w < n-t$;
- 4) $\sum_{j=s}^r z_j L(r-s, 2t+2, r-j) \leq U(n+r-s, 2t+2, r)$ for $0 \leq s \leq r$;
- 5) $\sum_{j=s}^r z_{n-j} L(r-s, 2t+2, r-j) \leq U(n+r-s, 2t+2, r)$ for $0 \leq s \leq r$;
- 6) $\sum_{i=1}^s \binom{n-w+i}{i} z_{w-i} + \sum_{j=0}^{t-s} \binom{w+j}{j} z_{w+j} + \left(\binom{w+t-s+1}{w} - \binom{t+1}{t-s+1} \left\lfloor \frac{w+t-s+1}{t+1} \right\rfloor \right) \times z_{w+t-s+1} \leq \binom{n}{w}$ for $0 \leq s \leq t < w < n-t$,
 $\sum_{i=1}^s \binom{n-w+i}{i} z_{w-i} + \sum_{j=0}^{t-s} \binom{w+j}{j} z_{w+j} + \left(\binom{n-w+s+1}{s+1} - \binom{t+1}{t-s} \left\lfloor \frac{n-w+s+1}{t+1} \right\rfloor \right) \times z_{w-s-1} \leq \binom{n}{w}$ for $0 \leq s \leq t < w < n-t$;
- 7) $\sum_{i=0}^n z_i = M$.

Then the number F of free points in a code of length n and cardinality M correcting t asymmetric errors is not greater than $\bar{F}(n, M, t)$.

Proof. Denote by $z_i, 0 \leq i \leq n$, the number of codewords of weight i in a code of length n correcting t asymmetric errors. In [16]–[18] it was proved that the z_i must satisfy conditions 1 and 3–6. It is easily seen that a code with the maximum number of free points must satisfy condition 2. The last condition fixes the cardinality of a considered code. The maximized expression $\bar{F}(n, M, t)$ corresponds to the number of free points in a code with weight distribution $\{z_i\}$. $\square$

We also apply the linear programming method to find codes with the maximum number of free points. Fix a code length n , cardinality M , and the number t of correctable asymmetric errors. Introduce 2^n binary variables x_i corresponding to all possible codewords. For each point p , define the set $D_t(p)$ of codewords from which this point can be reached as a result of t asymmetric errors. Impose the constraint

$$\sum_{i \in D_t(p)} x_i \leq 1. \text{ For } t = 1, \text{ we will maximize the number } 2^n - \sum_{i=0}^n z_i(i+1) \text{ of free points, where } z_i \text{ is}$$

the number of codewords of weight i . Note that the number of free points can be expressed through the variables x_i . Add the constraint $\sum x_i = M$ to fix the code cardinality. Note that any solution to the linear programming problem (if exists) yields an optimum number of free points for fixed code length and cardinality. To speed up computations, we have added the constraints from Theorem 5.

Despite these optimizations, the program operates with 2^n variables, so a solution can be found for small enough values of n only. In Table II we present the parameters of some F -optimal codes for $t = 1$ and $n = 6, 7, 8$, and 9 . Optimal weight distributions are presented in Table III.

The parameters of the codes of length $n = 6, 8$, and 9 coincide with the upper bounds given by Theorem 5. For $n = 7$ and $M = 18$, we have obtained 48 free points instead of 49 given by the upper bound of Theorem 5; i.e., the upper bound of Theorem 5 is not attained. All the other values coincide with the upper bounds.

Codes with the optimal weight distribution for the lengths $n = 7$ and 8 have been constructed in [16]. A code for $n = 6$ was also previously known. For the lengths $n = 6$ and 8 and all cardinalities $M \leq M_Z(n, 1)$,

optimal codes can be obtained from the code of the maximum cardinality with the weight distribution given in Table III by deleting $M_Z(n, d) - M$ codewords of the maximum weight. For the length $n = 7$ and cardinality $M = 17$, we know two codes with different weight distributions with the optimum number of free points: $1 + 0 + 3 + 5 + 5 + 3 + 0 + 0$ and $1 + 0 + 3 + 5 + 6 + 1 + 1 + 0$. By deleting codewords of the maximum weight from the code with the second weight distribution, we obtain F -optimal codes for all $M < 17$. However, only the code with the first weight distribution can be augmented to a code of cardinality 18.

The program works for all $n < 9$. For larger lengths, the complexity is too high. Since the F -optimal constructions for the lengths $n = 6$ and 8 are nested codes, for the length $n = 9$ we also restrict our search to such families. This approach allowed us to find a family of nested codes such that the maximal code of cardinality 62 has the weight distribution presented in Table III. The number of free points in codes of this family coincides with the upper bounds of Theorem 5 for all cardinalities M . This means that the codes of the constructed family are F -optimal. Note that the code of the maximum cardinality and of length $n = 9$ constructed in [16] has 171 free points, whereas in our code there are 177 free points.

$n = 6$	Cardinality M	12	11	10	9	8
	Free points F	16	23	28	33	38
$n = 7$	Cardinality M	18	17	16	15	14
	Free points F	48	56	62	68	73
$n = 8$	Cardinality M	36	35	34	33	32
	Free points F	76	85	92	99	106
$n = 9$	Cardinality M	62	61	60	59	58
	Free points F	177	186	193	200	207

Table II
OPTIMAL NUMBER OF FREE POINTS FOR $(n, M, 1)$ CODES.

Length and cardinality	Weight Distribution
$n = 6, M = 12$	1+0+3+4+3+0+1
$n = 7, M = 18$	1+0+3+5+5+3+1+0
$n = 7, M = 17$	1+0+3+5+6+1+1+0
$n = 8, M = 36$	1+0+4+8+10+8+4+0+1
$n = 9, M = 62$	1+0+4+9+17+17+11+2+1+0

Table III
OPTIMAL WEIGHT DISTRIBUTIONS.

Having in our disposal tables of codes with free points, we can apply Theorem 1 to construct transmission strategies for an asymmetric channel with feedback. In the case where the parameters $M(v)$ and $F(v)$ depend on a codeword weight only, we obtain the following.

Corollary 2. *Let $M(v) = M_w$ and $F(v) = F_w$ for all $v \in V$ such that the number of symbols 1 in v is w , i.e., $M(v)$ and $F(v)$ depend on the weight of the codeword v only. If the conditions*

$$(n_1 - w)M_{w+1} \leq F_w \quad (4)$$

are satisfied for all $w \in [0, n_1 - 1]$, then the number of transmitted messages is

$$M = \sum_{w=0}^{n_1} \binom{n_1}{w} M_w. \quad (5)$$

The numbers of messages transmitted by the algorithms constructed based on Corollary 2 and Theorem 1 are presented in Table IV. To compute the values of M_w and F_w that give optimal answers, we have used

the dynamic programming technique. In the examples presented below, we give a detailed description of codes obtained using Corollary 2 and Theorem 1 for the lengths $n = 9$ and $n = 8$, respectively.

n	5	6	7	8	9	10	11	12	13
M (Corollary 2)	9	16	29	52	96	177	327	607	1120
M (Theorem 1)	9	16	29	53	97	≥ 177	≥ 329	≥ 607	≥ 1120

Table IV

NUMBER OF MESSAGES TRANSMITTED THROUGH AN ASYMMETRIC CHANNEL WITH ONE-TIME FEEDBACK AND A SINGLE ERROR.

We will denote by $(n, M, F, t)_Z$ a nonadaptive code of length n correcting t asymmetric errors and having M codewords and F free points. In the first example we demonstrate an application of Corollary 2, where the code used after the feedback depends only on the weight of a codeword transmitted before the feedback. On the length $n = 8$, applying Corollary 2 allows to transmit 52 messages only. In the second example we show how one can transmit 53 messages using Theorem 1. This means that Corollary 2 does not always give an optimal answer.

Example 1. $n = 9$ and $M = 96$.

Let $n_1 = 5$ and $n_2 = 4$. To vertices that correspond to binary words of weights 0 and 1, we assign a $(4, 2, 12, 1)_Z$ code with two codewords $\{0000, 0011\}$. To vertices of weights 2 and 3, we assign a $(4, 3, 9, 1)_Z$ code with three codewords $\{0000, 0011, 1100\}$. To weights 4 and 5, we assign a $(4, 4, 4, 1)_Z$ code with four codewords $\{0000, 0011, 1100, 1111\}$.

Let us check the constraints $(n_1 - w)M_{w+1} \leq F_w$ for $w \in [0, 4]$:

$$w = 0 : 5 \cdot 2 \leq 12,$$

$$w = 1 : 4 \cdot 3 \leq 12,$$

$$w = 2 : 3 \cdot 3 \leq 9,$$

$$w = 3 : 2 \cdot 4 \leq 9,$$

$$w = 4 : 1 \cdot 4 \leq 4.$$

Using (5), we compute the number of transmitted messages:

$$1 \cdot 2 + 5 \cdot 2 + 10 \cdot 3 + 10 \cdot 3 + 5 \cdot 4 + 1 \cdot 4 = 96.$$

Example 2. $n = 8$ and $M = 53$.

Let $n_1 = 6$ and $n_2 = 2$. To the vertex 111111 we assign a $(2, 2, 0, 1)_Z$ code $\{00, 11\}$. To the vertices 111000, 001110, 010101, 100011, 100100, 010010, 001001, 110000, 010100, 001000, 000010, and 000001 we assign a $(2, 0, 4, 1)_Z$ code with 0 codewords. To all other vertices, we assign a $(2, 1, 3, 1)_Z$ code with one codeword $\{00\}$. One can easily check that conditions (2) of Theorem 1 are fulfilled. For example, let us check the conditions for the vertex $v = 101000$: in total, there are four vertices from which v can be reached: $\{111000, 101100, 101010, 101001\}$. The cardinalities of the corresponding codes are

$$M(111000) = 0, \quad M(101100) = 1,$$

$$M(101010) = 1, \quad M(101001) = 1.$$

The sum of these cardinalities is not greater than $F(101000) = 3$; i.e., the constraint for the vertex $v = 101000$ is satisfied. In the same way one can check the constraints for the other vertices.

The total number of transmitted messages is $2 + 0 + 51 = 53$.

We present a table with the number of messages that can be transmitted through a channel with a single asymmetric error and complete feedback. The best results are obtained in [11], where transmission of $M = 2^m$ messages requires the length $n = m - 1 + \lceil \log_2(m + 3) \rceil$. Although we use one-time feedback only, we can transmit more messages than in [11] for $n \leq 13$, except for the case of $n = 7$. For an

asymmetric channel with complete feedback and a single error, one can use an algorithm similar to DADA which allows to construct codes with the optimal number M_{ad} of transmitted messages. Cardinalities of these codes are presented in Table V. A detailed description of the construction of such codes will be given in one of subsequent papers.

n	5	6	7	8	9	10	11	12	13
M [11]	8	16	32	32	64	128	256	512	1024
M_{ad}	11	20	36	66	121	223	415	774	1452

Table V
CODE CARDINALITIES FOR AN ASYMMETRIC CHANNEL WITH COMPLETE FEEDBACK AND A SINGLE ERROR.

FUNDING

The research of I.V. Vorobyev was partially supported by the joint grant of the Russian Foundation for Basic Research and the National Science Foundation of Bulgaria, project no. 20-51-18002, Russian Foundation for Basic Research, project no. 20-01-00559, and BMBF-NEWCOM, grant no. 16KIS1005.

The research of K. Deppe was partially supported by BMBF-NEWCOM, grant no. 16KIS1005, and BMBF-6G-life, grant no. 16KISK002.

The research of A.V. Lebedev and V.S. Lebedev was partially supported by the joint grant of the Russian Foundation for Basic Research and the National Science Foundation of Bulgaria, project no. 20-51-18002.

REFERENCES

- [1] Rényi, A., On a Problem of Information Theory, *Magyar Tud. Akad. Mat. Kutató Int. Közl.*, 1961, vol. 6, pp. 505–516.
- [2] Berlekamp, E.R., Block Coding for the Binary Symmetric Channel with Noiseless, Delayless Feedback, *Error-Correcting Codes (Proc. Conf. Conducted by the Mathematics Research Center, United States Army, at the University of Wisconsin, Madison, May 6–8, 1968)*, Mann, H.B., Ed., New York: Wiley, 1969, pp. 61–85.
- [3] Zigangirov, K.Sh., On the Number of Correctable Errors for Transmission over a Binary Symmetrical Channel with Feedback, *Probl. Peredachi Inf.*, 1976, vol. 12, no. 2, pp. 3–19 [*Probl. Inf. Transm. (Engl. Transl.)*, 1976, vol. 12, no. 2, pp. 85–97].
- [4] Ulam, S.M., *Adventures of a Mathematician*, New York: Scribner, 1976.
- [5] Pelc, A., Solution of Ulam’s Problem on Searching with a Lie, *J. Combin. Theory Ser. A*, 1987, vol. 44, no. 1, pp. 129–140.
- [6] Guzicki, W., Ulam’s Searching Game with Two Lies, *J. Combin. Theory Ser. A*, 1990, vol. 54, no. 1, pp. 1–19.
- [7] Deppe, C., Solution of Ulam’s Searching Game with Three Lies or an Optimal Adaptive Strategy for Binary Three-Error-Correcting Codes, *Discrete Math.*, 2000, vol. 224, no. 1–3, pp. 79–98.
- [8] desJardins, D.L., Precise Coding with Noiseless Feedback, *PhD Thesis*, Dept. of Mathematics, Univ. of California, Berkeley, 2002. Available at
- [9] Rivest, R.L., Meyer, A.R., Kleitman, D.J., Winkelmann, K., and Spencer, J., Coping with Errors in Binary Search Procedures, *J. Comput. System Sci.*, 1980, vol. 20, no. 3, pp. 396–404.
- [10] Cicalese, F., *Fault-Tolerant Search Algorithms: Reliable Computation with Unreliable Information*, Berlin: Springer, 2013.
- [11] Cicalese, F. and Mundici, D., Optimal Coding with One Asymmetric Error: Below the Sphere Packing Bound, *Computing and Combinatorics (Proc. 6th Annu. Int. Conf. COCOON 2000, Sydney, Australia, July 26–28, 2000)*, Du, D.Z., Eades, P., Estivill-Castro, V., Lin, X., and Sharma, A., Eds., Lect. Notes Comput. Sci., vol. 1858, Berlin: Springer, 2000, pp. 159–169.
- [12] Dumitriu, I. and Spencer, J., A Halfliar’s Game, *Theoret., Comput. Sci.*, 2004, vol. 313, no. 3, pp. 353–369.
- [13] Spencer, J. and Yan, C.H., The Halfliar Problem, *J. Combin. Theory Ser. A*, 2003, vol. 103, no. 1, pp. 69–89.
- [14] Bassalygo, L.A., Nonbinary Error-Correcting Codes with One-Time Error-Free Feedback, *Probl. Peredachi Inf.*, 2005, vol. 41, no. 2, pp. 63–67 [*Probl. Inf. Transm. (Engl. Transl.)*, 2005, vol. 41, no. 2, pp. 125–129].
- [15] Dumitriu, I. and Spencer, J., The Two-Batch Liar Game over an Arbitrary Channel, *SIAM J. Discrete Math.*, 2005, vol. 19, no. 4, pp. 1056–1064.
- [16] Delsarte, P. and Piret, P., Bounds and Constructions for Binary Asymmetric Error-Correcting Codes, *IEEE Trans. Inform. Theory*, 1981, vol. 27, no. 1, pp. 125–128.
- [17] Kløve, T., Upper Bounds on Codes Correcting Asymmetric Errors, *IEEE Trans. Inform. Theory*, 1981, vol. 27, no. 1, pp. 128–131.
- [18] Weber, J., de Vroedt, C., and Boeke, D., New Upper Bounds on the Size of Codes Correcting Asymmetric Errors, *IEEE Trans. Inform. Theory*, 1987, vol. 33, no. 3, pp. 434–437.