scaleTRIM: Scalable TRuncation-Based Integer Approximate Multiplier with Linearization and Compensation

Ebrahim Farahmand Department of Electrical Engineering Shahid Bahonar University of Kerman Kerman, Iran ebi271@gmail.com Ali Mahani Department of Electrical Engineering Shahid Bahonar University of Kerman Kerman, Iran amahani@uk.ac.ir Behnam Ghavami Simon Fraser University Burnaby, BC, Canada behnam_ghavami@sfu.ca

Muhammad Abdullah Hanif eBrain Lab, Division of Engineering New York University Abu Dhabi Abu Dhabi, UAE mh6117@nyu.edu Muhammad Shafique eBrain Lab, Division of Engineering New York University Abu Dhabi Abu Dhabi, UAE muhammad.shafique@nyu.edu

Abstract—Approximate computing (AC) has become a prominent solution to improve the performance, area, and power/energy efficiency of a digital design at the cost of output accuracy. We propose a novel scalable approximate multiplier that approximates the multiplication of two operands using fitted linear functions with two inputs, referred to as linearization. Multiplication operations can be completely replaced by addition and bit-wise shift by using linearization. Moreover, it utilizes a lookup table-based compensation unit as a novel error-reduction method. Input operands are truncated to a reduced bitwidth representation (e.g., h bits) based on their leading one positions. Then, a curve-fitting method is employed to map the product term to a linear function, and a piecewise constant error-correction term is used to reduce the approximation error. In order to compute the piecewise constant error-compensation term, we divide the function space into M segments and average the errors within each segment. The multiplier supports various degrees of truncation and error-compensation to exploit accuracy-efficiency trade-off. The proposed approximate multiplier offers better error metrics such as mean and standard deviation of absolute relative error (MARED and StdARED) compare to a state-of-theart integer approximate multiplier. The proposed approximate multiplier improves the MARED and StdARED by about 38% and 32% when its energy consumption is about equal to the stateof-the-art approximate multiplier. Moreover, the performance of the proposed approximate multiplier is evaluated in image classification applications using a Deep Neural Network (DNN). The results indicate that the degradation of DNN accuracy is negligible especially due to the compensation properties of our approximate multiplier.

Index Terms—Approximate Computing, Approximate Multiplier, Error-Reduction, Scalable, Truncating, Efficiency, Trade-off, Compensation, DNNs, Machine Learning.

I. INTRODUCTION

Power consumption is a critical design concern for modern embedded devices. Due to the inherently error-tolerant behavior of a large number of application domains, such as digital signal processing (DSP) [13], data mining, and deep learning [7], using approximate computing (AC) appears as a promising solution to reduce their power/energy consumption [17], [6]. A major part of energy consumption in these applications is associated with the multiplication operations, which motivated researchers to investigate approximate multiplier architectures [10]. Research efforts focus on designing efficient hardware designs at the cost of minor accuracy loss. The accuracy can further be improved by compensating for the errors with ease in successive computations [15]. As different applications require different accuracy targets, an approximate multiplier with a wide range of trade-offs between accuracy and resource efficiency is highly desirable [14], [21].

A multiplication operation is generally accomplished by generating partial products, accumulating partial products, and summing the remaining two rows using a fast adder. In order to approximate the multiplier, the approximation can be applied to each of the three aforementioned steps of the approximate multiplication operation. Accordingly, in some works such as [18] [23] [8] and [22], approximations are applied in the first step of the approximate multiplier by reducing the number of partial products or reducing the complexity of partial product generation units. Some prior works aim to decrease the energy consumption or latency by applying approximate compressors to the different levels of partial product accumulation [1][5]. The architecture of the adder being used for accumulating the partial product affects the energy consumption of the multiplier [4]. Thus, employing approximations for adders can further reduce the energy consumption of a multiplier.

Motivational Analysis: It is important to note that, fixed approximate accuracy designs cannot accommodate a wide range of applications due to their diverse resilience profiles and different accuracy requirements. A class of approximate multipliers which provided flexibility and tunable error includes TOSAM [20], DSM [13] and DRUM [8]. These designs provide variable accuracy, but their efficiency in terms of delay, power and area drops as accuracy requirements rise, which negatively impacts both cost and computation power. Fig. 1 shows the Absolute Relative Error Distance (ARED) of these multipliers relative to one of the input operands (A). As depicted in Fig. 1, the peak error and mean of ARED (MARED) of these approximate multipliers is relatively high, i.e., TOSAM has the least MARED between these multipliers which is equal to 5.76%. However, the MARED of one of our proposed multiplier configurations (e.g. scaleTRIM (3,4)) is equal to 3.73%. Moreover, as shown in Fig. 1 (a-d), the peak ARED of our scaleTRIM (3,4) has the least ARED among the other state-of-the-art works.



Figure 1. Absolute Relative Error (ARED) of state-of-the-art works (a-c) and proposed approximate multiplier (d), and Mean of ARED (MARE) of Approximate Multipliers (e)

Our Novel Contributions: In this paper, a novel scalable approximate multiplier that utilizes a lookup table-based compensation unit to reduce the approximation error is proposed. To improve energy efficiency, input operands are truncated to the h bits based on the position of their Leading One bits Detection (LODs) position. The multiplication is then approximated using a curve fitting method to linear operations, dramatically reducing the energy cost of multiplication. Moreover, to decrease the error of the approximation, we obtained a piecewise constant error-correction term. For computing the piecewise constant error-compensation term, we partitioned the error value of approximate multiplier space into M segments and compute the compensation factor for each segment by averaging the errors in the segment. Hence, as depicted Fig. 1, the MRED of one of the scaleTRIM configurations has the lowest error behavior compared to state-of-the-art works. In Section III, we will demonstrate that error-configurable scaleTRIM offers better error-efficiency trade-offs than stateof-the-art approximate multipliers. The accuracy of our errorconfigurable approximate multiplier is dependent on multiple degrees of truncation (h) and error-compensation (M) parameter values, and provided various design points to exploit the accuracy-efficiency trade-off. These are the key concepts



Figure 2. Overview of our novel design of scaleTRIM (h,M) consist of 4 steps: design a novel approximate multiplier based on linearization, error compensation model, design space provided by various value of h and M, and Investigate for DNN as a case-study

of our methodology to design approximate multiplier. Fig. 2 presents an overview of our novel design of approximate multiplier called scaleTRIM (h,M) where h and M refer truncation bits and error-compensation term, respectively. The key contribution of this paper are summarized as follows.

- We present a novel scalable approximate unsigned multiplier which finds the position of inputs' Leading-One Detector (LODs) and uses a curve fitting model to fit the inputs product with a linear function called linearization.
- We propose a novel compensation scheme to reduce the approximation error. For computing the constant piecewise compensation error term, The error value space of approximation are divided into M segments and average the errors within each segment.
- We provide a design space to target different applications. Our approximate multiplier supports various degrees of truncation (h) and error-compensation terms (M) to offer better accuracy-efficiency trad-off.
- We investigate the application of our proposed multiplier for image classification using deep neural networks (DNN).

II. RELATED WORK

A review of works dealing with the design of approximate multipliers is presented in this section. The dynamic segment method (DSM) is proposed in [13] which is used for approximating fixed point multiplier. It captures m bits of n-bit inputs from two or three fixed bit positions depend on LODs position to feed into the $m \times m$ multiplier for calculating the approximate product of two input operands. This method made high mean relative error (MRE) in the output. In order to reduce the error of the truncated multiplier, a dynamic range unbiased multiplier (DRUM) method is proposed. DRUM captured the m bits of n-bit inputs from the LODs position and set the low significant bit (LSB) of m bits to '1'. Then, the m bits of inputs are fed into the mxm multiplier to calculate the approximate product of inputs operand. In recent years, new designs are proposed to improve the efficiency of approximate multipliers such as DRUM and DSM. LETAM [19] proposed the method that truncated the inputs operand to improve the efficiency of the proposed approximate multiplier. In RoBA [22], the authors used the rounding method. In this method, the input operands are rounded to the nearest power of two. In TOSAM [20] proposed the salable approximate multiplier using the truncating and rounding methods. First, the LODs position of input operands is found. Then, the next t bits which is placed next to LODs are fed into the t-bit adder. Moreover, the next h bits of LODs are captured and set the LSB with '1'. Then (h+1) bits are fed into the $(h+1)\times(h+1)$ multiplier. However, TOSAM achieves offers better quality in trade off between these multiplier, but the mean of absolute relative error (MRED) is still high, as depicted in Fig.1. Some works are focused on improving the speed of multiplication by performing addition instead of multiplication. One approach is to use the linearization method to transform the multiplication into a linear function. In this regards, ApproxLP [9] proposed a method which transformed the product of two input operands into linear functions. Hence, this method removed the multiplication with linearization method. However, ApproxLP is compatible with GPU and uses for floating point numbers. Another approach is to change the numbering system to a logarithmic which removed the multiplication. In this approach which called Mitchell [12], a logarithm is generated for each input operand, their sum is calculated, then an antilogarithm operation is applied to the sum to achieve the final result. Several studies have focused on improving the Mitchell approximate multiplier [16], [2] and [15]. In MBM [15] an error-reduction mechanism are proposed for Mitchell approximate multiplier to decrease the error of approximation. In this approach, the complexity arises from the calculations involving logarithms and antilogarithms. In this paper, a scalable approximate multiplier based on truncation and linearization is proposed which utilizes a compensating unit to reduce the approximation error. We will describe our approximate multiplier in detail in the following section.

III. PROPOSED METHOD

In this paper, an approximate multiplier is proposed which utilizes a compensating unit to reduce the approximation error. To improve energy consumption, after finding the leading one bits position of inputs operands, input operands are truncated to h bits. Then, a curve-fitting method based on the truncated input operands summation are proposed to fit the product to a linear function. This method approximate the multiplication operation with bit-wise shifter and adder operations. Moreover, to reduce the error of approximation, an error-reduction method is proposed based on partitioning approximation error into M segments and error-reduction factors are obtained by averaging the errors of each segment. We first present a mathematical formulation of the proposed method. Suppose two N-bit unsigned integers A and B, which can be represented as:

$$A = \sum_{i=0}^{N-1} 2^{i} a_{i} , B = \sum_{i=0}^{N-1} 2^{i} b_{i} \quad a_{i} = b_{i} = \{0, 1\}$$
(1)

Assume the leading-one bit position of A and B are n_A and n_B , respectively. By factoring the 2^{n_A} and 2^{n_B} from the inputs operand binary representation shown in Eq.(1), we can rewrite this equation as:

$$A = 2^{n_A} * \left(1 + \sum_{i=0}^{N-1} 2^{i-n_A} a_i\right) = 2^{n_A} * (1+X)$$

$$a_i = \{0,1\}, 0 \le X < 1$$

$$B = 2^{n_B} * \left(1 + \sum_{i=0}^{N-1} 2^{i-n_B} b_i\right) = 2^{n_B} * (1+Y)$$

$$b_i = \{0,1\}, 0 \le Y < 1$$
(2)

The multiplication result of A by B is calculated based on Eq. (3).

$$M_{ACC} = A * B = 2^{n_A} * (1 + X) * 2^{n_B} * (1 + Y)$$

= 2^{n_A+n_B} * (1 + X + Y + X * Y) (3)

Where, M_{ACC} represents the result of accurate multiplication. To perform multiplication using the truncating method, the approximate result of multiplication is calculated based on Eq. (4).

$$M_{AppR} = A * B \sim 2^{n_A + n_B} \tag{4}$$

Where, M_{AppR} represents the result of truncated approximate multiplication. Based on Eq. (3), the time and energy consumption are heavily dominated by calculating the terms of (X + Y + X * Y) for accurate multiplication. In order to improve the speed of computation, we can truncate the X and Y to h bits. Moreover, we proposed a method to improve the computational time used to calculate the value of these terms. Adder and multiplication operations are required to calculate these terms accurately, in which multiplication is a nonlinear operation. We proposed a curve-fitting method to estimate the value of these terms using linear operations such as addition and shifting. In order to achieve better hardware performance, we estimate the error value based on Eq.(5).

$$X + Y + X * Y \sim \alpha * (X_h + Y_h) \tag{5}$$

Where X_h and Y_h represent the the X and Y with h bits width. For better illustration, Fig. 3a shows an example of the estimation method based on the curve-fitting method. In this figure, we assumed h = 3 (the width of X and Y equal to 3 bits), and estimated the terms of (X + Y + X * Y) with a linear approximated curve modelled by $1.407 * (X_h + Y_h)$, i,e, in Eq.(5) the value of $\alpha = 1.407$. In order to achieve better hardware performance with only adder and left or right bitwise shift, we estimate the value of Eq.(5) based on Eq.(6).



Figure 3. An Example of (a) Curve Fitting method (b) rounded value for efficient hardware based on Curve Fitting method

Note that according to the experiment, α is within the range varying between 1 and 2.

$$\alpha * (X_h + Y_h) \sim (1 + 2^{\Delta EE}) * (X_h + Y_h) = (X_h + Y_h) + 2^{\Delta EE} * (X_h + Y_h)$$
(6)

Where ΔEE is an integer number, we can obtained the estimated value by an adder operator and left or right bitwise shift. To find the ΔEE value, it is required to round the $\alpha - 1$ to powers of two $(2^{\Delta EE})$. For this example shown also in Fig. 3b, the rounded value ΔEE and estimated line for effective hardware is shown in Fig. 3b. It is noteworthy that the ΔEE is equal to -2. Hence, the result of proposed approximate multiplier with is obtained based on Eq.(7).

$$M_{AppP}(h) = A * B \sim 2^{n_A + n_B} * (1 + (X_h + Y_h) + 2^{\Delta EE} * (X_h + Y_h))$$
(7)

Where, $M_{AppP}(h)$ represents the result of the the proposed approximate multiplication of inputs operand with h bit-width. Furthermore, the proposed approximation method causes errors in the computed result of multiplication. So a solution must be found to compensate for the error of approximation. In the next subsection, we describe our proposed compensation for approximation error.

A. Proposed Error Compensation Method

The approximate multiplier error is calculated by Eq. (8).

$$Err = M_{Acc} - M_{AppP}(h) =$$

$$2^{n_A + n_B} * (1 + X + Y + X * Y) - 2^{n_A + n_B}$$

$$* (1 + (X_h + Y_h) + 2^{\Delta EE} * (X_h + Y_h)) =$$

$$2^{n_A + n_B} * (X + Y + X * Y) - 2^{n_A + n_B}$$

$$* ((X_h + Y_h) + 2^{\Delta EE} * (X_h + Y_h))) =$$

$$2^{n_A + n_B} * ((X + Y + X * Y) - ((X_h + Y_h)) + 2^{\Delta EE} * (X_h + Y_h)))$$

$$+ 2^{\Delta EE} * (X_h + Y_h)))$$
(8)

It is noteworthy that the proposed approximate multiplier error depends on the width value of X and Y, called h. The approximate multiplier error value with h = 3 for $X_h + Y_h$ is shown in Fig. 4. We can observe from Fig. 4 that the approximate multiplier's error value (EV) is different for each interval of $X_h + Y_h$. We can add the average error value of the approximate multiplier for each interval of $X_h + Y_h$ as an error-compensated term to the result of the approximate multiplier.



Figure 4. An Example of Error Value (EV) of proposed approximate multiplier

In order to obtain the error-compensated term, we segmented $X_h + Y_h$ into M partitions, and then we took the average from each interval of $X_h + Y_h$. Thus, for M partitions, we only need to compute and store M values. C_i is presented as the error-compensated term value for a given interval of segmented $X_h + Y_h$, where $i \in \{1, 2, ..., M\}$. We proposed to add error-compensated term value before scaling the approximate multiplier final results. Mathematically, the error-compensated approximate multiplier is obtained by Eq.(9)

$$M_{AppP}(h) = A * B \sim 2^{n_A + n_B} * (1 + (X_h + Y_h) + 2^{\Delta EE} * (X_h + Y_h) + C_i)$$
(9)

Where C_i represents the error-compensated term calculated offline before building the multiplier and storing M values in the look-up table (LUT). In the following subsection, we will explain in detail the hardware design of the approximate multiplier. Our proposed approximate multiplier is defined by scaleTRIM (h,M), where h is the bit-width of X and Y, and M is the number of segmented intervals of $X_h + Y_h$.

B. Proposed Hardware Design

The block diagram of the hardware design of our proposed approximate multiplier is shown in Fig. 5a. First, the absolute value of the inputs operand is evaluated then the absolute values are fed into the Leading One Detector (LOD) block 5b. Furthermore, the LOD block determines the position of the absolute values leading to one bit. The LOD block can be implemented by : (1) implementing the logic [11], or (2) using look-up tables (LUTs) [20]. For some applications, including DNN, LUTs are a severe bottleneck because they increase memory usage. Therefore, the LOD block is implemented by logic. The output of the LOD block is represented by n_A and n_B , showing the position of absolute values of inputs' leading one bits. Also, the absolute value of inputs and inputs' LODs are fed into barrel shifters to generate the next bits of inputs LOD, which X and Y represent. Next, the truncated forms of the X and Y are generated using the Truncation block. The output of this unit X_h and Y_h , which has h bits.

In the next step, X_h and Y_h are fed into the Arithmetic unit 5c. First, the X_h and Y_h are added to the Arithmetic unit. Next, the added X_h and Y_h is bit-wise shifted with the amount that is calculated based on a curve fitting calculation in preprocessing. In order to decrease the error of the approximate multiplier, the compensated block generates the value added to the Arithmetic unit's output. The compensated values are calculated offline in pre-processing and stored in *M*-sized lookup-table (LUT). The values are stored as read-only hardwired



Figure 5. The hardware design of scaleTRIM

constants without the use of memory. Furthermore, the value for compensating the error is selected based on added X_h and Y_h value by $M \times 1$ multiplexer. In the last step, the result of added compensated unit and arithmetic unit is bit-wise shifted with the amount resulting from adding the LODs of the inputs operand.

Error-configurability: The proposed multiplier is error configurable by parameters of h and M. The parameter of h is used to truncate the input operands' low significant bits (LSBs). Truncating the input operands from N - 1 bits to h bits reduces the size of adders and bit-width shifters. Hence, design metrics such as area, delay, and power decrease, while output error increases. Additionally, The parameter of M is used to compensate for the error of the proposed approximate multiplier. Higher M requires a bigger multiplexer, which increases hardware overhead and reduces approximation error. Therefore, these two parameters (h and M) provided various trade-offs between accuracy and efficiency.

IV. RESULTS

In this section, we examine the scaleTRIM in terms of accuracy and efficiency, i.e., area, delay and energy. Therefore, we develop the software and hardware implementation of scaleTRIM. We compare the proposed approximate multiplier with several state-of-the-art approximate multipliers such as DRUM [8], DSM [13] and TOSAM [20]. For error analysis, we developed the scaleTRIM behavioral simulation model with PYTHON. The error metrics such as mean, max and variance of absolute relative error distance (ARED) were used to report the accuracy of scaleTRIM. Absolute relative errors are obtained by Eq.(10). The mean and standard deviation (std) of ARED and relative error (RED) are known as MARED, StdARED, MRED and StdRED, respectively. All error metrics are in percentage.

$$ARE = \left|\frac{M_{AppP}(h) - M_{Acc}}{M_{Acc}}\right| \tag{10}$$

Where M_{Acc} and $M_{AppP}(h)$ represent the exact and approximate values of the product result respectively.

We compare the efficiency of scaleTRIM and other stateof-the-art multipliers using Synopsys Design Compiler in a freepdk - 45nm Nangate technology. The metrics such as area, delay and power-delay product (PDP) are considered to gauge the compassion. Synthesis is performed using the "compile_ultra" command and targeting performance optimization. Post-synthesis timing simulations are performed using Modelsim to obtain precise switching activity. We simulate the examined multipliers for 100,000 random inputs to obtain accurate switching activity estimation. Then, Synopsys PrimeTime is used to calculate the power consumption.

1) Accuracy Comparison: The accuracy of 8-bit scaleTRIM with different configurations compared to the 8-bit state-of-the-art approximate multiplier is depicted in Fig 6a. Approximate multipliers such as DSM, DRUM, and TOSAM were implemented in different configurations to report the respective configurations' accuracy. Their papers describe these configurations in detail. All accuracy values in Fig. 6a are in percentage. Our evaluations depict that the MARED and StdARED values of scaleTRIM have improved compared to other approximate multipliers with the same truncation bits width. For example, the MARED and StdARED of scaleTRIM(4, 8) (see pointer b in Fig.6a) improved about 25% and 30% compared to the TOSAM(1, 4)(see pointer a in Fig.6a), respectively. Moreover, the StdRED values of scaleTRIM are lower than those of other works with the same truncation's bits width.

2) *Hardware Comparison:* The efficiency results of scaleTRIM and other state-of-the-art works in terms of power, delay, area, and power-delay product (PDP) are shown in Fig. 6b.

In Fig. 6b, we can observe that 8-bit scaleTRIM achieves lower area and power in most configurations with the same truncation's bit-width. For instance, scaleTRIM(5,0) (see pointer b in Fig.6b) improve the area and power about 7.5%and 6.5% in compared to TOSAM(1,5) (see pointer a in Fig.6b), respectively. However, the delay of scaleTRIM compared to TOSAM has higher values since the TOSAM used LUT-based LODs to find the position of the leading-one.

3) Design-space Comparison: To show the efficiency of scaleTRIM as an aspect of the design trade-off, we present the results of 8-bit and 16-bit scaleTRIM in the form of design space in Figs. 7 and 8. We depict the design space of the scaleTRIM based on the two design parameters of h and M in terms of area and power versus MARED. By noting the design space, we conclude that the scaleTRIM fall into Pareto optimal points. Hence, scaleTRIM offers better accuracy and efficiency in comparison with state-of-the-art works.

4) Applied scaleTRIM in CNN: We applied the proposed approximate multiplier in a VGG19, Resnet 18, and Resnet 50 used for Cifar10 data set and Lenet 5 used for Mnist data set. Fig. 9 compares the accuracy of different CNN architectures for the Mnist and Cifar10 datasets using approximate multipliers to their baseline accuracy using accurate multipliers. For





Figure 6. Accuracy and Efficiency of 8-bit Approximate Multipliers



Figure 7. Design space of comparison the 8-bit scaleTRIM with the state-of-the-art



Figure 8. Design space of comparison the 16-bit scaleTRIM with the state-of-the-art

implementing the proposed approximate multiplier in different CNN architecture, we used the Adapt: Fast Emulation of Approximate DNN Accelerators in PyTorch [3] to give the accuracy result of different CNN architecture.

The evaluation shows that the accuracy of CNN with scaleTRIM(4,4) is almost similar to that of CNN with an accurate multiplier. Hence, scaleTRIM has a negligible effect on the accuracy of CNN.



Figure 9. Comparison of accuracy of different CNN architecture used for Mnist and Cifar10 dataset by using an accurate and some configuration of 8-bit scaleTRIM multiplier

V. CONCLUSIONS

scaleTRIM is a new scalable integer approximate multiplier that utilizes the compensating unit to reduce the error of approximation. It designs based on truncation and linearization. First, the input operands are truncated to h bits based on their leading one-bit position. Then, we present a curve fitting method to fit the product term to the linear function based on their summation. Due to truncation and linearization, the accuracy of output is dropped. Therefore, an error-reduction method is proposed. The approximation error is partitioned into M segments, and error-reduction factors are obtained by averaging the errors of each segment. The obtained errorreduction factors are stored in the LUT to reduce the hardware overhead. scaleTRIM offers better error metrics, such as mean absolute relative error (MARED), compared to other state-ofthe-art approximate multipliers. Furthermore, results show that compared to different state-of-the-art approximate multipliers, scaleTRIM falls into Pareto optimal points in design space. Moreover, employing scaleTRIM in DNN demonstrates that using scaleTRIM in DNN has negligible impact on DNN accuracy.

ACKNOWLEDGEMENT

This research is partly funded through the ASPIRE AARE Grant (AARE20-327, S1561) on "Towards Extreme Energy Efficiency through Cross-Layer Approximate Computing".

REFERENCES

- Omid Akbari et al. "Dual-Quality 4:2 Compressors for Utilizing in Dynamic Accuracy Configurable Multipliers". In: *IEEE Transactions on Very Large Scale Integration (VLSI) Systems* 25.4 (2017), pp. 1352–1361. DOI: 10.1109/TVLSI. 2016.2643003.
- [2] Mohammad Saeed Ansari, Bruce F. Cockburn, and Jie Han. "An Improved Logarithmic Multiplier for Energy-Efficient Neural Computing". In: *IEEE Trans*actions on Computers 70.4 (2021), pp. 614–625. DOI: 10.1109/TC.2020.2992113.
- [3] Dimitrios Danopoulos et al. "AdaPT: Fast Emulation of Approximate DNN Accelerators in PyTorch". In: *IEEE Transactions on Computer-Aided Design of Integrated Circuits and Systems* (2022), pp. 1–1. DOI: 10.1109/TCAD.2022. 3212645.
- [4] Darjn Esposito et al. "On the use of approximate adders in carry-save multiplieraccumulators". In: 2017 IEEE International Symposium on Circuits and Systems (ISCAS). 2017, pp. 1–4. DOI: 10.1109/ISCAS.2017.8050437.
- [5] Bao Fang et al. "Approximate multipliers based on a novel unbiased approximate 4-2 compressor". In: *Integration* 81 (2021), pp. 17–24.
 [6] Ebrahim Farahmand et al. "High performance and optimal configuration of the second se
- [6] Ebrahim Farahmand et al. "High performance and optimal configuration of accurate heterogeneous block-based approximate adder". In: arXiv preprint arXiv:2106.08800 (2021).
- [7] Muhammad Abdullah Hanif, Rehan Hafiz, and Muhammad Shafique. "Error resilience analysis for systematically employing approximate computing in convolutional neural networks". In: 2018 Design, Automation & Test in Europe Conference & Exhibition (DATE). 2018, pp. 913–916. DOI: 10.23919/DATE. 2018.8342139.
- [8] Soheil Hashemi, R. Iris Bahar, and Sherief Reda. "DRUM: A Dynamic Range Unbiased Multiplier for approximate applications". In: 2015 IEEE/ACM International Conference on Computer-Aided Design (ICCAD). 2015, pp. 418–425. DOI: 10.1109/ICCAD.2015.7372600.
- [9] Mohsen Imani et al. "ApproxLP: Approximate Multiplication with Linearization and Iterative Error Control". In: 2019 56th ACM/IEEE Design Automation Conference (DAC). 2019, pp. 1–6.
- [10] Honglan Jiang et al. "A review, classification, and comparative evaluation of approximate arithmetic circuits". In: ACM Journal on Emerging Technologies in Computing Systems (JETC) 13.4 (2017), pp. 1–34.
- [11] K. Kunaraj and R. Seshasayanan. "Leading one detectors and leading one position detectors - An evolutionary design methodology". In: *Canadian Journal of Electrical and Computer Engineering* 36.3 (2013), pp. 103–110. DOI: 10.1109/ CJECE.2013.6704691.
- [12] John N. Mitchell. "Computer Multiplication and Division Using Binary Logarithms". In: *IRE Transactions on Electronic Computers* EC-11.4 (1962), pp. 512– 517. DOI: 10.1109/TEC.1962.5219391.
- [13] Srinivasan Narayanamoorthy et al. "Energy-Efficient Approximate Multiplication for Digital Signal Processing and Classification Applications". In: *IEEE Transactions on Very Large Scale Integration (VLSI) Systems* 23.6 (2015), pp. 1180–1184. DOI: 10.1109/TVLSI.2014.2333366.
- [14] Semeen Rehman et al. "Architectural-space exploration of approximate multipliers". In: 2016 IEEE/ACM International Conference on Computer-Aided Design (ICCAD). IEEE. 2016, pp. 1–8.
- [15] Hassaan Saadat, Haseeb Bokhari, and Sri Parameswaran. "Minimally Biased Multipliers for Approximate Integer and Floating-Point Multiplication". In: *IEEE Transactions on Computer-Aided Design of Integrated Circuits and Systems* 37.11 (2018), pp. 2623–2635. DOI: 10.1109/TCAD.2018.2857262.
- [16] Hassaan Saadat et al. "REALM: Reduced-Error Approximate Log-based Integer Multiplier". In: 2020 Design, Automation & Test in Europe Conference & Exhibition (DATE). 2020, pp. 1366–1371. DOI: 10.23919/DATE48585.2020. 9116315.
- [17] Muhammad Shafique et al. "Cross-layer approximate computing: From logic to architectures". In: Proceedings of the 53rd Annual Design Automation Conference. 2016, pp. 1–6.
- [18] Salim Ullah et al. "High-performance accurate and approximate multipliers for fpga-based hardware accelerators". In: *IEEE Transactions on Computer-Aided Design of Integrated Circuits and Systems* 41.2 (2021), pp. 211–224.
- [19] Shaghayegh Vahdat et al. "LETAM: A low energy truncation-based approximate multiplier". In: *Computers & Electrical Engineering* 63 (2017), pp. 1–17. ISSN: 0045-7906. DOI: https://doi.org/10.1016/j.compeleceng.2017.08.019.

- [20] Shaghayegh Vahdat et al. "TOSAM: An Energy-Efficient Truncation- and Rounding-Based Scalable Approximate Multiplier". In: *IEEE Transactions on Very Large Scale Integration (VLSI) Systems* 27.5 (2019), pp. 1161–1173. DOI: 10.1109/TVLSI.2018.2890712.
- [21] Swagath Venkataramani et al. "Approximate computing and the quest for computing efficiency". In: 2015 52nd ACM/EDAC/IEEE Design Automation Conference (DAC). IEEE. 2015, pp. 1–6.
- [22] Reza Zendegani et al. "RoBA Multiplier: A Rounding-Based Approximate Multiplier for High-Speed yet Energy-Efficient Digital Signal Processing". In: *IEEE Transactions on Very Large Scale Integration (VLSI) Systems* 25.2 (2017), pp. 393–401. DOI: 10.1109/TVLSI.2016.2587696.
- [23] Georgios Zervakis et al. "Design-Efficient Approximate Multiplication Circuits Through Partial Product Perforation". In: *IEEE Transactions on Very Large Scale Integration (VLSI) Systems* 24.10 (2016), pp. 3105–3117. DOI: 10.1109/TVLSI. 2016.2535398.