Boosting generation rate of squeezed single-photon states by generalized photon subtraction

Hiroko Tomoda,¹ Akihiro Machinaga,¹ Kan Takase,^{1, 2} Jun Harada,¹ Takahiro Kashiwazaki,³ Takeshi Umeki,³ Shigehito Miki,⁴ Fumihiro China,⁴ Masahiro Yabuno,⁴ Hirotaka Terai,⁴ Daichi Okuno,¹ and Shuntaro Takeda^{1, *}

¹Department of Applied Physics, School of Engineering,

The University of Tokyo, 7-3-1 Hongo, Bunkyo-ku, Tokyo 113-8656, Japan

Quantum Computing, 2-1 Hirosawa, Wako, Saitama 351-0198, Japan

Morinosato Wakamiya, Atsugi, Kanagawa 243-0198, Japan

 $^{4}Advanced \ ICT \ Research \ Institute, \ National \ Institute \ of \ Information \ and$

Communications Technology, 588-2 Iwaoka, Nishi, Kobe 651-2492, Japan

(Dated: May 1, 2024)

In optical quantum information processing with continuous variables, optical non-Gaussian quantum states are essential for universal and fault-tolerant quantum computation. Experimentally, their most typical generation method is photon subtraction (PS) where single-photon detection by an on/off detector probabilistically heralds the generation of squeezed single-photon states. In PS, however, trying to avoid unwanted multi-photon detection inevitably limits the generation rate, hindering the application of squeezed single-photon states. Here, we theoretically show that generalized photon subtraction (GPS), a simple extension of PS, can improve the generation rate while maintaining the quality of the generated states. Furthermore, we experimentally demonstrate the generation rate improvement for 2 dB- and 4 dB-squeezed single-photon states compared to PS, by more than one order of magnitude particularly for the case of 2 dB. Our results will accelerate the application of squeezed single-photon states to more advanced quantum information protocols.

I. INTRODUCTION

Thus far, quantum information processing (QIP) has been implemented with various physical systems, but optical systems are one of the reasonable choices due to their high-speed operation at room temperature [1]. In particular, the approach based on optical continuous variables (CVs) [2–4] offers advantageous technologies for QIP, such as deterministic entanglement generation [5, 6] and quantum gates [7–10]. Moreover, optical CV QIP can potentially implement fault-tolerant QIP in a hardware-efficient way by bosonic codes [11–15], which encode one logical qubit into only one mode by utilizing the infinite-dimensional Hilbert space of harmonic oscillators.

In such optical CV QIP, non-Gaussian states are essential as auxiliary states for universal quantum computation [16], quantum error correction [17], entanglement distillation [18–20], and other applications. Moreover, they are used as bosonic qubits for fault-tolerant CV QIP [11–15]. Optical non-Gaussian states have been experimentally generated by the heralding schemes with a photon detector, and the typical generation method is the probabilistic generation of squeezed single-photon states with photon subtraction (PS) [21].

In this scheme, we tap squeezed states by a beam splitter (BS), and detecting a reflected single photon heralds the squeezed single-photon states in the transmission side (Fig. 1(a)). These squeezed single-photon states are approximate states of small-amplitude Schrödinger's cat states and have applications in quantum computation and quantum metrology [22]. Moreover, such PS underlies the generation protocols of large-amplitude Schrödinger's cat states [23–25] and Gottesman-Kitaev-Preskill (GKP) states [26, 27], thus playing a key role in fault-tolerant CV QIP [11–15].

However, in the typical PS with an on/off detector [28– 33], the tap ratio should be set nearly zero to reduce the probability of undesired multi-photon detection, which cannot be distinguished from desired single-photon detection. As a result, the photon detection rate, namely the generation rate of the squeezed single-photon states, is limited. Recently GKP states were generated from two squeezed single-photon states [34] based on the generation protocol in Refs. [26, 27], but the generation rate was limited to only 10 Hz at a single-step breeding operation, whose extension to multiple steps is now required. In order to overcome such limitations, improving the generation rate of squeezed single photon states is essential. For this purpose, several generation methods have been theoretically proposed [35, 36] and one method to use photon addition, instead of PS, was experimentally demonstrated recently [37]. However, the demonstrated method requires in-line optical non-linear crystal acting on squeezed states, inevitably introducing a coupling loss on the fragile squeezed states.

In this paper, we theoretically and experimentally demonstrate the generation rate improvement by adopting generalized photon subtraction (GPS) [38]. GPS is extended from PS by adding one orthogonally-squeezed input state to the PS configuration (Fig. 1(b)). In GPS

²Optical Quantum Computing Research Team, RIKEN Center for

³NTT Device Technology Labs, NTT Corporation, 3-1,

^{*} takeda@ap.t.u-tokyo.ac.jp

with the on/off detector, we find that this additional squeezing parameter enables us to more efficiently generate the squeezed single-photon states with comparable quality to PS. To analytically reveal that, we first model PS and GPS and derive the qualities and generation rates of the heralded states in both cases. We then quantitatively evaluate how much GPS can increase the generation rate while maintaining the same quality. In addition, we experimentally confirm the validity of such calculations for the generation of 2 dB- and 4 dB-squeezed single-photon states. Their generation rates are significantly boosted, by more than one order of magnitude particularly for 2 dB. These results will accelerate the applications of squeezed single-photon states, which have been limited in PS.

This paper is organized as follows. In Sec. II, we theoretically analyze both PS and GPS in each case of using a photon-number resolving detector (PNRD) and an on/off detector. As for the case with the on/off detector, we mathematically clarify the relationship between the quality and generation rate, and numerically evaluate the generation rate improvement by GPS compared with PS. In Sec. III, we describe our experimental setup applicable to both PS and GPS. In Sec. IV, we first generate various quantum states to present the general characteristics of GPS and verify our theoretical model. Next, we generate the squeezed single-photon states with the same squeezing level by both PS and GPS to experimentally validate our theoretical conclusion about the generation rate improvement. In Sec. V, we summarize our discussion.

II. THEORY & NUMERICAL RESULTS

Figure 1 is the configuration of PS and GPS discussed in this paper. It has been known that PS with an on/off detector has a trade-off relationship between the quality and generation rate of the heralded states [39]. In this section, we theoretically show the trade-off improvement by adopting GPS.

First, we qualitatively explain how the trade-off arises. In PS of Fig. 1(a), since an on/off detector cannot resolve the number of photons, it heralds the mixed states of single- and multi-photon subtracted states. Hence the transmissivity T of the BS should be set to $T \approx 1$ to reduce contamination of the quantum states by unwanted multi-photon detection. However, this condition inevitably decreases the photon detection rate, corresponding to the generation rate. On the other hand, we can increase the photon detection rate by decreasing T, while the quality of the squeezed single-photon state gets worse due to the larger multi-photon detection effect in this case. Thus there is a trade-off relationship between the quality and generation rate in PS. In contrast, in GPS of Fig. 1(b), the additional orthogonally-squeezed state realizes generating the squeezed single-photon states with the comparable quality to PS even by using lower trans-



FIG. 1. Generation method of squeezed single-photon states. (a) Photon subtraction (PS). (b) Generalized photon subtraction (GPS). Both PS and GPS in these two subfigures use an on/off detector causing the trade-off, which we discuss in this paper.

Squeezed single

photon state

Undesired states by

multi-photon detection

value

Additional squeezed state

missivity. As a result, more photons reach the on/off detector, and thereby the trade-off is improved.

In the following, we theoretically analyze the qualities and generation rates in both PS and GPS and finally discuss the trade-off difference between these two generation methods.

A. PS and GPS with PNRD

Before considering PS and GPS with an on/off detector, we model the simpler case with a PNRD to derive the output states for various experimental parameters. This section is based on the more general discussion in Ref. [38].

Let us start the discussion using the model as illustrated in Fig. 2. We use $\hbar = 1$ throughout this paper, and define quadrature operators of two modes in Fig. 2 as \hat{x}_1 , \hat{x}_2 , \hat{p}_1 , and \hat{p}_2 . A two-mode covariance matrix V is introduced by using $\hat{q} = (\hat{x}_1, \hat{x}_2, \hat{p}_1, \hat{p}_2)^{\top}$:

$$V_{ij} = \frac{1}{2} \left\langle \hat{q}_i \hat{q}_j + \hat{q}_j \hat{q}_i \right\rangle - \left\langle \hat{q}_i \right\rangle \left\langle \hat{q}_j \right\rangle. \tag{1}$$

We also define a squeezing operator for mode-*i* (*i* = 1, 2) as $\hat{S}_{i}^{\dagger}(r)\hat{x}_{i}\hat{S}_{i}(r) = \hat{x}_{i}e^{-r}$, $\hat{S}_{i}^{\dagger}(r)\hat{p}_{i}\hat{S}_{i}(r) = \hat{p}_{i}e^{r}$ and write an *n*-photon state in mode-*i* as $|n\rangle_{i}$.

First, we prepare two squeezed vacuum states $\hat{S}_1(r_1) |0\rangle_1$ and $\hat{S}_2(r_2) |0\rangle_2$, which are characterized by



FIG. 2. Schematic picture of our model. The projection operator of the single-photon detector depends on its detector type: the PNRD or the on/off detector.

a two-mode covariance matrix V_0 as

$$V_0 = \operatorname{diag}\left(\frac{e^{-2r_1}}{2}, \frac{e^{-2r_2}}{2}, \frac{e^{2r_1}}{2}, \frac{e^{2r_2}}{2}\right).$$
(2)

In general, any value for two squeezing parameters r_1 and r_2 can be chosen in GPS, and PS corresponds to GPS where r_1 or r_2 is equal to zero. However, for later convenience, we here define GPS as the case with $r_1r_2 <$ 0 and PS as the case with $r_2 = 0$.

This state is then input to a BS with a transmissivity of T = 1 - R, whose 4×4 transformation matrix U is written as

$$U = \begin{pmatrix} B & 0 \\ 0 & B \end{pmatrix}, \quad B = \begin{pmatrix} \sqrt{R} & \sqrt{T} \\ -\sqrt{T} & \sqrt{R} \end{pmatrix}.$$
 (3)

By using the above, the covariance matrix $V_{\rm G}$ of the BS output, which is a two-mode Gaussian state, is calculated as

$$V_{\rm G} = U V_0 U^{\top} = \begin{pmatrix} \sigma_x & 0\\ 0 & \sigma_p \end{pmatrix}.$$
 (4)

Here 2×2 matrices σ_x and σ_p are

$$\sigma_x = \frac{1}{2} \begin{pmatrix} Re^{-2r_1} + Te^{-2r_2} & \sqrt{RT}(-e^{-2r_1} + e^{-2r_2}) \\ \sqrt{RT}(-e^{-2r_1} + e^{-2r_2}) & Te^{-2r_1} + Re^{-2r_2} \end{pmatrix}$$
(5)
$$\sigma_z = \frac{1}{2} \begin{pmatrix} Re^{2r_1} + Te^{2r_2} & \sqrt{RT}(-e^{2r_1} + e^{2r_2}) \\ Re^{2r_1} + Te^{2r_2} & \sqrt{RT}(-e^{2r_1} + e^{2r_2}) \end{pmatrix}$$
(6)

$$\sigma_p = \frac{1}{2} \begin{pmatrix} Re^{2r_1} + Ie^{2r_2} & \sqrt{RI(-e^{2r_1} + e^{2r_2})} \\ \sqrt{RT}(-e^{2r_1} + e^{2r_2}) & Te^{2r_1} + Re^{2r_2} \end{pmatrix}, (6)$$

which satisfy the relationship: $\sigma_x \sigma_p = I/4$ (*I* is an identity matrix). Moreover, this BS output can be represented with a two-mode Wigner function $W_{\rm G}(\boldsymbol{q})$ where $\boldsymbol{q} = (x_1, x_2, p_1, p_2)^{\top}$ are quadratures. Given zero mean value for each quadrature throughout the process, $W_{\rm G}(\boldsymbol{q})$ is written [40] as

$$W_{\rm G}(\boldsymbol{q}) = \frac{1}{\pi^2} \exp\left[-\frac{1}{2}\boldsymbol{q}^{\top} V_{\rm G}^{-1} \boldsymbol{q}\right].$$
(7)

Here one of the BS output (mode-1) goes to the photon detector, which we call *trigger mode*. Then photon detection heralds the quantum state in the other side (mode-2), which we call *signal mode*.

Let us discuss the state heralded by the PNRD. The projection operator of single-photon detection on mode-1 $\hat{\Pi}_{n=1}$ is

$$\hat{\Pi}_{n=1} = |1\rangle_{11} \langle 1| \,. \tag{8}$$

When the single-photon detection occurs in mode-1, the density matrix of the heralded state in mode-2 $\hat{\rho}_{out}$ is written using that of the BS output $\hat{\rho}_{G}$ as

$$\hat{\rho}_{\rm out} = \frac{\text{Tr}_1\left(\hat{\Pi}_{n=1}\hat{\rho}_{\rm G}\hat{\Pi}_{n=1}\right)}{P_{n=1}},\tag{9}$$

where Tr_1 represents partial trace over mode-1 and single-photon detection probability $P_{n=1}$ is

$$P_{n=1} = \operatorname{Tr}\left(\hat{\Pi}_{n=1}\hat{\rho}_{\mathrm{G}}\right).$$
(10)

Then using the following Wigner function of $|n\rangle$:

$$W_n(x,p) = \frac{(-1)^n}{\pi} e^{-x^2 - p^2} L_n\left(2(x^2 + p^2)\right),$$

$$L_n(x) = \sum_{k=0}^n \binom{n}{k} \frac{(-1)^k}{k!} x^k \qquad (11)$$

$$(L_0(x) = 1, \ L_1(x) = -x + 1, \cdots),$$

we derive the Wigner function corresponding to $\hat{\rho}_{out}$ as

$$W_{\text{out}}(x_2, p_2) = \frac{2\pi}{P_{n=1}} \int_{-\infty}^{\infty} \int_{-\infty}^{\infty} dx_1 dp_1 W_1(x_1, p_1) W_{\text{G}}(x_1, x_2, p_1, p_2) = W_1 \left(e^{r_{\text{out}}} x_2, e^{-r_{\text{out}}} p_2 \right).$$
(12)

This result represents a squeezed single-photon state $\hat{S}_2(r_{\rm out}) |1\rangle_2$ with a squeezing parameter $r_{\rm out}$, which is written as

$$e^{r_{\text{out}}} = e^{r_1 + r_2} \sqrt{\frac{2\sigma_{x,11} + 1}{2\sigma_{p,11} + 1}}.$$
 (13)

Here $\sigma_{x,11}$ and $\sigma_{p,11}$ are the (1,1) components of σ_x in Eq. (5) and σ_p in Eq. (6), respectively. Whenever we choose three parameters r_1, r_2 , and T which realize the same r_{out} , the PNRD heralds the same pure squeezed single-photon state and only the single-photon detection probability $P_{n=1}$ in Eq. (10) depends on these parameters. The above discussion remains valid for GPS and PS $(r_2 = 0)$ and thus the use of the PNRD avoids the trade-off relationship in the ideal lossless situation, while the use of an on/off detector causes the trade-off as discussed in the next section.

B. PS and GPS with on/off detector

In this section, we quantitatively discuss the trade-off relationship in the case with the on/off detector by formulating the quality and generation rate of the heralded state. First, we define the projection operator of the on/off detector on mode-1 as

$$\hat{\Pi}_{\text{off}} = |0\rangle_{11} \langle 0|, \quad \hat{\Pi}_{\text{on}} = \hat{I} - |0\rangle_{11} \langle 0|, \quad (14)$$

where \hat{I} is an identity operator. Photon detection in mode-1 heralds a quantum state in mode-2 with the following density matrix $\hat{\rho}_{out}$:

$$\hat{\rho}_{\rm out} = \frac{\text{Tr}_1\left(\hat{\Pi}_{\rm on}\hat{\rho}_{\rm G}\hat{\Pi}_{\rm on}\right)}{P_{\rm on}} = \frac{\text{Tr}_1\hat{\rho}_{\rm G} - {}_1\langle 0|\hat{\rho}_{\rm G}|0\rangle_1}{1 - P_{\rm off}}.$$
 (15)

Here zero-photon detection probability P_{off} and photon detection probability P_{on} are

$$P_{\text{off}} = \text{Tr}\left(\hat{\Pi}_{\text{off}}\hat{\rho}_{\text{G}}\right), \ P_{\text{on}} = \text{Tr}\left(\hat{\Pi}_{\text{on}}\hat{\rho}_{\text{G}}\right) = 1 - P_{\text{off}}.$$
 (16)

From the density matrix $\hat{\rho}_{out}$ in Eq. (15), we can calculate the corresponding Wigner function $W_{out}(x_2, p_2)$ as

$$W_{\text{out}}(x_2, p_2) = \frac{1}{1 - P_{\text{off}}} \left[\int_{-\infty}^{\infty} \int_{-\infty}^{\infty} dx_1 dp_1 W_{\text{G}}(x_1, x_2, p_1, p_2) -2\pi \int_{-\infty}^{\infty} \int_{-\infty}^{\infty} dx_1 dp_1 W_0(x_1, p_1) W_{\text{G}}(x_1, x_2, p_1, p_2) \right].$$
(17)

We here specifically examine $W_{\text{out}}(0,0)$ as a quality indicator. This is because pure squeezed single-photon states have $W_{\text{out}}(0,0) = -1/\pi$, whereas $W_{\text{out}}(0,0)$ becomes larger as they get more contaminated by other heralded states or more deteriorated by losses. Moreover, this indicator can be calculated analytically and compared with the experimental results easily. In fact, it has been used for quality evaluation in previous experiments [28–33]. From Eq. (17), $W_{\text{out}}(0,0)$ is calculated to be

$$W_{\rm out}(0,0) = \frac{1}{\pi} \frac{\frac{1}{2\sqrt{\sigma_{p,11}\sigma_{x,11}}} - P_{\rm off}}{1 - P_{\rm off}},$$
(18)

and P_{off} is

$$P_{\text{off}} = \frac{2}{\sqrt{(2\sigma_{p,11}+1)(2\sigma_{x,11}+1)}}.$$
 (19)

We here used Eqs. (4)–(7), (11) and the relationship $\sigma_x \sigma_p = I/4$. Since the on/off detector mixes the desired squeezed single-photon state and other undesired states due to its incapability of distinguishing the number of photons, $W_{\rm out}(0,0)$ in Eq. (18) is larger than $-1/\pi$ at any parameters.

Now we analyze the relationship between the quality indicator $W_{\text{out}}(0,0)$ and the photon detection probability P_{on} for both PS and GPS, considering the practical scenario where we want to prepare the squeezed single-photon states with the specific squeezing level r_{out} . In the following, we examine $W_{\text{out}}(0,0)$ and P_{on} for various combinations of r_1, r_2 , and T where the same $\hat{S}_2(r_{\text{out}}) |1\rangle_2$ is heralded by the single-photon detection.

First, we discuss the case of using PS, which has only two parameters r_1 and T ($r_2 = 0$). Once we choose the transmissivity T, the input squeezing parameter r_1 is automatically determined by Eq. (13), and both $W_{\text{out}}(0,0)$



(a)

FIG. 3. Numerical results of trade-offs. (a) Trade-off comparison between PS and GPS. As for GPS, we plot the best trade-off obtained by optimizing the three parameters r_1, r_2 , and T, and this trade-off is independent of the output squeezing parameter r_{out} . (b) Impact of losses on the trade-off improvement. The black solid line and orange dashed line are trade-off lines in the case of $e^{-2r_{out}} = 2 \,\mathrm{dB}$ without losses, which are the same as those in (a). Addition of losses without changing other conditions shifts these two lines toward the black dotted line and the orange dot-dashed line, respectively. We include signal channel loss of 25% and trigger channel loss of 90% (equivalent to the loss values of our experimental setup, described later) in our simulations with the losses. The circle and square symbols indicate the example of

and $P_{\rm on}$ are obtained by Eqs. (16), (18), and (19). Then the relationship between $W_{\rm out}(0,0)$ and $P_{\rm on}$ is determined by changing T as a parameter. Figure 3(a) shows the numerical results of this relationship for different $r_{\rm out}$. We see a better trade-off between $W_{\rm out}(0,0)$ and $P_{\rm on}$ for higher $r_{\rm out}$.

how the losses displace the points that have the same quality

 $W_{\rm out}(0,0) = -0.25$ for PS and GPS in lossless situations as

indicated by arrows.

Next, considering GPS, where three parameters r_1 , r_2 , and T are tunable for the best trade-off as shown below,

we first reformat $W_{\text{out}}(0,0)$ in Eq. (18) to

$$W_{\rm out}(0,0) = \frac{1}{\pi} \frac{\frac{P_{\rm off}}{\sqrt{P_{\rm off}^2 - 2P_{\rm off}(s+s^{-1}) + 4}} - P_{\rm off}}{1 - P_{\rm off}}$$
(20)

by introducing a new parameter s:

$$s = e^{r_{\text{out}} - r_1 - r_2} > 0. \tag{21}$$

Here we suppose that the output squeezing parameter and photon detection probability are given by $r_{out} = r_c$ and $P_{on} = P_c$, respectively. From Eqs. (13), (18), (19) and 0 < T < 1, r_1 and r_2 should satisfy the following conditions:

$$\cosh r_1 \cosh r_2 = \frac{\cosh r_c}{1 - P_c},\tag{22}$$

$$(r_1 - r_c)(r_2 - r_c) < 0, (23)$$

and this derives the possible range of s as

$$\begin{cases} 0 < s < \exp\left[\operatorname{arcosh}\left(\frac{1}{1-P_c}\right)\right] & \text{if } r_c > 0\\ s > 0 & \text{if } r_c = 0 \\ s > \exp\left[-\operatorname{arcosh}\left(\frac{1}{1-P_c}\right)\right] & \text{if } r_c < 0 \end{cases}$$

We finally minimize $W_{\text{out}}(0,0)$ in Eq. (20) by changing the parameter s within the above range. Regardless of the values of r_c and P_c , we can minimize $W_{\text{out}}(0,0)$ at s = 1, where the specific combinations of r_1 , r_2 , and Tare determined by Eqs. (13) and (21). At such minimum point, Eq. (20) becomes

$$W_{\rm out}(0,0) = -\frac{1}{\pi} \frac{P_{\rm off}}{2 - P_{\rm off}} = -\frac{1}{\pi} \frac{1 - P_{\rm on}}{1 + P_{\rm on}},$$
 (25)

which is the best trade-off in GPS. This trade-off relationship is independent of the output squeezing parameter r_{out} , unlike PS. We plot the numerical result of this best trade-off in Fig. 3(a) and see that GPS (black solid line) achieves a better trade-off than PS (the other three lines). Furthermore, this improvement is theoretically valid at any r_{out} . GPS with three adjustable parameters r_1 , r_2 , and T can reach s = 1 as described above, while PS with only two parameters r_1 and T ($r_2 = 0$) cannot. Hence GPS achieves smaller $W_{out}(0,0)$ for the given P_{on} at any r_{out} ; in other words, GPS increases P_{on} for the same $W_{out}(0,0)$ at any r_{out} . Particularly in the weak output squeezing regimes, such as 2 dB, the photon detection probability P_{on} becomes approximately 10 times larger in GPS for the same quality $W_{out}(0,0)$.

So far we have discussed the ideal situation without optical losses such as propagation losses and inefficiencies of the on/off detector. Here we briefly mention the practical situation with these losses by using Fig. 3(b) as an example. In Fig. 3(b), the black solid line and orange dashed line are trade-off lines for $e^{-2r_{\text{out}}} = 2 \text{ dB}$, which are the same as those plotted in Fig. 3(a). In contrast, the

other two lines are obtained by using the same conditions as already mentioned two lines but including a certain amount of losses. The circle and square symbols in this figure indicate an example of how the losses displace the points that have the same quality $W_{\text{out}}(0,0) = -0.25$ for PS and GPS in lossless situations. By focusing on these symbols, we can qualitatively discuss the impact of the losses on $P_{\rm on}$, $W_{\rm out}(0,0)$, and consequently the trade-off line, as follows. In the typical experiment where we generate high-quality states with $W_{out}(0,0) < 0$, the multiphoton detection probability is small compared with the single-photon detection probability. Hence $P_{\rm on}$ decreases almost linearly with respect to the trigger channel loss in the photon detection side, and the trade-off lines of both PS and GPS shrink uniformly by the same scale (by almost a factor of 10 in Fig. 3(b)) along the horizontal axis. As for $W_{out}(0,0)$, their degradations are mainly determined by the signal loss. Additionally taking into consideration that the squeezed single-photon states, which are dominant in the heralded states, are degraded in the same way in both PS and GPS, $W_{out}(0,0)$ of the heralded states by both PS and GPS increase by approximately the same degree. Thereby the trade-off lines of both PS and GPS are shifted almost similarly along both the horizontal and vertical axes. As a result, the generation rate is increased by GPS as well even when the effect of losses is included, and the degree of this increase does not change. Note that the losses slightly change the combinations of the parameters for the best trade-off in GPS, but at least the difference is expected to be small under the amount of losses we consider in this work. Analytically deriving these combinations is left for future work.

III. EXPERIMENTAL SETUP & DATA ACQUISITION

To experimentally prove our theoretical conclusion in Sec. II, we constructed the setup as shown in Fig. 4, which was applicable to both PS and GPS with an on/off detector. We use a continuous-wave laser with the center wavelength at 1545 nm. Its second-harmonic light at wavelength of 773 nm is divided and injected into two fibercoupled waveguide optical parametric amplifier (OPA) modules [41] as the pump light to generate squeezed states. Here we have variable attenuators (Var. Att.-1 and Var. Att.-2) before each OPA to change the input pump power that determines the squeezing level.

Then the output squeezed states are interfered with each other in free space by a variable beam splitter (VBS). This VBS consists of two polarization beam splitters (PBSs) and one half-wave plate (HWP), so its transmissivity can be set arbitrarily by changing the rotation angle of the HWP manually.

Next, each output of this VBS goes to a homodyne measurement and a photon detection system, respectively. The light to the homodyne measurement sys-



FIG. 4. Experimental setup. CW, continuous wave; SHG, second harmonic generator; AOM, acousto-optic modulator; Var. Att., variable attenuator; OPA, optical parametric amplifier; EOM, electro-optic modulator; SNSPD, superconducting nanostrip single-photon detector; LO, local oscillator; BS, beam splitter; LPF, low-pass filter; HPF, high-pass filter.

tem corresponds to the signal mode, and its quadrature amplitude is measured with the homodyne detector. Then the detector's output is acquired with the oscilloscope after electrical filtering. The other output of the VBS, corresponding to the trigger mode, first goes through the spectral filtering system. This filtering restricts the frequency region of the detected photons, and consequently limits that of the heralded squeezed singlephoton states within our homodyne measurement bandwidth, $\sim 200 \text{ MHz}$. Our filtering system has three parts: a dielectric multi-layer filter with half width at half maximum (HWHM) of 0.5 nm, a triangle cavity with HWHM of 2.8 MHz and free spectral range (FSR) of 4.8 GHz, and a Fabry-Perot cavity with HWHM of 160 MHz and FSR of 162 GHz. This combination ensures that only the trigger light within HWHM of 2.8 MHz around the center wavelength of the laser transmits the filtering system. Then this filtered trigger light goes to a superconducting nanostrip single-photon detector (SNSPD) [42] after the polarization controller. The detection efficiency of this SNSPD is $\sim 65\%$, and the dark count rate is $\sim 25 \text{ cps}$ (not

corrected by the ratio of the measurement period, which is described later) at the typical bias current applied to the nanostrip.

In Fig. 4, there is other miscellaneous apparatus required for optical phase control. To generate and observe phase-sensitive quantum states, we have to fix the relative phases between the pump light and the local oscillator (LO) light of the homodyne measurement. We alternately repeat the phase control period and measurement period at 2 kHz. During the control period, we input additional classical light at 1545 nm, called *probe* light, into each OPA. The frequencies of this probe light are shifted by acousto-optic modulators (AOM-1, AOM-2a, and AOM-2b) from the original frequency for the purpose of phase locking with a coherent control sideband method [43, 44]. We lock the relative phases with fiber stretchers and a piezo-mounted mirror so that we measure the anti-squeezed quadrature of the OPA-1's output squeezed state by default. This probe light is blocked by optical switches (Switch-2a and Switch-2b) before the SNSPD. We also input additional classical light into the filtering cavities and fix each cavity length by Pound-Drever-Hall method [45] so that its resonant frequency matches the incoming light frequency.

During the measurement period, we block the probe light and cavity-locking light by turning off all the AOMs and Switch-1. Then we shift the LO phase using an electro-optic modulator (EOM-2) from the locked phase to the target phase for the measurement. Meanwhile, we turn on Switch-2a and Switch-2b to allow the trigger photon to reach the SNSPD.

Using the above setup, we performed the experiments of PS and GPS as follows. We first adjusted the pump power and the transmissivity of the VBS to the target conditions $(r_1, r_2, \text{ and } T)$. Then we obtained the photon detection rate, which corresponds to P_{on} , by measuring the photon detection signal from the SNSPD with a frequency counter. Meanwhile, we acquired the homodyne detector's output using the photon detection signal as a trigger to evaluate the quality of the heralded states. We measured 5000 time waveforms of quadratures at 12 phases in 15° increments. Then we calculated the quadrature amplitude of a wave-packet mode which was automatically determined by the experimental setup [46]. Its temporal mode function is

$$f(t) \propto \begin{cases} e^{2\pi\gamma_1(t-t_0)} - e^{2\pi\gamma_2(t-t_0)} & \text{if } t \le t_0 \\ 0 & \text{if } t > t_0 \end{cases}$$
(26)

without normalization. Theoretically, the parameters γ_1 and γ_2 are determined by the HWHM of two filter cavities before the SNSPD, and t_0 is the temporal parameter that corresponds to the photon detection timing. In the data analysis, they were optimized based on the experimental results ($\gamma_1 = 2.8$ MHz and $\gamma_2 = 80$ MHz). Finally, we reconstructed the Wigner functions from these quadratures using the maximum likelihood estimation method [47].

IV. EXPERIMENTAL RESULTS & DISCUSSION

In this section, we show the experimental results of GPS performed with the setup of Fig. 4.

A. Comparison between theoretical and experimental GPS

First, we validate our theoretical model of GPS in Sec. II by comparing experimentally generated states with the corresponding simulation results. We used three combinations of r_1 and r_2 to observe how the heralded states and photon detection rates depend on the BS transmissivity T.

Figure 5 is the comparison between the simulation and experimental results of the Wigner functions. Figures 5(a), 5(b), and 5(c) are obtained at the following combinations of two input squeezing levels e^{-2r_1} and e^{-2r_2} : (a) 3 dB and -3 dB (symmetric condition,

 $|r_1| = |r_2|$, (b) 2.8 dB and -0.78 dB (weakly asymmetric condition), and (c) $4.7 \,\mathrm{dB}$ and $-0.67 \,\mathrm{dB}$ (strongly asymmetric condition). Within each subfigure, the different columns represent the results at various BS transmissivities with 0.1 intervals. We plot the experimental results in the lower rows, and the upper and central rows are the corresponding simulation results without and with the losses inherent in our experimental setup, respectively. In our simulations, we include the signal channel loss of 25%and the trigger channel loss of 90%. The breakdowns of the signal losses are shown in Table I. Among them, the fake photon detection triggers are divided into two types: dark counts of the SNSPD and undesired detections of slight reflection of the LO light from the surface of photodiodes in the homodyne detector. The former counts do not change among different experiments, $\sim 25 \,\mathrm{cps}$. In contrast, the latter counts depend on experimental conditions such as BS transmissivity and also fluctuate over time during the measurement. Hence the typical value is written in the table. On the other hand, the trigger channel loss involves the propagation loss between the VBS and the SNSPD, $\sim 80\%$, and the detection efficiency of the SNSPD, $\sim 65\%$.

TABLE I. Loss budget of signal path

Item	Typical value
Waveguide OPA	9%
Propagation (total)	5%
Spatial mode mismatch	4%
Inefficiency of photodiodes	1%
Circuit noise of homodyne detector	1%
98 kHz cutoff HPF	3%
Fake photon detection triggers of SNSPD	$\sim 5\%$
Total	$\sim 25\%$

Figure 5 shows that our experimental Wigner functions visually agree well with the simulations. Moreover, this figure clearly illustrates the general characteristics of GPS with the on/off detector. In the simulations without losses in Fig. 5(a), W(0,0) is minimized at T = 0.5 and the negative values of W(0,0) are gradually fading away as the transmissivity is set closer to T = 0 or 1. The squeezing degree and direction of the Wigner function of the generated states also change depending on T. In Figs. 5(b) and 5(c), we can see a similar trend, but with different optimal values of T which minimize W(0,0) depending on the combination of r_1 and r_2 . This trend is observed also in the simulations with losses and experiments. It is a distinctive feature of GPS compared to conventional PS, where W(0,0) changes monotonically with respect to T and is not minimized within 0 < T < 1. Such difference results from one additional degree of freedom r_2 in GPS, which also contributes to the trade-off improvement discussed in Sec. II.

For a more quantitative assessment, we graphically show how the values of W(0,0) as a quality indicator depend on T in the left column of Fig. 6. Here the plot-







FIG. 5. Wigner functions of the quantum states generated by various combinations of three parameters r_1 , r_2 , and T. Three subfigures correspond to the following combinations of input squeezing levels: (a) $e^{-2r_1} = 3.0 \,\mathrm{dB}$, $e^{-2r_2} = -3.0 \,\mathrm{dB}$, (b) $e^{-2r_1} = 2.8 \,\mathrm{dB}$, $e^{-2r_2} = -0.78 \,\mathrm{dB}$, (c) $e^{-2r_1} = 4.7 \,\mathrm{dB}$, $e^{-2r_2} = -0.67 \,\mathrm{dB}$.



FIG. 6. Quantitative evaluation of quantum states shown in Fig. 5. (a)–(c) Quality W_{00} of quantum states corresponding to Figs. 5(a)–5(c), respectively. (d)–(f) Photon detection rates corresponding to Figs. 5(a)–5(c), respectively. We plot simulation results of photon detection probabilities P_{on} by multiplying appropriate scaling constants C, which we obtain through the following fitting. In each subfigure, we obtained nine values of the ratio between the experimental detection rate and the corresponding P_{on} , and then used their average for C. The following is the values of C in each subfigure: (d) 1.47×10^6 , (e) 1.31×10^6 , and (f) 1.43×10^6 . Here the differences among these scaling constants are attributed to different trigger channel loss values in different measurements. All the error bars indicate the standard errors.

ted values W_{00} are defined as follows:

$$W_{00} = \begin{cases} \min W(x, p) & \text{if } W(0, 0) < 0\\ W(0, 0) & \text{if } W(0, 0) \ge 0 \end{cases},$$
(27)

neglecting the small displacements of the minimum points of the experimental Wigner functions, which are caused by some experimental reasons. Their errors plotted in Fig. 6 were calculated by Fisher information matrix [48]. The behavior of W_{00} in relation to T is wellmatched between the simulations and experiments, for example, in terms of where they reach their minimum. This consistency ensures the validity of our theoretical model. Note that the slight deviation between the experimental and simulation results of W_{00} is mainly attributed to the fluctuation of the signal loss from 25%.

As for photon detection rates, we show how they depend on T in the right column of Fig. 6. We plot their averages for 1 min with their standard errors. These are raw values that are not corrected by the duty cycle of the measurement period, 13%. We also plot the simulation results by multiplying the photon detection probabilities $P_{\rm on}$, defined by Eqs. (16) and (19), by appropriate scaling constants (details in the caption of Fig. 6). We first find that the experimental rates closely follow the simulation curves. Then, we see a drastic dependence of photon detection rates on T in Figs. 6(e) and 6(f), where the input squeezing levels are asymmetric. In such cases, the larger portion of the squeezed state with the higher squeezing level of the two input reaches the on/off detector, the higher the photon detection rate becomes. Additionally, the photon detection rates do not converge to zero even at $T \to 1$, which is a different characteristic from PS.

Thus by comparing the experimental results with the simulation results, we validated our theoretical model of GPS. This consequently ensures our discussion of the trade-off improvement in Sec. II, and then it is experimentally confirmed in the next section.

B. Improvement of trade-off by GPS

Finally, we experimentally prove our theoretical derivation that GPS can improve the trade-off between the quality and photon detection rate compared with PS. We generated 2 dB- and 4 dB-squeezed single-photon states using different experimental parameters r_1 , r_2 , and T by both PS and GPS, analyzed the data using the same method as Sec. IV A, and then compared the results between PS and GPS.

Figures 7(a) and 7(d) show the trade-off between the qualities and photon detection rates in the cases of 2 dB and 4 dB, respectively. In each of these subfigures, we plot three results for each of PS and GPS, which were obtained by different combinations of r_1 , r_2 , and T. We also plot the corresponding simulation results with losses by scaling the photon detection probabilities similarly to Figs. 6(d)–6(f). Tables II and III list the experimental

conditions and detailed results. In GPS, we used the parameters r_1 , r_2 , and T approximately satisfying the constraint for the best trade-off. As mentioned in Sec. II, their specific values are determined by Eqs. (13) and (21) (s = 1 at the best trade-off).

We discuss the trade-off results as follows. In Figs. 7(a)and 7(d), the experimentally obtained photon detection rates (horizontal axis) agree well with the simulations, and all the experimental values in GPS surpass those in PS. As for W_{00} (vertical axis), our experiments exhibit a similar trend to the simulations, and all the experimental values in GPS are either equivalent to or better than those in PS. The reason of differences in the qualities W_{00} between the experiments and simulations is that the negative value W_{00} is sensitive to the signal loss values, which depend on the alignment in each measurement. In particular, relatively large discrepancies in PS-1, 2, and 3 are attributed to the fake photon detection triggers. In these experimental conditions, the photon detection rates and fake count rates are several 100 cps and several 10 cps. respectively, which corresponds to almost 10% loss. This is higher than 5% loss in Table I, which is used in our simulation as shown in Table I. As a whole, as Figs. 7(a)and 7(d) show, the trade-off relationship becomes better by adopting GPS in both cases of 2 dB and 4 dB. At 2 dB in particular, the photon detection rate in GPS exceeds that in PS by over 10 times.

Here let us confirm that the generated states are close to each other in six different experimental conditions for 2 dB and 4 dB, respectively. Figure 7 shows representative Wigner functions. We here see that PS-2 and GPS-2 in Figs. 7(b) and 7(c) as well as PS-5 and GPS-5 in Figs. 7(e) and 7(f) have almost equivalent squeezing levels, respectively. In addition, we quantitatively evaluated the squeezing levels $e^{-2r_{\text{out}}}$ of the actually generated squeezed single-photon states by fitting their Wigner functions with those of the pure squeezed single-photon states. We list the obtained values as the output squeezing levels $e^{-2r_{\text{out}}}$ in Tables II and III, and their discrepancies among different experimental conditions are within $\pm 0.10 \,\mathrm{dB}$. Note that the differences between these values and the target squeezing levels $(2 \,\mathrm{dB} \text{ and } 4 \,\mathrm{dB})$ mainly arise from the fact that actually generated states are deteriorated by the losses.

Thus we experimentally confirmed our theoretical prediction of the trade-off improvement by GPS.

V. CONCLUSION

We numerically analyzed the generation of squeezed single-photon states by GPS with an on/off detector. We derived a trade-off relationship between the qualities $W_{\text{out}}(0,0)$ and photon detection probabilities P_{on} of the heralded states for both PS and GPS. Our calculation shows that GPS can more efficiently generate states with comparable quality to PS, and it was experimentally proven for 2 dB- and 4 dB-squeezed single-photon states.



FIG. 7. (a), (d) Experimental and simulation results of trade-off of 2 dB- and 4 dB-squeezed single-photon states, respectively. For scaling the simulation results of photon detection probabilities $P_{\rm on}$, we use the following values of C: (a) 1.45×10^6 and (d) 1.30×10^6 . (b), (c), (e), (f) Representative Wigner functions of quantum states generated by the following conditions in the order: PS-2, GPS-2, PS-5, and GPS-5. Refer to Tables II and III for the experimental conditions and detailed results.

TABLE II. Experimental conditions and results of 2 dB-squeezed single-photon states

	Input squeezing levels		Transmissivity	Output squeezing level	$\operatorname{Quality}^*$	Photon detection rate [*]
	e^{-2r_1} (dB)	e^{-2r_2} (dB)	T	$e^{-2r_{\rm out}}$ (dB)	$W_{00} = \min W(x, p)$	(cps)
PS-1	2.06	0	0.97	1.62	-0.109 ± 0.010	$(2.65 \pm 0.02) \times 10^2$
PS-2	2.11	0	0.95	1.58	-0.107 ± 0.009	$(4.32 \pm 0.03) \times 10^2$
PS-3	2.16	0	0.93	1.70	-0.106 ± 0.009	$(6.63 \pm 0.04) \times 10^2$
GPS-1	2.40	-0.39	0.86	1.63	-0.135 ± 0.008	$(1.82 \pm 0.01) \times 10^3$
GPS-2	2.80	-0.78	0.79	1.63	-0.137 ± 0.007	$(4.03 \pm 0.02) \times 10^3$
GPS-3	3.20	-1.14	0.74	1.58	-0.133 ± 0.005	$(6.82 \pm 0.02) \times 10^3$

^{*} Shown with the standard errors.

TABLE III. Experimental conditions and results of 4 dB-squeezed single-photon states

	Input squeezing levels $r^{-2r_1}(4\mathbf{P}) = r^{-2r_2}(4\mathbf{P})$		Transmissivity	Output squeezing level $e^{-2r_{out}}$ (dP)	Quality [*]	Photon detection rate [*]
	<i>e</i> - (ub)	е - (ав)	1	e out (db)	$w_{00} \equiv \min w(x, p)$	(cps)
PS-4	4.14	0	0.97	3.40	-0.111 ± 0.006	$(9.96 \pm 0.04) \times 10^2$
PS-5	4.24	0	0.95	3.35	-0.107 ± 0.006	$(1.895 \pm 0.006) \times 10^3$
PS-6	4.35	0	0.93	3.24	-0.102 ± 0.006	$(2.496 \pm 0.008) \times 10^3$
GPS-4	4.40	-0.39	0.93	3.36	-0.110 ± 0.006	$(3.15 \pm 0.01) \times 10^3$
GPS-5	4.70	-0.67	0.89	3.30	-0.115 ± 0.006	$(5.51 \pm 0.02) \times 10^3$
GPS-6	5.00	-0.94	0.86	3.31	-0.112 ± 0.005	$(8.09 \pm 0.02) \times 10^3$

* Shown with the standard errors.

In fact, the generation rate improvement at 2 dB exceeds one order of magnitude in our experiment.

Our theoretical and experimental studies reveal that we can boost the generation rates of the squeezed singlephoton states using GPS, which can be realized only by a slight extension from the conventional PS. This will accelerate the applications of squeezed single-photon states, which have been limited by the trade-off in PS, and also stimulate the progress of advanced CV QIP that requires non-Gaussian states.

- F. Flamini, N. Spagnolo, and F. Sciarrino, Rep. Prog. Phys. 82, 016001 (2019).
- [2] U. Andersen, G. Leuchs, and C. Silberhorn, Laser & Photonics Reviews 4, 337 (2010).
- [3] S. Takeda and A. Furusawa, APL Photonics 4, 060902 (2019).
- [4] W. Asavanant and A. Furusawa, Optical Quantum Computers: A Route to Practical Continuous Variable Quantum Information Processing (AIP Publishing LLC).
- [5] N. C. Menicucci, P. van Loock, M. Gu, C. Weedbrook, T. C. Ralph, and M. A. Nielsen, Phys. Rev. Lett. 97, 110501 (2006).
- [6] W. Asavanant, Y. Shiozawa, S. Yokoyama, B. Charoensombutamon, H. Emura, R. N. Alexander, S. Takeda, J. Yoshikawa, N. C. Menicucci, H. Yonezawa, and A. Furusawa, Science **366**, 373 (2019).
- [7] J. Yoshikawa, T. Hayashi, T. Akiyama, N. Takei, A. Huck, U. L. Andersen, and A. Furusawa, Phys. Rev. A 76, 060301 (2007).
- [8] Y. Miwa, J. Yoshikawa, N. Iwata, M. Endo, P. Marek, R. Filip, P. van Loock, and A. Furusawa, Phys. Rev. Lett. 113, 013601 (2014).
- [9] Y. Enomoto, K. Yonezu, Y. Mitsuhashi, K. Takase, and S. Takeda, Sci. Adv. 7, eabj6624 (2021).
- [10] A. Sakaguchi, S. Konno, F. Hanamura, W. Asavanant, K. Takase, H. Ogawa, P. Marek, R. Filip, J. Yoshikawa, E. Huntington, H. Yonezawa, and A. Furusawa, Nat. Commun. 14, 3817 (2023).
- [11] P. T. Cochrane, G. J. Milburn, and W. J. Munro, Phys. Rev. A 59, 2631 (1999).
- [12] D. Gottesman, A. Kitaev, and J. Preskill, Phys. Rev. A 64, 012310 (2001).
- [13] H. Jeong and M. S. Kim, Phys. Rev. A 65, 042305 (2002).
- [14] T. C. Ralph, A. Gilchrist, G. J. Milburn, W. J. Munro, and S. Glancy, Phys. Rev. A 68, 042319 (2003).
- [15] A. P. Lund, T. C. Ralph, and H. L. Haselgrove, Phys. Rev. Lett. **100**, 030503 (2008).
- [16] S. Lloyd and S. L. Braunstein, Phys. Rev. Lett. 82, 1784 (1999).
- [17] J. Niset, J. Fiurášek, and N. J. Cerf, Phys. Rev. Lett. 102, 120501 (2009).
- [18] J. Eisert, S. Scheel, and M. B. Plenio, Phys. Rev. Lett. 89, 137903 (2002).
- [19] J. Fiurášek, Phys. Rev. Lett. 89, 137904 (2002).

ACKNOWLEDGMENTS

This work was partly supported by JST Grant Numbers JPMJFR223R, JPMJMS2064, and JPMJPF2221; JSPS KAKENHI Grant Numbers 22K20351, 23H01102, 23K13038, and 23K17300; the Canon Foundation; MEXT Leading Initiative for Excellent Young Researchers; and the Research Foundation for Opto-Science and Technology. H. T. and A. M. acknowledge a financial support from The Forefront Physics and Mathematics Program to Drive Transformation (FoPM), WINGS Program, the University of Tokyo. The authors thank Takahiro Mitani for the careful proofreading of the manuscript.

- [20] G. Giedke and J. Ignacio Cirac, Phys. Rev. A 66, 032316 (2002).
- [21] M. Dakna, T. Anhut, T. Opatrný, L. Knöll, and D.-G. Welsch, Phys. Rev. A 55, 3184 (1997).
- [22] A. Gilchrist, K. Nemoto, W. J. Munro, T. C. Ralph, S. Glancy, S. L. Braunstein, and G. J. Milburn, J. Opt. B: Quantum Semiclass. Opt. 6, S828 (2004).
- [23] A. P. Lund, H. Jeong, T. C. Ralph, and M. S. Kim, Phys. Rev. A 70, 020101 (2004).
- [24] A. Laghaout, J. S. Neergaard-Nielsen, I. Rigas, C. Kragh, A. Tipsmark, and U. L. Andersen, Phys. Rev. A 87, 043826 (2013).
- [25] D. V. Sychev, A. E. Ulanov, A. A. Pushkina, M. W. Richards, I. A. Fedorov, and A. I. Lvovsky, Nat. Photon. 11, 379 (2017).
- [26] H. M. Vasconcelos, L. Sanz, and S. Glancy, Opt. Lett., 35, 3261 (2010).
- [27] D. J. Weigand and B. M. Terhal, Phys. Rev. A 97, 022341 (2018).
- [28] J. Wenger, R. Tualle-Brouri, and P. Grangier, Phys. Rev. Lett. 92, 153601 (2004).
- [29] A. Ourjoumtsev, R. Tualle-Brouri, J. Laurat, and P. Grangier, Science **312**, 83 (2006).
- [30] J. S. Neergaard-Nielsen, B. M. Nielsen, C. Hettich, K. Mølmer, and E. S. Polzik, Phys. Rev. Lett. 97, 083604 (2006).
- [31] K. Wakui, H. Takahashi, A. Furusawa, and M. Sasaki, Opt. Express 15, 3568 (2007).
- [32] R. Dong, A. Tipsmark, A. Laghaout, L. A. Krivitsky, M. Ježek, and U. L. Andersen, J. Opt. Soc. Am. B 31, 1192 (2014).
- [33] W. Asavanant, K. Nakashima, Y. Shiozawa, J. Yoshikawa, and A. Furusawa, Opt. Express 25, 32227 (2017).
- [34] S. Konno, W. Asavanant, F. Hanamura, H. Nagayoshi, K. Fukui, A. Sakaguchi, R. Ide, F. China, M. Yabuno, S. Miki, H. Terai, K. Takase, M. Endo, P. Marek, R. Filip, P. van Loock, and A. Furusawa, Science **383**, 289 (2024).
- [35] S. Zhang, S. Yang, and J. Ma, J. Opt. Soc. Am. B 41, 887 (2024).
- [36] P. Marek, J. Provazník, and R. Filip, Opt. Express 26, 29837 (2018).
- [37] Y.-R. Chen, H.-Y. Hsieh, J. Ning, H.-C. Wu, H. L. Chen, Z.-H. Shi, P. Yang, O. Steuernagel, C.-M. Wu, and

13

R.-K. Lee, Generation of heralded optical 'Schroedinger cat' states by photon-addition (2023), arXiv:2306.13011 [quant-ph].

- [38] K. Takase, J. Yoshikawa, W. Asavanant, M. Endo, and A. Furusawa, Phys. Rev. A 103, 013710 (2021).
- [39] S. Suzuki, K. Tsujino, F. Kannari, and M. Sasaki, Opt. Commun. 259, 758 (2006).
- [40] C. Weedbrook, S. Pirandola, R. García-Patrón, N. J. Cerf, T. C. Ralph, J. H. Shapiro, and S. Lloyd, Rev. Mod. Phys. 84, 621 (2012).
- [41] T. Kashiwazaki, T. Yamashima, N. Takanashi, A. Inoue, T. Umeki, and A. Furusawa, Appl. Phys. Lett. 119, 251104 (2021).
- [42] S. Miki, M. Yabuno, T. Yamashita, and H. Terai, Opt.

Express **25**, 6796 (2017).

- [43] H. Vahlbruch, S. Chelkowski, B. Hage, A. Franzen, K. Danzmann, and R. Schnabel, Phys. Rev. Lett. 97, 011101 (2006).
- [44] S. Chelkowski, H. Vahlbruch, K. Danzmann, and R. Schnabel, Phys. Rev. A 75, 043814 (2007).
- [45] E. D. Black, American Journal of Physics 69, 79 (2001).
- [46] J. Yoshikawa, W. Asavanant, and A. Furusawa, Phys. Rev. A 96, 052304 (2017).
- [47] A. I. Lvovsky, J. Opt. B: Quantum Semiclass. Opt. 6, S556 (2004).
- [48] J. Řeháček, D. Mogilevtsev, and Z. Hradil, New J. Phys. 10, 043022 (2008).