

Schrodinger equation for current carrying states

D.S. Kosov

Institute of Physical and Theoretical Chemistry,

J.W. Goethe University, Marie-Curie-Str. 11, D-60439 Frankfurt, Germany

Abstract

Schrodinger equation with given, a priori known current is formulated. A non-zero current density is maintained in the quantum system via a subsidiary condition imposed by vector, local Lagrange multiplier. Constrained minimization of the total energy on the manifold of an arbitrary current density topology results into a non-linear self-consistent Schrodinger equation. The applications to electronic transport in two-terminal molecular devices are developed and new macroscopic definition of a molecular current-voltage characteristic is proposed. The Landauer formula for the conductance of an ideal one-dimensional lead is obtained within the approach. The method is examined by modeling of current carrying states of one-dimensional harmonic oscillator.

Electronic address: kosov@theochem.uni-frankfurt.de

I. INTRODUCTION

The remarkable miniaturization of conventional microelectronic devices has been witnessed over the last decades. If the miniaturization trend is to continue, elements of microelectronic circuits, e.g. transistors and contacts, will soon shrink to single molecules or even atoms. In the past few years, there have been considerable advances towards fabrications and experimental studies of mono-molecular electronic devices [1]. This activity has been largely spurred on by development of experimental techniques to form atomic scale electrical contacts such as scanning tunneling microscopy [2] and mechanically controllable break junctions [3]. Measurements of current-voltage (I-V) characteristics have been recently performed on a single benzene-1,4-dithiolate molecule [4], buckminsterfullerene [5], individual atoms [6], nanoclusters [7] and carbon nanotubes [8]. These initial observations of conduction in molecules were followed quickly by experimental demonstration of the simplest devices: molecular diodes [9], switches [10] and memory elements [11] although molecular equivalent of a transistor is yet to be discovered.

Several theoretical approaches have been recently developed to describe electronic conductivity of molecules [12]. One of the widely used methods is based on the combination of extended Huckel model or density functional theory to treat the molecular electronic structure, an electronic reservoir model for the contacts and linear response approximation to compute the electronic current as a function of the applied voltage [13, 14, 15, 16, 17]. The most recent applications used Lippmann-Schwinger or non-equilibrium Green's functions formalism plus "jellium" model for the contacts and for the molecular-contact interactions [18, 19]. In all these approaches, the system is partitioned into three parts: molecular wire and two electron reservoirs to represent metallic contacts. The use of the model dependent reservoir-molecule interaction as one of the most pivotal ingredient diminishes the ability of these methods and prevents from a development of predictive and quantitative techniques for the electronic transport problem. Recent density functional theory based calculation demonstrates that a molecular wire is bonded to a gold contact by the thiol bridge which is known to be the strong covalent interaction [20]. The empirically treated coupling between metal contacts and the molecular wire, which serves as the interaction for the linear response calculations and represents the kernel of the corresponding Lippmann-Schwinger equation, is at least strong as intermolecular interaction. Recent papers also indicate the exact nature

of the molecule-contact bonding is critical in predicting the correct order of magnitude for the current with applied bias [18].

The miniaturization shrinks the size of the system to a level when the problem can be addressed by *ab initio* electronic structure methods. As an example consider a standard prototype molecular device system with a single benzene-1,4-dithiolate molecule covalently bonded to two gold electrodes [4]. The problem can be reduced to the system where the molecule is bonded to two small Au clusters [17]. A gold cluster with reasonably small edge influence on the molecular-surface bonding contains 10 atoms [20]. With a single benzene-1,4-dithiolate molecule as the molecular wire the contact-wire-contact system consists of just 32 atoms. Systems of such size can be routinely simulated by standard quantum chemistry codes. The main obstacle for the application of the first principle electronic structure methods is not the size of the system but modeling of the electronic current and interpretation of the applied voltage. Suppose that we have solved Hartree-Fock or Kohn-Sham equations for a molecular device. The ground state wave function is real in absence of a magnetic field and therefore the current density computed from this wave function is zero everywhere in the sample. Another important issue is an interpretation of the applied voltage. Virtually all present theoretical approaches are pivotally relied on simplified, noninteracting electrons type models for the metal contacts where the external voltage bias can be straightforwardly associated with the Fermi energies shift between left and right electronic baths. One of the reasons for use electronic reservoir models to represent the metallic contacts is principle theoretical difficulties related to a rigorous quantum mechanical definition of the applied voltage.

In this paper, we advocate an alternative approach where the use of the electronic reservoir to model contacts is completely avoided from the very beginning and a quantum system with current is treated effectively as a closed system. We begin by describing the variational principle for a quantum system with current. We then derive the Schrodinger equation with probability flux which provides exact wavefunctions on the manifold of a given current density. We next specify two-term in a molecular device steady current subsidiary condition and develop the Schrodinger equation for a two-term in a molecular device. We discuss the use of the energy balance condition to compute current-voltage characteristics of quantum systems. We then derive the Landauer formula for non-interacting charge carriers within the formalism. Finally, we demonstrate the salient features of the approach through the

numerical solution of the self-consistent Schrodinger equation for one-dimensional harmonic oscillator with constrained current.

II. SCHRODINGER EQUATION WITH PROBABILITY CURRENT

A. Variational principle

We start with the nonrelativistic Hamiltonian for a particle in the external scalar potential $v(r)$ (atomic units are used throughout the paper unless otherwise mentioned):

$$H = \frac{1}{2}r^2 + v(r) : \quad (1)$$

We define density and paramagnetic current density as:

$$\rho(r) = \psi^*(r)\psi(r) \quad (2)$$

$$j(r) = \text{Im} \left[\psi^*(r) \nabla \psi(r) \right] \quad (3)$$

where $\psi(r)$ is not generally an eigenvector of the Hamiltonian H . We will specify an eigenproblem for the $\psi(r)$ in the next section. The physical current is equivalent to the paramagnetic current densities in absence of an external magnetic field.

An eigenvector for a bound state of a real Hamiltonian can be always made real by a change of the phase of the wave function. The Hamiltonian H is real therefore if we just solve standard Schrodinger equation with the Hamiltonian H , we will obtain real wave function $\psi(r)$ and the current density $j(r)$ will be automatically zero. The standard way to get a complex wavefunction out of a real Hamiltonian is to assume certain boundary conditions. These boundary conditions could be an assumption of an incoming plane wave in scattering theory or periodic boundary conditions for a translationally invariant system. To solve a scattering problem for a molecular device is possible only at the cost of major unphysical approximations, e.g. via considering the molecular device as a single scattering center. Another approach is to assume periodic boundary conditions. The periodic boundary conditions prevent one from studying any situations where the change of chemical potential across the system is of finite magnitude because the chemical potential must be also periodic in space. The local chemical potential is the decreasing function in the direction of the

current and therefore the system can not be treated as translationally invariant at least along the current axis.

We have developed an alternative approach where a current carrying quantum system is treated effectively as a closed system with a subsidiary condition for the generally discontinuous current density distribution. We start our derivation with the assumption that current carrying states of an open quantum system can be described in terms of wave functions of an effectively closed quantum system if the current is maintained via explicit constraint. This assumption is a simplified, particular case of the standard assumption in statistical mechanics: a system coupled to a thermal bath can be described with statistical ensembles of a closed system in which the system-bath interaction is not explicitly considered, but enters only via Lagrange multipliers and subsidiary constraints. It has been recently demonstrated that a steady current open mesoscopic system can be described in terms of an ensemble of carrier states in the closed mesoscopic device itself if the steady current is additionally constrained [21, 22].

We require that the current density is constrained to be specified function $I(r)$. It results in the subsidiary constraint equation:

$$j(r) - I(r) = 0 : \quad (4)$$

The expression (4) generally can not be obtained by differentiating of a functional of ψ and with respect to r . It means that the constraint eq.(4) is nonholonomic [23]. The variational problem is to minimize the total energy with respect to ψ subject to the nonholonomic constraint for the current density (4). Two types of treatment are possible: we can either choose $\psi(r)$ in which the constraint is implicit or we can impose the constraint explicitly by using the Lagrange multiplier. We will follow the second approach which was recently suggested by Kosov and Greer [24], elimination the part of the wavefunction by imposing the explicit constraint. Although the constraint formulated as eq.(4) is vector and nonholonomic it can be included into a variational functional via pointwise, vector Lagrange multipliers $a(r)$ [24].

Within the Lagrange multiplier approach the constraint is explicitly achieved via introduction of the auxiliary functional:

$$[J] = \langle \psi | H | \psi \rangle - E \langle \psi | \psi \rangle - \int a(r) (j(r) - I(r)) dr : \quad (5)$$

The first two terms are standard in the variational derivation of the Schrodinger equation with the first giving the total energy and the second is introduced to maintain the normalization of the wave function. The third term with the vector Lagrange multipliers $a(r)$ has been introduced to impose the subsidiary constraint for the current density.

A use of the variational principle can be justified only for closed quantum systems. The choice of $I(r)$ can not be obviously completely arbitrary to maintain the closed system boundary condition. The localized in space quantum system will be considered closed if, first, there are no in- and out- probability flows in the system; and, second, if the wave function is an eigenvector of a Hermitian operator (it prevents the complex eigenenergies and therefore effectively closes the system). We will demonstrate in the next section that both these conditions are satisfied within our approach.

B. Self-consistent Schrodinger equation

The minimization of the total energy subject to the subsidiary constraint for the current density (4), i.e. the variation of the auxiliary functional [4], results into the following non-linear Schrodinger equation:

$$\frac{1}{2} \nabla^2 \psi + v(r) \psi - \frac{1}{2i} [a(r); \psi]_+ \psi = E \psi \quad (6)$$

The anti-commutator term,

$$\frac{1}{2i} [\psi; a(r)]_+ = \frac{1}{2i} (\psi a(r) + 2a(r)\psi); \quad (7)$$

is the additional completely imaginary potential arising directly from the constraint on the current density (consult with appendix A for the corresponding functional derivatives). This additional constraint potential forces the wave function $\psi(r)$ to be irreducibly complex and insures that $\psi(r)$ produces the required current density $I(r)$.

A physical interpretation of the Lagrange multiplier $a(r)$ can be made more explicit if we re-write eq.(6) in the following form:

$$\frac{1}{2} (\nabla^2 \psi - a(r)\psi)^2 + \frac{1}{2} a(r) \psi a(r) + v(r) \psi = E \psi \quad (8)$$

It can be now established that the current constraint has introduced the terms which are mathematically equivalent to an external vector potential. But unlike an external vector

potential, the Lagrange multiplier $a(r)$ does depend upon the wave function $\psi(r)$ and eq.(8) becomes nonlinear and must be solved self-consistently. The eigenvalue problem eq.(8) is generated by Hermitian operator since the Lagrange multiplier $a(r)$ is real. Being a solution of the Hermitian eigenproblem the eigenenergy E is real and the wavefunctions form a complete set in Hilbert space. Within our approach we deal with the localized in space system with the wave functions generated by the hermitian eigenproblem (8). Such system is by definition closed and therefore the use of the variational principle is formally justified.

The Schrodinger equation with current (8) is not yet in a form allowing for a solution to be found as the Lagrange multiplier $a(r)$ is not known yet. We next seek a solution for the Lagrangian multiplier $a(r)$. In the developing of this method we have found out that the most significant source of numerical instabilities in the solution of the nonlinear Schrodinger equation (8) arises from the determination of the Lagrange multiplier $a(r)$. The described below procedure obtaining of the Lagrange multiplier has been found to be the most robust. Multiplying eq. (6) from the left on the $\psi(r)$ and subtracting from the obtained equation its own Hermitian conjugate, yields

$$r \nabla^2 j(r) = r \nabla^2 (a(r) \psi(r)) : \quad (9)$$

Equation (9) can be resolved for $a(r)$ with the assumption that both the density $\psi(r)$ and the current density $j(r)$ decay to zero at infinity. In this case the direct integration of eq.(9) results into the following expression for the Lagrange multiplier $a(r)$:

$$a(r) = \frac{j(r)}{\psi(r)} \quad (10)$$

Substitution of the constraint for the current density eq.(4) into eq.(10) yields the simple expression in which the Lagrange multiplier depends upon the wave function only via the density in the denominator:

$$a(r) = \frac{I(r)}{\psi(r)} \quad (11)$$

There is a direct similarity between equation for the Lagrange multiplier (10) and the definition of the velocity of a quantum trajectory within de Broglie-Bohm causal description of quantum mechanics [25]. Within the de Broglie-Bohm dynamics the velocity $u(r;t)$ of a trajectory at a given point is computed as [26]:

$$u(r;t) = \frac{j(r;t)}{\psi(r;t)} ; \quad (12)$$

therefore, at least for stationary systems the vector Lagrange multiplier $\mathbf{a}(\mathbf{r})$ can be directly related to the velocity for a corresponding de Broglie-Bohm trajectory. By this analogy we can make the physical interpretation of the Lagrange multiplier more explicit. In the de Broglie-Bohm quantum dynamics to maintain the constant flux at the given density profile one needs to adjust the local trajectory velocities. The vector Lagrange multiplier appears to play the similar role in the Schrodinger equation with constrained current. Likewise for a point with the non-zero trajectory velocity, the current density has finite value at a point with the non-zero vector Lagrange multiplier. And likewise the de Broglie-Bohm velocity, a product of the vector Lagrange multiplier on the probability density yields the current density.

With this choice of the Lagrange multiplier (11) we obtain the Schrodinger equation with the current $I(\mathbf{r})$ in the self-consistent and closed form :

$$-\frac{\hbar^2}{2m} \nabla^2 \psi + V(\mathbf{r}) \psi + \frac{1}{2} \frac{I^2(\mathbf{r})}{\psi^2} \psi = E \psi : \quad (13)$$

The derivation of the self-consistent Schrodinger equation eq.(13) composes one of the central results of the paper.

III. SCHRÖDINGER EQUATION FOR A TWO TERMINAL MOLECULAR DEVICE

The desire to develop the basic Schrodinger equation for calculations of I-V characteristics of two terminal molecular devices is the impetus for the present study. To achieve this aim, we specify the molecular wire constraint on the current density:

$$\int_{-L}^R dy dz j_x(\mathbf{r}) = I_x \quad (x \in [-L, R]); \quad (14)$$

where I_x is the steady current through the molecular device. The step function,

$$\theta(x \in [-L, R]) = \theta(x + L) \theta(R - x); \quad (15)$$

equals to 1 if $-L \leq x \leq R$ and zero otherwise. L and R are the left and right boundaries for the molecular device. Within this description, net current flow is aligned along the x axis and there are no in- and out-flow: the current starts at the left boundary L and completely absorbed at the right R . With this constraint it is not required to fix the full

vector $\mathbf{j}(\mathbf{r})$ everywhere in the sample. Only the net current flow across a cross section $\int_R d\mathbf{y} d\mathbf{z} \mathbf{j}_x(\mathbf{r})$ is constrained, and this quantity is readily available experimentally. This is a simple geometric arrangement to specify current flow for the two terminal molecular device and can be extended to more complex device topologies, e.g. for the three terminal devices where three tips are connected to a single molecule [27].

Likewise, as for the derivation of the exact Schrodinger equation in the preceding section, with this choice of the constraint (14) the minimization of the auxiliary functional (5) now yields the Schrodinger equation for the steady current two terminal molecular device:

$$\frac{1}{2} + v(\mathbf{r}) - \frac{1}{2i} a_x(\mathbf{x}); \frac{\partial}{\partial \mathbf{x}} + (\mathbf{r}) = E(\mathbf{r}) : \quad (16)$$

The expression for the Lagrange multiplier given by eq.(11) can be straightforwardly extended to the steady current molecular device, with the result is

$$a_x(\mathbf{x}) = \frac{I_x}{y_z(\mathbf{x})} (\mathbf{x} \in L; R \in \mathbf{x}) ; \quad (17)$$

where we have introduced the quantity

$$y_z(\mathbf{x}) = \int d\mathbf{y} d\mathbf{z} (\mathbf{r}) : \quad (18)$$

With the expression for the Lagrange multiplier $a_x(\mathbf{x})$ in hands, we can complete the Schrodinger equation for the two-terminal molecular device with steady current $I_x(\mathbf{x})$

$$\frac{1}{2} + v(\mathbf{r}) - \frac{I_x}{2i} \frac{(\mathbf{x} \in L; R \in \mathbf{x})}{y_z(\mathbf{x})}; \frac{\partial}{\partial \mathbf{x}} + (\mathbf{r}) = E(\mathbf{r}) : \quad (19)$$

Some aspects of eq.(19) deserve special discussion. The imaginary potential which enforces the wave function to produce steady current I_x depends upon the x coordinate only. The range of this potential is restricted by the molecular device boundaries. One of the terms in this potential is proportional to the derivative of the step function,

$$\frac{\partial}{\partial x} (\mathbf{x} \in L; R \in \mathbf{x}) = (\mathbf{x} \in L) - (\mathbf{x} \in R) ; \quad (20)$$

and therefore yields the singular imaginary δ -function potential on the device boundaries. It is known from the standard quantum mechanics textbooks [28] that a δ -function potential results in the discontinuity of the first derivative of the corresponding solutions of the Schrodinger equation. Likewise, the imaginary component of the eigenfunction $\psi(\mathbf{r})$ of the

Schrodinger equation for a molecular device (19) has the discontinuous first derivative at the points $x = L$ and $x = R$.

The final comment regarding the computation of the I-V characteristic of a two-terminal molecular device is in due order. The current carrying states obtained as the solutions of the molecular device Schrodinger equation (19) must now be associated with current-voltage characteristics available experimentally. The rigorous definition of the applied voltage is a controversial issue if one does not invoke noninteracting electron reservoirs to represent contacts. We propose the following macroscopic definition of the applied voltage which has the direct relation with the quantities measured experimentally. The energy increase from the applied voltage U is computed by the numerical integration with an assumption of linear voltage drop between the left and right boundaries:

$$E_d(U) = \frac{U}{R - L} \int_L^R dx \langle R - x | \gamma_z | x \rangle : \quad (21)$$

We compute the energy of the non-active, i.e. with zero current, molecular device and compute the total energy of the same molecular device at an experimentally given current I_x . Then the energy increase for the establishment of the current carrying state, i.e. the energy difference

$$E_d(I_x) - E_d(I_x = 0) \quad (22)$$

is calculated. Because of the energy balance condition the $E_d(U)$ must be equal to the $E_d(I_x)$ and it results into the following equation for the applied voltage bias:

$$U = \frac{(R - L)}{\int_L^R dx \langle R - x | \gamma_z | x \rangle} E_d(I_x) : \quad (23)$$

The eigenenergy E of the Schrodinger equation (19) should not be confused with the energy of molecular device. The eigenenergy E serves only as the Lagrange multiplier to enforce orthogonality of the wave function. The energy of the molecular device can be obtained as an expectation value of the real physical Hamiltonian H with the integration restricted by the molecular device region:

$$E_d(I_x) = \int_L^Z \int_L^{Z^R} dx \langle r | \frac{1}{2} + v(r) | r \rangle ; \quad (24)$$

where $\psi(r)$ is the solution of the Schrodinger equation (19) with the given I_x . Since the wavefunction $\psi(r)$ is complex and the integration (24) is not performed over whole space, it is not obvious from the expression (24) that the device energy $E_d(I_x)$ must be real. We will show now that the device energy $E_d(I_x)$ is real if the wavefunction $\psi(r)$ produces the constrained current density (14). To prove this we subtract from eq.(24) its own complex conjugate and after a bit of algebra arrive to the following expression:

$$E_d(I_x) - E_d(I_x)^* = \frac{1}{i} \int_L^R dy dz \frac{d}{dx} \psi(r) - \frac{1}{i} \int_S dS n \cdot j(r) = 0 \quad (25)$$

The length of the quantum wire is aligned along the x axis and the surface integral does the integration over the surface of the rectangular box with one $y-z$ face at $x = L$, another $y-z$ face at $x = R$ and any of the $x-y$ or $x-z$ faces are removed at the infinity. Within our constraint, there is a positive current flowing into the $y-z$ face at $x = L$ and exactly the same positive current flowing out of the $y-z$ face at $x = R$. There is no current flow out of the region in any of the $x-y$ or $x-z$ faces. Therefore the surface integral vanishes

$$\int_S dS n \cdot j(r) = 0 \quad (26)$$

and the device energy $E_d(I_x)$ defined via eq.(24) becomes real.

IV . EXAMPLE CALCULATIONS

A . Conductance of an ideal one-dimensional lead

In order to establish connection with standard approaches and test the method we derive the Landauer formula [29] using the Schrodinger equation for current carrying states eq.(13) as the starting point. Consider noninteracting electrons moving along a one-dimensional wire without any scatterer. The electronic density does not depend upon x yielding the following Schrodinger equation with steady current I :

$$\frac{1}{2} \frac{d^2}{dx^2} \psi_k(x) + i \frac{I}{\hbar} \frac{d}{dx} \psi_k(x) = E_k \psi_k(x) \quad (27)$$

Equation (27) has the plane-wave solution

$$\psi_k(x) = \exp(ikx) \quad (28)$$

with eigenenergy

$$E_k = \frac{k^2}{2} - \frac{Ik}{2} : \quad (29)$$

The similar dispersion relation as given by eq.(29) has been obtained within the same approach for uniform electron gas with applied direct current [24]. For the small voltage and temperature transmissions of electrons take place only through the states in close vicinity of the Fermi level. There are two vectors k , one is positive and one is negative, which correspond to the Fermi energy:

$$k_+ = \frac{I}{2} + \frac{S}{2E_F + \frac{I^2}{2}} ; \quad (30)$$

$$k_- = \frac{I}{2} - \frac{S}{2E_F + \frac{I^2}{2}} : \quad (31)$$

Following the Landauer approach we associate the voltage drop (at the zero temperature) with the gap between the single-electron energies of the electrons moving in the direction of the current ($k > 0$) and electrons moving in the opposite direction ($k < 0$):

$$U = \frac{k_+^2}{2} - \frac{k_-^2}{2} : \quad (32)$$

Substituting the expressions for the k_+ and k_- eqs.(30,31) into the Landauer's definition of the applied voltage (32), we readily find

$$I = GU ; \quad (33)$$

with the conductance

$$G = \frac{2e^2}{2E_F + \frac{I^2}{2}} : \quad (34)$$

Then, the use of the standard relation between the Fermi momentum k_F and the electronic density $n = k_F^3/6\pi^2$ along with the small current expansion of the square root eq.(34) results into the Landauer formula for a single transport channel of an ideal one-dimensional lead [30]:

$$G = \frac{1}{2} : \quad (35)$$

If we take into account the spin degeneracy of real electrons, the conductance becomes multiplied by 2. By accounting the degeneracy and converting the conductance eq.(35) to SI units the standard value $G = e^2/h = (12.9 \text{ K})^{-1}$ is obtained. Re-deriving the standard result we demonstrate that in the low current and zero temperature limits our method is equivalent to the traditional approaches which are based on the Landauer formula.

B. Numerical solution of the Schrodinger equation with current

We demonstrate applications of the method with numerical examples. The numerical solution of a self-consistent Schrodinger equation is often performed within a finite basis set expansion for the wave function with subsequent diagonalization of the Hamiltonian matrix until the self-consistency is reached. We have found out that it is computationally convenient to form the complete, real basis set from the solutions of the zero-current Schrodinger equation:

$$\left(-\frac{\hbar^2}{2m} \nabla^2 + V(r) \right) \psi_n(r) = E_n \psi_n(r) ; \quad (36)$$

Then we expand the wave function of a current carrying state on this basis

$$\psi(r) = \sum_n C_n \psi_n(r) ; \quad (37)$$

the coefficients C_n must be complex for the wave function which produces a non-zero current. With the expansion (37) we arrive to the following complex, Hermitian eigenproblem:

$$\sum_n (H_{mn} - iW_{mn}(I)) C_n = E C_m ; \quad (38)$$

where the current dependent matrix element $W_{mn}(I)$ is computed in appendix B and is given by the following integral:

$$W_{mn}(I) = \frac{1}{2} \int dr \frac{\hbar}{m} \frac{1}{r} \left(\psi_m(r) \nabla \psi_n(r) - \psi_n(r) \nabla \psi_m(r) \right) ; \quad (39)$$

The matrix elements $W_{mn}(I)$ are real and depend on the expansion coefficients C_n via the density $\rho(r)$ thereby making the eigenvalue problem (38) nonlinear. The eigenproblem (38) is Hermitian because the matrix element $W_{mn}(I)$ changes its sign when we swap m and n indices:

$$W_{mn}(I) = -W_{nm}(I) ; \quad (40)$$

The numerical calculations were carried out for the one-dimensional system. With an eye on molecular device simulations we solve the self-consistent Schrodinger equation for the step function constraint as a primary example:

$$j(x) = I \quad (x \in [L; R]) \quad (41)$$

The external potential was taken in the harmonic oscillator form and we put $L = -2.0$ and $R = 2.0$ as left and right boundaries for the current carrying part of the system in all our calculations. Our basis set was built up from the 25 eigenvectors of the zero current Hamiltonian. The self-consistency was assumed to be achieved when the root mean square deviation of the wave function vectors of the two subsequent iterations was less than 10^{-8} .

First, we plot the Lagrange multiplier as a function of the coordinate on the figure 1. The Lagrange multiplier is discontinuous at the system boundaries. The Lagrange multiplier is vanishing out of the system region and it is the inverse function of the density $\rho(x)$ inside the system. As it can be expected from the analogy with the de Broglie-Bohm quantum hydrodynamics (12) (the lower the density, the larger the local velocity) the Lagrange multiplier reaches its maximum values in the regions of depleted density and has the minimal value at the point of maximal density.

In our next example we studied the deviation of the current carrying wave function $\psi(r)$ ($I = 0.1$) from the zero-current ground state wave function $\psi_0(r)$. The real component is depicted on the upper panel of the fig 2. The shape and magnitude of the real component do not undergo significant transformation with the establishment of the current carrying state. Although the admixture of the higher terms in the expansion (37) results in the small damping oscillations on the tails of the real component of the wave function. The imaginary part of the wave function (plotted on the lower panel of the fig 2) is identically zero when the current is vanished. The imaginary component reaches its negative minimum at the left boundary $L = -2.0$ of the current carrying part of the system and then it discontinuously changes the sign of the first derivative and undergoes almost linear increase until it reaches its maximum at the right boundary $R = 2.0$. When the coordinate x goes out of the non-zero current region the imaginary part of the wave function rapidly decays to zero value.

The establishment of the imaginary part of the wave function directly indicates the development of the current carrying state. We studied transformations of the imaginary component as a function of the increased current. The imaginary components of the wave functions

are plotted on the fig. 3 for three representative steady currents: $I = 0.01$, $I = 0.5$ and $I = 0.1$. At the very small current $I = 0.01$ the imaginary wave function is almost zero everywhere except the only small negative minimum at the left boundary and with the positive maximum at the right. The magnitudes of the imaginary component at the extremums are nearly linearly proportional to the value of the constrained current. The slope of the imaginary component, i.e. the derivative, is always positive and almost constant between the left and right boundaries of the system. The imaginary part becomes zero when the real component reaches its maximum, i.e. at the point $x = 0.0$. Although the total wave function is real at the point $x = 0.0$ the current is not vanished because the derivative of the wave function remains complex.

Now we turn to the calculations of a "device" energy required to establish the current carrying state. Being the Lagrangian multiplier to maintain the wavefunction orthonormality, the eigenenergy E of the eigenproblem (38) is not directly related to the energy of the system. The energy increase due to the establishment of the current carrying state is defined via the space restricted expectation value of the Hamiltonian (24):

$$E_d(I) = \int_L^{Z^R} dx \langle \psi(x) | \left(-\frac{1}{2} \frac{d^2}{dx^2} + v(x) \right) | \psi(x) \rangle = \int_L^{Z^R} dx \langle \psi(x) | \hat{H} | \psi(x) \rangle : \quad (42)$$

The table 1 contains the energy $E_d(I)$ and the energy difference between the nonactive, i.e. zero-current, and current I carrying state as a function of the increased current. The "device" energy is gradually increased with increasing current. As it can be deduced from the table 1, we need to pump into the system ~ 0.14 a.u. of energy to establish the current $I = 0.1$ a.u. carrying state. A simple fit of the data from the table 1 provides only the quadratic and cubic dependences of the "device" energy upon the steady current (for $I \leq 0.1$):

$$E_d(I) = E_d(I = 0) + 17.4I^2 - 36.5I^3 ; \quad (43)$$

thereby demonstrating that the term linear in the current has the minor importance for the energetics of the current carrying quantum system and the main energy contribution comes from the I^2 term. This energy dependence is generally agreed with the current-density functional theory of inhomogeneous interacting electron gas where the current dependent correction to the standard exchange-correlation energy functional is also mainly proportional to I^2 [31].

V . C O N C L U S I O N S

In this paper, we have given a variational formulation of the Schrodinger equation with non-zero current. The Schrodinger equation with current is derived via a constrained minimization of the total energy with a subsidiary condition for the current density. The subsidiary condition for the current density is maintained during the course of variation by a vector, pointwise Lagrange multiplier. An explicit elimination of this Lagrange multiplier results into the closed, self-consistent form of Schrodinger equation with current. We showed that the current carrying states are eigenvectors of the complex, Hermitian operator. The formulation has been developed for general current density topologies and then specified for the case of a two-terminal molecular device. We showed how the energy balance condition can be used for rigorous computation of I-V characteristics of molecular devices: the energy increase due to the establishment of a current carrying state is associated with the applied voltage bias. We demonstrate the salient features of the approach by re-deriving the Landauer formula for the conductance of an ideal one-dimensional lead and through a solution of the one-dimensional Schrodinger equation with fixed current density. The complex, Hermitian matrix was formed on a basis of the eigenvectors of the zero-current Hamiltonian. The numerical solution was achieved via the self-consistent solution of the complex, Hermitian eigenproblem. We found out that a basis set formed from the zero current Hamiltonian eigenvectors provides a robust algorithm for the self-consistent convergence. Our method has the great compatibility with standard electronic structure methods which are also based on a variational principle e.g. Hartree-Fock or configuration interaction approximations.

A cknow ledgm ents

The author wishes to thank G. Stock for stimulating discussions, critical reading the manuscript and his continuous support of the project. The author also thanks E. R. Bitner, J. C. Greer and A. Nitzan for valuable discussions.

APPENDIX A : FUNCTIONAL DERIVATIVES OF THE CONSTRAINT FUNCTIONAL

In this Appendix we compute the functional derivative of the constraint functional. The constraint functional has the following form

$$[] = \int_Z dr a(r) (j(r) - I(r)) : \quad (A1)$$

The direct variation of the constraint functional with respect to the (r) yields:

$$\begin{aligned} \frac{[]}{(r)} &= \int_Z dr^0 \frac{j(r^0)}{j(r)} - \frac{j(r^0)}{(r)} = \int_Z dr^0 a(r^0) - \frac{j(r^0)}{(r)} \\ &= \frac{1}{2i} \int_Z dr^0 a(r^0) - \frac{1}{(r)} f(r^0)r(r^0) - \frac{1}{(r)} r(r^0)g(r^0) \\ &= \frac{1}{2i} a(r) - r(r) \frac{1}{2i} \int_Z dr^0 a(r^0) - \frac{1}{(r)} r(r^0) \\ &= \frac{1}{2i} a(r) - r(r) \frac{1}{2i} \int_Z dr^0 r(r^0) f a(r^0) - \frac{1}{(r)} r(r^0)g \\ &+ \frac{1}{2i} \int_Z dr^0 (r^0)r(r^0) f a(r^0) - \frac{1}{(r)} r(r^0)g \\ &= \frac{1}{2i} a(r) - r(r) \frac{1}{2i} \int_Z dS_n a(r^0) - \frac{1}{(r)} r(r^0) + \frac{1}{2i} r(r) f a(r) - \frac{1}{(r)} g \\ &= \frac{1}{2i} a(r) - r(r) + \frac{1}{2i} r(r) f a(r) - \frac{1}{(r)} g = \frac{1}{2i} [a(r); r]_+ (r) \end{aligned}$$

APPENDIX B : MATRIX ELEMENTS OF THE ANTI-COMMUTATOR $[a(r); r]_+$

The computation of the matrix element of the anti-commutator is presented below. The notation r^a means that the gradient acts on the Lagrange multiplier $a(r)$ only.

$$\begin{aligned} \langle n | [a(r); r]_+ | m \rangle &= \langle n | r^a \int_Z a(r) + 2a(r) - r_m | i \\ &= \int_Z dr_n(r) - m(r)r - a(r) + 2 \int_Z dr a(r) - n(r)r - m(r) \\ &= \int_I dr r - f a(r) - n(r) - m(r)g - \int_Z dr a(r) - r f_n(r) - m(r)g + 2 \int_Z dr a(r) - n(r)r - m(r) \\ &= \int_Z dS_n a(r) - n(r) - m(r) - \int_Z dr a(r) - (m(r)r - n(r) - n(r)r - m(r)) \\ &= \int_Z dr a(r) - (m(r)r - n(r) - n(r)r - m(r)) \end{aligned}$$

-
- [1] C .Joachim , J.K .G im zew ski and A .Aviram , Nature (London)408, 541 (2001).
 - [2] C .A .M irkin and M .A .Ratner, Ann.Rev.ofPhys.Chem .43, 719 (1992).
 - [3] J.M .van Ruitenbeek, A .A lvarez, I.P ineiro, C .G rahm ann, P .Joyez, M .H .D evoret, D .E steve, and C .U rbina, Rev.ofScien .Instrum .67, 108 (1996).
 - [4] M .A .Reed, C .Zhou, C .J.M uller, T .P .Burgin, J.M .Tour, Science 278, 252 (1997).
 - [5] C .Joachim and J.K .G im zew ski, Chem .Phys.Lett.265, 353 (1997).
 - [6] E .Scheer, N .A grait, J.C .Cuevas, A .L .Yeyati, B .Ludoph, A .M artin-Rodero, G .R .Bollinger, J.M .Ruitenbeek, and C .U rbina, Nature (London) 394, 154 (1998).
 - [7] J.W .G .W ildoer, L .G .Venema, A .G .Rinzler, R .E .Smalley and C .Dekker, Nature 391, 59 (1998).
 - [8] R .M artel, T .Schmidt, H .R .Shea, T .Hertel and Ph.A vouris, ApplPhysLett.bf73, 2447 (1998).
 - [9] R .M .M etzger, Synth.M etals.109, 23 (2000).
 - [10] J.Chen, M .A .Reed, A .M .Rawlett and J.M .Tour, Science 286, 1550 (1999).
 - [11] M .A .Reed, J.Chen, A .M .Rawlett, D .W .Price and J.M .Tour, ApplPhysLett.bf78, 3735 (2001).
 - [12] A recent review of theoretical methods to describe electron transport through molecules is A .Nitzan, Annu.Rev.Phys.Chem .52, 681 (2001).
 - [13] V .M ujica, M .Kemp, M .A .Ratner, JChem Phys.101, 6849 (1994).
 - [14] W .Tian, S .Datta, S .Hong, R .Reifenberger, J.I.Henderson and C .P .Kubiak, JChem Phys.109, 2874 (1998).
 - [15] L .E .Hall, J.R .Reimers, N .S .Hush and K .Silverbrook, JChem Phys.112, 1510 (2000).
 - [16] R .Gutierrez, F .Grossmann, O .Knospe and R .Schmidt, PhysRev.A 64 , 013202 (2001).
 - [17] P .A .Derosa and J.M .Semenario, J.Phys.Chem .B 105, 471 (2001).
 - [18] M .DiVentra, S .T .Pantelides and N .D .Lang, PhysRevLett.84, 979 (2000).
 - [19] J.Taylor, H .Guo and J.W ang, PhysRev.B 63, 121104 (2001).
 - [20] A .Johansson and S .Stafstrom , Chem PhysLett.322, 301 (2000).
 - [21] O .Heinonen and M .D .Johnson , PhysRevLett.71, 1447 (1993).
 - [22] M .D .Johnson and O .Heinonen, PhysRev.B 51, 14421 (1995).
 - [23] R .Courand and D .Hilbert, Methods of mathematical physics, v.1, Wiley Classic Edi-

- tion, 1989.
- [24] D .S.K osov and J.C G reer, Physics Letters A 291, 46 (2001).
 - [25] P.R Holland, The quantum theory of motion, Cambridge University Press, 1993.
 - [26] E.R .B ittner, J.Chem Phys. 112, 9703 (2000).
 - [27] M .D iVentra, S.T .Pantelides and N.D .Lang, ApplPhysLett. 76, 3448 (2000).
 - [28] S.F luge, Practical quantum mechanics, vol.1 Springer Verlag, 1971. (problem 20, p.39)
 - [29] R .Landauer, Philos.M ag. 21, 863 (1970).
 - [30] S.D atta, Electronic transport in mesoscopic systems Cambridge University Press, 1995.
 - [31] G .V ignale and M .Rasolt, PhysRevLett. 59, 2360 (1987).

Table 1. The energy of the active, ie current carrying $L \times R$, part of the system as a function of the steady current. $E_d = E_d(I) - E_d(I = 0)$ is the energy increase to establish of the current I carrying state.

I	$E_d(I)$	$E_d(I)$
0.00	0.4977	0.0000
0.01	0.4994	0.0017
0.02	0.5043	0.0066
0.03	0.5124	0.0147
0.04	0.5233	0.0256
0.05	0.5368	0.0391
0.06	0.5526	0.0549
0.07	0.5706	0.0729
0.08	0.5905	0.0928
0.09	0.6122	0.1145
0.1	0.6356	0.1379

Figure 1. The Lagrange multiplier $a(x)$ is plotted as a function of the coordinate x . Calculations were performed for the step function current density distribution $j = 0.1$ ($x \in [-2; 2]$).




Figure 2. The spatial dependences of real and imaginary components of the current carrying wave function. Calculations were performed for the step function current density distribution $j = 0.1 \cdot (x - 2; 2 - x)$. The dashed line on the upper panel is the ground state wave function of the system with zero current.




Figure 3. The spatial dependences of imaginary components of the wave functions are plotted for different values of the current. The current density is constrained to be the step function $j = I \cdot (x - 2; 2 - x)$. The solid line corresponds to $I = 0.01$, dotted to $I = 0.05$ and dashed to $I = 0.1$.

