

Role of interference in M M -wave driven D C transport in two dimensional electron gas

Dung-Hai Lee^{a,b}, and Jon Magne Leinaas^{a,c}

(a) Department of Physics, University of California at Berkeley, Berkeley, CA 94720, USA

(b) Material Science Division, Lawrence Berkeley National Laboratory and

(c) Department of Physics, University of Oslo, P.O. Box 1048 Blindern, 0316 Oslo, Norway

In this paper we point out that in addition to the density of states effect proposed in Ref.[3, 4] one should consider the effect of constructive interference between the multi-M M -wave-photon processes shown in Fig.2. This process enhances the dark value of the conductivity. When the sample is very pure, i.e., when the transport life time is very long, this interference effect quickly diminishes as the M M -wave frequency deviates from the cyclotron frequency. In this paper we also present the linear response theory in the presence of strong harmonic time-dependent perturbation.

PACS numbers:

The recent observation of strong suppression of the longitudinal resistivity of a two-dimensional electron gas (2DEG) by a millimeter (M M) radiation source [1, 2] has stimulated considerable interests in the condensed matter community [3, 4, 5, 6, 7, 8, 9, 10, 11, 12]. In Ref. [3] and Ref.[4] it is pointed out that the combined effect of photo-excitation by the M M wave photon and scattering by impurities can lead to a sinusoidal modulation of the conductivity as a function of $\omega_0 = \omega_c$ (the M M wave photon frequency over the cyclotron frequency). When the amplitude of this modulation becomes big, the conductivity becomes negative and the system becomes unstable. In Ref.[4] and Ref.[5] it is postulated that this leads the system to self-organize into a state with zero conductivity.

In this work we propose another mechanism that may also be of importance for the observed phenomenon. In essence our mechanism associates the above experimental results with a phenomenon called "electromagnetically induced transparency" [13]. This phenomenon occurs when an optical transition can take place through many alternative processes. When these processes destructively interfere with one another, the net optical transition amplitude vanishes. This has been observed when two of the levels of a three-level system is resonantly coupled together by a strong coupling laser. As a consequence, the resonant peak due to the absorption from the third level to one of these strongly mixed states is suppressed to zero.

In the present case we assume that the M M wave is sufficiently strong to couple many electronic states together. When an additional low frequency probing source is turned on, the transition that involves the absorption/emission of a single probing photon can occur via many virtual processes with varying number of M M wave photons absorbed and subsequently emitted. The interference between these processes can lead to electromagnetically induced transparency. The effect is illustrated in Fig.1 where the vertical arrows indicate the emission/absorption of the M M wave photons, and the slanted horizontal arrows indicate the absorption of the probing photons. If the matrix elements associated with the slanted horizontal arrows at different vertical levels




FIG. 1: The processes in this figure and their particle-hole inversion analog causes interference discussed in the text. The vertical lines represent absorption or emission of the coupling field photons. The slanted horizontal arrows correspond to the absorption of the probing field photon.

are in phase, this leads to constructive interference. Otherwise destructive interference will be resulted. In the D C limit (vanishing probing photon frequency) destructive interference implies a strong suppression of the longitudinal conductivity. This is equivalent to a suppression of the longitudinal resistivity when $\rho_{yy} \gg \rho_{xx}$. In the following we shall argue that the ratio between the M M wave frequency and the cyclotron frequency determines whether the interference is constructive or destructive.

Our picture of this $\omega_0 = \omega_c$ dependence is the following. When ω_0 is an integral multiple of ω_c , the M M wave couples together states that have (essentially) the same guiding center orbit but different Landau level indices. Due to energy conservation we argue that the absorption/emission of a (low frequency) probing photon can only change the guiding center orbits not the Landau level index. More explicitly we assume that, with the initial and final guiding center orbits of the processes depicted in Fig.1 being all the same, the matrix elements corresponding to the slanted horizontal arrows are approximately equal. The processes shown in Fig.1 tend therefore to interfere constructively. However, when ω_0 is not close to an integer multiple of ω_c , the initial and final guiding center orbits of the different slanted horizontal arrows are different. This will generally give rise to matrix elements with different phases and lead to destructive interference.

The mechanism discussed here (like in [3, 4]) the electron-electron interaction does not play a central role. However it is important to keep in mind that electron-electron interaction affects the self-consistent potential each electron sees hence affect the eigenstates $|j\rangle$ in Eq. (1). In particular in the mechanism proposed in Ref.[5] where significant redistribution of charges can be resulted by the action of the MM wave radiation, the steady-state self-consistent potential can differ significantly from that in the absence of MM wave radiation. In the rest of the paper we shall ignore the electron-electron interaction with the understanding that the potential the electrons see is the steady-state self-consistent one.

In the following we first develop the formalism for describing this problem. We obtain a Kubo-like formula (Eq. (29)) that allows one to compute the AC/DC conductivity in the presence of a strong harmonic time-dependent driving field. We would like to stress that method developed here is not restricted to the specific problem considered. Rather it is a general formulation of linear response in the presence of a strong time-dependent perturbation, and in this respect it is a step in the direction of making a systematic approach to describing the behavior of a many-particle system in a presence of a strong oscillating field.

We emphasize that the mechanism described here is requires the assumption that MM wave field acts coherently on the system. It is of interest to look for experimental tests of the importance of coherence. We suggest that application of two radiation sources to the same sample (see the concluding paragraph) is a good way to determine how important the interference effects are.

In the rest of the paper we shall use the term coupling field to denote the MM radiation field, and probing field to denote the low frequency field associated the linear response measurement.

I. THE GENERAL FORMALISM

A. The Floquet eigenvalue problem

Let us assume $|j\rangle$ are the exact single particle eigenstates (in the presence of disorder) in the absence of the coupling field

$$H_0 |j\rangle = \epsilon_j |j\rangle : \quad (1)$$

With the coupling field turned on, the Hamiltonian becomes

$$H(t) = H_0 + g_c e^{i\omega_0 t} \sum_{ij} P_{ij} |j\rangle \langle ij| + e^{i\omega_0 t} \sum_{ij} P_{ji} |i\rangle \langle jj| : \quad (2)$$

In the above ω_0 is the frequency of the coupling field, and P_{ij} is the matrix element of the current operator.

The solution of the time-dependent Schrodinger equation

$$i\partial_t |j(t)\rangle = H(t) |j(t)\rangle \quad (3)$$

can be written as

$$|j(t)\rangle = \sum_i |i(t)\rangle |j\rangle ; \quad (4)$$

where $|i(t)\rangle$ satisfies

$$i\partial_t |i(t)\rangle = \epsilon_i |i(t)\rangle + g_c e^{i\omega_0 t} \sum_j P_{ij} |j(t)\rangle + g_c e^{i\omega_0 t} \sum_j P_{ji} |j(t)\rangle : \quad (5)$$

Due to the symmetry of Eq. (5) upon time translation

$$t \rightarrow t + n \frac{2\pi}{\omega_0} ; \quad (6)$$

the solutions of Eq. (5) $|i(t)\rangle$ can be written in the form

$$|i(t)\rangle = e^{i\epsilon_i t} \sum_n |n_i\rangle e^{in\omega_0 t} ; \quad (7)$$

where the index n labels the different solutions. In the above

$$\frac{\omega_0}{2} \leq E < \frac{\omega_0}{2} \quad (8)$$

is the "Brillouin zone" in frequency. This time version of the Bloch theorem is called the Floquet theorem [14]. By substituting Eq. (7) into Eq. (5) and equate coefficients of $e^{i(E + n\omega_0)t}$ we obtain the time independent equation

$$E |n_i\rangle = (\epsilon_i + n\omega_0) |n_i\rangle + g_c \sum_j P_{ij} |n-1_j\rangle + P_{ji} |n+1_j\rangle : (9)$$

Eq. (9) is an algebraic eigenvalue problem which can be solved to obtain eigenvalue E and corresponding eigenvector $|n_i\rangle$. Since $|n_i\rangle$ and $|n_i\rangle$ are eigenvectors of Eq. (9), they satisfy (when properly normalized) the orthogonality relation

$$\sum_{n,i} (|n_i\rangle)^\dagger |n_i\rangle = 1 : \quad (10)$$

It is straightforward to prove the following fact concerning the solutions of Eq. (9). If $|n_i\rangle$ is the eigenvector of Eq. (9) with eigenvalue E , then

$$|n+1_i\rangle \quad (11)$$

is also an eigenvector of Eq. (9). The eigenvalue associated with the latter is

$$E_0 = E + \omega_0 : \quad (12)$$

By repeated application of Eq. (11) we can generate a family of solutions $\{ |j_i(t)\rangle \}_{i=0}^{\infty}$ of Eq. (9). It is simple to show that all these solutions lead to the same time-dependent solution

$$|j(t)\rangle = e^{iE_j t} \sum_{i=0}^{\infty} |j_i(t)\rangle \quad (13)$$

In the above $\{ |j_i(t)\rangle \}$ denotes the entire class of Floquet eigenvectors related by Eq. (11) and Eq. (12).

It is simple to prove that

$$\langle j(0) | j(0) \rangle = 1 \quad (14)$$

Thus

$$|j(t)\rangle = \sum_{i=0}^{\infty} |j_i(t)\rangle \quad (15)$$

can be used as an orthonormal basis just as $|f_i\rangle$. We also note that because the time evolution is unitary, Eq. (14) ensures that

$$\langle j(t) | j(t) \rangle = 1 \quad (16)$$

for any $t > 0$.

Now we have obtained the an orthonormal set of solution of the time-dependent Schrodinger equation

$$H |j(t)\rangle = E_j |j(t)\rangle \quad (17)$$

Of course, any linear combination of these solutions

$$\sum_{i=0}^{\infty} A_i |j_i(t)\rangle \quad (18)$$

is itself a solution of the Schrodinger equation. The coefficient A_i in Eq. (18) are determined by the initial condition. For example by properly choosing A_i we can construct a orthonormal set of solutions $|f_j(t)\rangle$ satisfying the Schrodinger equation and the initial condition that

$$|f_j(0)\rangle = |j\rangle \quad (19)$$

Using Eq. (14) and Eq. (15) it is simple to show that

$$|f_j(t)\rangle = \sum_{i=0}^{\infty} \langle j | j_i(t) \rangle |j_i(t)\rangle \quad (20)$$

To gain some intuitive feeling for what Eq. (9) represents we consider the following model. For each n in Eq. (9) we define a replica of the physical system with eigenspectrum given by Eq. (1). These replicas are coupled together by P_{ij} in the following Hamiltonian

$$H_r = \sum_{n,i} \epsilon_i |n\rangle \langle n|_i + g_c \sum_{n,i,j} P_{ij} c_{ni}^\dagger c_{nj} + h.c. \quad (21)$$

In the above c_{ni}^\dagger create an electron in the i th states of the n th replica. The physical interpretation of the n variable

is the photon number of the coupling field. The single particle states in the n th layer are $|f_j; i\rangle$, and the associated eigen energies are ϵ_i . The replicas are coupled together by hopping (the terms proportional to g_c), and an "electric field" is turned on so that the potential energy of the n th replica is ϵ_n . The replica model is constructed so that Eq. (9) is its time-independent eigen equation. Each solution $|j_i\rangle$ of Eq. (9) uniquely defines an eigen state

$$\sum_{n,i} |f_j; i\rangle \quad (22)$$

of the replica model. Eq. (11) and Eq. (12) link a whole family of replica states together.

B. The linear response theory

In this section we derive the formula for the AC conductivity in the presence of the coupling field. The formalism developed in this section is rather general. The only restriction is that the electron-electron interaction is neglected.

The AC conductivity is the response of the system to a time-dependent probing field. The Hamiltonian in the presence of such probing field is given by

$$H^0(t) = H(t) + H_p(t) \quad (23)$$

$$H_p(t) = g_p e^{i\omega_p t} \sum_{ij} D_{ij} |j\rangle \langle j| + h.c.$$

where D_{ij} is the current matrix element coupling to the probing field. Unlike the coupling field, the probing field is very weak. Therefore we will treat its effect perturbatively to the lower order in g_p .

If we use $|j_i(t)\rangle$ as basis, the probability amplitude that the probing field will induce a transition from $|j_i\rangle$ at time zero to $|j_j(t)\rangle$ at time t is given by

$$A_{ji} = \sum_{i=0}^{\infty} \langle j | H_p(t) | j_i \rangle \langle j_i | j \rangle + \dots \quad (24)$$

If we model the decoherence by a single decoherence time $\tau = 1/\Gamma$ the averaged transition rate between $i \neq j$ is given by

$$W_{ji} = 2 \int_0^{\infty} dt e^{-t/\tau} \langle j(t) | H_p(t) | j_i(t) \rangle^2 \quad (25)$$

Straightforward calculation shows that

$$W_{ji} = W_{ji}^a + W_{ji}^e \quad (26)$$

("a" stands for absorption and "e" stands for emission), where

$$W_{ji}^a = 2 \sum_{i=1}^{\infty} \frac{\langle jj \rangle D^1 \langle j_i \rangle^2}{E_i - E_j + \epsilon_p + \epsilon_0 + i} \quad (27)$$

$$W_{ji}^e = 2 \sum_{i=1}^{\infty} \frac{\langle jj \rangle D^1 \langle j_i \rangle^2}{E_i - E_j + \epsilon_p + \epsilon_0 + i}$$

In Eq. (27)

$$D^{-1} \sum_{n,ij} \sum_{n+1i} D_{ij}^{-1} n_j : \quad (28)$$

For the and in the summation we choose one and one for each family of solutions and . We note that if these are chosen so that $E_{ij} = E_{n+1i}$ is small compared to ϵ_0 (we shall assume this choice in the rest of the paper), the main contribution in the sum over l comes from $l=0$, since ϵ_p is small.

The total absorption and emission rates and the AC conductivity are given by

$$\begin{aligned} A &= \sum_{ij} f_i (1 - f_j) W_{ji}^a \\ E &= \sum_{ij} f_i (1 - f_j) W_{ji}^e \\ \sigma_{xx}(\epsilon_p) &= \frac{1}{\epsilon_p} \lim_{\epsilon_p \rightarrow 0} \frac{1}{\epsilon_p} (A - E); \end{aligned} \quad (29)$$

where $f_i = f(\epsilon_i)$ is the Fermi function and ϵ is the volume (or area for 2D) of the sample.

In the limit of $\epsilon_0 \rightarrow 0$ only the diagonal terms in the expansion of $j::j$ in Eq. (27) survive. In that case $E_{ij} = \epsilon_p$ is constrained to zero. For finite ϵ_p on the other hand $E_{ij} = \epsilon$ is not strictly fixed by energy conservation, but can take values within a range around ϵ_p . In this case A and E do not only get contributions from the diagonal terms in the expansion of (27) but also from crossing terms. When the phase coherence length is much smaller than the sample dimension, the above formula should also be averaged over the configurations of the random potential.

Eq. (27), Eq. (28) and Eq. (29), which express the linear response coefficients of a strongly driven system in terms of the eigenenergies and eigenfunctions of a time-independent Hamiltonian (H_r in Eq. (21)), is a main result of this paper.

C. A simple model

In order to illustrate the application of the above formalism we now consider a simple model where the "dark" energy levels are labeled by two parameters, $i = (j; a)$, and the energies are given by

$$\epsilon_a = \epsilon_0 + V_a \quad (30)$$

where $\epsilon_0 = 2 V_a < \epsilon_0 = 2$: In the following we shall refer to j as the "vertical" and a as the "horizontal" indices. We shall assume resonant coupling, i.e., the absorption/emission of a coupling photon results in vertical transition $j; a \rightarrow j+1; a$, and the absorption/emission of a probing photon results in horizontal transition $j; a \rightarrow j; b$. More specifically we consider

the following Hamiltonian

$$\begin{aligned} H(t) &= H_0 + H_c(t) + H_p(t) \\ H_c(t) &= g_c e^{i\epsilon_0 t} \sum_{a,j} P_{a,j+1} |a\rangle \langle j| + h.c. \\ H_p(t) &= g_p e^{i\epsilon_p t} \sum_{a,b} D_{a,b} |a\rangle \langle b| + h.c. \end{aligned} \quad (31)$$

To simplify the Floquet eigen equation we further assume

$$P_a = P : \quad (32)$$

Given Eq. (31) and Eq. (32) the Floquet eigenvectors are given by

$$|n\rangle = \sum_{a,j} |n\rangle_{a,j} \quad (33)$$

where $|n\rangle$ and a are parameters that characterize the Floquet eigenstate, and $|n\rangle$ satisfies

$$E_n = (V_a + \epsilon_0) |n\rangle + g_c (P_{n-1} + P_{n+1}) \quad (34)$$

This equation is invariant under translations $n \rightarrow n+1$ and has, according to Bloch's theorem, solutions of the form

$$|n\rangle = \frac{1}{N} e^{in} \quad (35)$$

For simplicity we assume the variable n to take a finite number of values N , with $|n\rangle$ as a periodic function. This implies

$$n = \frac{2\pi}{N} m; \quad m = 0, 1, \dots, N-1 \quad (36)$$

with n as a new discrete parameter that characterizes the state. The energy of the Floquet state now is given by

$$E = \epsilon_0 + \cos(2 \frac{n}{N} + \phi) \quad (37)$$

with the parameters ϕ and ϵ_0 defined by

$$e^{i\phi} = g_c P : \quad (38)$$

With the expressions for $|n\rangle$ and E_n inserted in Eq. (27), the absorption/emission rate gets the form

$$\begin{aligned} W_{ji}^{a=e} &= 2 \frac{1}{N^2} \sum_{pq} \frac{1}{N} \sum_{a,b} P_{a,b}^2 e^{2i\epsilon_p n} D_{a,b}^{+n} \\ &= \frac{1}{N^2} \sum_{a,b} \frac{1}{\sin(2 \frac{a}{N}) \sin(2 \frac{b}{N} + 2 \phi)} \frac{1}{\epsilon_p + i} : \end{aligned} \quad (39)$$

with $V_{ab} = V_a - V_b$. This expression is illustrated by the diagram of Fig. 1, referred to in the introduction. Without the coupling field turned on the transition induced by the probing field is restricted to one value of j for each pair $(a; b)$. However, with the coupling field on, the

contributions from higher levels $+n$ are introduced, as illustrated by the vertical arrows in the diagram and by the sum over n in the formula.

The variations of D_{ab}^{+n} with n may give rise to terms in Eq. (39) that adds constructively or destructively. If we assume no dependence on n , $D_{ab}^{+n} = D_{ab}$, the sum over n can be explicitly done giving rise to N_p , hence p only gets contribution from $p = 0$ and the expression reduces to its "dark value", i.e. its value without the coupling field

$$W_{ji}^{a=e} = 2 \frac{D_{ab}^2}{V_{ab} |p + i|} : \quad (40)$$

However, if the phase of D_{ab}^{+n} varies randomly with n

$$\frac{1}{N} \sum_n e^{i\phi_n} D_{ab}^{+n} = \frac{1}{N} \quad (41)$$

and the phase generically varies randomly with p . In the limit $\epsilon \rightarrow 0$ only the diagonal terms in the expansion of j_{ji} in Eq. (39) contribute and, owing to Eq. (41), $W_{ji}^{a=e} N^2 = N^3 = 1/N$. Hence we have destructive interference. When $\epsilon \neq 0$ but much smaller compared to ϵ_0 , the non-diagonal terms become important. In that case simple estimate leads to

$$W_{ji}^{a=e} = \frac{K}{N} \frac{h c_1}{N} + \frac{c_2}{N} + c_3 - \frac{2i}{N}; \quad (42)$$

where $K; c_1; c_2; c_3$ are n -independent constants. From Eq. (42) we see that the suppression by large N depends on $\epsilon \ll \epsilon_0$. It is important to note that in the simple model considered here the suppression of the DC/AC conductivity is complete only when $N \rightarrow 1$ and $\epsilon = 0$.

In the model we have introduced several simplifications, in particular only including resonant couplings. However, we believe this model convey the essence of our idea. We note however, that with the simplifications introduced we do not see enhancement of the amplitudes for constructive interference, but rather a return to the dark value.

II. APPLICATION TO THE 2-DIMENSIONAL ELECTRON GAS.

When discussing the application of the general formalism to the 2DEG, there are two regimes of interest to discuss separately. The first one is the weak coupling limit, where the Floquet state is well localized with respect to layer index n and where the coupling field as well, as the probing field, can be treated perturbatively. The other case is the strong coupling regime, where the state is extended through many n 's. We first treat the weak coupling case and discuss this in a general way with focus especially on the effect of the density of states. The strong coupling case we discuss more qualitatively, with specific reference to the simple model discussed in the previous section.

A. Weak coupling. The density of states effect.

In this limit the eigenstates of H_x are qualitatively similar to those in the absence of the hopping between the replica's. In this limit the our calculation produces result similar that obtained in Ref.[3] and Ref.[5]. For a comparison with these references we restrict ourselves to the case of total coherence, i.e. $\epsilon \rightarrow 0$.

Assuming n_i leaks weakly to the adjacent layers we obtain (upon using Eq. (15))

$$j > jj > + \sum_{j^0} X_{jj^0} jj^0 > + \sum_{jj^0} X_{jj^0} jj^0 > \\ j > ji^0 > + \sum_{i^0} X_{ji^0} ji^0 > + \sum_{ji^0} X_{ji^0} ji^0 > : \quad (43)$$

In the above $ji^0 >; jj^0 >$ are states with energy ϵ_0 above those of $ji >; jj >$ and $ji^0 >; jj^0 >$ has energy ϵ_0 below those of $ji >; jj >$. In the rest of this section we shall treat $ji^0 >$ and $jj^0 >$ as first order in the coupling constant g_c and obtain A and E to $O(g_c^2)$ by substituting Eq. (43) into Eq. (29) and take the $\epsilon \rightarrow 0$ limit. The result for A is

$$A = 2 \sum_{ji} g_p^2 \left(\epsilon_{ji} - \epsilon_p \right) f_i (1 - f_j) D_{ji}^0 + \sum_{ij} X_{ij} \left(\epsilon_{ji} - \epsilon_0 - \epsilon_p \right) f_i (1 - f_j) j D_{ji}^0 + \sum_{ij} X_{ij} \left(\epsilon_{ji} - \epsilon_p \right) f_i \sum_{j^0} h X_{jj^0} (1 - f_{j^0}) j j j^0 + \sum_{ij} X_{ij} \left(\epsilon_{ji} - \epsilon_p \right) \sum_{i^0} h X_{ji^0} j j i^0 f_{i^0} (1 - f_j) D_{ji}^0 : \quad (44)$$

In the above

$$\epsilon_{ji} = \epsilon_j - \epsilon_i; \quad (45)$$

and D_{ji}, D_{ji}^0 are of order $O(\epsilon)$ respectively.

The first term of Eq. (44) is the value in the absence of coupling field (the matrix elements are slightly modified). distribution function due to the coupling laser. If we assume that the matrix elements in Eq. (44) are smooth function of energy we can replace this equation by

$$A = 2 \sum_{ji} g_p^2 \int dE f(E) (1 - f(E + \epsilon_p)) N(E) \\ N(E + \epsilon_p) M_1 + \int dE N(E) N(E + \epsilon_0 + \epsilon_p) \\ f(E) (1 - f(E + \epsilon_0 + \epsilon_p)) M_2; \quad (46)$$

where M_1 and M_2 are E -dependent functions that we do not write out explicitly. The corresponding emission

term is given by

$$E = 2 \frac{\hbar^2}{g_p^2} \sum_Z dE f(E) (1 - f(E - \epsilon_0 - \epsilon_p)) N(E) \\ N(E - \epsilon_p) M_1^2 + \sum_Z dE N(E) N(E + \epsilon_0 - \epsilon_p) \\ f(E) (1 - f(E + \epsilon_0 - \epsilon_p)) M_2^2 \quad (47)$$

From Eq. (46) and Eq. (47) we can compute the DC conductivity via

$$\sigma_{xx} = \lim_{\epsilon_p \rightarrow 0} \frac{A}{\epsilon_p} \frac{E}{\epsilon_p} : \quad (48)$$

If we take a simple form

$$N(E) = N_0 + N_1 \cos \frac{2E}{\epsilon_c} ; \quad (49)$$

as suggested at the beginning of Ref.[3], and assume M_1 and M_2 to be functions changing slowly with E , we obtain from Eq. (48), Eq. (46) and Eq. (47) the result

$$\sigma_{xx} = \frac{0}{\sigma_{xx}} + \frac{1}{\sigma_{xx}} \sin \frac{2\epsilon_0}{\epsilon_c} + ; \quad (50)$$

where $\epsilon_c = \tan^{-1}(k\epsilon_c - \epsilon_0)$ and $k = 1 + 2N_0/N_1$. This result is in qualitative agreement with that obtained in Ref.[3, 4].

B. Strong coupling. Constructive and destructive interference.

When the coupling constant g_c in Eq. (2) is large, the eigenstates of Eq. (21) become extended among many replicas, i.e. ϵ_{ni} is non-zero for a very wide range of n . For the electrons in the magnetic field this means that the MM field couples together many states, generally located at different guiding center orbits. The states coupled together will be selected by the condition of having the energy difference in resonance (or close to resonance) with the oscillating field.

The dipole matrix element of the coupling laser primarily couples states at neighboring Landau levels and the same guiding center orbit, or close by guiding center orbits in the same Landau level. However, the observed effect, with strong variations in the conductivity when the frequency of the coupling field matches integer multiples of the cyclotron frequency, indicates a rather strong coupling also between non-adjacent Landau levels. Such coupling clearly requires Landau level mixing. This mixing may be due to the presence of a dilute concentration of strong and localized scatterers and/or high gradients in the potential at the sample edge. In this picture the electrons mainly drift adiabatically in a smooth background potential, but occasionally encounter regions of high potential gradients where the Landau levels is mixed. Due to the dilute concentration of such regions, the effect on

e.g. the density of state can be very small. However for a strong coupling field this is enough to generate sufficient coupling to distant Landau levels/distant guiding center orbits that is required to delocalize the Floquet eigenstates among many replicas. For the transitions induced by the probing field this mixing is less important, since the low frequency transitions are limited to close by orbits in the same Landau level.

Let us first consider the case where the coupling source is tuned to one of the frequencies $m\epsilon_c$, with integer m . The matrix elements D_{ij} of the probing field in the sum of Eq. (28) now are defined between the same pair of guiding center orbits elevated to higher Landau levels by the coupling field. The model of the previous section can be viewed as giving a simplified description of this situation, with the "vertical" index identified with the Landau level index and the "horizontal" index a labelling the guiding center orbit.

The matrix elements D_{ab} now describe transitions between the same two guiding center orbits a and b at different Landau levels. These matrix elements are strongly correlated and we have checked that in an adiabatic approach they are only slowly dependent on the Landau level index.

As previously discussed, with D_{ab} independent of n , the sum over n in Eq. (39) will include terms that interfere constructively. Although one should note that in the expression found there was no enhancement relative to the dark value. Such an enhancement is clearly present in the observed effect. We believe such an enhancement is due to an increase in the magnitude of D_{ab} with and/or to the effect of including non-resonant terms both of which are ignored in our simple model.

Let us next turn to the case where the coupling frequency is not close to $n\epsilon_c$. In this case different $j; a >$ and $j + 1; a >$ label two distant guiding center orbits with the potential energy of the second orbit ϵ_0 higher than that of the first.

Since the matrix element D_{ab} , for different n , refers to transitions between distant pairs of guiding center orbits, they are no longer strongly correlated and may change substantially from one value of n to the next. In an adiabatic approximation the matrix element can be related to variations in the drift velocity along the guiding center orbit, and in a randomly varying background potential we therefore expect a corresponding random variation in the matrix element. In this case the n sum in Eq. (39) add destructively.

To recap, the difference between the case $\epsilon_0 = m\epsilon_c$ and $\epsilon_0 \neq m\epsilon_c$ lies in the fact that for the former the n sum in the absorption/emission amplitude tend to add non-destructively, whereas for the latter the sum tend to add destructively. Thus, we propose that in addition to the density of state mechanism discussed in Ref.[3, 4], and seen in our discussion of the weak coupling limit, the above interference mechanism will contribute, for ϵ_0 between integer multiples of ϵ_c , to suppress the magnitude of the longitudinal resistivity. This can reduce the

resistivity or even suppress it to zero when the effect is very strong. However, since our discussion at this point is qualitative, we cannot estimate the real strength of the effect.

III. SUMMARY

In this paper we present a general formalism for describing the DC/AC transport in the presence of an oscillating coupling field. The oscillating field couples together states in the form of a Floquet state, and by use of the expression for this state we derive a general form for the absorption and emission probabilities of an additional low frequency probing field. This gives a generalized Kubo formula for the conductivity in the presence of an oscillating field.

We further discuss in a general way the application of this to the 2D electron gas in a magnetic field radiated by a MM wave. For a weak coupling field we show the presence of oscillations due to variations in the density of states. For strong coupling we discuss in a qualitative way the difference between constructive interference when the frequency matches the energy difference between two Landau levels and destructive interference for intermediate values of the frequency. The discussion of the interference effects is illustrated by a simplified model.

Quantum interference between different virtual pro-

cesses described in this paper should in general exist. However, complete destructive interference requires a large number of interfering processes and small decoherence. We are currently uncertain about the values of these parameters for the experimental system. The mechanism presented here raises the question of whether an independent study of the strength of coherence effects can be performed. Clearly, if the coherent MM source is replaced by an incoherent source at the same frequency the coherence effects will be destroyed. As a simpler experiment we suggest that the importance of coherence for the observed effect can be studied by use of two independent coupling fields. If one of these is tuned to one of the peak values (say $2!_c$) and the other to a suppressed value (say, around $\frac{1}{2}!_c$), we predict that the effect of the second source will be to suppress the peak of the first source, even to destroy the peak completely if the coherent effect is sufficiently strong.

Acknowledgments

We thank R. Chiao, R. R. Du, T. H. Hansson, and Z. Wang for helpful discussions. DHL is supported by DOE. DHL is supported by DOE grant DE-AC03-76SF00098. JML has been associated with the Miller Institute for Basic Research in Science as a visiting professor in the fall of 2002 and will acknowledge the financial support and the hospitality of the Miller institute.

-
- [1] M. A. Zudov, R. R. Du, J. A. Simmons and J. L. Reno, Phys. Rev. B 64, 201311 (2001); M. A. Zudov, R. R. Du, L. N. Pfeiffer and K. W. West, Phys. Rev. Lett. 90, 046807 (2003).
 - [2] R. G. Mani, J. H. Smet, K. von Klitzing, V. Narayana-murti, W. B. Johnson and V. Umansky, Nature, 420, 646 (2002).
 - [3] A. C. Durst, S. Sachdev, N. Read and S. M. Girvin, cond-mat/0301569 (2003).
 - [4] P. W. Anderson and W. F. Brinkman, cond-mat/0302129.
 - [5] A. V. Andreev, I. L. Aleiner and A. J. Millis, cond-mat/0302063.
 - [6] J. Shi and X. C. Xie, cond-mat/0302393.
 - [7] J. C. Phillips, cond-mat/0303184.
 - [8] F. S. Bergeret, B. Huckestein and A. F. Volkov, cond-mat/0303530.
 - [9] S. I. Doroshkin, cond-mat/0304604.
 - [10] V. Ryzhii and V. V. Yurkov, cond-mat/0305199.
 - [11] K. N. Shrivastava, cond-mat/0305032.
 - [12] P. H. Rivera and P. A. Schulz, cond-mat/0305019.
 - [13] See, e.g., M. O. Scully and M. S. Zubairy, "Quantum Optics", page 220. Cambridge University Press, 1997.
 - [14] See, e.g., Morse and Feshbach, "Method of Theoretical Physics", Part I, page 557. McGraw-Hill, New York, 1953.
-