

## Heisenberg constraints on mesoscopic and molecular amplifiers

U. Gavish<sup>1</sup>, B. Yurke<sup>2</sup>, Y. Imry<sup>3</sup><sup>1</sup>LKB, Ecole Normale Supérieure, Paris<sup>2</sup>Bell Labs, Lucent Technologies, Murray Hill, NJ<sup>3</sup>Condensed Matter Physics Dept., Weizmann Institute, Rehovot

Heisenberg uncertainty relations for current components impose constraints on the performance of linear amplifiers. Here we derive such constraints for amplifiers in which the input signal modulates a bias current in order to produce an amplified output. These amplifiers include transistors, macroscopic, mesoscopic, or molecular, operated as linear amplifiers.

## 1 Introduction

Commutation relations or Heisenberg uncertainty relations for observable associated with the inputs and outputs of amplifiers have played an important role in determining the optimum performance that can be achieved by amplifiers and detectors<sup>1–14</sup>. Most of these discussions have focused on maser, laser, and optical parametric amplifiers, the first devices to achieve nearly quantum limited performance. The arguments that establish the quantum limited performance of amplifiers of the electromagnetic field, such as optical amplifiers, do not directly carry over to devices that employ fermionic currents. It is thus worth addressing the issue of the quantum limits of amplifier performance in a way that is directly applicable to semiconductor devices, particularly since semiconductor device development, such as in the case of single electron transistors<sup>8,12</sup>, has proceeded to the point where quantum limited performance seems to be within reach. Here we present further results in our investigation<sup>16</sup> of quantum mechanical restrictions on transistor amplifier performance.

Let  $I_{in}$  denote the current delivered by a signal source to the input of an amplifier and  $I_{out}$  denote the current delivered by the amplifier to a load. Ideally, the relation between these two currents would be

$$I_{out}(t) = G_p \sqrt{\frac{g_l}{g_s}} I_{in}(t); \quad (1)$$

where  $G_p^2$  is the power gain and  $g_s$  and  $g_l$  are the differential conductances of the source and load respectively. However, for  $G_p \notin 1$ , the current-current commutation relations required by quantum mechanics cannot be satisfied. This situation is remedied by replacing Eq. (2) with

$$I_{out}(t) = G_p \sqrt{\frac{g_l}{g_s}} I_{in}(t) + I_N(t); \quad (2)$$

where  $I_N(t)$  is a current operator associated with noise generated within the amplifier. As noise,  $I_N$  is independent of  $I_{in}$  and the two commute:  $[I_{in}; I_N] = 0$ :

We consider the case when the current  $I(t)$  is investigated with detectors that respond over only over a frequency window  $\omega$  around a center frequency  $\omega_0$ . Introducing the Fourier transform

$$I(t) = \frac{1}{2\pi} \int_{-\infty}^{\infty} d\omega I(\omega) e^{-i\omega t}; \quad (3)$$

the current sensed by the detectors is then given by

$$I(t) = \frac{1}{2\pi} \int_{-\infty}^{\infty} d\omega I(\omega) + H \mathcal{X} \quad (4)$$

where we defined the band-integrated current transform (analogous to the annihilation operator of the harmonic oscillator) by

$$I(\omega) = \int_{-\infty}^{\infty} I(t) e^{-i\omega t} dt \quad (5)$$

For an ideal power amplification (i.e. when one is interested in transferring maximum power from the system to the amplifier and from the amplifier to a load resistor) in a stationary (though nonequilibrium) state it has been shown<sup>15</sup> in Ref. 16 that  $I_N$  satisfies

$$\langle I_N(\omega); I_N^\dagger(\omega) \rangle = (G_P^2 - 1) \frac{\hbar \omega}{2} g, \quad (6)$$

and

$$I_N^2(t) = (G_P^2 - 1) \frac{\hbar \omega}{2} g_1 \quad (7)$$

provided  $\hbar \omega = \hbar \omega_0 \ll \hbar \omega_0$ , where  $A = (\hbar \omega_0^2 i - \hbar \omega_0^2)^{1/2}$ ; Eq. 7 is a very general constraint on the minimal noise added in linear amplification. The basic assumptions in its derivation are that the amplifier is linear (i.e. that Eq. 2 holds), that the total system is in a stationary state, and that the differential conductance of the amplifier remains constant independently of the input current signal. These assumptions make possible the derivation through the application of Kubo's fluctuation-dissipation theorem<sup>17,18</sup> generalized to nonequilibrium steady states<sup>19-22</sup>.

We turn now to considering a more specific class of devices, namely transistor amplifiers (such as, for example, field effect, single-electron, or molecular transistors). A typical feature of these devices is that they operate in a nonequilibrium current-carrying state even in the absence of coupling to an input signal. This nonequilibrium current is accompanied by shot-noise – the nonequilibrium current fluctuations. It is therefore natural to ask whether the constraint Eq. 7 can be refined to take the existence of this noise into account. The positive answer to this question is stated in the next section, and derived in the last one.

## 2 Main result

Consider a specific case of a linear amplifier operating in a stationary state where current is flowing through it even in the absence of a coupling to any signal. In this case it is useful to write  $I_N$  in Eq. 2 as a sum of two currents:

$$I_N = I_0 + I_n \quad (8)$$

where  $I_0$  is the current of the amplifier before the coupling interaction between the signal and the amplifier is turned on and  $I_n$  is the change in  $I_N$  due to switching on the coupling. Assume now that the coupling is proportional to a small dimensionless parameter,  $\epsilon$ : Since  $I_0$  existed before  $\epsilon$  was switched on, it is of zeroth order in  $\epsilon$ ;  $I_n$  appeared as a result of the coupling and therefore it is of higher order in  $\epsilon$ : Also the power gain  $G_P$  is of higher order in  $\epsilon$  since no coupling implies no gain. We assume that  $I_n$  is of higher order in  $\epsilon$  than the gain. Our main result states that the following inequality must be satisfied:

$$I_0(t) I_n(t) \geq \frac{1}{4} G_P^2 \hbar \omega g, \quad (9)$$

Eq. 9 has several nontrivial consequences. For example, it implies that the "old" shot-noise  $I_0^2(t)$  is necessary for an ideal operation of the amplifier since coupling a device with vanishing shot-noise to a signal will result in the appearance of "new" shot noise  $I_n^2(t)$  which should diverge in order to maintain the inequality in Eq. 9.

### 3 Derivation of the Heisenberg constraint

To derive Eq.9 we make use of Eq.6 twice, first in the presence and then in the absence of the coupling. The current noise in these cases is given by

$$\begin{aligned} I_N &= I_0 + I_n \neq 0 \\ I_N &= I_0 = 0 \end{aligned} \quad (10)$$

Inserting these into Eq.6 yields

$$\begin{aligned} \langle I_0(t_0); I_0^Y(t_0) \rangle + \langle I_n(t_0); I_0^Y(t_0) \rangle + \langle I_0(t_0); I_n^Y(t_0) \rangle + \langle I_n(t_0); I_n^Y(t_0) \rangle \\ = (G_p^2 - 1) \frac{\hbar \omega_0}{2} g, \quad (11) \end{aligned}$$

and

$$\langle I_0(t_0); I_0^Y(t_0) \rangle = \frac{\hbar \omega_0}{2} g, \quad (12)$$

where we have used the fact that  $G = 0$  when  $\omega = 0$ : Subtracting the last equation from the previous one, one gets

$$\langle I_n(t_0); I_0^Y(t_0) \rangle + \langle I_0(t_0); I_n^Y(t_0) \rangle + \langle I_n(t_0); I_n^Y(t_0) \rangle = G_p^2 \frac{\hbar \omega_0}{2} g, \quad (13)$$

Since we assumed that  $I_n$  is of higher order in  $\omega$  than the gain, the term  $\langle I_n(t_0); I_n^Y(t_0) \rangle$  is of higher order in  $\omega$  than the three other terms in Eq.13. Since this equation should hold for any value of  $\omega$  small enough for the amplifier to be regarded as linear,  $\langle I_n(t_0); I_n^Y(t_0) \rangle$  must vanish. Thus, Eq.13 becomes:

$$\langle I_n(t_0); I_0^Y(t_0) \rangle + \langle I_0(t_0); I_n^Y(t_0) \rangle = G_p^2 \frac{\hbar \omega_0}{2} g, \quad (14)$$

We now use the fact that for any pair of hermitian Heisenberg operators  $A_1(t)$  and  $A_2(t)$ , one has

$$\langle A_i(t_0) \rangle = 0 \quad \omega_0 \neq 0 \quad i = 1, 2; \quad (15)$$

and

$$\langle A_2(t_0) A_1(t_0) \rangle = \langle A_1(t_0) A_2(t_0) \rangle = 0 \quad (16)$$

where  $A_i(t_0) = \int_{t_0 - \frac{1}{2}}^{t_0 + \frac{1}{2}} dt \frac{1}{2} \int_{-1}^1 dt_1 e^{i\omega t_1} A_i(t_1)$ ;  $i = 1, 2$ ; provided that the averages are performed in a stationary state (the proof of Eq.16 is straightforward by substitution of the definition of  $A_i(t_0)$ ; making a change of the integration variables  $t_1 = t_1 - t_2$ ;  $t_2 = \frac{1}{2}(t_1 + t_2)$  and integrating over  $t_2$ ). Taking  $A_1 = I_0$  and  $A_2 = I_n$ ; Eq.16 enables us to rewrite Eq.14 in the form of an expectation value of a commutator of two hermitian operators  $I_n(t_0) + I_n^Y(t_0)$  and  $i(I_0^Y(t_0) - I_0(t_0))$  which are analogous to a position and a momentum operator, respectively, or to the field quadrature components of quantum optics:

$$\langle I_n(t_0) + I_n^Y(t_0); i(I_0^Y(t_0) - I_0(t_0)) \rangle = iG_p^2 \frac{\hbar \omega_0}{2} g, \quad (17)$$

This implies the uncertainty relation

$$\langle I_n(t_0) + I_n^Y(t_0) \rangle \langle i(I_0^Y(t_0) - I_0(t_0)) \rangle \geq \frac{1}{2} G_p^2 \frac{\hbar \omega_0}{2} g, \quad (18)$$

Eqs. 15 and 16 also imply (together with Eq.4):

$$\begin{aligned} (I_n(t_0) + I_n^y(t_0))^2 &= 2 h I_n^2(t) i \\ (i(I_0^y(t_0) - I_0(t_0)))^2 &= 2 h I_0^2(t) i: \end{aligned} \quad (19)$$

Finally, substituting the last two equalities into Eq.18 one recovers the constraint, Eq.9.

To conclude, a novel Heisenberg constraint on shot-noise carrying linear amplifier was obtained. This constraint relates the device shot noise before coupling to the signal and the one added due to this coupling. One consequence of this relation is that an attempt to indefinitely reduce the shot-noise in the device in the absence of a signal will result in the appearance of diverging new shot-noise after the coupling to the signal is switched on.

#### Acknowledgments

The research at WIS was supported by a Center of Excellence of the Israel Science Foundation (ISF) and by the German Federal Ministry of Education and Research (BMBF), within the framework of the German-Israeli Project Cooperation (DIP).

#### References

1. K. Shimoda, H. Takahasi, and C. H. Towns, J. Phys. Soc. Japan 12, 686 (1957).
2. H. Heiser and G. Wade, J. Appl. Phys. 29, 1262 (1958).
3. W. H. Louisell, A. Yariv, and A. E. Siegman, Phys. Rev. 124, 1646 (1961).
4. H. A. Haus and S. A. Mullen, Phys. Rev. 128, 2407 (1962).
5. H. Takahasi, Advances in Communication Systems, ed. A. V. Balakrishnan (Academic, New York, 1965).
6. C. M. Caves, K. S. Thorne, R. Drever, V. Sandberg, and M. Zimmermann, Rev. Mod. Phys. 52, 341 (1980).
7. C. M. Caves, Phys. Rev. D 26, 1817 (1982).
8. See e.g. M. H. Devoret and R. J. Schoelkopf, Nature 406, 1039 (2000) and references therein.
9. B. Yurke and J. S. Denker, Phys. Rev. A 29, 1419 (1984).
10. H. P. Yuen, Phys. Rev. A 13, 2226 (1976).
11. J. N. Hollenhorst, Phys. Rev. D 19, 1669 (1979).
12. M. D. LaHaye, O. Buu, B. Camarota, and K. C. Schwab, Science 304, 74 (2004).
13. D. V. Averin, cond-mat/0301524.
14. A. A. Clerk, S. M. Girvin and A. D. Stone Phys. Rev. B 67, 165324 (2003).
15. Eqs.6 and 7 here are immediately obtained from Eqs.11,12, 26-30, 35 and 37 in Ref. 16.
16. U. Gavish, B. Yurke and Y. Imry "Generalized Constraints on Quantum Amplification" cond-mat/0407415.
17. R. Kubo, Can. J. Phys. 34, 1274 (1956).
18. R. Kubo, J. Phys. Soc. Japan, 12, 570 (1957);
19. L. D. Landau and E. M. Lifshitz, Statistical Physics Part 1, 3rd ed., Sec. 126, Butterworth Heinemann (1997).
20. U. Gavish, Y. Levinson and Y. Imry, Proc. of Rencontres de Moriond 2001: Electronic Correlations: from Mesoscopic to Nanophysics, T. Martin et al., eds. EDP Science 2001.
21. U. Gavish, Y. Imry, and B. Yurke, Vol. 5449, 257, Proc. SPIE Noise Conference, Grand Canary, 2004, cond-mat/0404270.
22. D. Cohen, Ann. Phys. 283, 175 (2000).