

Feedback effects on the current correlations in Y-shaped conductors

Shin-Tzsa Wu¹ and Sungkit Yip²¹Department of Physics, National Chung-Cheng University, Chiayi 621, Taiwan²Institute of Physics, Academia Sinica, Nankang, Taipei 115, Taiwan

(Dated: January 13, 2002)

We study current fluctuations in a Y-shaped conductor connected to external leads with finite impedances. We show that, due to voltage fluctuations in the circuit, the moments of the transferred charges cannot be obtained from simple rescaling of the bare values already in the second moments. The cross-correlation between the output terminals can change from negative to positive under certain parameter regimes.

PACS numbers: 05.40.-1, 72.70.+m, 73.23.-b, 74.40.+k

Current fluctuations in mesoscopic systems are of intense interest recently. Besides the fact that they inevitably exist and become more important in electric circuits when these are miniaturized, it is now well-appreciated that they contain interesting and fundamental physics (see, e.g., [1, 2, 3]). For example, Fermi statistics of the electrons are responsible for the reduction of the shot noise as compared with a corresponding system of classical or Bosonic particles. Furthermore, the same Fermi statistics of the charge carriers have important implications in multi-terminal setups. The quantity of interest in this case is the cross-correlation between different terminals [1, 4, 5, 6]. Experiment of this type is the solid-state analogue of the Hanbury Brown-Twiss experiment in quantum optics [7]. It has been shown that generally Fermi statistics implies that the cross-correlations between the currents in two different output arms are negative [4, 5, 6]. This theoretical result assumes non-interacting electrons and is supported by experiments available so far [8].

The sign of this cross-correlation has triggered many investigations into the question as to under what circumstances it would be reversed. Several mechanisms have been proposed. A few invoke possible electronic ground states that are not normal metallic (Landau-Fermi liquid) states, such as superconducting (e.g. [9]), quantum Hall, or Luttinger liquids states (e.g. [10]). Still another mechanism has been proposed relying on finite frequency and capacitive couplings [11], and one in ferromagnetic system based on "bunching" of transferred electrons due to spin blockade [12].

Here we show that a feedback mechanism in the presence of external impedances can also lead to this sign change. We consider the system as shown in Fig. 1. The "sample" A is a Y-shaped conductor in which electrons propagate coherently. It can consist of tunnel barriers or diffusive conductors, and is connected to external resistors Z_a , Z_b and Z_c . Our considerations are also of relevance for practical measurements (c.f. [13]). In measurements of cross-correlations, one injects an incident beam of charge carriers (here from reservoir a) and then splits the beam into two parts using a "beam splitter",

such as the Y-shaped conductor here. One would like to measure the current correlation between two output terminals, here b and c . In most current measurements however, one needs to couple the sample to external measuring circuits. For example, here we are considering the case where the current measurements are actually made by voltage measurements across the impedances Z_b and Z_c . If the external measuring circuit can be idealized as having zero impedance, then the voltage across the sample would be non-fluctuating and the current fluctuations are entirely due to intrinsic properties of the sample and the carriers. With finite external impedances, the voltage across the sample then becomes fluctuating and the current correlations will be modified.

Previously, feedback due to the presence of external impedances has been considered for two-terminal conductors [1], and more recently, in the context of third moment of the shot noise [13, 14, 15, 16]. The results based on the Langevin formalism [1] concluded that the second moments of current fluctuations can be obtained from the corresponding zero-impedance (intrinsic or "bare") values by a simple scaling. However, it was shown, using both a Keldysh technique [14, 15] and the Langevin formalism [15, 16], that this rescaling breaks down at the third moment. In this work we show that, for our three-terminal setup, even the second moment cannot be obtained from a rescaling of the corresponding bare value. For instance, the cross-correlation acquires contributions from auto-correlators. Since the bare auto-correlators are always positive, it is then possible to have positive cross-correlations in appropriate parameter regimes. The effect of external impedances on current fluctuations of multi-terminal circuits has also been considered by Buttiker and his collaborators [1] using the Langevin formalism. However, they considered a multiprobe measurement of a two-terminal conductor and thus not directly our geometry here.

We have performed the calculations using both the Langevin and Keldysh formalisms [17]. The results are identical. To illustrate the physics more clearly, let us first consider a simplified case where only $Z_b \neq 0$ using the Langevin formalism. Let us first introduce some

short-hand notations. We denote the conductances of the three arms of our sample as G_a, G_b, G_c . We shall denote $G = G_a + G_b + G_c$ and also the dimensionless parameters $\alpha = G_a/G$ etc (thus $\alpha + \beta + \gamma = 1$). In the present situation, the potentials ϕ_1 and ϕ_3 at points 1 and 3 are given by the external potentials V_a and V_c respectively and do not fluctuate. However, the quantity ϕ_2 is a fluctuating quantity. The current in an arm b , say, is a linear combination of two contributions, one being linear in the bias potentials ϕ 's and another due to the Langevin noise. Thus we have

$$I_b = G_b [\alpha (V_a - V_c) + \phi_2] + I_b^L \quad (1)$$

The first term follows easily from circuit theory. I_b^L is the Langevin noise whose expectation value is zero. We shall specify its variance later. Similarly for arm c , we have

$$I_c = G_c [\gamma V_a + \beta \phi_2] + I_c^L \quad (2)$$

The fluctuating potential ϕ_2 is related to I_b by

$$\phi_2 = I_b Z_b \quad (3)$$

(We are interested in the zero frequency limit so the current along arm A_b is equal to that through the resistor Z_b .) By taking the expectation values of (1)-(3), we can obtain $\overline{I_b}$, $\overline{I_c}$ and $\overline{\phi_2}$. In particular, we have

$$\overline{\phi_2} = \frac{1}{Z_t} Z_b G_a \beta V_a \quad (4)$$

Here $Z_t = 1 + Z_b G_b (\alpha + \gamma)$ is a dimensionless quantity. Subtracting the expectation values of Eqs. (1)-(3) from these equations themselves, we find, by eliminating ϕ_2 in favor of I_b , $\overline{I_b}$,

$$\overline{I_b} - I_b = \frac{1}{Z_t} I_b \quad (5)$$

$$\overline{I_c} - I_c = \frac{1}{Z_t} Z_b G_b \gamma I_b + I_c^L \quad (6)$$

From these, we can readily obtain the fluctuations $\delta I_b, \delta I_c$ etc. (We leave out the frequency variables for simplicity here. See below for more accurate notations). In particular,

$$\delta I_b \delta I_c = \frac{1}{Z_t^2} Z_b G_b \gamma \delta I_b \delta I_b + \frac{1}{Z_t} \delta I_b \delta I_c^L \quad (7)$$

This shows immediately that the cross-correlation has several contributions. Besides one which is a rescaling of the "bare" correlator $\delta I_b \delta I_c$, there is another contribution being proportional to $\delta I_b \delta I_b$. The origin of this latter term is obvious also from the above derivation, that is, the sample is "driven" by the potential ϕ_2 which is itself fluctuating. To complete the calculation we need the expressions for $\delta I_b \delta I_b$ and $\delta I_b \delta I_c^L$. For this, we have to notice that the sample is now biased at voltages V_a at point 1, ϕ_2 at point 2, and 0 at point 3. Let us denote the bare (superscript (0)) correlators $C_{bc}^{(0)}$ by the expression $\delta I_b (!) \delta I_c (!^0) = 2 (! + !^0) C_{bc}^{(0)}$ etc. In the shot noise (temperature $T \rightarrow 0$) regime, we expect these correlators to be linear combinations of contributions that are proportional to the average potential differences, i.e.,

$$C_{bb}^{(0)} = e = s_{bb}^{(b)} (V_a - \overline{\phi_2}) + s_{bb}^{(c)} (V_c - 0); \quad (8)$$

$$C_{bc}^{(0)} = e = s_{bc}^{(b)} (V_a - \overline{\phi_2}) + s_{bc}^{(c)} (V_c - 0); \quad (9)$$

The values of the coefficients $s_{bb}^{(b)}$ etc will be given below. Here the superscripts are denoted according to the potentials relative to a and the subscripts, the currents. Writing $\delta I_b (!) \delta I_c (!^0) = 2 (! + !^0) C_{bc}$, we can now obtain the "renormalized" correlator C_{bc} (which is also proportional to the correlators for transferred charges) from Eq. (7), using (4), (8) and (9):

$$C_{bc} = \frac{(Z_b G_b \gamma) (1 + Z_b G_b \gamma)}{Z_t^3} s_{bb}^{(b)} + \frac{(1 + Z_b G_b \gamma)}{Z_t^2} s_{bc}^{(b)} + \frac{(Z_b G_b \gamma)}{Z_t^2} s_{bb}^{(c)} + \frac{1}{Z_t} s_{bc}^{(c)} eV \quad (10)$$

The modifications needed for our general case are straight-forward in principle. We simply state our final results:

$$C_{bb} = \frac{eV}{Z_t^3} (P + S) P^2 s_{bb}^{(b)} + Q^2 s_{cc}^{(b)} + 2PQ s_{bc}^{(b)} + (Q + R) P^2 s_{bb}^{(c)} + Q^2 s_{cc}^{(c)} + 2PQ s_{bc}^{(c)} \quad (11)$$

$$C_{cc} = \frac{eV}{Z_t^3} (P + S) S^2 s_{bb}^{(b)} + R^2 s_{cc}^{(b)} + 2SR s_{bc}^{(b)} + (Q + R) S^2 s_{bb}^{(c)} + R^2 s_{cc}^{(c)} + 2SR s_{bc}^{(c)} \quad (12)$$

$$C_{bc} = \frac{eV}{Z_t^3} (P + S) P S s_{bb}^{(b)} + Q R s_{cc}^{(b)} + (P R + Q S) s_{bc}^{(b)} + (Q + R) P S s_{bb}^{(c)} + Q R s_{cc}^{(c)} + (P R + Q S) s_{bc}^{(c)} \quad (13)$$

In these equations

$$\begin{aligned} Z_t &= \alpha (1 + G Z_b \beta) (1 + G Z_c \gamma) \\ &+ \beta (1 + G Z_c \gamma) (1 + G Z_a \alpha) \\ &+ \gamma (1 + G Z_a \alpha) (1 + G Z_b \beta) \end{aligned} \quad (14)$$

is a dimensionless number, and the symbols $P; Q; R; S$

stand for

$$\begin{aligned} P &= 1 + Z_a G_{ac} + Z_c G_{cb} (a + b); \\ Q &= Z_a G_{ab} + Z_c G_{bc}; \\ R &= 1 + Z_a G_{ab} + Z_b G_{ba} (a + c); \\ S &= Z_a G_{ac} + Z_b G_{bc}. \end{aligned} \quad (15)$$

The coefficients $s_{bb}^{(b)}$ etc in Eqs. (11)–(13) are the same as those entering Eqs. (8), (9). Generalization of the intrinsic ("bare") correlation between arms b and c in the shot noise regime is thus (c.f. Eqs. (8), (9))

$$C_{bc}^{(0)} = s_{bb}^{(b)} \overline{1_1 2_2} + s_{cc}^{(c)} \overline{1_1 3_3}: \quad (16)$$

These coefficients take different forms for tunnel junctions and for diffusive wires. For tunnel junctions, if $\overline{1_1 2_2 3_3}$, they are given by

$$\begin{aligned} s_{bb}^{(b)} &= G_{ba} [a(1 - 2_{ab}) - c(1 - 2_{bc})]; \\ s_{bb}^{(c)} &= G_{bc} (1 - 2_{bc}); \\ s_{cc}^{(b)} &= G_{bc} (1 - 2_{ac} - 2_{bc}); \\ s_{cc}^{(c)} &= G_{ca} [a(1 - 2_{ac}) + b(1 - 2_{ac} - 2_{bc})]; \\ s_{bc}^{(b)} &= G_{bc} (1 - 2_a^2 - 2_{ac} - 2_{bc}); \\ s_{bc}^{(c)} &= G_{bc} (1 - 2_{ac} - 2_{bc}): \end{aligned} \quad (17)$$

In the case $\overline{1_1 3_3 2_2}$ [18], the corresponding coefficients can be obtained from the above expressions by exchanging the indices b and c . For example, $s_{cc}^{(b)}$ can be obtained from the above expression for $s_{bb}^{(c)}$ with all indices of its right hand members making the exchange $b \leftrightarrow c$. For diffusive wires, if $\overline{1_1 2_2 3_3}$,

$$\begin{aligned} s_{bb}^{(b)} &= \frac{G}{3} b(a - c); & s_{bb}^{(c)} &= \frac{G}{3} b_c(1 + 2_a); \\ s_{cc}^{(b)} &= \frac{G}{3} b_c(2_a - 1); & s_{cc}^{(c)} &= \frac{G}{3} c(a + b); \\ s_{bc}^{(b)} &= \frac{G}{3} b_c(1 - 2_a); & s_{bc}^{(c)} &= \frac{G}{3} b_c: \end{aligned} \quad (18)$$

Again, for $\overline{1_1 3_3 2_2}$, one can get the coefficients by exchanging $b \leftrightarrow c$ in the formulas above. These coefficients have been calculated using generalization of the methods proposed by Nazarov [19]. Some of these coefficients can also be deduced from the literature (e.g. [6], [9], and [20]).

Equations (11)–(15) are the main analytic results of this paper. The auto-correlators C_{bb} and C_{cc} can be shown to be positive definite [17]. We shall concentrate on the cross-correlation C_{bc} for the rest of the paper.

For C_{bc} , we can show that [17] it is always negative if $Z_a a$ is larger than $Z_b b$ and $Z_c c$. Hence, we shall focus on the rest of the parameter space. We show the results for two particular examples, $Z_a = 0$, $Z_b = Z_c = 1=G$ in Fig. 2, and $Z_a = 0$, $Z_b = Z_c = 10=G$ in Fig. 3. We see

that, for sufficiently large Z_b and Z_c , it is indeed possible to have positive C_{bc} . The positive region starts near small a , and grows with increasing Z_b and Z_c . Indeed, for Z_b and Z_c both $\gg 1$, one can show that the cross-correlation actually becomes positive for any a 's. (This sign change is not confined to $Z_a = 0$, for more examples, see [17].)

We can understand this behavior physically as follows. (For more quantitative statements, see [17].) When there is a positive fluctuation of the current through, say the arm b , there is a corresponding increase in the potential at point 2 in Fig. 1. This voltage fluctuation in turn will lead to an extra current through the arm c , thus giving a positive contribution to the cross-correlation C_{bc} . This contribution will in particular be large for small a , since most of this fluctuating current will flow through c . We have a net positive C_{bc} if these contributions overwhelm the "bare" negative correlation contribution (see Eq. (13)). In particular, since $s_{bc}^{(b)} + s_{bc}^{(c)} (< 0)$ is proportional to a^2 for tunnel junctions whereas it is proportional to a for diffusive wires for small a , it is therefore easier to get positive C_{bc} for tunnel junctions than for diffusive wires.

Our mechanism for sign change is distinct from that due to bunching (c.f. [12]). We have calculated also the Fano factors and found no bunching in the injected current [17].

In conclusion, we have shown that, for a multi-terminal conductor connected to external leads with finite impedances, the moments of the transferred charges cannot be obtained from simple rescaling of the bare moments. The cross-correlation between the output terminals can even become positive under certain parameter regimes.

This research was supported by NSC of Taiwan under grant numbers NSC 93-2112-M-194-019 and NSC 93-2112-M-001-016.

-
- [1] Ya. M. Blanter and M. Buttiker, Phys. Rep. 336, 1 (2000).
 - [2] C. Beenakker and C. Schonenberger, Phys. Today 56, 37 (2003).
 - [3] Quantum Noise in Mesoscopic Physics, edited by Yu. V. Nazarov (Kluwer, Dordrecht, 2003).
 - [4] M. Buttiker, Phys. Rev. Lett. 65, 2901 (1990); Phys. Rev. B 46, 12485 (1992).
 - [5] Th. Martin and R. Landauer, Phys. Rev. B 45, 1742 (1992).
 - [6] E. V. Sukhorukov and D. Loss, Phys. Rev. B 59, 13054 (1999).
 - [7] See, e.g., M. O. Scully and M. S. Zubairy, Quantum Optics (Cambridge University Press, Cambridge, 1997).
 - [8] M. Henny et al., Science 284, 296 (1999); W. D. Oliver et al., Science 284, 299 (1999); H. Kiesel, A. Renz, and F. Hasselbach, Nature 418, 392 (2002).

- [9] J. Borlin, W. Belzig and C. Bruder, Phys. Rev. Lett. 88, 197001 (2002).
- [10] I. Sa, P. Devillard, and T. Martin, Phys. Rev. Lett. 86, 4628 (2001); A. Crepeux et al., Phys. Rev. B 67, 205408 (2003).
- [11] A. Martin and M. Buttiker, Phys. Rev. Lett. 84, 3386 (2000).
- [12] A. Cottet, W. Belzig, and C. Bruder, Phys. Rev. Lett. 92, 206801 (2004).
- [13] B. Reulet, J. Senzier, and D. E. Prober, Phys. Rev. Lett. 91, 196601 (2003).
- [14] M. Kindermann, Yu. V. Nazarov, and C. W. J. Beenakker, Phys. Rev. Lett. 90, 246805 (2003).
- [15] M. Kindermann, PhD thesis, Leiden University (2003).
- [16] C. W. J. Beenakker, M. Kindermann, and Yu. V. Nazarov, Phys. Rev. Lett. 90, 176802 (2003).
- [17] S. T. Wu and S. K. Yip, unpublished.
- [18] For $\frac{V_a}{1} > \frac{V_b}{2} > \frac{V_c}{3}$, the intermediate potentials must satisfy $\frac{V_a}{1}$ and $\frac{V_b}{2}$ and $\frac{V_c}{3}$.
- [19] Yu. V. Nazarov, Ann. Phys. (Leipzig) 8, SI-193 (1999); Yu. V. Nazarov and D. A. Bagrets, Phys. Rev. Lett. 88, 196801 (2002).
- [20] S.-K. Yip, Phys. Rev. B 71, 085319 (2005).

FIG. 1: Schematic for the circuit considered in this paper. The arms A_a , A_b , A_c of the Y-shaped conductor A are connected to external leads biased, respectively, at voltages $V_a = V$, V_b , and V_c ($V_b = V_c = 0$ in this paper). The leads are assumed to have impedances Z_a , Z_b , and Z_c , which are schematized as external resistors connected to the sample arms. The nodes 1;2;3 between the sample arms and the resistors are where voltage fluctuations set in.

FIG. 2: Plots for the cross-correlations of Y-shaped conductors with (a) tunnel junctions and (b) diffusive wires in the arms. Here the external impedances are $Z_a = 0$ and $Z_b = Z_c = 1=G$. C_{bc} is in units of eGV and the thick lines over the surfaces mark the contour $C_{bc} = 0$.

FIG. 3: Same as Fig. 2 except that impedances are $Z_a = 0$ and $Z_b = Z_c = 10=G$.