

On geometrical scaling of split-ring and double-bar resonators at optical frequencies

Sergei Tretyakov

Radio Laboratory / SMARAD Center of Excellence
TKK Helsinki University of Technology
P.O. Box 3000, FI-02015 TKK, Finland

Address for correspondence:

Sergei Tretyakov
Radio Laboratory, Helsinki University of Technology,
P.O. Box 3000, FI-02015 TKK, Finland.
Fax: + 358-9-451-2152
E-mail: sergei.tretyakov@tkk.

Abstract

In this paper we consider the resonant frequency of split-ring resonators and double-bar resonators used to create artificial magnetic response at terahertz and optical frequencies. It is known that geometrical scaling of the resonant frequency of split rings breaks down at high frequencies (in the visible) due to electromagnetic properties of metals at those frequencies. Here we will discuss this phenomenon in terms of equivalent inductance and capacitance of the ring, derive an approximate formula for the resonant frequency of split rings in the visible and show how the limiting value of the resonant frequency of extremely small split rings and double bars depends on particle shape.

Key words: Negative index materials, negative permeability, split ring, double-bar resonators, artificial magnetism.

1 Introduction

Realization of low-loss metamaterials possessing properties of an artificial magnetic in the visible would allow realization of artificial materials with negative index of refraction and open a way for many novel applications. One of the possible routes is the use of nano-sized resonant metal particles of complex shapes. Various shapes have been proposed, and the operational principle is basically the same: The particle shape is chosen so that one of the lowest eigenmodes has a current distribution with a large magnetic moment. In particular, several variants of split rings [1,3] and double bars [4,5] have been manufactured and measured in frequency range of hundreds of terahertz and in the visible. Also, arrays of pillar pairs have been studied in [6]. However, it has been noticed that the geometrical scaling of the particle resonant frequency breaks down when the working frequency gets higher, so that the resonant frequency saturates at the level of several hundreds of terahertz [7,8]. This effect is explained by the plasmonic behavior of metals at optical frequencies, usually in terms of kinetic energy of electrons carrying current and an additional "electron self-inductance" [7].

In this paper we theoretically study the phenomenon of geometrical scaling breakdown and saturation of the resonant frequency using the equivalent circuit model. We show that the full model of the phenomenon requires not only an additional inductance, but also an additional capacitance. The model correctly gives the ultimate maximum resonant frequency which is equal to the plasma frequency of metal. This model allows us to study the dependence of the achievable resonant frequency on the particle shape.

2 Magnetic mode resonant frequency in the visible

In contrast to the microwave regime, in the visible range metals do not behave as ideal conductors, instead, their permittivity can be modeled by the Drude model:

$$\epsilon = \epsilon_0 \left(1 - \frac{\omega_p^2}{\omega^2} \right) \quad (1)$$

where ω_p is the plasma frequency. This means that the fields in the bulk of metal strips cannot be neglected or modeled as fields in a thin skin layer. Let us assume that the current density is approximately uniform over the cross section of the strip and express the displacement current density in the metal strip as

$$J_d = j\omega D = j\epsilon_0 \left(1 - \frac{\omega_p^2}{\omega^2} \right) E \quad (2)$$

Next, we can relate the total current passing the ring cross section with the voltage along the ring perimeter, because the current amplitude equals $I = J_d w h$ (again assuming uniform current distribution over the ring cross section) and the voltage is $V = E l_e$. Here the effective ring length can be approximated as $l_e = (\pi/2)l$, where l is the physical length,




Figure 1: The geometry of split rings and double-bar particles. The particles are fabricated from a strip of thickness h . The total length of metal strips in each particle is denoted by l . Arrows show the current direction of the magnetic mode. Magnetic flux and electric field exist not only in air but also inside metal strips.

because the current distribution along an open loop or along short bars is approximately sinusoidal. The result reads:

$$I = J_d w h = j \omega \frac{w h}{l_e} \left(1 - \frac{\omega_p^2}{\omega^2} \right) V \quad (3)$$

This relation can be interpreted in terms of additional inductance and capacitance of the ring due to magnetic and electric fields inside the metal ring:

$$I = j \omega \left(\frac{\omega h}{l_e} + \frac{\omega h \omega_p^2}{j \omega l_e} \right) V = j \omega C_{add} + \frac{1}{j \omega L_{add}} V \quad (4)$$

The additional capacitance and inductance can be then identified from the above equation as

$$C_{add} = \frac{\omega h}{l_e}; \quad L_{add} = \frac{l_e}{\omega h \omega_p^2} \quad (5)$$

Formula (5) for L_{add} was derived earlier in [7] in terms of kinetic energy of electrons in metal.

The resonant frequency of the split ring is given by

$$\omega_0 = \sqrt{\frac{1}{(L + L_{add})(C + C_{add})}} \quad (6)$$

which differs from the earlier model in [7] by the additional capacitance term.




Figure 2: Equivalent circuit of a split ring or a double-bar particle in the visible. L_{add} and C_{add} model additional stored energy inside the metal volume.

The parameters of the ideally conducting particle L and C depend on the dimensions and the shape of the particle. Considering the split-ring geometry, we can write:

$$L = \mu_0 \frac{1}{4} \ln \frac{8l}{w+h}; \quad C = \epsilon_0 \frac{wh}{l} \quad (7)$$

where we have approximated the split capacitance as the parallel-plate capacitance (l is the split width). For the inductance estimations, we can use the formula for the round-loop inductance

$$L = \mu_0 a \ln \frac{8a}{r_0} \quad (8)$$

and estimate the equivalent loop radius $a = \frac{l}{2} = \frac{l}{4}$ and the equivalent wire radius $r_0 = \frac{(h+w)}{4}$. Finally, the resonant frequency of split rings reads

$$\omega_0 = \frac{1}{\sqrt{1 + \frac{1}{2} \frac{1}{\epsilon_0 \mu_0 \frac{wh}{2} \ln \frac{8l}{w+h} + \frac{1}{l_p^2}}}} \quad (9)$$

Metal losses can be modeled by replacing formula (2) by

$$J_d = j\omega_0 \left(1 - \frac{\omega_p^2}{\omega^2} \right) E \quad (10)$$

where γ is the damping coefficient. The result for the resonant frequency (6) changes to

$$\omega_0 = \frac{1}{\sqrt{(L + L_{\text{add}})(C + C_{\text{add}})}} \sqrt{\frac{R}{(L + L_{\text{add}})^2}} \quad (11)$$

where the equivalent resistance reads

$$R = \frac{l}{\epsilon_0 wh \omega_p^2} \quad (12)$$




Figure 3: Resonant frequency of a split ring particle [formula (9)] as a function of geometrical scaling factor. Particle parameters are the same as in paper [8].

A numerical example of the dependence of the resonant frequency on the geometrical scaling factor is given in Figure 3. The particle is a split ring made of gold, and its dimensions are the same as in paper [8]. The plasma frequency of gold is assumed to equal $\omega_p = 13.8 \cdot 10^{15}$ 1/s, and the loss factor $\gamma = 107 \cdot 10^2$ 1/s [9]. Despite several model simplifications, the estimated resonant frequency (316.4 THz) corresponds surprisingly well with numerical and experimental results of [8] (close to 330 THz). It is interesting to note that metal losses have negligible effect on the resonant frequency in this case. This can be understood by comparing the values of $\omega_0 L_{\text{add}}$ and R , which differ only by replacement of the resonant frequency ω_0 by the loss factor γ . Because $\omega_0 \ll \gamma$, the contribution of the term proportional to R in (11) can be neglected. However, losses degrade the resonator quality factor and one has to take them into account especially at very high frequencies. In the optical region, the level of losses depends not only on the material but also on the particle shape, because of Landau damping (scattering on particle boundaries). This means that the choice of the optimal shape should include consideration of losses in addition to the resonant frequency of the particle.

3 Discussion and conclusions

In order to increase the resonant frequency, the denominator in formula (9) should be made as small as possible. Clearly, this has a fundamental limit since even in the limit of zero dimensions the limiting value is not infinity but equals to the plasma frequency of the metal (it is stated also in paper [8] that the limit is determined by the plasma frequency). This is a very expected conclusion because even if in the limit of small size the loop closes completely and there is zero magnetic flux outside the particle, electrons inside metal still can oscillate, and the resonant frequency of these oscillations is the plasma frequency. Inspecting formula (9) we can see that the preferred design should minimize the strip cross section area wh . This, however, has its own limit determined by increased losses for smaller values of wh . In addition, our results reveal that the limiting resonant frequency for particles with all

the dimensions going to zero proportionally to the same scaling factor depends also on the particle shape:

$$\lim_{\substack{\rightarrow \\ \rightarrow}} f_{0g} = \frac{\omega_p}{1 + \frac{1}{2}} \quad (13)$$

[see formula (9)]. The ultimate highest resonant frequency equals to the plasma frequency of metal:

$$\max f_{0g} = \frac{1}{C_{\text{add}} L_{\text{add}}} = \omega_p \quad (14)$$

and it can be in principle achieved if in diminishing the particle dimensions

$$\lim_{\substack{\rightarrow \\ \rightarrow}} \frac{1}{\dots} = 0 \quad (15)$$

This design recipe suggests that, when reducing the particle size, the loop or bar length should be reduced in larger proportion than the gap width. This has a clear meaning of reducing both geometrical inductance and capacitance, since the inductance is proportional to l , while the capacitance is inversely proportional to l .

Finally, in choosing the particle shape it is important to remember that the current induced by external magnetic field (in the LC-circuit model) is proportional to $\omega_p^2 (C + C_{\text{add}}) = (1 - \omega_p^2 / \omega_0^2)$. This means that comparing two particles with the same resonant frequency ω_0 , the induced current is stronger in the particle with the larger total capacitance. This consideration suggests to decrease capacitance in a smaller proportion than inductance, if the goal is to design an optical metamaterial, but this contradicts with the criterium of raising the limiting resonant frequency (15). Thus, the particle shape choice is a compromise between the increased resonant frequency and strong magnetic response.

Acknowledgements

This work has been done within the frame of the European Network of Excellence Metamorphose. The author wishes to thank Liisi Jylha for helpful comments.

References

- [1] S. Linden, C. Enkrich, M. Wegener, J. Zhou, T. Koschny, C. M. Soukoulis, *Science*, vol. 306, 1351, 2004.
- [2] H. O. Moser, B. D. F. Casse, O. Wilhelm, and B. T. Saw, *Terahertz Response of a Microfabricated Rod Split-Ring-Resonator Electromagnetic Metamaterial*, PRL 94, 063901 (2005)
- [3] N. Katsarakis, G. Konstantinidis, A. Kostopoulos, R. S. Penciu, T. F. Gundogdu, M. Kafesaki, E. N. Economou, Th. Koschny and C. M. Soukoulis, *Magnetic response of split-ring resonators in the far-infrared frequency regime*, 1348-1350, OPTICS LETTERS / Vol. 30, No. 11 / June 1, 2005

- [4] A .V .K ildishev, W .Cai, U K .Chettiar, H .K .Yuan, A K .Sarychev, V P .D rachev, and V M .Shalaev, Negative refractive index in optics of metamaterial dielectric composites, Vol. 23, No. 3/M arch 2006/J.Opt.Soc.Am .B 423-433.
- [5] V M .Shalaev, W .Cai, U K .Chettiar, H .K .Yuan, A K .Sarychev, V P .D rachev, and A .V .K ildishev, Negative index of refraction in optical metamaterials, OPTICS LETTERS / Vol. 30, No. 24 / December 15, 2005, 3356-3358.
- [6] A N .G rigorenko, A K .G eim , H F .G leeson, Y .Zhang, A A .F irsov, I.Y .K hrushchev, J. Petrovic, Nanofabricated media with negative permeability at visible frequencies, Nature 438 November 2005, pp. 17-20.
- [7] J. Zhou, Th. Koschny, M . Kafesaki, E N .Econom ou, J.B .Pendry, C M . Soukoulis, Saturation of the magnetic response of split-ring resonators at optical frequencies, Phys. Rev. Lett., vol. 95, 223902, 2005.
- [8] M W .K lein, et al., Single-split split-ring resonators at optical frequencies: limits of size scaling, Optics Letters, vol. 31, no. 9, pp. 1259-1261, 2006.
- [9] A .Ishikawa, T .Tanaka, S.K awata, Negative magnetic permeability in the visible light region, Phys. Rev. Lett., 95, 237401, 2005.