

Quantum noise limits for nonlinear, phase-invariant amplifiers

Dmitri Kouznetsov*

*Centro de Instrumentos, Universidad Nacional Autónoma de México, Ap.70-186,
Cd. Universitaria, 04510 D. F., Mexico, and Lebedev Physics Institute, Leninsky 54, 117924
Russia*

Roberto Ortega

*Centro de Instrumentos, Universidad Nacional Autónoma de México, Ap.70-186,
Cd. Universitaria, 04510 D. F., Mexico*

Daniel Rohrlich[†]

School of Physics and Astronomy, Tel-Aviv University, Ramat-Aviv 69978 Tel-Aviv, Israel
(August 26, 2021)

Abstract

Any quantum device that amplifies coherent states of a field while preserving their phase generates noise. A nonlinear, phase-invariant amplifier may generate less noise, over a range of input field strengths, than any linear amplifier with the same amplification. We present explicit examples of such nonlinear amplifiers, and derive lower bounds on the noise generated by a nonlinear, phase-invariant quantum amplifier.

3.65.Bz, 42.50.Ar, 42.50.Lc, 42.65.Ky

Typeset using REVTeX

*E-mail: kusnecov@aleph.cinstrum.unam.mx

[†]E-mail: daniel@vm.tau.ac.il

Any quantum device that amplifies a field while preserving its phase generates noise. Noise is unavoidable since the phase and number operators for modes of a quantum field do not commute. Two values characterize a phase-preserving or phase-invariant [1] amplifier: the amplification coefficient $G = \langle A \rangle / \langle a \rangle$, and the noise $D = \langle A^\dagger A \rangle - \langle A^\dagger \rangle \langle A \rangle$. Here we focus on a single field mode, for simplicity: a and A denote the field mode before and after amplification, respectively. We take expectation values in a coherent state $|\alpha\rangle$; since $a|\alpha\rangle = \alpha|\alpha\rangle$, the noise in the unamplified field is zero. For a *linear* quantum amplifier, G is a constant, independent of the initial state, and the minimal noise is well known [2–4]: $D \geq |G|^2 - 1$ for $|G| \geq 1$. For a nonlinear amplifier, G depends on $x \equiv \alpha^* \alpha$ (but not on the phase of α). In this Letter, we derive lower limits for the quantum noise in nonlinear quantum amplifiers, and demonstrate that a nonlinear amplifier may generate less noise, for the same amplification, than any linear amplifier, over a range of input field strengths.

What makes an amplifier a *quantum* amplifier is that the mode operators before and after amplification must be related by a unitary transformation, $A = U^\dagger a U$. Thus, $[a, a^\dagger] = 1$ implies [2] that $[A, A^\dagger] = 1$. In principle, U could depend on the field operators a and a^\dagger alone. However, then there will be no amplification. If U depends on a and a^\dagger alone, then phase invariance requires it to depend only on $a^\dagger a$; the noise, $\langle U^\dagger a^\dagger a U \rangle - \langle U^\dagger a^\dagger U \rangle \langle U^\dagger a U \rangle = |\alpha|^2 - |\alpha G(x)|^2$, cannot be negative, so $|G| \leq 1$. When $|G(x)| = 1$ there is no noise, but the amplifier does not amplify. We must introduce operators for the amplifier, and these induce noise. The choice $U = \exp(-iHt)$, with $H = i(a^\dagger b^\dagger - ab)$, leads to a linear amplifier. (The amplifier degree of freedom b obeys $[b, b^\dagger] = 1$, and t is real.) We find $A = U^\dagger a U = a \cosh t + b^\dagger \sinh t$; for an amplifier prepared in the ground state $G = \cosh t$, and the noise $D = \sinh^2 t$ saturates the bound $D \leq |G|^2 - 1$ for linear amplifiers.

For nonlinear amplifiers, we have no general expression for U and A in terms of field and amplifier degrees of freedom. Nevertheless, we have the following lower bounds for the noise of a nonlinear, phase-invariant quantum amplifier:

Theorem. Let $D = \langle \alpha | A^\dagger A | \alpha \rangle - \langle \alpha | U^\dagger A^\dagger U | \alpha \rangle \langle \alpha | U^\dagger A U | \alpha \rangle$, and

$$E(x) = \sum_{n=1}^{\infty} \frac{x^{n+1}}{n!} \left| \frac{d^n}{dx^n} G(x) \right|^2, \quad F(x) = \sum_{n=1}^{\infty} \frac{x^{n-1}}{n!} \left| \frac{d^n}{dx^n} (xG(x)) \right|^2 - 1; \quad (1)$$

Then $D \geq E(x)$ and $D \geq F(x)$.

Proof. Define the set of states $|\alpha^{(n)}\rangle$

$$|\alpha^{(n)}\rangle = \frac{(a^\dagger - \alpha^*)^n}{\sqrt{n!}} |\alpha\rangle, \quad (2)$$

where $\langle \alpha^{(m)} | \alpha^{(n)} \rangle = \delta_{mn}$ and $|\alpha^{(0)}\rangle = |\alpha\rangle$. Differentiating the expansion

$$|\alpha\rangle = e^{-\alpha^* \alpha / 2} \sum_{n=0}^{\infty} \frac{(\alpha a^\dagger)^n}{n!} |0\rangle, \quad (3)$$

we obtain

$$\frac{\partial}{\partial \alpha} |\alpha\rangle = -\frac{\alpha^*}{2} |\alpha\rangle + a^\dagger |\alpha\rangle, \quad \frac{\partial}{\partial \alpha^*} |\alpha\rangle = -\frac{\alpha}{2} |\alpha\rangle. \quad (4)$$

Note that $A = U^\dagger a U$ does not depend on α , since the amplifier cannot anticipate the input state. Thus, Eqs. (2-3) imply

$$\frac{1}{\sqrt{n!}} \frac{\partial^n}{\partial \alpha^n} (\alpha G) = \langle \alpha | A | \alpha^{(n)} \rangle, \quad \frac{1}{\sqrt{n!}} \frac{\partial^n}{\partial \alpha^n} (\alpha^* G^*) = \langle \alpha | A^\dagger | \alpha^{(n)} \rangle. \quad (5)$$

Consider the identity operator I_0 in the Hilbert space of states of the field:

$$I_0 = \sum_{n=0}^{\infty} |\alpha^{(n)}\rangle \langle \alpha^{(n)}|. \quad (6)$$

I_0 is only part of the identity operator I in the Hilbert space of states of the field and amplifier:

$$I = \sum_{m,n=0}^{\infty} |m, \alpha^{(n)}\rangle \langle m, \alpha^{(n)}|. \quad (7)$$

The index m refers to the states of the amplifier. Without loss of generality, we may identify I_0 with the $m = 0$ term in I , where $m = 0$ represents the initial state of the amplifier. Inserting I into the expectation value $\langle \alpha | A^\dagger A | \alpha \rangle$ — where we identify $|\alpha\rangle$ with $|0, \alpha\rangle$ — we obtain

$$\langle \alpha | A^\dagger A | \alpha \rangle = \langle \alpha | A^\dagger I A | \alpha \rangle \geq \langle \alpha | A^\dagger I_0 A | \alpha \rangle, \quad (8)$$

$$D \geq \langle \alpha | A^\dagger I_0 A | \alpha \rangle - |\alpha G|^2 = \sum_{n=1}^{\infty} \frac{1}{n!} \left| \frac{\partial^n}{\partial \alpha^n} (\alpha^* G^*) \right|^2 = E(x) . \quad (9)$$

On the other hand, since $A^\dagger A = A A^\dagger - 1$ and $\langle \alpha | A I A^\dagger | \alpha \rangle \geq \langle \alpha | A I_0 A^\dagger | \alpha \rangle$, we have

$$D \geq \langle \alpha | A I_0 A^\dagger | \alpha \rangle - 1 - |\alpha G|^2 = \sum_{n=1}^{\infty} \frac{1}{n!} \left| \frac{\partial^n}{\partial \alpha^n} (\alpha G) \right|^2 - 1 = F(x) . \quad (10)$$

(End of proof)

Both $E(x)$ and $F(x)$ are lower bounds on the noise of a nonlinear, phase-invariant quantum amplifier. When G is constant, $F(x)$ reduces to the bound for linear amplifiers, $|G|^2 - 1$. But both bounds can be less than $|G(x)|^2 - 1$, for a range of values of x , if $|G(x)|$ decreases with x . ($|G(x)|$ decreasing with x describes amplifier saturation.) We have not yet shown that, for any given $G(x)$, a nonlinear amplifier can realize these lower bounds. A class of amplifiers which do realize the lower bound $F(x)$ have a linear amplification followed by a nonlinear refraction depending only on $a^\dagger a$:

$$A = e^{itH} \left[G_0 a + (|G_0|^2 - 1)^{1/2} b^\dagger \right] e^{-itH} , \quad (11)$$

where t is real. For example, let $H = a^\dagger a (a^\dagger a - 1)/2$. We find (using Eq. (3)) that $G(x) = G_0 \exp(-qx)$, and $D = |G_0|^2 [1 + x - x \exp(-|q|^2 x)] - 1$, where $q = 1 - e^{-it}$. The amplifier realizes the lower bound $F(x) = D$, while $E(x) = D - 1 + |G_0|^2$. For this class of amplifiers, the linear lower bound $D \geq |G(x)|^2 - 1$ also holds. It is broken in the next example.

The resonant interaction of N identical two-level atoms with a single-mode field can be described [5] by the Hamiltonian $H = iab^\dagger - ia^\dagger b$, where $b = \sum_{k=1}^N b_k$, $b_k b_j = (1 - \delta_{jk}) b_j b_k$, $b_k^\dagger b_j = b_j b_k^\dagger$ for $j \neq k$, and $b_k^\dagger b_k + b_k b_k^\dagger = 1$. (b_k^\dagger is the operator for exciting the k -th atom.) The evolution operator $\exp(-iHt)$ defines the transformation U . Let all atoms be excited in the initial state of the amplifier. In this case G is real. For $N = 10$ and a given value of t , let G_t denote the amplification factor and D_t the noise. We compute the evolution from the initial state numerically. Fig. 1 shows the coefficient $g = G_t^2$ and the noise D_t versus t at input intensity $x = 1$. The noise D_t oscillates quasiperiodically while G_t has “revivals”. Fig. 2, a plot of $D_t(1)$ versus $|G_t(1)|^2$, shows that the linear relation

$D \geq |G|^2 - 1$ is valid only at small t (for $G_t^2 \lesssim 2$), where the amplifier is linear, and violated at larger x . Fig. 3 compares D , $|G|^2 - 1$, E , and F as functions of x , while Fig. 4 is a plot of the three bounds versus $|G(x)|^2$, for $t = 0.5$. The nonlinear amplifier beats the linear limit, while the lower limits of the Theorem hold.

The final example involves a small nonlinear perturbation on a linear amplifier. We define

$$A = Ca + Sb^\dagger - \epsilon \left[a^\dagger a^2 - (C/S)a^2 b + (2C/S)a^\dagger ab^\dagger \right] \quad , \quad (12)$$

where $C \equiv \cosh t$, $S \equiv \sinh t$, and $[a, a^\dagger] = 1 = [b, b^\dagger]$, $[a, b^\dagger] = 0 = [a, b]$. Let ϵ be small and positive. We find $[A, A^\dagger] = 1$ to order ϵ , and $\langle A \rangle = (C - \epsilon x)\alpha$, i.e. $G = C - \epsilon x$. The noise is $D = C^2 - 1 - 4Cx\epsilon < G^2 - 1$, violating the linear limit to first order in ϵ . It saturates the bound $F(x)$, while $E(x) = 0$ to this order.

In summary, we have obtained lower bounds on the irreducible noise of a nonlinear, phase-preserving quantum amplifier, in terms of the amplification factor G and its derivatives. For G constant, the amplifier is linear, and the bound F reproduces the linear bound. For G not a constant, however, the nonlinear bound can undercut the linear bound. Explicit examples confirm that the noise of a nonlinear amplifier can be less than that of an ideal linear amplifier with the same amplification coefficient, over a range of input field strengths. However, we have not determined in general which functions $G(x)$ correspond to nonlinear amplifiers, nor whether the lower bounds can be realized.

ACKNOWLEDGMENTS

The work of D. K. was partially supported by CONACyT of Mexico. D. R. thanks the Ticho Fund for support.

REFERENCES

- [1] The term ‘phase-preserving’ is used for linear amplifiers when $\langle A \rangle$ and $\langle a \rangle$ have the same phase; without loss of generality G may be taken real, and independent of the phase of α . Applied to *nonlinear* amplifiers, however, the term may be ambiguous: G could depend on the phase of α but in such a way that $\langle A \rangle$ and $\langle a \rangle$ have the same phase. For clarity, we call an amplifier ‘phase-invariant’ when G depends only on $x \equiv \alpha^* \alpha$, although G need not be real.
- [2] H. A. Haus and J. A. Mullen, *Phys. Rev.* **128**, 2407 (1962).
- [3] C. M. Caves, *Phys. Rev.* **D26**, 1817 (1982).
- [4] Y. Yamamoto and H. A. Haus, *Rev. Mod. Phys.* **58**, 1001 (1986).
- [5] M. Tavis and F. M. Cummings. *Phys. Rev.* **188**, 692 (1969).

FIGURES

FIG. 1. Amplification coefficient $g = G_t^2$ and noise D_t versus t at $x = 1$ for the Cummings-Tavis amplifier with $N = 10$ atoms. At $t = 0$, $G^2 = 1$ (thick line) and $D = 0$ (thin line).

FIG. 2. The noise D_t versus G_t^2 under the same conditions.

FIG. 3. The noise D (thick curve), linear lower bound $G^2 - 1$ (thin curve), and lower bounds E (dotted curve) and F (dashed curve) versus x for the Cummings-Tavis amplifier at $N = 10$, $t = 0.5$.

FIG. 4. The noise D and all bounds versus G^2 under the same conditions.




FIG. 1. Amplification coefficient $g = G_t^2$ and noise D_t versus t at $x = 1$ for the Cummings-Tavis amplifier with $N = 10$ atoms. At $t = 0$, $G^2 = 1$ (thick dotted line) and $D = 0$ (thin line).




FIG. 2. The noise D_t versus G_t^2 under the same conditions.




FIG. 3. The noise D (thick curve), linear lower bound $G^2 - 1$ (thin curve), and lower bounds E (dotted curve) and F (dashed curve), versus x for the Cummings-Tavis amplifier at $N = 10$, $t = 0.5$.




FIG. 4. The noise D and all bounds versus $|G|^2$ under the same conditions.