

Excess Noise in Biased Superconducting Weak LinksJ. P. Hessling* ⁽¹⁾, V. S. Shumeiko ⁽¹⁾, Yu. M. Galperin ⁽²⁾, G. Wendin ⁽¹⁾⁽¹⁾ *Department of Applied Physics, Chalmers University of Technology and Göteborg University, S-412 96, Göteborg, Sweden*⁽²⁾ *Department of Physics, University of Oslo, P.O. Box 1048 Blindern, N 0316 Oslo 3, Norway, and A.F. Ioffe Physico-Technical Institute, 194021 St. Petersburg, Russia*

August 24, 2021

Abstract

Non-equilibrium excess noise of a short quasi one-dimensional constriction between two superconductors is considered. A general expression for the current-current correlation function valid for arbitrary temperatures and bias voltages is derived. This formalism is applied to a current-carrying quantum channel with perfect transparency. Contrary to a transparent channel separating two normal conductors, a weak link between two superconductors exhibits a finite level of noise. The source of noise is fractional Andreev scattering of quasiparticles with energies $|E|$ greater than the half-width Δ of the superconducting gap. For high bias voltages, $V \gg \Delta/e$, the relation between the zero-frequency limit of the noise spectrum, $S(0)$, and the excess current I_{exc} reads $S(0) = (1/5)|e|I_{\text{exc}}$. As $\Delta \rightarrow 0$ both the excess noise and the excess current vanish linearly in Δ , their ratio being constant.

PACS numbers: 74.50.+r, 74.80.Fp, 73.20 Dx

Typeset using REVTeX

*Electronic address: hessling@fy.chalmers.se

Introduction. As is well known ((see, e.g., Ref. [1]), electron transport through short superconducting weak links can be described in terms of multiple Andreev reflections (MAR). Calculations of dc $I - V$ curves of voltage-biased weak links [2–7] have predicted specific current singularities at voltages $V = 2\Delta/en$, $n = 1, 2, \dots$, where 2Δ is the superconducting energy gap and e the electronic charge. This feature is a manifestation of MAR. However, dc properties carry only indirect information about weak link dynamics – more direct information can be found from theoretical studies of ac currents. Studies of ac transport have mostly been carried out for large voltages, $eV \gg \Delta$, the limitation being caused by the fact that at low voltages it is necessary to take into account a large number of MAR. Recently, Averin and Bardas [8] have considered a model of a short constriction between two superconductors which permits quantitative calculations of ac currents for arbitrary voltages V and transparencies D . Unfortunately, experimental studies of ac characteristics are difficult.

In addition to studies of transport properties, investigations of non-equilibrium excess noise provide qualitative information about the dynamics of mesoscopic junctions. This type of noise can be investigated without ac bias, and directly probes the correlation between particles passing through the junction. It is not surprising that noise properties of weak links of the Josephson type have been extensively discussed (see, e.g., Refs [9,10] for a review). The specific role of quantum mechanical correlations in normal contacts due to the Fermi statistics of electrons was considered in Refs. [11–13]. There it was found a specific quantum reduction of noise in comparison with the so-called Schottky limit [14].

In the present study we discuss noise properties of a short voltage-biased constriction separating two superconductors. The junction is modeled as an adiabatically-smooth point contact with typical length L much larger than the Fermi wave length k_F^{-1} , but much less than the coherence length of the superconductors. In this limit when $k_FL \gg 1$, one can neglect intermode scattering within the constriction and write the electron wave function as a superposition of different independent modes for the transverse motion. As a result, both current and noise is a sum of independent contributions from each mode. Each term corresponding to a certain mode can be expressed through the solution of the scattering problem for electronic states in the leads. In the following, a general theoretical approach to non-equilibrium noise in voltage-biased contacts is presented and noise is given in terms of the solution of the scattering problem.

The case of perfect transparency, $D = 1$, is particularly interesting because then there is no excess noise in the normal state (see below). In this limit we give an explicit result for large bias voltages, $eV \gg \Delta$. In the superconducting state there is a *finite* level of excess noise due to Andreev reflection. The physical origin is that the amplitude for this type of reflection is non-zero but less than one, for quasiparticle states outside the gap, i.e. having energies $|E| > \Delta$. The quasiparticle then have a finite probability to be reflected from, *or* transmitted through, the junction which is required in order to have a fluctuating current. We show that the zero-frequency limit of the noise spectrum is proportional to the excess current [1,2], the proportionality coefficient being $e/5$.

This letter is organized as follows. First, a formulation of the general scattering problem will be given and the solution for $D = 1$ specified. Then the excess noise will be expressed in terms of the scattering solution, and finally we apply this to the limiting case $D = 1$, zero temperature and zero frequency in the large voltage limit.

Scattering problem. In the original Landauer picture [15], scattering in a normal voltage-biased point contact is elastic. The voltage V only enters as a relative displacement of the Fermi levels in the reservoirs. For a contact between superconductors, an alternative picture where the voltage V is included in the phase of the wave function is more convenient. According to this picture, constant electric potentials in the leads far from the contact are removed by local gauge transformations which are different on the two sides of the junction. Consequently, the voltage is included as phase factors in all scattering states. Transmission through the contact now formally appears as inelastic and for a normal contact there is one transmitted state at energy $E + eV$ with amplitude d , and one reflected state with amplitude r at the same energy E as the incoming state. In a voltage-biased superconducting contact though, multiple Andreev scattering processes to all energies $E + neV$ (where n is an integer) are possible [1].

In the leads, the electronic states can be described as solutions to the Bogoliubov-de Gennes (BdG) equation [16] and have the form of two-component spinors Ψ which can be specified by the side of the junction (L or R) as a subscript, and by the direction of the longitudinal momentum (\pm) as a superscript. Introducing slowly varying spinors $\Phi_{L(R)}^\pm$ the total wave function for each transverse mode will be expanded as $\Psi = e^{-iEt/\hbar} \sum_{\pm} e^{\pm ik_F x} \Phi^\pm$. The spinors Φ satisfy a reduced time-independent BdG equation [16], $(\pm \hbar k_F \hat{p}/m_e + \sigma_x \Delta) \Phi^\pm = E \Phi^\pm$ where m_e is the electronic mass and \hat{p} the momentum operator. The Fermi wave vector (energy) is k_F (E_F) outside the channel, and $\tilde{k}_F = \hbar^{-1} \sqrt{2m_e E_F [1 - (n\pi/k_F w)^2]}$ for mode n inside the contact of width w . The spinors Φ change on the scale of the coherence length $\xi_0 = \hbar^2 k_F / \pi \Delta m_e$, i.e. they can be considered as being constant in the contact region. In the following we adopt the Andreev approximation [17] which is valid up to lowest order in the small parameter Δ/E_F . In this approximation the scattering is described by the boundary condition [5,8],

$$\begin{pmatrix} \Phi_L^- \\ \Phi_R^+ \end{pmatrix} = \hat{V} \begin{pmatrix} \Phi_L^+ \\ \Phi_R^- \end{pmatrix}, \quad \hat{V} = \begin{pmatrix} \hat{r} & \hat{d} e^{-i\hat{\sigma}_z eVt/\hbar} \\ \hat{d} e^{i\hat{\sigma}_z eVt/\hbar} & -\hat{r}^* d/d^* \end{pmatrix}. \quad (1)$$

The parameter $r(d)$ is the normal reflection (transmission) amplitude, while the matrix $\hat{r}(\hat{d})$ is the same quantity multiplied by the 2×2 unit matrix. Since the junction length is much less than the coherence length [18], the coordinate dependence of the phase of the order parameter can be approximated by a step function centered at the junction, and the magnitude of the order parameter by a constant. This allows us to include the phase difference eVt/\hbar in the matching matrix \hat{V} , see above. The general boundary condition (1) has to be applied to the four distinct scattering cases – electron- and hole-like quasi particles incident from the left and the right, and for positive as well as for negative energies.

The scattering problem substantially simplifies for the case of perfect transmission, $d = 1$. The wave vector is then conserved to lowest order in Δ/E_F . Hence only wave vector conserving scattering events can take place, that is, Andreev reflection to energies $E + 2neV$ with amplitudes \mathcal{A}_{2n} and normal transmission to energies $E + (2n + 1)eV$ with amplitudes \mathcal{N}_{2n+1} . Further, the direction of energy transfer is prescribed by the sign of the voltage and by the scattering case. For a given scattering case only scattering to higher (*or* lower) energies is possible. A typical scattering state is shown in Fig. 1. The scattering amplitudes \mathcal{A}_{2n} and \mathcal{N}_{2n+1} can be expressed as

$$\mathcal{A}_{2n} = X_{2n}, \quad \mathcal{N}_{2n+1} = X_{2n+1}, \quad (2)$$

through the function X_n ,

$$X_n \equiv \begin{cases} [(u_0^2 - v_0^2)/v_0 u_n] \prod_{k=0}^{n-1} (v_k/u_k), & n \neq 0 \\ -v_0/u_0, & n = 0. \end{cases} \quad (3)$$

with upward (downward) recursion, $n \geq 0$, for scattering states associated with incident electron-like (hole-like) quasiparticles from the left and hole-like (electron-like) ones from the right. The coherence factors $u_n \equiv u(E + neV)$, $v_n \equiv v(E + neV)$ are for $E > 0$ given by $u^2(E) = \min[1, E/\Delta](1 + \sqrt{1 - \Delta^2/E^2})/2$ and $v^2(E) = \min[1, E/\Delta](1 - \sqrt{1 - \Delta^2/E^2})/2$; for $E < 0$, $u(E) = -v^*(-E)$ and $v(E) = u^*(-E)$. In the large voltage limit $eV \gg \Delta$ only three scattering amplitudes have to be taken into account,

$$\mathcal{A}_0 = -v_0/u_0, \quad \mathcal{A}_{\pm 2} = -v_{\pm 1}/u_{\pm 1}, \quad \mathcal{N}_{\pm 1} = (u_0^2 - v_0^2)/(u_0 u_{\pm 1}). \quad (4)$$

All other amplitudes are at most of order Δ/eV for all energies.

Excess Noise. Current noise is usually defined as the Fourier transform of the current-current correlation function, $S(\tau) = 1/2 \langle [\hat{I}(t + \tau), \hat{I}(t)]_+ \rangle - \langle \hat{I}(t) \rangle^2$, where $[A, B]_+ = AB + BA$. Using the Bogoliubov-de Gennes transformation [16], we can express electron field operators in terms of quasiparticle operators γ . The current operator will be

$$\hat{I}(t) = \frac{\hbar e}{2m_e} \sum_{\bar{1}, \bar{2}} \left[\hat{\gamma}_{\bar{1}}^\dagger \hat{\gamma}_{\bar{2}} j_+(\bar{1}, \bar{2}, t) + \hat{\gamma}_{\bar{1}} \hat{\gamma}_{\bar{2}}^\dagger j_-(\bar{1}, \bar{2}, t) + \hat{\gamma}_{\bar{1}} \hat{\gamma}_{\bar{2}} \sigma_{\bar{1}} j_x(\bar{1}, \bar{2}, t) + \hat{\gamma}_{\bar{1}}^\dagger \hat{\gamma}_{\bar{2}}^\dagger \sigma_{\bar{2}} j_x(\bar{2}, \bar{1}, t) \right]. \quad (5)$$

The sum is over quantum labels $\bar{1}$ and $\bar{2}$ ranging over *all* states (meaning scattering case index, energy of incoming state, side bands n , and spins σ). Above we have defined three different types of generalized currents,

$$j_+(\bar{1}, \bar{2}, t) \equiv \langle \Phi(\bar{1}) | i \nabla \hat{\sigma}_{11} \Phi(\bar{2}) \rangle + \langle i \nabla \Phi(\bar{1}) | \hat{\sigma}_{11} \Phi(\bar{2}) \rangle, \quad (6)$$

$$j_-(\bar{1}, \bar{2}, t) \equiv \langle \Phi^*(\bar{1}) | i \nabla \hat{\sigma}_{22} \Phi^*(\bar{2}) \rangle + \langle i \nabla \Phi^*(\bar{1}) | \hat{\sigma}_{22} \Phi^*(\bar{2}) \rangle, \quad (7)$$

$$j_x(\bar{1}, \bar{2}, t) \equiv \langle \Phi^*(\bar{1}) | i \nabla \hat{\sigma}_{21} \Phi(\bar{2}) \rangle + \langle i \nabla \Phi^*(\bar{1}) | \hat{\sigma}_{21} \Phi(\bar{2}) \rangle, \quad (8)$$

expressed through the 2×2 matrices $\hat{\sigma}_{ij}$ having element (i, j) equal 1 and zero otherwise. The scalar product between two spinors is here defined as (assume $\Phi^T = (u, v)$), $\langle \Phi(\bar{1}) | \Phi(\bar{2}) \rangle \equiv u^*(\bar{1})u(\bar{2}) + v^*(\bar{1})v(\bar{2})$. Introducing the normalized BCS density of states per spin for incoming quasiparticles, $\tilde{g}(E) = [|E|/\sqrt{E^2 - \Delta^2}] \Theta(|E| - \Delta)$, our general expression for noise can be written as [19]

$$S(\omega, V, T) = \frac{e^2}{8\pi^2 \hbar} \sum_{\pm, n} \int_{-\mu}^{\infty} f(E) [1 - f(E + neV \pm \hbar\omega)] \times \tilde{g}(E) \tilde{g}(E + neV \pm \hbar\omega) \text{Tr} \hat{\Omega}^{(n)}(E, E + neV \pm \hbar\omega) dE, \quad (9)$$

$$\hat{\Omega}^{(n)}(E, E') \equiv \hat{Q}^{(n)}(E, E') \hat{P}(E', E) + \sum_{\nu=1,2} \hat{Q}_{\nu}^{(n)}(E, E') \hat{P}_{\nu}(E', E), \quad (10)$$

$$\hat{Q}_{(\nu)}^{(n)}(E, E') \equiv \sum_m \langle \Phi_{n+m}(E) \hat{s} | \otimes (\hat{\sigma}_{\nu\nu}) \Phi_m(E') \rangle, \quad (11)$$

$$\hat{P}_{(\nu)}(E', E) \equiv \langle \sum_n \Phi_n(E') \hat{s} | \otimes (\hat{\sigma}_{\nu\nu}) \sum_m \Phi_m(E) \rangle. \quad (12)$$

Above, $\Phi_m(E)$ is a row vector for harmonic side-band m consisting of four two-component (column) spinors $\Phi_m(E)$, each corresponding to one of the four scattering cases. The symbol \otimes denotes outer product in scattering case indices. Thus Q and P are 4×4 matrices with element (i, j) corresponding to scattering cases i and j in the bra and ket states in the definitions above. The trace is then calculated in this four-dimensional space. The parenthesis around $\hat{\sigma}_{\nu\nu}$ implies that $\hat{\sigma}_{\nu\nu}$ should be excluded when calculating $\hat{Q}^{(n)}$ and \hat{P} . The operator \hat{s} causes the inner product to be multiplied by the average of the wave vectors (in units of the Fermi vector) of the bra and ket states – only if the wave vectors have equal sign will the term contribute ($\hat{s} \Rightarrow \pm 1$).

For perfect transmission ($d = 1$), the wave vector is conserved when quasiparticles are scattered in the junction implying that all subbands have the same wave vector (to leading order in Δ/E_F). This allows us to assign a value of the sign of the wave vector ($\pm k_F$) to each scattering state containing all its subband components. The number of contributing terms in the trace in the noise expression is then reduced from 16 to 8 (see operator \hat{s} in $S(\omega)$). In the limit of large bias voltages V all scattering amplitudes, to lowest order in Δ/eV , are given by Eq. (4).

Putting in proper coherence factors into the expressions for scattering amplitudes and spinors, we find that for zero temperature, the zero frequency limit of the noise can be written as

$$S_{\text{exc}}(0) \rightarrow \frac{2e^2}{\pi^2\hbar} \int_{-\infty}^{-\Delta} D_A(E)[1 - D_A(E)] dE = \frac{8e^2\Delta}{15\pi^2\hbar}, \quad (13)$$

as $\Delta/eV \rightarrow 0$. The quantity $D_A(E) \equiv 1 - \mathcal{A}_0^2$ can be interpreted as the elastic Andreev transparency at energy E . As a function of E , $D_A = 0$ for $|E| \leq \Delta$ (complete Andreev reflection). It is close to 1 for $E \gg \Delta$, while in the vicinity of the gap for $|E| > \Delta$, both D_A and $1 - D_A$ are finite. For arbitrary voltages, noise also contains inelastic contributions. In the limit of large voltages though, these terms vanish because of the decay of the Andreev reflection probability \mathcal{A}_0^2 far away from the gap region $|E| \leq \Delta$. This voltage independent level of noise is proportional to the excess current [1,2], $S_{\text{exc}}(0) = |eI_{\text{exc}}|/5$. It is illuminating to compare this with the level of noise in a normal quantum point contact [11–13] at $\omega = 0$ and $T = 0$,

$$S_N(0) = \frac{e^2}{\pi^2\hbar} \int_{-eV}^0 D_N(E)(1 - D_N(E)) dE, \quad (14)$$

where $D_N(E)$ is the normal transparency. In our case, $D_N = |d|^2 = 1$, and S_N vanishes.

Conclusion. We have shown that there is a finite level of current noise in voltage-biased junctions between superconductors, even if the transparency in the normal state is perfect. This excess noise is induced by fractional Andreev reflection and for large bias voltages ($eV \gg \Delta$) it is proportional to the excess current, the proportionality coefficient being equal to $|e|/5$. Consequently, the relationship between the excess noise and the excess current is qualitatively similar to the classical relation between shot noise and average current in the *low-voltage* regime, $S = 2|e|I$. The quantum reduction of excess noise (coefficient 1/5) is in our case pronounced.

This work was supported by NorFA, grant no. 94.35.174-O, the Nordic Research Network on the Physics of Nanometer Electronic Devices, the Swedish Natural Science Research

Council (NFR), and the Swedish Superconductivity Consortium. JPH gratefully acknowledges the hospitality of the Department of Physics at Oslo University, Norway.

REFERENCES

- [1] T. M. Klapwijk, G. E. Blonder, and M. Tinkham, Physica B **109&110**, 1657 (1982); G. E. Blonder, M. Tinkham, and T. M. Klapwijk, Phys. Rev. B **25**, 4515 (1982); M. Octavio, M. Tinkham, G. E. Blonder, and T. M. Klapwijk Phys. Rev. B, **27**, 6739 (1983).
- [2] A. Zaitzev, Sov. Phys. JETP **51**, 111 (1980); **59**, 1015 (1983).
- [3] G. B. Arnold, J. Low Temp. Phys. **59**, 143 (1985).
- [4] U. Günsenheimer and A. D. Zaikin, Phys. Rev. B **50**, 6317 (1994).
- [5] E. N. Bratus, V. S. Shumeiko, and G. Wendin, Phys. Rev. Lett. **74**, 2110 (1995).
- [6] A. W. Kleinsasser, R. E. Miller, W. H. Mallison, G.B. Arnold, Phys. Rev. Lett. **72**, 1738 (1994).
- [7] N. van der Post, E. T. Peters, I. K. Yanson, and J. M. van Ruitenbeek, Phys. Rev. Lett. **73**, 2611 (1994).
- [8] D. Averin and A. Bardas, preprint cond-mat/9505096.
- [9] D. Rogovin and D. J. Scalapino, Ann. Phys. (New York) **86**, 1 (1974).
- [10] K. K. Likharev, *“Dynamics of Josephson Junctions and Circuits”* (Gordon and Breach, New York-London-Paris-Montreux-Tokyo, 1986).
- [11] V. A. Khlus, Zh. Eksp. Teor. Fiz. **93**, 2179 (1987) [Sov. Phys. JETP **66**, 1243 (1987)].
- [12] G. B. Lesovik, Pis'ma Zh. Eksp. Teor. Fiz. **49** 513 (1989) [JETP Lett. **49**, 592 (1989)].
- [13] M. Büttiker, Phys. Rev. Lett. **65**, 2901 (1990); Physica **175**, 199 (1991); Phys. Rev. B **45** 3807 (1992).
- [14] W. Schottky, Ann. Phys. (Leipzig) **57**, 541 (1918).
- [15] R. Landauer, IBM J. Res. Dev. **1**, 223 (1957); **32**, 306 (1988).
- [16] P.G. De Gennes, *Superconductivity of Metals and Alloys* (Benjamin, New York, 1966), Chap. 5.
- [17] A. F. Andreev, Zh. Exp. Teor. Fiz. **46**, 1823 (1964) [Sov. Phys. JETP **19**, 1228 (1964)].
- [18] K. Likharev, Rev. Mod. Phys. **51**, 101 (1979).
- [19] Details of the derivation of noise will be published elsewhere.

FIGURES




FIG. 1. A scattering state for the perfect transmission ($d = 1$) case. Full lines represents one quasiparticle character $e(h)$ while dashed lines means the opposite character $h(e)$ – full thick line corresponds to incoming quasiparticle. Some Andreev reflection \mathcal{A}_n and normal transmission amplitudes \mathcal{N}_n to sidebands n with energy $E + neV$ are shown. Interchanging e and h characters, or changing the sign of the applied bias voltage, or interchanging left and right, causes the scattering state to be mirror-imaged around the energy E of the incoming particle, $n \rightarrow -n$.