

FUNCTIONAL DETERMINANTS IN THE PRESENCE OF ZERO MODES

KLAUS KIRSTEN AND ALAN J. MCKANE

ABSTRACT. We present a simple and accessible method which uses contour integration methods to derive formulae for functional determinants. To make the presentation as clear as possible we illustrate the general ideas using the Laplacian with Dirichlet boundary conditions on the interval. Afterwards, we indicate how more general operators as well as general boundary conditions can be covered.

1. INTRODUCTION

In the Euclidean path-integral formalism, physical properties of systems are conveniently described by means of path-integral functionals. The leading order contribution to path-integrals often involves the integration of the exponential of a quadratic form. This integration can be carried out exactly and yields a functional determinant[1, 2].

In recent years, a contour integration method for the evaluation of determinants has been developed[3, 4, 5]. Although the applicability of the method in higher dimension seems to be restricted to highly symmetric configurations, it turns out that in one dimension quite generic situations can be considered[6]. In particular, the case with zero modes present can be dealt with very elegantly and the determinants with the zero mode extracted can be found in closed form.

We will first introduce the contour integral methods using the simple example of the Laplace operator with Dirichlet boundary conditions on the interval. There will be no zero modes present and the example serves to introduce and explain some details of the method. Based on the example, more general second order operators with Dirichlet boundary conditions will be considered. The results found can be compared with known answers[7, 8]. Afterwards, we explain the additional complications when zero modes are present. The conclusions summarize the main results and will indicate further possible generalizations of the approach to Sturm-Liouville type operators with arbitrary boundary conditions.

2. EXAMPLE FOR THE LAPLACIAN ON THE INTERVAL

Let us consider first the Laplacian $L = -\frac{d^2}{dx^2}$ on the interval $I = [0, 1]$ with Dirichlet boundary conditions. The eigenvalues λ_n^2 and eigenfunctions u_n are defined by the equations

$$\begin{aligned} (1) \quad & -\frac{d^2}{dx^2}u_n(x) = \lambda_n^2 u_n(x), \\ (2) \quad & u_n(0) = u_n(1) = 0. \end{aligned}$$

Equation (1) is satisfied by

$$(3) \quad u_n(x) = C_1 \cos(\lambda_n x) + C_2 \sin(\lambda_n x).$$

The boundary condition $u_n(0) = 0$ forces $C_1 = 0$, and $u_n(1) = 0$ forces

$$\sin \lambda_n = 0 \quad \Leftrightarrow \quad \lambda_n = \pi n, \quad n \in \mathbb{Z}.$$

The set of nontrivial linearly independent eigenfunctions is given by $n \in \mathbb{N}$. For this case where eigenvalues are known explicitly, it is straightforward to write down the zeta function associated with L ,

$$\zeta_L(s) = \sum_{n=1}^{\infty} \frac{1}{(\pi n)^{2s}} = \pi^{-2s} \zeta_R(2s),$$

and to calculate the functional determinant in the zeta function scheme[9, 10, 11],

$$(4) \quad -\ln \det L = \zeta'_L(0) = -2\zeta'_R(0) \ln \pi + 2\zeta'_R(0) = \ln \pi - \ln(2\pi) = -\ln 2.$$

However, for cases where (1) contains a potential, eigenvalues are mostly not known and a simple procedure such as the one above is not available. To make this more general case accessible, we will therefore introduce contour integration methods to study the above example. The methods are then directly generalizable to cases with a potential.

Starting point for the contour integration method is the implicit eigenvalue equation

$$(5) \quad \sin \lambda_n = 0.$$

This equation allows the zeta function to be written as the contour integral

$$\zeta_L(s) = \frac{1}{2\pi i} \int_{\gamma} dk k^{-2s} \frac{\partial}{\partial k} \ln \sin k,$$

where the contour γ is counterclockwise and encloses all eigenvalues on the positive real axis. As given, the representation is valid for $\Re s > 1/2$. Next, one would like to shift the contour towards the imaginary axis. In doing so, we pick up a contribution from the origin because $\sin 0 = 0$. Therefore, a slightly more elegant formulation is obtained when starting with

$$(6) \quad \zeta_L(s) = \frac{1}{2\pi i} \int_{\gamma} dk k^{-2s} \frac{\partial}{\partial k} \ln \frac{\sin k}{k},$$

where the contribution from the origin is avoided because now $\lim_{k \rightarrow 0} \frac{\sin k}{k} = 1$. So now, nothing prevents us from shifting the contour to the imaginary axis and by taking due care of the cut of the complex root, which we place along the negative real axis, we find

$$(7) \quad \zeta_L(s) = \frac{\sin \pi s}{\pi} \int_0^{\infty} dk k^{-2s} \frac{\partial}{\partial k} \ln \frac{\sinh k}{k}.$$

As the $k \rightarrow 0$ behavior, and the $k \rightarrow \infty$ behavior, obtained from

$$\frac{\sinh k}{k} = \frac{e^k}{2k} (1 - e^{-2k}),$$

show, this integral representation is well defined for $1/2 < \Re s < 1$. The restriction $\Re s < 1$ comes from the $k \rightarrow 0$ behavior and $\Re s > 1/2$ comes from the $k \rightarrow \infty$ behavior. Writing for some $\epsilon > 0$

$$\zeta_L(s) = \frac{\sin \pi s}{\pi} \int_0^\epsilon dk k^{-2s} \frac{\partial}{\partial k} \ln \frac{\sinh k}{k} + \frac{\sin \pi s}{\pi} \int_\epsilon^\infty dk k^{-2s} \frac{\partial}{\partial k} \ln \frac{\sinh k}{k},$$

we need to construct the analytical continuation of the second integral to $s = 0$. This is achieved by adding and subtracting the leading $k \rightarrow \infty$ asymptotics, thus writing

$$\begin{aligned} \zeta_L(s) &= \frac{\sin \pi s}{\pi} \int_0^\epsilon dk k^{-2s} \frac{\partial}{\partial k} \ln \frac{\sinh k}{k} \\ &+ \frac{\sin \pi s}{\pi} \int_\epsilon^\infty dk k^{-2s} \frac{\partial}{\partial k} \ln \left(\frac{\sinh k}{k} 2k e^{-k} \right) + \frac{\sin \pi s}{\pi} \int_\epsilon^\infty dk k^{-2s} \frac{\partial}{\partial k} \ln \left(\frac{e^k}{2k} \right) \\ &= \frac{\sin \pi s}{\pi} \int_0^\epsilon dk k^{-2s} \frac{\partial}{\partial k} \ln \frac{\sinh k}{k} \\ &+ \frac{\sin \pi s}{\pi} \int_\epsilon^\infty dk k^{-2s} \frac{\partial}{\partial k} \ln \left(\frac{\sinh k}{k} 2k e^{-k} \right) + \frac{\sin \pi s}{\pi} \left(\frac{\epsilon^{1-2s}}{2s-1} - \frac{\epsilon^{-2s}}{2s} \right), \end{aligned}$$

valid around $s = 0$.

The derivative can now be easily carried out and its value at $s = 0$ is given in its simplest form by letting $\epsilon \rightarrow 0$. We obtain

$$\begin{aligned} (8) \quad \zeta'_L(0) &= \lim_{\epsilon \rightarrow 0} \left\{ \ln \left(\frac{\sinh k}{k} \right) \Big|_0^\epsilon + \ln \left(\frac{\sinh k}{k} 2k e^{-k} \right) \Big|_\epsilon^\infty - \epsilon + \ln \epsilon \right\} \\ &= - \lim_{k \rightarrow 0} \ln \left(\frac{\sinh k}{k} \right) - \ln 2 = - \ln 2, \end{aligned}$$

as given in (4).

3. MORE GENERAL SECOND ORDER OPERATORS

Generalizing from the previous example, it is the aim of this section to develop the contour integration approach for operators of the type

$$(9) \quad L = -\frac{d^2}{dx^2} + V(x),$$

again on the interval $I = [0, 1]$. The potential $V(x)$ is assumed to be continuous and to start with all eigenvalues will be assumed to be positive, so no zero modes are present. With an eye on equation (6) we let $u_k(x)$ be the unique solution of

$$(10) \quad (L - k^2)u_k(x) = 0$$

satisfying

$$(11) \quad u_k(0) = 0, \quad u'_k(0) = 1.$$

The condition $u_k(0) = 0$ is chosen such that the eigenvalues are fixed by imposing

$$(12) \quad u_k(1) = 0.$$

Then, the contour integral representation of the associated zeta function is

$$(13) \quad \zeta_L(s) = \frac{1}{2\pi i} \int_{\gamma} dk k^{-2s} \frac{\partial}{\partial k} \ln u_k(1).$$

The normalization $u'_k(0) = 1$ is chosen such that when shifting the contour towards the imaginary axis no contributions from the origin arise, see (6). As the leading $k \rightarrow \infty$ asymptotics does not depend on the potential $V(x)$, the subsequent steps are precisely as for the example in Section 2. Therefore, a glance at equation (8) shows that

$$(14) \quad \zeta'_L(0) = - \lim_{k \rightarrow 0} \ln(u_{ik}(1)) - \ln 2 = - \ln u_0(1) - \ln 2 = - \ln(2u_0(1)),$$

where, by definition, $u_0(x)$ is the solution of the homogeneous differential equation

$$Lu_0(x) = 0 \quad \text{with} \quad u_0(0) = 0, \quad u'_0(0) = 1.$$

4. PRESENCE OF ZERO MODES

For the case when zero modes are present, the formula (14) can not be applied simply because, as a zero mode, $u_0(x)$ satisfies $u_0(1) = 0$. Therefore, the contour cannot be shifted to the imaginary axis; instead, particular attention is needed when approaching the origin in the k -plane. We first need to determine the behavior of $u_k(1)$ for small k in order to eliminate the pole in the integrand. To do this, we note that integrating the left-hand side of

$$\int_0^1 dx u_0(x) Lu_k(x) = k^2 \int_0^1 dx u_0(x) u_k(x) \equiv k^2 \langle u_0 | u_k \rangle$$

by parts gives

$$[u'_0(x) u_k(x) - u'_k(x) u_0(x)]_0^1 + \int_0^1 dx u_k(x) (Lu_0(x)) = k^2 \langle u_0 | u_k \rangle.$$

Using the boundary conditions this yields

$$(15) \quad u_k(1) = \frac{k^2 \langle u_0 | u_k \rangle}{u'_0(1)} \equiv -k^2 f_k.$$

Since f_k is finite and non-zero as $k \rightarrow 0$, we have the desired behavior of $u_k(1)$. The minus sign has been included in the definition of f_k for later convenience. It is important to note that (15) is true for any k .

We can now modify the discussion of Section 3 to cover the case when a zero mode is present, by using the following observations. The function f_k , defined by (15), vanishes at all values of k for which k^2 is a positive eigenvalue, as $u_k(1)$ does. Only in the case of the zero eigenvalue do we have the situation where $f_0 \neq 0$, but $u_0(1) = 0$. Therefore if we use f_k instead of $u_k(1)$ in (13), and choose the contour so as to surround the positive eigenvalues, the contour can be shifted towards the origin. However, the notion that $u_k(1)$ may be straightforwardly substituted by f_k has to be amended slightly, since these functions have different behaviors as $k \rightarrow \infty$. This difference in behavior is accounted for if we replace $u_k(1)$ not by f_k , but by $(1 - k^2)f_k$, since then $u_{ik}(1) \sim k^2 f_{ik}$ as $k \rightarrow \infty$, while $(1 - k^2)f_k$ remains non-zero at $k = 0$.

These remarks lead us to consider the contour integral

$$(16) \quad \frac{1}{2\pi i} \int_{\gamma} dk k^{-2s} \frac{d}{dk} \ln(1 - k^2) f_k = \zeta_{L_1}(s) + \frac{1}{2\pi i} \int_{\gamma} dk k^{-2s} \frac{d}{dk} \ln(1 - k^2)$$

where the contour surrounds all the eigenvalues on the positive k axis. Depending on whether the contour encloses the point $k = 1$, this might differ from $\zeta_L(s)$ by a constant. But given our focus is on $\zeta'_L(0)$, this is irrelevant.

In summary, we are now in a position to proceed precisely as before. In (14), instead of having $u_0(1)$ make its appearance, it's now f_0 that comes into play. The contributions resulting from the asymptotics at infinity are not influenced at all by the existence of a zero mode and therefore remain the same as above in (14). Therefore, again referring to this equation, the answer now reads

$$(17) \quad \zeta'_L(0) = - \lim_{k \rightarrow 0} \ln(f_k) - \ln 2 = - \ln f_0 - \ln 2 = - \ln(2f_0).$$

For a particular problem specified, namely for any given potential $V(x)$, the derivative of the zero mode at the endpoint of the interval can be easily determined numerically and so can the determinant.

5. CONCLUSIONS

The calculation provided can be generalized in various respects. First, instead of considering (9), one can analyze determinants for general Sturm-Liouville type operators

$$L = - \frac{d}{dx} \left(P(x) \frac{d}{dx} \right) + V(x).$$

Reformulating the second order differential operator as a first order system we then introduce $v_k(x) = P(x)u'_k(x)$. General boundary conditions are imposed as

$$(18) \quad M \begin{pmatrix} u_{j,k}(0) \\ v_{j,k}(0) \end{pmatrix} + N \begin{pmatrix} u_{j,k}(1) \\ v_{j,k}(1) \end{pmatrix} = \begin{pmatrix} 0 \\ 0 \end{pmatrix},$$

where M and N are 2×2 matrices whose entries characterize the nature of the boundary conditions. For this quite generic situation closed formulas for the determinant can be derived and applied for different examples[12]. We can also relax the condition that the eigenvalues are nonnegative. In order that the associated zeta function can be defined in the presence of negative eigenvalues, we place the cut of the complex root at some angle different from 0 and from π . Choosing a suitable contour γ for the representation of the zeta function, only minor changes to the procedure explained are necessary[12].

REFERENCES

- [1] R. P. Feynman and A. R. Hibbs, *Quantum Mechanics and Path Integrals* (McGraw-Hill, New York, 1965).
- [2] L. S. Schulman, *Techniques and Applications of Path Integration* (Wiley-Interscience, New York, 1981).
- [3] M. Bordag, E. Elizalde and K. Kirsten, *J. Math. Phys.* **37**:895, 1996.
- [4] M. Bordag, K. Kirsten and J. S. Dowker, *Commun. Math. Phys.* **182**:371, 1996.
- [5] K. Kirsten, *Spectral Functions in Mathematics and Physics* (Chapman & Hall/CRC, Boca Raton, 2001).
- [6] K. Kirsten and A.J. McKane, *Ann. Phys. [NY]* **308**:502, 2003.
- [7] R. Forman, *Commun. Math. Phys.* **147**:485, 1992.
- [8] D. Burghelea, L. Friedlander and T. Kappeler, *Proc. Amer. Math. Soc.* **123**:3027, 1995.

- [9] D.B. Ray and I.M. Singer, *Advances in Math.* **7**:145, 1971.
- [10] S.W. Hawking, *Commun. Math. Phys.* **55**:133, 1977.
- [11] J.S. Dowker and R. Critchley, *Phys. Rev. D* **13**:3224, 1976.
- [12] K. Kirsten and A.J. McKane, *J. Phys. A: Math. Gen.* **37**:4649, 2004.

KK: MATHEMATICS DEPARTMENT, BAYLOR UNIVERSITY, WACO TX 76798, USA, E-MAIL: KLAUS_KIRSTEN@BAYLOR.EDU

AJMCK: DEPARTMENT OF THEORETICAL PHYSICS, UNIVERSITY OF MANCHESTER, MANCHESTER M13 9PL, ENGLAND, E-MAIL: ALAN.MCKANE@MAN.AC.UK