Quantum Left-handed metamaterial with superconducting quantum interference devices

C hunguang D u^y

HongyiChen

Shiqun Li

Key Laboratory for Quantum Information and Measurements of Education Ministry, Department of Physics, T singhua University, Beijing 100084, P.R.China.

A scheme of left-handed m etam aterial (LHM) composed of superconducting quantum interference devices (SQUIDs) and conducting wires is proposed. The permeability of a probe eld can be smoothly tuned over a wide range with another electrom agnetic (coupling) eld due to quantum interference effect. Sim ilar to electrom agnetically induced transparency (EII) of atom ic systems, the absorption of the probe eld can be strongly suppressed even in the case of negative permeability. There are two passbands of negative refractive index with low loss, which can be tuned with the coupling eld.

PACS numbers: 42.50 Gy, 78.20 Ci, 03.67 Lx, 42.50 Ct, 32.80 Qk

Recently, research on left-handed materials (LHM s) [1] has attracted considerable attentions. The LHM s are a kind of metameterial which have negative permittivity and negative permeability, which lead to negative refractive index in a narrow frequency band. M any novel phenomena can occur on LHM such as superprism, perfect at lens, inverse light pressure, and reverse D oppler and Vavilov-Cherenkov e ects. Large nonlinearity can also occur, e.g. the bistable transition of permeability from positive to negative [2]. The quantum phenomena in LHM s have also attracted attentions such as the modied spontaneous emission of atom s in LHM [3, 4]. However, the background of the ordinary LHM such as array of conductor lines and slit-ring resonators (SRR s)

^yE -m ail: duchunguang@ tsinghua.org.cn

is a 'classical' system where the negative and negative arise from the classical plasm a oscillations. In this sense, the ordinary LHM s are quite di erent from quantum system s such as atom ic gases. On the other hand, in ordinary situations, the magnetic response of atom ic gases to a laser eld is too weak to generate negative permeability. How to enhance the magnetic response of a quantum system is essential to realize LHM s at optical frequency band. There may be other ways to obtain negative permeability, e.g., recently, a scheme of electrom agnetically-induced left-handedness in atom ic gases is proposed [5], where large density of atom s is necessary and special restrictions on frequencies of driven elds and atom ic transitions are required. In contrast, an arti cial quantum system with high magnetic sensibility can has much more advantage than atom ic systems to realize negative permeability.

In this letter we propose a new kind of LHM composed of superconducting rings with Josephson junctions and conductor wires. For simplicity, the wires are assumed to be normal conductors. It should be note that quite di erent from our work, recently analysis and design of superconducting transm ission lines are presented by Salehiet al [6], and m ore recently, R icciet al have experim entally researched on a metam aterial that employs superconducting N b m etals and low-loss dielectric m aterials, in which case negative e ective index passband are seen between 50M Hz to 18G Hz [7]. The focus of our work is on the negative permeability which arises from quantum feature of the composite. In contrast with the 'classical' SRR, in our model the split of the ring is replaced by a Josephson junction, which is essential to the quantum feature of the LHM . We will show analytically that due to the quantum interference e = ects[8] the permeability can be tuned over a wide range with an external m icrowave eld. A lso, we will show that the absorption of the medium for the probe eld can be strongly suppressed even in the case of negative refractive index.

2

A scheme for supperconducting LHM is show in Fig.1, where the composite is composed of superconducting rings with Josephson junctions, and, an electric electric medium with electric permittivity as a background, which, e.g., can be an array of norm all conducting wires. The radius of the ring is denoted by a , and the period of the array is denoted by d. Schematic of the potential energy and the rst six eigen energies of the SQUID is shown in Fig. 2. We assume a probemicrow ave led is interacting with the composite. The wavelength of the led is assumed to be much longer than the period, i.e., d <<. For a classical cylindrical SRR system, the permeability can be given by the relation (according to Ref.[2])

$$B(!) = H_{x}(!) + FH^{0}(!);$$
(1)

where $H_x(!)$ is the alternating external magnetic eld and $H^{0}(!)$ is the additional magnetic eld induced by $H_x(!)$, which determ ines the magnetization of the composite, and $F = a^2 = d^2$ is the fraction of the structure with a being the radius of the ring and d being the periodicity of the array. Also, a << d << is assumed.

The permeability at angular frequency ! can be given by

$$(!) = 1 + F - \frac{(!)}{x};$$
 (2)

where (!) is the ux of frequency ! induced by the external microw ave eld, i.e. (!) = H⁰s with $s = a^2$ being the area of the ring. For the quantum LHM here, the SRRs are replaced by the SQUIDs, then (!) becomes an operator although the external driven elds are assumed to be classical. In order to calculate , (!) in Eq. (2) should be replaced by the quantum averaging of it, i.e. < (!) >.

The Ham iltonian of a SQUID (a ring with a Josephson junction) can be given by [9]

$$H_0 = -\frac{h}{2m}\frac{Q}{Qx^2} + V(x)$$
 (3)

with the potential of the SQUID being

$$V(\mathbf{x}) = \frac{1}{2} m !_{LC}^{2} (\mathbf{x} + \mathbf{x}^{0}) - \frac{1}{4^{2}} m !_{LC}^{2} \cos(2 \mathbf{x})$$
(4)

where $x = =_0$, $m = C_0^2$, $!_{LC}^2 = \frac{1}{LC}$, $= 2 L I_{C} =_0$, and $x^0 =_x =_0$. Here is the total ux in the ring, L is the ring inductance, x is an external applied magnetic ux to the SQUID, I_c is the critical current of the junction, C is the capacitance of the junction, and $_0 (= h=2e)$ is the ux quantum. W e consider a realistic SQUID system which can be described by use of the parameters as in the work of Zhou etal [9], where L = 100pH, C = 40fF, and $I_c = 3.95$ A, leading to $!_{LC} = 5 10^{11}$ rad=s, and = 1.2. The external DC magnetic eld parameters x^0 is taken to be 0.501.

The interaction between the SQUID and microwave elds, which are assumed to be linearly polarized with their magnetic eld perpendicular to the plane of the SQUID ring, is described by the time dependent potential

$$V_{int}(x;t) = m !_{LC}^{2} (x x^{0}) ("\cos!t + "_{c}\cos!_{c}t):$$
(5)

In the interaction picture ,the dynamics of the system is governed by the Schrodinger equation

$$i\hbar\frac{\theta}{\theta t}j (t) > = V_{int}j (t) > :$$
 (6)

Here ", "_c are m icrowave magnetic ux of the probe eld and the coupling eld in units of $_0$. The frequency of the probe eld and the coupling eld are chosen near resonant with transition $j0 > j_1 > and jl > j_1 >)$ respectively, where $j_1 >$ denotes the n-th eigen state of H₀. This is usually referred to as the three-level approximation. In this case, the wave function can be written as

$$j (t) > = c_0 (t) j > + c_1 (t) j > + c_n (t) j > ;$$
(7)

and the interaction Ham iltonian after the rotating-wave approxim ation, can

bewritten as [9]

$$V_{int} = h(e^{it}) > < nj + ce^{ict}) = < nj + hc: i - \frac{1}{2} > < 1j i - \frac{n}{2} > < 2j:$$
(8)

Here the Rabi frequency and _c are de ned as

$$= x_{0n}m !_{LC}^{2} =h; c = x_{1n}m !_{LC}^{2} =h;$$
(9)

where x_{0n} and x_{1n} are de ned as < 0 is $j_1 > and < 1$ is $j_1 > respectively$. Also, here = ! $!_{0n}$, $_c = !_c$ $!_{1n}$, $_1$ and $_n$ are the background decay rate of the state $j_1 > and j_1 > .$ The equations for am plitudes c_0 , c_1 , and c_n can be easily obtained from Eq.(6) as

$$i\frac{dc_{0}}{dt} = \frac{1}{2}C_{n}$$

$$i\frac{dc_{n}}{dt} = (+ i\frac{n}{2})C_{n} + \frac{1}{2}C_{0} + \frac{c}{2}C_{1}; \qquad (10)$$

$$i\frac{dc_{1}}{dt} = (-c_{1} + i\frac{1}{2})C_{1} + \frac{c}{2}C_{n}$$

We assume that $_1 << _n$, where $_n$ can be taken to be about 1G H z according to R ef. [10, 8]. We assume that initially the system is prepared in the ground state j >, and for simplicity, we assume the probe eld is weak enough, i.e. $<< _n$, $<< _c$. In this case the steady-state solution can be obtained as in ordinary E IT system s.

It is easy to prove that the mean value of the ux (< (!) >) can be given by

$$\frac{\langle (!) \rangle}{x(!)} = \frac{c_0 c_1}{z};$$
(11)

where $=\frac{m!_{LC}^2 x_{0n}^2}{h} = \frac{2}{hL} x_{0n}^2$. Here is a parameter measures the sensibility of the elective medium to the probe eld, which has the dimensions of frequency (Hz). For n = 4, $x_{04} = 5:39798$ 10⁻³, which is given by Ref.[11, 12]. Taking L = 100pH, we obtain = 11:815G Hz. This value will be used in the following analysis.

We rst consider the case of $_{\rm c}$ = 0, i.e. of two-level system (non-EIT

system). A coording to Eq.(2),(11) and (10), the permeability can be give by

$$= 1 \frac{F}{2 + i_4 = 2}$$
(12)

, It is clearly a Lorentz pro le. W hen the probe eld is near resonant with the transition $j0 > j_1 >$, strong absorption will occur. The absorption becomes sharp with the decrease of $_4$. Sim ilar to classical SRR composite, negative can occur (see Fig. 3(a)) if is large enough. The condition for the negative

can be easily deduced from Eq. 12 as that $F > 2_4$. A lso, it is clear that there is only one frequency band of negative Re(). However, it is worth to note that the -spectrum for the quantum composite here is similar but not the same as that in classical composite[2].

If the coupling eld is applied to the system ($_{c} \in 0$), the magnetic response could be significantly modified. For a strong coupling eld, i.e. $_{c} >>$, 4, from Eq.(2),(11) and (10), the permeability can be given by

$$= 1 \quad \frac{F}{2} \frac{c + i\frac{1}{2}}{c + i\frac{1}{2} + i\frac{4}{2} - \frac{c^2}{4}}; \tag{13}$$

The spectrum of in three-level case is show in Fig. 3(b). It can be easily seen that the transparency occurs when $= _{c} = 0$, which is similar to E IT of atom ic system except that here the coupling eld is used to control the permember meability instead of the permittivity of the probe eld. Superconductive analog to electrom agnetically induced transparency that utilizes superconductive quantum circuit designs of present day experimental consideration has also been investigated by Muralial et al [8]. The width of the transparency window can be de ned by the frequency distance between the two absorption peaks which is about $_{c}$ due to Auther-Tow nes splitting. The frequency band for low absorption and large refraction can occur over a wide range for large $_{c}$. On the contrary, the group velocity of the probe eld can be reduced to near zero as in atom ic E IT system s. If F is very sm all, is positive for all probe detunings (), which can be easily seen from Eq.(13). If F is large

enough, however, negative Re() can occur near the transparency window. The condition for negative can be deduced from Eq. (13) as that

$$F > 2_4$$
: (14)

This condition is the same as that for nonEIT case, but the frequency band for negative in the EIT case and nonEIT case is quite di erent. In the EIT case there are two frequency bands for negative , which can be given by

$$f(x) < = _4 < f(x_+); \quad f_+(x) < = _4 < f_+(x_+);$$
 (15)

where

$$f(x) = \frac{x}{2} \frac{q}{x^2 + \frac{2}{c^2} = \frac{2}{4}}{2};$$
 (16)

and

$$x = \frac{1}{2} (g \quad \frac{q}{g^2} \quad 1)$$
 (17)

with $g = \frac{F}{2_4} > 1$

For example, we consider the case of = 11.815G H z as above. If taking F = 0.14, we can obtain that F = 2 = 2.5982G H z. In this case negative Re() can occur if the condition $_4 < 2.5982$ G H z is met.

It should be note that, when $= _{c}$ and $_{1} = 0$, exactly zero absorption occcur (Im () = 0), but in this case Re() = +1. When Re() is negative, Im () is always nonzero, i.e. negative refractive index without loss can never occur. However, the absorption can be strongly suppressed near the condition of $= _{c}$. It is similar to ordinary EIT in atom ic systems, but here the zero absorption occurs due to magnetic response instead of electric response, and, here, the magnetic is so strong that negative Re() can occur near EIT condition. The permeability () can be smoothly tuned over a wide range with the coupling detuning $_{c}$ (see Fig. 4) and its Rabifrequency $_{c}$ (see Fig.(5)). It is worth to note that the tunability is due to the quantum interference e ect which is absent in classical norm al conductor systems. The permeability and refractive index n can be smoothly tuned by the coupling eld over a wide range, and the continuous transition from Re() = 1 to Re() = 1 is possible. From the -spectrum it is easy to see that there are four frequencies for Re() = 1, but only two of them are for low loss (sm all Im ()), one of which is in EIT window, while the other one is out of EIT window. It is should be note that both of them can be tuned with the coulpling eld. For this two frequencies, Im ()! 0 when 4! 0 and 1! 0.

In order to calculate the refractive index, the perm ittivity and perm eability can be written as

$$= j \dot{\mathbf{p}}^{i} \cdot \mathbf{;} = j \dot{\mathbf{p}}^{i} \cdot \mathbf{;}$$
(18)

where $0 < e_{e} < 0 < m_{m} < 0$. Then the refractive index n can be given by [3]

$$n = \int j j j j e^{i(e^+ m)=2}$$
(19)

For the sake of simplicity, we consider the case where the electric permittivity is generated by an array of normal conducting classical current wires [3, 2]. In this case

$$= 1 + \frac{!_{pe}^{2}}{!_{Te}^{2} ! !_{pe}^{2}}$$
(20)

where $!_{pe}$ and $!_{Te}$ are the parameters which measure the elective plasma oscillations and $_{e}$ measures the loss of the wires. The refractive index spectrum of the composite is shown in Fig. (6), where (a) is for (), (b) is for (), and (c) is for n(). For simplicity, we consider the frequency band of negative which is far from resonance, in which case is slow ly varing with , and Im () is small. We nd in this case there are two minima on the Im (n)-spectrum. The absorption minima arise from two reasons: (1) small Im () and small Im (); (2)Re() and Re() are simultaneously negative. On the contrary, if Re()Re() < 0, Im (n) will be large even if both of Im () and Im () are innitely small. Two passbands of negative refractive index appear around the two minima, both of them are sensitive to the coupling eld.

In conclusion, we have analytically investigated the metam aterial com posed of superconducting rings with Josephson junctions and conducting wires. It is found that negative permeability for a probe microwave eld can occur when $g = \frac{F}{2A} > 1$. There are two passbands of negative refractive index with low loss, which can be tuned with the coupling eld. To our know ledge, it is for the st time that the quantum left-handed metam aterial being com posed of SQUIDs has been investigated. One of the advantages of this kind of LHM is that the negative refractive index with low loss is easy to obtain due to that the perm eability can be sm oothly tuned over a wide range includina = 1 + i" ("! 0+). In the quantum composite, some new physics could be found, such as that associated with transient properties of the lefthandedness, large nonlinearity due to the quantum interference e ect and that due to strong m agnetic response of the com posite. A lso, the tunability of the com posite via quantum interference e ect could be used in quantum inform ation process [13]. On the other hand, the LHM with SQUIDs can be regarded as a bridge between the 'classical' LHM s (e.g. composed of SRRs and wires) and the 'quantum' system s composed of microscopic particles (e.g. atom s or quantum dots). Hence, further research on the quantum LHM could facilitate the realizing of the tunable LHM s of high-frequency (towarding to optical) band.

ACKNOW LEDGMENT

This work is supported by the National Nature Science Foundation of China (G rant No. 10504016) and funded by the State K ey D evelopm ent P rogram for Basic Research of China (G rant No. 001C B 309308).

References

- [1] V.G.Veælago, Usp.Fiz Nauk 8, 2854 (1967) [Sov.Phys.Usp.10, 509 (1968)]
- [2] A.A. Zharov, I.V. Shadrivov, and Y.S.Kivshar, Phys. Rev. Lett., 91 037401 (2003)
- [3] H.T.Dung, S.Y.Buhmann, L.Knollet al, Phys. Rev A 68, 043816 (2003)
- [4] J.Kastel and M.Fleischhauer, PhysRev.A bf 71 011804 (2005)
- [5] M.O.Okteland O.E.Mustecaplioglu, Phys. Rev. A 70, 053806 (2004).
- [6] H. Salehi, A. H. Majedi, R. R. Mansour, EEE TRANSACTIONS ON APPLIED SUPERCONDUCTIVITY 15,996 (2005)
- [7] M.Ricci, N.Orb, and S.M. Anlage, Appl. Phys. Lett., 87 034102 (2005)
- [8] K.V.R.M.Murali, Z.Dutton, W.D.Oliver, D.S.Crankshaw, and T.P. Orlando, Phys Rev. Lett. 93 087003 (2004)
- [9] Z. Zhou, S. I. Chu, and S. Han, Phys. Rev. B 66, 054527 (2002)
- [10] Y.N.Ovchinnikov, P.Silvestrini, V.Corato, and S.Rombetto, Phys. Rev.B 71,024529 (2005).
- [11] E. Paspalakis and N. J. Kylstra, J. M od. Opt. 51, 1679 (2004);
- [12] N.A ravantinos-Za ris and E. Paspalakis, Phys. Rev. A 72 014303 (2005).
- [13] C.P.Yang, S.I.Chu, and S.Han, Phys. Rev. Lett. 92 117902 (2004).

Figure Captions

Fig. 1. Schem atic of the composite m etam aterial structure composed of superconducting rings with Josephson junctions (SQUID s) and the e ect electric m edium such as conductor wires. Each SQUID is an articial -con guration three-level system which coupled with a probem icrow ave eld and a coupling m icrow ave eld.

Fig. 2. Schem atic of the potential energy and the rst six eigen energies of the SQUID. The energies of the ground state j > , m eta-stable state j > , and the excited state j > are 7.81984m ev, 7.90183m ev, and 8.14057m ev, respectively.

Fig. 3. Realpart (solid curve) and in aginary part (dashed curve) of the permeability () versus the probe detuning for $_{c} = 0$, where F = 0:14, $_{4} = 0:0423$, $_{1} = 0:1_{4}$, = 1:2, $x^{0} = 0:501$. (a) is for $_{c} = 0$ and (b) is for $_{c} = 0:5078$. All parameters are in units of , which is taken to be 11.815G H z.

Fig. 4. Real part (solid curve) and imaginary part (dashed curve) of the permeability () versus the coupling detuning $_{\rm c}$ for the case of = 0. The parameters are the same as that in Fig. 3

Fig.5. The band edges of negative Re() versus the Rabi frequency of the coupling eld _c. Negative Re() occurs when is between the two solid curves (band1) or that between the dashed curves (band2). The parameters are the same as that in Fig.3.

Fig.6. The spectrum of perm ittivity (a), perm eability (b), and refractive index (c), where $!_{pe} = 1.5!_{04}$, $!_{Te} = 0.43!_{04}$, $_{e} = 0.1!_{04}$. The solid line is for the real part of them, while the dashed line is for the imaginary part of them. Here $!_{04} = 48.727$ G Hz. O ther parameters are the same as that in

11

Fig.3.



Fig. 1

Du et al



Fig. 2

Du et al.



Fig.3

Du et al



Fig. 4

Du et al.



Fig. 5

Du et al.



Fig. 6

Du et al.