

Quantum error correction in the presence of spontaneous emission.

M. B. Plenio, V. Vedral, and P. L. Knight

Blackett Laboratory, Imperial College London, London SW 7 2BZ, England

(February 7, 2022)

We present a quantum error correcting code that is invariant under the conditional time evolution between spontaneous emissions and which can correct for one general error. The code presented here generalizes previous error correction codes in that not all errors lead to different error syndromes. This idea may lead to shorter codes than previously expected.

89.70.+c, 89.80.h, 03.65.Bz

I. INTRODUCTION

With the discovery of an algorithm to factorize a large number on a quantum computer in polynomial time instead of exponential time as required by a classical computer [1], the question of how to implement such a quantum computer has received considerable attention [2]. However, realistic estimates soon showed that decoherence processes and spontaneous emission severely limit the bit size of the number that can be factorized [3,4]. It has become clear that the solution to the problem does not lie in an increase in the lifetime of the transitions used in the computation. Attention has now shifted towards the investigation of methods to encode qubits such that the correction of errors due to interaction with the environment becomes possible. In a number of recent publications, possible encoding schemes have been considered and theoretical work has been undertaken to elucidate the structure of quantum error correction codes [5-22]. However, we show that these codes do not perfectly correct errors due to the conditional time evolution [23] between spontaneous emissions. This has the effect that for example the encoded lower state of a qubit, which, if unencoded, is not influenced by the conditional time evolution, acquires an error due to the conditional time evolution. We then proceed to construct a code that is able to correct one general error and is able to correct to all orders the errors due to the conditional time evolution between spontaneous emissions. By one general error we mean an arbitrary one bit operation acting on a single bit of the code. The conditional time evolution, however, contains terms that act on many qubits. Our code proposed in this paper is the first code that has the ability to correct a special kind of error (here due to the conditional time evolution) to all orders. This is an interesting feature, as one would be interested to correct those errors which frequently occur to higher order than rare errors. The code presented here is optimal in the

sense that it uses the smallest possible number of qubits required to perform its task (correcting one general error and all errors due to the conditional time evolution).

II. SINGLE ERROR CORRECTING CODES

Several codes have been proposed to encode one qubit which can correct one general error, i.e. amplitude and phase error or a combination of both applied to the same qubit. An example [10] of such a code is one where state $|j\rangle_i$ is represented by

$$|j\rangle_L = |j0000\rangle_i + |j1100\rangle_i + |j0011\rangle_i + |j1111\rangle_i + |j1010\rangle_i + |j0110\rangle_i + |j1001\rangle_i + |j0101\rangle_i \quad (1)$$

and the state $|j\rangle_i$ by

$$|j\rangle_L = |j1111\rangle_i + |j0011\rangle_i + |j1100\rangle_i + |j0000\rangle_i + |j0101\rangle_i + |j1001\rangle_i + |j0110\rangle_i + |j1010\rangle_i; \quad (2)$$

where the subscript L indicates that the encoded state $|j\rangle_L$ differs from the initial state $|j\rangle_i$. We omit the obvious normalization factor in the states $|j\rangle_L$ and $|j\rangle_i$ throughout this letter as they are irrelevant for the present analysis. Starting with a state $|j\rangle_i = |j\rangle_i + |j\rangle_i$, this is encoded as $|j\rangle_L = |j\rangle_L + |j\rangle_L$. If the state suffers an amplitude error A_i (which acts as a NOT operation on qubit i) or a phase error P_i (which gives the upper state of qubit i a minus sign) or the combination $A_i P_i$ of both to the i th qubit of $|j\rangle_L$ it is possible to reconstruct the initial state $|j\rangle_i$. The code given in eqs. (1) - (2) has the attractive feature that it is optimal in the sense that it only requires 5 qubits which can be shown to be the minimal possible number [13]. Using ideas similar to classical error correcting codes one can estimate that if one wants to encode l qubits in terms of n qubits in such a way that one can reconstruct the state after t general errors, then the inequality

$$2^{l \sum_{i=0}^t X^i} 3^{i \sum_{i=0}^t n} 2^n \quad (3)$$

has to be satisfied [11]. The bound eq. (3) is related to the sphere packing bound in classical coding theory [24]. The reason for that is that eq. (3) was obtained using the assumption that different errors lead to different mutually orthogonal error syndromes. However, we will later see that the code presented in this paper (like

the one presented in [5]) in fact violates this assumption which shows that it may be possible to find codes that go beyond eq. (3).

The code given in eqs. (1) – (2) does not correct for multiple errors. Especially, it is not able to correct to all orders for errors that arise due to the conditional time evolution between spontaneous emissions. The conditional time evolution between spontaneous emissions is unavoidable and it differs from the unit operation because the fact that no spontaneous emission has taken place provides information about the state of the system and therefore changes its wave function. The conditional time evolution of the system under the assumption that no spontaneous emission has taken place is given by the non-unitary time evolution operator $\exp(-iH_{\text{eff}}t) = \exp(-iH_g t)$ [23]. For the case that the qubits are not driven by external fields we obtain for the code given in eqs. (1) – (2) the effective Hamilton operator

$$H_{\text{eff}} = \sum_{i=1}^5 X_i^5 \quad i h_{11}^{(i)} ; \quad (4)$$

where $h_{11}^{(i)}$ is the projector $|j_L i\rangle\langle j_L i|$ onto the excited state of the i th qubit leaving all other qubits unaffected. $h_{11}^{(i)}$ is the Einstein coefficient of the upper level 1 of the qubits. If we apply the conditional time evolution $\exp(-iH_{\text{eff}}t)$ to the encoded state

$$|j_L i\rangle = |j_L i\rangle + |j_L i\rangle \quad (5)$$

and subsequently apply the appropriate error correction procedure for this 5-bit code [10] we do not recover the original state. This becomes obvious in the special case $t = 1$ in which one obtains

$$|j_C i\rangle = |j_0000i\rangle + |j_0010i\rangle + |j_1000i\rangle + |j_1110i\rangle + |j_1000i\rangle + |j_1001i\rangle + |j_1100i\rangle + |j_1110i\rangle : \quad (6)$$

This shows that this 5-bit code is not able to correct errors due to the conditional time evolution exactly. Especially striking is the effect when we assume that $\gamma = 0$, i.e. we encode the (stable) ground state. The conditional time evolution then leads to no errors in the unencoded state while it changes the encoded state such that it cannot be corrected perfectly anymore. Note, however, that the error introduced by the conditional time evolution is, for short times, of fourth order. If, however, a spontaneous emission (or any other kind of error) occurs then a subsequent conditional time evolution induces contributions which after error correction lead to second order errors in the state. Our code presented later in this paper preserves the encoded state in both cases perfectly, i.e. to all orders.

The reason that the code eqs. (1)–(2) cannot perfectly correct errors due to the conditional time evolution derives from the fact that the words (product states) of

which the code consists do not all have the same number of excited states. This leads to a difference in the rate at which the amplitude of these states decays. The amplitude of $|j_0000i\rangle$ remains unchanged under the conditional time evolution while the amplitude of $|j_1110i\rangle$ for example decreases at a rate $\exp(-3t)$. This can be seen as a multiple amplitude error with which the code can not cope. This problem is not restricted to the 5-bit code given in [10] but is present in all other previously proposed codes. It should be noted that it is not necessary to observe the system for these conclusions to hold. If we do not observe the system, it then has to be described by a density operator, whose time evolution follows the appropriate Bloch equations. This time evolution can in principle be decomposed into individual trajectories each of which consists of no jump evolutions interrupted by spontaneous emissions [23]. For each of these trajectories our considerations above hold and therefore also hold for the incoherent sum of these trajectories which make up the ensemble. Therefore our error correction code is not restricted to a particular measurement scheme such as for example the detection and reconstruction scheme discussed in [25], where it is necessary to detect individual quantum jumps. Nevertheless such a detection of individual jumps would improve the performance of our code, as that would exclude the contribution of multiple quantum jumps with which our code cannot cope. This would enhance the importance of the conditional time evolution as a error source compared to other sources and it is here where our code is superior to previous codes.

III. CORRECTING SPONTANEOUS EMISSION

The discussion of the last section shows that it is of some interest to construct a quantum error correcting code that corrects errors due to the conditional time evolution to all orders. This is possible, and in the following we present such a quantum error correcting code.

The following code was constructed starting from the code (1)–(2). State $|j_i\rangle$ is encoded as

$$|j_L i\rangle = |j_0001111i\rangle + |j_1101000i\rangle + |j_10010110i\rangle + |j_11100001i\rangle + |j_11010100i\rangle + |j_01100111i\rangle + |j_1001101i\rangle + |j_0101010i\rangle ; \quad (7)$$

while state $|j_i\rangle$ is encoded as

$$|j_L i\rangle = |j_1110000i\rangle + |j_0010111i\rangle + |j_1101001i\rangle + |j_0001110i\rangle + |j_0101011i\rangle + |j_11001100i\rangle + |j_0110010i\rangle + |j_0101010i\rangle ; \quad (8)$$

The state eq. (7) encoding the logical 0 was obtained in the following way. We started with state eq. (1) and for each word, e.g. $|j_1110i\rangle$ we constructed the bitwise inverse, i.e. $|j_0001i\rangle$. We concatenated the two words where the second one is taken in reverse bit order to obtain $|j_111011000i\rangle$. This method, applied to all words in eq. (1), already yields a possible code. However, it is

for some errors, a slightly different effect than expected. Take for example a phase error P_1 on bit 1 and compare with the effect of a phase error P_8 on bit 8. We observe that they both lead to the same error syndrome but that the resulting state differs by a global phase -1 . Therefore it is not possible to correct both states in such a way that they go over to the initial state. After the correction they differ by a global phase -1 . But this also shows that the dimension of the space H_{code} spanned by the code together with all states that result from it by single errors is 21 and not as expected from eq. (3) 25. The latter number results from the considerations of Ekert and Macchiavello [11] who have presented a set of conditions that have to be satisfied by any quantum error correction code. The violation of these conditions by the code eq. (7)–(8) leads to these different predictions for the dimension of H_{code} . More general conditions can be derived and it can be checked easily that our code satisfies these conditions [13,26] while it violates the conditions given in [11].

So far we have shown that our code can indeed correct a general single error without taking into account the conditional time evolution due to spontaneous emission. Now we show that our code is able to correct errors due to the conditional time evolution perfectly, i.e. to all orders. For our code given in eqs. (7)–(8) the conditional time evolution under the assumption that no spontaneous emission has taken place is generated by the effective Hamiltonian operator

$$H_{\text{eff}} = \sum_{i=1}^8 X_i^{(i)} \quad (9)$$

If the code undergoes a conditional time evolution before it experiences an error like e.g. a spontaneous emission, it is obvious that the code eqs. (7)–(8) will work properly, as it is invariant under the conditional time evolution $\exp(-iH_{\text{eff}}t)h$. However, it is not so obvious that the code corrects general single errors that occur before or in between the conditional time evolution. As we do not know the time at which the general error occurs, this situation will almost certainly occur and has to be examined. If the error was a phase error, then no problem will occur, as this error does not change the excitation of the state. However, for amplitude errors or a combination of amplitude and phase errors we have to investigate the code more closely. The problem is that, for example after an amplitude error in the first qubit, we obtain

$$\begin{aligned} A_1 |j_L\rangle_i = & |j_0001111\rangle_i + |j_1110001\rangle_i + |j_1001101\rangle_i + |j_0110011\rangle_i \\ & + |j_1101001\rangle_i + |j_0010110\rangle_i + |j_1010100\rangle_i + |j_0101010\rangle_i : \quad (10) \end{aligned}$$

Now the code words have a different degree of excitation so that their relative weights will change during the subsequent conditional time evolution. How-

ever, for $|j_L\rangle_i = |j_0\rangle_i + |j_1\rangle_i$ we have the relations $|j_L\rangle_i = |j_0\rangle_i + |j_1\rangle_i$

$$e^{-iH_{\text{eff}}t}h A_i |j_L\rangle_i = \frac{1}{2} e^{-3t} (1 + e^{-2t}) A_i |j_L\rangle_i + (1 - e^{-2t}) A_i P_i |j_L\rangle_i \quad (11)$$

and

$$e^{-iH_{\text{eff}}t}h A_i P_i |j_L\rangle_i = \frac{1}{2} e^{-3t} (1 - e^{-2t}) A_i |j_L\rangle_i + (1 + e^{-2t}) A_i P_i |j_L\rangle_i : \quad (12)$$

Eq. (11) shows that after an amplitude error A_i on the i th qubit, the conditional time evolution transforms the state into a superposition of a state without conditional time evolution after this amplitude error, and a state without conditional time evolution obtained after a combined amplitude and phase error $A_i P_i$ on the i th qubit. Inspecting table 1 we see that both errors A_i and $A_i P_i$ lead to a different error syndrome. A measurement of the syndrome will then indicate one or the other error, A_i or $A_i P_i$, which can then be corrected. Therefore the code (7)–(8) corrects properly even if the error is followed by a conditional time evolution.

IV. CONCLUSIONS

We conclude that the code presented here is able to correct a single general error and in addition errors due to the conditional time evolution to arbitrary order. It is the first code proposed so far that can correct general errors to first order and a special kind of errors to all orders. This is an interesting result as it shows that it is possible to correct special kinds of errors to all orders. As some errors are more frequent than others it would be in our interest to correct those errors to higher order than less frequently occurring errors. We have adapted our code to errors due to the conditional time evolution between spontaneous emissions. Other applications will require different adaptations. The code presented here (similar to the one given in [5]) violates the conditions for quantum codes given in [11] which shows that these conditions are overly restrictive, as they exclude codes like the one presented here that map different errors onto the same error syndromes. This can lead to the construction of shorter quantum error correction codes than expected from the quantum sphere packing bound as derived in [11]. These results may become important in different fields such as quantum computation, the distribution of entangled particles and in quantum cryptography [27–30].

Acknowledgements

The authors thank A. Ekert, C. Macchiavello and A. M.

Steane for discussions about quantum error correction. This work was supported by the European Community, the UK Engineering and Physical Sciences Research Council and by a Feodor-Lynen grant of the Alexander von Humboldt foundation.

-
- [1] P.W. Shor. In Proc. 35th Annual Symposium on Foundations of Computer Science, ed. S. Goldwasser. (IEEE Computer Society Press, Nov. 1994) pp. 124-134.
 - [2] J.I. Cirac and P. Zoller, Phys. Rev. Lett. 74, 4091 (1995)
 - [3] M.B. Plenio and P.L. Knight, Phys. Rev. A 53, 2986 (1996)
 - [4] M.B. Plenio and P.L. Knight, Proceedings of the 2nd International Symposium on Fundamental Problems in Quantum Physics, 1996 edited by M. Ferrero and A. Van der Merwe (Kluwer, Dordrecht)
 - [5] P.W. Shor, Phys. Rev. A 52, R2493 (1995)
 - [6] I.L. Chuang and R. Laamme, Quantum Error Correction by Coding., preprint quant-ph/9511003
 - [7] A.R. Calderbank and P.W. Shor, Good Quantum Error-Correcting Codes Exist. preprint quant-ph/9512032
 - [8] A.M. Steane, Phys. Rev. Lett. 77, 793 (1996)
 - [9] A.M. Steane, Multiple Particle Interference and Quantum Error Correction. lanl e-print quant-ph/9601029
 - [10] R. Laamme, C. Miquel, J.P. Paz, and W.H. Zurek, Perfect Quantum Error Correction Code. preprint quant-ph/9602019
 - [11] A. Ekert and C. Macchiavello, Error Correction in Quantum Communication. preprint quant-ph/9602022, Oxford University
 - [12] L. Vaidman, L. Goldenberg, and S. Wiesner, Error Prevention Scheme with Four Particles, lanl e-print quant-ph/9603031
 - [13] E. Knill and R. Laamme, A theory of quantum error-correcting code, lanl e-print quant-ph/9604015
 - [14] C.H. Bennett, D.P. DiVincenzo, J.A. Smolin, and W.K. Wootters, Mixed state entanglement and quantum error-correction codes, lanl e-print quant-ph/9604024
 - [15] A. Barenco, A. Berthiaume, D. Deutsch, A. Ekert, R. Josza, and C. Macchiavello, Stabilisation of quantum computations by symmetrisation, lanl e-print quant-ph/9604028
 - [16] A.R. Calderbank, E.M. Rains, P.W. Shor, and N.J.A. Sloane, lanl e-print quant-ph/9605005
 - [17] P.W. Shor, Fault-Tolerant Quantum Computation, lanl e-print quant-ph/9605011
 - [18] A.M. Steane, Simple Quantum Error Correcting Codes, lanl e-print quant-ph/9605021
 - [19] D.P. DiVincenzo and P.W. Shor, Fault-Tolerant Error Correction with Efficient Quantum Codes, lanl e-print quant-ph/9605031
 - [20] D. Gottesman, Pasting Quantum Codes, lanl e-print quant-ph/9607027
 - [21] D. Gottesman, Phys. Rev. A 54, September 1996
 - [22] D. Gottesman, Efficient Computations of Encodings for Quantum Error Correction, lanl e-print quant-ph/9607030
 - [23] J. Dalibard, Y. Castin, and K. Mølmer, Phys. Rev. Lett. 68, 580 (1992)
 - G.C. Hegerfeldt and T.S. Wilser, Proceedings of the II. International Wigner Symposium, Goslar 1991, H.D. Doebner, W. Scherer, and F. Schroeck, Eds., World Scientific, Singapore 1992
 - H.J. Carmichael, An Open Systems Approach to Quantum Optics. Lecture Notes In Physics, (Springer, Berlin 1993)
 - [24] V. Pless, Introduction to the Theory of Error-Correcting Codes, John Wiley & Sons 1982
 - [25] H. Mabuchi and P. Zoller, Phys. Rev. Lett. 76, 3108 (1996)
 - [26] V. Vedral, M. Rippin, and M.B. Plenio, submitted to Phys. Rev. A 1996
 - [27] C.H. Bennett and G. Brassard, in Proceedings of IEEE Conference on Computers, Systems and Signal Processing, p.175 (IEEE 1984)
 - [28] A. Ekert, Phys. Rev. Lett. 67, 661 (1991)
 - [29] R.J. Hughes, D.M. Aldle, P. Dyer, G.G. Luther, G.L. Morgan and M. Schauer, Cont. Physics 36, 149 (1995)
 - [30] S.J.D. Phoenix and P.D. Townsend, Cont. Physics 36, 165 (1995)