

Efficient calculation of the mutual inductance of arbitrarily oriented circular filaments via a generalisation of the Kalantarov-Zeitlin method

Kirill V. Poletkin^{a,*}, Jan G. Korvink^a

^a*The Institute of Microstructure Technology, Karlsruhe Institute of Technology, Hermann-von-Helmholtz-Platz 1, 76344 Eggenstein-Leopoldshafen, Germany*

Abstract

In this article, we present a new analytical formulation for calculation of the mutual inductance between two circular filaments arbitrarily oriented with respect to each other, as an alternative to Grover [1] and Babič [2] expressions reported in 1944 and 2010, respectively. The formula is derived via a generalisation of the Kalantarov-Zeitlin method, which showed that the calculation of mutual inductance between a circular primary filament and any other secondary filament having an arbitrary shape and any desired position with respect to the primary filament is reduced to a line integral. In particular, the obtained formula provides a solution for the singularity issue arising in the Grover and Babič formulas for the case when the planes of the primary and secondary circular filaments are mutually perpendicular. The efficiency and flexibility of the Kalantarov-Zeitlin method allow us to extend immediately the application of the obtained result to a case of the calculation of the mutual inductance between a primary circular filament and its projection on a tilted plane. Newly developed formulas have been successfully validated through a number of examples available in the literature, and by a direct comparison with the results of calculation performed by the *FastHenry* software.

Keywords: Inductance, circular filaments, coils, line integral, electromagnetic

*Corresponding author

Email address: kirill.poletkin@kit.edu (Kirill V. Poletkin)

1. Introduction

Analytical and semi-analytical methods in the calculation of inductances, and in particular the mutual inductances of filament wires and their loops, play an important role in power transfer, wireless communication, and sensing and actuation, and is applied in different fields of science, including electrical and electronic engineering, medicine, physics, nuclear magnetic resonance, mechatronics and robotics, to name the most prominent. Collections of formulas for the calculation of mutual inductance between filaments of different geometrical shapes covering a wide spectrum of practical arrangements have variously been presented in classical handbooks by Rosa [3], Grover [4], Dwight [5], Snow [6], Zeitlin [7], Kalantarov [8], among others.

The availability of efficient numerical methods such as *FastHenry* [9] (based on the multipole expansion) currently provides an accurate and fast solution for the calculation of mutual and self-inductance for any circumstance, including the use of arbitrary materials, conductor cross-sections, loop shapes, and arrangements. However, analytical methods allow to obtain the result in the form of a final formula with a finite number of input parameters, which when applicable may significantly reduce computation effort. It will also facilitate mathematical analysis, for example when derivatives of the mutual inductance w.r.t. one or more parameters are required to evaluate electromagnetic forces via the stored magnetic energy, or when optimization is performed.

Analytical methods applied to the calculation of the mutual inductance between two circular filaments is a prime example, and has been successfully used in an increasing number of applications, including electromagnetic levitation [10], superconducting levitation [11, 12, 13], magnetic force interaction [14], wireless power transfer [15, 16, 17], electromagnetic actuation [18, 19, 20, 21], micro-machined contactless inductive suspensions [22, 23, 24, 25] and hybrid suspensions [26, 27, 28], biomedical applications [29, 30], topology optimiza-

tion [31], nuclear magnetic resonance [32, 33], indoor positioning systems [34], navigation sensors [35], and magneto-inductive wireless communications [36].

The original formula of the mutual inductance between two coaxial circular filaments was derived by Maxwell [37, page 340, Art. 701] and expressed in terms of elliptic integrals. Butterworth obtained a formula covering the case of circular filaments with parallel axes [38]. Then, a general formal expression made for cases where the axes of the circles are parallel, and where their axes intersect, was derived by Snow [39]. However, the Butterworth and Snow expressions suffer from a low rate of convergence. This issue was recognized and solved by Grover, who developed the most general method in the form of a single integral [1]. Using the vector potential method, as opposed to the Grover means, the general case for calculating the mutual inductance between inclined circular filaments arbitrarily positioned with respect to each other was subsequently obtained by Babič et al. [2].

Kalantarov and Zeitlin showed that the calculation of mutual inductance between a circular primary filament and any other secondary filament having an arbitrary shape and any desired position with respect to the primary filament can be reduced to a line integral [8, Sec. 1-12, page 49]. In the present paper, we report an adaptation of this method to the case of two circular filaments and then derive a new analytical formula for calculating the mutual inductance between two circular filaments having any desired position with respect to each other as an alternative to the Grover and Babič expressions.

In particular, the obtained formula provides a solution for the singularity issue arising in the Grover and Babič formulas for the case when the planes of the primary and secondary circular filaments are mutually perpendicular. The efficiency and flexibility of the Kalantarov-Zeitlin method allow us to extend immediately the application of the obtained result to a case of the calculation of the mutual inductance between a primary circular filament and its projection on a tilted plane. For instance, this particular case appears in micro-machined inductive suspensions and has a direct practical application in studying their stability [25] and pull-in dynamics [27, 28]. The new analytical formulae were




Figure 1: General scheme of arbitrarily positioning two circular filaments with respect to each other: P is an arbitrary point on the secondary filament.

verified by comparison with series of reference examples covering all cases given by Grover[4], Kalantarov and Zeitlin [8], and using direct numerical calculations performed by the Babič Matlab function [2] and the *FastHenry* software [9].

2. Preliminary discussion

Two circular filaments having radii of R_p and R_s for the primary circular filament (the primary circle) and the secondary circular filament (the secondary circle), respectively are considered to be arbitrarily positioned in space, namely, they have a linear and angular misalignment, as is shown in Figure 1. Let us assign a coordinate frame (CF) denoted as XYZ to the primary circle in a such way that the Z axis is coincident with the circle axis and the XOY plane of the CF lies on the circle's plane, where the origin O corresponds to the centre of primary circle. In turn, the xyz CF is assigned to the secondary circle in a similar way so that its origin B is coincident with the centre of the secondary circle.

The linear position of the secondary circle with respect to the primary one is defined by the coordinates of the centre B (x_B, y_B, z_B). The angular position of the secondary circle can be defined in two ways. Firstly, the angular position is defined by the angle θ and η corresponding to the angular rotation around an axis passing through the diameter of the secondary circle, and then the rotation




Figure 2: Two manners for determining the angular position of the secondary circle with respect to the primary one: $x'y'z'$ is the auxiliary CF the axes of which are parallel to the axes of XYZ , respectively; $x''y''z''$ is the auxiliary CF defined in such a way that the x' and x'' are coincide, but the z'' and y'' axis is rotated by the α angle with respect to the z' and y' axis, respectively.

of this axis lying on the surface $x'By'$ around the vertical z' axis, respectively, as it is shown in Figure 2(a). These angles for determination of angular position of the secondary circle was proposed by Grover and used in his formula numbered by (179) in [4, page 207] addressing the general case for calculation of the mutual inductance between two circular filaments.

The same angular position can be determined through the α and β angle, which corresponds to the angular rotation around the x' axis and then around the y'' axis, respectively, as it is shown in Figure 2(b). This additional second manner is more convenient in a case of study dynamics and stability issues, for instance, applying to axially symmetric inductive levitation systems [23, 25] in compared with the Grover manner. These two pairs of angles have the following relationship with respect to each other such as:

$$\begin{cases} \sin \beta = \sin \eta \sin \theta; \\ \cos \beta \sin \alpha = \cos \eta \sin \theta. \end{cases} \quad (1)$$

The details of the derivation of this set presented above are shown in Appendix A.




Figure 3: The Kalantarov-Zeitlin method: $s = \sqrt{x_B^2 + y_B^2}$ is the distance to the centre B on the XOY plane.

3. The Kalantarov-Zeitlin method

Using the general scheme for two circular filaments shown in Figure 1 as an illustrative one, the Kalantarov-Zeitlin method is presented. The method reduces the calculation of mutual inductance between a circular primary filament and any other secondary filament having an arbitrary shape and any desired position with respect to the primary circular filament to a line integral [8, Sec. 1-12, page 49].

Indeed, let us choose an arbitrary point P of the secondary filament (as it has been mentioned above the filament can have any shape), as shown in Figure 1. An element of length $d\ell''$ of the secondary filament at the point P is considered. Also, the point P is connected the point Q lying on the Z axis by a line, which is perpendicular to the Z axis and has a length of ρ , as shown in Figure 3. Then the element $d\ell''$ can be decomposed on dz along the Z axis and on $d\rho$ along the ρ line and $d\lambda$ along the λ -circle having radius of ρ (see, Figure 4). It is obvious that the mutual inductance between dz and the primary circular filament is equal to zero because dz is perpendicular to a plane of primary circle. But the mutual inductance between $d\rho$ and the primary circular filament is also equal to zero because of the symmetry of the primary circle relative to the $d\rho$ direction.

Thus, the mutual inductance dM between element $d\ell''$ and the primary circle




Figure 4: The Kalantarov-Zeitlin method: projection of the secondary filament on the ρ -plane passed through the point P and parallel to the plane of the primary circular filament; $d\ell$ is the projection of the element $d\ell''$ on the ρ -plane.

is equal to the mutual inductance dM_λ between element $d\lambda$ and the primary circle. Moreover, due to the fact that the primary and the λ -circle are coaxial and, consequently, symmetric then we can write:

$$\frac{dM_\lambda}{M_\lambda} = \frac{d\lambda}{\lambda} = \frac{d\lambda}{2\pi\rho}, \quad (2)$$

where M_λ is the mutual inductance of the primary **coil** and λ -circle.

From Figure 4, it is directly seen that

$$d\lambda = dy \cos \varphi - dx \sin \varphi = (\cos \zeta \cos \varphi - \cos \varepsilon \sin \varphi) d\ell, \quad (3)$$

where $\cos \varepsilon$ and $\cos \zeta$ are the direction cosines of element $d\ell$ relative to the X and Y axis, respectively. Hence, accounting for (2) and (3), we can write:

$$dM = dM_\lambda = M_\lambda \frac{\cos \zeta \cos \varphi - \cos \varepsilon \sin \varphi}{2\pi\rho} d\ell, \quad (4)$$

and as a result, a line integral for calculation mutual inductance between the primary circle and a filament is

$$M = \frac{1}{2\pi} \int_\ell M_\lambda \frac{\cos \zeta \cos \varphi - \cos \varepsilon \sin \varphi}{\rho} d\ell, \quad (5)$$

where M_λ is defined by the Maxwell formula for mutual inductance between two coaxial circles [37, page 340, Art. 701]. Note that during integrating, the Z




Figure 5: Determination of the position of the point P on the ρ -plane through the fixed parameter s and the distance r .

coordinate of the element $d\ell$ is also changing and this dependency is taken into account by the M_λ function directly.

4. Derivation of Formulas

Due to the particular geometry of secondary filament under consideration, its projection on the ρ -plane (the ρ -plane is parallel to the primary circle plane and passed through the point P) is an ellipse, which can be defined in a polar coordinate by a function $r = r(\varphi)$ with the origin at the point B as it is shown in Figure 5. Hence, the distance ρ can be expressed in terms of the parameter s , which is fixed, and the distance r from the origin B , which is varied with




Figure 6: The relationship between $d\lambda$ and $d\varphi$.

the angular variable φ . Introducing the angle γ as shown in Figure 6, for the distance ρ the following equations can be written:

$$\begin{aligned}\rho \cos \gamma &= r + s \cos(\xi - \varphi), \\ \rho \sin \gamma &= s \sin(\xi - \varphi).\end{aligned}\tag{6}$$

Due to (6), we have:

$$\rho^2 = r^2 + r \cdot s \cos(\xi - \varphi) + s^2,\tag{7}$$

where the function $r = r(\varphi)$ can be defined as [40]:

$$r = \frac{R_s \cos \theta}{\sqrt{\sin^2(\varphi - \eta) + \cos^2 \theta \cos^2(\varphi - \eta)}}.\tag{8}$$

The angle θ and η defines the angular position of the secondary circle with respect to the primary one according to manner I considered in Sec. 2. Note that the function r can be also defined via the angles α and β of manner II also considered in Sec. 2 as it is shown in Appendix B. However, for the further derivation, the angular position of the secondary circle is defined through manner I, since it is convenient for the direct comparison with Grover's and Babič' results.

According to Figure 6, the relationship between the element $d\lambda$ of the λ -circle and an increment of the angle φ is as follows:

$$d\lambda = r \cdot d\varphi \cos \gamma - dr \sin \gamma = \left(r \cos \gamma - \frac{dr}{d\varphi} \sin \gamma \right) d\varphi.\tag{9}$$

Then, accounting for (9), (7) and (6), line integral (5) can be replaced by a definite integral for the calculation of mutual inductance as follows:

$$M = \frac{1}{2\pi} \int_0^{2\pi} M_\lambda \frac{r^2 + r \cdot s \cos(\xi - \varphi) - \frac{dr}{d\varphi} s \sin(\xi - \varphi)}{\rho^2} d\varphi.\tag{10}$$

Now, let us introduce the following dimensionless parameters such as:

$$\begin{aligned}\bar{x}_B &= \frac{x_B}{R_s}; \bar{y}_B = \frac{y_B}{R_s}; \bar{z}_B = \frac{z_B}{R_s}; \bar{r} = \frac{r}{R_s}; \\ \bar{\rho} &= \frac{\rho}{R_s}; \bar{s} = \sqrt{\bar{x}_B^2 + \bar{y}_B^2}.\end{aligned}\tag{11}$$




Figure 7: The special case: the two filament circles are mutually perpendicular to each other.

The φ -derivative of \bar{r} is

$$\frac{d\bar{r}}{d\varphi} = \frac{1}{2}\bar{r}^3 \tan^2 \theta \sin(2(\varphi - \eta)), \quad (12)$$

The mutual inductance M_λ is

$$M_\lambda = \mu_0 \frac{2}{k} \Psi(k) \sqrt{R_p R_s \bar{\rho}}, \quad (13)$$

where μ_0 is the magnetic permeability of free space, and

$$\Psi(k) = \left(1 - \frac{k^2}{2}\right) K(k) - E(k), \quad (14)$$

where $K(k)$ and $E(k)$ are the complete elliptic functions of the first and second kind, respectively, and

$$k^2 = \frac{4\nu\bar{\rho}}{(\nu\bar{\rho} + 1)^2 + \nu^2\bar{z}_\lambda^2}, \quad (15)$$

where $\nu = R_s/R_p$ and $\bar{z}_\lambda = \bar{z}_B + \bar{r} \tan \theta \sin(\varphi - \eta)$. Accounting for dimensionless parameters (11) and substituting (12) and (14) into integral (10), the new formula to calculate the mutual inductance between two circular filaments having any desired position with respect to each other becomes

$$M = \frac{\mu_0 \sqrt{R_p R_s}}{\pi} \int_0^{2\pi} \frac{\bar{r} + t_1 \cdot \cos \varphi + t_2 \cdot \sin \varphi}{k\bar{\rho}^{1.5}} \cdot \bar{r} \cdot \Psi(k) d\varphi, \quad (16)$$

where terms t_1 and t_2 are defined as

$$\begin{aligned} t_1 &= \bar{x}_B + 0.5\bar{r}^2 \tan^2 \theta \sin(2(\varphi - \eta)) \cdot \bar{y}_B; \\ t_2 &= \bar{y}_B - 0.5\bar{r}^2 \tan^2 \theta \sin(2(\varphi - \eta)) \cdot \bar{x}_B, \end{aligned} \quad (17)$$

and $\bar{\rho} = \sqrt{\bar{r}^2 + 2\bar{r} \cdot \bar{s} \cos(\xi - \varphi) + \bar{s}^2}$.

Formula (16) can be applied to any possible cases, but one is excluded when the two filament circles are mutually perpendicular to each other. In this case the projection of the secondary circle onto the ρ -plane becomes simply a line as it is shown in Fig. 7 and as a result to integrate with respect to φ is no longer possible.

For the treatment of this case, the Kalantarov-Zeitlin formula (5) is directly used. Let us introduce the dimensionless variable $\bar{\ell} = \ell/R_s$ and then the integration of (5) is performed with respect to this dimensionless variable $\bar{\ell}$ within interval $-1 \leq \bar{\ell} \leq 1$. The direction cosines $\cos \zeta$ and $\cos \varepsilon$ become as $\sin \eta$ and $\cos \eta$, respectively (see, Fig. 7). Accounting for

$$\begin{aligned} \rho \cos \varphi &= s \cos \xi + \ell \cos \eta, \\ \rho \sin \varphi &= s \sin \xi + \ell \sin \eta, \end{aligned} \quad (18)$$

and the Maxwell formula (14) and (15), where the Z -coordinate of the element $d\bar{\ell}$ is defined as

$$\bar{z}_\lambda = \bar{z}_B \pm \sqrt{1 - \bar{\ell}^2}, \quad (19)$$

then the formula to calculate the mutual inductance between two filament circles, which are mutually perpendicular to each other, becomes as follows:

$$\begin{aligned} M &= \frac{\mu_0 \sqrt{R_p R_s}}{\pi} \left[\int_{-1}^1 \frac{t_1 - t_2}{k \bar{\rho}^{1.5}} \cdot \Psi(k) d\bar{\ell} \right. \\ &\quad \left. + \int_1^{-1} \frac{t_1 - t_2}{k \bar{\rho}^{1.5}} \cdot \Psi(k) d\bar{\ell} \right], \end{aligned} \quad (20)$$

where terms t_1 and t_2 are defined as

$$\begin{aligned} t_1 &= \sin \eta (\bar{x}_B + \bar{\ell} \cos \eta); \\ t_2 &= \cos \eta (\bar{y}_B + \bar{\ell} \sin \eta), \end{aligned} \quad (21)$$

and $\bar{\rho} = \sqrt{\bar{s}^2 + 2\bar{\ell} \cdot \bar{s} \cos(\xi - \eta) + \bar{\ell}^2}$. Note that integrating (20) between -1 and 1 equation (19) is calculated with the positive sign and for the other direction the negative sign is taken.

In order to demonstrate the efficiency and flexibility of the Kalantarov-Zeitlin method, a formula for the calculation of the mutual inductance between the primary circular filament and its projection on a tilted plane is obtained as follows. In this case, the function of $r = r(\varphi)$ is constant and defined through the radius of primary coil as $r = R_p$. Since the centre of the projection is coincide with the Z -axis, thus $s = 0$. Then, the formula is derived from (16) as its particular case ($\bar{s} = 0$ and $\bar{r} = \bar{\rho} = 1$) and becomes, simply,

$$M = \frac{\mu_0 R_p}{\pi} \int_0^{2\pi} \frac{1}{k} \cdot \Psi(k) d\varphi. \quad (22)$$

The obtained formulas can be easily programmed, they are intuitively understandable for application. Also, the singularity arises in Grover's and Babič's formula for the calculate of the mutual inductance between two filament circles, which are mutually perpendicular to each other, is solved in developed formula (20). The *Matlab* files with the implemented formulas (16), (20) and (22) are available from the authors as supplementary materials to this article. Also, in Appendix B the the developed formulas can be rewritten through the pair of the angle α and β .

5. Examples of Calculation. Numerical Verification

In this section, developed new formulas (16), (20) and (22) are verified by the examples taken from Grover [4] and Kalantarov [8] books and Babič article [2]. The special attention was addressed to the singularity case arisen when the two filament circles are mutually perpendicular to each other. Then, formula (22) was validated with the *FastHenry* software [9]. All calculations for considered cases proved the robustness and efficiency of developed formulas.

Note that the notation proposed in Grover's and Kalantarov's books in order to define the linear misalignment of the secondary coil is different from the




Figure 8: Geometrical scheme of coaxial circular filaments denoted via Grover's notation: radii a and A of secondary and primary coils, respectively; d is the distance between the planes of circles.

notation used in the Babič article and in our article as well. Also, the angular misalignment in the Babič formula must be defined through the parameters of the secondary coil plane. These particularities of the notation will be discussed specifically for each case. For all calculation, the primary coil is located on the plane XOY and its centre at the origin $O(0,0,0)$.

5.1. Mutual inductance of coaxial circular filaments

Let us consider the circular filaments, which are coaxial and have a distance between their centres, as shown in Fig. 8. Then, this case in the notation proposed in this article is defined as $R_p = A$, $R_s = a$, the linear misalignment is $z_B = d$, $x_B = y_B = 0$, the angular misalignment (manner I, Sec. 2) is $\theta = 0$ and $\eta = 0$. For the Babič formula the linear misalignment is defined in the same way, but for angular one the parameters of the secondary circle plane must be calculated and becomes $a = 0$, $b = 0$ and $c = 1$ (the Babič notation). These parameters have the following relationship with the angle θ and η : $a = \sin \eta \sin \theta$; $b = -\cos \eta \sin \theta$ and $c = \cos \theta$ [2, Eq. (27), page 3597].

Example 1 (Example 24, page 78 in Grover's book [4])

Let us suppose that two circles of radii $a=20$ cm and $A=25$ cm with their planes $d=10$ cm apart are given. The results of calculation are

	Grover's book	The Babič formula	This work, Eq. (16)
$M, \text{ nH}$	248.79	248.7874	248.7874

Example 2 (Example 25, page 78 in Grover's book [4])

Two circles of radii $a=2$ in= 5.08 cm and $A=5$ in=12.7 cm with their planes $d=4$ in=10.16 cm apart, the results become

	Grover's book	The Babič formula	This work, Eq. (16)
$M, \text{ nH}$	18.38	18.3811	18.3811

Example 3 (Example 5-4, page 215 in Kalantarov's book [8])

For two circles having the same radii of 10.00 cm with their planes $d=4$ cm apart, the calculation shows the following

	Kalantarov's book	The Babič formula	This work, Eq. (16)
$M, \text{ nH}$	135.1	135.0739	135.0739

Example 4 (Example 5-5, page 215 in Kalantarov's book [8])

Circles having the same radii as in *Example 3*, but their planes $d=50$ cm apart are given. The results are

	Kalantarov's book	The Babič formula	This work, Eq. (16)
$M, \text{ nH}$	1.41	1.4106	1.4106




Figure 9: Geometrical scheme of circular filaments with parallel axes denoted via Grover's notation: ρ is the distance between axes; r is the distance between the centres; φ is the angle between the Z -axis and the radius vector r .

Example 5 (Example 5-6, page 224 in Kalantarov's book [8])

Two circular coaxial filaments, radii of which are $A=25$ cm and $a=20$ cm, with their planes $d=8$ cm apart are given. The results are as follows

	Kalantarov's book	The Babič formula	This work, Eq. (16)
M , nH	289.11	289.0404	289.0404

5.2. Mutual inductance of circular filaments with parallel axes

The scheme for calculation of the mutual inductance between circular filaments with parallel axes is shown in Fig. 9. The linear misalignment in the Grover notation can be defined by d is the distance between the planes of circles (the same parameter as in Sec. 5.1) and ρ is the distance between axes or via r is the distance between the centres and φ is the angle between the Z -axis and the radius vector r . These parameters have the following relationship to the notation defined in this article, namely, $z_B = d = r \cos \varphi$ and $\rho = \sqrt{x_B^2 + y_B^2} = r \sin \varphi$. The angular misalignment is defined in the same way as described in Sec. 5.1).

Example 6 (Example 62, page 178 in Grover's book [4])

Two circles of radii $a = A = 15$ cm have a distance between their centres $r = 20$ cm and an angle $\varphi = \cos^{-1} 0.8$ between the Z -axis and the radius vector

r (please, see Fig. 9). Assuming that $y_B = \rho = r \sin \varphi = 12$ cm and $z_B = r \cos \varphi = 16$ cm, the results of calculation are as follows

	Grover's book	The Babič formula	This work, Eq. (16)
M , nH	45.31	45.3342	45.3342

Example 7 (Example 63, page 178 in Grover's book [4])

Two circles of the same diameter of $2a = 2A = 48$ in = 121.92 cm are arranged so that the distance between their planes $d = 15$ in = 38.1 cm and the distance between their axes is $\rho = 47.7$ in = 121.158 cm (please, see Fig. 9). Thus, we have $R_p = R_s = 60.96$ cm, $y_B = \rho$ and $z_B = d$, the results of calculation are as follows

	Grover's book	The Babič formula	This work, Eq. (16)
M , nH	-24.56	-24.5728	-24.5728

Example 8 (Example 65, page 183 in Grover's book [4])

Two circles with radii of $A = 10$ cm and $a = 8$ cm have the distance between their centres $r = 50$ cm and an angle of $\cos \varphi = 0.4$ (please, see Fig. 9). Hence, we have $R_p = A$ and $R_s = a$, assuming that $y_B = r \sin \varphi = 45.83$ cm and $z_B = r \cos \varphi = 20.0$ cm, the results of calculation are as follows

	Grover's book	The Babič formula	This work, Eq. (16)
M , nH	-0.2480	-0.24828	-0.24828

Example 9 (Example 66, page 184 in Grover's book [4])

Two circles with radii of $A = 10$ cm and $a = 8$ cm have the distance between their centres $r = 20$ cm and an angle of $\cos \varphi = 0.6$ (please, see Fig. 9), to find the mutual inductance between these circles. Hence, we have $R_p = A$ and

$R_s = a$, assuming that $y_B = r \sin \varphi = 16.0$ cm and $z_B = r \cos \varphi = 12.0$ cm, the results of calculation are as follows

	Grover's book	The Babič formula	This work, Eq. (16)
M , nH	4.405	4.465	4.465

Example 10 (Example 5-8, page 231 in Kalantarov's book [8])

Two circular filaments of the same radius of $A = a = 5$ cm are arranged that the distance between their centres is $r = 40$ cm and an angle of $\cos \varphi = 0.4$. Hence, we have $R_p = R_s = 5$ cm, assuming that $y_B = r \sin \varphi = 36.66$ cm and $z_B = r \cos \varphi = 16.0$ cm, the results are as follows

	Kalantarov's book	The Babič formula	This work, Eq. (16)
M , nH	-0.049	-0.048963	-0.048963

Example 11 (Example 5-9, page 233 in Kalantarov's book [8])

Two circular filaments of radii of $A = 10$ cm and $a = 5$ cm are arranged that the distance between their centres is $r = 20$ cm and an angle of $\cos \varphi = 0.8$. Hence, we have $R_p = 10$ cm and $R_s = 5$ cm, assuming that $y_B = r \sin \varphi = 36.66$ cm and $z_B = r \cos \varphi = 16.0$ cm, the results are as follows

	Kalantarov's book	The Babič formula	This work, Eq. (16)
M , nH	2.95	3.0672	3.0672

Example 12 (Example 5-10, page 234 in Kalantarov's book [8])

Two circular filaments of radii of $A = 20$ cm and $a = 4$ cm are arranged that the distance between their centres is $r = 2$ cm and an angle of $\cos \varphi = 0.66$. Hence, we have $R_p = 20$ cm and $R_s = 4$ cm, assuming that $y_B = r \sin \varphi = 1.5$ cm




Figure 10: Geometrical scheme of inclined circular filaments with intersect axes denoted via Grover's notation: x_1 and x_2 are the distances from S , θ is the angle of inclination of the axes.

and $z_B = r \cos \varphi = 1.32$ cm, the results become as follows

	Kalantarov's book	The Babič formula	This work, Eq. (16)
M , nH	15.99	15.9936	15.9936

5.3. Mutual inductance of inclined circular filaments with intersect axes

The general scheme of the arrangement of two inclined circular filaments whose axes intersect for calculation of mutual inductance is shown in Fig. 10. In Grover's notation, we have A and a are radii of circular filaments and S is the point of intersection of the circles axes. The centres of circles are at the distances x_1 and x_2 from S of the primary and secondary circle, respectively. θ is the angle of inclination of the axes. Also, the following relationships are true, namely, $d = x_1 - x_2 \cos \theta$ and $\rho = x_2 \sin \theta$. Thus, the linear misalignment in the notation of this paper is defined again through $z_B = d$, $\rho = \sqrt{x_B^2 + y_B^2}$ and the angular misalignment is defined by the angle θ , but η is equal to zero. For the Babič formula, the angular misalignment is defined by the parameters of the secondary circle plane as follows: $a = 0$; $b = -\sin \theta$ and $c = \cos \theta$.

From the general scheme shown in Fig. 10, two particular cases can be recognized. Namely, the first case is corresponded to concentric circles, when $x_1 = x_2 = 0$ and the second case is corresponded to circular filaments whose

axes intersect at the centre of one of the circle, when $x_2 = 0$. For the first case, to calculate the mutual inductance, the angle θ and radii of circles must be known. For the second particular case, in addition to the distance d between the centre B of the secondary circle and the plane of the primary circle must be given.

Example 13 (Example 5-7, page 227 in Kalantarov's book [8])

Two circular filaments of radii of $A = 10$ cm and $a = 2.5$ cm are concentric and an angle of inclination of the plane of the secondary circle is $\theta = 60^\circ$. Hence, assuming that $x_B = y_B = z_B = 0$, the calculation of mutual inductance shows

	Kalantarov's book	The Babič formula	This work, Eq. (16)
M , nH	6.044	6.0431	6.0431

Example 14 (Example 69, page 194 in Grover's book [4])

Two concentric circles with radii of $A = 20$ cm and $a = 14$ cm are arranged that an angle of inclination of the plane of the secondary circle is $\cos \theta = 0.3$. Hence, assuming that $x_B = y_B = z_B = 0$ and $\theta = 72.5424^\circ$, the results of calculation are as follows

	Grover's book	The Babič formula	This work, Eq. (16)
M , nH	47.44	47.4431	47.4431

Example 15 (Example 70, page 194 in Grover's book [4])

Two circles with radii of $A = 10$ in = 25.4 cm and $a = 3$ in = 7.62 cm are arranged that an angle of inclination of the plane of the secondary circle is $\cos \theta = 0.4$ and a distance $d = 3$ in = 7.62 cm. Hence, assuming that $x_B = y_B = 0$,

$z_B = d$ and $\theta = 66.4218^\circ$, the results of calculation are as follows

	Grover's book	The Babič formula	This work, Eq. (16)
$M, \text{ nH}$	15.543	15.5435	15.5435

Example 16 (Example 71, page 201 in Grover's book [4])

Two circles of radii $A = 20.0$ cm and $a = 10.0$ cm are considered with the centre of one on the axis of the other and a distance, d , of 20.0 cm between the centres. The axes are to be inclined at an angle, θ , of 30° . The results of calculation show

	Grover's book	The Babič formula	This work, Eq. (16)
$M, \text{ nH}$	29.436	29.4365	29.4365

Example 17 (Example 5-11, page 235 in Kalantarov's book [8])

Two circular filaments have radii of $A = 10$ cm and $a = 8$ cm. The axis the primary circle is crossed through the centre of the secondary circle at a distance d of 8 cm between their centres. The axes are to be inclined at an angle, $\cos \theta = 0.7$. Hence, assuming that $x_B = y_B = 0$, $z_B = d$ and an angle of 45.5730° , the results of calculation are

	Kalantarov's book	The Babič formula	This work, Eq. (16)
$M, \text{ nH}$	23.2	24.3794	24.3794

Example 18 (Example 73, page 204 in Grover's book [4])

Two circles of radii $A = 16.0$ cm and $a = 10.0$ cm are considered to be intersect the axes at point S in such a way that distances x_1 and x_2 are to be 20.0 cm and 5.0 cm, respectively. An angle of inclination between axes is $\cos \theta = 0.5$. Hence,

assuming that $x_B = 0$, $y_B = 4.3301$ cm, $z_B = 17.5$ cm and an angle of 60.0° , we have

	Grover's book	The Babič formula	This work, Eq. (16)
M , nH	13.612	13.6113	13.6113

Table 1: Calculation of mutual inductance for Example 19

η	The Grover formula, [4, Eq. (179)] M , nH	The Babič formula, [2, Eq. (24)] M , nH	This work, Eq. (16) M , nH
0	13.6113	13.6113	13.6113
$\pi/6$	14.4688	14.4688	14.4688
$\pi/4$	15.4877	15.4877	15.4877
$\pi/4$	16.8189	16.8189	16.819
$\pi/2$	20.0534	20.0534	20.0534
$2\pi/3$	23.3252	23.3252	23.3252
$3\pi/4$	24.6936	24.6936	24.6936
$5\pi/6$	25.7493	25.7493	25.7493
π	26.6433	26.6433	26.6433
$7\pi/6$	25.7493	25.7493	25.7493
$5\pi/4$	24.6936	24.6936	24.6936
$4\pi/3$	23.3253	23.3253	23.3252
$3\pi/2$	20.0534	20.0534	20.0534
$5\pi/3$	16.8189	16.8189	16.819
$7\pi/4$	15.4877	15.4877	15.4877
$11\pi/6$	14.4688	14.4688	14.4688
2π	13.6113	13.6113	13.6113

5.4. *Mutual inductance of circular filaments arbitrarily positioned in the space*

The validation of the developed formulas (16) and (20) for the general case, when the angular misalignment is defined through the angle θ and η as shown in Fig. 2(a) in an range from 0 to 360°, the examples from the Babič article [2] were used. Also, we utilized the Matlab functions with the Grover formula [4, page 207, Eq. (179)] and the Babič formula [2, page 3593, Eq. (24)] implemented by F. Sirois and S. Babič.

Example 19 (Example 12, page 3597 in the Babič article [2])

Using the geometrical arrangement as in Example 18 (two circles with radii $A = 16.0$ cm and $a = 10.0$ cm and the centre of the secondary circle is located at $x_B = 0$, $y_B = 4.3301$ cm, $z_B = 17.5$ cm and the angle, θ of 60.0°), but the angle η is varied in a range from 0 to 360°. The results of calculation are summed up in Table 1. Analysis of Table 1 shows that the developed formula (16) works identically to the Grover and Babič formula.

Example 20 (Example 11, page 3596 in the Babič article [2])

Let us consider two circular filaments having radii of $R_p = 40$ cm and $R_s = 10$ cm, which are mutually perpendicular to each other that angles of $\eta = 0$ and $\theta = 90.0^\circ$. The centre of the secondary circle has the following coordinates: $x_B = 0$, $y_B = 20$ cm, and $z_B = 10$ cm. The problem illustrates the application of new formula (20). The results are

	The Grover formula	The Babič formula	This work, Eq. (20)
M , nH	-10.73	-10.73	-10.7272

Example 21

Now we again apply formula (20) to the problem considered in Example 20, but in this case the centre of the secondary coil is located at origin, thus




Figure 11: Distribution of the error of the Babič formula in dependent on changing the η -angle within a range $0 < \eta \leq 360^\circ$ for Example 21 ($x_B = y_B = z_B = 0$).

$x_B = y_B = z_B = 0$. Hence, we have

	The Grover formula	The Babič formula	This work, Eq. (20)
M , nH	NaN^1	NaN	0

Thus, the calculation shows that the Babič and Grover formula gives an indeterminate results, but developed formula (20) equals explicitly zero as expected for this case. Then, rotating the angle η in a range $0 < \eta \leq 360^\circ$, we reveal that the calculation of mutual inductance performed by developed formula (20) shows zero within this range of the η -angle, but the Babič formula demonstrates a small error, which is not exceeded $M = 2.9205 \times 10^{-15}$ nH and distributed with the η -angle as shown in Figure 11.

Example 22

Let us consider mutually perpendicular circles (angles of $\theta = 90.0^\circ$ and $\eta = 0$) having the same radii as in Example 20, but the centre of the secondary coil occupies a position on the XOY -surface with the following coordinates $x_B =$

¹Not-a-Number




Figure 12: Chaotic distribution of the error of the Babič formula in dependent on changing the η -angle within a range $0 < \eta \leq 360^\circ$ for Example 22 ($x_B = y_B = 10$ cm and $z_B = 0$): the scaled-up images show the interruption of continuity of the curve at $\eta = 90^\circ$ and 270° .




Figure 13: Geometrical scheme for calculation of mutual inductance between a primary circular filament and its projection. The angular misalignment is given by an angle of θ , while the linear misalignment by the coordinate z_B .

$y_B = 10$ cm and $z_B = 0$. Results of calculation are

	The Grover formula	The Babič formula	This work, Eq. (20)
M , nH	4.013×10^{-15}	2.416×10^{-15}	0

Thus, the calculation expresses that the Babič and Grover formula gives the small errors, but developed formula (20) shows, explicitly, zero. Then, again let us rotate the angle η in a range $0 < \eta \leq 360^\circ$, the calculation of mutual

Table 2: Calculation of mutual inductance for Example 23

θ	This work, Eq. (22) M , nH	<i>FastHenry</i> [9] M , nH
0	135.0739	135.076
10°	142.0736	142.086
15°	153.3233	153.298

inductance performed by developed formula (20) reveals zero within this range of the η -angle, but the Babič formula demonstrates the chaotic distribution of the small error of calculation as shown in Fig. 12, which is in a range from -0.7×10^{-14} to 2.921×10^{-14} nH and at the η -angle of 90° and 270° the calculation of mutual inductance is indeterminate (see, the scaled-up images of Fig. 12, which present the interruption of continuity at $\eta = 90^\circ$ and 270°).

5.5. Mutual inductance between a primary circular filament and its projection on a tilted plane

In this section new formula (22) for calculation of mutual inductance between a primary circular filament and its projection on a tilted plane is validated by comparison with the calculation performed via the *FastHenry* software [9]. The angular misalignment is given by the angle θ and η , while the linear misalignment is defined by the coordinate z_B of the point B crossing the tilted plane and the Z -axis. Fig. 13 shows a geometrical scheme for the calculation. The shown arrangement of the primary circle and its projection on the tilted plane corresponds to a particular case, when $\eta = 0$. Worth noting that the η -angle has no effect on the result of the calculation of the mutual inductance.

Example 23

Let us consider primary circle having a radius of 10.00 cm and a tilting plane crosses the Z -axis at the point $z_B=4$ cm. When a tilting angle of zero, then the geometry and arrangement corresponds to Example 3 (Example 5-4, page 215

in Kalantarov’s book) for the case of two coaxial circles with the same radii. We calculate the mutual inductance for three values of a tilted angle at 0 , 10° and 15° . The results of calculation are shown in Table 2.

Although, there is the small deviation between results obtained with the *FastHenry* software and analytical formula (22), but this deviation is not significant and can be explained by the fact that the circles in the *FastHenry* software are divided into straight segments with a finite cross section in comparing with the analytical formula where the circles have no segments and a cross section. We are concluding the validity of developed formula (22).

Table 3: Calculation of mutual inductance for Example 24

θ	This work, Eq. (22) M , nH	<i>FastHenry</i> [9] M , nH
0	1.4106	1.3761
5°	1.4117	1.3844
10°	1.4151	1.3933
15°	1.421	1.4031
20°	1.4298	1.4120
25°	1.4422	1.4202
30°	1.4594	1.4268
35°	1.4831	1.4336
40°	1.5161	1.4574
45°	1.5631	1.5230
50°	1.6329	1.6180
55°	1.7425	1.7273
60°	1.9299	1.8765
65°	2.2971	2.2416
70°	3.2127	3.1806
75°	7.1274	7.1679

Example 24

In this last example, we increase a distance between the centre of the primary circle with a radius of 10.00 cm and a tilting plane to $z_B=50$ cm. Hence, a range of the tilted angle becomes larger then in example 23. Note that for zero tilting angle the geometry of the considered problem corresponds to example 4 (Example 5-5, page 215 in Kalantarov's book). The results of calculation are shown in Table 3. Analysis of Table 3 shows a good agreement between the calculations, which confirms the validity of developed formula (22).

6. Conclusion

We derived and validated new formulas (16) and (20) for calculation of the mutual inductance between two circular filaments arbitrarily oriented with respect to each other. These analytic formulas have been developed based on the Kalantarov-Zeitlin method, which showed that the calculation of mutual inductance between a circular primary filament and any other secondary filament having an arbitrary shape and any desired position with respect to the primary filament is reduced to a line integral. In particular, the developed formula (20) provides a solution for the singularity issue arising in Grover's and Babič' formulas for the case when the planes of the primary and secondary circular filaments are mutually perpendicular.

Moreover, a curious reader can already recognize that formula (20) can be applied for calculation of the mutual inductance between the circular filament and a line, position of which with respect to the circle is defined through the linear and angular misalignment. For this reason, in Eq. (19) we assume that $\bar{z}_\lambda = \bar{z}_B$ and formula (20) is integrated only from -1 to 1 . This fact proves again the efficiency and flexibility of the Kalantarov-Zeitlin method.

The advantages of the Kalantarov-Zeitlin method allow us to extend immediately the application of the obtained result to a case of the calculation of the mutual inductance between a primary circular filament and its projection on a tilted plane and to furnish this case via formula (22). For instance, this par-

particular case appears in micro-machined inductive suspensions and has a direct practical application in studying their stability and pull-in dynamics.

New developed formulas have been successfully validated through a number of examples available in the literature. Also, the direct comparison the results of calculation with the numerical results obtained by utilizing the *FastHenry* software shows a good agreement. Besides, the obtained formulas can be easily programmed, they are intuitively understandable for application.

Acknowledgment

Kirill Poletkin acknowledges with thanks to Prof. Ulrike Wallrabe for the continued support of his research. Also, Kirill Poletkin acknowledges with thanks the support from German Research Foundation (Grant KO 1883/26-1).




Figure .14: The relationship between the angles of two manners for determining angular misalignment of the secondary circle: I and II are denoted for two spherical triangles highlighted by arcs in red color.

Appendix A. Determination of angular position of the secondary circular filament

The angular position of the secondary circle can be defined through the pair of angle θ and η corresponding to manner I and the angle α and β manner II. The relationship between two pairs of angles can be determined via two spherical triangles denoted in Roman number I and II as shown in Fig. .14. According to the law of sines, for spherical triangle I we can write the following relationship:

$$\frac{\sin \eta}{\sin \pi/2} = \frac{\sin \beta}{\sin \theta}. \quad (\text{A.1})$$

For spherical triangle II, we have

$$\frac{\sin(\pi/2 - \eta)}{\sin(\pi/2 - \beta)} = \frac{\sin \alpha}{\sin \theta}. \quad (\text{A.2})$$

Accounting for (A.1) and (A.2), the final set determining the relationship between two pairs of angles becomes as

$$\begin{cases} \sin \beta = \sin \eta \sin \theta; \\ \cos \beta \sin \alpha = \cos \eta \sin \theta. \end{cases} \quad (\text{A.3})$$

Appendix B. Presentation of developed formulas via the pair of angles α and β

Using set (A.3), we can write the following equations:

$$\begin{cases} \cos^2 \theta = \cos^2 \beta (1 + \sin^2 \alpha); \\ \sin^2 \theta = \sin^2 \beta + \cos^2 \beta \sin^2 \alpha; \\ \tan^2 \theta = \frac{\sin^2 \beta + \cos^2 \beta \sin^2 \alpha}{\cos^2 \beta (1 + \sin^2 \alpha)}; \\ \cos^2 \eta = \cos^2 \beta \sin^2 \alpha / \sin^2 \theta; \\ \sin^2 \eta = \sin^2 \beta / \sin^2 \theta. \end{cases} \quad (\text{B.1})$$

Now, applying set (B.1) to (8), the square of the dimensionless function \bar{r} becomes as

$$\bar{r}^2 = \frac{\cos^2 \beta (1 + \sin^2 \alpha) (\sin^2 \beta + \cos^2 \beta \sin^2 \alpha)}{(\sin \varphi \cos \beta \sin \alpha - \cos \varphi \sin \beta)^2 + \cos^2 \beta (1 + \sin^2 \alpha) (\cos \varphi \cos \beta \sin \alpha + \sin \varphi \sin \beta)^2}. \quad (\text{B.2})$$

Then, for the dimensionless parameter \bar{z}_λ , we have

$$\bar{z}_\lambda = \bar{z}_B + \bar{r} \frac{\sin \varphi \cos \beta \sin \alpha - \cos \varphi \sin \beta}{\sqrt{\cos^2 \beta (1 + \sin^2 \alpha)}}. \quad (\text{B.3})$$

Substituting (B.2), (B.3) and

$$\begin{aligned} t_1 &= \bar{x}_B + \bar{y}_B \cdot \bar{r}^2 \frac{\sin^2 \beta + \cos^2 \beta \sin^2 \alpha}{\cos^2 \beta (1 + \sin^2 \alpha)} \times \\ &\quad (\sin \varphi \cos \beta \sin \alpha - \cos \varphi \sin \beta) \times \\ &\quad (\cos \varphi \cos \beta \sin \alpha + \sin \varphi \sin \beta); \\ t_2 &= \bar{y}_B - \bar{x}_B \cdot \bar{r}^2 \frac{\sin^2 \beta + \cos^2 \beta \sin^2 \alpha}{\cos^2 \beta (1 + \sin^2 \alpha)} \times \\ &\quad (\sin \varphi \cos \beta \sin \alpha - \cos \varphi \sin \beta) \times \\ &\quad (\cos \varphi \cos \beta \sin \alpha + \sin \varphi \sin \beta), \end{aligned} \quad (\text{B.4})$$

into Eq. (16), the angular misalignment of the secondary circle are defined through the pair of angle α and β corresponding to the manner II.

For the case when the two circles are mutually perpendicular to each other, assuming that $\alpha = \pi/2$ then just replacing the angle η by β in formula (20), it can be used for calculation with new pair of angle α and β .

Since formula (22) is a particular case of (16), when $\bar{s} = 0$ and $\bar{r} = \bar{\rho} = 1$. Hence, substituting $\bar{r} = 1$ into (B.3) and using this modified equation for formula (22), it can be used for calculation of mutual inductance between the primary circle and its projection on a tilted plane, an angular position of which is defined by the pair of angle α and β .

References

References

- [1] F. W. Grover, The calculation of the mutual inductance of circular filaments in any desired positions, Proceedings of the IRE 32 (10) (1944) 620–629. doi:10.1109/JRPROC.1944.233364.
- [2] S. Babic, F. Sirois, C. Akyel, C. Girardi, Mutual inductance calculation between circular filaments arbitrarily positioned in space: Alternative to

Grover's formula, *IEEE Transactions on Magnetics* 46 (9) (2010) 3591–3600. doi:10.1109/TMAG.2010.2047651.

URL <https://doi.org/10.1109/TMAG.2010.2047651>

- [3] E. B. Rosa, The self and mutual inductances of linear conductors, US Department of Commerce and Labor, Bureau of Standards, 1908.
- [4] F. W. Grover, Inductance calculations : working formulas and tables, special ed. prepared for instrument society of america Edition, Research Triangle Park, N.C. : Instrument Society of America, 1981, reprint. Originally published: New York : Van Nostrand, 1946. With publisher's comment.
- [5] H. B. Dwight, *Electrical Coils and Conductors: Their Electrical Characteristics*, McGraw-Hill, 1945.
- [6] C. Snow, *Formulas for computing capacitance and inductance*, Vol. 544, US Govt. Print. Off., 1954.
- [7] L. A. Zeitlin, *Induktivnosti provodov i konturov (Inductances of wires and loops)*, Gosenergoizdat, Leningrad - Moskva, 1950.
- [8] P. L. Kalantarov, L. A. Zeitlin, *Raschet induktivnostey (Calculation of Inductances)*, 3rd Edition, Energoatomizdat, Leningrad, 1986.
- [9] M. Kamon, M. J. Tsuk, J. K. White, Fasthenry: a multipole-accelerated 3-D inductance extraction program, *IEEE Transactions on Microwave Theory and Techniques* 42 (9) (1994) 1750–1758. doi:10.1109/22.310584.
- [10] E. Okress, D. Wroughton, G. Comenetz, P. Brace, J. Kelly, Electromagnetic levitation of solid and molten metals, *Journal of Applied Physics* 23 (5) (1952) 545–552.
- [11] Y. M. Urman, Theory for the calculation of the force characteristics of an electromagnetic suspension of a superconducting body, *Technical Physics* 42 (1) (1997) 1–6. doi:10.1134/1.1258645.
URL <https://doi.org/10.1134/1.1258645>

- [12] Y. M. Urman, Calculation of the force characteristics of a multi-coil suspension of a superconducting sphere, *Technical Physics* 42 (1) (1997) 7–13. doi:10.1134/1.1258654.
URL <https://doi.org/10.1134/1.1258654>
- [13] M. W. Coffey, Mutual inductance of superconducting thin films, *Journal of Applied Physics* 89 (10) (2001) 5570–5577.
- [14] Y. Urman, S. Kuznetsov, Translational transformations of tensor solutions of the helmholtz equation and their application to describe interactions in force fields of various physical nature, *Quarterly of Applied Mathematics* 72 (1) (2014) 1–20.
- [15] U.-M. Jow, M. Ghovanloo, Design and optimization of printed spiral coils for efficient transcutaneous inductive power transmission, *IEEE Transactions on biomedical circuits and systems* 1 (3) (2007) 193–202.
- [16] Y. P. Su, X. Liu, S. Y. R. Hui, Mutual inductance calculation of movable planar coils on parallel surfaces, *IEEE Transactions on Power Electronics* 24 (4) (2009) 1115–1123. doi:10.1109/TPEL.2008.2009757.
- [17] S. Y. Chu, A. T. Avestruz, Transfer-power measurement: A non-contact method for fair and accurate metering of wireless power transfer in electric vehicles, in: *2017 IEEE 18th Workshop on Control and Modeling for Power Electronics (COMPEL)*, 2017, pp. 1–8. doi:10.1109/COMPEL.2017.8013344.
- [18] A. Shiri, A. Shoulaie, A new methodology for magnetic force calculations between planar spiral coils, *Progress In Electromagnetics Research* 95 (2009) 39–57.
- [19] R. Ravaud, G. Lemarquand, V. Lemarquand, Force and stiffness of passive magnetic bearings using permanent magnets. part 1: Axial magnetization, *IEEE transactions on magnetics* 45 (7) (2009) 2996.

- [20] S. Obata, A muscle motion solenoid actuator, *Electrical Engineering in Japan* 184 (2) (2013) 10–19.
- [21] R. Shalati, K. V. Poletkin, J. G. Korvink, V. Badilita, Novel concept of a series linear electromagnetic array artificial muscle, *Journal of Physics: Conference Series* 1052 (1) (2018) 012047.
URL <http://stacks.iop.org/1742-6596/1052/i=1/a=012047>
- [22] K. Poletkin, A. I. Chernomorsky, C. Shearwood, U. Wallrabe, An analytical model of micromachined electromagnetic inductive contactless suspension., in: *the ASME 2013 International Mechanical Engineering Congress & Exposition*, ASME, San Diego, California, USA, 2013, pp. V010T11A072–V010T11A072. doi:10.1115/IMECE2013-66010.
URL <http://dx.doi.org/10.1115/IMECE2013-66010>
- [23] K. Poletkin, A. Chernomorsky, C. Shearwood, U. Wallrabe, A qualitative analysis of designs of micromachined electromagnetic inductive contactless suspension, *International Journal of Mechanical Sciences* 82 (2014) 110–121. doi:10.1016/j.ijmecsci.2014.03.013.
URL <http://authors.elsevier.com/sd/article/S0020740314000897>
- [24] Z. Lu, K. Poletkin, B. den Hartogh, U. Wallrabe, V. Badilita, 3D micro-machined inductive contactless suspension: Testing and modeling, *Sensors and Actuators A Physical* 220 (2014) 134–143. doi:10.1016/j.sna.2014.09.017.
URL <http://dx.doi.org/10.1016/j.sna.2014.09.017>
- [25] K. Poletkin, Z. Lu, U. Wallrabe, J. Korvink, V. Badilita, Stable dynamics of micro-machined inductive contactless suspensions, *International Journal of Mechanical Sciences* 131-132 (2017) 753 – 766. doi:<https://doi.org/10.1016/j.ijmecsci.2017.08.016>.
URL <http://www.sciencedirect.com/science/article/pii/S0020740316306555>

- [26] K. V. Poletkin, A. I. Chernomorsky, C. Shearwood, A proposal for micro-machined accelerometer, base on a contactless suspension with zero spring constant, *IEEE Sensors J.* 12 (07) (2012) 2407–2413. doi:10.1109/JSEN.2012.2188831.
- [27] K. V. Poletkin, R. Shalati, J. G. Korvink, V. Badilita, Pull-in actuation in hybrid micro-machined contactless suspension, *Journal of Physics: Conference Series* 1052 (1) (2018) 012035.
URL <http://stacks.iop.org/1742-6596/1052/i=1/a=012035>
- [28] K. V. Poletkin, J. G. Korvink, Modeling a pull-in instability in micro-machined hybrid contactless suspension 7 (1) (2018) 11.
- [29] T. Theodoulidis, R. J. Ditchburn, Mutual impedance of cylindrical coils at an arbitrary position and orientation above a planar conductor, *IEEE Transactions on Magnetics* 43 (8) (2007) 3368–3370. doi:10.1109/TMAG.2007.894559.
- [30] M. Sawan, S. Hashemi, M. Sehil, F. Awwad, M. Hajj-Hassan, A. Khouas, Multicoils-based inductive links dedicated to power up implantable medical devices: modeling, design and experimental results, *Biomedical Microdevices* 11 (5) (2009) 1059. doi:10.1007/s10544-009-9323-7.
URL <https://doi.org/10.1007/s10544-009-9323-7>
- [31] S. Kuznetsov, J. K. Guest, Topology optimization of magnetic source distributions for diamagnetic and superconducting levitation, *Journal of Magnetism and Magnetic Materials* 438 (2017) 60 – 69. doi:<https://doi.org/10.1016/j.jmmm.2017.04.052>.
URL <http://www.sciencedirect.com/science/article/pii/S0304885316319515>
- [32] D. Hoult, B. Tomanek, Use of mutually inductive coupling in probe design, *Concepts in Magnetic Resonance* 15 (4) (2002) 262–285. arXiv:<https://onlinelibrary.wiley.com/doi/pdf/10.1002/>

cmr.10047, doi:10.1002/cmr.10047.

URL <https://onlinelibrary.wiley.com/doi/abs/10.1002/cmr.10047>

- [33] N. Spengler, P. T. While, M. V. Meissner, U. Wallrabe, J. G. Korvink, Magnetic lens lenses improve the limit-of-detection in nuclear magnetic resonance, *PLOS ONE* 12 (8) (2017) 1–17. doi:10.1371/journal.pone.0182779.
URL <https://doi.org/10.1371/journal.pone.0182779>
- [34] G. D. Angelis, V. Pasku, A. D. Angelis, M. Dionigi, M. Mongiardo, A. Moschitta, P. Carbone, An indoor ac magnetic positioning system, *IEEE Transactions on Instrumentation and Measurement* 64 (5) (2015) 1267–1275. doi:10.1109/TIM.2014.2381353.
- [35] F. Wu, J. Jeon, S. K. Moon, H. J. Choi, H. Son, Voice coil navigation sensor for flexible silicone intubation, *IEEE/ASME Transactions on Mechatronics* 21 (2) (2016) 851–859. doi:10.1109/TMECH.2015.2476836.
- [36] B. Gulbahar, A communication theoretical analysis of multiple-access channel capacity in magneto-inductive wireless networks, *IEEE Transactions on Communications* 65 (6) (2017) 2594–2607. doi:10.1109/TCOMM.2017.2669995.
- [37] J. C. Maxwell, *A Treatise on Electricity and Magnetism*, 3rd Edition, Vol. 2, Dover Publications Inc., 1954.
- [38] S. Butterworth, LIII. On the coefficients of mutual induction of eccentric coils, *The London, Edinburgh, and Dublin Philosophical Magazine and Journal of Science* 31 (185) (1916) 443–454. arXiv:<https://doi.org/10.1080/14786440508635521>, doi:10.1080/14786440508635521.
URL <https://doi.org/10.1080/14786440508635521>
- [39] C. Snow, Mutual inductance of any two circles, *Bur. Stand. J. Res* 1 (1928) 531–542.

- [40] M. R. Spiegel, S. Lipschutz, J. Liu, Schaum's outline of mathematical handbook of formulas and tables, 3rd Edition, McGraw-Hill New York, 2009.