

Inverse spectral problem for a third-order differential operator with non-local potential

V. A. Zolotarev

Abstract. Spectral problem for a self-adjoint third-order differential operator with non-local potential on a finite interval is studied. Elementary functions that are analogues of sines and cosines for such operators are described. Direct and inverse problems for third-order operators with non-local potential are solved.

Key words: third-order differential operator, non-local potential, inverse problem.

Introduction

Direct and inverse problems for second-order differential operators (Sturm – Liouville) are well studied and play an important role in mathematical physics and in theory of nonlinear equations [1, 2]. As a rule, these studies are based on transformation operators [1, 2]. Absence of transformation operators for differential operators higher than the second-order does not allow generalizing the formalism of the Sturm – Liouville operators to this class of operators [3].

Construction of the Lax L-A pair for nonlinear Camassa-Holm and Degasperis-Procesi equations leads to a third-order differential operator which is interpreted as an operator describing vibrations of a cubic string [4]. Therefore, the statement of inverse problems is natural for such operators.

This work deals with direct and inverse spectral problems for third-order self-adjoint operators of the form

$$(L_\alpha y)(x) = iy'''(x) + \alpha \int_0^l y(t) \overline{v(t)} dt v(x)$$

where $\alpha \in \mathbb{R}$, $v \in L^2(0, l)$ ($0 < l < \infty$), domain of which is formed by functions $y \in W_3^2(0, l)$ such that $y(0) = 0$, $y'(0) = y'(l)$, $y(l) = 0$. Non-local potentials play an important role in mathematical physics [5]. Works [6, 7, 8] study second-order differential operators with non-local potentials.

The paper consists of 4 sections. First section deals with spectral analysis of the self-adjoint operator L_0 of the third derivative. New class of functions (similar to sines and cosines) is introduced and its properties are described. In terms of these functions, eigenfunctions of the operator L_0 are described and characteristic function is obtained. Spectrum of the operator L_0 is described.

Section 2 studies operator L_α and constructs its eigenfunctions and calculates its characteristic function. Section 3 describes spectral characteristics of the operator L_α . Section 4 presents solution to the inverse problem and specifies technique of recovery of one-dimensional perturbation by spectral data of the operator L_α .

1 Characteristic function and eigenfunctions of the operator L_0

1.1. Denote by L_0 the self-adjoint differential operator

$$(L_0 y)(x) \stackrel{\text{def}}{=} iD^3 y(x) \quad \left(D = \frac{d}{dx} \right) \quad (1.1)$$

acting in the space $L^2(0, l)$ ($0 < l < \infty$). Domain $\mathfrak{D}(L_0)$ of the operator L_0 is formed by the functions $y \in W_3^2(0, l)$ that satisfy boundary conditions

$$y(0) = 0, \quad y'(0) = y'(l), \quad y(l) = 0. \quad (1.2)$$

Let $\{\zeta_k\}_1^3$ be roots of the equation $\zeta^3 = 1$,

$$\zeta_1 = 1, \quad \zeta_2 = -\frac{1}{2} + \frac{i\sqrt{3}}{2}, \quad \zeta_3 = -\frac{1}{2} - \frac{i\sqrt{3}}{2}, \quad (1.3)$$

then

$$\begin{aligned} \zeta_1 + \zeta_2 + \zeta_3 &= 0, & \zeta_1 \zeta_2 \zeta_3 &= 1, & \zeta_1 - \zeta_2 &= i\sqrt{3}\zeta_3, & \zeta_2 - \zeta_3 &= i\sqrt{3}\zeta_1, \\ \zeta_3 - \zeta_1 &= i\sqrt{3}\zeta_2. \end{aligned} \quad (1.4)$$

The equation

$$iD^3 y(x) = \lambda^3 y(x) \quad (\lambda \in \mathbb{C}) \quad (1.5)$$

has three linearly independent solutions $\{e^{i\lambda\zeta_k x}\}_1^3$ and each solution to equation (1.5) is their linear combination. In particular, solution to the Cauchy problem

$$iD^3 y(x) = \lambda^3 y(x) + f(x); \quad y(0) = y_0, \quad y'(0) = y_1, \quad y''(0) = y_2 \quad (1.6)$$

for $f(x) \equiv 0$ is

$$y_0(\lambda, x) = \frac{1}{3} \sum_k \left(y_0 + \frac{y_1}{i\lambda\zeta_k} + \frac{y_2}{(i\lambda\zeta_k)^2} \right) e^{i\lambda\zeta_k x}. \quad (1.7)$$

Hence, by the method of variation of constants, one finds solution to the Cauchy problem (1.6) when $f(x) \neq 0$,

$$y(\lambda, x) = \frac{1}{3} \sum_k \left(y_0 + \frac{y_1}{i\lambda\zeta_k} + \frac{y_2}{(i\lambda\zeta_k)^2} \right) e^{i\lambda\zeta_k x} - i \int_0^x \frac{1}{3} \sum_k \frac{e^{i\lambda\zeta_k(x-t)}}{(i\lambda\zeta_k)^2} f(t) dt. \quad (1.8)$$

Integral term in (1.8) is a solution to equation (1.6) and satisfies zero initial data $y(0) = 0$, $y'(0) = 0$, $y''(0) = 0$ due to (1.4).

Instead of the exponents $\{e^{i\lambda\zeta_k x}\}_1^3$, one can take another system of fundamental solutions to equation (1.5), for example, $c(i\lambda x)$, $s(i\lambda x)$, $d(i\lambda x)$, where

$$c(z) = \frac{1}{3} \sum_k e^{z\zeta_k}; \quad s(z) = \frac{1}{3} \sum_k \frac{1}{\zeta_k} e^{z\zeta_k}; \quad d(z) = \frac{1}{3} \sum_k \frac{1}{\zeta_k^2} e^{z\zeta_k} \quad (1.9)$$

($z \in \mathbb{C}$). Functions (1.9) are similar to cosines and sines for a second-order equation.

Lemma 1.1 *Entire functions of exponential type (1.9) satisfy the relations:*

- (i) $\underline{s'(z)} = c(z)$, $\underline{d'(z)} = s(z)$, $\underline{c'(z)} = d(z)$;
- (ii) $\underline{c(z)} = c(\bar{z})$, $\underline{s(z)} = s(\bar{z})$, $\underline{d(z)} = d(\bar{z})$;
- (iii) $c(z\zeta_2) = c(z)$, $s(z\zeta_2) = \zeta_2 s(z)$, $d(z\zeta_2) = \zeta_2^2 d(z)$;
- (iv) *Euler's formula*

$$e^{z\zeta_p} = c(z) + \zeta_p s(z) + \zeta_p^2 d(z) \quad (1 \leq p \leq 3);$$

(v) *the functions (1.9) are solutions to the equation $D^3 y = y$ and satisfy the initial data at zero:*

$$\begin{aligned} c(0) &= 1, & c'(0) &= 0, & c''(0) &= 0; \\ s(0) &= 0, & s'(0) &= 1, & s''(0) &= 0; \\ d(0) &= 0, & d'(0) &= 0, & d''(0) &= 1; \end{aligned} \quad (1.10)$$

(vi) *the main identity*

$$c^3(z) + s^3(z) + d^3(z) - 3c(z)s(z)d(z) = 1;$$

(vii) *the summation formulas*

$$\begin{aligned} c(z+w) &= c(z)c(w) + s(z)d(w) + d(z)s(w); \\ s(z+w) &= c(z)s(w) + s(z)c(w) + d(z)d(w); \\ d(z+w) &= c(z)d(w) + s(z)s(w) + d(z)c(w), \end{aligned}$$

(viii)

$$\begin{aligned} 3c^2(z) &= c(2z) + 2c(-z); \\ 3s^2(z) &= d(2z) + 2d(-z), \\ 3d^2(z) &= s(2z) + 2s(-z), \end{aligned}$$

(ix)

$$s^2(z) - d(z)c(z) = d(-z);$$

$$\begin{aligned}d^2(z) - s(z)c(z) &= s(-z); \\c^2(z) - s(z)d(z) &= c(-z);\end{aligned}$$

(x) *Taylor's formulas*

$$\begin{aligned}c(z) &= 1 + \frac{z^3}{3!} + \frac{z^6}{6!} + \dots, \\s(z) &= z + \frac{z^4}{4!} + \frac{z^7}{7!} + \dots, \\d(z) &= \frac{z^2}{2!} + \frac{z^5}{5!} + \frac{z^8}{8!} + \dots\end{aligned}$$

Proof of the lemma follows from the formulas (1.4).

The roots $\{\zeta_p\}_1^3$ divide the plane \mathbb{C} into three sectors:

$$S_p = \left\{ z \in \mathbb{C} : \frac{2\pi}{3}(p-1) < \arg z < \frac{2\pi p}{3} \right\} \quad (1 \leq p \leq 3). \quad (1.11)$$

Relations (iii) (1.10) imply that it is sufficient to know functions (1.9) in one of the sectors S_p .

Lemma 1.2 *Zeros of the functions $c(z)$, $s(z)$, $d(z)$ (1.9) lie on the rays formed by bisectors of the sectors S_p (1.11) and they correspondingly are given by*

$$\left\{ -\zeta_2^l x_c(k) \right\}_{k=1}^\infty; \quad \left\{ -\zeta_2^l x_s(k) \right\}_{k=1}^\infty; \quad \left\{ -\zeta_2^l x_d(k) \right\}_{k=1}^\infty$$

where $l = -1, 0, 1$ and $x_c(k)$, $x_s(k)$, $x_d(k)$ are nonnegative numbers in ascending order.

Besides, $x_c(k)$ are simple positive roots of the equation

$$\cos \frac{\sqrt{3}}{2}x = -\frac{1}{2}e^{-\frac{3}{2}x} \quad (x_c(1) > 0) \quad (1.12)$$

and the numbers $x_s(k)$ and $x_d(k)$ are nonnegative simple roots of the equations

$$\sin \left(\frac{\sqrt{3}}{2}x + \frac{\pi}{6} \right) = \frac{1}{2}e^{-\frac{3}{2}x} \quad (x_s(1) = 0); \quad \sin \left(\frac{\sqrt{3}}{2}x - \frac{\pi}{6} \right) = -\frac{1}{2}e^{-\frac{3}{2}x} \quad (x_d(1) = 0). \quad (1.13)$$

The sequence $x_d(k)$ is interlacing with the sequence $x_s(k)$, which, in its turn, is interlacing with the sequence $x_c(k)$.

Asymptotic behavior of $x_c(k)$, $x_s(k)$, $x_d(k)$ as $k \rightarrow \infty$ can be obtained from the equations (1.12), (1.13).

Formulas (1.7), (1.8) in terms of the functions (1.9) are given by

$$y_0(\lambda, x) = y_0 c(i\lambda x) + y_1 \frac{s(i\lambda x)}{i\lambda} + y_2 \frac{d(i\lambda x)}{(i\lambda)^2}; \quad (1.14)$$

$$y(\lambda, x) = y_0 c(i\lambda x) + y_1 \frac{s(i\lambda x)}{i\lambda} + y_2 \frac{d(i\lambda x)}{(i\lambda)^2} + i \int_0^x \frac{d(i\lambda(x-t))}{\lambda^2} f(t) dt. \quad (1.15)$$

1.2. Find eigenfunctions of the operator L_0 (1.1), (1.2). Relation (1.14) implies that the function

$$y_0(\lambda, x) = y_1 \frac{s(i\lambda x)}{i\lambda} + y_2 \frac{d(i\lambda x)}{(i\lambda)^2} \quad (1.16)$$

is the solution to equation (1.5) and satisfies the first boundary condition $y(0) = 0$. Since

$$y_0'(\lambda, x) = y_1 c(i\lambda x) + y_2 \frac{s(i\lambda x)}{(i\lambda)},$$

due to (i) (1.10), then the boundary condition $y'(0) = y'(l)$ gives

$$y_1 = y_1 c(i\lambda l) + y_2 \frac{s(i\lambda l)}{i\lambda}. \quad (1.17)$$

Remark 1.1 *If $\lambda = 0$, then (1.17) implies that $y_2 = 0$, thus, $y_0(0, x) = y_1 x$, using the third boundary condition (1.2), one obtains that $y_1 = 0$, i. e., $y_0(0, x) = 0$ and thus the eigenfunction $y_0(0, x)$ is trivial.*

Assuming that $\lambda \neq 0$, from (1.17) one finds that

$$y_1 = \frac{y_2}{i\lambda} \cdot \frac{S(i\lambda l)}{1 - c(i\lambda l)}$$

and thus function (1.16) is

$$y_0(\lambda, x) = -\frac{y_2}{\lambda^2(1 - c(i\lambda l))} \{s(i\lambda x)s(i\lambda l) + d(i\lambda x)(1 - c(i\lambda l))\}. \quad (1.18)$$

The third boundary condition $y(l) = 0$ implies

$$\frac{s^2(i\lambda l) + d(i\lambda l)(1 - c(i\lambda l))}{\lambda^2(1 - c(i\lambda l))} = 0 \quad (\lambda \neq 0). \quad (1.19)$$

Remark 1.2 *Numerator and denominator of fraction (1.19), as $\lambda \neq 0$, do not vanish simultaneously. If this is not the case, then $c(i\lambda l) = 1$ and $s(i\lambda l) = 0$ and thus $d(i\lambda l) = 0$, due to (vi) (1.10). This and (iv) (1.10) imply that $e^{i\lambda l \zeta_k} = 0$ ($k = 1, 2, 3$), which is impossible.*

The function

$$\Delta(0, \lambda) \stackrel{\text{def}}{=} \{s^2(i\lambda l) + d(i\lambda l)(1 - c(i\lambda l))\} \quad (1.20)$$

is said to be the **characteristic function of the operator** L_0 (1.1), (1.2).

Remark 1.3 *Equality (1.17) and boundary condition $y(l) = 0$ for $y_0(\lambda, x)$ (1.16) lead to the system of linear equations*

$$\begin{cases} y_1(c(i\lambda l) - 1) + y_2 \frac{s(i\lambda l)}{i\lambda l} = 0; \\ y_1 \frac{s(i\lambda l)}{i\lambda} - y_2 \frac{d(i\lambda l)}{\lambda^2} = 0 \end{cases} \quad (1.21)$$

relative to y_1, y_2 . Solution to system (1.21) is non-trivial if its determinant $D(\lambda) = \Delta(0, \lambda)$ (1.20) vanishes, $D(\lambda) = 0$.

Using (ix) (1.10), one writes characteristic function $\Delta(0, \lambda)$ (1.20) as

$$\Delta(0, \lambda) = \frac{1}{\lambda^2}(d(i\lambda l) + d(-i\lambda l)) = \frac{2}{3\lambda^2} \sum_k \zeta_k \cos \lambda \zeta_k l. \quad (1.22)$$

Lemma 1.3 *The function $\Delta(0, \lambda)$ (1.23) is an even entire function of exponential type and*

$$\overline{\Delta(0, \lambda)} = \Delta(0, \bar{\lambda}); \quad \Delta(0, \zeta_2 \lambda) = \Delta(0, \lambda). \quad (1.23)$$

Zeros of $\Delta(0, \lambda)$ are given by $\{\pm \zeta_2^l \lambda_k(0)\}_{k=1}^\infty$ ($l = 0, 1, 2$) where $\{\lambda_k(0)\}_1^\infty$ are positive simple zeros of $\Delta(0, \lambda)$ on \mathbb{R}_+ , $0 < \lambda_1(0) < \lambda_2(0) < \dots$, each zero $\lambda_k(0)$ lies in the interval $\left(\frac{\pi}{l}(2k-1), \frac{\pi}{l}(2k+1)\right)$ ($k = 1, 2, \dots$) and the asymptotic

$$\lambda_k(0) = \frac{2\pi k}{l} - \frac{\pi}{3l} + \delta_k \quad (\delta = o\left(\frac{1}{k}\right), k \rightarrow \infty) \quad (1.24)$$

is true.

P r o o f. Due to evenness and symmetry $\Delta(0, \zeta_2 \lambda) = \Delta(0, \lambda)$ (1.24), it is sufficient to find zeros of $\Delta(0, \lambda)$ that are situated on \mathbb{R}_+ . Since $\Delta(0, 0) = -2l^2$, then $\lambda = 0$ is not a zero of the function $\Delta(0, \lambda)$ (1.22). Therefore the equation $\Delta(0, \lambda) = 0$ is equivalent to the equality

$$\sum_k \zeta_k \cos \lambda \zeta_k l = 0$$

or, taking into account (1.3),

$$\cos \lambda l - \cos \frac{\lambda l}{2} \operatorname{ch} \frac{\lambda \sqrt{3} l}{2} - \sqrt{3} \sin \frac{\lambda l}{2} \operatorname{sh} \frac{\lambda \sqrt{3} l}{2} = 0,$$

i. e.,

$$\cos \frac{\lambda l}{2} \left(\cos \frac{\lambda l}{2} - \operatorname{ch} \frac{\lambda \sqrt{3} l}{2} \right) = \sin \frac{\lambda l}{2} \left(\sin \frac{\lambda l}{2} + \sqrt{3} \operatorname{sh} \frac{\lambda \sqrt{3} l}{2} \right). \quad (1.25)$$

It is necessary to find positive zeros λ (> 0) of this equation. Since $\sin \frac{\lambda l}{2} + \sqrt{3} \operatorname{sh} \frac{\lambda \sqrt{3} l}{2} > 0$, for $\lambda > 0$, then equation (1.25) is equivalent to the equality

$$\tan \frac{\lambda l}{2} = f(\lambda) \quad (\lambda > 0),$$

where

$$f(\lambda) = \frac{\cos \frac{\lambda l}{2} \operatorname{ch} \frac{\lambda \sqrt{3} l}{2}}{\sin \frac{\lambda l}{2} + \sqrt{3} \operatorname{sh} \frac{\lambda \sqrt{3} l}{2}}.$$

$f(\lambda) < 0$, as $\lambda > 0$, and $f(0) = 0$. Using

$$f'(\lambda) = l \frac{1 - \sqrt{3} \sin \frac{\lambda l}{2} \operatorname{sh} \frac{\lambda \sqrt{3} l}{2} - \cos \frac{\lambda l}{2} \operatorname{ch} \frac{\lambda \sqrt{3} l}{2}}{\left(\sin \frac{\lambda l}{2} + \sqrt{3} \operatorname{sh} \frac{\lambda \sqrt{3} l}{2} \right)^2}$$

and obvious inequalities $\sin x < \operatorname{sh} \sqrt{3}x$, $\cos x < \operatorname{ch} \sqrt{3}x$ that are true for all $x > 0$, one obtains that

$$f'(\lambda) < l \frac{1 - \sqrt{3} \sin^2 \frac{l\lambda}{2} - \cos^2 \frac{l\lambda}{2}}{\left(\sin \frac{l\lambda}{2} + \sqrt{3} \operatorname{sh} \frac{\lambda \sqrt{3} l}{2} \right)^2} < 0.$$

Consequently, the function $f(\lambda)$ decreases on \mathbb{R}_+ and $f(\lambda) \rightarrow -\frac{1}{\sqrt{3}}$, as $\lambda \rightarrow \infty$, therefore $f(\lambda)$ monotonously decreases starting from $f(0) = 0$ and up to the horizontal asymptote $y \rightarrow -\frac{1}{\sqrt{3}}$. Hence it follows that in each interval $\left(\frac{\pi}{l}(2k-1), \frac{\pi}{l}(2k+1) \right)$ ($k \in \mathbb{N}$) there lies exactly one root $\lambda_k(0)$ of the equation $\tan \frac{\lambda l}{2} = f(\lambda)$ ($\lambda \in \mathbb{R}_+$) and

$$\lambda_k(0) = \frac{2\pi k}{l} - \varepsilon_k \quad (0 < \varepsilon_k < \frac{\pi}{l}). \quad (1.26)$$

Numbers $\lambda_k(0)$ are enumerated in accordance with the intervals $\left(\frac{\pi}{l}(2k-1), \frac{\pi}{l}(2k+1)\right)$ ($k \in \mathbb{N}$) and are in ascending order.

Asymptotic (1.24) follows from $f(\lambda) \rightarrow -\frac{1}{\sqrt{3}}$ ($\lambda \rightarrow \infty$).

Function $\Delta(0, \lambda)$ has no complex zeros lying inside sector S_1 (1.11) (as in S_2, S_3). In other case, if $\Delta(0, \mu) = 0$ and $\mu \in S_1$, then $y(\mu, x)$ (1.18) is an eigenfunction of the operator L_0 corresponding to the eigenvalue μ^3 which is impossible in view of self-adjointness of L_0 since μ^3 is a complex number. ■

Theorem 1.1 *Spectrum $\sigma(L_0)$ of the operator L_0 (1.1), (1.2) is simple and*

$$\sigma(L_0) = \{\pm\lambda_k^3(0) : \lambda_k(0) > 0, k \in \mathbb{N}\} \quad (1.27)$$

where $\lambda_k(0)$ are positive zeros of characteristic function $\Delta(0, \lambda)$ (1.22) (Lemma 1.3). Eigenfunctions corresponding to $\lambda_k(0)$ are

$$u(0, \lambda_k(0), x) = \frac{1}{u_k} \{s(i\lambda_k(0)x)s(i\lambda_k(0)l) + d(i\lambda_k(0)x)[1 - c(i\lambda_k(0)l)]\} \quad (1.28)$$

where $u_k = \|u(0, \lambda_k(0), x)\|_{L^2}$.

1.2. Calculate the resolvent $R_{L_0}(\lambda^3) = (L_0 - \lambda^3 I)^{-1}$ of the operator L_0 (1.1), (1.2) and let $R_{L_0}(\lambda^3)f = y$, then $L_0 y = \lambda^3 y + f$ and according to (1.15) the function

$$y(\lambda, x) = y_1 \frac{s(i\lambda x)}{i\lambda} - y_2 \frac{d(i\lambda x)}{\lambda^2} + i \int_0^x \frac{d(i\lambda(x-t))}{\lambda^2} f(t) dt \quad (1.29)$$

is a solution to equation (1.6) and satisfies the first boundary condition $y(\lambda, 0) = 0$. Since

$$y'(\lambda, x) = y_1 c(i\lambda x) - iy_2 \frac{s(i\lambda x)}{\lambda} - \int_0^x \frac{s(i\lambda(x-t))}{\lambda} f(t) dt,$$

then the boundary conditions $y'(0) = y'(l)$ and $y(l) = 0$ yield the system of linear equations for y_1, y_2 ,

$$\begin{cases} y_1(c(i\lambda l) - 1) - iy_2 \frac{s(i\lambda l)}{\lambda} = \int_0^l \frac{s(i\lambda(l-t))}{\lambda} f(t) dt; \\ y_1 \frac{s(i\lambda l)}{i\lambda} - y_2 \frac{d(i\lambda l)}{\lambda^2} = -i \int_0^l \frac{d(i\lambda(l-t))}{\lambda^2} f(t) dt \end{cases} \quad (1.30)$$

coinciding with system (1.21) as $f = 0$. Using the fact that determinant of this system $D(\lambda)$ equals $\Delta(0, \lambda)$ (1.20) (Remark 1.3), one obtains that

$$\begin{aligned} y_1 &= \frac{1}{\lambda^3 D(\lambda)} \int_0^l \{s(i\lambda l)d(i\lambda(l-t)) - d(i\lambda l)s(i\lambda(l-t))\} f(t) dt; \\ y_2 &= \frac{i}{\lambda^2 D(\lambda)} \int_0^l \{[1 - c(i\lambda l)]d(i\lambda(l-t)) + s(i\lambda l)s(i\lambda(l-t))\} f(t) dt. \end{aligned} \quad (1.31)$$

Hence one finds $y(\lambda, x)$ (1.29),

$$\begin{aligned} y(\lambda, x) &= \frac{i}{\lambda^4 \Delta(0, \lambda)} \left\{ s(i\lambda x) \int_0^l [d(i\lambda l)s(i\lambda(l-t)) - s(i\lambda l) \right. \\ &\quad \times d(i\lambda(l-t))] f(t) dt - d(i\lambda x) \int_0^l [(1 - c(i\lambda l))d(i\lambda(l-t)) + s(i\lambda l) \\ &\quad \times s(i\lambda(l-t))] f(t) dt + \left. \int_0^x d(i\lambda(x-t)) [s^2(i\lambda l) + d(i\lambda l)(1 - c(i\lambda l))] f(t) dt \right\}. \end{aligned} \quad (1.32)$$

To simplify this expression, one use the statement.

Lemma 1.4 *For all z , the identities*

$$\begin{aligned} (a) \quad & d(zl)s(z(l-t)) - s(zl)d(z(l-t)) = s(-zl)d(-zt) - d(-zl)s(-zt); \\ (b) \quad & (c(zl) - 1)d(z(l-t)) - s(zl)s(z(l-t)) = -(d(zl) + d(-zl))c(-zt) \\ & \quad - s(zl)s(-zt) - (c(zl) - c(-zl))d(-zt); \end{aligned} \quad (1.33)$$

$$(c) \quad s(zx)[d(zl)s(z(l-t)) - s(zl)d(z(l-t)) + d(zx)[(c(zl) - 1)d(z(l-t)) - s(zl)s(z(l-t))]] = d(z(x-l))d(-zt) - d(zx)d(z(l-t)) - d(z(x-t))d(-zl)$$

are true.

P r o o f. Using the summation formulas (vii) (1.10), one obtains

$$\begin{aligned} d(zl)s(z(l-t)) - s(zl)d(z(l-t)) &= d(zl)[c(zl)s(-zt) + s(zl)c(-zt) \\ &\quad + d(zl)d(-zt)] - s(zl)[c(zl)d(-zt) + s(zl)s(-zt) + d(zl)c(-zt)] \\ &= s(-zt)[c(zl)d(zl) - s^2(zl)] + d(-zt)[d^2(zl) - s(zl)c(zl)] \\ &= -s(-zt)d(-zl) + d(-zt)s(-zl), \end{aligned}$$

due to (ix) (1.10), which proves (a) (1.33). The second equality (b) (1.33) is similarly proved. Substituting (a), (b) into expression for (c), one obtains

$$\begin{aligned}
& s(zx)d(-zt)s(-zl) - s(zx)s(-zt)d(-zl) - d(zx)c(-zt)[d(zl) \\
& \quad - d(zl)] - d(zx)s(-zt)s(zl) - d(zx)d(-zt)[c(zl) - c(-zl)] \\
& = -(s(zx)s(-zt) + d(zx)c(-zt))d(-zl) - d(zx)[c(-zt)d(zl) \\
& \quad + s(-zt)s(zl) + d(-zt)c(zl)] + [s(zx)s(-zl) + d(zx)c(-zl)]d(-tz) \\
& = -d(z(x-t))d(-zl) - d(zx)d(z(l-t)) + d(z(x-l))d(-zt),
\end{aligned}$$

due to (vii) (1.10). ■

Substituting (c) (1.33) into (1.32), one obtains

$$\begin{aligned}
y(x, \lambda) = \frac{i}{\lambda^4 \Delta(0, \lambda)} \left\{ \int_0^l [d(i\lambda(x-l))d(-i\lambda t) - d(i\lambda x)d(i\lambda(l-t))] \right. \\
\left. - d(i\lambda(x-t))d(i\lambda l)] f(t) dt + \int_0^x d(i\lambda(x-t))[d(i\lambda l) + d(-i\lambda l)] f(t) dt \right\}, \tag{1.34}
\end{aligned}$$

hence the statement follows.

Theorem 1.2 *Resolvent $R_{L_0}(\lambda^3) = (L_0 - \lambda^3 I)^{-1}$ of the operator L_0 (1.2), (1.3) is*

$$\begin{aligned}
(R_{L_0}(\lambda^3)f)(x) = \frac{i}{\lambda^4 \Delta(0, \lambda)} \left\{ \int_0^x [d(i\lambda(x-l))d(-i\lambda t) + d(i\lambda(x-t))d(i\lambda l) \right. \\
\left. - d(i\lambda x)d(i\lambda(l-t))] + \int_x^l [d(i\lambda(x-l))d(-i\lambda t) - d(i\lambda(x-t))d(-i\lambda l) \right. \\
\left. - d(i\lambda x)d(i\lambda(l-t))] f(t) dt \right\} \tag{1.35}
\end{aligned}$$

where $\Delta(0, \lambda)$ is the characteristic function (1.23) of the operator L_0 .

2 Operator L_α

2.1 Consider a self-adjoint operator $L_\alpha (= L_\alpha(v))$ in $L^2(0, l)$ which is a one-dimensional perturbation of L_0 (1.1), (1.2),

$$(L_\alpha y)(x) \stackrel{\text{def}}{=} iD^3 y(x) + \alpha \int_0^l y(t) \bar{v}(t) dt v(x) \tag{2.1}$$

where $\alpha \in \mathbb{R}$ and $v \in L^2(0, l)$. Without loss in generality, assume that $\|v\|_{L^2} = 1$. Domains of the operators L_α and L_0 coincide, $\mathfrak{D}(L_\alpha) = \mathfrak{D}(L_0)$.

Using the functions $c(z)$, $s(z)$, $d(z)$ (1.9), define Fourier transforms

$$\begin{aligned}\tilde{v}_c(\lambda) &\stackrel{\text{def}}{=} \langle v(x), c(i\bar{\lambda}x) \rangle = \frac{1}{3} \sum_k \tilde{v}_k(\lambda); \\ \tilde{v}_s(\lambda) &\stackrel{\text{def}}{=} \langle v(x), s(i\bar{\lambda}x) \rangle = \frac{1}{3} \sum_k \zeta_k^{-1} \tilde{v}_k(\lambda); \\ \tilde{v}_d(\lambda) &\stackrel{\text{def}}{=} \langle v(x), d(i\bar{\lambda}x) \rangle = \frac{1}{3} \sum_k \zeta_k \bar{v}_k(\lambda)\end{aligned}\tag{2.2}$$

where

$$\tilde{v}_k(\lambda) = \int_0^l e^{-i\lambda\zeta_k x} v(x) dx \quad (1 \leq k \leq 3).\tag{2.3}$$

Introduce the operation of involution

$$f^*(\lambda) = \overline{f(\bar{\lambda})},\tag{2.4}$$

then

$$\begin{aligned}\tilde{v}_c^*(\lambda) &= \langle c(i\lambda x), v(x) \rangle = \frac{1}{3} \sum_k \tilde{v}_k^*(\lambda); \\ \tilde{v}_s^*(\lambda) &= \langle s(i\lambda x), v(x) \rangle = \frac{1}{3} \sum_k \zeta_k \tilde{v}_k^*(\lambda); \\ \tilde{v}_d^*(\lambda) &= \langle d(i\lambda x), v(x) \rangle = \frac{1}{3} \sum_k \zeta_k^{-1} \tilde{v}_k^*(\lambda),\end{aligned}\tag{2.5}$$

besides,

$$\tilde{v}_1^*(\lambda) = \int_0^l e^{i\lambda\zeta_1 x} \bar{v}(x) dx; \quad \tilde{v}_2^*(\lambda) = \int_0^l e^{i\lambda\zeta_3 x} \bar{v}(x) dx; \quad \bar{v}_3^*(\lambda) = \int_0^l e^{i\lambda\zeta_2 x} \bar{v}(x) dx.\tag{2.6}$$

According to the Cauchy problem (1.6), equation $L_\alpha y = \lambda^3 y$ has the solution (see (1.15))

$$y(\lambda, x) = y_1 \frac{s(i\lambda x)}{i\lambda} - y_2 \frac{d(i\lambda x)}{\lambda^2} - i\alpha \langle y, v \rangle \int_0^x \frac{d(i\lambda(x-t))}{\lambda^2} v(t) dt\tag{2.7}$$

satisfying the boundary condition $y(0) = 0$. Multiplying equality (2.7) by $\bar{v}(x)$ and integrating it from 0 to l , one obtains

$$iy_1 \frac{\tilde{v}_s^*(\lambda)}{\lambda} + y_2 \frac{\tilde{v}_d^*(\lambda)}{\lambda^2} + \langle y, v \rangle \left(1 + \frac{i\alpha}{\lambda^2} m(x) \right) = 0\tag{2.8}$$

where $\tilde{v}_s^*(\lambda)$ and $\tilde{v}_d^*(\lambda)$ are given by (1.5) and

$$m(\lambda) \stackrel{\text{def}}{=} \left\langle \int_0^x d(i\lambda(x-t))v(t)dt, v(x) \right\rangle = \frac{1}{3} \sum \zeta_k \psi_k(\lambda); \quad (2.9)$$

$$\psi_k(\lambda) \stackrel{\text{def}}{=} \int_0^l dx e^{i\lambda\zeta_k x} \overline{v(x)} \int_0^x dt e^{-i\lambda\zeta_k t} v(t) \quad (1 \leq k \leq 3).$$

Remark 2.1 *The functions $\tilde{v}_k(\lambda)$ (2.3) and $\tilde{v}_k^*(\lambda)$ (2.6) (and thus the functions (2.2) and (2.5) also) are entire functions of exponential type.*

Lemma 2.1 *The function $m(\lambda)$ (2.9) is an entire function of exponential type and*

$$m(\lambda) + m^*(\lambda) = \tilde{v}_d(\lambda)\tilde{v}_c^*(\lambda) + \tilde{v}_s(\lambda)\tilde{v}_s^*(\lambda) + \tilde{v}_c(\lambda)\tilde{v}_d^*(\lambda). \quad (2.10)$$

P r o o f. Since $\psi_k(\lambda)$ (2.9) is the Fourier transform of the convolution

$$\psi_k(\lambda) = \int_0^l dx \int_0^x dt e^{i\lambda\zeta_k(x-t)} v(t) \overline{v(x)} = \int_0^l ds e^{i\lambda\zeta_k s} \int_s^l v(x-s) \overline{v(x)} dx,$$

then $\psi_k(\lambda)$ is an entire function of exponential type, thus $m(\lambda)$ also has this property.

Relation (2.9) implies that

$$m(\lambda) + m^*(\lambda) = \frac{1}{3} \{ \zeta_1(\psi_1(\lambda) + \psi_1^*(\lambda)) + \zeta_2(\psi_2(\lambda) + \psi_2^*(\lambda)) + \zeta_3(\psi_3(\lambda) + \psi_3^*(\lambda)) \}.$$

Integrating by parts, one obtains

$$\psi_k(\lambda) = \int_0^l dt e^{-i\lambda\zeta_k t} v(t) \int_0^l dx e^{i\lambda\zeta_k x} \overline{v(x)} - \int_0^l dt e^{-i\lambda\zeta_k t} v(t) \int_0^t dx e^{i\lambda\zeta_k x} \overline{v(x)},$$

therefore

$$\begin{aligned} \psi_1(\lambda) &= \tilde{v}_1(\lambda)\tilde{v}_1^*(\lambda) - \psi_1^*(\lambda), & \psi_2(\lambda) &= \tilde{v}_2(\lambda)\tilde{v}_3^*(\lambda) - \psi_3^*(\lambda), \\ \psi_3(\lambda) &= \tilde{v}_3(\lambda)\tilde{v}_2^*(\lambda) - \psi_2^*(\lambda). \end{aligned}$$

So,

$$\begin{aligned} m(\lambda) + m^*(\lambda) &= \frac{1}{3} \{ \zeta_1 \tilde{v}_1(\lambda)\tilde{v}_1^*(\lambda) + \zeta_2 \tilde{v}_2(\lambda)\tilde{v}_3^*(\lambda) + \zeta_3 \tilde{v}_3(\lambda)\tilde{v}_2^*(\lambda) \} \\ &= \int_0^l dx \int_0^l dt d(i\lambda(x-t)) \overline{v(x)} v(t) = \int_0^l dx \int_0^l dt \overline{v(x)} v(t) \{ c(i\lambda x) d(-i\lambda t) \} \end{aligned}$$

$$+s(i\lambda x)s(-i\lambda t) + d(i\lambda x)c(-i\lambda t)\}$$

due to (vii) (1.10) and according to (2.2), (2.5),

$$m(\lambda) + m^*(\lambda) = \tilde{v}_d(\lambda)\tilde{v}_c^*(\lambda) + \tilde{v}_s(\lambda)\tilde{v}_s^*(\lambda) + \tilde{v}_c(\lambda)\tilde{v}_d^*(\lambda). \quad \blacksquare$$

Equality (2.10) is an analogue of a well-known statement on the Fourier transform of a convolution.

Formula (2.8) and boundary conditions $y'(0) = y'(l)$, $y(l) = 0$ for $y(\lambda, x)$ (2.7) yield the system of linear equations for $y_1, y_2, \langle y, v \rangle$,

$$\begin{cases} y_1 i \frac{\tilde{v}_s^*(\lambda)}{\lambda} + y_2 \frac{\tilde{v}_d^*(\lambda)}{\lambda^2} + \langle y, v \rangle \left(1 + \frac{i\alpha}{\lambda^2} m(\lambda) \right) = 0; \\ y_1 (1 - c(i\lambda l)) + y_2 i \frac{s(i\lambda l)}{\lambda} - \alpha \langle y, v \rangle \int_0^l \frac{s(i\lambda(l-t))}{\lambda} v(t) dt = 0, \\ y_1 \frac{is(i\lambda l)}{\lambda} + y_2 \frac{d(i\lambda l)}{\lambda^2} + \alpha i \langle y, v \rangle \int_0^l \frac{d(i\lambda(l-t))}{\lambda^2} v(t) dt = 0. \end{cases} \quad (2.11)$$

Solutions to system (2.11) are non-trivial then and only then when its determinant $D_\alpha(\lambda)$ vanishes. The function $\Delta(\alpha, \lambda) = D_\alpha(\lambda)$ is said to be **characteristic function of the operator** L_α (2.1) and equals

$$\begin{aligned} \Delta(\alpha, \lambda) \stackrel{\text{def}}{=} & \left(1 + \frac{\alpha i}{\lambda^2} m(\lambda) \right) \Delta(0, \lambda) + \frac{i\alpha}{\lambda^4} \left\{ \tilde{v}_d^*(\lambda) \int_0^l [(c(i\lambda l) - 1)d(i\lambda(l-t)) \right. \\ & \left. - s(i\lambda l)s(i\lambda(l-t))]v(t)dt + \tilde{v}_s^*(\lambda) \int_0^l [d(i\lambda l)s(i\lambda(l-t)) \right. \\ & \left. - s(i\lambda l)d(i\lambda(l-t))]v(t)dt \right\} \end{aligned} \quad (2.12)$$

Using (1.22) and (a), (b) (1.33), one has

$$\begin{aligned} \Delta(\alpha, \lambda) - \Delta(0, \lambda) &= \frac{i\alpha}{\lambda^4} \{ m(\lambda)(d(i\lambda l) + d(-i\lambda l)) - \tilde{v}_d^*(\lambda)\tilde{v}_c(\lambda) \\ &\times (d(i\lambda l) + d(-i\lambda l)) - \tilde{v}_d^*(\lambda)\tilde{v}_s(-\lambda)s(i\lambda l) - \tilde{v}_d^*(\lambda)\tilde{v}_d(\lambda)(c(i\lambda l) - c(-i\lambda l)) \\ &\quad + \tilde{v}_s^*(\lambda)\tilde{v}_d(\lambda)s(-i\lambda l) - \tilde{v}_s^*(\lambda)v_s(\lambda)d(-i\lambda l) \}. \end{aligned}$$

Expressing $\tilde{v}_s^*(\lambda)\tilde{v}_s(\lambda)$ from (2.10) and substituting it into this expression, one obtains

$$\Delta(\alpha, \lambda) - \Delta(0, \lambda) = \frac{i\alpha}{\lambda^4} \{ m(\lambda)d(i\lambda l) + \tilde{v}_d(\lambda)[\tilde{v}_c^*(\lambda)d(-i\lambda l)$$

$$\begin{aligned}
& +\tilde{v}_s^*(\lambda)s(-i\lambda l) + \tilde{v}_d^*(\lambda)c(-i\lambda l)] - m^*(\lambda)d(-i\lambda l) - \tilde{v}_d^*(\lambda) \\
& \times [\tilde{v}_c(\lambda)d(i\lambda l) + \tilde{v}_s(\lambda)s(i\lambda l) + \tilde{v}_d(\lambda)c(i\lambda l)]\}.
\end{aligned}$$

Taking (vii) (1.10) into account, one finds

$$\begin{aligned}
\tilde{v}_c(\lambda)d(i\lambda l) + \tilde{v}_s(\lambda)s(i\lambda l) + \tilde{v}_d(\lambda)c(i\lambda l) &= \int_0^l d(i\lambda(l-x))v(x)dx \\
&= \int_0^l d(i\lambda t)v(l-t)dt = \tilde{w}_d(-\lambda)
\end{aligned}$$

where $\tilde{w}_d(\lambda)$ is the Fourier transform $\tilde{w}_d(\lambda) = \langle w(x), d(i\lambda x) \rangle$ (2.2) of the function

$$w(x) \stackrel{\text{def}}{=} v(l-x). \quad (2.13)$$

Lemma 2.2 *Characteristic function $\Delta(\alpha, \lambda)$ (2.12) of the operator L_α (2.1) is*

$$\Delta(\alpha, \lambda) - \Delta(0, \lambda) = \frac{i\alpha}{\lambda^4} \{F(\lambda) - F^*(\lambda)\} \quad (2.14)$$

where

$$F(\lambda) \stackrel{\text{def}}{=} m(\lambda)d(i\lambda l) + \tilde{v}_d(\lambda)\tilde{w}_d^*(-\lambda), \quad (2.15)$$

besides, $\tilde{v}_d(\lambda)$ and $m(\lambda)$ are given by (2.5), (2.9), $\tilde{w}_d(\lambda)$ is the Fourier transform (2.2) of the function $w(x)$ (2.13). Moreover, $\Delta(\alpha, \lambda)$ (2.14) is a real entire function of exponential type and

$$\Delta(\alpha, \lambda\zeta_2) = \Delta(\alpha, \lambda), \quad \Delta^*(\alpha, \lambda) = \Delta(\alpha, \lambda). \quad (2.16)$$

2.2. Find eigenfunctions of the operator L_α (2.1). Boundary conditions $y'(0) = y'(l)$ and $y(l) = 0$ for the function $y(\lambda, x)$ (2.7) yield system of equations formed by the two last equalities in (2.11)

$$\begin{cases}
y_2 i \frac{s(i\lambda l)}{\lambda} - \frac{\alpha \langle y, v \rangle}{\lambda} \int_0^l s(i\lambda(l-t))v(t)dt = -y_1(1 - c(i\lambda l)), \\
y_2 \frac{d(i\lambda l)}{\lambda} + \frac{\alpha i \langle y, v \rangle}{\lambda} \int_0^l d(i\lambda(l-t))v(t)dt = -y_1 i s(i\lambda l).
\end{cases}$$

Hence we find that

$$\begin{aligned}
\frac{y_2}{\lambda} &= \frac{iy_1}{a(\lambda)} \int_0^l [(c(i\lambda l) - 1)d(i\lambda(l-t)) - s(i\lambda l)s(i\lambda(l-t))]v(t)dt; \\
\frac{\alpha \langle y, v \rangle}{\lambda} &= \frac{y_1}{a(\lambda)} (s(i\lambda l)^2 + d(i\lambda l))(1 - c(i\lambda l)),
\end{aligned} \quad (2.17)$$

besides,

$$a(\lambda) = \int_0^l [d(i\lambda l)s(i\lambda(l-t)) - s(i\lambda t)d(i\lambda(l-t))]v(t)dt.$$

Substituting expressions (2.17) into (2.7), one obtains

$$y(\lambda, x) = -\frac{iy_1}{\lambda\alpha(\lambda)} \left\{ \int_0^l \{s(i\lambda x)[d(i\lambda l)s(i\lambda(l-t)) - s(i\lambda l)d(i\lambda(l-t))] \right. \\ \left. + d(i\lambda x)[(c(i\lambda l) - 1)d(i\lambda(l-t)) - s(i\lambda l)s(i\lambda(l-t))]\}v(t)dt \right.$$

and according to (c) (1.33),

$$y(\lambda, x) = -\frac{iy_1}{\lambda\alpha(\lambda)} \left\{ \int_0^l [d(i\lambda(x-l))d(-i\lambda t) - d(i\lambda x)d(i\lambda(l-t))] \right. \\ \left. - d(i\lambda(x-t))d(-i\lambda l)]v(t)dt + (d(i\lambda l) + d(-i\lambda l)) \int_0^x d(i\lambda(x-t))v(t)dt \right\}$$

Lemma 2.3 *Eigenfunctions* $u(\alpha, \lambda, x)$ *of the operator* L_α (2.1) *are given by*

$$u(\alpha, \lambda, x) = \frac{1}{u(\alpha, \lambda)} \left\{ d(i\lambda(x-l))\tilde{w}_d(\lambda) - d(i\lambda x)\tilde{w}_d(-\lambda) \right. \\ \left. + d(i\lambda l) \int_0^x d(i\lambda(x-t))v(t)dt - d(-i\lambda l) \int_x^l d(i\lambda(x-t))v(t)dt \right\} \quad (2.18)$$

where $\lambda = \lambda_k(\alpha)$ is a zero of the characteristic function $\Delta(\alpha, \lambda)$ (2.14), $\tilde{w}_d(\lambda)$ is the Fourier transform (2.2) of the function $w(x)$ (2.13); $u(\alpha, \lambda) = \|u(\alpha, \lambda, x)\|_{L^2}$ and

$$u(\alpha, \lambda\zeta_2, x) = u(\alpha, \lambda, x). \quad (2.19)$$

3 Abstract problem

3.1. Consider an abstract problem of one-dimensional perturbation of a self-adjoint operator with simple spectrum. Let L_0 be a self-adjoint operator acting in a Hilbert space H with simple discrete spectrum

$$\sigma(L_0) = \{z_n : z_n \in \mathbb{R}, n \in \mathbb{Z}\}. \quad (3.1)$$

Its eigenfunctions u_n ($L_0 u_n = z_n u_n$) are orthonormal, $\langle u_n, u_m \rangle = \delta_{n,m}$, and form an orthonormal basis in the space H . Resolvent $R_{L_0}(z) = (L_0 - zI)^{-1}$ of the operator L_0 is

$$R_{L_0}(z) = \sum_h \frac{f_n}{z_n - z} u_n \quad (3.2)$$

where $f_n = \langle f, u_n \rangle$ are Fourier coefficients of the vector f in the basis $\{u_n\}$.

By L_α denote a self-adjoint operator which is a one-dimensional perturbation of L_0 (cf. (2.1)),

$$L_\alpha \stackrel{\text{def}}{=} L_0 + \alpha \langle \cdot, v \rangle v \quad (3.3)$$

where $\alpha \in \mathbb{R}$ and v is a fixed vector from H such that $\|v\| = 1$. Domains of L_α and L_0 coincide, $\mathfrak{D}(L_\alpha) = \mathfrak{D}(L_0)$.

Lemma 3.1 *Resolvent $R_{L_\alpha}(z) = (L_\alpha - zI)^{-1}$ of the operator L_α (3.3) is*

$$R_{L_\alpha}(z)f = R_{L_0} - \alpha \frac{\langle R_{L_0}(z)f, v \rangle}{1 + \alpha \langle R_{L_0}(z)v, v \rangle} \cdot R_{L_0}(z)v \quad (3.4)$$

where $R_{L_0}(z) = (L_0 - zI)^{-1}$ is the resolvent of operator L_0 and $f \in H$.

P r o o f. Let $y = R_{L_0}(z)f$, then

$$f = (L_0 - zI)y + \alpha \langle y, v \rangle v,$$

and thus

$$R_{L_0}(z)f = y + \alpha \langle y, v \rangle R_{L_0}(z)v. \quad (3.5)$$

Scalar multiplying this equality by v , one obtains

$$\langle R_{L_0}(z)f, v \rangle = \langle y, v \rangle (1 + \alpha \langle R_{L_0}(z)v, v \rangle).$$

From here expressing $\langle y, v \rangle$ and substituting it into (3.5), one arrives at formula (3.4). ■

Formulas (3.2), (3.4) imply

$$R_{L_\alpha}(z)f = \sum_n \frac{f_n}{z_n - z} u_n - \alpha \frac{\sum_k \frac{f_k \bar{v}_k}{z_k - z}}{1 + \alpha \sum_k \frac{|v_k|^2}{z_k - z}} \cdot \sum_n \frac{v_n}{z_n - z} u_n \quad (3.6)$$

where $f_n = \langle f, u_n \rangle$ and $v_n = \langle v, u_n \rangle$ are Fourier coefficients of the vectors f and v correspondingly.

Lemma 3.2 *If $v_p \neq 0$, then point z_p ($\in \sigma(L_0)$ (3.1)) does not belong to the spectrum $\sigma(L_\alpha)$ operator L_α (3.3).*

P r o o f. Really, residue of the resolvent $R_{L_\alpha}(z)$ (3.6) vanishes at the point z_p ,

$$\lim_{z \rightarrow z_p} (z_p - z) R_{L_\alpha}(z) = f_p u_p - \frac{\alpha f_p \bar{v}_p}{\alpha v_p \bar{v}_p} \cdot v_p u_p = 0. \quad \blacksquare$$

Hence it follows that it is natural to divide the set $\sigma(L_0)$ (3.1) into two disjoint subsets $\sigma(L_0) = \sigma_0 \cup \sigma_1$ where

$$\sigma_0 \stackrel{\text{def}}{=} \{z_n^0 = z_n \in \sigma(L_0) : v_n = 0\}, \quad \sigma_1 \stackrel{\text{def}}{=} \{z_n^1 = z_n \in \sigma(L_0) : v_n \neq 0\}. \quad (3.7)$$

Assume that elements from $\sigma(L_0)$, σ_0 , σ_1 are numbered in ascending order. Partition $\sigma(L_0) = \sigma_0 \cup \sigma_1$ corresponds to the decomposition of the space H into orthogonal sum $H = H_0 \oplus H_1$ where

$$H_0 \stackrel{\text{def}}{=} \text{span}\{u_n : z_n \in \sigma_0\}, \quad H_1 \stackrel{\text{def}}{=} \text{span}\{u_n : z_n \in \sigma_1\}. \quad (3.8)$$

The subspaces H_0 , H_1 reduce the operator L_α (3.3) and

$$L_\alpha|_{H_0} = L_{\alpha,0}; \quad L_\alpha|_{H_1} = L_{\alpha,1}, \quad (3.9)$$

therefore

$$R_{L_\alpha}(z) = R_{L_{\alpha,0}}(z) \oplus R_{L_{\alpha,1}}(z)$$

where

$$\begin{aligned} R_{L_{\alpha,0}}(z)f &= \sum_{z_n^0 \in \sigma_0} \frac{f_n}{z_n^0 - z} u_n; \\ R_{L_{\alpha,1}}(z)f &= \frac{1}{Q(z)} \sum_{z_n^1 \in \sigma_1} \frac{1}{z_n^1 - z} \{f_n Q(z) - \alpha v_n P(z, f)\} u_n, \end{aligned} \quad (3.10)$$

besides,

$$Q(z) \stackrel{\text{def}}{=} 1 + \alpha \sum_{z_n^1 \in \sigma_1} \frac{|v_n|^2}{z_n^1 - z}; \quad P(z, f) \stackrel{\text{def}}{=} \sum_{z_n^1 \in \sigma_1} \frac{f_n \bar{v}_n}{z_n^1 - z}. \quad (3.11)$$

Lemma 3.2 implies that the resolvent $R_{L_{\alpha,1}}(z)$ (3.10) does not have singularities at the points $z_n^1 \in \sigma_1$ but can have singularities at zeros of the function $Q(z)$ (3.11).

The function

$$G(z) = \sum_{z_n^1 \in \sigma_1} \frac{|v_n|^2}{z_n^1 - z} \quad (3.12)$$

monotonously increases for all $z \in \mathbb{R} \setminus \sigma_1$ (since $F'(z) > 0$ for all $z \in \mathbb{R} \setminus \sigma_1$). Therefore equation $1 + \alpha F(z) = 0$, which is equivalent to $Q(z) = 0$, has only simple roots.

Lemma 3.3 *Zeros of $Q(z)$ (3.11) are real, simple and alternate with numbers $z_n^1 \in \sigma_1$ (3.7).*

Define the set

$$Q(L_{\alpha,1}) \stackrel{\text{def}}{=} \{\mu_n : Q(\mu_n) = 0\} \quad (3.13)$$

where $Q(z)$ is given by (3.11) and numbers $\mu_n = \mu(\alpha)$ depend on the parameter α . Resolvent $R_{L_{\alpha,1}}(z)$ (3.10) cannot have removable singularities at the points $\mu_n \in \sigma(L_{\alpha,1})$. Thus singularities of $R_{L_{\alpha,1}}(z)$ are the simple poles at the points $\mu_n \in \sigma(L_{\alpha,1})$.

3.2 Find eigenfunctions of the operator $L_{\alpha,1}$. Formula (3.10) implies that residue of the resolvent $R_{L_{\alpha,1}}(z)$ at the point $z = \mu_p$ is

$$c_p(f) \stackrel{\text{def}}{=} \lim_{z \rightarrow \mu_p} (\mu_p - z) R_{L_{\alpha,1}}(z) = \frac{\alpha}{Q'(\mu_p)} \sum_{z_n^1 \in \sigma_1} \frac{v_n}{z_n^1 - \mu_p} \left(\sum_{z_k^1 \in \sigma_1} \frac{f_k \bar{v}_k}{z_k^1 - \mu_p} \right) u_n. \quad (3.14)$$

Note that

$$Q'(\mu_p) = \alpha \sum_{z_n^1 \in \sigma_1} \frac{|v_n|^2}{z_n^1 - \mu_p} = \alpha G'(\mu_p) (\neq 0)$$

where $G(z)$ is given by (3.12) and $G'(\mu_p) > 0$. Define the vectors

$$\tilde{u}_p \stackrel{\text{def}}{=} \frac{1}{\sqrt{G'(\mu_p)}} \sum_{z_n^1 \in \sigma_1} \frac{v_n}{z_n^1 - \mu_p} u_n. \quad (3.15)$$

This series converges in H and $\|\tilde{u}_p\| = 1$. Moreover, \tilde{u}_p are eigenfunctions of the operator $L_{\alpha,1}$, $L_{\alpha,1}\tilde{u}_p = \mu_p\tilde{u}_p$. Really,

$$\begin{aligned} L_{\alpha,1}\tilde{u}_p &= \frac{1}{\sqrt{G'(\mu_p)}} \sum_{z_n^1 \in \sigma_1} \frac{v_n}{z_n^1 - \mu_p} z_n^1 u_n + \frac{\alpha}{\sqrt{G'(\mu_p)}} \sum_{z_n^1 \in \sigma_1} \frac{|v_n|^2}{z_n^1 - \mu_p} v \\ &= \mu_p \tilde{u}_p + \frac{1}{\sqrt{G'(\mu_p)}} Q(\mu_p) v = \mu_p \tilde{u}_p \end{aligned}$$

due to $Q(\mu_p) = 0$. Formula (3.15) implies that $c_p(f)$ (3.14) equal $c_p(f) = \langle f, \tilde{u}_p \rangle \tilde{u}_p$. Therefore resolvent $R_{L_{\alpha,1}}(z)$ (3.11) is given by

$$R_{L_{\alpha,1}}(z)f = \sum_{\mu_p \in \sigma(L_{\alpha,1})} \frac{\tilde{f}_p}{\mu_p - z} \tilde{u}_p \quad (3.16)$$

where $\tilde{f}_p = \langle f, \tilde{u}_p \rangle$ are Fourier coefficients of the vector f in the basis $\{\tilde{u}_p\}$ (3.15) of the subspace H_1 .

Lemma 3.4 *Spectrum of the operator $L_{\alpha,1}$ (3.9) is simple and coincides with the set $\sigma(L_{\alpha,1})$ (3.13). Eigenvectors of $L_{\alpha,1}$ corresponding to eigenvalues μ_p are given by (3.15) and resolvent $R_{L_{\alpha,1}}(z)$ is given by formula (3.16).*

It can turn out that a number $\mu_p \in \sigma(L_{\alpha,1})$ coincides with $z_n^0 \in \sigma_0$ (3.7), then the proper subspace of the operator L_α (3.3) is two-dimensional and is generated by the vectors $\{u_n, \tilde{u}_p\}$.

Theorem 3.1 *Spectrum of the operator L_α (3.3) is*

$$\sigma(L_\alpha) = \sigma_0 \cup \sigma(L_{\alpha,1}) \quad (3.17)$$

where σ_0 and $\sigma(L_{\alpha,1})$ are given by (3.7) and (3.13) correspondingly. Spectrum of the operator L_α is simple, excluding points belonging to $\sigma_0 \cap \sigma(L_{\alpha,1})$ where it is of multiplicity 2.

Remark 3.1 *Let the set $\sigma(L_0)$ (3.1) be such that*

$$\lim_{n \rightarrow \infty} z_n = \infty; \quad \min_{n,s} |z_n - z_s| = d > 0, \quad (3.18)$$

then the intersection $\sigma_0 \cap \sigma(L_{\alpha,1})$ is finite. Thus, when conditions (3.18) hold, the operator L_α (3.3) has finite number of points of the spectrum of multiplicity 2.

Really, if $\sigma_0 \cap \sigma(L_{\alpha,1})$ is infinite and consists of points $\{\widehat{z}_p^0\}_1^\infty$, then in view of $Q(\widehat{z}_p^0) = 0$

$$1 + \alpha \sum_{z_n^1 \in \sigma_1} \frac{|v_n|^2}{z_n^1 - \widehat{z}_p^0} = 0 \quad (\forall p).$$

Formula (3.18) and $\sum |v_n|^2 = 1$ imply that this series converges uniformly. Passing to the limit as $p \rightarrow \infty$ in this equality and taking into account (3.18), one obtains $1 = 0$ which is absurd.

Lemma 1.3 implies that the conditions (3.18) for the operator L_0 (1.1), (1.2) hold, therefore for the operator L_α (2.1) Theorem 3.1 holds and there is finite number of points in $\sigma(L_\alpha)$ of multiplicity 2.

3.3. Calculate $Q(z) = 1 + \alpha \langle R_{L_0}(z)v, v \rangle$ for the operator L_0 (1.1), (1.2). Relation (1.35) implies that

$$\langle R_{L_0}(\lambda^3)v, v \rangle = \frac{i}{\lambda^4 \Delta(0, \lambda)} \left\{ \left\langle \int_0^l [d(i\lambda(x-l))d(-i\lambda t) - d(i\lambda x)d(i\lambda(l-t))] \right\rangle \right.$$

$$\begin{aligned} & \times v(t)dt, v(x) \rangle + \left\langle d(i\lambda) \int_0^x d(i\lambda(x-t))v(t)dt, v(x) \right\rangle \\ & - \left\langle d(-i\lambda) \int_x^l d(i\lambda(x-t))v(t)dt, v(x) \right\rangle \Bigg\}. \end{aligned}$$

Taking into account (2.2), (2.5) and

$$m(\lambda) = \left\langle \int_0^x d(i\lambda(x-t))v(t)dt, v(x) \right\rangle,$$

one obtains

$$\begin{aligned} \langle R_{L_0}(\lambda^3)v, v \rangle &= \frac{i}{\lambda^4 \Delta(0, \lambda)} \{m(\lambda)d(i\lambda) - \tilde{v}_d^*(\lambda)\tilde{w}_d(-\lambda) \\ & - m^*(\lambda)d(-i\lambda) + \tilde{v}_d(\lambda)\tilde{w}_d^*(-\lambda)\} = \frac{i}{\lambda^4 \Delta(0, \lambda)} \{F(\lambda) - F^*(\lambda)\} \end{aligned}$$

where $F(\lambda)$ is given by (2.15), using (2.14), one arrives at the equality

$$\alpha \langle R_{L_0}(\lambda^3)v, v \rangle = \frac{\Delta(\alpha, \lambda) - \Delta(0, \lambda)}{\Delta(0, \lambda)}.$$

Lemma 3.5 *For the operator L_0 (1.1), (1.2), the identity*

$$Q(\lambda^3) = \frac{\Delta(\alpha, \lambda)}{\Delta(0, \lambda)} \quad (3.19)$$

where $Q(z) = 1 + \alpha \langle R_{L_0}(z)v, v \rangle$ and $\Delta(0, \lambda)$ (1.23) and $\Delta(\alpha, \lambda)$ (2.14) are characteristic functions of the operators L_0 (1.1), (1.2) and L_α (2.1).

4 Inverse problem

4.1. To obtain multiplicative expansions of characteristic functions $\Delta(0, \lambda)$ (1.23) and $\Delta(\alpha, \lambda)$ (2.14), use the well-known Hadamard theorem on factorization [9, 10].

Theorem 4.1 (Hadamard) *Let $f(z)$ be an entire function of exponential type and $\{z_n\}_1^\infty$ be a subsequence of its zeros where each zero is repeated according to its multiplicity, besides, $z_1 \neq 0$ and $0 < |z_1| \leq |z_2| \leq \dots$. Then*

$$f(z) = cz^k e^{bz} \prod_n \left(1 - \frac{z}{z_n}\right) e^{z/z_n} \quad (4.1)$$

where $k \in \mathbb{Z}_+$; $c, b \in \mathbb{C}$.

Lemma 1.3 implies that zeros of the function $\Delta(0, \lambda)$ come in triplets $\{\zeta_l \lambda_n(0)\}_{l=1}^3$ (and $\{-\zeta_l \lambda_n(0)\}_{l=1}^3$) ($\lambda_n(0) > 0$), therefore

$$\prod_{n=1}^3 \left(1 - \frac{\lambda}{\zeta_k \lambda_n(0)}\right) e^{\lambda/\zeta_k \lambda_n(0)} = 1 - \frac{\lambda^3}{\lambda_n^3(0)} \quad (4.2)$$

due to (1.4) (similarly for $\{-\zeta_l \lambda_n(0)\}$ also), and according to (4.1)

$$\Delta(0, \lambda) = c \lambda^k e^{b\lambda} \prod_n \left(1 - \frac{\lambda^6}{\lambda_n^6(0)}\right). \quad (4.3)$$

Infinite product (4.3) converges uniformly on every compact due to location of $\lambda_n(0)$ (Lemma 1.3). Taylor formula (ix) (1.10) for $d(z)$ and (1.23) imply the expansion

$$\Delta(0, \lambda) = -l^2 + \frac{2}{8} \lambda^5 l^8 + \dots \quad (4.4)$$

and thus $\Delta(0, 0) = -l^2$ ($\neq 0$) and $k = 0$, $c = -l^2$ in the formula (4.3). So,

$$\Delta(0, \lambda) = -l^2 e^{b\lambda} \prod_n \left(1 - \frac{\lambda^6}{\lambda_n^6(0)}\right).$$

Differentiating this equality and assuming that $\lambda = 0$, one obtains that $b = 0$ since $\Delta'(0, 0) = 0$ due to (4.4). Thus, multiplicative expansion of $\Delta(0, \lambda)$ is

$$\Delta(0, \lambda) = -l^2 \prod_n \left(1 - \frac{\lambda^6}{\lambda_n^2(0)}\right). \quad (4.5)$$

Property (2.16) of the characteristic function $\Delta(\alpha, \lambda)$ (2.14) yields that its roots also form triplets $\{\zeta_l \lambda_n(\alpha)\}_{l=1}^3$ ($0 = \lambda_n(\alpha) \in \mathbb{R}$) and for them equality (4.2) is true, therefore, due to Theorem 4.1,

$$\Delta(\alpha, \lambda) = c \lambda^k e^{b\lambda} \prod_n \left(1 - \frac{\lambda^3}{\lambda_n^3(\alpha)}\right). \quad (4.6)$$

This product also converges uniformly on every compact. Again using the Taylor formula (ix) (1.10) for $d(z)$, one finds series expansion of the function $F(\lambda)$ (2.15),

$$F(\lambda) = \frac{\lambda^4}{4} a_1(v) - \frac{i\lambda^7}{2 \cdot 5!} a_2(v) + \dots \quad (4.7)$$

where

$$a_1(v) = \left\langle l^2 \int_0^x (x-t)^2 v(t) dt + (l-x)^2 \int_0^l t^2 v(t) dt, v(x) \right\rangle. \quad (4.8)$$

Substituting (4.4) and (4.7) into (2.14), one finds the expansion

$$\Delta(\alpha, \lambda) = -l^2 + \alpha i 4(a_1(v) - \overline{a_1(v)}) + \frac{\lambda^3 \alpha}{2 \cdot 5!}(a_2(v) - \overline{a_2(v)}) + \dots \quad (4.9)$$

Hence (4.6) implies that $k = 0$ and

$$c = -l^2 + \frac{\alpha i}{4}(a_1(v) - \overline{a_1(v)}) \neq 0. \quad (4.10)$$

Take into account that $\Delta'(\alpha, 0) = 0$ (4.9), then (4.6) implies that $b = 0$. So,

$$\Delta(\alpha, \lambda) = c \prod_n \left(1 - \frac{\lambda^3}{\lambda_n^3(\alpha)}\right) \quad (4.11)$$

where c is given by (4.10). Further, the number c will be found in terms of spectral data.

4.2. Use equality (3.19),

$$Q(z) = \frac{\Delta(\alpha, z^{1/3})}{\Delta(0, z^{1/3})}, \quad (4.12)$$

and note that in the quotient all terms in infinite products (4.5), (4.14) which correspond to $z_n(0) = \pm \lambda_n^3(0)$ from σ_0 (3.7) reduce. Only terms corresponding to $z_n(0) = \varepsilon \lambda_n^3(0) \in \sigma_1$ (3.7) ($\varepsilon = 1$ or -1) and corresponding to it in numerator $z_n(\alpha)$ remain. So,

$$1 + \alpha \sum_{z_n \in \sigma_1} \frac{|v_p|^2}{z_n - z} = -\frac{c}{l^2} \prod_{z_n \in \sigma_1} \frac{z_n}{z_n(\alpha)} \left(1 + \frac{z_n(\alpha) - z_n}{z_n - z}\right). \quad (4.13)$$

Substituting $z = iy$ ($y \in \mathbb{R}$) and passing to the limit as $y \rightarrow \infty$, one obtains

$$1 = -\frac{c}{l^2} \prod_{z_n \in \sigma_1} \frac{z_n}{z_n(\alpha)},$$

hence once finds the number c via the spectral data

$$c = -l^2 \prod_{z_n \in \sigma_1} \left(1 + \frac{z_n(\alpha) - z_n}{z_n}\right). \quad (4.14)$$

Calculating residue at the point $z = z_n$ in both parts of the equality (4.13), one has

$$\alpha |v_p|^2 = -\frac{c}{l^2} \frac{z_p}{z_p(\alpha)} (z_p(\alpha) - z_p) \prod_{n \neq p} \frac{z_n}{z_n(\alpha)} \left(1 + \frac{z_n(\alpha) - z_n}{z_n - z_p}\right). \quad (4.15)$$

Theorem 4.2 Using the formulas (4.15), the numbers $\alpha|v_p|^2$, where c is given by (4.14), are found unambiguously from spectra $\sigma(L_0) = \{z_n\}$ and $\sigma(L_\alpha) = \{z_n(\alpha)\}$ of the operators L_0 (1.1), (1.2) and L_α (2.1).

Remark 4.1 The number α is defined by the numbers $\alpha|v_p|^2$ (4.15) from the condition $\sum |v_p^2| = 1$. Thus, $\{\alpha, |v_p|^2\}$ is unambiguously recovered by the spectra $\sigma(L_0)$ and $\sigma(L_\alpha)$.

Relation (1.28) implies that Fourier coefficient equals

$$v_p = \langle v(x), u(0, \lambda_p(0), x) \rangle = \frac{1}{u_p} \{s(-i\lambda_p(0)l)\tilde{v}_s(\lambda_p(0)) + (1 - c(-i\lambda_p(0)l))\tilde{v}_d(\lambda_p(0))\} \quad (4.16)$$

where $\tilde{v}_s(\lambda)$ and $\tilde{v}_d(\lambda)$ are given by (2.2). For the function $g(x) = l - x$, Fourier coefficients are calculated explicitly,

$$g_p = \langle g(x), u(0, \lambda_p(0), x) \rangle = \frac{il}{\lambda_p(0)} (c(-i\lambda_p(0)) - 1). \quad (4.17)$$

Theorem 4.3 The number α and the function $v(x)$ ($\|v\| = 1$) are unambiguously recovered from the spectra $\sigma(L_0)$, $\sigma(L_\alpha(v))$, $\sigma(L_\alpha(v + g))$, $\sigma(L_\alpha(v + ig))$ where $L_\alpha(v)$ is given by (2.1) and $g(x) = l - x$.

P r o o f. Theorem 4.2 implies that numbers $\alpha|v_p|^2$ are unambiguously defined by $\sigma(L_0)$ and $\sigma(L_\alpha(v))$. Exactly in the same way from $\sigma(L_0)$ and $\sigma(L_\alpha(v + g))$ one finds

$$\alpha|v_p + g_p|^2 = \alpha|v_p|^2 + 2 \operatorname{Re}(\alpha v_p \overline{g_p}) + |g_p|^2$$

where g_p are given by (4.17). Hence, the numbers $\operatorname{Re}(\alpha v_p \overline{g_p})$ are unambiguously calculated by the three spectra $\sigma(L_0)$, $\sigma(L_\alpha(v))$, $\sigma(L_\alpha(v + g))$. Similarly, from $\sigma(L_0)$, $\sigma(L_\alpha(v))$, $\sigma(L_\alpha(v + ig))$ $\operatorname{Im}(\alpha v_p \overline{g_p})$ are defined. Thus, $\alpha v_p \overline{g_p}$, and so αv_p also, are unambiguously calculated from the four spectra $\sigma(L_0)$, $\sigma(L_\alpha(v))$, $\sigma(L_\alpha(v + g))$, $\sigma(L_\alpha(v + ig))$. Finally, numbers α and v_p are found from the normalization condition $\sum |v_p|^2 = 1$. Thereafter, the function $v(x)$ is defined by its Fourier series,

$$v(x) = \sum_p v_p u(0, \lambda_p(0), x). \quad \blacksquare$$

4.3. Proceed to description of the data of inverse problem. Denote by σ_1 a subset in $\sigma(L_0) = \{z_n(0, \varepsilon) = \varepsilon \lambda_n^3(0) : \Delta(0, \lambda_n(0)) = 0, \varepsilon = \pm 1\}$,

$$\sigma_1 \stackrel{\text{def}}{=} \{z_n^1(0, \varepsilon) : z_n^1(0, \varepsilon) \in \sigma(L_0)\} \quad (4.18)$$

where the numbers $z_n^1(0, \varepsilon)$ are enumerated in ascending order (the case of $\sigma_1 = \sigma(L_0)$ is not excluded). And let

$$\sigma_0 \stackrel{\text{def}}{=} \sigma(L_0) \setminus \sigma_1 = \{z_n^0(0, \varepsilon) : z_n^0(0, \varepsilon) = \sigma(L_0)\}. \quad (4.19)$$

Consider the set

$$\sigma(\mu) \stackrel{\text{def}}{=} \{\mu_n \in \mathbb{R} : n \in \mathbb{N}\} \quad (4.20)$$

assuming that sets $\sigma(\mu)$ and σ_1 interlace, moreover, μ_k are enumerated in ascending order, $\mu_k \neq \mu_s$ ($k \neq s$), $\mu_1 \neq 0$ ($\sigma(\mu) \cap \sigma(1) = \emptyset$).

Condition 1 *The intersection $\sigma(\mu) \cap \sigma_0$ is finite.*

Since the number c (4.14) is finite, then one arrives at the second condition.

Condition 2 *The sets σ_1 and $\sigma(\mu)$ are such that the series*

$$\sum_n \ln \left(1 + \frac{\mu_n - z_n^1(0, \varepsilon)}{z_n^1(0, \varepsilon)} \right) < \infty \quad (4.21)$$

which is equivalent to the convergence of the product

$$\prod_n \left(1 + \frac{\mu_n - z_n^1(0)}{z_n^1} \right). \quad (4.22)$$

Numbers $v_p \in l^2(\mathbb{N})$, therefore the following requirement is natural, due to (4.15).

Condition 3 *The numerical series*

$$\sum_p \frac{z_p^1(0, \varepsilon)}{\mu_p} (\mu_p - z_p^1(0, \varepsilon)) \left[\prod_{n \neq p} \frac{z_n^1(0, \varepsilon)}{\mu_n} \left(1 + \frac{\mu_n - z_n^1(0, \varepsilon)}{z_n^1(0) - z_p^1(0, \varepsilon)} \right) \right] < \infty \quad (4.23)$$

converges.

Form the infinite product

$$b_{\sigma_1}(z) \stackrel{\text{def}}{=} \prod_{z_n^1 \in \sigma_1} \left(1 - \frac{z}{z_n^1(0, \varepsilon)} \right) \quad (4.24)$$

converging in any circle $C_R = \{z \in \mathbb{C} : |z| < R\}$ due to $z_n \in \sigma(L_0)$. Similarly, set

$$b_{\sigma(\mu)}(z) \stackrel{\text{def}}{=} \prod_{z_n^1 \in \sigma_1} \left(1 - \frac{z}{\mu_n} \right). \quad (4.25)$$

Consider a meromorphic function

$$Q(z) = k \frac{b_{\sigma(\mu)}(z)}{b_{\sigma_1}(z)} \quad (k \in \mathbb{R}).$$

Residue of $Q(z)$ at the point $z_p^1(0, \varepsilon)$ equals

$$c_p = \lim_{z \rightarrow z_p^1(0)} (z_p^1(0, \varepsilon) - z)Q(z) = kz_p^1(0) \frac{b_{\sigma(\mu)}(z_n^1(0, \varepsilon))}{\prod_{n \neq p} \left(1 - \frac{z_p^1(0, \varepsilon)}{z_n^1(0, \varepsilon)}\right)}. \quad (4.26)$$

Remark 4.2 *Interlacing of sequences $z_n^1(0)$ and μ_n implies that all the numbers c_p are of the same sign, $\text{sign } c_p = \text{sign } c_1$ ($\forall p$).*

If Condition 3 is met, then defining the number

$$\frac{1}{\alpha} \stackrel{\text{def}}{=} \sum_p \frac{z_p^1(0, \varepsilon)}{\mu_p} (\mu_p - z_p^1(0, \varepsilon)) \prod_{n \neq p} \frac{z_n^1(0, \varepsilon)}{\mu_n} \left(1 + \frac{\mu_n - z_n^1(0, \varepsilon)}{z_n^1(0) - z_p^1(0, \varepsilon)}\right)$$

one obtains that the numbers

$$|v_p|^2 \stackrel{\text{def}}{=} \frac{c_p}{\alpha} \quad (p \in \mathbb{N})$$

are positive and $\sum |v_p|^2 = 1$.

Theorem 4.4 *Let σ be a countable set on \mathbb{R} and $\sigma = \sigma_0 \cup \sigma(\mu)$ where $\sigma_0 \subset \sigma(L_0)$ (4.19) ($\sigma(L_0) = \{z_n(0, \varepsilon) = \varepsilon \lambda_n^3(0) : \Delta(0, \lambda_n(0)) = 0, \varepsilon = \pm 1\}$) and $\sigma(\mu)$ (4.20) consists of pairwise different points μ_n ($\mu_1 \neq 0$), $n \in \mathbb{N}$, enumerated in ascending order and interlacing with $z_n^1(0, \varepsilon) \in \sigma_1 = \sigma(L_0) \setminus \sigma_0$ and $\sigma_1 \cap \sigma(\mu) = \emptyset$.*

In order that σ coincide with the spectrum $\sigma(L_\alpha)$ of the operator L_α (2.1) it is necessary and sufficient that

- (a) $\sigma(\mu) \cap \sigma_0$ is finite;
- (b) the series

$$\sum \ln \left(1 + \frac{\mu_n - z_n^1(0, \varepsilon)}{z_n^1(0, \varepsilon)} < \infty\right);$$

$$\sum_p \frac{z_p^1(0, \varepsilon)}{\mu_p} (\mu_p - z_p^1(0, \varepsilon)) \prod_{n \neq p} \left(\frac{\mu_n - z_p^1(0, \varepsilon)}{z_n^1(0) - z_p^1(0, \varepsilon)}\right) < \infty \quad (4.27)$$

converge.

Description of the spectrum $\sigma(L_\alpha)$ of the operator L_α (2.1) one can give in terms of characterization of the class of functions $\Delta(\alpha, \lambda)$ that are characteristic for L_α [7].

References

- [1] B. M. Levitan, *Inverse Sturm – Liouville problems*, Utrecht, The Netherlands, VNU Science Press, 1987, 240 pp.
- [2] V. Marchenko, *Sturm-Liouville Operators and Applications* Ser. “Operator Theory: Advances and Applications”, Vol. 22, Birkhäuser Basel, 1986, xi + 367 pp.
- [3] M. A. Naimark, *Linear Differential Operator: Two Volumes Bound As One* (Dover Books on Mathematics), Dover Publications, 2014, 528 pp.
- [4] J. Kohlenberg, H. Lundmark, J. Szmigielski, “The inverse spectral problem for the discrete cubic string”, *Inverse Problems*, 23 (2007), 99 – 121.
- [5] K. Chadan, P. C. Sabatier, *Inverse Problems in Quantum Scattering Theory* Ser. “Theoretical and Mathematical Physics”, Springer-Verlag Berlin Heidelberg, 1977, xxii + 346 pp.
- [6] V. A. Zolotarev, “Direct and inverse problems for an operator with non-local potential”, *Sbornik: Mathematics*, 203:12 1785 - 1807.
- [7] V. A. Zolotarev, “Inverse spectral problem for the operators with non-local potential”, *Mathematische Nachrichten*, 2019, 292:3, 661 – 681.
- [8] L. Nizhnik, “Inverse spectral nonlocal problem for the first order ordinary differential equation”, *Tamkang Journal of Mathematics*, 42:3 (2001), 385 – 394.
- [9] B. Ya. Levin, *Lectures on entire functions*, American Mathematical Society (Translations of Mathematical Monographs Vol 150), 1997.
- [10] P. Koosis, *The logarithmic integral. I.*, University Press, Cambridge, 1980.