

FPGA deep learning acceleration based on convolutional neural network*

1st Xiong Jun

(Chongqing University)

School of Microelectronics and Communication Engineering

Chongqing, China

923253779@qq.com

Abstract—In view of the large amount of calculation and long calculation time of convolutional neural network (CNN), this paper proposes a convolutional neural network hardware accelerator based on field programmable logic gate array (FPGA). First, through in-depth analysis of the forward operation principle of the convolutional layer and exploration of the parallelism of the convolutional layer operation, a hardware architecture of input channel parallelism, output channel parallelism and convolution window deep pipeline is designed. Then in the above architecture, a fully parallel multiplication-addition tree module is designed to accelerate the convolution operation and an efficient window buffer module to implement the pipeline operation of the convolution window. The final experimental results show that the energy efficiency ratio of the accelerator proposed in this article reaches 32.73 GOPS/W, which is 34% higher than the existing solution, and the performance reaches 317.86 GOPS.

Index Terms—convolutional neural network, hardware acceleration, field programmable logic gate array, computational parallelism, deep pipeline

I. INTRODUCTION

In recent years, Convolutional Neural Network (CNN) has been widely used in the field of artificial intelligence [1]. However, while CNN is constantly approaching the limit of task accuracy, its network depth and the number of parameters are also growing rapidly, which consumes more and more computing resources and memory resources [2].

Currently, there are three main platforms for accelerating convolutional neural networks: Graphics Processing Unit (GPU). Its software programmable and multi-CUDA architecture are very suitable for accelerating convolutional neural networks, but its significant power consumption makes it difficult Integrated into embedded platforms with limited power consumption [3]; Application-Specific Integrated Circuit (ASIC), which has the characteristics of high performance and low power consumption, but has a long design cycle and high manufacturing costs [4]; Field-Programmable Gate Array (FPGA), with the characteristics of low power consumption and high flexibility, has become the most popular platform for studying convolutional neural network hardware acceleration.

The research of FPGA-based convolutional neural network accelerator design mainly focuses on parallel computing and memory bandwidth optimization. In terms of parallel computing, Motamedi et al. [5] summarized the convolutional

layer parallel computing optimization method in detail, and proposed three parallel computing methods: parallel between outputs, parallel between convolution kernels, and parallel within convolution kernels. If the area, bandwidth, and on-chip storage of the FPGA are not limited, theoretically all the above methods can be used to speed up the neural network to the maximum, but in practice it is impossible. Therefore, the challenge is to study the best combination of multiple parallel mechanisms. In terms of memory bandwidth optimization, Zhang et al. [6] first store the input feature map and weight data in BRAM, and then read the data from it for convolution operation. Although the weight data is reused, the input feature map is not used. The convolution window is reused, and the memory utilization is not high. In addition, all the above designs use a large number of classic addition tree units in parallel computing, which requires a large bandwidth and takes up a lot of resources.

In order to solve the above problems, this paper has completed the following research work:

- Analyze the feasibility of parallel acceleration of the convolutional layer, and propose three parallel computing methods: intra-convolution, input channel parallel, and output channel parallel;
- A new addition tree design method is proposed, a fully parallel multiplication-addition tree module is designed, which reduces computing resources and memory resources and maintains the same computing performance;
- Pipeline operation is adopted for the convolution window, and the designed efficient window buffer module generates a convolution window every clock cycle, thereby improving the performance of pipeline;
- A convolutional layer hardware accelerator is designed, which performs pipeline operations on input channel parallelism, output channel parallelism, and convolution window, which greatly improves computing performance.

II. RELATED WORK

The calculation in the convolutional neural network is mainly concentrated in the convolutional layer [7], Fig.1 shows the overall process of the convolutional layer operation.

The input feature map X in Fig.1 is a three-dimensional matrix whose shape is $[N, H, W]$, where N is the number




Fig. 1. Convolutional layer operation process.

of channels of the input feature map, and H and W are the height and width of the input feature map, respectively. The convolution kernel W is a 4-dimensional matrix whose shape is $[M, N, H_k, W_k]$, where M is the number of convolution kernels, N is the number of channels of the convolution kernel, that is, the number of channels of the input feature map, and the height and width of the H_k and W_k convolution kernels. The vertical and horizontal steps of the convolution kernel are H_s and W_s respectively. The offset is a 1-dimensional vector of length M , denoted as b . The output feature map O is a 3-dimensional matrix whose shape is $[M, H_o, W_o]$, where M is the number of channels of the output feature map, that is, the number of convolution kernels, and H_o and W_o are the height and width of the output feature map, respectively. The relation is

$$H_o = \lfloor \frac{H - H_k}{H_s} \rfloor + 1 \quad (1)$$

$$W_o = \lfloor \frac{W - W_k}{W_s} \rfloor + 1 \quad (2)$$

Convolution output feature map m channel i' row j' column data $O_{mi'j'}$ satisfy

$$O_{mi'j'} = \sum_{n=1}^N \sum_{i=1}^{H_k} \sum_{j=1}^{W_k} X_{n(i+(i'-1)H_s)(j+(j'-1)W_s)} \quad (3)$$

If the channel size of a certain convolution kernel is 3×3 , the channel size of the input feature map is 5×5 , and the step size in both the vertical and horizontal directions is 2, then it obtains the output channel component of the size 2×2 .

III. MATH

A. Feasibility analysis of convolutional layer parallel acceleration

Since each convolution window has the same operation method, for the convolution window located in the upper left

corner of the input feature map, namely $i' = 1, j' = 1$, equation (3) can be rewritten as

$$O_m = \sum_{n=1}^N \sum_{i=1}^{H_k} \sum_{j=1}^{W_k} X_{nij} W_{mnij} + b_m \quad (4)$$

Among them, $m \in [1, M]$, the output value corresponding to the convolution window has M , respectively O_1, O_2, \dots, O_M . Fig.2 is a schematic diagram of the above calculation process.




Fig. 2. Parallel calculation of convolution windows for N input channels.

According to equation (4), let

$$a_{mn} = \sum_{i=1}^{H_k} \sum_{j=1}^{W_k} X_{nij} W_{mnij} \quad (5)$$

Then there is

$$O_m = \sum_{n=1}^N a_{mn} + b_m \quad (6)$$

To calculate the values of O_1, O_2, \dots, O_M and M , the following two methods can be used:

(1) From equation (6), we can first calculate $a_{m1}, a_{m2}, \dots, a_{mN}$, then sum the numbers of N and add b_m to get O_m . Let m take $[1, M]$, then O_1, O_2, \dots, O_M can be calculated.

(2) It can be seen from equation (6),

$$O = \begin{bmatrix} O_1 \\ O_2 \\ \vdots \\ O_M \end{bmatrix} = \begin{bmatrix} a_{11} \\ a_{21} \\ \vdots \\ a_{M1} \end{bmatrix} + \begin{bmatrix} a_{12} \\ a_{22} \\ \vdots \\ a_{M2} \end{bmatrix} + \dots + \begin{bmatrix} a_{1N} \\ a_{2N} \\ \vdots \\ a_{MN} \end{bmatrix} + \begin{bmatrix} b_1 \\ b_2 \\ \vdots \\ b_M \end{bmatrix} = \hat{O}_1 + \hat{O}_2 + \dots + \hat{O}_N + b \quad (7)$$

Among them, \hat{O}_n is the n component of the convolution output O , which satisfies

$$\hat{O}_n = \begin{bmatrix} a_{1n} \\ a_{2n} \\ \vdots \\ a_{Mn} \end{bmatrix} \quad (8)$$

Among them, $n \in [1, M]$.

As shown in Fig.3, using M accumulators, first find $a_{11}, a_{21}, \dots, a_{M1}$ and store them in M registers respectively, then find and accumulate $a_{12}, a_{22}, \dots, a_{M2}$, find and accumulate $a_{1N}, a_{2N}, \dots, a_{MN}$ at the N time, and finally add offset b_1, b_2, \dots, b_M , you can find O_1, O_2, \dots, O_M .




Fig. 3. Accumulator parallel operation.

It can be seen that there are 3 parts that can be calculated in parallel in the convolutional layer:

(1) In equation (5), $H_k W_k$ multiplications can be calculated in parallel. Parallel is located inside the convolution kernel, which is called intra-convolution parallel;

(2) In equation (6), when calculating the m convolution output O_m , the convolution of the corresponding N input channels can be calculated in parallel, and the $a_{m1}, a_{m2}, \dots, a_{mN}$ and N intermediate results can be obtained. Finally, the N values are summed to get O_m . This is the input channel parallel;

(3) In equation (7), when calculating the n component of the convolution output O , the convolution of the n input channel and the corresponding channel in the M convolution kernel can be calculated in parallel, which is the parallel output of the output channels.

B. Basic module design

1) *Fully parallel multiplication-addition tree module:* It can be seen from equation (3) that each convolution window of each output channel of the convolution operation contains $N \times H_k \times W_k$ multiplications, so the entire convolution layer has $M \times G \times N \times H_k \times W_k$ multiplications. The corresponding summation symbol in equation (3) is the addition calculation. And each window of each output channel needs to sum the number of $N \times H_k \times W_k + 1$, so the entire convolutional layer needs to sum the number of $M \times G \times (N \times H_k \times W_k + 1)$.

Therefore, such multiplication and addition operations must be optimized in parallel. The shape of the convolution kernel is generally square. Assuming the size of the convolution kernel is $W_k = H_k = K$, the convolution output y can be obtained by equation (3)

$$y = \sum_{i=1}^K \sum_{j=1}^K x_{ij} w_{ij} \quad (9)$$

It can be seen from equation (9) that the operation includes K^2 multiplication operations and K^2 number addition operations. For K^2 multiplication operations, K^2 multipliers are used for full parallel calculation; for the addition of K^2 numbers, in hardware acceleration design, the classic addition tree is generally used to achieve [8], this addition tree first passes the input number. The way of filling 0 is expanded from K^2 to $2^{\lceil \log_2(K^2) \rceil}$, and then the sum of every two numbers is used as the input of the second layer. In this way, it is accumulated step by step until the final layer gets the sum. Fig.4 shows the structure of this design for $K = 3$.




Fig. 4. Classic addition tree.

Although this addition tree structure greatly improves the parallelism of addition, it also has the following two disadvantages:

(1) Consume too many hardware resources For the addition of the number of η , the number of adders required by this addition tree is $f_1(\eta)$, the number of registers required is $g_1(\eta)$, and the required clock cycle $h_1(\eta)$ is respectively

For example, for the addition operation of 144 numbers and 256 numbers, this kind of addition tree requires that the number of adders is 255, the number of registers is 511, and the clock cycle is 8. It can be seen that in the above two cases, although the number of addition inputs is different, they consume the same number of adders, registers, and clock cycles. Obviously, this method wastes computing resources

and memory resources when the number of addition inputs is slightly larger than the power of two.

(2) Large bandwidth demand

When $K = 12$, the number of data that the classical addition tree needs to be calculated at the same time is increased from 144 to 256, and the bandwidth requirement is almost doubled.

In view of the above problems, the improvement of the additive tree designed in this paper is as follows:

(1) If the number of inputs in the current layer is even, it can be the same as the classic addition tree, adding every two numbers;

(2) If the number of inputs of the current layer is odd, first use the method (1) for parallel calculation for the even number, and finally output the remaining addend directly to the next layer.

This kind of addition tree does not need to add 0, that is, additional memory, and does not need an additional adder, and the required clock cycle is the same as the classic method. For the addition of 9 numbers, the addition tree designed in this article is shown in Fig.5.




Fig. 5. Addition tree.

It can be seen from Fig.5 that for the addition of 9 numbers, the addition tree designed in this article requires 8 adders, 20 registers, and 4 clock cycles. The corresponding classic addition tree requires 15 adders, 31 registers, and a calculation clock cycle of 4.

Suppose the number of inputs in the additive tree is η , then the number of inputs in the next layer is $\lceil \eta/2 \rceil$, and so on.

The operation steps of the multiplication-addition tree module are:

(1) Store the input feature map matrix and the convolution kernel weight matrix in the buffer area, which are called input buffer and weight buffer respectively;

(2) Read data from the input buffer and weight buffer, and use K^2 multipliers to calculate the K^2 multiplications in equation (9) in parallel to obtain K^2 intermediate results;

(3) Finally, use the method of designing the addition tree in this paper to build an addition tree with the number of addition inputs K^2 . The input of the addition tree is the K^2 intermediate results obtained in (2), and the output is the final result of the multiplication-addition module.

2) *Efficient window cache module*: According to equation (3), it can be seen that when the convolution layer is calculated, many convolution windows are generated. From equation (1) and equation (2), it can be seen that the number of convolution windows generated is $G = H_0W_0$. Suppose the size of the convolution kernel is $W_k = H_k = K$, and the shape of a channel matrix x of the input feature map is $[H, K]$, let

$$x = \begin{bmatrix} x_{11} & x_{12} & \cdots & x_{1W} \\ x_{21} & x_{22} & \cdots & x_{2W} \\ \vdots & \vdots & \ddots & \vdots \\ x_{H1} & x_{H2} & \cdots & x_{HW} \end{bmatrix} \quad (10)$$

For the convenience of explanation, the subscript of matrix x becomes continuous, that is, the subscript of the element in row i and column j is $j+(i-1)$, then matrix x is re-expressed as

$$x = \begin{bmatrix} x_1 & x_2 & \cdots & x_W \\ x_{W+1} & x_{W+2} & \cdots & x_{2 \times W} \\ \vdots & \vdots & \ddots & \vdots \\ x_{(H-1)W+1} & x_{(H-1)W+2} & \cdots & x_{H \times W} \end{bmatrix} \quad (11)$$

Definition $x_{(i)}$ represents the i convolution window, where $i \in [1, G]$. As shown in Fig.6, the data in the second to the K column of $x_{(1)}$ and the first to the $K-1$ column of $x_{(2)}$ are exactly the same. The first convolution window and the second convolution window all have $2 \times K \times K$ data, and the shared data has $2 \times K \times (K-1)$ so the data repetition ratio is $(K-1)/K$, and when the value of K is greater, the data between the two windows is repeated. The proportion is also larger.




Fig. 6. Convolution window data reuse.

If hardware parallelism is used for all convolution windows, too much computing resources will be consumed. Therefore, this article considers pipelining the convolution window, which can greatly reduce storage resources and computing resources. These convolution windows use the same circuit structure, and input different convolution window data at different times to obtain convolution operation results. In order to pipelining the convolution window, this paper designs a window buffer module, which consists of two 2-dimensional registers, one of which is the window buffer register WINDOW_BUFFER, the other is the shift register SHITF_BUFFER, as shown in Figure 7 for the window Schematic diagram of the cache structure.

As can be seen from Fig.7, the storage size of WINDOW_BUFFER is $K \times K$, and the storage size of




Fig. 7. Window cache structure.

SHIFT_BUFFER is $(K - 1) \times (W - K)$, and the following 5 steps are performed in parallel in each clock cycle:

- (1) Input a piece of data from the input buffer INPUT_BUFFER to the first column of row K of WINDOW_BUFFER;
- (2) WINDOW_BUFFER performs right shift operation every time;
- (3) The data in the second column to the K row of WINDOW_BUFFER is assigned to all the rows of the first column of SHIFT_BUFFER;
- (4) SHIFT_BUFFER right shift operation for each line;
- (5) The data in the last column of SHIFT_BUFFER is assigned to the first column from row 1 to row $K - 1$ of WINDOW_BUFFER.

Fig.8 shows the timing diagram of the above steps. The data in the WINDOW_BUFFER register in the previous $(K - 1) \times W + K - 1$ clock cycle is invalid, which is called the invalid area, which defines the invalid clock cycle $T_u = (K - 1) \times W + K - 1$; at the $T_u + 1$ clock cycle, the data stored in WINDOW_BUFFER is $x_{(1)}$; After another clock cycle, the data stored in WINDOW_BUFFER is $x_{(2)}$; and so on, when the $K \times W$ clock cycle, the data stored in WINDOW_BUFFER is $x_{(W_0)}$; finally, at the $H \times W$ clock cycle, WINDOW_BUFFER is stored The data is the last convolution window, which is $x_{(H_0 W_0)}$.




Fig. 8. Window cache structure.

From the Fig.8 and the previous analysis, we can see that the window buffer module designed in this article can generate a convolution window for subsequent operations in each clock cycle, which is the most efficient window pipeline method.

IV. EXPERIMENT

A. Experiment environment

In this experiment, a multi-layer convolutional neural network was trained on the GPU platform to classify the MNIST data set [9], and then accelerated forward inference was implemented on the FPGA platform. The FPGA platform used is the Cyclone V (5CGXFC9D6F27C7) development board developed by ALTERA, which contains DDR3 SDRAM with

a maximum bandwidth of 2GB/s and a capacity of 1GB. And through the PLL frequency multiplication, the FPGA operating frequency is increased to 100 MHz. The used neural network structure parameters are shown in Tab I.

In addition, comparative tests were conducted on CPU and GPU. The CPU and GPU software codes all use the TensorFlow [10] deep learning framework, and the underlying operation code is C++. The CPU uses Intel(R) CoreTM i7-7700, the main frequency is 3.6GHz; the GPU uses NVIDIA GTX1080Ti, the peak double-precision floating-point computing performance is 5.75TFLOPS, the peak single-precision floating-point computing performance is 11.5TFLOPS, and the memory capacity It is 11 GB, the memory bandwidth is 484 GB/s, the number of CUDA cores is 3584, and the core frequency is 1.582 GHz.

B. Experimental results

The resource consumption on FPGA circuit board is shown in Tab II. The DSP resource consumption in Tab II is more, mainly because more multipliers are used in the convolution operation.

As shown in Fig. 9 when only one picture is used for forward inference, that is, when the batch size is 1, FPGA is about 40.4 times faster than CPU and about 33.52 times faster than GPU. As the batch size increases, FPGAs are still more than 7.8 times faster than CPUs. But when the batch size is increased to more than 64, the advantage of GPU is highlighted, because GPU computing is characterized by large bandwidth, which can meet the simultaneous parallel computing of multiple pictures. However, in the task of real-time video detection on embedded platforms, the processing of pictures one by one, that is, when the batch size is 1, the advantage of FPGA is very obvious, and the power consumption is much lower than that of GPU, which is more suitable for practical applications. use.




Fig. 9. FPGA, CPU, GPU performance comparison.

Tab III compares the results with other convolutional neural network FPGA implementations. Since the literature uses

TABLE I
CONVOLUTIONAL NEURAL NETWORK STRUCTURE PARAMETERS

Layer name	Layer structure	Parameter amount
Convolutional layer 1	Convolution kernel size 3×3, number of convolution kernel 15, step size 1	150
Active layer 1	No	0
Pooling layer 1	Pooling size 2×2, step size 2	0
Convolutional layer 2	Convolution kernel size 6×6, number of convolution kernels 20, step size 1	10820
Active layer 2	No	0
Pooling layer 2	Pooling size 2×2, step size 2	0
Fully connected layer	Number of output neurons 10	3210

TABLE II
FPGA RESOURCE CONSUMPTION

	Resources	Proportion(%)
ALMs	89423/113560	79
Block Memory	730151/12492800	6
DSPs	342/342	100

different FPGA devices and different network structures, if only performance is used as a reference index, it will lack fairness, so it also increases the power efficiency. Parameters for comprehensive comparison of acceleration effects.

It can be seen from Tab III that the energy efficiency ratio of the accelerator designed in this paper reaches 32.73 GOPS/W, which is better than the other three schemes, and is 34% higher than the best implementation method in the existing literature [11]. In addition, its acceleration performance has reached 317.86 GOPS. Compared with literature [7] and literature [11], the acceleration effect is obvious, but there are still some gaps in performance compared with literature [12]. The reason is that the FPGA platform used in this article has a DSP resource ratio Other platforms are much less, and the number of DSPs is one of the key factors to improve accelerator performance. Although limited by resources, the test platform did not give full play to the optimal performance of the accelerator designed in this paper. However, the existing results have shown that the accelerator implemented in this paper has a high energy efficiency ratio and good acceleration performance.

V. CONCLUSION

This article deeply analyzes the principle and feasibility of parallel acceleration of convolutional layers Performance, re-designed the addition tree module, combined with the multiplication design A universal fully parallel multiplication-addition tree module, and then designed The efficient window cache module pipelines the convolution window, And designed an acceleration scheme with parallel input channels and parallel output channels Accelerate the convolution operation and finally build a complete forward inference Convolutional neural network FPGA accelerator. Through experimental analysis, this article The designed accelerator energy efficiency ratio reaches 32.73 GOPS/W, which is higher than the existing The solution is 34% higher. Show that the convolutional neural network implemented in this article Network hardware

accelerator has a high energy efficiency ratio, which is very suitable for Embedded platform.

REFERENCES

- [1] LIU Weibo, WANG Zidong, LIU Xiaohui, et al. A survey of deep neural network architectures and their applications[J]. *Neurocomputing*, 2017, 234: 11–26. doi: 10.1016/j.neucom.2016.12.038.
- [2] HAN Song, MAO Huizi, and DALLY W J. Deep compression: Compressing deep neural networks with pruning, trained quantization and huffman coding[J]. *arXiv preprint arXiv: 1510.00149*, 2015.
- [3] COATES A, HUVAL B, WANG Tao, et al. Deep learning with COTS HPC systems[C]. *Proceedings of the 30th International Conference on International Conference on Machine Learning*, Atlanta, USA, 2013: III-1337–III-1345.
- [4] JOUPPI N P, YOUNG C, PATIL N, et al. In-datacenter performance analysis of a tensor processing unit[C]. *Proceedings of the 44th Annual International Symposium on Computer Architecture*, Toronto, Canada, 2017: 1–12. doi: 10.1145/3079856.3080246.
- [5] MOTAMED M, GYSEL P, AKELLA V, et al. Design space exploration of FPGA-based deep convolutional neural networks[C]. *Proceedings of the 21st Asia and South Pacific Design Automation Conference*, Macau, China, 2016:575–580. doi: 10.1109/ASPDAC.2016.7428073.
- [6] ZHANG Jialiang and LI Jing. Improving the performance of OpenCL-based FPGA accelerator for convolutional neural network[C]. *Proceedings of 2017 ACM/SIGDA International Symposium on Field-Programmable Gate Arrays*, Monterey, USA, 2017: 25–34. doi: 10.1145/3020078.3021698.
- [7] QIU Jiantao, WANG Jie, YAO Song, et al. Going deeper with embedded FPGA platform for convolutional neural network[C]. *Proceedings of 2016 ACM/SIGDA International Symposium on Field-Programmable Gate Arrays*, Monterey, USA, 2016: 26–35. doi: 10.1145/2847263.2847265.
- [8] YU Qi. Deep learning accelerator design and implementation based on FPGA[D]. [M],University of Science and Technology of China, 2016: 30–38.
- [9] LECUN Y, BOTTOU L, BENGIO Y, et al. Gradient-based learning applied to document recognition[J]. *Proceedings of the IEEE*, 1998, 86(11): 2278–2324. doi: 10.1109/5.726791.
- [10] ABADI M, BARHAM P, CHEN Jianmin, et al. Tensorflow:A system for large-scale machine learning[C]. *Proceedings of the 12th USENIX Conference on Operating Systems Design and Implementation*, Savannah, USA, 2016: 265–283.
- [11] XIAO Qingcheng, LIANG Yun, LU Liqiang, et al. Exploring heterogeneous algorithms fo accelerating deep convolutional neural networks on FPGAs[C]. *Proceedings of the 54th Annual Design Automation Conference*, Austin,USA, 2017: 62. doi: 10.1145/3061639.3062244.
- [12] SHEN Junzhong, HUANG You, WANG Zelong, et al.Towards a uniform template-based architecture for accelerating 2D and 3D CNNs on FPGA[C]. *Proceedings of the 2018 ACM/SIGDA International Symposium on Field Programmable Gate Arrays*, Monterey, USA, 2018: 97–106. doi: 10.1145/3174243.3174257.

TABLE III
COMPARED WITH LITERATURE FPGA HARDWARE ACCELERATION

	Document [7]	Document [11]	Document [12]	The method of this paper
FPGA	ZynqXC7Z045	ZynqXC7Z045	Virtex-7 VX690T	Cyclone V 5CGXF
Frequency (MHz)	150	100	150	100
DSP resources	780	824	1376	342
Quantitative strategy	16 bit fixed	16 bit fixed	16 bit fixed	16 bit fixed
Power consumption (W)	9.630	9.400	25.000	9.711
Performance (GOPS)	136.97	229.50	570.00	317.86
Energy efficiency ratio (GOPS/W)	14.22	24.42	22.80	32.73