

Matrix Representation of Time-Delay Interferometry

Massimo Tinto*

*University of California San Diego, Center for Astrophysics and Space Sciences,
9500 Gilman Dr, La Jolla, CA 92093, U.S.A. and*

Divisão de Astrofísica, Instituto Nacional de Pesquisas Espaciais, S. J. Campos, SP 12227-010, Brazil

Sanjeev Dhurandhar†

Inter University Centre for Astronomy and Astrophysics, Ganeshkhind, Pune, 411 007, India

Prasanna Joshi‡

IISER, Pashan, Pune, 411 008, India

(Dated: May 6, 2021)

Time-Delay Interferometry (TDI) is the data processing technique that cancels the large laser phase fluctuations affecting the one-way Doppler measurements made by unequal-arm space-based gravitational wave interferometers. By taking finite linear combinations of properly time-shifted Doppler measurements, laser phase fluctuations are removed at any time t and gravitational wave signals can be studied at a requisite level of precision.

In this article we show the delay operators used in TDI can be represented as matrices acting on arrays associated with the laser noises and Doppler measurements. We show here that the matrix formulation is nothing but the group theoretic representation of the earlier approach involving time-delay operators and so in principle is the same. To understand the potential advantages the matrix representation brings, care must be taken by the data analyst to account for the light travel times when linearly relating the one-way Doppler measurements to the laser noises. This is especially important in view of the future gravitational wave projects envisaged. We show that the matrix formulation of TDI results in the cancellation of the laser noises at an arbitrary time t by only linearly combining a finite number of samples of the one-way Doppler data measured at and around time t .

I. INTRODUCTION

Interferometric detectors of gravitational waves with frequency content $0 < f < f_0$ may be thought of as optical configurations with one or more arms folding coherent trains of electromagnetic waves (or beams) of nominal frequency $\nu_0 \gg f_0$. At points where these intersect, relative fluctuations of frequency or phase are monitored (homodyne detection). Frequency fluctuations in a narrow Fourier band can alternatively be described as fluctuating sideband amplitudes. Interference of two or more beams, produced and monitored by a (nonlinear) device such as a photo detector, exhibits these sidebands as a low frequency signal again with frequency content $0 < f < f_0$. The observed low frequency signal is due to frequency variations of the sources of the beams about ν_0 , to relative motions of the sources and any mirrors (or amplifying microwave or optical transponders) that do any beam folding, to temporal variations of the index of refraction along the beams, and, according to general relativity, to any time-variable gravitational fields present, such as the transverse traceless metric curvature of a passing plane gravitational wave train. To observe these gravitational fields in this way, it is thus necessary to control, or monitor, the other sources of relative frequency fluctuations, and, in the data analysis, to optimally use algorithms based on the different characteristic interferometer responses to gravitational waves (the signal) and to the other sources (the noise).

By comparing phases of split beams propagated along equal but non-parallel arms, frequency fluctuations from the source of the beams are removed directly at the photo detector and gravitational wave signals at levels many orders of magnitude lower can be detected. Especially for interferometers that use light generated by presently available lasers, which display frequency stability roughly a few parts in 10^{-13} in the millihertz band, it is essential to remove these fluctuations when searching for gravitational waves of dimensionless amplitude smaller than 10^{-21} .

Space-based, two-arm interferometers [1–5] are prevented from canceling the laser noise by directly interfering the beams from the two unequal arms at a single photo detector because laser phase fluctuations experience different delays. As a result, two Doppler data from the two arms are measured at two different photo detectors and are then

* mtinto@ucsd.edu

† sanjeev@iucaa.in

‡ joshi.prasanna@students.iiserpune.ac.in

digitally processed to compensate for the inequality of the arms. This data processing technique, called Time-Delay Interferometry (TDI) [6], entails time-shifting and linearly combining the two Doppler measurements so as to achieve the required sensitivity to gravitational radiation.

In a recent article [7], a data processing alternative to TDI has been proposed for the two-arm configuration. This technique, which has been named TDI- ∞ (as it cancels the laser noise at an arbitrary time t by linearly combining all the Doppler measurements made up to time t), relies on an identified linear relationship between the two Doppler measurements made by an unequal-arm Michelson interferometer and the laser noise. Based on this formulation, TDI- ∞ cancels laser phase fluctuations by applying linear algebra manipulations to the Doppler data. Through its implementation, TDI- ∞ is claimed to (i) simplify the data processing for gravitational wave signal searches in the laser-noise-free data over that of TDI, (ii) work for any time-dependent light-time delays, and (iii) automatically handle data gaps.

After briefly reviewing the TDI- ∞ technique for the two unequal-arm configuration, we show care must be taken to account for the light-travel-times when linearly relating the two-way Doppler measurements to the laser noise [7]. The two-way Doppler data at a time t is the result of the interference between the returning beam and the outgoing beam. As such it contains the difference between the value of the laser noise at time $t - l_i(t)$ affecting the returning beam (with $l_i(t)$ being the round-trip-light-time) and the laser noise of the outgoing beam at time t when the measurement is recorded. From the instant the laser is switched on (let us say $t = 0$) each two-way Doppler measurement becomes different from zero only for $t \geq l_i(t)$, i.e. when the returning beam and the outgoing beam start to interfere. By accounting for this observation in the “boundary conditions” of the matrix formulation of TDI- ∞ [7] we show TDI- ∞ reduces to a matrix representation of TDI.

We would like to briefly mention here another matrix based approach. Romano and Woan [8] have used Bayesian inference to set up a noise covariance matrix of the data streams. Then by performing a principal component analysis of the covariance matrix, they identify the principal components with large eigenvalues with the laser noise and so distinguish it from other ambient noises and signal which correspond to small eigenvalues. We argue that this approach is also a matrix representation of the original TDI.

Here we provide a summary of this article. In section II we present the key-points of TDI- ∞ and correct the expression of the matrix introduced in [7] relating the two arrays associated with the two-way Doppler measurements to the array of the laser noise. We then recast this linear relationship in terms of two square-matrices, each relating the array associated with one of the two-way Doppler measurement to the array of the laser noise. As expected these matrices are singular, reflecting the physical impossibility of reconstructing the laser noise array from the arrays associated with the two-way Doppler data. In the simple configuration of a stationary interferometer whose round-trip-light-times are integer-multiples of the sampling time, we show that the linear combination of the two-way Doppler arrays canceling the laser noise is equal to the sampled unequal-arm Michelson TDI combination X . In section III we then turn to the problem of a stationary three-arm array with three laser noises and six one-way Doppler measurements. After deriving the expressions of the matrices relating the laser noises to the one-way Doppler measurements, we show that the generators of the space of the combinations canceling the laser noises are equal to the sampled TDI-combinations $(\alpha, \beta, \gamma, \zeta)$ [6] in which the delay operators have been replaced by our derived matrices. This is rigorously established in section IV by showing that the matrix formulation is just a ring representation of the first module of syzygies - a ring homomorphism. Thus the matrix formulation is in principle the same as the original formulation of TDI, although it might offer some advantages when implemented numerically. Finally, in section V we present our concluding remarks and summarize our thoughts about potential advantages in processing the TDI measurements cast in matrix form when searching for gravitational wave signals.

II. MATRIX REPRESENTATION OF THE TWO-WAY DOPPLER MEASUREMENTS

Equal-arm interferometer detectors of gravitational waves can observe gravitational radiation by canceling the laser frequency fluctuations affecting the light injected into their arms. This is done by comparing phases of split beams propagated along the equal (but non-parallel) arms of the detector. The laser frequency fluctuations affecting the two beams experience the same delay within the two equal-length arms and cancel out at the photodetector where relative phases are measured. This way gravitational-wave signals of dimensionless amplitude less than 10^{-22} can be observed when using lasers whose frequency stability can be as large as roughly a few parts in 10^{-18} in the kilohertz band.

If the arms of the interferometer have different lengths, however, the exact cancellation of the laser frequency fluctuations, say $C(t)$, will no longer take place at the photodetector. In fact, the larger the difference between the two arms, the larger will be the magnitude of the laser frequency fluctuations affecting the detector response. If l_1 and l_2 are the round-trip-light-times of the laser beams within the two arms, it is easy to see that the amount of laser

relative frequency fluctuations remaining in the response are equal to:

$$\Delta C(t) = C(t - l_1) - C(t - l_2). \quad (2.1)$$

In the case of a space-based interferometer such as LISA for instance, whose lasers are expected to display relative frequency fluctuations equal to about $10^{-13}/\sqrt{\text{Hz}}$ in the mHz band and round-trip-light-times will differ by a few percent [1], Eq. (2.1) implies uncanceled fluctuations from the laser as large as $\approx 10^{-16}/\sqrt{\text{Hz}}$ at a millihertz frequency [6]. Since the LISA sensitivity goal is about $10^{-20}/\sqrt{\text{Hz}}$ in this part of the frequency band, it is clear that an alternative experimental approach for canceling the laser frequency fluctuations is needed.

An elegant method entirely implemented in the time domain was first suggested in [9] and then generalized in a series of related publications (see [6] and references therein). Such a method, named Time-Delay Interferometry (or TDI) as it requires time-shifting and linearly combining the recorded data, carefully accounts for the time-signature of the laser noise in the two-way Doppler data. TDI relies on the optical configuration exemplified by Fig. 1 [10–13]. In this idealized model the two beams exiting the two arms are not made to interfere at a common photodetector. Rather, each is made to interfere with the incoming light from the laser at a photodetector, decoupling in this way the laser phase fluctuations experienced by the two beams in the two arms. In the case of a stationary array, cancellation of the laser noise at an arbitrary time t requires only four samples of the measurements made at and around t . Contrary to a previously proposed technique [10–13], which required processing in the Fourier domain a large (\sim six months) amount of data to sufficiently suppress the laser noise at a time t [6, 9], TDI can be regarded as a “local” method.

In a recent publication [7], a new “global” technique for canceling the laser noise has been proposed. This technique, which has been named TDI- ∞ , establishes a linear relationship between the sampled Doppler measurements and the laser noise arrays. It is claimed to work for any time-dependent delays and to cancel the laser noise at an arbitrary time t by taking linear combinations of the two-way Doppler measurements sampled at all times before t .

To understand the formulation of TDI- ∞ , let us consider again the simplified (and stationary) two-arm optical configuration shown in Figure 1. In it the laser noise, $C(t)$, folds into the two two-way Doppler data, $y_1(t)$, $y_2(t)$, in the following way (where we disregard the contributions from all other physical effects affecting the two-way Doppler data):

$$\begin{aligned} y_1(t) &= C(t - l_1(t)) - C(t) , \\ y_2(t) &= C(t - l_2(t)) - C(t) , \end{aligned} \quad (2.2)$$

where l_1 , l_2 are the two round-trip-light-times, in general also functions of time t .

Operationally, Eq. (2.2) says that each sample of the two-way Doppler data at time t contains the difference between the laser noise C generated at a round-trip-light time earlier, $t - l_i(t)$, $i = 1, 2$ and that generated at time t . Figure 2 displays graphically what we have just described. The important point to note here is what happens during the first l_i seconds from the instant $t = 0$ when the laser is switched on. Since the y_i measurements are the result of interfering the returned beam with the outgoing one, during the first l_i seconds (i.e. from the moment the laser has been turned on) the y_i measurements are identically equal to zero because no interference measurements can be performed during this time. In other words, during the first l_i seconds there is not yet a returning beam with which the local light is made to interfere with. In [7], however, only the first terms on the right-hand-sides of Eq. (2.2) were disregarded during these time intervals.

As it will be shown below, this incorrect assumption invalidates the results derived in [7] as it translates in an incorrect mathematical formulation of TDI- ∞ . In it, the sampled two two-way Doppler data are packaged in a single array in an alternating fashion starting from time $t = t_0$ when the laser is switched on. Assuming a stationary array configuration in which the round-trip-light-times l_1 , l_2 are equal to twice and three times the sampling time Δt , (as exemplified in [7]), the measurements array is linearly related to the array associated with the samples of the laser noise C through a rectangular $2N \times N$ matrix M (N being the number of considered samples) in the following way:

$$\begin{pmatrix} y_1(t_0) \\ y_2(t_0) \\ y_1(t_1) \\ y_2(t_1) \\ y_1(t_2) \\ y_2(t_2) \\ y_1(t_3) \\ y_2(t_3) \\ y_1(t_4) \\ y_2(t_4) \\ \vdots \end{pmatrix} = \begin{pmatrix} -1 & 0 & 0 & 0 & 0 & \cdots \\ -1 & 0 & 0 & 0 & 0 & \cdots \\ 0 & -1 & 0 & 0 & 0 & \cdots \\ 0 & -1 & 0 & 0 & 0 & \cdots \\ 1 & 0 & -1 & 0 & 0 & \cdots \\ 0 & 0 & -1 & 0 & 0 & \cdots \\ 0 & 1 & 0 & -1 & 0 & \cdots \\ 1 & 0 & 0 & -1 & 0 & \cdots \\ 0 & 0 & 1 & 0 & -1 & \cdots \\ 0 & 1 & 0 & 0 & -1 & \cdots \\ \vdots & \vdots & \vdots & \vdots & \vdots & \ddots \end{pmatrix} \cdot \begin{pmatrix} c(t_0) \\ c(t_1) \\ c(t_2) \\ c(t_3) \\ c(t_4) \\ \vdots \end{pmatrix}. \quad (2.3)$$




FIG. 1. Light from a laser is split into two beams, each injected into an arm formed by pairs of free-falling mirrors. Since the round-trip-light-times, l_1 and l_2 , are different, now the light beams from the two arms are not recombined at one photo detector. Instead each is separately made to interfere with the light that is injected into the arms. Two distinct photo detectors are now used, and phase (or frequency) fluctuations are then monitored and recorded there.

As shown by Eq. (2.3), rows 1 through 4 and row 6 of matrix M reflect the assumption made in [7] of the two Doppler measurements to contain the laser noise C only at time t during the time intervals $t_0 \leq t < t_0 + l_i$. If, on the other hand, we correctly assume rows 1 through 4 and row 6 to be identically equal to zero, the null-space associated to the matrix M will clearly be different.

To better understand and quantify this difference, we split the above measurement's array in two arrays, (Y_1, Y_2) , (one per measurement) and introduce two corresponding $(N \times N)$ square-matrices relating the measurement arrays to the array of the laser noise. We assume again a stationary configuration with round-trip-light-times (l_1, l_2) equal to twice and three-times the sampling time respectively. The two vectors, Y_1, Y_2 , are related to the laser noise vector C through the following expressions:

$$Y_1 = A_1.C \quad ; \quad Y_2 = A_2.C \quad , \quad (2.4)$$




FIG. 2. The laser noise random process (blue color), $C(t)$, together with the corresponding two-way Doppler measurement (red color), y_i . The laser is switched on at time $t = 0$. Since it takes l_i seconds for the beam to return to the transmitting spacecraft, y_i is identically equal to zero since no Doppler measurements can be performed during this time interval.

where the symbol $.$ denotes matrix multiplication, and A_1, A_2 are equal to the following square-matrices:

$$A_1 = \begin{pmatrix} 0 & 0 & 0 & 0 & 0 & 0 & \cdots \\ 0 & 0 & 0 & 0 & 0 & 0 & \cdots \\ 1 & 0 & -1 & 0 & 0 & 0 & \cdots \\ 0 & 1 & 0 & -1 & 0 & 0 & \cdots \\ 0 & 0 & 1 & 0 & -1 & 0 & \cdots \\ 0 & 0 & 0 & 1 & 0 & -1 & \cdots \\ \vdots & \vdots & \vdots & \vdots & \vdots & \ddots & \ddots \end{pmatrix}, A_2 = \begin{pmatrix} 0 & 0 & 0 & 0 & 0 & 0 & \cdots \\ 0 & 0 & 0 & 0 & 0 & 0 & \cdots \\ 0 & 0 & 0 & 0 & 0 & 0 & \cdots \\ 1 & 0 & 0 & -1 & 0 & 0 & \cdots \\ 0 & 1 & 0 & 0 & -1 & 0 & \cdots \\ 0 & 0 & 1 & 0 & 0 & -1 & \cdots \\ \vdots & \vdots & \vdots & \vdots & \vdots & \ddots & \ddots \end{pmatrix}. \quad (2.5)$$

Note the above matrices incorporate the correct “boundary conditions” as their first few rows are null (the number of null rows depends on the magnitude of the round-trip-light-time). It is evident that the rank of the matrices A_1, A_2 is less than the number of samples N and therefore they cannot be inverted. Physically this means that, although the laser noise cannot be known/measured at any time t , one can still cancel it by taking suitable linear combinations of the two-way Doppler data. Let us consider the following linear combination of the two-way Doppler measurements:

$$X \equiv A_2.Y_1 - A_1.Y_2 = (A_2.A_1 - A_1.A_2).C. \quad (2.6)$$

We have verified that the commutator $[A_1, A_2]$ starts to become zero from row 6 onward. If we write the vectors Y_1, Y_2 in terms of their components, the linear combination X becomes equal to:

$$X = \begin{pmatrix} 0 \\ 0 \\ 0 \\ y_1(t_3) - y_2(t_3) \\ y_1(t_4) - y_2(t_4) \\ -y_1(t_2) + y_1(t_5) + y_2(t_3) - y_2(t_5) \\ -y_1(t_3) + y_1(t_6) + y_2(t_4) - y_2(t_6) \\ \vdots \end{pmatrix} \quad (2.7)$$

The problem of identifying all possible TDI combinations associated with the six one-way Doppler measurements becomes one of determining six matrices, $q_i, q_{i'}$ such that the following equation holds:

$$\sum_{i=1}^3 q_i \cdot y_i + \sum_{i'=1}^3 q_{i'} \cdot y_{i'} = 0 , \quad (3.5)$$

where the above equality means “zero laser noises”. Before proceeding, note that the matrices D_i and I_i satisfy the following identities which may be useful later on:

$$\begin{aligned} I_i \cdot D_k &= D_k , & i \leq k \\ &\neq D_k , & i > k \\ I_i \cdot I_k &= I_k \cdot I_i = I_k , & i \leq k . \end{aligned} \quad (3.6)$$

The above identities in particular state that $I_k^2 = I_k$, that is, I_k are idempotent, or in other words they are projection operators.

By redefining the matrices $q_i, q_{i'}$ in the following way:

$$\begin{aligned} q_1 \cdot I_3 &\rightarrow q_1 , & q_2 \cdot I_1 &\rightarrow q_2 , & q_3 \cdot I_2 &\rightarrow q_3 , \\ q_{1'} \cdot I_2 &\rightarrow q_{1'} , & q_{2'} \cdot I_3 &\rightarrow q_{2'} , & q_{3'} \cdot I_1 &\rightarrow q_{3'} , \end{aligned} \quad (3.7)$$

Eq. (3.5) assumes the following form:

$$\begin{aligned} &(-q_1 - q_{1'} + q_3 \cdot D_2 + q_{2'} \cdot D_3) \cdot C_1 \\ &+ (-q_2 - q_{2'} + q_1 \cdot D_3 + q_{3'} \cdot D_1) \cdot C_2 \\ &+ (-q_3 - q_{3'} + q_2 \cdot D_1 + q_{1'} \cdot D_2) \cdot C_3 = 0 \end{aligned} \quad (3.8)$$

Since the three random processes C_i , $i = 1, 2, 3$ are independent, the above equation can be satisfied iff the three matrices multiplying the three random processes are identically equal to zero, i.e.:

$$\begin{aligned} -q_1 - q_{1'} + q_3 \cdot D_2 + q_{2'} \cdot D_3 &= 0 , \\ -q_2 - q_{2'} + q_1 \cdot D_3 + q_{3'} \cdot D_1 &= 0 , \\ -q_3 - q_{3'} + q_2 \cdot D_1 + q_{1'} \cdot D_2 &= 0 . \end{aligned} \quad (3.9)$$

Since the system of Eqs. (3.9) is identical in form to the corresponding equations derived in [6] (see section 4.3 of [6] and equations therein), the solutions will assume the same forms. It should be noticed, however, that the “matrix” expressions of the generators $\alpha, \beta, \gamma, \zeta$ can be obtained from the usual TDI-expressions by taking into account that the q s had been redefined (see Eq.(3.7)). This means that the Sagnac combination α , for instance, assumes the following form:

$$\alpha = (y_1 + D_3 y_2 + D_1 D_3 y_3) - (y_{1'} + D_2 y_{3'} + D_1 D_2 y_{2'}) , \quad (3.10)$$

where we have accounted for the identities given by Eqs. (3.6). When considering seven time-samples of the six one-way measurements, the above expression for α reduces to the following vector:

$$\alpha = \begin{pmatrix} 0 \\ 0 \\ -y_{1'}(t_2) - y_{3'}(t_0) \\ y_1(t_3) - y_{1'}(t_3) + y_2(t_0) - y_{2'}(t_0) - y_{3'}(t_1) \\ y_1(t_4) - y_{1'}(t_4) + y_2(t_1) - y_{2'}(t_1) + y_3(t_0) - y_{3'}(t_2) \\ y_1(t_5) - y_{1'}(t_5) + y_2(t_2) - y_{2'}(t_2) + y_3(t_1) - y_{3'}(t_3) \\ y_1(t_6) - y_{1'}(t_6) + y_2(t_3) - y_{2'}(t_3) + y_3(t_2) - y_{3'}(t_4) \\ \vdots \end{pmatrix} \quad (3.11)$$

As in the case of the combination X presented in the previous section, here also the first few entries of the vector cannot cancel the laser noises. This is because some of the measurements at those time stamps are equal to zero. However, it is easy to verify that all measurements at row seven and higher are different from zero and reproduce the usual TDI combination α that cancels the laser noise.

IV. TDI AND MATRIX REPRESENTATIONS OF RINGS

A. Group and ring structures of time-delay operators

Let us consider the data $y_j(t)$ as above. For the purpose of this section we will drop the subscript from y_j and call it just $y(t)$. Also in the beginning of this section for purposes of argument, we consider $-\infty < t < \infty$, that is $t \in \mathcal{R}$, the set of real numbers. Later we will consider the realistic situation of finite length data segment. A time delay operator \mathcal{D} with delay l acts on the y as follows:

$$\begin{aligned} \mathcal{D} : \mathcal{R} &\longrightarrow \mathcal{R} \\ y(t) &\longrightarrow y(t - l). \end{aligned} \tag{4.1}$$

After having defined the delay operator \mathcal{D} , we may analogously define several delay operators $\mathcal{D}_1, \mathcal{D}_2, \dots$ with time delays l_1, l_2, \dots respectively. The \mathcal{D} operators are translations in one dimension and hence form the translation group in one dimension. The group operation here is then defined as the successive application of the operators:

$$\mathcal{D}_1 \mathcal{D}_2 y(t) = \mathcal{D}_1 y(t - l_2) = y(t - l_1 - l_2).$$

With the operation so defined the \mathcal{D} s form an uncountable infinite group. When the l_1, l_2 are constants, the group is Abelian.

If l_1 and l_2 are functions of time themselves, then, the product becomes $\mathcal{D}_1 \mathcal{D}_2 y(t) = \mathcal{D}_1 y(t - l_2(t)) = y(t - l_1 - l_2(t - l_1))$ which is in general non-commutative and the group is non-Abelian. Then this is not the usual translation group, but nevertheless it is a group, because any \mathcal{D} defines a bijective map from \mathcal{R} to \mathcal{R} , so that the inverse exists.

When we consider several data streams y_j as in two arm or three arm interferometers, the \mathcal{D} operators in fact form a polynomial ring instead of only a group with the different \mathcal{D}_j operators as indeterminates [14]. The ring could be commutative or non-commutative according as the arm-lengths are time independent [14, 15] or time dependent [6, 16–18]. The TDI data combinations constitute a module over the polynomial ring of delay operators known as the first module of syzygies. See [6, 14] for details. The ring operations in general are defined in the obvious way on a data stream $y(t)$. Given two operators \mathcal{D}_1 and \mathcal{D}_2 :

$$\begin{aligned} (\mathcal{D}_1 + \mathcal{D}_2)y(t) &= \mathcal{D}_1 y(t) + \mathcal{D}_2 y(t) = y(t - l_1) + y(t - l_2) \\ \mathcal{D}_1 \mathcal{D}_2 y &= \mathcal{D}_1 y(t - l_2(t)) = y(t - l_1 - l_2(t - l_1)). \end{aligned} \tag{4.2}$$

These operations can be extended to the whole ring by linearity. In the examples in this paper, we consider the arm lengths to be constant in time and so $\mathcal{D}_1 \mathcal{D}_2 = \mathcal{D}_2 \mathcal{D}_1$ and the polynomial ring is commutative.

B. Matrix representations of time-delay operators

We now consider the more realistic situation where the data segment is of finite duration $[0, T]$. We will also assume that the data are sampled uniformly with sampling time interval Δt . Now there are finite number of samples N labeled by the times $t_k = k \Delta t$, $k = 0, 1, 2, \dots, N - 1$ and also we have $N \Delta t = T$. See [19] for more details. Here typically N could be a large number, but the point is that it is *finite*. So the measurements y or the laser noise C can be represented by N dimensional vectors in \mathcal{R}^N . Because noise is a random process these are random vectors.

The operators \mathcal{D} now take the form of linear transformations from $\mathcal{R}^N \longrightarrow \mathcal{R}^N$ and hence in our formulation can be represented by $N \times N$ matrices which now for this case we will represent by just D . With the arm-lengths taken as in section III, the operators $\mathcal{D}_1, \mathcal{D}_2, \mathcal{D}_3$ are represented by the matrices given by Eqs. (3.2), (3.3), (3.4). We have essentially discretized the previous situation of the continuum. In the matrix representation we have represented the abstract TDI operators \mathcal{D} by matrices. The operations which were valid in the abstract case map faithfully to the discretized version. The sum and product of the \mathcal{D} operators maps to the sum and product of the D matrices - the ring operations are preserved. This is in fact known as a representation of a group or a ring in the literature. We now formally define a representation [20]:

Definition 1. *Let \mathcal{G} be a group and V be a finite dimensional vector space. For every $g \in \mathcal{G}$ there is associated $T_g : V \longrightarrow V$ be a linear map. Then the map*

$$\begin{aligned} \varphi : \mathcal{G} &\longrightarrow \text{Hom}(V, V) \\ g &\longrightarrow T_g \end{aligned} \tag{4.3}$$

is called a representation if φ is a group homomorphism, i. e. for every $g_1, g_2 \in \mathcal{G}$, $T_{g_1 g_2} = T_{g_1} T_{g_2}$ and the group identity $e \in G$ maps to $T_e = I$, the unit matrix. $\text{Hom}(V, V)$ is the space of linear transformations from $V \rightarrow V$ - the endomorphisms of V .

This definition easily extends to that of rings with identity, where now the homomorphism must be a ring homomorphism; both operations of the ring must be preserved under the homomorphism [21]. V is called the carrier space. In our situation, φ maps $\mathcal{D} \rightarrow D$ or $\varphi(\mathcal{D}) = D$; the delay operator \mathcal{D} is mapped to the matrix D . It is easy to verify that this is a ring homomorphism. $V = \mathcal{R}^N$, the space of the vectors y or C , plays the role of the carrier space.

Now consider any TDI observable of LISA. If we consider a simple model of LISA with just three time-delay operators $\mathcal{D}_1, \mathcal{D}_2, \mathcal{D}_3$ and constant arm-lengths, the TDI observable is six component polynomial vector in the delay operators. Let us for example consider the simplest of the TDI observables, namely, ζ . In the operator picture, it is an element of the module of syzygies:

$$\zeta = (-\mathcal{D}_1, -\mathcal{D}_2, -\mathcal{D}_3, \mathcal{D}_1, \mathcal{D}_2, \mathcal{D}_3). \quad (4.4)$$

In the matrix formulation, under the ring homomorphism, the matrix form of ζ is:

$$\zeta = -D_1 y_1 - D_2 y_2 - D_3 y_3 + D_1 y_{1'} + D_2 y_{2'} + D_3 y_{3'}, \quad (4.5)$$

where now the D_k are $N \times N$ matrices and the $y_j, y_{j'}$ are N dimensional column vectors. ζ is now a $N \times 1$ column vector which is devoid of laser frequency noise. Let us now check whether ζ as defined here cancels the laser frequency noise. We may write ζ in terms of the laser noises C_1, C_2, C_3 from Eq. (3.1):

$$\zeta = D_1(I_3 - I_2)C_1 + D_2(I_1 - I_3)C_2 + D_3(I_2 - I_1)C_3. \quad (4.6)$$

At the time t_k , we then have,

$$\zeta(k) = (I_3 - I_2)C_1(k-1) + (I_1 - I_3)C_2(k-2) + (I_2 - I_1)C_3(k-3), \quad (4.7)$$

where in order to avoid clutter we have written k for the sampling time t_k . From the above equation we deduce that $\zeta(k) = 0$ for $k \geq 5$ and also $\zeta(0) = \zeta(1) = \zeta(2) = 0$. However, $\zeta(3) = C_2(1) - C_1(2) \neq 0$ and $\zeta(4) = C_3(1) - C_2(2) \neq 0$ and so at these sampling times the laser noise does not cancel.

In the algebraic approach [6, 14], any TDI observable is a 6-tuple polynomial vector in the operators \mathcal{D}_k . In the matrix formulation, since the operators \mathcal{D}_k map to the matrices D_k under the ring homomorphism, an operator polynomial maps also to a matrix. Thus in the matrix formulation any TDI observable is expressed in terms of 6 matrices $q_i, q_{i'}$; the polynomials $q_i, q_{i'}$ in the operators \mathcal{D}_k are now interpreted as matrices. In the two arm configuration discussed in Section II only two matrices are required A_1 and A_2 . In terms of the D_k matrices defined, $A_1 = D_1 - I_1$ and $A_2 = D_2 - I_2$. In a recent work [7] the two $N \times N$ matrices are juxtaposed in the form of a $2N \times N$ matrix M , called the design matrix, and in which the y_1, y_2 measurements are interleaved together in rows as in Eq. (2.3). Note that the TDI combinations presented in matrix form can be repackaged in a format $T.y$ [7], which might turn out to be more streamlined for numerical manipulations and data analysis.

A Bayesian inference approach has been adopted by Romano and Woan [8]. They set up a noise covariance matrix of the data streams $y_j, y_{j'}$ and perform a principal component analysis. From the principal components they identify large eigenvalues with laser noise and so distinguish it from the signal. We remark that this is also a matrix representation of the original TDI, although a little more complex - it is a tensor representation or product representation [20]. The covariance matrix is a second rank tensor. Any entry of the covariance matrix C_{ik} is an ensemble average of outer products of the form $y_\alpha(i)y_\beta^T(k)$, $y_{\alpha'}(i)y_{\beta'}^T(k)$ or $y_{\alpha'}(i)y_{\beta'}^T(k)$. We use Greek indices $\alpha, \beta = 1, 2, 3$ to label data streams and operators to distinguish them from time samples which are tensor indices. At each (i, k) , the products in y contain tensor products - for example, $y_1(i)y_{1'}^T(k)$ contains products of the D matrices, namely, $D_{3ij}D_{2mk}C_{2j}C_{3m}$. The outer product of the vectors C_2 and C_3 , namely, $C_2 \otimes C_3 \in \mathcal{R}^N \otimes \mathcal{R}^N$ is a tensor of second rank and the product of the D s acts on this tensor. These products of D s define the tensor representation. $\mathcal{R}^N \otimes \mathcal{R}^N$ acts as the carrier space for this representation.

In summary, we emphasize here that the matrix formulation is a ring representation of the original TDI formulation. In principle it is no different. However, in practice, there may be advantages to this approach, because representations using matrices lend themselves to easy analytical and numerical manipulations.

V. CONCLUSIONS

The main result of our article has been the demonstration that the delay operators characterizing TDI may be represented as matrices. Through this approach we recovered the well known result characterizing TDI: the cancellation of the laser noise in an unequal-arm interferometer is a “local operation” as it is achieved at any time t by linearly combining only a few neighboring measurement-samples. Our conclusion is the consequence of correctly accounting for the delays between the time the lasers are turned-on and the instant the data acquisition starts.

In mathematical terms, we have shown that the cancellation of the laser noises using matrices is just the ring representation of the original TDI formulation and it is not different from it. It should be said, however, that the matrix approach we have introduced might offer some advantages to the data processing and analysis tasks of currently planned gravitational wave missions [1–3] as it is more flexible, allows for easier numerical implementation and manipulation and also adapts to time-dependent arm-lengths in a natural way. Further on another front, it might in fact be possible to extend to our matrix formulation of TDI the data processing algorithm discussed in [7] to handle data gaps. We have just started to analyze this problem and might report about its solution in a forthcoming article.

We remark that regardless of the approach we follow, both the original as well as the matrix approaches look for null spaces whose vectors describe the TDI observables. In the original TDI approach, the first module of syzygies is in fact a null space - the kernel of a homomorphism; the kernel is important because it contains elements, namely, those TDI observables which map the laser noise to zero.

ACKNOWLEDGMENTS

M.T. thanks the Center for Astrophysics and Space Sciences (CASS) at the University of California San Diego (UCSD, U.S.A.) and the National Institute for Space Research (INPE, Brazil) for their kind hospitality while this work was done. S.V.D. acknowledges the support of the Senior Scientist Platinum Jubilee Fellowship from NASI, India.

-
- [1] P. Amaro-Seoane et al., ArXiv e-prints (2017), 1702.00786.
 - [2] W.-R. Hu and Y.-L. Wu, National Sci. Rev. **4**, 685 (2017), ISSN 2095-5138.
 - [3] J. Luo, L.-S. Chen, H.-Z. Duan, Y.-G. Gong, S. Hu, J. Ji, Q. Liu, J. Mei, V. Milyukov, M. Sazhin, et al., Class. Quantum Grav. **33**, 035010 (2016).
 - [4] M. Tinto, D. DeBra, S. Buchman, and S. Tilley, Review of Scientific Instruments **86**, 014501 (2015), <https://doi.org/10.1063/1.4904862>, URL <https://doi.org/10.1063/1.4904862>.
 - [5] W.-T. Ni, International Journal of Modern Physics D **25**, 1630001 (2016), URL <https://doi.org/10.1142/S0218271816300019>.
 - [6] M. Tinto and S. V. Dhurandhar, Living Reviews in Relativity **24**, 6 (2021), ISSN 1433-8351, URL <https://doi.org/10.1007/s41114-020-00029-6>.
 - [7] M. Vallisneri, J.-B. Bayle, S. Babak, and A. Petiteau, *Tdi-infinity: time-delay interferometry without delays* (2020), 2008.12343.
 - [8] J. D. Romano and G. Woan, Phys. Rev. D **73**, 102001 (2006), URL <https://link.aps.org/doi/10.1103/PhysRevD.73.102001>.
 - [9] M. Tinto and J. W. Armstrong, Phys. Rev. D **59**, 102003 (pages 11) (1999).
 - [10] J. E. Faller and P. L. Bender, in *Precision Measurement and Fundamental Constants II*, edited by B. N. Taylor and W. D. Phillips (U.S. Dept. of Commerce / National Bureau of Standards, Washington, DC, 1984), vol. 617 of *NBS Special Publication*, pp. 689–690.
 - [11] J. E. Faller, P. L. Bender, J. L. Hall, D. Hils, and M. A. Vincent, in *Kilometric Optical Arrays in Space*, edited by N. Longdon and O. Melita (ESA Publications Division, Noordwijk, 1985), vol. SP-226 of *ESA Conference Proceedings*, pp. 157–163.
 - [12] J. E. Faller, P. L. Bender, J. L. Hall, D. Hils, R. T. Stebbins, and M. A. Vincent, Adv. Space Res. **9**, 107 (1989), COSPAR and IAU, 27th Plenary Meeting, 15th Symposium on Relativistic Gravitation, Espoo, Finland, July 18–29, 1988.
 - [13] G. Giampieri, R. W. Hellings, M. Tinto, and J. E. Faller, Opt. Commun. **123**, 669 (1996).
 - [14] S. V. Dhurandhar, K. Rajesh Nayak, and J.-Y. Vinet, Phys. Rev. D **65**, 102002 (pages 16) (2002).
 - [15] J. W. Armstrong, F. B. Estabrook, and M. Tinto, Astrophys. J. **527**, 814 (1999).
 - [16] D. A. Shaddock, M. Tinto, F. B. Estabrook, and J. W. Armstrong, Phys. Rev. D **68**, 061303 (pages 4) (2003).
 - [17] M. Tinto, F. B. Estabrook, and J. W. Armstrong, Phys. Rev. D **69**, 082001 (2004).
 - [18] S. V. Dhurandhar, K. Rajesh Nayak, and J.-Y. Vinet, Class. Quantum Grav. **27**, 135013 (2010), 1001.4911.
 - [19] W. H. Press, S. A. Teukolsky, W. T. Vetterling, and B. P. Flannery, *Numerical Recipes 3rd Edition: The Art of Scientific Computing* (Cambridge University Press, USA, 2007), 3rd ed., ISBN 0521880688.

- [20] S. Z. Y. Gelfand I. M., Minlos R. A., *Representations of the Rotation and Lorentz Groups and Their Applications* (Pergamon Press, Oxford, 1963).
- [21] M. Burrow, *Representation Theory of Finite Groups* (Academic Press Inc., New York, 1965).