

Identification Over Quantum Broadcast Channels

Uzi Pereg^{1,2}, Johannes Rosenberger¹, and Christian Deppe¹

¹Institute for Communications Engineering, Technical University of Munich, 80333 Munich, Germany

²Munich Center for Quantum Science and Technology, 80799 Munich, Germany

Identification over quantum broadcast channels is considered. As opposed to the information transmission task, the decoder only identifies whether a message of his choosing was sent or not. This relaxation allows for a double-exponential code size. An achievable identification region is derived for a quantum broadcast channel, and full characterization for the class of classical-quantum broadcast channels. The results are demonstrated for a depolarizing broadcast channel. Furthermore, the identification capacity region of the single-mode pure-loss bosonic broadcast channel is obtained as a consequence. In contrast to the single-user case, the capacity region for identification can be significantly larger than for transmission.

1 Introduction

Modern data systems have an ever-growing gap between the available information storage and the bit per second rates, which are limited by the noisy transmission medium [1, 2]. Quantum communication is thus expected to enter the sixth generation of cellular networks (6G) in order to achieve performance gains [3–5].

Data volumes are even larger when limiting a system to identifying alerts, rather than recovering information. In Shannon’s transmission task [6], a transmitter sends a message over a noisy channel, and the receiver needs to find which message was sent. In some modern event-triggered applications, however, the receiver may simply perform a binary decision on whether a particular message of interest was sent or not. This setting is known as identification via channels [7]. Identification (ID) is relevant for various applications such as watermarking [8–10] and sensor communication [11]. In vehicle-to-X communication [12], a vehicle may announce information about its future movements to the surrounding road users. Every road user is interested in one specific movement that interferes with its plans, and it checks only if this movement is announced or not.

The ID capacity of a classical-quantum channel was determined by Löber [13] and Ahlswede and Winter [14] (see also [15]). The ID capacity turns out to have the same value as the transmission capacity for all single-user channels that we know of. However, the units are different. Specifically, the ID code size grows doubly exponentially in the block length, provided that the encoder has access to a source of randomness. Thereby, identification codes achieve an exponential advantage in throughput compared to transmission codes. This is attained by letting the encoding and decoding sets overlap. General results for

Uzi Pereg: uzi.pereg@tum.de

Johannes Rosenberger: johannes.rosenberger@tum.de

Christian Deppe: christian.deppe@tum.de

ID are surveyed in [16]. Löber [13] considered a simultaneous identification scenario, in which the same measurement is performed in order to perform identification for multiple receivers. This is also relevant to a network that consists of chains [17]. In [18], Boche *et al.* considered identification over the classical-quantum channel under channel uncertainty and secrecy constraints. Hayden and Winter [19] further considered identification of quantum states and showed that the code size is exponential in this case, as in transmission.

The broadcast channel is a fundamental multi-user communication model, whereby a single transmitter sends messages to two receivers [20]. In the traditional transmission setting, the capacity region of the discrete memoryless broadcast channel is generally unknown, even in the classical case. The best known lower bound is due to Marton [21], and the best known upper bound was proven by Nair and El Gamal [22]. The two bounds coincide in special cases such as more capable, less noisy or degraded broadcast channel [23]. On the other hand, the ID capacity region of the classical broadcast channel was fully characterized by Bracher and Lapidoth [24, 25], for uniformly distributed messages. Namely, the ID capacity region is known for *any* classical broadcast channel, without special requirements on the channel. The derivation in [24, 25] is based on a pool-selection technique that differs from the standard arguments. Related settings were also considered in [26–28]. The authors of the present paper have recently considered ID over the classical compound multiple-input multiple-output (MIMO) broadcast channel [29, 30].

Quantum broadcast channels were studied in various settings [31–46]. Yard *et al.* [31] derived the superposition inner bound and determined the capacity region for the degraded classical-quantum broadcast channel. Wang *et al.* [34] used the previous characterization to determine the capacity region for Hadamard broadcast channels. Dupuis *et al.* [35, 36] developed the entanglement-assisted version of Marton’s region. Quantum broadcast channels with conferencing decoders were recently considered in [47] as well, providing an information-theoretic perspective to the operation of quantum repeaters. In addition, security aspects were treated in [48, 49].

Optical communication forms the backbone of the Internet [50–53]. The Gaussian bosonic channel is a simple quantum-mechanical model for optical communication over free space or optical fibers [54, 55]. An optical communication system consists of a modulated source of photons, the optical channel, and an optical detector. For a single-mode bosonic broadcast channel, the channel input is an electromagnetic field mode with annihilation operator \hat{a} , and the output is a pair of modes with annihilation operators \hat{b}_1 and \hat{b}_2 , corresponding to each receiver. Bosonic broadcast channels are considered in different settings in [56–63].

In this work, we consider ID over the quantum broadcast channel. We derive an achievable ID rate region for the general quantum broadcast channel, and establish full characterization for the classical-quantum broadcast channel under a semi-average error criterion. We demonstrate our results and determine the ID capacity region of a broadcast depolarizing channel. Furthermore, we establish the capacity region of the single-mode pure-loss bosonic broadcast channel. The ID capacity region of the bosonic broadcast channel is depicted in Figure 1 as the area below the solid blue line. For comparison, the transmission capacity region, as determined by Guha and Shapiro [56] subject to the minimum output-entropy conjecture, is indicated by the red dashed line. It can be seen that the ID capacity region is significantly larger than the transmission counterpart. We note that the ID result does not require the conjecture.

While the properties above are analogous to the classical setting [29], the analysis is more involved. To prove the direct part, we extend the pool-selection method due to Bracher and Lapidoth [24, 25] to the quantum setting. On the other hand, our converse




Figure 1: The transmission and ID capacity regions of the pure-loss bosonic broadcast channel, with mean photon-number input constraint $N_A = 10$ and transmissivity $\eta = 0.8$. The transmission capacity region C_T is indicated by the area below the dashed red line, and the ID capacity region C_{ID} by the rectangular area below the solid blue line.

proof is based on completely different arguments than in Bracher and Lapidoth’s classical proof. Instead, we exploit recent observations made by Boche et al. [18] as they treated the classical-quantum compound channel, combined with the arguments of Ahlswede and Winter [14] in their seminal paper on ID for the single-user classical-quantum channel.

This paper is organized as follows: In Section 2, we introduce the notation, give basic definitions, and introduce the communication model. Section 3 contains our main results. In Section 4, we demonstrate our results and determine the ID capacity region of the depolarizing broadcast channel and the pure-loss bosonic broadcast channel. Section 5 provides the achievability proof for identification over the quantum broadcast channel in finite dimensions, and Section 6 provides the proof for the ID capacity region of the classical-quantum broadcast channel. Finally, the results are summarized in Section 7.

2 Preliminaries and Related Work

2.1 Notation

We use the following notation conventions. Script letters $\mathcal{X}, \mathcal{Y}, \mathcal{Z}, \dots$ are used for finite sets. Lowercase letters x, y, z, \dots represent constants and values of classical random variables, and uppercase letters X, Y, Z, \dots represent classical random variables. The distribution of a random variable X is specified by a probability mass function (PMF) $P_X(x)$ over a finite set \mathcal{X} . The set of all PMFs over \mathcal{X} is denoted by $\mathcal{P}(\mathcal{X})$. We use $x^j = (x_1, x_2, \dots, x_j)$ to denote a sequence of letters from \mathcal{X} . A random sequence X^n and its distribution $P_{X^n}(x^n)$ are defined accordingly.

2.2 Quantum States and Information Measures

The Hilbert space that corresponds to a quantum system A is denoted by \mathcal{H}_A . The state of a quantum system A is a density operator ρ on the Hilbert space \mathcal{H}_A , *i.e.* a positive semi-definite operator with unit trace, *i.e.* $\rho \succeq 0$ and $\text{Tr}(\rho) = 1$. The set of all such density operators is denoted by $\mathcal{D}(\mathcal{H}_A)$. The state is said to be pure if $\rho = |\psi\rangle\langle\psi|$, for some vector $|\psi\rangle \in \mathcal{H}_A$, where $\langle\psi| = |\psi\rangle^\dagger$. A measurement of a quantum system can be specified by any set of operators $\{\Lambda_j\}$ that forms a positive operator-valued measure (POVM), *i.e.* the operators are positive semi-definite and $\sum_j \Lambda_j = \mathbb{1}$, where $\mathbb{1}$ is the identity operator. According to the Born rule, if the system is in state ρ , then the probability of

the measurement outcome j is given by $p_A(j) = \text{Tr}(\Lambda_j \rho)$. The trace distance between two density operators ρ and σ is $\|\rho - \sigma\|_1$ where $\|F\|_1 \equiv \text{Tr}(\sqrt{F^\dagger F})$.

Define the quantum entropy of the density operator ρ as $H(\rho) \triangleq -\text{Tr}[\rho \log(\rho)]$, which is the same as the Shannon entropy associated with the eigenvalues of ρ . Consider the state of a pair of systems A and B on the tensor product $\mathcal{H}_A \otimes \mathcal{H}_B$ of the corresponding Hilbert spaces. Given a bipartite state σ_{AB} , define the quantum mutual information by

$$I(A; B)_\sigma = H(\sigma_A) + H(\sigma_B) - H(\sigma_{AB}). \quad (1)$$

The conditional quantum entropy and mutual information are defined by $H(A|B)_\sigma = H(\sigma_{AB}) - H(\sigma_B)$ and $I(A; B|C)_\sigma = H(A|C)_\sigma + H(B|C)_\sigma - H(A, B|C)_\sigma$, respectively.

A pure bipartite state is called *entangled* if it cannot be expressed as the tensor product of two states in \mathcal{H}_A and \mathcal{H}_B . The maximally entangled state between two systems of dimension D is defined by $|\Phi_{AB}\rangle = \frac{1}{\sqrt{D}} \sum_{j=0}^{D-1} |j\rangle_A \otimes |j\rangle_B$, where $\{|j\rangle_A\}_{j=0}^{D-1}$ and $\{|j\rangle_B\}_{j=0}^{D-1}$ are respective orthonormal bases.

2.3 Quantum Broadcast Channel

A quantum broadcast channel maps a quantum state at the sender system to a quantum state at the receiver systems. Here, we consider a channel with two receivers. Formally, a quantum broadcast channel is a linear, completely positive, trace-preserving map $\mathcal{N}_{A \rightarrow B_1 B_2} : \mathcal{D}(\mathcal{H}_A) \rightarrow \mathcal{D}(\mathcal{H}_{B_1} \otimes \mathcal{H}_{B_2})$ corresponding to a quantum physical evolution. We assume that the channel is memoryless. That is, if the systems $A^n = (A_1, \dots, A_n)$ are sent through n channel uses, then the input state ρ_{A^n} undergoes the tensor product mapping $\mathcal{N}_{A^n \rightarrow B_1^n B_2^n} \equiv \mathcal{N}_{A \rightarrow B_1 B_2}^{\otimes n}$. The marginal channel $\mathcal{N}_{A \rightarrow B_1}^{(1)}$ is defined by

$$\mathcal{N}_{A \rightarrow B_1}^{(1)}(\rho_A) = \text{Tr}_{B_2}(\mathcal{N}_{A \rightarrow B_1 B_2}(\rho_A)) \quad (2)$$

for Receiver 1, and similarly $\mathcal{N}_{A \rightarrow B_2}^{(2)}$ for Receiver 2. One may say that $\mathcal{N}_{A \rightarrow B_1 B_2}$ is an extension of $\mathcal{N}_{A \rightarrow B_1}^{(1)}$ and $\mathcal{N}_{A \rightarrow B_2}^{(2)}$. The transmitter, Receiver 1, and Receiver 2 are often called Alice, Bob 1, and Bob 2.

A quantum broadcast channel has a Kraus representation,

$$\mathcal{N}_{A \rightarrow B_1 B_2}(\rho_A) = \sum_j N_j \rho_A N_j^\dagger \quad (3)$$

for some set of operators N_j such that $\sum_j N_j^\dagger N_j = \mathbb{1}$.

Remark 1. The classical broadcast channel is the special case where the input and the outputs can be represented by classical random variables X and Y_1, Y_2 , respectively, while the Kraus operators are $N_{x, y_1, y_2} = \sqrt{P_{Y_1 Y_2 | X}(y_1, y_2 | x)} |y_1, y_2\rangle \langle x|$ for some probability kernel $P_{Y_1 Y_2 | X}$ and orthonormal bases $\{|x\rangle\}, \{|y_1, y_2\rangle\}$. Therefore, given an input $x \in \mathcal{X}$, the output state of a classical broadcast channel is

$$\mathcal{N}^{\text{c-c}}(x) \equiv \mathcal{N}_{X \rightarrow Y_1 Y_2}^{\text{c-c}}(|x\rangle \langle x|) = \sum_{(y_1, y_2) \in \mathcal{Y}_1 \times \mathcal{Y}_2} P_{Y_1 Y_2 | X}(y_1, y_2 | x) |y_1, y_2\rangle \langle y_1, y_2|. \quad (4)$$

where the super-script stands for a classical-input classical-output channel.

A classical-quantum (c-q) broadcast channel is defined, in a similar manner, as a mapping from \mathcal{X} to $\mathcal{D}(\mathcal{H}_B)$. To distinguish it from the general case, we denote the classical-quantum broadcast channel by $\mathcal{N}_{X \rightarrow B_1 B_2}^{\text{c-q}}$.




Figure 2: Identification over the quantum broadcast channel $\mathcal{N}_{A \rightarrow B_1 B_2}^{\otimes n}$. Alice chooses a message pair (i_1, i_2) . She encodes the messages by preparing an input state $\mathcal{E}_{A^n}(i_1, i_2)$, and sends the input system A^n through n uses of the quantum broadcast channel $\mathcal{N}_{A \rightarrow B_1 B_2}^{\otimes n}$. Bob 1 and Bob 2 receive the output systems B_1^n and B_2^n , respectively. As Bob k is interested in the message $i'_k \in [N_k]$, he performs the binary measurement $\mathcal{D}_{B_k^n}^{i'_k} = \{\mathbb{1} - D_{i'_k}^{(k)}, D_{i'_k}^{(k)}\}$ to determine whether i'_k was sent or not.

2.4 Identification Codes

In the following, we define the communication task of identification over a quantum broadcast channel, where the decoder is not required to recover the sender's message i , but simply determines whether a particular message i' was sent or not.

Definition 1. An (N_1, N_2, n) identification (ID) code for the quantum broadcast channel $\mathcal{N}_{A \rightarrow B_1 B_2}$ consists of an encoding channel $\mathcal{E}_{A^n} : [N_1] \times [N_2] \rightarrow \mathcal{D}(\mathcal{H}_A^{\otimes n})$ and a collection of binary decoding POVMs $\mathcal{D}_{B_1^n}^{i_1} = \{\mathbb{1} - D_{i_1}^{(1)}, D_{i_1}^{(1)}\}$ and $\mathcal{D}_{B_2^n}^{i_2} = \{\mathbb{1} - D_{i_2}^{(2)}, D_{i_2}^{(2)}\}$, for $i_1 \in [N_1]$ and $i_2 \in [N_2]$. We denote the identification code by $\mathcal{C} = (\mathcal{E}_{A^n}, \mathcal{D}_{B_1^n}, \mathcal{D}_{B_2^n})$.

The identification scheme is depicted in Figure 2. Alice chooses a pair of messages (i_1, i_2) , where $i_k \in [N_k]$, for $k \in \{1, 2\}$. She encodes the messages by preparing an input state $\rho_{A^n}^{i_1, i_2} \equiv \mathcal{E}_{A^n}(i_1, i_2)$, and sends the input system A^n through n uses of the quantum broadcast channel $\mathcal{N}_{A \rightarrow B_1 B_2}$. Bob 1 and Bob 2 receive the output systems B_1^n and B_2^n , respectively. Suppose that Bob k is interested in a particular message $i'_k \in [N_k]$, where $k \in \{1, 2\}$. Then, he performs the binary measurement $\{\mathbb{1} - D_{i'_k}^{(k)}, D_{i'_k}^{(k)}\}$ to determine whether i'_k was sent or not, and obtains a measurement outcome $s_k \in \{0, 1\}$. He declares 'no' if the measurement outcome is $s_k = 0$, and 'yes' if $s_k = 1$.

The ID rates of the code \mathcal{C} are defined as $R_k = \frac{1}{n} \log \log(N_k)$, for $k \in \{1, 2\}$. In this work, we assume that the ID messages i_k are uniformly distributed over the set $[N_k]$, for $k \in \{1, 2\}$. Therefore, the error probabilities are defined on average over the messages for the other receiver. Bob 1 makes an error in two cases: (1) He decides that i_1 was *not* sent (missed ID); (2) Bob 1 decides that i'_1 was sent, while in fact i_1 was sent, and $i_1 \neq i'_1$ (false ID). The probabilities of these two kinds of error, averaged over $i_2 \in [N_2]$, are defined as

$$\bar{e}_{1,1}(\mathcal{N}, n, \mathcal{C}, i_1) = \frac{1}{N_2} \sum_{i_2 \in [N_2]} \text{Tr} \left[(\mathbb{1} - D_{i_1}^{(1)}) \mathcal{N}^{\otimes n}(\mathcal{E}(i_1, i_2)) \right], \quad (5a)$$

$$\bar{e}_{1,2}(\mathcal{N}, n, \mathcal{C}, i'_1, i_1) = \frac{1}{N_2} \sum_{i_2 \in [N_2]} \text{Tr} \left[D_{i'_1}^{(1)} \mathcal{N}^{\otimes n}(\mathcal{E}(i_1, i_2)) \right], \quad (5b)$$

for $i_1, i'_1 \in [N_1]$ such that $i_1 \neq i'_1$. Similarly, Bob 2's error probabilities are

$$\bar{e}_{2,1}(\mathcal{N}, n, \mathcal{C}, i_2) = \frac{1}{N_1} \sum_{i_1 \in [N_1]} \text{Tr} \left[(\mathbb{1} - D_{i_2}^{(2)}) \mathcal{N}^{\otimes n}(\mathcal{E}(i_1, i_2)) \right], \quad (5c)$$

$$\bar{e}_{2,2}(\mathcal{N}, n, \mathcal{C}, i'_2, i_2) = \frac{1}{N_1} \sum_{i_1 \in [N_1]} \text{Tr} \left[D_{i'_2}^{(2)} \mathcal{N}^{\otimes n}(\mathcal{E}(i_1, i_2)) \right]. \quad (5d)$$

for $i_2, i'_2 \in [N_2]$ such that $i_2 \neq i'_2$.

An $(N_1, N_2, n, \lambda_1, \lambda_2)$ ID-code \mathcal{C} for the quantum broadcast channel $\mathcal{N}_{A \rightarrow B_1 B_2}$ satisfies

$$\max_{i_k \in [N_k]} \bar{e}_{k,1}(\mathcal{N}, n, \mathcal{C}, i_k) < \lambda_1, \quad (6a)$$

$$\max_{\substack{i_k, i'_k \in [N_k], \\ i'_k \neq i_k}} \bar{e}_{k,2}(\mathcal{N}, n, \mathcal{C}, i'_k, i_k) < \lambda_2, \quad (6b)$$

for $k \in \{1, 2\}$. An ID rate pair (R_1, R_2) is *achievable* if for every $\lambda_1, \lambda_2 > 0$ and sufficiently large n , there exists an $(\exp e^{nR_1}, \exp e^{nR_2}, n, \lambda_1, \lambda_2)$ ID-code. The ID capacity region $\mathsf{C}_{\text{ID}}(\mathcal{N})$ of the quantum broadcast channel $\mathcal{N}_{A \rightarrow B_1 B_2}$ is defined as the set of achievable rate pairs.

2.5 Previous Results

In the traditional transmission setting [6], the decoder Bob is required to find an estimate \hat{i} of Alice's message. This is a more stringent requirement than identification and it results in exponentially slower communication. Specifically, the number of messages scales as $\exp(nR)$ for transmission, whereas $\exp(e^{nR})$ for identification. While the transmission rate is measured in units of information bits per channel use, the identification rate has different units. Nonetheless, for the single-user channel, it turns out that the identification and transmission capacities have the same *value*.

In the single-user setting, the ID capacity of the classical-quantum channel was determined by Löber [13] and Ahlswede and Winter [14]. Let $\mathcal{W}_{X \rightarrow B}$ be a single-user c-q channel. The ID capacity $C_{\text{ID}}(\mathcal{W})$ is then defined, in a similar manner, as the supremum of achievable ID rates over the c-q channel $\mathcal{W}_{X \rightarrow B}$.

Theorem 1 (see [13, 14][64, Theorem 4]). The ID capacity of a single-user classical-quantum channel $\mathcal{W}_{X \rightarrow B}$ is given by

$$C_{\text{ID}}(\mathcal{W}) = \max_{P_X \in \mathcal{P}(\mathcal{X})} I(X; B)_\rho, \quad (7)$$

where $\rho_{XB} = \sum_{x \in \mathcal{X}} P_X(x) |x\rangle \langle x| \otimes \mathcal{W}(x)$.

While the single-user achievability proof in [7, 13] employs a random binning scheme based on transmission codes [65], we will see that the broadcast coding methods are significantly more involved and do not follow from the transmission characterization.

3 Results

Our results are presented below. Consider the quantum broadcast channel $\mathcal{N}_{A \rightarrow B_1 B_2}$, as defined in Subsection 2.3. Define the rate region $\mathcal{R}(\mathcal{N})$ as

$$\mathcal{R}(\mathcal{N}) = \bigcup_{P_X \in \mathcal{P}(\mathcal{X}), |\phi_A^x\rangle} \left\{ (R_1, R_2) : \begin{array}{l} R_1 \leq I(X; B_1)_\rho, \\ R_2 \leq I(X; B_2)_\rho \end{array} \right\} \quad (8)$$

with $\rho_{XB_1 B_2} = \sum_{x \in \mathcal{X}} P_X(x) |x\rangle \langle x| \otimes \mathcal{N}(|\phi_A^x\rangle \langle \phi_A^x|)$.

Theorem 2.

1. The region $\mathcal{R}(\mathcal{N})$ is achievable for identification over the quantum broadcast channel $\mathcal{N}_{A \rightarrow B_1 B_2}$. That is,

$$\mathsf{C}_{\text{ID}}(\mathcal{N}) \supseteq \mathcal{R}(\mathcal{N}). \quad (9)$$

2. The identification capacity region of a classical-quantum broadcast channel $\mathcal{N}_{X \rightarrow B_1 B_2}^{c-q}$ is given by

$$C_{\text{ID}}(\mathcal{N}^{c-q}) = \bigcup_{P_X \in \mathcal{P}(\mathcal{X})} \left\{ (R_1, R_2) : \begin{array}{l} R_1 \leq I(X; B_1)_\rho, \\ R_2 \leq I(X; B_2)_\rho \end{array} \right\}, \quad (10)$$

with $\rho_{XB_1 B_2} = \sum_{x \in \mathcal{X}} P_X(x) |x\rangle \langle x| \otimes \mathcal{N}^{c-q}(x)$.

The proof of part 1 is given in Section 5, where we show that all rate pairs in the interior of the region $\mathcal{R}(\mathcal{N})$ are achievable. In Section 6, we prove part 2 and show the classical-quantum converse part, *i.e.* that no rate pair outside the region above can be achieved for identification over the classical-quantum broadcast channel. In the proof of part 1, we use the pool-selection method by Bracher and Lapidoth [24, 25]. This will enable the same extension to the broadcast setting as in [24, 25]. On the other hand, in the converse proof, we used a different approach exploiting recent observations by Boche et al. [18] along with the methods of Ahlswede and Winter [14].

Remark 2. As mentioned in Subsection 2.5, in the single-user setting, the ID and transmission capacity characterizations are identical. On the other hand, in the broadcast ID setting, we see a departure from this equivalence [24, 25, 28]. The examples in the following section demonstrate this departure in a more explicit manner, showing that the ID capacity region can be strictly larger than the transmission capacity region.

Remark 3. Consider the classical-quantum broadcast channel. In general, the rate R_k of User k must be limited by the ID capacity of the single-user channel from A to B_k , for $k \in \{1, 2\}$. This observation leads to the following rectangular upper bound,

$$C_{\text{ID}}(\mathcal{N}^{c-q}) \subseteq \left\{ (R_1, R_2) : \begin{array}{l} R_1 \leq C_{\text{ID}}^{(1)}, \\ R_2 \leq C_{\text{ID}}^{(2)} \end{array} \right\}, \quad (11)$$

where $C_{\text{ID}}^{(k)} = \max_{P_X} I(X; B_k)_\rho$. However, in identification over the broadcast channel, the users cannot necessarily achieve the full capacity of each marginal channel simultaneously, since both marginal channels must share the same input distribution in the capacity formula on the right hand side of (10). Equality holds in (11) if the same input distribution P_X^* maximizes both mutual informations simultaneously, *i.e.* when

$$P_X^* = \arg \max_{P_X} I(X; B_1)_\rho = \arg \max_{P_X} I(X; B_2)_\rho. \quad (12)$$

4 Examples

As examples, we consider a depolarizing broadcast channel and the pure-loss bosonic broadcast channel.

4.1 Depolarizing Broadcast Channel

Consider a qubit depolarizing broadcast channel $\mathcal{N}_{A \rightarrow B_1 B_2}$ specified as follows. By linearity, it suffices to write the output for the input states $|0\rangle_A$ and $|1\rangle_A$. Then, let $\mathcal{N}_{A \rightarrow B_1 B_2} : \mathcal{D}(\mathcal{H}_A) \rightarrow \mathcal{D}(\mathcal{H}_{B_1} \otimes \mathcal{H}_{B_2})$ be a map such that

$$\begin{aligned} |x\rangle_A &\mapsto \left[(1 - p_1) |x\rangle \langle x|_{B_1} + p_1 \frac{\mathbb{1}_{B_1}}{2} \right] \\ &\otimes \left[(1 - p_2) |x\rangle \langle x|_{B_2} + p_2 \frac{\mathbb{1}_{B_2}}{2} \right] \end{aligned} \quad (13)$$

for $x \in \{0, 1\}$, where $p_1, p_2 \in [0, 1]$ are given parameters. Observe that each marginal is a standard depolarizing channel, *i.e.* $\mathcal{N}^{(k)}(\rho) = (1 - p_k)\rho + p_k\frac{\mathbb{1}}{2}$, for $k \in \{1, 2\}$. The ID capacity region of the qubit depolarizing broadcast channel $\mathcal{N}_{A \rightarrow B_1 B_2}$ is given by

$$\mathsf{C}_{\text{ID}}(\mathcal{N}) = \left\{ (R_1, R_2) : \begin{array}{l} R_1 \leq 1 - H_2\left(\frac{p_1}{2}\right), \\ R_2 \leq 1 - H_2\left(\frac{p_2}{2}\right) \end{array} \right\}, \quad (14)$$

where $H_2(x) = -x \log(x) - (1-x) \log(1-x)$ is the binary entropy function. This result is obtained by a straightforward extension of the classical proof. The converse part immediately follows from the single-user characterization, since the ID capacity of the single-user marginal channel $\mathcal{N}_{A \rightarrow B_k}^{(k)}$ is given by $\mathsf{C}_{\text{ID}}(\mathcal{N}^{(k)}) = 1 - H_2\left(\frac{p_k}{2}\right)$. To show achievability, we apply part 1 of Theorem 2 and set $P_X = \left(\frac{1}{2}, \frac{1}{2}\right)$ over the ensemble $\{|0\rangle, |1\rangle\}$.

4.2 Bosonic Broadcast Channel

To demonstrate our results, consider the single-mode bosonic broadcast channel. We extend the finite-dimension result in Theorem 2 to the bosonic channel with infinite-dimension Hilbert spaces based on the discretization limiting argument by Guha *et al.* [66]. A detailed description of (continuous-variable) bosonic systems can be found in [54]. Here, we only define the notation for the quantities that we use. We use hat-notation, *e.g.* \hat{a} , \hat{b} , \hat{e} , to denote operators that act on a quantum state. The single-mode Hilbert space is spanned by the Fock basis $\{|n\rangle\}_{n=0}^{\infty}$. Each $|n\rangle$ is an eigenstate of the number operator $\hat{n} = \hat{a}^\dagger \hat{a}$, where \hat{a} is the bosonic field annihilation operator. In particular, $|0\rangle$ is the vacuum state of the field. The *creation operator* \hat{a}^\dagger creates an excitation: $\hat{a}^\dagger |n\rangle = \sqrt{n+1} |n+1\rangle$, for $n \geq 0$. Reversely, the *annihilation operator* \hat{a} takes away an excitation: $\hat{a} |n+1\rangle = \sqrt{n+1} |n\rangle$. A coherent state $|\alpha\rangle$, where $\alpha \in \mathbb{C}$, corresponds to an oscillation of the electromagnetic field, and it is the outcome of applying the displacement operator to the vacuum state, *i.e.* $|\alpha\rangle = D(\alpha)|0\rangle$, which resembles the creation operation, with $D(\alpha) \equiv \exp(\alpha \hat{a}^\dagger - \alpha^* \hat{a})$. A thermal state $\tau(N)$ is a Gaussian mixture of coherent states, where

$$\tau(N) \equiv \int_{\mathbb{C}} d^2\alpha \frac{e^{-|\alpha|^2/N}}{\pi N} |\alpha\rangle \langle \alpha| = \frac{1}{N+1} \sum_{n=0}^{\infty} \left(\frac{N}{N+1}\right)^n |n\rangle \langle n| \quad (15)$$

with an average photon number $N \geq 0$.

Consider a bosonic broadcast channel, whereby the channel input is an electromagnetic field mode with annihilation operator \hat{a} , and the output is a pair of modes with annihilation operators \hat{b}_1 and \hat{b}_2 . The annihilation operators correspond to Alice, Bob 1, and Bob 2, respectively. The input-output relation of the pure-loss bosonic broadcast channel in the Heisenberg picture [67] is given by bosonic channel is given by

$$\hat{b}_1 = \sqrt{\eta} \hat{a} + \sqrt{1-\eta} \hat{e}, \quad (16)$$

$$\hat{b}_2 = \sqrt{1-\eta} \hat{a} - \sqrt{\eta} \hat{e} \quad (17)$$

where \hat{e} is associated with the environment noise which is the vacuum state $|0\rangle$, and the parameter η is the transmissivity, $0 \leq \eta \leq 1$, which captures, for instance, the length of the optical fiber and its absorption length [68]. The relations above correspond to the outputs of a beam splitter, as illustrated in Figure 3. It is assumed that the encoder uses a coherent state protocol with an input constraint. That is, the input state is a coherent state $|x\rangle$, $x \in \mathbb{C}$, such that each codeword satisfies $\frac{1}{n} \sum_{i=1}^n |x_i|^2 \leq N_A$.




Figure 3: The beam splitter relation of the single-mode bosonic broadcast channel. The channel input is an electromagnetic field mode with annihilation operator \hat{a} , and the output is a pair of modes with annihilation operators \hat{b}_1 and \hat{b}_2 , corresponding to each receiver. The mode \hat{e} is associated with the environment noise which is the vacuum state $|0\rangle$, and the parameter η is the transmissivity, which captures the length of the optical fiber and its absorption length.

Based on part 1 of Theorem 2, the ID capacity region of the pure-loss bosonic broadcast channel is given by

$$\mathsf{C}_{\text{ID}}(\mathcal{N}) = \left\{ (R_1, R_2) : \begin{array}{l} R_1 \leq g(\eta N_A) \\ R_2 \leq g((1-\eta)N_A) \end{array} \right\} \quad (18)$$

where $g(N)$ is the entropy of a thermal state with mean photon number N ,

$$g(x) = \begin{cases} (x+1)\log(x+1) - x\log(x) & x > 0 \\ 0 & x = 0. \end{cases} \quad (19)$$

See Figure 1. As in the previous example, the converse part immediately follows from the single-user capacity characterization. To show achievability, set the input to be an ensemble of coherent states, $|X\rangle$, with a circularly-symmetric Gaussian distribution with zero mean and variance $N_A/2$.

On the other hand, the transmission capacity region of the single-mode pure-loss bosonic broadcast channel is [56, 66],

$$\mathsf{C}_{\text{T}}(\mathcal{N}) = \bigcup_{0 \leq \beta \leq 1} \left\{ (R_1, R_2) : \begin{array}{l} R_1 \leq g(\eta\beta N_A) \\ R_2 \leq g((1-\eta)N_A) - g((1-\eta)\beta N_A) \end{array} \right\}. \quad (20)$$

where the subscript ‘T’ stands for ‘Transmission’, under the assumption that the minimum output-entropy conjecture holds (see Strong Conjecture 2 in [57]). The ID capacity region and the transmission capacity region are depicted in Figure 1 as the area below the solid blue line and below the dashed red line, respectively. We note that our result does not rely on any conjectures. As the figure indicates, the ID capacity region is significantly larger.

5 Proof of Part 1

In this section we lower-bound the capacity region in Theorem 2, *i.e.* we show that

$$\mathsf{C}_{\text{ID}}(\mathcal{N}) \supseteq \mathcal{R}(\mathcal{N}). \quad (21)$$

In the classical achievability proof, Bracher and Lapdidoth [24, 25] first generate a single-user random code, based on a pool-selection technique, as shown below. Then, a similar pool-selection code is constructed for the BC using a pair of single-user codes, one for each receiver. It is shown in [24, 25] that the corresponding ID error probabilities for the BC can be approximated in terms of the error probabilities of the single-user codes. We use a similar approach, and begin with the *single-user* quantum channel.

5.1 Quantum Method of Types

Before we give the achievability proof, we briefly review the basic method-of-types properties that will be useful in the analysis. The n -type \hat{P}_{x^n} of a sequence $x^n \in \mathcal{X}^n$ is defined by $\hat{P}_{x^n}(a) = \frac{n(a|x^n)}{n}$ for $a \in \mathcal{X}$, where $n(a|x^n)$ is the number of occurrences of the letter a in the sequence x^n . The set of all n -types over a set \mathcal{X} is denoted by $\mathcal{P}(n, \mathcal{X})$. Joint and conditional types are defined similarly, as in [69]. Furthermore, an ϵ -typical set is defined as follows. Given a PMF $P_X \in \mathcal{P}(\mathcal{X})$ over \mathcal{X} , define the strongly δ -typical set,

$$\mathcal{T}_\delta^n(P_X) = \{x^n \in \mathcal{X}^n : |\hat{P}_{x^n}(a) - P_X(a)| \leq \delta \cdot P_X(a), a \in \mathcal{X}\}. \quad (22)$$

Given $P_{Y|X} : \mathcal{X} \rightarrow \mathcal{P}(\mathcal{Y})$, the *conditionally* δ -typical set is defined as

$$\mathcal{T}_\delta^n(x^n) = \{y^n \in \mathcal{Y}^n : (x^n, y^n) \in \mathcal{T}_\delta^n(\hat{P}_{x^n} \times P_{Y|X})\}. \quad (23)$$

We will use the property

$$\Pr(X^n \in \mathcal{T}_\delta^n(P_X)) \geq 1 - 2|\mathcal{X}|2^{-2n\delta^2} \quad (24)$$

(see [70, Lemma 2.12]). In the analysis, we will repeatedly use Hoeffding's inequality: For an i.i.d. random sequence $(X_t)_{t=1}^n$ satisfying $0 < X_t < 1$,

$$\Pr\left\{\frac{1}{n}\sum_{t=1}^n X_t - \mathbb{E}[X_1] \geq \alpha\right\} \leq e^{-2\alpha^2 n} \quad (25)$$

for all $\alpha > 0$.

Consider the state of a quantum system generated from an ensemble $\{P_X(x), |x\rangle\}_{x \in \mathcal{X}}$. Then, the average density operator is $\rho = \sum_{x \in \mathcal{X}} P_X(x) |x\rangle\langle x|$. The projector onto the δ -typical subspace is defined as

$$\Pi^\delta(\rho) \equiv \sum_{x^n \in \mathcal{T}_\delta^n(P_X)} |x^n\rangle\langle x^n|. \quad (26)$$

For every $\delta > 0$ and sufficiently large n , the δ -typical projector satisfies

$$\text{Tr}(\Pi^\delta(\rho)\rho^{\otimes n}) \geq 1 - 2^{-b\delta n}, \quad (27)$$

$$\begin{aligned} 2^{-n(H(\rho)+c\delta)}\Pi^\delta(\rho) &\leq \Pi^\delta(\rho)\rho^{\otimes n}\Pi^\delta(\rho) \\ &\leq 2^{-n(H(\rho)-c\delta)}\Pi^\delta(\rho), \end{aligned} \quad (28)$$

$$\text{Tr}(\Pi^\delta(\rho)) \leq 2^{n(H(\rho)+c\delta)} \quad (29)$$

where $b, c > 0$ are constants [71, Subsection 15.1.3], while the exponential convergence in (27) follows from Hoeffding's inequality (25) (see proof of (24) in [70, Lemma 2.12]).

We will also need the conditional δ -typical subspace. As in [71, Definition 15.2.3], given a classical-quantum state σ_{XB} , the conditional δ -typical projector $\Pi^\delta(\sigma_B|x^n)$ is defined by

$$\Pi^\delta(\sigma_B|x^n) = \bigotimes_{x \in \mathcal{X}} \Pi^\delta\left((\sigma_B^x)^{\otimes N(x|x^n)}\right). \quad (30)$$

Given $x^n \in \mathcal{T}_\delta^n(P_X)$, it satisfies

$$\text{Tr}\left(\Pi^\delta(\sigma_B|x^n)\sigma_{B^n}^{x^n}\right) \geq 1 - 2^{-b'\delta n}, \quad (31)$$

$$\begin{aligned} 2^{-n(H(B|X)_\sigma+c'\delta)}\Pi^\delta(\sigma_B|x^n) &\leq \Pi^\delta(\sigma_B|x^n)\sigma_{B^n}^{x^n}\Pi^\delta(\sigma_B|x^n) \\ &\leq 2^{-n(H(B|X)_\sigma-c'\delta)}\Pi^\delta(\sigma_B|x^n), \end{aligned} \quad (32)$$

$$\text{Tr}(\Pi^\delta(\sigma_B|x^n)) \leq 2^{n(H(B|X)_\sigma+c'\delta)} \quad (33)$$

where $b', c' > 0$ is a constant, $\sigma_{B^n}^{x^n} = \bigotimes_{i=1}^n \sigma_{B_i}^{x_i}$. Furthermore,

$$\text{Tr}(\Pi^\delta(\sigma_B)\sigma_{B^n}^{x^n}) \geq 1 - 2^{-c'\delta n} \quad (34)$$

(see [71, Property 15.2.7]), and hence, by the Gentle Operator Lemma [71, Lemma 9.4.2],

$$\left\| \sigma_{B^n}^{x^n} - \Pi^\delta(\sigma_B)\sigma_{B^n}^{x^n}\Pi^\delta(\sigma_B) \right\|_1 \leq 2^{-c'\delta n/2+1}. \quad (35)$$

5.2 Single-User Quantum Channel

Let $\mathcal{L}_{A \rightarrow B}$ be a single-user quantum channel.

5.2.1 Code Construction

Let $N = \exp e^{nR}$ be the code size. Fix a PMF P_X over \mathcal{X} , a pool rate R_{pool} , and a binning rate \tilde{R} , such that

$$R < \tilde{R} < I(X; B)_\rho \quad (36)$$

$$R_{\text{pool}} > \tilde{R}. \quad (37)$$

We generate the codebook such that all codewords are δ -typical. Therefore, consider the distribution

$$P_{X^n}(x^n) = \frac{P_X^n(x^n)}{P_X^n(\mathcal{T}_\delta^n(P_X))} \cdot \mathbb{1}(x^n \in \mathcal{T}_\delta^n(P_X)). \quad (38)$$

For every index $v \in \mathcal{V} = [e^{nR_{\text{pool}}}]$, choose a codeword $F(v) \sim P_{X^n}$ at random. Then, for every $i \in [N]$, decide whether to add v to the set \mathcal{V}_i by a binary experiment, with probability $e^{-n\tilde{R}}/|\mathcal{V}| = e^{-n(R_{\text{pool}}-\tilde{R})}$. That is, decide to include v in \mathcal{V}_i with probability $e^{-n(R_{\text{pool}}-\tilde{R})}$, and not to include it with probability $1 - e^{-n(R_{\text{pool}}-\tilde{R})}$. Reveal this construction to all parties. Denote the collection of codewords and index bins by

$$\mathcal{B} = \left(\{F(v)\}_{v \in \mathcal{V}}, \{\mathcal{V}_i\}_{i=1}^N \right). \quad (39)$$

5.2.2 Encoding

To send an ID Message $i \in [N]$, Alice chooses an index v uniformly at random from \mathcal{V}_i . If \mathcal{V}_i is non-empty, she prepares the state

$$\left| \phi_{A^n}^{F(v)} \right\rangle \equiv \bigotimes_{t=1}^n \left| \phi_A^{F_t(v)} \right\rangle, \quad (40)$$

where $F_t(v)$ is the t -th symbol of the sequence $F(v)$. Otherwise, if $\mathcal{V}_i = \emptyset$, she prepares $|\phi_{A^n}^{F(1)}\rangle$. Then, Alice transmits the systems A^n through the channel. Therefore, if $\mathcal{V}_i \neq \emptyset$, then the average input state $\mathcal{E}_{A^n}(i)$ is given by

$$\mathcal{E}_{A^n}(i) = \frac{1}{|\mathcal{V}_i|} \sum_{v \in \mathcal{V}_i} \left| \phi_{A^n}^{F(v)} \right\rangle \left\langle \phi_{A^n}^{F(v)} \right|. \quad (41)$$

5.2.3 Decoding

Bob receives the output systems B^n and he would like to determine whether the message i' was sent. To this end, he selects any constant δ such that

$$0 < \delta < \frac{I(X; B)_\rho - \tilde{R}}{c + c'}, \quad (42)$$

where $c, c' > 0$ are constants as in Section 5.1. Then, he performs a series of binary decoding measurements (POVMs)

$$\mathcal{D}^{F(v)} = \left\{ \mathbb{1} - \Pi \Pi^{F(v)} \Pi, \Pi \Pi^{F(v)} \Pi \right\}, \quad (43)$$

where we denote $\Pi \equiv \Pi^\delta(\rho_B)$ and $\Pi^{F(v)} \equiv \Pi^\delta(\rho_{B^n} | F(v))$. Bob obtains a binary sequence of measurement outcomes $(a(v))_{v \in \mathcal{V}_{i'}}$. If $a(v) = 1$ for some $v \in \mathcal{V}_{i'}$, then Bob declares that i' was sent. Otherwise, he declares that i' was not sent. Note that we can also construct one POVM \mathcal{D}'_{B^n} that is equivalent to the series of measurements.

Thus, the ID code that is associated with the construction above is denoted by

$$\mathcal{C}_B = (\mathcal{E}_{A^n}, \mathcal{D}_{B^n}).$$

5.2.4 Error Analysis

We show that for some $\tau > 0$, the error probabilities of the random code \mathcal{C}_B satisfy

$$\lim_{n \rightarrow \infty} \Pr \left\{ \max_{i \in [N]} e_1(\mathcal{L}_{A \rightarrow B}, n, \mathcal{C}_B, i) \geq e^{-n\tau} \right\} = 0, \quad (44a)$$

$$\lim_{n \rightarrow \infty} \Pr \left\{ \max_{i, i' \in [N]} \max_{i \neq i'} e_2(\mathcal{L}_{A \rightarrow B}, n, \mathcal{C}_B, i', i) \geq e^{-n\tau} \right\} = 0. \quad (44b)$$

The codebook that is used here is the same as in the classical derivation [24, 25]. Hence, we can use the cardinality bounds for the index bins $\{\mathcal{V}_i\}_{i \in [N]}$ that were established in [24, 25]. Denote the collection of index bins by $\mathcal{V}^N = \{\mathcal{V}_i\}_{i \in [N]}$.

Lemma 3 (see [24, Lemma 5]). Given $\mu > 0$, let \mathcal{G}_μ be the set of all realizations \mathcal{V}^N of \mathcal{V}^N such that

$$|\mathcal{V}_i| > (1 - \delta_n) e^{n\tilde{R}}, \quad (45)$$

$$|\mathcal{V}_i| < (1 + \delta_n) e^{n\tilde{R}}, \quad (46)$$

$$|\mathcal{V}_i \cap \mathcal{V}_{i'}| < 2\delta_n e^{n\tilde{R}} \quad (47)$$

for all $\mathcal{V}_i, \mathcal{V}_{i'} \in \mathcal{V}^N, i \neq i'$, where $\delta_n = e^{-n\mu/2}$. Then, the probability that $\mathcal{V}^N \in \mathcal{G}_\mu$ converges to 1 as $n \rightarrow \infty$, *i.e.*

$$\lim_{n \rightarrow \infty} \Pr \left\{ \mathcal{V}^N \in \mathcal{G}_\mu \right\} = 1, \quad (48)$$

for $\mu < R_{\text{pool}} - \tilde{R}$.

Hence, it suffices to consider the bin collection realizations \mathcal{V}^N of \mathcal{V}^N that satisfy (46)–(47), for $\mu \in (0, R_{\text{pool}} - \tilde{R})$. Thus, the input state is as in (41), since $\mathcal{V}_i \neq \emptyset$ by (45).

Missed ID Error Consider an index bin $\mathcal{V}_i \in \mathcal{V}^N$. We bound the probability of the missed-ID error (first kind), given by

$$e_1(\mathcal{L}_{A \rightarrow B}, n, \mathcal{C}_B, i) = \frac{1}{|\mathcal{V}_i|} \sum_{v \in \mathcal{V}_i} \Pr(a(v') = 0, \text{ for all } v' \in \mathcal{V}_i \mid F(v) \text{ was sent}) \quad (49)$$

Note that

$$\begin{aligned} & \Pr(a(v') = 0, \text{ for all } v' \in \mathcal{V}_i \mid F(v) \text{ was sent}) \\ &= \text{Tr} \left(\prod_{v' \in \mathcal{V}_i} (\mathbb{1} - \Pi \Pi^{F(v')} \Pi) \rho_{B^n}^{F(v)} \right) \\ &\leq \text{Tr} \left((\mathbb{1} - \Pi \Pi^{F(v)} \Pi) \rho_{B^n}^{F(v)} \right) \\ &= 1 - \text{Tr} \left(\Pi \Pi^{F(v)} \Pi \rho_{B^n}^{F(v)} \right) \\ &= 1 - \text{Tr} \left(\Pi^{F(v)} \Pi \rho_{B^n}^{F(v)} \Pi \right) \\ &\leq 1 - \text{Tr} \left(\Pi^{F(v)} \rho_{B^n}^{F(v)} \right) + \left\| \rho_{B^n}^{F(v)} - \Pi \rho_{B^n}^{F(v)} \Pi \right\|_1. \end{aligned} \quad (50)$$

By the Gentle Operator Lemma [71, Lemma 9.4.2], we have $\left\| \rho_{B^n}^{F(v)} - \Pi \rho_{B^n}^{F(v)} \Pi \right\|_1 \leq e^{-nc'\delta/2+1}$ (see (35)), because $F(v) \in \mathcal{T}_\delta^n(P_X)$, for all $v \in \mathcal{V}$. Since also $\text{Tr} \left(\Pi^{F(v)} \rho_{B^n}^{F(v)} \right) \geq 1 - e^{-nb'\delta}$ (31), there exists $\tau_1 > 0$ such that

$$e_1(\mathcal{L}_{A \rightarrow B}, n, \mathcal{C}_B, i) \leq e^{-nb'\delta} + e^{-nc'\delta/2+1} < e^{-n\tau_1}. \quad (51)$$

False ID Error Next, we bound the probability of an error of the second kind. Suppose that the sender sends an ID message i and the receiver is interested in $i' \neq i$. Recall that we can restrict our attention to realizations $\mathcal{V}^N = \{\mathcal{V}_i\} \in \mathcal{G}_\mu$, following Lemma 3. Let $v \in \mathcal{V}_i$ be the index that Alice has chosen. Observe that

$$\begin{aligned} & e_2(\mathcal{L}_{A \rightarrow B}, n, \mathcal{C}_B, i', i) \\ &= \frac{1}{|\mathcal{V}_i|} \sum_{v \in \mathcal{V}_i} \Pr(\exists v' \in \mathcal{V}_{i'} : a(v') = 1 \mid F(v) \text{ was sent}) \\ &\leq \frac{1}{|\mathcal{V}_i|} \sum_{v \in \mathcal{V}_i \cap \mathcal{V}_{i'}} 1 + \frac{1}{|\mathcal{V}_i|} \sum_{v \in \mathcal{V}_i \cap \mathcal{V}_{i'}^c} \Pr(\exists v' \in \mathcal{V}_{i'} : a(v') = 1 \mid F(v) \text{ was sent}) \\ &\leq \frac{1}{|\mathcal{V}_i|} |\mathcal{V}_i \cap \mathcal{V}_{i'}| + \frac{1}{|\mathcal{V}_i \cap \mathcal{V}_{i'}^c|} \sum_{v \in \mathcal{V}_i \cap \mathcal{V}_{i'}^c} \Pr(\exists v' \in \mathcal{V}_{i'} : a(v') = 1 \mid F(v) \text{ was sent}), \end{aligned} \quad (52)$$

since any probability is at most 1 and $|\mathcal{V}_i \cap \mathcal{V}_{i'}^c| \leq |\mathcal{V}_i|$. The first term is bounded by

$$\frac{|\mathcal{V}_i \cap \mathcal{V}_{i'}|}{|\mathcal{V}_i|} < \frac{2\delta_n}{1 - \delta_n} < \delta_n \quad (53)$$

(see (45) and (47)), where the second inequality holds as $\delta_n < 1/2$, for sufficiently large n .

It remains to bound the second term in the right-hand side of (52), for which $v \in \mathcal{V}_i$ and $v \notin \mathcal{V}_{i'}$. For every pair of indices $v \notin \mathcal{V}_{i'}$ and $v' \in \mathcal{V}_{i'}$, we have that the codewords $F(v)$ and $F(v')$ are statistically independent.

Assume without loss of generality that $\mathcal{V}_{i'} = \{1, 2, \dots, |\mathcal{V}_{i'}|\}$. Let $\mathcal{A}_{i'}(v')$ denote the event that $v' \in \mathcal{V}_{i'}$ is the first index to hit 'yes' as the measurement outcome, *i.e.* $a(1) = a(2) = \dots = a(v' - 1) = 0$ and $a(v') = 1$. Then,

$$\begin{aligned} \Pr(\mathcal{A}_{i'}(v') \mid F(v) \text{ was sent}) &= \text{Tr} \left(D_{v'} D_{v'-1}^c \cdots D_1^c \rho_{B^n}^{F(v)} D_1^c \cdots D_{v'-1}^c \right) \\ &\leq \text{Tr} \left(D_{v'} \rho_{B^n}^{F(v)} \right) \\ &= \text{Tr} \left(\text{III} \Pi^{F(v')} \Pi \rho_{B^n}^{F(v)} \right) \\ &= \text{Tr} \left(\Pi^{F(v')} \Pi \rho_{B^n}^{F(v)} \Pi \right) \end{aligned} \quad (54)$$

where $D_v = \text{III} \Pi^{F(v)} \Pi$ and $D_v^c = \mathbb{1} - D_v$. Thus,

$$\mathbb{E}_{\mathcal{B}} [\Pr(\mathcal{A}_{i'}(v') \mid F(v) \text{ was sent})] \leq \text{Tr} \left(\mathbb{E} [\Pi^{F(v')}] \Pi \mathbb{E} [\rho_{B^n}^{F(v)}] \Pi \right), \quad (55)$$

and note that by (24), there exists ϵ_n with $\lim_{n \rightarrow \infty} \epsilon_n = 0$ such that

$$\begin{aligned} \mathbb{E} [\rho_{B^n}^{F(v)}] &= \frac{1}{P_X(\mathcal{T}_\delta^n(P_X))} \sum_{x^n \in \mathcal{T}_\delta^n(P_X)} P_X^n(x^n) \rho_{B^n}^{x^n} \\ &\preceq \frac{1}{1 - \epsilon_n} \sum_{x^n \in \mathcal{X}^n} P_X^n(x^n) \rho_{B^n}^{x^n} \\ &= \frac{1}{1 - \epsilon_n} \rho_B^{\otimes n}. \end{aligned} \quad (56)$$

It follows that

$$\begin{aligned} (1 - \epsilon_n) \mathbb{E}_{\mathcal{B}} [\Pr(\mathcal{A}_{i'}(v') \mid F(v) \text{ was sent})] &= \text{Tr} \left(\mathbb{E} [\Pi^{F(v')}] \Pi \rho_B^{\otimes n} \Pi \right) \\ &\stackrel{(a)}{\leq} e^{-n(H(B)_\rho - c\delta)} \text{Tr} \left(\mathbb{E} [\Pi^{F(v')}] \Pi \right) \\ &\leq e^{-n(H(B)_\rho - c\delta)} \text{Tr} \left(\mathbb{E} [\Pi^{F(v')}] \right) \\ &\stackrel{(b)}{<} e^{-n(H(B)_\rho - H(B|X)_\rho - (c+c')\delta)} \\ &= e^{-n(I(X;B)_\rho - (c+c')\delta)} \end{aligned} \quad (57)$$

where (a) holds by (28), and (b) by (33) since $F(v') \in \mathcal{T}_\delta^n(P_X)$ for all $v' \in \mathcal{V}$. Therefore, there exists $\theta > 0$ such that

$$\begin{aligned} \mathbb{E}_{\mathcal{B}} [\Pr(\exists v' \in \mathcal{V}_{i'} : a(v') \mid F(v) \text{ was sent})] &= \mathbb{E}_{\mathcal{B}} [\Pr(\exists v' \in \mathcal{V}_{i'} : \mathcal{A}_{i'}(v') \mid F(v) \text{ was sent})] \\ &\stackrel{(a)}{\leq} \frac{1}{1 - \epsilon_n} \sum_{v' \in \mathcal{V}_{i'}} \mathbb{E}_{\mathcal{B}} [\Pr(\mathcal{A}_{i'}(v') \mid F(v) \text{ was sent})] \\ &\leq \frac{1}{1 - \epsilon_n} |\mathcal{V}_{i'}| e^{-n(I(X;B)_\rho - (c+c')\delta)} \\ &\stackrel{(b)}{<} \frac{1 + \delta_n}{1 - \epsilon_n} e^{-n(I(X;B)_\rho - \tilde{R} - (c+c')\delta)} \\ &\stackrel{(c)}{<} e^{-n\theta}, \end{aligned} \quad (58)$$

where (a) follows from the union-of-events bound, (b) is due to (46), and (c) holds since $(c + c')\delta < I(X; B)_\rho - \tilde{R}$ by (42).

We show now that the false-ID error is small with high probability. Let α satisfy

$$0 < \alpha < (\tilde{R} - R)/2. \quad (59)$$

By the union-of-events bound,

$$\begin{aligned} & \Pr \left(\max_{i' \in [N]} \max_{i \neq i'} e_2(\mathcal{L}_{A \rightarrow B}, n, \mathcal{C}_B, i', i) \geq \delta_n + e^{-n\theta} + e^{-n\alpha} \right) \\ & \leq \sum_{i' \in [N]} \sum_{i \neq i'} \Pr \left(e_2(\mathcal{L}_{A \rightarrow B}, n, \mathcal{C}_B, i', i) \geq \delta_n + e^{-n\theta} + e^{-n\alpha} \right). \end{aligned} \quad (60)$$

Note that by (52) and (53),

$$e_2(\mathcal{L}_{A \rightarrow B}, n, \mathcal{C}_B, i', i) \leq \delta_n + \frac{1}{|\mathcal{V}_i \cap \mathcal{V}_{i'}^c|} \sum_{v \in \mathcal{V}_i \cap \mathcal{V}_{i'}^c} \Pr(\exists v' \in \mathcal{V}_{i'} : a(v') = 1 \mid F(v) \text{ was sent}) \quad (61)$$

Therefore, there exists $\tau_2 > 0$ such that

$$\begin{aligned} & \Pr \left\{ \max_{i' \in [N]} \max_{i \neq i'} e_2(\mathcal{L}_{A \rightarrow B}, n, \mathcal{C}_B, i', i) \geq e^{-n\tau_2} \right\} \\ & \leq \sum_{i' \in [N]} \sum_{i \neq i'} \Pr \left\{ \frac{1}{|\mathcal{V}_i \cap \mathcal{V}_{i'}^c|} \sum_{v \in \mathcal{V}_i \cap \mathcal{V}_{i'}^c} \Pr(\exists v' \in \mathcal{V}_{i'} : a(v') = 1 \mid F(v) \text{ was sent}) \right. \\ & \quad \left. \geq e^{-n\theta} + e^{-n\alpha} \right\} \\ & \stackrel{(a)}{\leq} \exp \left(-2e^{-2n\alpha} |\mathcal{V}_i \cap \mathcal{V}_{i'}^c| \right) \\ & \stackrel{(b)}{<} \exp \left(2e^{nR} - e^{-2n\alpha} e^{-n\tilde{R}} \right), \end{aligned} \quad (62)$$

for sufficiently large n , where (a) follows from Hoeffding's inequality (see (25)), since the codewords $F(v), v \in \mathcal{V}$ are i.i.d., (b) follows from $N = \exp(e^{nR})$, and

$$|\mathcal{V}_i \cap \mathcal{V}_{i'}^c| = |\mathcal{V}_i| - |\mathcal{V}_i \cap \mathcal{V}_{i'}| > (1 - \delta_n)e^{n\tilde{R}} - 2\delta_n e^{n\tilde{R}} \geq e^{n\tilde{R}}/2, \quad (63)$$

as $|\mathcal{V}_i| \geq (1 - \delta_n)e^{n\tilde{R}}$ and $|\mathcal{V}_i \cap \mathcal{V}_{i'}| < 2\delta_n e^{n\tilde{R}}$, by Lemma 3 (see (45) and (47), respectively), where the last inequality follows from $\delta_n < 1/2$, for sufficiently large n .

Based on (51) and (62), we have established that (44) holds for $\tau = \min\{\tau_1, \tau_2\}$.

5.3 Broadcast Channel

In this section, we show the direct part for the ID capacity region of the quantum broadcast channel. That is, we show that $\mathsf{C}_{\text{ID}}(\mathcal{N}) \supseteq \mathcal{R}(\mathcal{N})$. The analysis makes use of our single-user derivation above.

5.3.1 Code Construction

We extend Bracher and Lapdith's [24, 25] idea to combine two BL codebooks $\mathcal{B}^{(1)}, \mathcal{B}^{(2)}$ that share the same pool. Fix a PMF P_X over \mathcal{X} and rates R_k, \tilde{R}_k , for $k \in \{1, 2\}$, that

satisfy

$$R_1 < \tilde{R}_1 < \min_{s \in \mathcal{S}} I(X; B_1)_\rho \quad (64a)$$

$$R_2 < \tilde{R}_2 < \min_{s \in \mathcal{S}} I(X; B_2)_\rho \quad (64b)$$

$$\max \{ \tilde{R}_1, \tilde{R}_2 \} < R_{\text{pool}} \quad (64c)$$

$$R_{\text{pool}} < \tilde{R}_1 + \tilde{R}_2. \quad (64d)$$

Let $N_k = e^{nR_k}$. For every index $v \in \mathcal{V} = [e^{nR_{\text{pool}}}]$, perform the following. Choose a codeword $F(v) \sim P_X^n$ at random, as in the single-user case. Then, for every i_k , decide whether to add v to the set $\mathcal{V}_{i_k}^{(k)}$ by a binary experiment, with probability $e^{-n\tilde{R}_k}/|\mathcal{V}| = e^{-n(R_{\text{pool}} - \tilde{R}_k)}$. That is, decide that v is included in $\mathcal{V}_{i_k}^{(k)}$ with probability $e^{-n(R_{\text{pool}} - \tilde{R}_k)}$, and not to include with probability $1 - e^{-n(R_{\text{pool}} - \tilde{R}_k)}$. Finally, for every pair $(i_1, i_2) \in [N_1] \times [N_2]$, select a common index V_{i_1, i_2} uniformly at random from $\mathcal{V}_{i_1}^{(1)} \cap \mathcal{V}_{i_2}^{(2)}$, if this intersection is non-empty. Otherwise, if $\mathcal{V}_{i_1}^{(1)} \cap \mathcal{V}_{i_2}^{(2)} = \emptyset$, then draw V_{i_1, i_2} uniformly from \mathcal{V} . Reveal this construction to all parties.

Denote the collection of codewords and index bins for the quantum broadcast channel by

$$\mathcal{B}_{\mathcal{N}} = \left(F, \left\{ \mathcal{V}_{i_1}^{(1)} \right\}_{i_1 \in [N_1]}, \left\{ \mathcal{V}_{i_2}^{(2)} \right\}_{i_2 \in [N_2]}, \left\{ V_{i_1, i_2} \right\}_{(i_1, i_2) \in [N_1] \times [N_2]} \right). \quad (65)$$

Note that, for $k \in \{1, 2\}$, $\mathcal{B}_{\mathcal{N}}$ includes all elements of

$$\mathcal{B}^{(k)} = \left(F, \left\{ \mathcal{V}_{i_k}^{(k)} \right\}_{i_k \in [N_k]} \right), \quad (66)$$

defined for the marginal channels $\mathcal{N}_{A \rightarrow B_k}^{(k)}$ as in Section 5.2. We denote the corresponding single-user code by

$$\mathcal{C}_{\mathcal{B}^{(k)}} = (\tilde{\mathcal{E}}_{A^n}^{(k)}, \mathcal{D}_{B_k^n}). \quad (67)$$

5.3.2 Encoding

To send an ID message pair $(i_1, i_2) \in [N_1] \times [N_2]$, Alice prepares the input state $|\phi_{A^n}^{F(V_{i_1, i_2})}\rangle$ and transmits the input system A^n .

5.3.3 Decoding

Receiver k , for $k = 1, 2$, employs the decoder of the single-user code $\mathcal{C}_{\mathcal{B}^{(k)}}$. Specifically, suppose that Bob k is interested in an ID message $i'_k \in [N_k]$. Then, he uses the decoding POVM $\mathcal{D}_{B_k^n}^{i'_k}$ to decide whether i'_k was sent or not.

We denote the ID code for the CBC that is associated with the construction above by

$$\mathcal{C}_{\mathcal{B}_{\mathcal{N}}} = (\mathcal{E}_{A^n}, \mathcal{D}_{B_1^n}, \mathcal{D}_{B_2^n}) \quad (68)$$

5.3.4 Error Analysis

We show that the semi-average error probabilities of the ID code defined above can be approximately upper-bounded by the respective error probabilities of the single-user ID-codes $\mathcal{C}_{\mathcal{B}^{(1)}}$ and $\mathcal{C}_{\mathcal{B}^{(2)}}$ for the respective receivers.

Consider a given pair of codebooks $\mathcal{B}^{(1)}$ and $\mathcal{B}^{(2)}$. Conditioned on those codebooks, the input state can also be written in terms of an encoding distribution as follows,

$$\mathcal{E}_{A^n}(i_1, i_2) = \sum_{v \in \mathcal{V}} \mathbf{Q}_{i_1, i_2}(v) \left| \phi_{A^n}^{F(v)} \right\rangle \left\langle \phi_{A^n}^{F(v)} \right| \quad (69)$$

where $\mathbf{Q}_{i_1, i_2}(v) = \mathbb{1}(v = V_{i_1, i_2})$. Similarly,

$$\tilde{\mathcal{E}}_{A^n}^{(k)}(i_k) = \sum_{v \in \mathcal{V}} \tilde{\mathbf{Q}}_{i_k}^{(k)}(v) \left| \phi_{A^n}^{F(v)} \right\rangle \left\langle \phi_{A^n}^{F(v)} \right| \quad (70)$$

where $\tilde{\mathbf{Q}}_{i_k}^{(k)}(v)$ is the respective distribution for the single-user code from Section 5.2, namely

$$\tilde{\mathbf{Q}}_{i_k}^{(k)}(v) = \begin{cases} \frac{1}{|\mathcal{V}_{i_k}^{(k)}|} \mathbb{1}(v \in \mathcal{V}_{i_k}^{(k)}) & \text{if } \mathcal{V}_{i_k}^{(k)} \neq \emptyset \\ \mathbb{1}(v = 1) & \text{if } \mathcal{V}_{i_k}^{(k)} = \emptyset. \end{cases} \quad (71)$$

We consider now only Receiver 1 and his marginal channel $\mathcal{N}_{A_1 \rightarrow B}^{(1)}$. Since the code construction is completely symmetric between the two receivers, the same arguments hold for Receiver 2 and $\mathcal{N}_{A_2 \rightarrow B}^{(2)}$. The missed-ID error probability for $\mathcal{C}_{\mathcal{B}_N}$ and Bob 1 is given by

$$\bar{e}_{1,1}(\mathcal{N}, n, \mathcal{C}_{\mathcal{B}_N}, i_1) = \frac{1}{N_2} \sum_{i_2 \in [N_2]} \text{Tr} \left[(\mathbb{1} - D_{i_1}^{(1)}) \mathcal{N}_{A \rightarrow B_1}^{(1) \otimes n} (\mathcal{E}_{A^n}(i_1, i_2)) \right] \quad (72)$$

and for $\mathcal{C}_{\mathcal{B}^{(k)}}$ it is given by

$$e_1(\mathcal{N}_{A \rightarrow B_1}^{(1)}, n, \mathcal{C}_{\mathcal{B}^{(1)}}, i_1) = \text{Tr} \left[(\mathbb{1} - D_{i_1}^{(1)}) \mathcal{N}_{A \rightarrow B_1}^{(1) \otimes n} (\tilde{\mathcal{E}}_{A^n}^{(k)}(i_1)) \right]. \quad (73)$$

By the linearity of the channel and the measurement, we have

$$\begin{aligned} & \bar{e}_{1,1}(\mathcal{N}, n, \mathcal{C}_{\mathcal{B}_N}, i_1) - e_1(\mathcal{N}_{A \rightarrow B_1}^{(1)}, n, \mathcal{C}_{\mathcal{B}^{(1)}}, i_1) \\ & \leq \frac{1}{2} \left\| \frac{1}{N_2} \sum_{i_2 \in [N_2]} \mathcal{E}_{A^n}(i_1, i_2) - \tilde{\mathcal{E}}_{A^n}^{(k)}(i_1) \right\|_1 \\ & = \frac{1}{2} \left\| \frac{1}{N_2} \sum_{i_2 \in [N_2]} \sum_{v \in \mathcal{V}} \mathbf{Q}_{i_1, i_2}(v) \left| \phi_{A^n}^{F(v)} \right\rangle \left\langle \phi_{A^n}^{F(v)} \right| - \sum_{v \in \mathcal{V}} \tilde{\mathbf{Q}}_{i_1}(v) \left| \phi_{A^n}^{F(v)} \right\rangle \left\langle \phi_{A^n}^{F(v)} \right| \right\|_1 \\ & = \frac{1}{2} \left| \sum_{v \in \mathcal{V}} \left(\frac{1}{N_2} \sum_{i_2 \in [N_2]} \mathbf{Q}_{i_1, i_2}(v) - \sum_{v \in \mathcal{V}} \tilde{\mathbf{Q}}_{i_1}(v) \right) \right| \\ & \leq \delta_{i_1}^{(1)}, \end{aligned} \quad (74)$$

where $\delta_{i_1}^{(1)}$ is the total variation distance

$$\delta_{i_1}^{(1)} = \frac{1}{2} \sum_{v \in \mathcal{V}} \left| \frac{1}{N_2} \sum_{i_2 \in [N_2]} \mathbf{Q}_{i_1, i_2}(v) - \sum_{v \in \mathcal{V}} \tilde{\mathbf{Q}}_{i_1}(v) \right| = d \left(\frac{1}{N_2} \sum_{i_2 \in [N_2]} \mathbf{Q}_{i_1, i_2}, \tilde{\mathbf{Q}}_{i_1}^{(1)} \right), \quad (75)$$

and the inequalities follow from the triangle inequality. The same argument applies to the false-ID error. Hence,

$$\bar{e}_{1,1}(\mathcal{N}, n, \mathcal{C}_{\mathcal{B}_N}, i_1) \leq e_1(\mathcal{N}_{A \rightarrow B_1}^{(1)}, n, \mathcal{C}_{\mathcal{B}^{(1)}}, i_1) + \delta_{i_1}^{(1)}, \quad (76a)$$

$$\bar{e}_{1,2}(\mathcal{N}, n, \mathcal{C}_{\mathcal{B}_N}, i_1', i_1) \leq e_2(\mathcal{N}_{A \rightarrow B_1}^{(1)}, n, \mathcal{C}_{\mathcal{B}^{(1)}}, i_1', i_1) + \delta_{i_1}^{(1)}, \quad (76b)$$

Similarly, the error probabilities for the second marginal channel are bounded by

$$\bar{e}_{2,1}(\mathcal{N}, n, \mathcal{C}_{\mathcal{B}_N}, i_2) \leq e_1(\mathcal{N}_{A \rightarrow B_2}^{(2)}, n, \mathcal{C}_{\mathcal{B}^{(2)}}, i_2) + \delta_{i_2}^{(2)}, \quad (76c)$$

$$\bar{e}_{2,2}(\mathcal{N}, n, \mathcal{C}_{\mathcal{B}_N}, i'_2, i_2) \leq e_2(\mathcal{N}_{A \rightarrow B_2}^{(2)}, n, \mathcal{C}_{\mathcal{B}^{(2)}}, i'_2, i_2) + \delta_{i_2}^{(2)}, \quad (76d)$$

where $\delta_{i_2}^{(2)} = d\left(\frac{1}{N_1} \sum_{i_1 \in [N_1]} \mathbf{Q}_{i_1, i_2}, \tilde{\mathbf{Q}}_{i_2}^{(2)}\right)$.

From this point, we can continue as in the classical derivation due to Bracher and Lapidoth [24, 25]. The next lemma bounds $\delta_{i_k}^{(k)}$ in (76) to zero in probability as $n \rightarrow \infty$.

Lemma 4 (see [24, Equations (98, 113–156)]). For every $k \in \{1, 2\}$ and some $\tau > 0$,

$$\lim_{n \rightarrow \infty} \Pr \left(\max_{i_k \in [N_k]} \delta_{i_k}^{(k)} \geq e^{-n\tau} \right) = 0. \quad (77)$$

Hence by (76), the error probabilities for the quantum broadcast-channel code $\mathcal{C}_{\mathcal{B}_N}$ are approximately upper-bounded by the corresponding error probabilities for the single-user marginal codes $\mathcal{C}_{\mathcal{B}^{(1)}}$ and $\mathcal{C}_{\mathcal{B}^{(2)}}$.

By (44) for the single-user quantum channel $\mathcal{N}_{A \rightarrow B_k}^{(k)}$ and $k \in \{1, 2\}$, the error probabilities $e_1(\mathcal{N}_{A \rightarrow B_k}^{(k)}, n, \mathcal{C}_{\mathcal{B}^{(k)}}, i_k)$ and $e_2(\mathcal{N}_{A \rightarrow B_k}^{(k)}, n, \mathcal{C}_{\mathcal{B}^{(k)}}, i'_k, i_k)$ converge in probability to zero with convergence speed exponentially in n , for all messages $i_k, i'_k \in [N_k]$ such that $i_k \neq i'_k$. This completes the proof of the direct part. \square

6 Proof of Part 2

The direct part follows from part 1. Hence, it remains to prove the converse part.

Consider now an $(N_1, N_2, n, \lambda_1, \lambda_2)$ ID code, $\mathcal{C} = (\mathcal{E}_{X^n}, \mathcal{D}_{B_1^n}, \mathcal{D}_{B_2^n})$, for the c-q broadcast channel $\mathcal{N}_{X \rightarrow B_1 B_2}$. In the case of a classical input, the encoder effectively assigns a probability distribution Q_{i_1, i_2} to each message pair, *i.e.*

$$\mathcal{E}_{X^n}(i_1, i_2) = \sum_{x^n \in \mathcal{X}^n} Q_{i_1, i_2}(x^n) |x^n\rangle \langle x^n|. \quad (78)$$

Thus, the ID code is specified by $\{(Q_{i_1, i_2}, D_{i_1}^{(1)}, D_{i_2}^{(2)}) : (i_1, i_2) \in [N_1] \times [N_2]\}$. We denote the Holevo information for each c-q channel $\mathcal{N}_{X \rightarrow B_k}^{(k)}$ with respect to an input distribution $P_X \in \mathcal{P}(\mathcal{X})$ by

$$I(P_X, \mathcal{N}_{X \rightarrow B_k}^{(k)}) \equiv I(X; B_k)_\rho. \quad (79)$$

Following the approach of Boche et al. [18], we prove the converse part in three stages, beginning with a modification of the code.

6.1 Code Modification

6.1.1 δ -net on $\mathcal{P}(\mathcal{X})$

First, we fix a δ -net \mathcal{T} of probability distributions on \mathcal{X} . That is, for $|\mathcal{T}| \leq \left(\frac{e}{\delta}\right)^{|\mathcal{X}|}$, there exists $\mathcal{T} \subseteq \mathcal{P}(\mathcal{X})$ such that

$$\mathcal{X}^n = \bigcup_{P \in \mathcal{T}} \mathcal{A}_P \quad (80)$$

and such that the type of an input sequence $x^n \in \mathcal{A}_P$ is δ -close to P . Hence,

$$Q_{i_1, i_2} = \bigoplus_{P \in \mathcal{T}} \mu_{i_1, i_2}(P) Q_{i_1, i_2}^P \quad (81)$$

where μ_{i_1, i_2} is a probability distribution over \mathcal{T} , and Q_{i_1, i_2}^P are probability distributions over \mathcal{A}_P .

6.1.2 ϵ -net on $\mathcal{P}(\mathcal{T})$

For $|\mathcal{M}| \leq (\frac{c}{\epsilon})^{|\mathcal{T}|}$, there exists an ϵ -net $\mathcal{M} \subseteq \mathcal{P}(\mathcal{T})$. Hence, for every i_2 , there exists a probability distribution $\mu'_{i_2} \in \mathcal{M}$ such that at least a fraction of $\frac{1}{|\mathcal{M}|}$ of the messages $i_1 \in [N_1]$ has μ_{i_1, i_2} that is ϵ -close to μ'_{i_2} . Without loss of generality, for $N'_1 = \lfloor \frac{N_1}{|\mathcal{M}|} \rfloor$,

$$\forall i_1 \in [N'_1] : \frac{1}{2} \|\mu_{i_1, i_2} - \mu'_{i_2}\|_1 \leq \epsilon. \quad (82)$$

Similarly, there exists a probability distribution $\mu'' \in \mathcal{M}$ such that at least a $\frac{1}{|\mathcal{M}|}$ of the messages $i_2 \in [N_2]$ has μ'_{i_2} that is ϵ -close to μ'' . Without loss of generality, for $N'_2 = \lfloor \frac{N_2}{|\mathcal{M}|} \rfloor$,

$$\forall i_2 \in [N'_2] : \frac{1}{2} \|\mu'_{i_2} - \mu''\|_1 \leq \epsilon. \quad (83)$$

Thereby,

$$\forall (i_1, i_2) \in [N'_1] \times [N'_2] : \frac{1}{2} \|\mu'_{i_1, i_2} - \mu''\|_1 \leq 2\epsilon. \quad (84)$$

Then, we modify the encoding distribution and define

$$Q''_{i_1, i_2} = \bigoplus_{P \in \mathcal{T}} \mu''(P) Q_{i_1, i_2}^P \quad (85)$$

leaving the decoder as it is. This results in an $(n, N'_1, N'_2, \lambda_1 + 2\epsilon, \lambda_2 + 2\epsilon)$ code, where we choose ϵ to be sufficiently small such that $\lambda_1 + \lambda_2 + 2\epsilon < 1$.

6.2 Encoder Truncation

There exists $P^* \in \mathcal{T}$ such that $\mu''(P^*) \geq \frac{1}{|\mathcal{T}|}$. Thereby, we modify the code once more and truncate all the other distributions in \mathcal{T} . That is, we consider the code $\{(Q_{i_1, i_2}^{P^*}, D_{i_1}^{(1)}, D_{i_2}^{(2)}) : (i_1, i_2) \in [N'_1] \times [N'_2]\}$. For the new code, the error probabilities of the first and the second kind are bounded by $\lambda_k^* = |\mathcal{T}|(\lambda_k + 2\epsilon)$ for $k \in \{1, 2\}$. Letting $\epsilon \equiv \epsilon(\lambda_1, \lambda_2) \rightarrow 0$ as $\lambda_1, \lambda_2 \rightarrow 0$, the error probabilities of the truncated code tend to zero for every given $\delta > 0$.

6.3 Rate bounds

Consider the marginal $\mathcal{N}_{A \rightarrow B_1}^{(1)}$ and $Q_{i_1}^{P^*} \equiv \frac{1}{N'_2} \sum_{i_2=1}^{N'_2} Q_{i_1, i_2}^{P^*}$. Let i_2 be uniformly distributed. Then, observe that the randomized-encoder code $\{(Q_{i_1}^{P^*}, D_{i_1}^{(1)}) : i_1 \in [N'_1]\}$ is an $(n, N'_1, \lambda_1^*, \lambda_2^*)$ ID code for the single-user channel $\mathcal{N}_{A \rightarrow B_1}^{(1)}$. Therefore, following the single-user converse proof by Ahlswede and Winter [14] (see also [18, Section III]),

$$\begin{aligned} R_1 &= \frac{1}{n} \log \log(N'_1) \\ &< I(P^*, \mathcal{N}_{X \rightarrow B_1}^{(1)}) + \epsilon_1 \\ &= I(X; B_1)_\rho + \epsilon_1 \end{aligned} \quad (86)$$

where $X \sim P^*$ and ϵ_1 tends to zero as $\delta \rightarrow 0$. For completeness, we prove the inequality in the appendix. Similarly, we also have

$$R_2 < I(P^*, \mathcal{N}_{X \rightarrow B_2}^{(2)}) + \epsilon_2 = I(X; B_2)_\rho + \epsilon_2. \quad (87)$$

This completes the proof of the ID capacity theorem. \square

7 Summary

We derived an achievable ID region for the quantum broadcast channel and established full characterization for the classical-quantum broadcast channel. To prove achievability, we extended the classical proof due to Bracher and Lapidoth [24, 25] to the quantum setting. On the other hand, in the converse proof, we used the truncation approach by Boche et al. [18] along with the arguments of Ahlswede and Winter [14].

As examples, we derived explicit expressions for the ID capacity regions for the qubit depolarizing broadcast channel and for the pure-loss bosonic broadcast channel in Section 4. In those examples, each user can achieve the capacity of the respective marginal channel. In particular, the ID capacity region of the pure-loss bosonic broadcast channel is rectangular and strictly larger than the transmission capacity region. In general, the ID capacity region is not necessarily rectangular, as demonstrated for the classical Z-channel [29, Section IV.C] and the classical Gaussian Product channel [29, Section IV.E], [30, Section IV.B].

The ID capacity has a different behavior compared to the single-user setting, in which the ID capacity equals the transmission capacity [72] (see Section 2.5). Here, in the broadcast setting, the ID capacity region can be strictly larger than in transmission, since interference between receivers can be seen as part of the randomization of the coding scheme.

8 Acknowledgments

This work was supported by the German Ministry of Education and Research (BMBF) through grants 16KISQ028 (Uzi Pereg, Christian Deppe), 16KISK002 (Johannes Rosenberger, Christian Deppe), 16KIS1005 (Christian Deppe). Uzi Pereg was also supported by German Research Foundation (DFG) under Germany's Excellence Strategy – EXC-2111 – 390814868, and by the Israel CHE Fellowship for Quantum Science and Technology.

A Proof of Inequality (86)

The rate bound is based on the combinatorial argument in the single-user converse proof, due to Ahlswede and Winter [14]. First, we define a quantum hypergraph and give the Ahlswede-Winter covering lemma [14].

Definition 2. A quantum hypergraph $(\mathcal{H}, \mathcal{G})$ is defined by a finite-dimensional Hilbert space \mathcal{H} and a finite collection $\mathcal{G} = \{G_x\}_{x \in \mathcal{X}}$ of operators on \mathcal{H} , where $0 \preceq G_x \preceq \mathbb{1}$ for $x \in \mathcal{X}$.

Lemma 5 (see [14, Lemma 9]). Let $(\mathcal{H}, \mathcal{G})$ be a quantum hypergraph such that $G \preceq \eta \mathbb{1}$ for all $G \in \mathcal{G}$, and fix $\epsilon, \tau > 0$. Given a probability distribution P on \mathcal{G} , define

$$\rho = \sum_{G \in \mathcal{G}} P(G)G. \quad (88)$$

Then, there exists a subspace $\mathcal{H}_0 \subseteq \mathcal{H}$ and operators $G_1, \dots, G_L \in \mathcal{G}$ such that

$$\text{Tr}(\Pi_0 \rho) \leq \tau \quad (89)$$

$$(1 - \epsilon)\Pi_1 \rho \Pi_1 \preceq \Pi_1 \bar{\rho} \Pi_1 \preceq (1 + \epsilon)\Pi_1 \rho \Pi_1 \quad (90)$$

$$L \leq 1 + \eta |\mathcal{H}| \frac{2 \ln 2 \log(2|\mathcal{H}|)}{\epsilon^2 \tau} \quad (91)$$

with

$$\bar{\rho} = \frac{1}{L} \sum_{\ell=1}^L G_\ell, \quad (92)$$

while Π_0 and Π_1 are the orthogonal projections onto \mathcal{H}_0 and $\mathcal{H}_1 \equiv \mathcal{H}/\mathcal{H}_0$, respectively.

Intuitively, the covering lemma has the following interpretation. We can think of ρ as the average of an ensemble \mathcal{G} of operators. Then, we consider a compressed ensemble, $\{G_1, \dots, G_L\} \subseteq \mathcal{G}$, from which an operator is drawn uniformly. The resulting average of this compression is $\bar{\rho}$. Then, within the subspace \mathcal{H}_1 , the projection $\Pi_1 \rho \Pi_1$ onto \mathcal{H}_1 is almost unaffected by the compression. The idea in the single-user converse proof for the classical-quantum channel $\mathcal{N}_{X \rightarrow B_1}^{(1)}$, is now to replace the arbitrary distributions Q_{i_1} of an ID code by uniform distributions \bar{Q}_{i_1} on subsets of \mathcal{A}_{P^*} , with cardinality bounded by $L \approx e^{nI(P^*; \mathcal{N}^{(1)})}$. The condition is that the corresponding output states are close, so the resulting ID code will have similar error probabilities. As reliable identification requires the encoder to assign a different distribution \bar{Q}_{i_1} to each message i_1 , the number messages is thus bounded by the number of options for choosing L input sequences, which is $|\mathcal{X}^n|^L$. Now, we formalize this argument. Let $\lambda > 0$ be arbitrarily small, such that $\lambda < 1 - \lambda_1^* - \lambda_2^*$. Let $\Pi^\delta(B_1^n)$ and $\Pi^\delta(B_1^n|x^n)$ denote the δ -typical projector and the conditional δ -typical projector, respectively, for $\rho_{B_1} = \sum_{x \in \mathcal{X}} P^*(x) \mathcal{N}_{A \rightarrow B_1}^{(1)}(x)$. Then, denote the projection of each output state onto the δ -typical subspace by

$$\Upsilon_{X^n \rightarrow B_1^n}(x^n) = \Pi^{2\delta}(B_1^n) \Pi^\delta(B_1^n|x^n) \mathcal{N}_{X^n \rightarrow B_1^n}^{(1)}(x^n) \Pi^\delta(B_1^n|x^n) \Pi^{2\delta}(B_1^n). \quad (93)$$

Then, for sufficiently large n ,

$$\left\| \Upsilon(x^n) - \mathcal{N}^{(1)}(x^n) \right\|_1 \leq \frac{\lambda}{6}, \quad (94)$$

for all $x^n \in \mathcal{A}_{P^*}$, by [73, Lemma V.9].

We apply Lemma 5 with $\epsilon = \tau = \frac{\lambda^2}{1200}$ to the quantum hypergraph for which the vertex space \mathcal{H} is the range of $\Pi^{2\delta}(B_1^n)$, and the edges are $\Upsilon_{X^n \rightarrow B_1^n}(x^n)$, $x^n \in \mathcal{A}_{P^*}$. Thereby, for every $i_1 \in [N'_1]$, there exist L_1 sequences $x^n(\ell_{i_1}) \in \mathcal{A}_{P^*}$,

$$L_1 = e^{n(\mathbb{I}(P^*; \mathcal{N}_{A \rightarrow B_1}^{(1)}) + \delta_n)}, \quad (95)$$

such that $G_{\ell_{i_1}} = \Upsilon_{X^n \rightarrow B_1^n}(x^n(\ell_{i_1}))$ satisfy the properties in the lemma, with $\bar{\rho}_{B_1^n}^{i_1} = \frac{1}{L_1} \sum_{j_{i_1}=1}^{L_1} \Upsilon_{X^n \rightarrow B_1^n}(x^n(j_{i_1}))$. Then, the uniform L_1 -distribution $\bar{Q}_{i_1}^{P^*}$ satisfies

$$\left\| Q_{i_1}^{P^*} \Upsilon^{(k)} - \bar{Q}_{i_1}^{P^*} \Upsilon^{(k)} \right\|_1 \leq \frac{\lambda}{6}. \quad (96)$$

Thus, by (94),

$$\left\| Q_{i_1}^{P^*} \mathcal{N}^{(1)} - \bar{Q}_{i_1}^{P^*} \mathcal{N}^{(1)} \right\|_1 \leq \frac{\lambda}{3} \quad (97)$$

for $i_1 \in [N'_1]$. Therefore, $\{\bar{Q}_{i_1}^{P^*}, D_{i_1}^{(1)}\}$ is an $(n, N'_1, \lambda_1^* + \frac{\lambda}{3}, \lambda_2^* + \frac{\lambda}{3})$ code for the single-user channel $\mathcal{N}_{A \rightarrow B_1}^{(1)}$.

Since $\lambda_1^* + \lambda_2^* + \frac{2\lambda}{3} < 1$, each message must have a different input distribution. That is, $\bar{Q}_{i_1}^{P^*} \neq \bar{Q}_{i'_1}^{P^*}$ for $i_1 \neq i'_1$. As each $\bar{Q}_{i_1}^{P^*}$ is uniform over L_1 sequences in \mathcal{X}^n , it follows that

$$\begin{aligned} N'_1 &\leq |\mathcal{X}^n|^{L_1} \\ &= \exp(e^{n(\mathbb{I}(P^*; \mathcal{N}_{A \rightarrow B_1}^{(1)}) + \delta_n + \frac{1}{n} \log \log |\mathcal{X}|)}) \\ &\leq \exp(e^{n(\mathbb{I}(P^*; \mathcal{N}_{A \rightarrow B_1}^{(1)}) + \epsilon_1)}) \end{aligned} \quad (98)$$

for sufficiently large n . Inequality (86) readily follows. \square

References

- [1] J. de Carvalho Silva, J. J. P. C. Rodrigues, A. M. Alberti, P. Solic, and A. L. L. Aquino, "Lorawan — a low power wan protocol for internet of things: A review and opportunities," in *2017 2nd Int'l Multidisciplinary Conf. Comp. Energy Science (SpliTech)*, 2017, pp. 1–6.
- [2] V. Srinadh, M. S. Rao, M. R. Sahoo, and K. Rameshchandra, "An analytical study on security and future research of internet of things," *Materials Today: Proceedings*, 2021.
- [3] F. Tariq, M. R. A. Khandaker, K.-K. Wong, M. A. Imran, M. Bennis, and M. Debbah, "A Speculative Study on 6G," *IEEE Wireless Commun.*, vol. 27, no. 4, pp. 118–125, 2020.
- [4] G. P. Fettweis and H. Boche, "6g: The personal tactile internet - and open questions for information theory," *IEEE BITS Info. Th. Magazine*, pp. 1–1, 2021.
- [5] S. Dang, O. Amin, and M. S. Shihada, B. and Alouini, "What should 6g be?" *Nature Electronics*, vol. 3, no. 1, pp. 20–29, 2020.
- [6] C. E. Shannon, "A Mathematical Theory of Communication," *Bell System Technical Journal*, vol. 27, no. 4, pp. 623–656, Oct. 1948.
- [7] R. Ahlswede and G. Dueck, "Identification via channels," *IEEE Trans. Inf. Theory*, vol. 35, no. 1, pp. 15–29, 1989.

- [8] Y. Steinberg and N. Merhav, “Identification in the presence of side information with application to watermarking,” *IEEE Trans. Inf. Theory*, vol. 47, no. 4, pp. 1410–1422, 2001.
- [9] P. Moulin and R. Koetter, “A framework for the design of good watermark identification codes,” in *Security, Steganography, and Watermarking of Multimedia Contents VIII*, E. J. D. III and P. W. Wong, Eds., vol. 6072, International Society for Optics and Photonics. SPIE, 2006, pp. 565 – 574.
- [10] R. Ahlswede and N. Cai, “Watermarking Identification Codes with Related Topics on Common Randomness,” in *General Theory of Information Transfer and Combinatorics*, ser. Lecture Notes in Computer Science. Springer Berlin Heidelberg, 2006, vol. 4123, pp. 107–153.
- [11] O. Günlü, J. Kliewer, R. F. Schaefer, and V. Sidorenko, “Doubly-Exponential Identification via Channels: Code Constructions and Bounds,” in *Proc. IEEE Int. Symp. Inf. Theory (ISIT’2021)*, 2021, pp. 1147–1152.
- [12] H. Boche and C. Deppe, “Secure Identification for Wiretap Channels; Robustness, Super-Additivity and Continuity,” *IEEE Trans. Inf. Forensics Security*, vol. 13, no. 7, pp. 1641–1655, 2018.
- [13] P. Löber, “Quantum channels and simultaneous ID coding,” Ph.D. dissertation, Universität Bielefeld, Bielefeld, Germany, 1999.
- [14] R. Ahlswede and A. Winter, “Strong converse for identification via quantum channels,” *IEEE Trans. Inf. Theory*, vol. 48, no. 3, pp. 569–579, 2002.
- [15] A. Winter, “Identification via quantum channels,” in *Information Theory, Combinatorics, and Search Theory*. Springer, 2013, pp. 217–233.
- [16] R. Ahlswede, *Identification and Other Probabilistic Models*, 1st ed., ser. Foundations in Signal Processing, Communications and Networking. Cham: Springer International Publishing, 2021.
- [17] S. Di Adamo and H. Boche, “The simultaneous identification capacity of the classical–quantum multiple access channel with stochastic encoders for transmission,” arXiv: [1903.03395](https://arxiv.org/abs/1903.03395), 2019.
- [18] H. Boche, C. Deppe, and A. Winter, “Secure and robust identification via classical–quantum channels,” *IEEE Trans. Inf. Theory*, vol. 65, no. 10, pp. 6734–6749, 2019.
- [19] P. Hayden and A. Winter, “Weak decoupling duality and quantum identification,” *IEEE Trans. Inf. Theory*, vol. 58, no. 7, pp. 4914–4929, 2012.
- [20] T. M. Cover and J. A. Thomas, *Elements of Information Theory*, 2nd ed. Wiley, 2006.
- [21] K. Marton, “A coding theorem for the discrete memoryless broadcast channel,” *IEEE Trans. Inf. Theory*, vol. 25, no. 3, pp. 306–311, May 1979.
- [22] C. Nair and A. El Gamal, “An Outer Bound to the Capacity Region of the Broadcast Channel,” *IEEE Trans. Inf. Theory*, vol. 53, no. 1, pp. 350–355, 2007.
- [23] A. El Gamal, “The capacity of a class of broadcast channels,” *IEEE Trans. Inf. Theory*, vol. 25, no. 2, pp. 166–169, 1979.
- [24] A. Bracher and A. Lapidoth, “Identification via the Broadcast Channel,” *IEEE Trans. Inf. Theory*, vol. 63, no. 6, pp. 3480–3501, 2017.
- [25] A. Bracher, “Identification and Zero-Error Codes,” Ph.D. dissertation, ETH Zurich, Konstanz, 2016.
- [26] B. Verboven and E. van der Meulen, “Capacity bounds for identification via broadcast channels that are optimal for the determination broadcast channel,” *IEEE Trans. Inf. Theory*, vol. 36, no. 6, pp. 1197–1205, 1990.

- [27] I. Bilik and Y. Steinberg, “Inner and outer bounds on the identification capacity region of the degraded broadcast channel,” in *Proc. IEEE Int. Symp. Inf. Theory (ISIT’2001)*, 2001.
- [28] R. Ahlswede, “General theory of information transfer: Updated,” *Discr. Appl. Math.*, vol. 156, no. 9, pp. 1348–1388, May 2008.
- [29] J. Rosenberger, U. Pereg, and C. Deppe, “Identification over Compound Multiple-Input Multiple-Output Broadcast Channels,” Dec. 2021, arXiv: [2110.15101v2](https://arxiv.org/abs/2110.15101v2).
- [30] —, “Identification over Compound MIMO Broadcast Channels,” *Accepted for the 2022 IEEE Int. Conf. Commun. (ICC’2022)*, 2022.
- [31] J. Yard, P. Hayden, and I. Devetak, “Quantum broadcast channels,” *IEEE Trans. Inf. Theory*, vol. 57, no. 10, pp. 7147–7162, Oct 2011.
- [32] I. Savov and M. M. Wilde, “Classical codes for quantum broadcast channels,” *IEEE Trans. Inf. Theory*, vol. 61, no. 12, pp. 7017–7028, Dec 2015.
- [33] J. Radhakrishnan, P. Sen, and N. Warsi, “One-shot marton inner bound for classical-quantum broadcast channel,” *IEEE Trans. Inf. Theory*, vol. 62, no. 5, pp. 2836–2848, May 2016.
- [34] Q. Wang, S. Das, and M. M. Wilde, “Hadamard quantum broadcast channels,” *Quantum Inform. Process.*, vol. 16, no. 10, p. 248, 2017.
- [35] F. Dupuis, P. Hayden, and K. Li, “A father protocol for quantum broadcast channels,” *IEEE Trans. Inf. Theory*, vol. 56, no. 6, pp. 2946–2956, June 2010.
- [36] F. Dupuis, “The decoupling approach to quantum information theory,” Ph.D. dissertation, Université de Montréal, 2010.
- [37] C. Hirche and C. Morgan, “An improved rate region for the classical-quantum broadcast channel,” in *Proc. IEEE Int. Symp. Inf. Theory (ISIT’2015)*, Hong Kong, China, June 2015, pp. 2782–2786.
- [38] K. P. Seshadreesan, M. Takeoka, and M. M. Wilde, “Bounds on entanglement distillation and secret key agreement for quantum broadcast channels,” *IEEE Trans. Inf. Theory*, vol. 62, no. 5, pp. 2849–2866, May 2016.
- [39] S. Bäuml and K. Azuma, “Fundamental limitation on quantum broadcast networks,” *Quantum Science and Tech.*, vol. 2, no. 2, p. 024004, 2017.
- [40] T. Heinosaari and T. Miyadera, “Incompatibility of quantum channels,” *J. Phys. A: Mat. and Theo.*, vol. 50, no. 13, p. 135302, 2017.
- [41] H. Boche, M. Cai, and C. Deppe, “The broadcast classical–quantum capacity region of a two-phase bidirectional relaying channel,” *Quantum Information Processing*, vol. 14, no. 10, pp. 3879–3897, 2015.
- [42] C. Hirche, “Polar codes in quantum information theory,” Ph.D. dissertation, Leibniz Universität Hannover, 2015.
- [43] W. Xie, X. Wang, and R. Duan, “Converse bounds for classical communication over quantum broadcast channels and quantum multi-access channels,” in *Proc. IEEE Int. Symp. Inf. Theory (ISIT’2018)*, June 2018, pp. 2341–2345.
- [44] G. De Palma, “New lower bounds to the output entropy of multi-mode quantum gaussian channels,” *IEEE Trans. Inf. Theory*, vol. 65, no. 9, pp. 5959–5968, Sep. 2019.
- [45] A. Anshu, R. Jain, and N. A. Warsi, “Building blocks for communication over noisy quantum networks,” *IEEE Trans. Inf. Theory*, vol. 65, no. 2, pp. 1287–1306, Feb 2019.
- [46] H. C. Cheng, N. Datta, and C. Rouzé, “Strong converse for classical-quantum degraded broadcast channels,” arXiv: [1905.00874](https://arxiv.org/abs/1905.00874), 2019.
- [47] U. Pereg, C. Deppe, and H. Boche, “Quantum broadcast channels with cooperating decoders: An information-theoretic perspective on quantum repeaters,” *J. Math. Phys.*, vol. 62, no. 6, p. 062204, 2021.

- [48] F. Salek, M. H. Hsieh, and J. R. Fonollosa, “Publicness, privacy and confidentiality in the single-serving quantum broadcast channel,” arXiv: [1903.04463](https://arxiv.org/abs/1903.04463), 2019.
- [49] F. Salek, M. Hsieh, and J. R. Fonollosa, “Publicness, privacy and confidentiality in the single-serving quantum broadcast channel,” in *Proc. IEEE Int. Symp. Inf. Theory (ISIT’2019)*, Paris, France, July 2019, pp. 1712–1716.
- [50] B. R. Bardhan and J. H. Shapiro, “Ultimate capacity of a linear time-invariant bosonic channel,” *Phys. Rev. A*, vol. 93, no. 3, p. 032342, 2016.
- [51] U. Pereg, “Bosonic dirty paper coding,” in *Proc. IEEE Int. Symp. Inf. Theory (ISIT’2021)*, July 2021.
- [52] —, “Communication Over Quantum Channels With Parameter Estimation,” *IEEE Trans. Inf. Theory*, vol. 68, no. 1, pp. 359–383, 2022.
- [53] S. Kumar and M. J. Deen, *Fiber optic communications: fundamentals and applications*. John Wiley & Sons, 2014.
- [54] C. Weedbrook, S. Pirandola, R. García-Patrón, N. J. Cerf, T. C. Ralph, J. H. Shapiro, and S. Lloyd, “Gaussian quantum information,” *Rev. Mod. Phys.*, vol. 84, pp. 621–669, May 2012.
- [55] M. M. Wilde, P. Hayden, and S. Guha, “Quantum trade-off coding for bosonic communication,” *Phys. Rev. A*, vol. 86, no. 6, p. 062306, 2012.
- [56] S. Guha and J. H. Shapiro, “Classical information capacity of the bosonic broadcast channel,” in *Proc. IEEE Int. Symp. Inf. Theory (ISIT’2007)*, Nice, France, June 2007, pp. 1896–1900.
- [57] S. Guha, J. H. Shapiro, and B. I. Erkmen, “Classical capacity of bosonic broadcast communication and a minimum output entropy conjecture,” *Phys. Rev. A*, vol. 76, no. 3, p. 032303, 2007.
- [58] G. De Palma, A. Mari, and V. Giovannetti, “A generalization of the entropy power inequality to bosonic quantum systems,” *Nature Photonics*, vol. 8, no. 12, p. 958, 2014.
- [59] M. Takeoka, K. P. Seshadreesan, and M. M. Wilde, “Unconstrained distillation capacities of a pure-loss bosonic broadcast channel,” in *Proc. IEEE Int. Symp. Inf. Theory (ISIT’2016)*, Barcelona, Spain, July 2016, pp. 2484–2488.
- [60] M. Takeoka, K. P. Seshadreesan, and M. M. Wilde, “Unconstrained capacities of quantum key distribution and entanglement distillation for pure-loss bosonic broadcast channels,” *Phys. Rev. Lett.*, vol. 119, no. 15, p. 150501, 2017.
- [61] R. Laurenza and S. Pirandola, “General bounds for sender-receiver capacities in multipoint quantum communications,” *Phys. Rev. A*, vol. 96, no. 3, p. 032318, 2017.
- [62] E. Anderson, S. Guha, and B. Bash, “Fundamental limits of bosonic broadcast channels,” in *Proc. IEEE Int. Symp. Inf. Theory (ISIT’2021)*, 2021.
- [63] U. Pereg, R. Ferrara, and M. R. Bloch, “Key Assistance, Key Agreement, and Layered Secrecy for Bosonic Broadcast Channels,” in *Proc. IEEE Inf. Theory Workshop (ITW’2021)*, 2021, pp. 1–6.
- [64] A. Winter, “Quantum and classical message identification via quantum channels,” 2004, arXiv: [quant-ph/0401060](https://arxiv.org/abs/quant-ph/0401060).
- [65] R. Ahlswede and G. Dueck, “Identification in the presence of feedback—a discovery of new capacity formulas,” *IEEE Trans. Inf. Theory*, vol. 35, no. 1, pp. 30–36, 1989.
- [66] S. Guha, J. H. Shapiro, and B. I. Erkmen, “Classical capacity of bosonic broadcast communication and a minimum output entropy conjecture,” *Phys. Rev. A*, vol. 76, no. 3, p. 032303, 2007.
- [67] A. S. Holevo and R. F. Werner, “Evaluating capacities of bosonic gaussian channels,” *Phys. Rev. A*, vol. 63, no. 3, p. 032312, 2001.

- [68] J. Eisert and M. M. Wolf, “Gaussian quantum channels,” 2005, arXiv: [quant-ph/0505151](https://arxiv.org/abs/quant-ph/0505151).
- [69] A. El Gamal and Y.-H. Kim, *Network Information Theory*. Cambridge University Press, 2011.
- [70] I. Csiszár and J. Körner, *Information Theory: Coding Theorems for Discrete Memoryless Systems*, 2nd ed. Cambridge University Press, 2011.
- [71] M. M. Wilde, *Quantum information theory*, 2nd ed. Cambridge University Press, 2017.
- [72] S. Watanabe, “Minimax converse for identification via channels,” *IEEE Trans. Inf. Theory*, vol. 68, no. 1, pp. 25–34, 2022.
- [73] A. Winter, “Coding theorem and strong converse for quantum channels,” *IEEE Trans. Inf. Theory*, vol. 45, no. 7, pp. 2481–2485, Nov 1999.