

Exact output tracking in prescribed finite time via funnel control [★]

Lukas Lanza ^a

^a*Institut für Mathematik, Universität Paderborn, Warburger Str. 100, 33098 Paderborn*

Abstract

We extend a recent result in high-gain feedback output tracking control to achieve exact tracking within finite time, i.e., the output of a system and its relevant derivatives have certain exact values at a predefined finite time. We propose a new funnel control scheme achieving this, whereas the error between the reference and the output evolves within prescribed bounds. Applications of this are, for instance, linking up two parts of a train, or docking spaceships.

Key words: Exact output tracking in finite time; funnel control; nonlinear systems

1 Preface and Preliminaries

Since rendezvous of spacecraft has been a hot topic from the early sixties to the present, a brief motivation from the engineering point of view seems adequate. The first successful automated docking manoeuvre was carried out in 1967 between *Cosmos 186* and *Cosmos 188* in the context of the Soviet space program. In the subsequent years more and more such docking manoeuvres became relevant as for bringing crew members to a space station (successful in 1971 for the first time), supplying a space station as well as for service missions for, e.g., the Hubble Space Telescope. In view of the recent space mission to Mars (rover “Perseverance” and helicopter “Ingenuity”) due to the finite speed of information travelling through space-time, the farther away from the earth spacecraft are, the more and more *feedback control schemes* become relevant in launching, landing and docking manoeuvres.

However, back to earth, in daily life contexts there is use of docking manoeuvres as well, as for instance, in automatic production processes, linking up two parts of a train or charging of autonomous vehicles to name but a few possible fields of application.

Reviewing the current literature on feedback based output reference tracking, one gets the impression that *exact tracking* is an old problem which has only recently

been addressed, and *exact tracking in finite time* represents a chapter that has hardly been written yet.

Referring to the results in [5], in [13] it is shown that the proposed funnel control scheme can achieve global asymptotic stabilization for a class of linear multi-input multi-output (MIMO) systems of relative degree one. A generalization to a class of nonlinear relative degree one MIMO systems is proposed in [21]. In [19] an extended sliding mode controller is proposed which achieves asymptotic tracking of linear single-input single-output (SISO) systems. This controller is extended to linear MIMO systems in [18]. In [7] backstepping is combined with feedback linearization techniques and higher order sliding modes to design a controller which achieves exponential tracking. In [20] a high-gain based sliding mode controller is introduced, where the peaking related to the high-gain observer is obviated introducing a dwell-time activation scheme. This controller achieves asymptotic tracking for a class of nonlinear SISO systems of arbitrary relative degree, where the reference signal is generated by a reference model. To the price of a discontinuous control, asymptotic tracking for nonlinear MIMO systems is achieved in [23,24]. In [17] a funnel control scheme is proposed, which achieves asymptotic tracking for a class of nonlinear relative degree one MIMO systems. This result is extended in the recent work [2], where it is shown that the proposed funnel controller achieves asymptotic tracking of nonlinear MIMO systems with arbitrary relative degree whereas the tracking error has prescribed transient behaviour.

Now, we turn from asymptotic tracking towards exact tracking in finite time. In [1] sliding mode control concepts and results from [4] are used to establish control

[★] This work was supported by the German Research Foundation (Deutsche Forschungsgemeinschaft) via the grant BE 6263/1-1.

Email address: lanza@math.upb.de (Lukas Lanza).

schemes which achieve finite time stabilization for linear (SISO & MIMO) systems. In [9] backstepping and higher order sliding mode control are combined to construct a control scheme which achieves exact output tracking in finite time for nonlinear MIMO systems in nonlinear block controllable form. Similar to the prescribed performance controller in [8] this controller suffers from the proper initialization problem, where it is not clear how large to choose the involved parameters. The controller in [9], along with limiting conditions on the system class, presumes knowledge of the system's functions and explicitly involves inverses of some. In [25] a controller is introduced which achieves exact tracking in finite time for a class of nonlinear SISO systems satisfying a certain homogeneity assumption. This controller relies on estimating techniques of the external disturbances, where the problem of proper initialization is avoided by assuming explicit knowledge of the bounds of the disturbances and the reference. The control scheme explicitly involves (parts of) the system's right hand side and is of relatively high complexity. As far as we understand, in the control schemes for exact tracking in finite time discussed above, the final time, this is the time when the desired state should be matched, cannot be prescribed; only the existence of such a finite time is ensured. Contrary, in [14] a control scheme is introduced which solves a *predefined-time exact tracking problem* for the class of fully actuated mechanical (relative degree two) systems. The controller relies on a backstepping procedure and consists of a *predefined-time stabilization function* and involves the system's equations explicitly. In [22] a funnel controller is introduced which achieves asymptotic tracking as well as convergence to zero of the tracking error in finite time for a class of relative degree one SISO systems.

Circumventing the drawbacks mentioned above, in the present article we introduce a funnel control scheme which achieves *exact tracking in predefined finite time*. Since the control scheme is of funnel type it inherits the advantages of robustness with respect to noise, being model free, i.e., no knowledge of the system's parameters (roughly speaking no knowledge of the right hand side) is assumed - except the relative degree $r \in \mathbb{N}$ and the input/output dimension $m \in \mathbb{N}$ -, and moreover, the tracking error evolves within prescribed bounds. The system class under consideration is the same as in [2].

1.1 Nomenclature

Throughout the present article we use the following notation, where $I \subseteq \mathbb{R}$ denotes an interval. \mathbb{N} the set of positive integers; $[a, b], [a, b), (a, b)$ a closed, half-open, and open interval for $a, b \in \mathbb{R}, a < b$; $\mathbb{R}_{\geq 0} := [0, \infty)$; $\langle \cdot, \cdot \rangle$ inner product in \mathbb{R}^n ; $\|x\| := \sqrt{\langle x, x \rangle}$ Euclidean norm of $x \in \mathbb{R}^n$; $\mathcal{L}_{\text{loc}}^\infty(I; \mathbb{R}^p)$ the set of locally essentially bounded functions $f : I \rightarrow \mathbb{R}^p$; $\mathcal{L}^\infty(I; \mathbb{R}^p)$ the set of essentially bounded functions $f : I \rightarrow \mathbb{R}^p$; $\|f\|_\infty := \text{ess sup}_{t \in I} \|f(t)\|$ norm of $f \in \mathcal{L}^\infty(I; \mathbb{R}^p)$; $\mathcal{W}^{k, \infty}(I; \mathbb{R}^p)$

the set of k -times weakly differentiable functions $f : I \rightarrow \mathbb{R}^p$ such that $f, \dot{f}, \dots, f^{(k)} \in \mathcal{L}^\infty(I; \mathbb{R}^p)$; $\mathcal{C}^k(I; \mathbb{R}^p)$ the set of k -times continuously differentiable functions $f : I \rightarrow \mathbb{R}^p$, $\mathcal{C}(I; \mathbb{R}^p) = \mathcal{C}^0(I; \mathbb{R}^p)$; $f|_J$ the restriction of $f : I \rightarrow \mathbb{R}^n$ to $J \subseteq I$, I, J intervals.

1.2 System class

To introduce the class of systems under consideration properly, first of all we provide some definitions. We introduce a class of operators to which the operator appearing in the system class under consideration belongs. This definition is taken from [2, Sec. 1.2].

Definition 1.1. If the operator $\mathbf{T} : \mathcal{C}([-\sigma, \infty); \mathbb{R}^n) \rightarrow \mathcal{L}_{\text{loc}}^\infty(\mathbb{R}_{\geq 0}; \mathbb{R}^q)$ has following properties

- (a) \mathbf{T} maps bounded trajectories to bounded trajectories, i.e., for all $c_1 > 0$, there exists $c_2 > 0$ such that for all $\xi \in \mathcal{C}([-\sigma, \infty); \mathbb{R}^n)$,

$$\sup_{t \in [-\sigma, \infty)} \|\xi(t)\| \leq c_1 \Rightarrow \sup_{t \in [0, \infty)} \|\mathbf{T}(\xi)(t)\| \leq c_2,$$

- (b) \mathbf{T} is causal, i.e., for all $t \geq 0$ and all $\zeta, \xi \in \mathcal{C}([-\sigma, \infty); \mathbb{R}^n)$,

$$\zeta|_{[-\sigma, t]} = \xi|_{[-\sigma, t]} \Rightarrow \mathbf{T}(\zeta)|_{[0, t]} \stackrel{a.a.}{=} \mathbf{T}(\xi)|_{[0, t]},$$

- (c) \mathbf{T} is locally Lipschitz continuous in the following sense: for all $t \geq 0$ and all $\xi \in \mathcal{C}([-\sigma, t]; \mathbb{R}^n)$ there exist $\Delta, \delta, c > 0$ such that for all $\zeta_1, \zeta_2 \in \mathcal{C}([-\sigma, \infty); \mathbb{R}^n)$ with $\zeta_1|_{[-\sigma, t]} = \xi, \zeta_2|_{[-\sigma, t]} = \xi$ and $\|\zeta_1(s) - \xi(s)\| < \delta, \|\zeta_2(s) - \xi(s)\| < \delta$ for all $s \in [t, t + \Delta]$ we have

$$\begin{aligned} \text{ess sup}_{s \in [t, t + \Delta]} \|\mathbf{T}(\zeta_1)(s) - \mathbf{T}(\zeta_2)(s)\| \\ \leq c \sup_{s \in [t, t + \Delta]} \|\zeta_1(s) - \zeta_2(s)\|, \end{aligned}$$

then we say the operator \mathbf{T} belongs to the operator class $\mathcal{T}_\sigma^{n, q}$.

To introduce the notion of a *solution* to an initial value problem, let $\mathcal{D} \subseteq \mathbb{R}_{\geq 0} \times \mathbb{R}^n$ a non-empty, connected and relatively open set in $\mathbb{R}_{\geq 0} \times \mathbb{R}^n$. Let $q \in \mathbb{N}$ and assume that $F : \mathcal{D} \times \mathbb{R}^q \rightarrow \mathbb{R}^n$ is a *Carathéodory function* as in [12, App. B]. Let $\mathbf{T} \in \mathcal{T}_\sigma^{n, q}$, $t_0 \in \mathbb{R}_{\geq 0}$ and consider the initial value problem

$$\begin{aligned} \frac{d}{dt}x(t) &= F(t, x(t), \mathbf{T}(x)(t)), \\ x|_{[-\sigma, t_0]} &= x^0 \in \mathcal{C}([-\sigma, t_0]; \mathbb{R}^n), (t_0, x^0(t_0)) \in \mathcal{D}. \end{aligned} \quad (1)$$

Then, in virtue of [12, App. B] we have the following definition.

Definition 1.2. A *solution* of (1) is a function $x \in \mathcal{C}(I; \mathbb{R}^n)$ on an interval of the form $I = [-\sigma, \bar{\omega}]$, for $t_0 < \bar{\omega} < \infty$, or $I = [-\sigma, \omega)$, for $\omega \leq \infty$, such that, for $J := I \setminus [-\sigma, t_0]$, we have $x|_{[-\sigma, t_0]} = x^0$, $x|_J$ is absolutely continuous with $(t, x(t)) \in \mathcal{D}$ for all $t \in J$, and

$$\forall t \in J : x(t) = x(t_0) + \int_{t_0}^t F(s, x(s), \mathbf{T}(x)(s)) ds. \quad (2)$$

A solution is maximal if it has no proper right extension that is also a solution.

Remark 1.3. As pointed out in [11, p. 234] the interpretation of the “local Lipschitz property” in Definition 1.1 (c) and so the interpretation of a solution $x \in \mathcal{C}(I; \mathbb{R}^n)$ of (1), where $I = [-\sigma, \bar{\omega}]$ or $I = [-\sigma, \omega)$ for finite ω , requires special attention since the operator \mathbf{T} has $\mathcal{C}([-\sigma, \infty); \mathbb{R}^n)$ as its domain. Let $J := I \setminus [-\sigma, 0)$ and $x \in \mathcal{C}(I; \mathbb{R}^n)$. For each $\tau \in J$ define the function $x_\tau \in \mathcal{C}([-\sigma, \infty); \mathbb{R}^n)$ by

$$x_\tau(t) = \begin{cases} x(t), & t \in [-\sigma, \tau], \\ x(\tau), & t > \tau. \end{cases}$$

Now, we associate with the operator $\mathbf{T} \in \mathcal{T}_\sigma^{n,q}$ its “localisation”, namely the operator $\tilde{\mathbf{T}} : \mathcal{C}(I; \mathbb{R}^n) \rightarrow \mathcal{L}_{\text{loc}}^\infty(J; \mathbb{R}^n)$ defined as

$$\forall \tau \in J : \tilde{\mathbf{T}}(x)|_{[0, \tau]} = \mathbf{T}(x_\tau)|_{[0, \tau]}.$$

Note, that by Definition 1.1 (b) the operator $\tilde{\mathbf{T}}$ is well defined. Together, a replacement of \mathbf{T} by $\tilde{\mathbf{T}}$ in (2) yields the correct interpretation of a solution; however, in what follows we will (notationally) not distinguish between $\mathbf{T} \in \mathcal{T}_\sigma^{n,q}$ and $\tilde{\mathbf{T}}$.

Throughout the present article we consider the following functional differential equation

$$\begin{aligned} y^{(r)}(t) &= f\left(d(t), \mathbf{T}(y, \dot{y}, \dots, y^{(r-1)})(t), u(t)\right), \\ y|_{[-\sigma, 0]} &= y^0 \in \mathcal{C}^{r-1}([-\sigma, 0]; \mathbb{R}^m), \end{aligned} \quad (3)$$

where $\sigma > 0$ is the “memory” of the system, the parameter $r \in \mathbb{N}$ is related to the concept of relative degree; furthermore, the dimension $m \in \mathbb{N}$ of the input u and the output y of the system coincide.

In order to characterize the class of admissible nonlinearities f in (3) we recall the definition of “high-gain property” from [2, Sec. 1.2].

Definition 1.4. For $p, q, m \in \mathbb{N}$ a function $f \in \mathcal{C}(\mathbb{R}^p \times \mathbb{R}^q \times \mathbb{R}^m; \mathbb{R}^m)$ satisfies the *high-gain property*, if there exists $\rho \in (0, 1)$ such that, for every compact $K_p \subset \mathbb{R}^p$

and compact $K_q \subset \mathbb{R}^q$ the continuous function

$$\chi : \mathbb{R} \rightarrow \mathbb{R},$$

$$s \mapsto \min \left\{ \langle v, f(\delta, z, -sv) \mid \begin{array}{l} (\delta, z) \in K_p \times K_q, \\ v \in \mathbb{R}^m, \rho \leq \|v\| \leq 1 \end{array} \right\}$$

is such that $\sup_{s \in \mathbb{R}} \chi(s) = \infty$.

For a detailed discussion and equivalent conditions of the high-gain property we refer to [2, Rem. 1.3 & 1.4]. Now, with the definitions so far, we may introduce the system class under consideration, which is the same class of systems as in [2].

Definition 1.5. For $m, r \in \mathbb{N}$ a system (3) is said to belong to the system class $\mathcal{N}^{m,r}$ if for some $p, q \in \mathbb{N}$ the “disturbance” is bounded, i.e., $d \in \mathcal{L}^\infty(\mathbb{R}_{\geq 0}; \mathbb{R}^p)$, the function $f \in \mathcal{C}(\mathbb{R}^p \times \mathbb{R}^q \times \mathbb{R}^m; \mathbb{R}^m)$ satisfies the high-gain property from Definition 1.4 and for $\sigma > 0$ the operator \mathbf{T} belongs to $\mathcal{T}_\sigma^{r,m,q}$; we write $(d, f, \mathbf{T}) \in \mathcal{N}^{m,r}$.

1.3 Control objective and feedback law

We aim to find a control structure which achieves exact output reference tracking in the following sense. For every system (3) belonging to the class $\mathcal{N}^{m,r}$ and any reference trajectory $y_{\text{ref}} \in \mathcal{W}^{r,\infty}([0, T]; \mathbb{R}^m)$, $T > 0$, the output approaches the reference within the interval $[0, T]$, whereas for a given function $\varphi(\cdot)$ introduced next, the error $e(\cdot) := y(\cdot) - y_{\text{ref}}(\cdot)$ evolves within the so called “performance funnel” defined by

$$\mathcal{F}_\varphi := \{ (t, e) \in [0, T] \times \mathbb{R}^m \mid \varphi(t) \|e\| < 1 \}.$$

Moreover, the control achieves exact tracking in finite time with predefined accuracy, this is

$$\begin{aligned} \forall i = 0, \dots, r-1, \forall t \in [0, T] : \\ (t, e(t)) \in \mathcal{F}_\varphi, \text{ and } \lim_{t \rightarrow T} \|e^{(i)}(t)\| = 0, \end{aligned} \quad (4)$$

where $e^{(i)}(\cdot)$ denotes the i^{th} derivative of $e(\cdot)$. In order to establish the control structure, we introduce the following funnel control parameters. Choose the final time $T > 0$ and some $c > 0$, then we define the funnel function

$$\varphi(t) = \frac{1}{c} \frac{1}{T-t}, \quad t \in [0, T], \quad (5a)$$

where we highlight $\lim_{t \rightarrow T} \varphi(t) = \infty$, further choose

$$N \in \mathcal{C}(\mathbb{R}_{\geq 0}; \mathbb{R}) \text{ a surjection}, \quad (5b)$$

and for $c > 0$ from (5a) choose

$$\alpha \in \mathcal{C}^{r-1}([0, 1]; [c(r+1), \infty)) \text{ a bijection}, \quad (5c)$$

e.g. $\alpha(s) = c(r+1)/(1-s)$. For a detailed comment on the surjection N and possible simplifications we recommend reading [2, Rem. 1.8].

Remark 1.6. Compared to the funnel control schemes proposed in the common literature, see e.g. [13, 11, 3, 2] to name but a few, the explicit choice of $\varphi(\cdot)$ in (5a) seems to be quite restrictive. Anticipating the initial condition (11) in Theorem 2.1, the choice of the funnel function $\varphi(\cdot)$ in (5a) reflects the intuition that the shorter the final time T is chosen, the better the initial guess has to be. Further, the tuning parameter c in (5a) links the funnel function to the gain function $\alpha(\cdot)$ in (5c). If the final time T is short and the error between the initial state of system (3) and the reference, however, can not be influenced to be small, a large c can ensure the initial condition (11) to be satisfied; this in turn causes a larger lower bound of the gain function $\alpha(\cdot)$ which means that small tracking errors cause high input values.

Remark 1.7. A careful inspection of the proof of [2, Thm. 1.9] yields that a crucial property of the feasible funnel functions is a growth condition, namely

$$\exists d > 0 : |\dot{\varphi}(t)| \leq d(1 + \varphi(t)) \text{ for almost all } t \geq 0.$$

This condition prevents a “blow up” in finite time, i.e., $\varphi(\cdot)$ is bounded on $\mathbb{R}_{\geq 0} \setminus \{\infty\}$. With this, however, exact tracking in finite time via funnel control is impossible. Contrary, the funnel functions $\varphi(\cdot)$ defined in (5a) do not satisfy this growth condition. Therefore, in order to achieve exact tracking in finite time via funnel control, we propose a modified feedback law in the present article.

We introduce the control law which achieves the previously formulated control objective (4). For $i = 0, \dots, r-1$ we set $e^{(i)}(\cdot) := y^{(i)}(\cdot) - y_{\text{ref}}^{(i)}(\cdot)$ and recursively define for $k = 1, \dots, r$ with $\alpha(\cdot)$ from (5c) and $\gamma_0(\cdot) \equiv 0$ the functions

$$e_k(t) = \varphi(t)e^{(k-1)}(t) + \varphi(t) \sum_{i=1}^{k-1} \gamma_i^{(k-1-i)}(t), \quad (6a)$$

$$\alpha_k(t) = \alpha(\|e_k(t)\|^2), \quad (6b)$$

$$\gamma_k(t) = \alpha_k(t)e_k(t). \quad (6c)$$

Then, with the functions introduced in (5),(6) we define the feedback law $u : \mathbb{R}_{\geq 0} \rightarrow \mathbb{R}^m$ as

$$u(t) = (N \circ \alpha_r)(t) e_r(t) = (N \circ \alpha)(\|e_r(t)\|^2) e_r(t). \quad (7)$$

Remark 1.8. We comment on the computation of the expressions recursively given in (6). We define the set

$$\mathcal{D}_0 := \{ \zeta \in \mathbb{R}^m \mid \|\zeta\| < 1 \},$$

and, for $\alpha(\cdot)$ from (5c), the function $\Gamma_0 : \mathcal{D}_0 \rightarrow \mathbb{R}^m$ by

$$\Gamma_0(t, \zeta) := \alpha(\|\zeta\|^2) \zeta.$$

For $k = 1, \dots, r-1$ we recursively define the sets \mathcal{D}_k and the functions $\Gamma_k : [0, T) \times \mathcal{D}_k \rightarrow \mathbb{R}^m$ by

$$\begin{aligned} \mathcal{D}_k &:= \underbrace{\mathcal{D}_0 \times \dots \times \mathcal{D}_0}_{k\text{-times}} \times \mathbb{R}^m, \\ \Gamma_k(t, \zeta_1, \dots, \zeta_{k+1}) &:= \frac{\partial \Gamma_{k-1}(t, \zeta_1, \dots, \zeta_k)}{\partial t} \quad (8) \\ &+ \sum_{i=1}^k \frac{\partial \Gamma_{k-1}(t, \zeta_1, \dots, \zeta_k)}{\partial \zeta_i} \left(\varphi(t) (c\zeta_i - \Gamma_0(\zeta_i)) + \zeta_{i+1} \right). \end{aligned}$$

Then, with $e_k(\cdot)$ from (6a) and $\gamma_k(\cdot)$ from (6c) we obtain

$$\gamma_k^{(j)}(t) = \Gamma_j(t, e_k(t), \dots, e_{k+j}(t)), \quad 0 \leq j \leq r-k,$$

which can be seen via a brief induction over k using equations (6).

Remark 1.9. Due to the recursive structure, the implementation of the control scheme (7) in the present article is not as simple as for the control scheme in [2, Eq. (9)]. However, with the explicit recursion (8) given in Remark 1.8 calculation of the required expressions can be done completely algorithmically.

We complete the preliminaries by recording the following lemma.

Lemma 1.10. If for $x \in \mathcal{C}^1([\tau, T]; \mathbb{R}^m)$, $m \in \mathbb{N}$, there exists $M \geq \|x(\tau)\| \geq 0$ such that

$$\forall t \in [\tau, T) : (\|x(t)\| \geq M \Rightarrow \frac{d}{dt} \|x(t)\|^2 \leq 0), \quad (9)$$

then

$$\forall t \in [\tau, T) : \|x(t)\| \leq M. \quad (10)$$

Proof. The proof follows the ideas in [16, Thm. 4.3]. Seeking a contradiction we assume that there exists $t_1 \in (\tau, T)$ such that $\|x(t_1)\| > M$. Then, by continuity, there exists $t_0 := \max \{ t \in [\tau, t_1) \mid \|x(t)\| = M \}$, and hence we have $\|x(t)\| \geq M$ for all $t \in [t_0, t_1]$. Then, using (9) we obtain

$$\|x(t_1)\|^2 - \|x(t_0)\|^2 = \int_{t_0}^{t_1} \left(\frac{d}{dt} \frac{1}{2} \|x(t)\|^2 \right) dt \leq 0,$$

and we find the contradiction

$$M^2 < \|x(t_1)\|^2 \leq \|x(t_0)\|^2 = M^2.$$

Therefore, (10) holds for all $t \in [\tau, T)$. \square

2 Main result

In this section we show that the application of the control scheme (7) to a system (3) yields an initial value problem

that has a solution; the input and output signals are bounded and in particular, we show that the introduced control scheme achieves exact output tracking in finite time with prescribed transient behaviour of the tracking error. As highlighted in earlier works, see e.g. [11,3,2] some care is required when showing boundedness of the involved signals since the bijection $\alpha(\cdot)$ may introduce a singularity. Moreover, in the present context expressions involving the unbounded funnel function $\varphi(\cdot)$ demand particularly high attention.

Theorem 2.1. Consider a system (3) with $(d, f, \mathbf{T}) \in \mathcal{N}^{m,r}$ and initial data $y^0 \in \mathcal{C}^{r-1}([-\sigma, 0]; \mathbb{R}^m)$, for $m, r \in \mathbb{N}$. Let $T > 0$ and $y_{\text{ref}} \in \mathcal{W}^{r,\infty}([0, T]; \mathbb{R}^m)$. Assume that for the control design parameters introduced in (5) and $e_k(\cdot)$ defined in (6) the initial condition

$$\forall k = 1, \dots, r : \|e_k(0)\| < 1 \quad (11)$$

is satisfied. Then, the funnel control scheme (7) applied to (3) yields an initial value problem which has a solution and every maximal solution $y : [-\sigma, \omega] \rightarrow \mathbb{R}^m$ has the following properties

- i) $\omega = T$,
- ii) $u \in \mathcal{L}^\infty([0, T]; \mathbb{R}^m)$, $y \in \mathcal{W}^{r,\infty}([-\sigma, T]; \mathbb{R}^m)$,
- iii) the tracking error $e(t) = y(t) - y_{\text{ref}}(t)$ evolves within the performance funnel \mathcal{F}_φ , this is,

$$\forall t \in [0, T] : \varphi(t)\|e(t)\| < 1,$$

- iv) the tracking of the reference and its derivatives is exact at $t = T$, this is,

$$\forall i = 0, \dots, r-1 : \lim_{t \rightarrow T} \|e^{(i)}(t)\| = 0.$$

The proof is relegated to the appendix.

Remark 2.2. Assertion *i*) in Theorem 2.1, namely $[0, T]$ being the maximal solution interval, naturally raises the question of a global solution in time. If the system's equations (3) are available and $y_{\text{ref}}(\cdot)$ is defined on $\mathbb{R}_{\geq 0}$, then $y(t) - y_{\text{ref}}(t) \equiv 0$ for all time $t \geq T$ can be achieved by asking the reference to satisfy (3) for $t \geq T$, with $u(\cdot) \equiv 0$ and "initial" conditions $y_{\text{ref}}(T) = y(T)$, $\dot{y}_{\text{ref}}(T) = \dot{y}(T)$, \dots , $y_{\text{ref}}^{(r-1)}(T) = y^{(r-1)}(T)$.

Remark 2.3. We highlight the following aspect of Theorem 2.1 which is of interest from a practical point of view. For any given $\varepsilon > 0$ there exists a time $T_\varepsilon < T$ such that the norm of each of the first $r-1$ derivatives of the error $e(\cdot) = y(\cdot) - y_{\text{ref}}(\cdot)$ is smaller than (or equal to) ε for all $t \in [T_\varepsilon, T]$, this is, for all $k = 0, \dots, r-1$

$$\forall \varepsilon > 0 \exists T_\varepsilon < T \forall t \in [T_\varepsilon, T] : \|e^{(k)}(t)\| \leq \varepsilon;$$

in fact we have $\|e^{(k)}(t)\| < \varepsilon$ for all $t \in (T_\varepsilon, T)$. This property is relevant, e.g. if during a docking manoeuvre the demanded accuracy changes.

3 Example

In this section we simulate an application of the control scheme (7) to a system (3) with $(d, f, \mathbf{T}) \in \mathcal{N}^{m,r}$. As indicated in the introduction, docking of two spaceships is a red-hot application of the findings of the present article. Therefore, we look at such a situation as an example. Consider a passive target space station, e.g., the international space station ISS, in a circular orbit around the earth and an active spacecraft chasing the first. We assume the passive space station to be on a constant altitude r_s with constant angular velocity $\omega = \sqrt{\mu/(r_e + r_s)^3}$, where $\mu \approx 3.986 \cdot 10^{14} \text{ m}^3/\text{s}^2$ is the standard gravitational parameter and $r_e = 6378137 \text{ m}$ the radius of the earth. To analyse the motion of the spacecraft, we use Hill's local-vertical-local-horizontal coordinate frame introduced in [10], see Figure 1. Within




Figure 1. Hill's local-vertical-local-horizontal coordinate frame.

this frame we use the commonly used Clohessy-Wiltshire model for satellite rendezvous proposed in [6] and elaborated on in [15] for instance. Let $r(t)$ denote the altitude of the chasing spacecraft at time t . Then, for $x(\cdot) = r(\cdot) - r_s(\cdot)$ the component of relative distance along the radial direction, $y(\cdot)$ the downtrack component along satellite's circular orbit, and $z(\cdot)$ the distance component along the satellite's angular momentum, and setting $\zeta(\cdot) := (\zeta_1(\cdot), \zeta_2(\cdot), \zeta_3(\cdot))^\top := (x(\cdot), y(\cdot), z(\cdot))^\top$ we obtain the Clohessy-Wiltshire equations

$$\begin{aligned} \ddot{\zeta}_1(t) &= 3\omega^2 \zeta_1(t) + 2\omega \dot{\zeta}_2(t) + u_x(t), \\ \ddot{\zeta}_2(t) &= -2\omega \dot{\zeta}_1(t) + u_y(t), \\ \ddot{\zeta}_3(t) &= -\omega^2 \zeta_3(t) + u_z(t). \end{aligned}$$

Defining the control input $u(\cdot) := (u_1(\cdot), u_2(\cdot), u_3(\cdot))^\top = (u_x(\cdot), u_y(\cdot), u_z(\cdot))^\top$, and $f : \mathbb{R}^3 \times \mathbb{R}^3 \rightarrow \mathbb{R}^3$, $(\xi, \nu) \mapsto (3\omega^2 \xi_1 + 2\omega \nu_2, -2\omega \nu_1, -\omega^2 \xi_3)^\top$ with $B = I_3 \in \mathbb{R}^{3 \times 3}$ the equations of motion above with output $\zeta(\cdot)$ can compactly be written as $\ddot{\zeta}(t) = f(\zeta(t), \dot{\zeta}(t)) + Bu(t)$, which is a system of relative degree two and belongs to the system class $\mathcal{N}^{3,2}$. For simulation purposes we choose $r_s = 415000 \text{ m}$ (\approx altitude ISS) which yields $\omega \approx 0.00113 \text{ s}^{-1}$ corresponding to an orbital period of approximately 93 minutes. Since we aim to simulate a docking manoeuvre we choose the reference trajectory $\zeta_{\text{ref}}(\cdot)$ such that $\zeta(T) = (0, 0, 0)^\top$ in Hill's

coordinate frame. To this end, we choose

$$\zeta_{\text{ref}}(t) = \zeta(0) \left(1 - \sin \left(\frac{\pi t}{2T} \right) \right),$$

guiding the spacecraft smoothly to the satellite, with $\zeta_{\text{ref}}(T) = \dot{\zeta}_{\text{ref}}(T) = (0, 0, 0)^\top$. We take the initial conditions as in [15] $x(0) = -y(0) = 1000$ m, and additionally $z(0) = 250$ m; and $\dot{x}(0) = -0.1$ ms⁻¹, $\dot{y}(0) = 1.69$ ms⁻¹ and $\dot{z}(0) = -0.05$ ms⁻¹. As docking time we choose $T = 1800$ s, this is docking within thirty minutes. For the funnel parameters we choose $N : s \mapsto -s \cos(10^{-2} s)$ and $\alpha : s \mapsto (r + 1)c/(1 - s)$, where with $c = 1$ the initial conditions (11) are satisfied. Since $\lim_{t \rightarrow T} \varphi(t) = \infty$ simulation is possible only for $[0, t_{\text{max}}]$ with $t_{\text{max}} = T - \text{eps}$ for a predefined $\text{eps} > 0$. Now, since $\varphi(t) \|e(t)\| < 1$ for all $t \in [0, T)$ we choose eps such that a certain upper bound of the spatial error at final time t_{max} is guaranteed, this is

$$\begin{aligned} \|e(t_{\text{max}})\| &< \frac{1}{\varphi(t_{\text{max}})} = c(T - t_{\text{max}}) \leq \text{eps} \\ &\Rightarrow t_{\text{max}} \geq T - \text{eps}/c. \end{aligned}$$

For the simulation we choose $\text{eps} = 10^{-10}$ m which means a spatial accuracy of Ångström (range of size of atoms). This seems to be a unnecessary high accuracy since in real applications the required rendezvous distance is about centimetres, then magnetic docking structures become active; however, if these fail unexpectedly, the feedback control still is capable to perform a docking manoeuvre. The simulation has been performed in MATLAB (solver: ode23tb). Figure 2 shows




Figure 2. Motion of the chasing spacecraft and the satellite with indicated earth (not true to scale) as center.

the docking manoeuvre with indicated earth (not true to scale) as center. Figure 3 shows the error between the reference and the respective coordinates. It can be seen that the docking manoeuvre is successful within the predefined finite time T and the errors evolve within the prescribed funnel boundary. In Figure 4 the errors of the respective velocities are depicted. As expectable from Theorem 2.1, the errors of the velocities tend to zero for $t \rightarrow T$. The control input is depicted in Figure 5; note that only little control effort is necessary to




Figure 3. Errors and funnel.






Figure 4. Error of the respective velocities.

reach the prescribed docking position. Figure 5b shows



(a) Control input.



(b) Control input in the very last moments.

Figure 5. Control input.

the control input in the very last moments before docking; where the largest input signals are generated, which may not be needed if the magnetic docking tools are activated and work as intended.

4 Conclusion and outlook

We introduced a funnel control scheme which achieves exact tracking in predefined finite time while the error between the reference and the output evolve within the boundaries of a prescribed funnel. We proved that the application of the proposed control scheme yields a closed loop system which has a maximal solution, all signals are bounded, and the error as well as all its relevant derivatives are zero at the predefined final time.

Acknowledgements

I am deeply indebted to Thomas Berger (University of Paderborn) for many fruitful discussions and helpful advices.

Appendix: Proof of Theorem 2.1

Proof. The proof is subdivided in several steps.
Step one. We show existence of a solution of (3),(7). To this end, we aim to reformulate (3),(7) as an initial value problem of the form

$$\begin{aligned} \dot{x}(t) &= F(t, x(t), \mathbf{T}(x)(t)), \\ x(0) &= (y^0(0), \dot{y}^0(0), \dots, (\frac{d}{dt})^{r-1}y^0(0)), \end{aligned} \quad (12)$$

where we set $n = rm$, and

$$x(t) = \left(y(t), \dot{y}(t), \dots, y^{(r-1)}(t) \right).$$

Setting $\mathcal{D}_0 := \{v \in \mathbb{R}^m \mid \|v\| < 1\}$ we choose some interval $I \subseteq [0, T)$ with $0 \in I$ such that $(e_1, \dots, e_r) : I \rightarrow \mathbb{R}^n$ satisfy the relations in (6) and be such that for all $t \in I$ we have $e_1(t), \dots, e_{r-1}(t) \in \mathcal{D}_0$, which is possible via the initial condition (11). Then, with the aid of (8) we have for all $k = 1, \dots, r-1$

$$\gamma_k^{(j)}(t) = \Gamma_j(t, e_k(t), \dots, e_{k+j}(t)), \quad 0 \leq j \leq r-k, \quad t \in I.$$

Next, we define the function

$$\begin{aligned} \tilde{e}_1 : [0, T) \times \mathbb{R}^m &\rightarrow \mathbb{R}^m, \\ (t, \xi_0) &\mapsto \varphi(t) (\xi_0 - y_{\text{ref}}(t)), \end{aligned}$$

and the set

$$\tilde{\mathcal{D}}_1 := \{(t, \xi_0) \in [0, T) \times \mathbb{R}^m \mid \tilde{e}_1(t, \xi_0) \in \mathcal{D}_0\}.$$

With this, we recursively define for $k = 2, \dots, r$ the functions

$$\begin{aligned} \tilde{e}_k : \tilde{\mathcal{D}}_{k-1} \times \mathbb{R}^m &\rightarrow \mathbb{R}^m, \\ (t, \xi_0, \dots, \xi_{k-1}) &\mapsto \varphi(t) \left(\xi_{k-1} - y_{\text{ref}}^{(k-1)}(t) \right) \\ &\quad + \varphi(t) \sum_{i=1}^{k-1} \Gamma_{k-1-i}(t, \tilde{e}_i, \dots, \tilde{e}_{k-1}), \end{aligned}$$

where for the sake of better legibility we omit the arguments of \tilde{e}_j , $j = 1, \dots, k-1$; and further, we define the sets

$$\begin{aligned} \tilde{\mathcal{D}}_k &:= \{(t, \xi_0, \dots, \xi_{k-1}) \in \tilde{\mathcal{D}}_{k-1} \times \mathbb{R}^m \mid \\ &\quad \tilde{e}_i(t, \xi_0, \dots, \xi_{k-1}) \in \mathcal{D}_0, i = 1, \dots, k\}. \end{aligned}$$

Together with $\alpha(\cdot), N(\cdot)$ as in (5) we define for $t \in I$

$$N_r(t) := (N \circ \alpha) \left(\|\tilde{e}_r(t, y(t), \dot{y}(t), \dots, y^{(r-1)}(t))\|^2 \right).$$

Then, the control $u(\cdot)$ defined in (7) reads

$$u(t) = N_r(t) \cdot \tilde{e}_r(t, y(t), \dots, y^{(r-1)}(t)), \quad t \in I.$$

Lastly, we define the function $F : \tilde{\mathcal{D}}_{r-1} \times \mathbb{R}^q \rightarrow \mathbb{R}^n$ by

$$(t, \xi_0, \dots, \xi_{r-1}, \eta) \mapsto (\xi_1, \dots, \xi_{r-1}, f(d(t), \eta, N_r(t) \cdot \tilde{e}_r)),$$

where in $\tilde{e}_r = \tilde{e}_r(t, \xi_0, \dots, \xi_{r-1})$ we omit the arguments for the sake of better legibility. Together, the initial value problem (3),(7) is equivalent to (12). In particular, we have $(0, x(0)) \in \tilde{\mathcal{D}}_{r-1}$, the function F is measurable in the variable t , continuous in $(\xi_0, \dots, \xi_{r-1}, \eta)$ and locally essentially bounded. Hence, invoking Remark 1.3, adapted to the current context, [12, Thm. B.1] yields the existence of a maximal solution $x : [-\sigma, \omega) \rightarrow \mathbb{R}^n$ of (12), $0 < \omega \leq T$. In particular, the graph of the solution of (12) is not a compact subset of $\tilde{\mathcal{D}}_{r-1}$.

Step two. For the functions $e_k(\cdot)$ introduced in (6a) we show that for all $k = 1, \dots, r-1$ there exists $\varepsilon_k \in (0, 1)$ such that $\|e_k(t)\| \leq \varepsilon_k$ for all $t \in [0, \omega)$. We observe that for $t \in [0, \omega)$ and $k = 1, \dots, r$ we have

$$e_k(t) - \varphi(t) \sum_{i=1}^{k-1} \gamma_i^{(k-1-i)}(t) = \varphi(t) e^{(k-1)}(t).$$

With this, and using $\dot{\varphi}(t) = c\varphi(t)^2$, we calculate for $k = 1, \dots, r-1$

$$\begin{aligned}
\dot{e}_k(t) &= \dot{\varphi}(t)e^{(k-1)}(t) + \varphi(t)e^{(k)}(t) \\
&+ \dot{\varphi}(t) \sum_{i=1}^{k-1} \gamma_i^{(k-1-i)}(t) + \varphi(t) \sum_{i=1}^{k-1} \gamma_i^{(k-i)}(t) \\
&= \frac{\dot{\varphi}(t)}{\varphi(t)} \left(e_k(t) - \varphi(t) \sum_{i=1}^{k-1} \gamma_i^{(k-1-i)}(t) \right) \\
&+ \left(e_{k+1}(t) - \varphi(t) \sum_{i=1}^k \gamma_i^{(k-i)}(t) \right) \\
&+ \dot{\varphi}(t) \sum_{i=1}^{k-1} \gamma_i^{(k-1-i)}(t) + \varphi(t) \sum_{i=1}^{k-1} \gamma_i^{(k-i)}(t) \\
&= (c - \alpha_k(t))\varphi(t)e_k(t) + e_{k+1}(t), \\
\dot{e}_r(t) &= c\varphi(t)e_r(t) + \varphi(t)e^{(r)}(t) + \varphi(t) \sum_{i=1}^{r-1} \gamma_i^{(r-i)}(t).
\end{aligned} \tag{13}$$

Further, using the definitions of $\alpha_k(\cdot)$ and $\gamma_k(\cdot)$, we record for later use

$$\begin{aligned}
\dot{\gamma}_k(t) &= \frac{d}{dt}(\alpha_k(t)e_k(t)) \\
&= 2\alpha'(\|e_k(t)\|^2)\langle e_k(t), \dot{e}_k(t) \rangle e_k(t) + \alpha_k(t)\dot{e}_k(t).
\end{aligned} \tag{14}$$

We observe $e_k(t) = \tilde{e}_k(y(t), \dots, y^{(k-1)}(t))$ and hence, since $\tilde{e}_k(\cdot) \in \mathcal{D}_0$ due to the initial conditions (11), we have

$$\forall k = 1, \dots, r \quad \forall t \in [0, \omega) : \|e_k(t)\| < 1.$$

We set $\hat{\varepsilon}_k := \|e_k(0)\|^2 < 1$ and $\lambda := \varphi(0) = \inf_{s \in [0, T)} \varphi(s) > 0$. Let ε be the unique point in $(0, 1)$ such that $\alpha(\varepsilon)\varepsilon = (1 + c\lambda)/\lambda$ and define $\varepsilon_k := \max\{\varepsilon, \hat{\varepsilon}_k\} < 1$. We show that

$$\forall k \in \{1, \dots, r-1\} \quad \forall t \in [0, \omega) : \|e_k(t)\|^2 \leq \varepsilon_k. \tag{15}$$

Seeking a contradiction we suppose this is false for at least one $\ell \in \{1, \dots, r-1\}$. Then $\|e_\ell(t_1)\|^2 > \varepsilon_\ell$ for some $t_1 \in (0, \omega)$ and we define

$$t_0 := \max \{ t \in [0, t_1] \mid \|e_\ell(t)\|^2 = \varepsilon_\ell \}.$$

With this we have

$$\forall t \in [t_0, t_1] : \varepsilon \leq \varepsilon_\ell \leq \|e_\ell(t)\|^2,$$

which gives, invoking monotonicity of $\alpha(\cdot)$, the following relation

$$\forall t \in [t_0, t_1] : \alpha(\varepsilon) \leq \alpha(\|e_\ell(t)\|^2) = \alpha_\ell(t).$$

Hence,

$$\forall t \in [t_0, t_1] : \alpha_\ell(t)\|e_\ell(t)\|^2 \geq \alpha(\varepsilon)\varepsilon = \frac{1 + c\lambda}{\lambda}.$$

With this, using $\alpha_\ell(\cdot) \geq c$ via (5c), and the relations in (13), we calculate for $t \in [t_0, t_1]$

$$\begin{aligned}
\frac{d}{dt} \frac{1}{2} \|e_\ell(t)\|^2 &= \langle e_\ell(t), (c - \alpha_\ell(t))\varphi(t)e_\ell(t) + e_{\ell+1}(t) \rangle \\
&= -\varphi(t)(\alpha_\ell(t) - c)\|e_\ell(t)\|^2 + \langle e_\ell(t), e_{\ell+1}(t) \rangle \\
&< -\varphi(t)(\alpha_\ell(t) - c)\|e_\ell(t)\|^2 + 1 \\
&\leq -\lambda(\alpha_\ell(t) - c)\|e_\ell(t)\|^2 + 1 \\
&< -\lambda\alpha_\ell(t)\|e_\ell(t)\|^2 + c\lambda + 1 \leq 0,
\end{aligned}$$

which implies the contradiction

$$\varepsilon_\ell < \|e_\ell(t_1)\|^2 < \|e_\ell(t_0)\|^2 = \varepsilon_\ell.$$

Therefore (15) holds. This implies boundedness of α_k (bounded by $\alpha(\varepsilon_k)$) and boundedness of γ_k (bounded by $\alpha(\varepsilon_k)\sqrt{\varepsilon_k}$) for all $k = 1, \dots, r-1$.

Step three. Since the functions $e_k(\cdot)$ defined in (6a) involve higher derivatives of the functions $\gamma_k(\cdot)$ we aim to show boundedness of the latter. In order to do so, recalling the definition of $\gamma_k(\cdot)$ we establish boundedness of higher derivatives of $\alpha_k(\cdot)$ on $[0, \omega)$, which in turn involve higher derivatives of $e_k(\cdot)$. Hence, we show boundedness of higher derivatives of $e_k(\cdot)$ on $[0, \omega)$; more precise, we show boundedness of $e_k^{(r-k)}(\cdot)$ on $[0, \omega)$ for $k = 1, \dots, r-1$. Recalling the definition of $\varphi(\cdot)$ in (5a) we have $\varphi^{(j)}(t) = c^j j! \varphi(t)^{j+1}$ for $j \in \mathbb{N}$. Using the generalized Leibniz rule, we obtain via (13) for $k = 1, \dots, r-1$ and $1 \leq j \leq r-k$ the recursion

$$\begin{aligned}
e_k^{(j)}(t) &= ((c - \alpha_k(t))\varphi(t)e_k(t))^{(j-1)} + e_{k+1}^{(j-1)}(t) \\
&= \sum_{j_1+j_2+j_3=j-1} \frac{(j-1)!}{j_1!j_2!j_3!} (c - \alpha_k(t))^{(j_1)} \varphi^{(j_2)}(t) e_k^{(j_3)}(t) \\
&+ e_{k+1}^{(j-1)}(t) \\
&= \sum_{j_1+j_2+j_3=j-1} \frac{(j-1)!}{j_1!j_3!} (c - \alpha_k(t))^{(j_1)} c^{j_2} \varphi(t)^{j_2+1} e_k^{(j_3)}(t) \\
&+ e_{k+1}^{(j-1)}(t).
\end{aligned} \tag{16}$$

We expatiate on the expression above for $j = 2$:

$$\begin{aligned}
\ddot{e}_k(t) &= -2\alpha'(\|e_k(t)\|^2)\langle e_k(t), \dot{e}_k(t) \rangle \varphi(t)e_k(t) \\
&+ (c - \alpha_k(t))c\varphi^2 e_k(t) \\
&+ (c - \alpha_k(t))((c - \alpha_k(t))\varphi(t)^2 e_k(t) + \varphi(t)e_{k+1}(t)) \\
&+ (c - \alpha_{k+1}(t))\varphi(t)e_{k+1}(t) + e_{k+2}(t).
\end{aligned}$$

This recursion successively leads to the following observations. Since $j_1 + j_2 + j_3 = j - 1$

- for $j_1 = 0$ the expression $\varphi(\cdot)^{j_2+1} e_k^{(j_3)}(\cdot)$ involves at most the $j - 1$ st derivative of $e_k(\cdot)$, and at

most the j^{th} power of $\varphi(\cdot)$; the other terms involve (at most) derivatives and powers of the form $\varphi(\cdot)^{j_2+1} e_k^{(j_1-j_2)}(\cdot)$ for $j \leq r-k$,

- $e_k^{(j)}(\cdot)$ involves $e_{k+1}^{(j-1)}(\cdot)$ which itself involves $e_{k+2}^{(j-2)}(\cdot)$ and so forth; therefore $e_k^{(j)}(\cdot)$ involves $e_{k+j}(\cdot)$,
- the highest derivative of $\alpha_k(\cdot)$ appearing in $e_k^{(j)}(\cdot)$ is $\alpha_k^{(j-1)}(\cdot)$, which itself involves at most the $j-1^{\text{st}}$ derivative of $e_k(\cdot)$.

These observations together with the fact that

$$\begin{aligned} \forall j \in \mathbb{N} : \varphi(\cdot)^j e_k(\cdot) &\in \mathcal{L}^\infty([0, \omega]; \mathbb{R}^m) \\ \Rightarrow \varphi(\cdot)^{j-1} e_k(\cdot) &\in \mathcal{L}^\infty([0, \omega]; \mathbb{R}^m) \end{aligned} \quad (17)$$

yield that boundedness of $e_k^{(j)}(\cdot)$ on $[0, \omega)$ can be established by showing boundedness of $\varphi(\cdot)^{r-k} e_k(\cdot)$ for all $k = 1, \dots, r-1$. In order to show this we initially establish the following: for all $k = 2, \dots, r-1$

$$\begin{aligned} \varphi(\cdot)^{r-k} e_k(\cdot) &\in \mathcal{L}^\infty([0, \omega]; \mathbb{R}^m) \\ \Rightarrow \varphi(\cdot)^{r-k+1} e_{k-1}(\cdot) &\in \mathcal{L}^\infty([0, \omega]; \mathbb{R}^m). \end{aligned} \quad (18)$$

To see this, let $\varphi(\cdot)^{r-k} e_k(\cdot) \in \mathcal{L}^\infty([0, \omega]; \mathbb{R}^m)$ and set $M_k := \sup_{s \in [0, \omega)} \|\varphi(s)^{r-k} e_k(s)\| < \infty$. Then we consider for $t \in [0, \omega)$

$$\begin{aligned} &\frac{d}{dt} \frac{1}{2} \|\varphi(t)^{r-k+1} e_{k-1}(t)\|^2 \\ &= \langle \varphi(t)^{r-k+1} e_{k-1}(t), \varphi(t)^{r-k+1} \dot{e}_{k-1}(t) \rangle \\ &\quad + \langle \varphi(t)^{r-k+1} e_{k-1}(t), c(r-k+1) \varphi(t)^{r-k+2} e_{k-1}(t) \rangle \\ &= \langle \varphi(t)^{r-k+1} e_{k-1}(t), \varphi(t)^{r-k+1} ((c - \alpha_{k-1}(t)) \varphi(t) e_{k-1}(t)) \rangle \\ &\quad + \langle \varphi(t)^{r-k+1} e_{k-1}(t), c(r-k+1) \varphi(t)^{r-k+2} e_{k-1}(t) \rangle \\ &\quad + \langle \varphi(t)^{r-k+1} e_{k-1}(t), \varphi(t)^{r-k+1} e_k(t) \rangle \\ &\leq -\varphi(t) (c(r+1) - c(r-k+2)) \|\varphi(t)^{r-k+1} e_{k-1}(t)\|^2 \\ &\quad + \varphi(t) M_k \|\varphi(t)^{r-k+1} e_{k-1}(t)\| \\ &\leq -\varphi(t) (c(k-1) \|\varphi(t)^{r-k+1} e_{k-1}(t)\| \\ &\quad - M_k) \cdot \|\varphi(t)^{r-k+1} e_{k-1}(t)\| \end{aligned}$$

which is non-positive for $\|\varphi(t)^{r-k+1} e_{k-1}(t)\| \geq \frac{M_k}{c(k-1)} \geq 0$ and hence Lemma 1.10 yields boundedness of $\varphi(\cdot)^{r-k+1} e_{k-1}(\cdot)$ on $[0, \omega)$. A successive application of (18) yields

$$\forall k = 1, \dots, r-1 : \varphi(\cdot)^{r-k} e_k(\cdot) \in \mathcal{L}^\infty([0, \omega]; \mathbb{R}^m). \quad (19)$$

In particular, via (17) we have $\varphi(\cdot) e_k(\cdot) \in \mathcal{L}^\infty([0, \omega]; \mathbb{R}^m)$ for all $k = 1, \dots, r-1$ from which boundedness of $\dot{e}_k(\cdot)$ follows, which in turn implies boundedness of $\dot{\alpha}_k(\cdot)$ and $\dot{\gamma}_k(\cdot)$ on $[0, \omega)$. Now, via (16) and (17) boundedness of $e_k^{(j)}(\cdot)$ successively follows for

all $j \leq r-k-1$, from which we may deduce boundedness of $\alpha_k^{(j)}(\cdot)$ and $\gamma_k^{(j)}(\cdot)$ for $j \leq r-k-1$, this is, for all $k = 1, \dots, r-1$ and $j \leq r-k-1$ there exists $\bar{\gamma}_k^j := \sup_{s \in [\tau, \omega)} \gamma_k^{(j)}(s) < \infty$.

Step four. We show boundedness of $x(\cdot)$ on $[0, \omega)$. Recalling the definition of $e_k(\cdot)$ we see that for all $k = 1, \dots, r$ we have via the previous steps

$$\begin{aligned} \forall t \in [\tau, \omega) : \|e^{(k-1)}(t)\| &\leq \left\| \frac{e_k(t)}{\varphi(t)} \right\| + \left\| \sum_{i=1}^{k-1} \gamma_i^{(k-1-i)}(t) \right\| \\ &\leq \frac{1}{\lambda} + \sum_{i=1}^{k-1} \bar{\gamma}_i^{k-1-i} < \infty. \end{aligned} \quad (20)$$

Therefore, since $x(\cdot) = (y(\cdot), \dots, y^{(r-1)}(\cdot)) = (e(\cdot) + y_{\text{ref}}(\cdot), \dots, e^{(r-1)}(\cdot) + y_{\text{ref}}^{(r-1)}(\cdot))$ and the reference $y_{\text{ref}} \in \mathcal{W}^{r, \infty}([0, T]; \mathbb{R}^m)$, we have $x \in \mathcal{L}^\infty([0, \omega]; \mathbb{R}^m)$.

Step five. We show boundedness of $\alpha_r(\cdot)$ on $[0, \omega)$. Invoking the previous steps, in particular boundedness of $x(\cdot)$ on $[0, \omega)$, and the properties of the operator class $\mathcal{T}_\sigma^{n, q}$ we deduce the existence of a compact $K_q \subset \mathbb{R}^q$ such that $T(x)(t) \in K_q$ for $t \in [0, \omega)$; furthermore, since $d \in L^\infty(\mathbb{R}_{\geq 0}; \mathbb{R}^p)$ there exists a compact $K_p \subset \mathbb{R}^p$ such that $d(t) \in K_p$ for $t \in [0, \omega)$. Via the high gain property there exists $\rho \in (0, 1)$ such that the continuous function

$$\begin{aligned} \chi : \mathbb{R} \rightarrow \mathbb{R}, \quad s \mapsto \min \{ \langle v, f(\delta, z, -sv) \rangle | \\ (\delta, z, v) \in K_q \times K_p \times V \} \end{aligned}$$

is unbounded from above; where we defined the compact set $V := \{v \in \mathbb{R}^m \mid \rho \leq \|v\| \leq 1\}$. We show boundedness of $\alpha_r(\cdot)$ by contradiction. Since $N : \mathbb{R}_{\geq 0} \rightarrow \mathbb{R}$ is surjective, the set $\{\kappa > \rho_0 \mid N(\kappa) = \rho_1\}$ is non-empty for every $\rho_0 \in \mathbb{R}_{\geq 0}$ and every $\rho_1 \in \mathbb{R}$. Following the proof in [2, pp. 188-190], we choose a real sequence (s_j) such that the corresponding sequence $(\chi(s_j))$ is positive, strictly increasing and in particular unbounded. We initialize a sequence (κ_j) by choosing $\kappa_1 > \alpha(\rho^2) + \alpha_r(0)$ such that $N(\kappa_1) = s_1$, and hereinafter define the strictly increasing sequence (κ_j) via

$$\kappa_{j+1} := \inf \{ \kappa > \kappa_j \mid N(\kappa) = s_{j+1} \},$$

which obviously yields that $\lim_{j \rightarrow \infty} \chi(N(\kappa_j)) = \lim_{j \rightarrow \infty} \chi(s_j) = \infty$. Now, since we assumed $\alpha_r(\cdot)$ to be unbounded and we have $\kappa_{j+1} > \kappa_1 > \alpha_r(0)$ for all $j \in \mathbb{N}$, we may define the sequence

$$\tau_j := \inf \{ t \in [0, \omega) \mid \alpha_r(t) = \kappa_{j+1} \}, \quad j \in \mathbb{N}_0,$$

which lies within $(0, \omega)$. Note that (τ_j) is strictly increasing and we have $N(\alpha_r(\tau_j)) = N(\kappa_{j+1}) = s_{j+1}$ for each $j \in \mathbb{N}_0$. Next, we define a second sequence in $(0, \omega)$

$$\sigma_j = \sup \{ t \in [\tau_{j-1}, \tau_j] \mid \chi(N(\alpha_r(t))) = \chi(s_j) \}, \quad j \in \mathbb{N}.$$

With this, since the sequence $(\chi(s_j))$ is strictly increasing, we obtain for all $j \in \mathbb{N}$

$$\chi(N(\alpha_r(\sigma_j))) = \chi(s_j) < \chi(s_{j+1}) = \chi(N(\alpha_r(\tau_j))),$$

and therefore,

$$\forall j \in \mathbb{N} : \sigma_j < \tau_j, \quad (21a)$$

as well as for all $j \in \mathbb{N}$

$$\forall t \in (\sigma_j, \tau_j] : \chi(N(\alpha_r(\sigma_j))) = \chi(s_j) < \chi(N(\alpha_r(t))). \quad (21b)$$

Next, we show by contradiction that for all $j \in \mathbb{N}$ and for all $t \in [\sigma_j, \tau_j]$ we have $e_r(t) \in V$. To this end, we first show - by contradiction - that for all $j \in \mathbb{N}$ we have $\alpha_r(t) \geq \kappa_j$ for $t \in [\sigma_j, \tau_j]$. Suppose that $\alpha_r(t) < \kappa_j$ for some $t \in [\sigma_j, \tau_j]$. Then by $\alpha_r(\tau_j) = \kappa_{j+1} > \kappa_j$ and by continuity of α_r there exists $\tilde{t} \in (\sigma_j, \tau_j)$ such that $\alpha_r(\tilde{t}) = \kappa_j$. Hence, we find $\chi(N(\alpha_r(\tilde{t}))) = \chi(N(\kappa_j)) = \chi(s_j)$, which contradicts the definition of σ_j . Therefore, $\alpha_r(t) \geq \kappa_j$ for all $t \in [\sigma_j, \tau_j]$. Now, suppose $e_r(t) \notin V$, this is, since for all $t \in [0, \omega)$ we have $\|e_r(t)\| < 1$, we suppose $\|e_r(t)\| < \rho$ for some $[\sigma_j, \tau_j]$. This, together with $\alpha_r(t) \geq \kappa_j$, leads to the contradiction $\alpha(\rho^2) < \kappa_1 \leq \kappa_j \leq \alpha_r(t) = \alpha(\|e_r(t)\|^2) < \alpha(\rho^2)$. Hence, we deduce

$$\forall j \in \mathbb{N} \forall t \in [\sigma_j, \tau_j] : e_r(t) \in V.$$

Now, since $d(t) \in K_p$ and $T(x)(t) \in K_q$ for $t \in [0, \omega)$ we obtain, using (21), for all $j \in \mathbb{N}$ and $t \in [\sigma_j, \tau_j]$

$$\begin{aligned} & \langle e_r(t), f(d(t), (Tx)(t), u(t)) \rangle \\ &= -\langle -e_r(t), f(d(t), \mathbf{T}(x)(t), -N(\alpha_r(t))(-e_r(t))) \rangle \\ &\leq -\min \left\{ \langle v, f(\delta, z, -N(\alpha_r(t))v) \mid \begin{array}{l} (\delta, z, v) \\ \in K_p \times K_q \times V \end{array} \right\} \\ &= -\chi(N(\alpha_r(t))) \\ &\leq -\chi(s_j). \end{aligned} \quad (22)$$

Since $y_{\text{ref}} \in \mathcal{W}^{r, \infty}([0, T]; \mathbb{R}^m)$ we may set $c_{\text{ref}} := \sup_{s \geq 0} \|y_{\text{ref}}^{(r)}(s)\| < \infty$, and we recall $\sum_{i=1}^{r-1} \tilde{\gamma}_i^{r-i} < \infty$ from the previous steps. Furthermore, we observe $\sigma_1 > 0$ and therefore, by properties of $\varphi(\cdot)$ we may define $0 < \inf_{s \in [\sigma_1, T]} \varphi(s) =: c_\varphi$. Then, with the aid of (13)

and (22) for all $j \in \mathbb{N}$ and $t \in [\sigma_j, \tau_j]$ we obtain

$$\begin{aligned} & \frac{d}{dt} \frac{1}{2} \|e_r(t)\|^2 \\ &= \langle e_r(t), c_\varphi(t) e_r(t) \rangle \\ &\quad + \langle e_r(t) \varphi(t) (f(d(t), (Tx)(t), u(t)) - y_{\text{ref}}^{(r)}(t)) \rangle \\ &\quad + \langle e_r(t), \varphi(t) \sum_{i=1}^{r-1} \tilde{\gamma}_i^{(r-i)}(t) \rangle \\ &< \varphi(t) \left(c + c_{\text{ref}} + \sum_{i=1}^{r-1} \tilde{\gamma}_i^{r-i} - \chi(s_j) \right). \end{aligned}$$

Thus, still seeking a contradiction, we may choose $J \in \mathbb{N}$ large enough such that for $t \in [\sigma_J, \tau_J]$ we have

$$\begin{aligned} & \varphi(t) \left(c + c_{\text{ref}} + \sum_{i=1}^{r-1} \tilde{\gamma}_i^{r-i} - \chi(s_J) \right) \\ &\leq -c_\varphi \left(\chi(s_J) - \left(c + c_{\text{ref}} + \sum_{i=1}^{r-1} \tilde{\gamma}_i^{r-i} \right) \right) < 0, \end{aligned}$$

which yields $\|e_r(\tau_J)\|^2 < \|e_r(\sigma_J)\|^2$, which in turn gives for $t \in [\sigma_J, \tau_J]$

$$\alpha_r(\tau_J) = \alpha(\|e_r(\tau_J)\|^2) < \alpha(\|e_r(\sigma_J)\|^2) = \alpha_r(\sigma_J).$$

This, however, contradicts the definition of τ_J , by which we have $\alpha_r(t) < \alpha_r(\tau_J)$ for all $t \in [0, \tau_J)$. Therefore, the assumption of an unbounded $\alpha_r(\cdot)$ cannot be true. As a direct consequence thereof, we may infer the existence of $\varepsilon_r \in (0, 1)$ such that

$$\forall t \in [0, \omega) : \|e_r(t)\|^2 \leq \varepsilon_r.$$

Step six. We show $\omega = T$. Via the previous steps we have for all $k = 1, \dots, r$

$$\forall t \in [0, \omega) : \|e_k(t)\| \leq \varepsilon^* := \sqrt{\max\{\varepsilon_1, \dots, \varepsilon_r\}} < 1,$$

by which the set

$$\hat{\mathcal{D}} := \{ (\zeta_1, \dots, \zeta_r) \in \mathbb{R}^{rm} \mid \|\zeta_i\| \leq \varepsilon^*, i = 1, \dots, r \}$$

is a compact subset of $\tilde{\mathcal{D}}_{r-1}$. Assume $\omega < T$. Then,

$$\forall t \in [0, \omega) : x(t) \in \hat{\mathcal{D}} \subset \tilde{\mathcal{D}}_{r-1}.$$

So, by compactness of $\hat{\mathcal{D}}$ the closure of the graph of the solution $x(\cdot)$ of (12) on $[0, \omega)$ is a compact subset of $\tilde{\mathcal{D}}_{r-1}$ which contradicts the findings of *Step one*. Thus, $\omega = T$. *Step seven.* Assertion *ii*) is a direct consequence of *Step four* and *Step six*; and assertion *iii*) follows from *Step two* and *Step six*.

Step eight. We show that the tracking error $e(\cdot)$ and its derivatives tend to zero as $t \rightarrow T$, this is, we show

$$\forall k = 1, \dots, r : \lim_{t \rightarrow T} \|e^{(k-1)}(t)\| = 0. \quad (23)$$

Note that the estimation in (20) is too rough to show (23). Recalling the definition (6c) of $\gamma_k(\cdot) = \alpha_k(\cdot)e_k(\cdot)$ and exemplify its derivative (14) we see that by *Step three* not only $\gamma_k^{(j)}(\cdot)$ is bounded on $[0, \omega)$ for $j \leq r - k - 1$ but with the aid of (19) even the product $\varphi(\cdot)\gamma_k^{(j)}(\cdot)$ is bounded on $[0, \omega)$, i.e., for all $\ell = 1 \dots, r - 1$ there exists $\hat{\gamma}_\ell^j := \sup_{s \in [\tau, \omega)} \varphi(s)\gamma_\ell^{(j)}(s) < \infty$ for $0 \leq j \leq r - \ell - 1$. Invoking *Step two* and *Step five* we may improve estimation (20) for all $k = 1, \dots, r$ and all $t \in [\tau, \omega)$ as follows

$$\begin{aligned} \|e^{(k-1)}(t)\| &\leq \frac{\|e_k(t)\|}{\varphi(t)} + \frac{1}{\varphi(t)} \left\| \sum_{i=1}^{k-1} \varphi(t)\gamma_i^{(k-1-i)}(t) \right\| \\ &\leq \frac{\sqrt{\varepsilon_k} + \sum_{i=1}^{k-1} \hat{\gamma}_i^{k-1-i}}{\varphi(t)}. \end{aligned}$$

From this, since $\omega = T$ by *Step six*, and $\lim_{t \rightarrow T} \varphi(t) = \infty$ we obtain (23) for all $k = 1, \dots, r$, which shows assertion *iv*) of the theorem and completes the proof. \square

References

- [1] Michael Basin, Chandrasekhara Bharath Panathula, Yuri B. Shtessel, and Pablo Rodriguez-Ramirez. Continuous finite-time higher-order output regulators for systems with unmatched unbounded disturbances. *IEEE Transactions on Industrial Electronics*, pages 1–1, 2016.
- [2] Thomas Berger, Achim Ilchmann, and Eugene P. Ryan. Funnel control of nonlinear systems. *Mathematics of Control, Signals, and Systems*, 33(1):151–194, feb 2021.
- [3] Thomas Berger, Huy Hoàng Lê, and Timo Reis. Funnel control for nonlinear systems with known strict relative degree. *Automatica*, 87:345–357, 2018.
- [4] S. P. Bhat and D. S. Bernstein. Geometric homogeneity with applications to finite-time stability. *Mathematics of Control, Signals, and Systems*, 17(2):101–127, may 2005.
- [5] Christopher I. Byrnes and Jan C. Willems. Adaptive stabilization of multivariable linear systems. In *Proc. 23rd IEEE Conf. Decis. Control*, pages 1574–1577, 1984.
- [6] W. H. Clohessy and R. S. Wiltshire. Terminal guidance system for satellite rendezvous. *Journal of the Aerospace Sciences*, 27(9):653–658, sep 1960.
- [7] Jorge Davila. Exact tracking using backstepping control design and high-order sliding modes. *IEEE Transactions on Automatic Control*, 58(8):2077–2081, aug 2013.
- [8] Ioannis S. Dimanidis, Charalampos P. Bechlioulis, and George A. Rovithakis. Output feedback approximation-free prescribed performance tracking control for uncertain MIMO nonlinear systems. *IEEE Transactions on Automatic Control*, 65(12):5058–5069, dec 2020.
- [9] Antonio Estrada, Leonid Fridman, and Rafael Iriarte. Combined backstepping and HOSM control design for a class of nonlinear MIMO systems. *International Journal of Robust and Nonlinear Control*, 27(4):566–581, jul 2016.
- [10] G. W. Hill. Researches in the lunar theory. *American Journal of Mathematics*, 1(3):245, 1878.
- [11] Achim Ilchmann. Decentralized tracking of interconnected systems. In Knut Hüper and Jochen Trumpf, editors, *Mathematical System Theory - Festschrift in Honor of Uwe Helmke on the Occasion of his Sixtieth Birthday*, pages 229–245. CreateSpace, 2013.
- [12] Achim Ilchmann and Eugene P. Ryan. Performance funnels and tracking control. *Int. J. Control*, 82(10):1828–1840, 2009.
- [13] Achim Ilchmann, Eugene P. Ryan, and Christopher J. Sangwin. Tracking with prescribed transient behaviour. *ESAIM: Control, Optimisation and Calculus of Variations*, 7:471–493, 2002.
- [14] Esteban Jiménez-Rodríguez, Juan Diego Sánchez-Torres, and Alexander G. Loukianov. Predefined-time backstepping control for tracking a class of mechanical systems. *IFAC-PapersOnLine*, 50(1):1680–1685, jul 2017.
- [15] Craig A. Kluever. Feedback control for spacecraft rendezvous and docking. *Journal of Guidance, Control, and Dynamics*, 22(4):609–611, jul 1999.
- [16] Lukas Lanza. Internal dynamics of multibody systems. *Systems & Control Letters*, 152:104931, jun 2021.
- [17] Jin Gyu Lee and Stephan Trenn. Asymptotic tracking via funnel control. In *2019 IEEE 58th Conference on Decision and Control (CDC)*. IEEE, dec 2019.
- [18] Eduardo V.L. Nunes, Alessandro J. Peixoto, Tiago Roux Oliveira, and Liu Hsu. Global exact tracking for uncertain MIMO linear systems by output feedback sliding mode control. *Journal of the Franklin Institute*, 351(4):2015–2032, 2014-04.
- [19] E.V.L. Nunes, Liu Hsu, and F. Lizarralde. Global exact tracking for uncertain systems using output-feedback sliding mode control. *IEEE Transactions on Automatic Control*, 54(5):1141–1147, 2009-05.
- [20] Tiago Roux Oliveira, Alessandro Jacoud Peixoto, and Liu Hsu. Peaking free output-feedback exact tracking of uncertain nonlinear systems via dwell-time and norm observers. *Int. J. Robust & Nonlinear Control*, 23(5):483–513, 2013.
- [21] Eugene P. Ryan, Christopher J. Sangwin, and Philip Townsend. Controlled functional differential equations: approximate and exact asymptotic tracking with prescribed transient performance. *ESAIM: Control, Optimisation and Calculus of Variations*, 15:745–762, 2009.
- [22] Stephan Trenn. Asymptotic tracking with funnel control. *PAMM*, 19(1), sep 2019.
- [23] Christos K. Verginis and Dimos V. Dimarogonas. Asymptotic stability of uncertain Lagrangian systems with prescribed transient response. In *Proceeding 58th IEEE Conference on Decision and Control, Nice, France*, pages 7037–7042. IEEE, 2019-12.
- [24] Christos K. Verginis and Dimos V. Dimarogonas. Asymptotic tracking of second-order nonsmooth feedback stabilizable unknown systems with prescribed transient response. *IEEE Transactions on Automatic Control*, 66(7):3296–3302, 2021-07.
- [25] Jun Yang, Zhengtao Ding, Shihua Li, and Chuanlin Zhang. Continuous finite-time output regulation of nonlinear systems with unmatched time-varying disturbances. *IEEE Control Systems Letters*, 2(1):97–102, 2018-01.