

Differential-algebraic systems with dissipative Hamiltonian structure

V. Mehrmann^{†*} A.J. van der Schaft[†]

August 5, 2022

Abstract

Different representations of dissipative Hamiltonian and port-Hamiltonian differential-algebraic equations (DAE) systems are presented and compared. Using global geometric and algebraic points of view, translations between the different representations are presented. Characterizations are also derived when a general DAE system can be transformed into one of these structured representations. Approaches for computing the structural information and the described transformations are derived that can be directly implemented as numerical methods. The results are demonstrated with a large number of examples.

Keywords. Port-Hamiltonian system, dissipative Hamiltonian system, differential algebraic equation, Lagrange structure, Dirac structure, matrix pencil.

AMS subject classification. 15A18, 15A21, 15A22

1 Introduction

In recent years, a variety of approaches have been taken to extend the energy based modeling concept of port-Hamiltonian (pH) systems to systems with constraints, called pH differential-algebraic equations (pHDAEs) or pH descriptor systems, see e.g. [6, 21, 22, 31, 32, 33, 37]. Constraints typically arise in electrical or transport networks, where Kirchhoff's laws constrain the models at network nodes, as balance equations in chemical engineering, or as holonomic or non-holonomic constraints in mechanical multibody systems. Furthermore, they arise in the interconnection of pH systems when the interface conditions are explicitly formulated and enforced via Lagrange multipliers, see [4, 29, 36, 37, 38, 39], or the recent survey [30].

In this paper we recall different model representations of pHDAEs, respectively dissipative Hamiltonian DAEs (dHDAEs) and provide a systematic geometric and algebraic theory that also provides a 'translation' between the different representations. We also discuss approaches for explicitly computing the structural information that can be directly implemented as numerical methods. We mainly restrict ourselves to finite-dimensional linear time-invariant systems without inputs and outputs, but indicate in several places where extensions to general systems are possible. We also discuss only real systems although most of the results can also be formulated for complex problems in a similar way.

*Institut für Mathematik, Sekr. MA 4-5, TU Berlin, Straße des 17. Juni 136, 10623 Berlin, Germany. mehrmann@math.tu-berlin.de. Research supported by Deutsche Forschungsgemeinschaft DFG through priority Programm SPP 1984 within project 790 39-2: Distributed dynamic control of network security.

[†]Bernoulli institute for Mathematics, Computer Science and AI, Jan C. Willems Center for Systems and Control, University of Groningen, Nijenborgh 9, Groningen, the Netherlands

For general linear time-invariant homogeneous differential-algebraic equations (DAEs)

$$E\dot{x} = Ax, \quad (1)$$

where $E, A \in \mathbb{R}^{\ell, n}$ (without considering the geometric and algebraic structures) and also for their extensions to linear time-varying and nonlinear systems, the theory is well understood [23]. The structural properties are characterized via the (real) Kronecker canonical form of the matrix pair (E, A) , see e.g. [19] and Appendix A. In this paper we will mainly discuss *regular* square systems, i.e., systems with $\ell = n$ and $\det(\lambda E - A)$ not identically zero, but the methods also extend to over- and under-determined systems. An important quantity that will be used through the paper is the size of the largest Kronecker block associated with the eigenvalue ∞ , which is called the (*differentiation*) *index of the pair* (E, A) *as well as the associated DAE*, where, by convention, $\nu = 0$ if E is invertible.

1.1 Dissipative Hamiltonian DAEs

In contrast to general DAEs of the form (1), the DAEs that arise in energy based modeling have extra structure and symmetries. One well established representation is that of *dissipative Hamiltonian DAEs* (*dHDAEs*) which has been studied in detail in [4, 27, 28] and has the form

$$E\dot{z} = (J - R)Qz, \quad (2)$$

where $J = -J^\top, R = R^\top \in \mathbb{R}^{\ell, \ell}$, and $E, Q \in \mathbb{R}^{\ell, n}$ with $E^\top Q = Q^\top E$. In this representation the associated Hamilton function (*Hamiltonian*) is given by the quadratic form

$$\mathcal{H}^z(z) = \frac{1}{2}z^\top E^\top Qz, \quad (3)$$

which (as an energy) is typically nonnegative for all z , but more general Hamiltonians also arise in practice. Furthermore, the dissipation term R is positive semidefinite, denoted as $R \geq 0$, but we will first discuss the case that $R = 0$ which we call *Hamiltonian DAE* (*HDAEs*).

Remark 1 The definition of (dHDAEs) in (2) can be easily extended to systems with ports in which case it takes the form

$$\begin{aligned} E\dot{z} &= (J - R)Qz + (F - G)u, \\ y &= (F + G)^\top Qz + Du, \end{aligned} \quad (4)$$

with

$$\begin{bmatrix} Q^\top JQ & Q^\top F \\ -F^\top Q & \frac{1}{2}(D - D^\top) \end{bmatrix} = - \begin{bmatrix} Q^\top JQ & Q^\top F \\ -F^\top Q & \frac{1}{2}(D - D^\top) \end{bmatrix}^\top$$

and

$$\begin{bmatrix} Q^\top RQ & Q^\top G \\ G^\top Q & \frac{1}{2}(D + D^\top) \end{bmatrix} = \begin{bmatrix} Q^\top RQ & Q^\top G \\ G^\top Q & \frac{1}{2}(D + D^\top) \end{bmatrix}^\top \geq 0,$$

see [4]. We will call these systems *dissipative pHDAE* (*dpHDAE*) *systems*.

Structured DAEs of the form (2) arise naturally in almost all physical domains.

Example 2 A simple model of an RLC network, see e.g. [4, 12, 18], has the form

$$\underbrace{\begin{bmatrix} G_c C G_c^\top & 0 & 0 \\ 0 & L & 0 \\ 0 & 0 & 0 \end{bmatrix}}_{:=E} \begin{bmatrix} \dot{V} \\ \dot{I}_l \\ \dot{I}_v \end{bmatrix} = \underbrace{\begin{bmatrix} -G_r R_r^{-1} G_r^\top & -G_l & -G_v \\ G_l^\top & 0 & 0 \\ G_v^\top & 0 & 0 \end{bmatrix}}_{:=J-R} \begin{bmatrix} V \\ I_l \\ I_v \end{bmatrix}, \quad (5)$$

where the real positive definite matrices L , C , R_r describe inductances, capacitances, and resistances, respectively. The matrices G_l encode the network topology and G_v is of full column rank. The subscripts r , c , l , and v refer to the resistors, capacitors, inductors, and voltage sources, while V , I_l , I_v denote voltage and currents, respectively. This system has the form (2), with $E = E^\top \geq 0$, $Q = I$ and where J and $-R$ are defined to be the skew-symmetric and symmetric part, respectively, of the matrix on the right hand side of (5). The Hamiltonian is given by $\mathcal{H}(V, I_l) = \frac{1}{2}(V^\top G_c C G_c^\top V + I_l^\top L I_l)$ and it does not involve the variables I_v that are in the kernel of E .

Example 3 Space discretization of the Stokes equation in fluid dynamics, see, e.g., [17], leads to a dissipative Hamiltonian system

$$\begin{bmatrix} M & 0 \\ 0 & 0 \end{bmatrix} \begin{bmatrix} \dot{v}_h \\ \dot{p}_h \end{bmatrix} = \begin{bmatrix} A & B \\ -B^\top & 0 \end{bmatrix} \begin{bmatrix} v_h \\ p_h \end{bmatrix} + \begin{bmatrix} f_h \\ 0 \end{bmatrix},$$

where $A = A^\top$ is a positive semidefinite discretization of the negative Laplace operator, B is a discretized gradient, and $M = M^\top$ is a positive definite mass matrix. The homogeneous system has the form (2), with

$$R = \begin{bmatrix} A & 0 \\ 0 & 0 \end{bmatrix}, \quad J = \begin{bmatrix} 0 & B \\ -B^\top & 0 \end{bmatrix}, \quad E = \begin{bmatrix} M & 0 \\ 0 & 0 \end{bmatrix}, \quad Q = I.$$

The Hamiltonian is given by $\mathcal{H} = \frac{1}{2}v_h^\top M v_h$; it does not involve the variables p_h .

Example 4 Space discretization of the Euler equation describing the acoustic wave propagation in a gas pipeline network [14, 15] leads to a DAE

$$\begin{bmatrix} M_1 & 0 & 0 \\ 0 & M_2 & 0 \\ 0 & 0 & 0 \end{bmatrix} \begin{bmatrix} \dot{p}_h \\ \dot{q}_h \\ \dot{\lambda} \end{bmatrix} = \left(\begin{bmatrix} 0 & -G & 0 \\ G^\top & 0 & K^\top \\ 0 & -K & 0 \end{bmatrix} - \begin{bmatrix} 0 & 0 & 0 \\ 0 & D & 0 \\ 0 & 0 & 0 \end{bmatrix} \right) \begin{bmatrix} p_h \\ q_h \\ \lambda \end{bmatrix} + f,$$

where p_h is the discretized pressure, q_h is a discretized flux, and λ is a Lagrange multiplier that penalizes the violation of the conservation of mass and momentum at the pipeline nodes.

The homogeneous system has the form (2) with $Q = I$, and Hamiltonian $\mathcal{H}(p_h, q_h) = \frac{1}{2}(p_h^\top M_1 p_h + q_h^\top M_2 q_h)$. The Hamiltonian does not involve the Lagrange multiplier λ .

Example 5 Consider a linear mechanical system $M\ddot{x} + D\dot{x} + Wx = f$, together with kinematic constraints $G\dot{x} = 0$, see e.g. [16]. Incorporating the constraints in the dynamical system using a Lagrange multiplier λ via $M\ddot{x} + D\dot{x} + Wx = f + G^\top \lambda$, the system can be written in first order form as

$$\begin{bmatrix} M & 0 & 0 \\ 0 & I & 0 \\ 0 & 0 & 0 \end{bmatrix} \begin{bmatrix} \ddot{x} \\ \dot{x} \\ \dot{\lambda} \end{bmatrix} + \begin{bmatrix} D & I & -G^\top \\ -I & 0 & 0 \\ G & 0 & 0 \end{bmatrix} \begin{bmatrix} I & 0 & 0 \\ 0 & W & 0 \\ 0 & 0 & I \end{bmatrix} \begin{bmatrix} \dot{x} \\ x \\ \lambda \end{bmatrix} = \begin{bmatrix} f \\ 0 \\ 0 \end{bmatrix}.$$

Here, $E = E^\top$ and $Q = Q^\top$ are commuting matrices, E , W , and $R = R^\top$ are positive semidefinite, so the homogeneous system is of the form (2). The Hamiltonian is given by $\mathcal{H}(x, \dot{x}) = \frac{1}{2}(\dot{x}^\top M \dot{x} + x^\top W x)$ (kinetic plus potential energy) and does not involve the Lagrange multiplier λ . Note that $G^\top \lambda$ has the interpretation of the vector of *constraint forces* due to the kinematic constraints $G\dot{x} = 0$.

As indicated in the presented examples, singularity of E , and thus the presence of algebraic constraints, implies that the Hamiltonian (total stored energy) $\frac{1}{2}z^\top E^\top Q z$ does not involve all of the variables contained in the state vector z . In fact in some of the examples the variables that do not show up in the Hamiltonian are *Lagrange multipliers*. Conversely, singularity of E may arise as a limiting situation of otherwise regular Hamiltonians, as shown by the following simple example.

Example 6 Consider the model of standard mass-spring-damper system

$$\begin{bmatrix} \dot{q} \\ \dot{p} \end{bmatrix} = \begin{bmatrix} 0 & 1 \\ -1 & -d \end{bmatrix} \begin{bmatrix} k & 0 \\ 0 & \frac{1}{m} \end{bmatrix} \begin{bmatrix} q \\ p \end{bmatrix}$$

with Hamiltonian $\mathcal{H}(q, p) = \frac{1}{2}kq^2 + \frac{p^2}{2m}$ and take the limit $m \rightarrow 0$. To compute the limit, we rewrite the system in coordinates q and $v := \frac{p}{m}$ as

$$\begin{bmatrix} \dot{q} \\ m\dot{v} \end{bmatrix} = \begin{bmatrix} 0 & 1 \\ -1 & -d \end{bmatrix} \begin{bmatrix} kq \\ v \end{bmatrix}$$

with Hamiltonian $\mathcal{H}(q, v) = \frac{1}{2}kq^2 + \frac{1}{2}mv^2$. For $m \rightarrow 0$ this converges to the DAE system

$$\begin{bmatrix} \dot{q} \\ 0 \end{bmatrix} = \begin{bmatrix} 0 & 1 \\ -1 & -d \end{bmatrix} \begin{bmatrix} kq \\ v \end{bmatrix},$$

which is of (differentiation) index one if $d \neq 0$, and of index two if $d = 0$. The limiting Hamiltonian $\mathcal{H}(q, v) = \frac{1}{2}kq^2$ is not a function of v anymore.

Alternatively, we can compute the limit for $k \rightarrow \infty$. For this we rewrite the system in coordinates $F := kq$ and p as

$$\begin{bmatrix} \frac{1}{k}\dot{F} \\ \dot{p} \end{bmatrix} = \begin{bmatrix} 0 & 1 \\ -1 & -d \end{bmatrix} \begin{bmatrix} F \\ \frac{p}{m} \end{bmatrix},$$

with Hamiltonian $\mathcal{H}(F, p) = \frac{1}{2k}F^2 + \frac{1}{2m}p^2$. For $k \rightarrow \infty$ this converges to the DAE system

$$\begin{bmatrix} 0 \\ \dot{p} \end{bmatrix} = \begin{bmatrix} 0 & 1 \\ -1 & -d \end{bmatrix} \begin{bmatrix} F \\ \frac{p}{m} \end{bmatrix},$$

which is index two for any d , with Hamiltonian $\mathcal{H}(F, p) = \frac{1}{2m}p^2$, which is not involving F .

We may also take the limits $m \rightarrow 0$ and $k \rightarrow \infty$ simultaneously. By rewriting the system in the variables F, v , with Hamiltonian $\mathcal{H}(F, p) = \frac{1}{2k}F^2 + \frac{1}{2}mv^2$. This leads to the purely algebraic system

$$\begin{bmatrix} 0 \\ 0 \end{bmatrix} = \begin{bmatrix} 0 & 1 \\ -1 & -d \end{bmatrix} \begin{bmatrix} F \\ v \end{bmatrix},$$

with zero Hamiltonian, and having a single solution $v = 0, F = 0$, irrespective of the damper.

1.2 Extended Hamiltonian DAEs

Classically, Hamiltonian systems and also their extension to systems with inputs and outputs, called port-Hamiltonian systems, see e.g. [13, 21, 26, 35, 37, 40, 41], are defined by a *Dirac structure*, representing the power-conserving interconnection structure, an *energy-dissipation relation*, and a *Hamilton function (Hamiltonian)*, capturing the total energy storage in the system. The Dirac structure formalizes the *generalized junction structure* known from port-based modeling theory. Importantly, the Dirac structure may entail linear constraints on the so-called effort variables, called *effort constraints*. Through the gradient vector of the Hamilton function, these effort constraints induce algebraic constraints on the state variables, see especially [29, 36] for a discussion of general nonlinear, port-Hamiltonian DAEs. In the special case of a linear autonomous system without energy dissipation and without inputs and outputs, the equations of motion take the DAE form

$$K\dot{x} = LQx, \quad (6)$$

where the pair of matrices K, L , satisfying $KL^\top + LK^\top = 0$ and $\text{rank} \begin{bmatrix} K & L \end{bmatrix} = \dim(x)$, describes the Dirac structure, and $H(x) = \frac{1}{2}x^\top Qx$ defines the Hamilton function for some $Q = Q^\top$. Denoting by \ker and im the kernel and image of a linear map or its matrix representation, geometrically the Dirac structure is defined by the subspace $\mathcal{D} \subset \mathcal{X} \times \mathcal{X}^*$ given as $\ker \begin{bmatrix} K & L \end{bmatrix}$, where \mathcal{X} is the linear state space, and \mathcal{X}^* its dual space.

Remark 7 More precisely $\mathcal{D} \subset \hat{\mathcal{X}} \times \mathcal{X}^*$, where $\hat{\mathcal{X}}$ is the *tangent space* to \mathcal{X} at $x \in \mathcal{X}$. However, since \mathcal{X} is linear, tangent spaces at any $x \in \mathcal{X}$ can be identified with each other and with \mathcal{X} .

Algebraic constraints occur if the matrix K is singular, and are represented via

$$Qx \in \text{im } K^\top.$$

Singularity of K often results from network modeling as the following example demonstrates.

Example 8 Consider a general linear LC -electrical circuit. Let the circuit graph be determined by an incidence matrix D , defining Kirchhoff's current laws $I \in \ker D$ and voltage laws $V \in \text{im } D^\top$. Split the currents I into currents I_C through the capacitors and currents I_L through the inductors, and the voltages V into voltages V_C across the capacitors and voltages V_L across the inductors. Furthermore, let $I_C = -\dot{q}_C$ and $V_L = -\dot{\varphi}$, with q the vector of charges at the capacitors and φ the flux linkages of the inductors. Split the incidence matrix D accordingly as $D = \begin{bmatrix} D_C & D_L \end{bmatrix}$. Then Kirchhoff's current laws take the form

$$D_C \dot{q} = D_L I_L.$$

Furthermore, let F be a maximal annihilator of D^\top , i.e., $\ker F = \text{im } D^\top$. Then Kirchhoff's voltage laws take the form $F \begin{bmatrix} V_C \\ V_L \end{bmatrix} = 0$, and after splitting $F = \begin{bmatrix} F_C & F_L \end{bmatrix}$ accordingly, we have

$$F_L \dot{\varphi} = F_C V_C.$$

Writing the linear constitutive equations for the capacitors as $q = CV_C$ for some positive definite diagonal matrix C and those for the inductors as $\varphi = LI_L$ for some positive definite diagonal matrix L , we finally obtain the system of equations

$$\begin{bmatrix} D_C & 0 \\ 0 & F_L \end{bmatrix} \begin{bmatrix} \dot{q} \\ \dot{\varphi} \end{bmatrix} = \begin{bmatrix} 0 & D_L \\ F_C & 0 \end{bmatrix} \begin{bmatrix} C^{-1} & 0 \\ 0 & L^{-1} \end{bmatrix} \begin{bmatrix} q \\ \varphi \end{bmatrix}$$

in the form (6) with Hamilton function $\mathcal{H}(q, \varphi) = \frac{1}{2}q^\top C^{-1}q + \frac{1}{2}\varphi^\top L^{-1}\varphi$. It is easily checked that singularity of $K = \begin{bmatrix} D_C & 0 \\ 0 & F_L \end{bmatrix}$ corresponds to parallel interconnection of capacitors or series interconnection of inductors.

Motivated by [4] the port-Hamiltonian point of view on DAE systems was extended in [38] by replacing the gradient vector Qx of the Hamiltonian function $\mathcal{H}(x) = \frac{1}{2}x^\top Qx$ by a general Lagrangian subspace, called *Lagrange structure* in the present paper, since we want to emphasize the similarity with Dirac structures. As we will see, this extension allows to bridge the gap with the (dissipative) Hamiltonian formulation (4) of the previous subsection 1.1.

In the linear homogeneous case without dissipation, one starts with a Dirac structure $\mathcal{D} \subset \mathcal{X} \times \mathcal{X}^*$ defined by a pair K, L as in (6), and a Lagrange structure $\mathcal{L} \subset \mathcal{X} \times \mathcal{X}^*$. The *composition* of the Dirac structure \mathcal{D} and the Lagrange structure \mathcal{L} , over the *shared variables* $e \in \mathcal{X}^*$, is then defined as

$$\mathcal{D} \circ \mathcal{L} = \{(f, x) \in \mathcal{X} \times \mathcal{X} \mid \text{there exists } e \in \mathcal{X}^* \text{ such that } (f, e) \in \mathcal{D}, (e, x) \in \mathcal{L}\}. \quad (7)$$

Substituting $f = -\dot{x}$ this leads to the coordinate-free definition of the dynamics

$$(-\dot{x}, x) \in \mathcal{D} \circ \mathcal{L}. \quad (8)$$

In order to obtain a coordinate representation of the dynamics (8), the simplest option (later on in Section 3.1 we will discuss another one) is to start from the *image representation* of the Lagrange structure \mathcal{L} , defined by a pair of matrices P, S satisfying $P^\top S = S^\top P$ and $\text{rank} \begin{bmatrix} P^\top & S^\top \end{bmatrix} = \dim \mathcal{X}$. Taking linear coordinates x for \mathcal{X} , the image representation of \mathcal{L} is given by

$$\begin{bmatrix} x \\ e \end{bmatrix} = \begin{bmatrix} Pz \\ Sz \end{bmatrix}, \quad (9)$$

for some parameterizing vector z in a space \mathcal{Z} (of the same dimension as x), where e denotes dual coordinates in \mathcal{X}^* . Analogously, we consider a *kernel representation* of the Dirac structure \mathcal{D} given by matrices K, L satisfying $KL^\top = -LK^\top$ and $\text{rank} \begin{bmatrix} K & L \end{bmatrix} = \dim \mathcal{X}$, such that $\mathcal{D} = \{(f, e) \in \mathcal{X} \times \mathcal{X}^* \mid Kf + Le = 0\}$. (More details will be given in Section 2.)

Substituting $f = -\dot{x} = P\dot{z}$ and $e = Sz$ this leads to the coordinate representation

$$KP\dot{z} = LSz. \quad (10)$$

We will call this class *extended Hamiltonian differential-algebraic systems (extended HDAEs)*. If dissipation is incorporated, see Section 2.2, then it is called *extended dHDAEs*.

Importantly, the presence of algebraic constraints in (10) may arise *both* by singularity of K (as was already the case for (6)) as well as by singularity of P (as was the case for (2)). This motivated the introduction of the notions of *Dirac algebraic constraints* (corresponding

to singularity of K) and of *Lagrange algebraic constraints* (corresponding to singularity of P) in [38].

Similar to dHDAE systems (2), the Hamiltonian of the extended HDAE system (10) is specified by the Lagrange structure, and is given by

$$\mathcal{H}(z) = \frac{1}{2}z^\top S^\top Pz. \quad (11)$$

Indeed, one immediately has the energy conservation property

$$\frac{d}{dt}\mathcal{H}(z) = z^\top S^\top P\dot{z} = -e^\top f = 0,$$

since $(f, e) \in \mathcal{D}$.

While singularity of K in physical systems modeling typically arises by *interconnection* due to the network structure, singularity of P often arises as a limiting situation. An elaborate example will be provided later as Example 13.

Remark 9 Note that if K is *invertible*, then by multiplying (10) with K^{-1} from the left we obtain the lossless version of the dHDAE system (2) in Section 1.1 with $E = P$, $Q = S$, $J = -J^\top = K^{-1}L$ (and $R = 0$). Thus the replacement of the Hamiltonian $\mathcal{H}(x) = \frac{1}{2}x^\top Qx$ by a Lagrange subspace (9) constitutes a first step towards an *overarching* formulation of (dissipative) Hamiltonian DAE systems.

The goal of this paper is to study in detail the relationship and differences between different classes of (extended) Hamiltonian DAEs; without making any a priori invertibility assumptions. Furthermore, we exploit at the same time a *geometric* point of view on Hamiltonian DAEs using Lagrange and Dirac structures (as well maximally monotone subspaces; cf. Section 2.2), and an *algebraic* point of view using (computationally feasible) condensed forms. From an DAE analysis point of view, similar to the result known already for Hamiltonian DAEs of the form (2) in [27], we also show that the index of an (extended) dissipative Hamiltonian DAEs can be at most two. Moreover, we will show that index two algebraic constraints may only arise from singularity of P , i.e., from the Lagrange structure, and thus are strictly linked to singular Hamiltonians.

Another important question that we will answer is the characterization when a general DAE is equivalent to a structured DAE the form ((2) or ((10)).

The paper is organized as follows. In Section 2 we will present the geometric theory of dissipative Hamiltonian DAEs, we introduce Dirac and Lagrange structures as well maximally monotone subspaces to introduce dissipation. Section 3 presents different coordinate representations and their relation. To derive algebraic characterizations, in Section 4 we present different types of equivalence transformations and corresponding condensed forms for the different classes of (extended dissipative) Hamiltonian DAEs. In Section 5 it is analyzed when general linear DAEs can be represented as (extended dissipative) Hamiltonian systems. In all sections we present examples that illustrate the properties of the different representations. In several appendices we present proofs that can be implemented as numerically stable algorithms.

2 Geometric theory of (dissipative) Hamiltonian DAEs

In this section we take a systematic geometric view on Hamiltonian DAE systems, extending the existing geometric treatment of extended HDAE systems, as already discussed in Section

1.2. We also incorporate the discussed classes of dHDAE systems from Section 1.1.

Consider an n -dimensional linear state space \mathcal{X} with elements denoted by x . Let $\hat{\mathcal{X}}$ denote the *tangent space* to \mathcal{X} at $x \in \mathcal{X}$, with elements denoted by f and called *flow* vectors. Since \mathcal{X} is linear, tangent spaces at different x can be identified with each other and with \mathcal{X} ; implying that $f \in \mathcal{X}$ as well. Furthermore, let \mathcal{X}^* be the *dual space* of \mathcal{X} , with elements denoted by e and called *effort* vectors.

2.1 Dirac and Lagrange structures

The product space $\mathcal{X} \times \mathcal{X}^*$ is endowed with the two canonical bilinear forms

$$\begin{aligned} \langle (f_1, e_1), (f_2, e_2) \rangle_+ &:= f_1^\top e_2 + f_2^\top e_1, \\ \langle (f_1, e_1), (f_2, e_2) \rangle_- &:= f_1^\top e_2 - f_2^\top e_1, \end{aligned} \tag{12}$$

represented by the two matrices

$$\Pi_+ := \begin{bmatrix} 0 & I_n \\ I_n & 0 \end{bmatrix}, \quad \Pi_- := \begin{bmatrix} 0 & I_n \\ -I_n & 0 \end{bmatrix},$$

where we recognize Π_- as the standard symplectic form on \mathcal{X} .

Definition 10 *A subspace $\mathcal{D} \subset \mathcal{X} \times \mathcal{X}^*$ is called a Dirac structure on \mathcal{X} if the bilinear form $\langle \cdot, \cdot \rangle_+$ is zero on \mathcal{D} and moreover \mathcal{D} has maximal dimension with respect to this property. A subspace $\mathcal{L} \subset \mathcal{X} \times \mathcal{X}^*$ is a Lagrange structure if the bilinear form $\langle \cdot, \cdot \rangle_-$ is zero on \mathcal{L} and moreover \mathcal{L} has maximal dimension with respect to this property. A Lagrange structure $\mathcal{L} \subset \mathcal{X} \times \mathcal{X}^*$ is called nonnegative if the quadratic form defined by Π_+ is nonnegative on \mathcal{L} .*

Remark 11 In this paper we have chosen the terminology ‘Lagrange structure’, instead of the more common terminology ‘Lagrangian subspace’, in order to emphasize the similarity to Dirac structures. Also note that the definition of Dirac structures can be extended to manifolds instead of linear state spaces \mathcal{X} ; in this context Dirac structures on linear spaces are often referred to as *constant Dirac structures*.

We have the following characterizations of Lagrange and Dirac structures, see e.g. [13, 37].

Proposition 12 *Consider an n -dimensional linear state space \mathcal{X} and its dual space \mathcal{X}^* .*

- i) A subspace $\mathcal{D} \subset \mathcal{X} \times \mathcal{X}^*$ is a Dirac structure on \mathcal{X} if and only if $\mathcal{D} = \mathcal{D}^{\perp\perp+}$, where $\perp\perp+$ denotes the orthogonal complement with respect to the bilinear form $\langle \cdot, \cdot \rangle_+$ if and only if $e^\top f = 0$ for all $(f, e) \in \mathcal{D}$ and $\dim \mathcal{D} = n$.*
- ii) A subspace $\mathcal{L} \subset \mathcal{X} \times \mathcal{X}^*$ is a Lagrange structure if and only if $\mathcal{L} = \mathcal{L}^{\perp\perp-}$, where $\perp\perp-$ denotes the orthogonal complement with respect to the bilinear form $\langle \cdot, \cdot \rangle_-$. Any Lagrange structure satisfies $\dim \mathcal{L} = \dim \mathcal{X}$.*

Dirac and Lagrange structures admit structured *coordinate representations*, see e.g. [37, 38]. For this paper the following representations are most relevant. Using matrices $K, L \in \mathbb{R}^{n,n}$, any Dirac structure $\mathcal{D} \subset \mathcal{X} \times \mathcal{X}^*$ admits the kernel/image representation

$$\mathcal{D} = \ker \begin{bmatrix} K & L \end{bmatrix} = \text{im} \begin{bmatrix} L^\top \\ K^\top \end{bmatrix} \subset \mathcal{X} \times \mathcal{X}^*, \tag{13}$$

with K, L satisfying $\text{rank} \begin{bmatrix} K & L \end{bmatrix} = n$ as well as the generalized *skew-symmetry condition*

$$KL^\top + LK^\top = 0. \quad (14)$$

Conversely any such pair K, L defines a Dirac structure.

Analogously, any Lagrange structure $\mathcal{L} \subset \mathcal{X} \times \mathcal{X}^*$ can be represented as

$$\mathcal{L} = \ker \begin{bmatrix} -P^\top & S^\top \end{bmatrix} = \text{im} \begin{bmatrix} S \\ P \end{bmatrix} \subset \mathcal{X}^* \times \mathcal{X}, \quad (15)$$

for certain matrices $S, P \in \mathbb{R}^{n,n}$ satisfying $\text{rank} \begin{bmatrix} P \\ S \end{bmatrix}$ as well as the generalized *symmetry condition*

$$S^\top P = P^\top S. \quad (16)$$

A Lagrange structure is, furthermore, *nonnegative* if and only if $S^\top P \geq 0$.

As already described in Section 1.2, by using the image representation $x = Pz$, $e = Sz$ of the Lagrange structure \mathcal{L} , and the kernel representation $Kf + Le = 0$ of the Dirac structure \mathcal{D} one is led to the representation (10) of the extended HDAE system defined by \mathcal{D} and \mathcal{L} . The following is a physical example where both K and P turn out to be singular. The singularity of K is due to the presence of kinematic constraints, while the singularity of P is caused by a limiting argument in the energy expression.

Example 13 Consider two masses m_1 and m_2 connected by a spring with spring constant k , where the right mass m_2 is subject to the kinematic constraint $v_2 = 0$ (velocity is zero). With positions q_1, q_2 and momenta p_1, p_2 , the Hamiltonian is given by

$$\mathcal{H}(q_1, q_2, p_1, p_2) = \frac{1}{2}k(q_1 - q_2)^2 + \frac{p_1^2}{2m_1} + \frac{p_2^2}{2m_2}.$$

Denoting by e_{q1}, e_{q2} the spring forces at both ends of the spring, and by e_{p1}, e_{p2} the velocities of the two masses, we obtain the relation

$$\begin{bmatrix} q_1 \\ q_2 \\ p_1 \\ p_2 \\ e_{q1} \\ e_{q2} \\ e_{p1} \\ e_{p2} \end{bmatrix} = \begin{bmatrix} 1 & 0 & 0 & 0 \\ 0 & 1 & 0 & 0 \\ 0 & 0 & 1 & 0 \\ 0 & 0 & 0 & 1 \\ \hline k & -k & 0 & 0 \\ -k & k & 0 & 0 \\ 0 & 0 & \frac{1}{m_1} & 0 \\ 0 & 0 & 0 & \frac{1}{m_2} \end{bmatrix} \begin{bmatrix} z_1 \\ z_2 \\ z_3 \\ z_4 \end{bmatrix}$$

To consider the limit $k \rightarrow \infty$, meaning that the spring is replaced by rigid connection, we first express the system in different coordinates.

$$\begin{bmatrix} z_1 \\ z_2 \\ z_3 \\ z_4 \end{bmatrix} = \begin{bmatrix} \frac{m_2}{m_1+m_2} & 1 & 0 & 0 \\ -\frac{m_1}{m_1+m_2} & 1 & 0 & 0 \\ 0 & 0 & 1 & \frac{m_1}{m_1+m_2} \\ 0 & 0 & -1 & \frac{m_2}{m_1+m_2} \end{bmatrix} \begin{bmatrix} \tilde{z}_1 \\ \tilde{z}_2 \\ \tilde{z}_3 \\ \tilde{z}_4 \end{bmatrix}.$$

This yields the transformed representation

$$\begin{bmatrix} q_1 \\ q_2 \\ p_1 \\ p_2 \\ e_{q1} \\ e_{q2} \\ e_{p1} \\ e_{p2} \end{bmatrix} = \begin{bmatrix} \frac{m_2}{m_1+m_2} & 1 & 0 & 0 \\ -\frac{m_1}{m_1+m_2} & 1 & 0 & 0 \\ 0 & 0 & 1 & \frac{m_1}{m_1+m_2} \\ 0 & 0 & -1 & \frac{m_2}{m_1+m_2} \\ k & 0 & 0 & 0 \\ -k & 0 & 0 & 0 \\ 0 & 0 & \frac{1}{m_1} & \frac{1}{m_1+m_2} \\ 0 & 0 & -\frac{1}{m_2} & \frac{1}{m_1+m_2} \end{bmatrix} \begin{bmatrix} \tilde{z}_1 \\ \tilde{z}_2 \\ \tilde{z}_3 \\ \tilde{z}_4 \end{bmatrix}.$$

Taking the limit $k \rightarrow \infty$ yields the Lagrange structure \mathcal{L} in image representation

$$\begin{bmatrix} q_1 \\ q_2 \\ p_1 \\ p_2 \\ e_{q1} \\ e_{q2} \\ e_{p1} \\ e_{p2} \end{bmatrix} = \begin{bmatrix} 0 & 1 & 0 & 0 \\ 0 & 1 & 0 & 0 \\ 0 & 0 & 1 & \frac{m_1}{m_1+m_2} \\ 0 & 0 & -1 & \frac{m_2}{m_1+m_2} \\ 1 & 0 & 0 & 0 \\ -1 & 0 & 0 & 0 \\ 0 & 0 & \frac{1}{m_1} & \frac{1}{m_1+m_2} \\ 0 & 0 & -\frac{1}{m_2} & \frac{1}{m_1+m_2} \end{bmatrix} \begin{bmatrix} \tilde{z}_1 \\ \tilde{z}_2 \\ \tilde{z}_3 \\ \tilde{z}_4 \end{bmatrix}$$

and the limiting Hamiltonian is just the kinetic energy

$$\mathcal{H}(\tilde{z}_1, \tilde{z}_2, \tilde{z}_3, \tilde{z}_4) = \frac{1}{2} \left(\frac{1}{m_1} + \frac{1}{m_2} \right) \tilde{z}_3^2 + \frac{\tilde{z}_4^2}{2(m_1 + m_2)} = \frac{\tilde{z}_4^2}{2(m_1 + m_2)}.$$

The system has a *Lagrange algebraic constraint* due to the linear dependency in the rows of P .

The Dirac structure \mathcal{D} is given as

$$\begin{aligned} \mathcal{D} &= \{(f_{q1}, f_{q2}, f_{p1}, f_{p2}, e_{q1}, e_{q2}, e_{p1}, e_{p2}) = 0 \mid \text{there exists } \lambda \\ \text{s.t. } \begin{bmatrix} f_{q1} \\ f_{q2} \\ f_{p1} \\ f_{p2} \end{bmatrix} &= \begin{bmatrix} 0 & 0 & -1 & 0 \\ 0 & 0 & 0 & -1 \\ 1 & 0 & 0 & 0 \\ 0 & 1 & 0 & 0 \end{bmatrix} \begin{bmatrix} e_{q1} \\ e_{q2} \\ e_{p1} \\ e_{p2} \end{bmatrix} + \begin{bmatrix} 0 \\ 0 \\ 0 \\ 1 \end{bmatrix} \lambda \}. \end{aligned}$$

After elimination of the Lagrange multiplier λ this yields

$$K = \begin{bmatrix} 1 & 0 & 0 & 0 \\ 0 & 1 & 0 & 0 \\ 0 & 0 & 1 & 0 \\ 0 & 0 & 0 & 0 \end{bmatrix}, \quad L = \begin{bmatrix} 0 & 0 & 1 & 0 \\ 0 & 0 & 0 & 1 \\ -1 & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 \end{bmatrix},$$

and hence

$$KP = \begin{bmatrix} 0 & 1 & 0 & 0 \\ 0 & 1 & 0 & 0 \\ 0 & 0 & 1 & \frac{m_1}{m_1+m_2} \\ 0 & 0 & 0 & 0 \end{bmatrix}, \quad LS = \begin{bmatrix} 0 & 0 & \frac{1}{m_1} & \frac{1}{m_1+m_2} \\ 0 & 0 & -\frac{1}{m_2} & \frac{1}{m_1+m_2} \\ -1 & 0 & 0 & 0 \\ 0 & 0 & -\frac{1}{m_2} & \frac{1}{m_1+m_2} \end{bmatrix}.$$

Finally subtracting the second equation from the first equation, we obtain the HDAE system

$$\begin{bmatrix} 0 & 0 & 0 & 0 \\ 0 & 1 & 0 & 0 \\ 0 & 0 & 1 & \frac{m_1}{m_1+m_2} \\ 0 & 0 & 0 & 0 \end{bmatrix} \begin{bmatrix} \dot{\tilde{z}}_1 \\ \dot{\tilde{z}}_2 \\ \dot{\tilde{z}}_3 \\ \dot{\tilde{z}}_4 \end{bmatrix} = \begin{bmatrix} 0 & 0 & \frac{1}{m_1} + \frac{1}{m_2} & 0 \\ 0 & 0 & -\frac{1}{m_2} & \frac{1}{m_1+m_2} \\ -1 & 0 & 0 & 0 \\ 0 & 0 & -\frac{1}{m_2} & \frac{1}{m_1+m_2} \end{bmatrix} \begin{bmatrix} \tilde{z}_1 \\ \tilde{z}_2 \\ \tilde{z}_3 \\ \tilde{z}_4 \end{bmatrix}.$$

Here the first equation is the Lagrange algebraic constraint $\tilde{z}_3 = 0$ (and eventually $\tilde{z}_1 = 0$) obtained by taking $k \rightarrow \infty$ (corresponding to singularity of P), and the last equation is the Dirac algebraic constraint $-\frac{\tilde{z}_3}{m_2} + \frac{\tilde{z}_4}{m_1+m_2} = 0$, i.e., $\tilde{z}_4 = 0$ resulting from the kinematic constraint, leading to singularity of K and resulting in the trivial dynamics $\dot{\tilde{z}}_2 = 0$.

Remark 14 Instead of using a parametrization of the Lagrange structure \mathcal{L} one can also use a parameterization of the Dirac structure \mathcal{D} ,

$$\begin{bmatrix} f \\ e \end{bmatrix} = \begin{bmatrix} L^\top \\ K^\top \end{bmatrix} v \quad (17)$$

with $v \in \mathcal{V}$, where \mathcal{V} is an n -dimensional parameter space. This yields an extended dHDAE system (but now in the parameter vector v) given by

$$P^\top K^\top \dot{v} = S^\top L^\top v \quad (18)$$

which is the *adjoint system* of (10). See [24] for a detailed discussion of adjoint systems of DAEs.

2.2 Incorporation of dissipation

As noted in Section 2, extended HDAE systems (10), geometrically defined by a Dirac and Lagrange structure, already include HDAE systems (2) *without* dissipation. Conversely, any HDAE system with K invertible can be rewritten into the form (2) with $R = 0$.

In order to complete the geometric viewpoint towards the inclusion of dissipation (and thus to (2)), we recall the geometric definition of a port-Hamiltonian system [34, 37, 40]. By replacing the Hamiltonian function by a Lagrange structure as in [38], and specializing to the case without external variables (inputs and outputs), such systems will be called *extended dHDAE systems*.

Definition 15 Consider a state space \mathcal{X} with linear coordinates x and a linear space of resistive flows \mathcal{F}_R . Furthermore, consider a Dirac structure \mathcal{D} on $\mathcal{X} \times \mathcal{F}_R$, a Lagrange structure $\mathcal{L} \subset \mathcal{X} \times \mathcal{X}^*$, and a nonnegative Lagrange structure $\mathcal{R} \subset \mathcal{F}_R \times \mathcal{F}_R^*$. Then an extended dissipative Hamiltonian DAE (extended dHDAE) system is defined as the tuple $(\mathcal{X}, \mathcal{F}_R, \mathcal{D}, \mathcal{L}, \mathcal{R})$ with

$$\left\{ (\dot{x}, x) \mid \text{there exist } e \in \mathcal{X}^*, f_R \in \mathcal{F}_R, e_R \in \mathcal{F}_R^* \text{ such that } (-\dot{x}, -f_R, e, e_R) \in \mathcal{D}, (f_R, e_R) \in \mathcal{R}, (x, e) \in \mathcal{L} \right\}. \quad (19)$$

If \mathcal{L} is represented as in (15), i.e.

$$\mathcal{L} = \left\{ \left[\begin{array}{c} x \\ e \end{array} \right] \mid \left[\begin{array}{c} x \\ e \end{array} \right] = \left[\begin{array}{c} P \\ S \end{array} \right] z, z \in \mathbb{R}^n \right\}, \quad (20)$$

then it immediately follows from the properties of the Dirac structure \mathcal{D} and the nonnegative Lagrange structure \mathcal{R} that the dynamics of the extended dHDAE satisfies

$$\frac{d}{dt}\left(\frac{1}{2}z^\top S^\top Pz\right) = e_R^\top f_R \leq 0.$$

More generally we will now introduce the notion a *maximally monotone subspace*, which is overarching the notions of a Dirac structure \mathcal{D} and a nonnegative Lagrange structure \mathcal{R} .

Definition 16 Consider a linear space \mathcal{X} . A subspace $\mathcal{M} \subset \mathcal{X} \times \mathcal{X}^*$ is called *monotone subspace* if

$$e^\top f \geq 0 \tag{21}$$

for all $(f, e) \in \mathcal{M}$, and it is *maximally monotone* if additionally there does not exist a monotone subspace $\mathcal{M}' \subset \mathcal{X} \times \mathcal{X}^*$ with $\mathcal{M} \subsetneq \mathcal{M}'$.

Remark 17 The definition of a monotone subspace is a special case of the notion of a monotone *relation* \widetilde{M} , which is defined as a *subset* of $\mathcal{X} \times \mathcal{X}^*$ satisfying

$$(e_1 - e_2)^\top (f_1 - f_2) \geq 0 \tag{22}$$

for all $(f_1, e_1), (f_2, e_2) \in \widetilde{M}$. Clearly if \widetilde{M} is a subspace then (22) reduces to (21). Nonlinear port-Hamiltonian systems with respect to a general (maximal) monotone relation were coined as *incremental port-Hamiltonian systems* in [9]; see [10] for further developments.

Obviously, a subspace \mathcal{M} is monotone if and only if the quadratic form defined by Π_+ is nonnegative on \mathcal{M} , since

$$\langle (f, e), (f, e) \rangle_+ = 2e^\top f, \quad (f, e) \in \mathcal{X} \times \mathcal{X}^*.$$

Proposition 18 Consider a state space \mathcal{X} with $\dim \mathcal{X} = n$. Then any monotone subspace of $\mathcal{X} \times \mathcal{X}^*$ has dimension less than or equal to n , and any maximally monotone subspace of $\mathcal{X} \times \mathcal{X}^*$ has dimension n . Any maximally monotone subspace $\mathcal{M} \subset \mathcal{X} \times \mathcal{X}^*$ can be represented as

$$\mathcal{M} = \text{im} \begin{bmatrix} N^\top \\ M^\top \end{bmatrix} \tag{23}$$

for $M, N \in \mathbb{R}^{n,n}$ satisfying $\text{rank} \begin{bmatrix} N & M \end{bmatrix} = n$ and

$$MN^\top + NM^\top \geq 0. \tag{24}$$

Conversely, any subspace defined by M, N satisfying (24) is a maximally monotone subspace.

Proof. The proof follows, since Π_+ has n positive and n negative eigenvalues. \square

Obviously any Dirac structure \mathcal{D} given by a pair of matrices K, L is maximally monotone (take $M = K$ and $N = L$). In a similar way any nonnegative Lagrange structure \mathcal{R} given by a pair of matrices P, S with $S^\top P \geq 0$ is maximally monotone by taking $N^\top = P$, $M^\top = S$. Importantly, also the *composition* of two maximally monotone subspaces is again maximally monotone.

In order to prove this we first state the following lemma.

Lemma 19 *Let $A : \mathcal{F} \rightarrow \mathcal{G}$ be a linear map between two linear spaces \mathcal{F}, \mathcal{G} . Let $\mathcal{M}_{\mathcal{G}} \subset \mathcal{G} \times \mathcal{G}^*$ be a maximally monotone subspace. Then the pull-back of $\mathcal{M}_{\mathcal{G}}$ via A , defined as*

$$b_A(\mathcal{M}_{\mathcal{G}}) := \{(f, A^*g^*) \in \mathcal{F} \times \mathcal{F}^* \mid (Af, g^*) \in \mathcal{M}_{\mathcal{G}}\},$$

is maximally monotone. Furthermore, let $\mathcal{M}_{\mathcal{F}} \subset \mathcal{F} \times \mathcal{F}^$ be a maximally monotone subspace. Then the push-forward of $\mathcal{M}_{\mathcal{F}}$ via A , defined as*

$$f_A(\mathcal{M}_{\mathcal{F}}) := \{(Af, g^*) \in \mathcal{G} \times \mathcal{G}^* \mid (f, A^*g^*) \in \mathcal{M}_{\mathcal{F}}\},$$

is maximally monotone.

Proof. It is immediately checked that $b_A(\mathcal{M}_{\mathcal{G}})$ is monotone. Furthermore

$$\begin{aligned} \dim b_A(\mathcal{M}_{\mathcal{G}}) &= \dim \mathcal{M}_{\mathcal{G}} + \dim \ker A - \dim \ker A^* = \\ &\dim \mathcal{G} + \dim \ker A - \dim \ker A^* = \dim \mathcal{F}, \end{aligned}$$

and thus $b_A(\mathcal{M}_{\mathcal{G}})$ is maximally monotone. The proof to show that $f_A(\mathcal{M}_{\mathcal{F}})$ is maximally monotone is analogous. \square

Using Lemma 19 we can show that maximally monotone subspaces satisfy the following composition property, which was derived recently (under some regularity assumptions) for general *maximally monotone relations* in [10].

Proposition 20 *Consider an extended dHDAE system as in (19) and let \mathcal{M}_a and \mathcal{M}_b be maximally monotone subspaces*

$$\mathcal{M}_a \subset \mathcal{F}_a \times \mathcal{F} \times \mathcal{E}_a \times \mathcal{E}, \quad \mathcal{M}_b \subset \mathcal{F}_b \times \mathcal{F} \times \mathcal{E}_b \times \mathcal{E}$$

with $\mathcal{E} = \mathcal{F}^, \mathcal{E}_a = \mathcal{F}_a^*, \mathcal{E}_b = \mathcal{F}_b^*$. Define the composition*

$$\begin{aligned} \mathcal{M}_a \circ \mathcal{M}_b &:= \{(f_a, f_b, e_a, e_b) \mid \text{there exist } f \in \mathcal{F}, e \in \mathcal{E} \text{ such that} \\ &\quad (f_a, f, e_a, e) \in \mathcal{M}_a, (f_b, -f, e_b, e) \in \mathcal{M}_b\}. \end{aligned}$$

Then $\mathcal{M}_a \circ \mathcal{M}_b \subset \mathcal{F}_a \times \mathcal{F}_b \times \mathcal{E}_a \times \mathcal{E}_b$ is again maximally monotone.

Proof. Let $\mathcal{V}_a := \mathcal{F}$ and $\mathcal{V}_b := \mathcal{F}$. Define the linear maps

$$\begin{aligned} \phi : \mathcal{F}_a \times \mathcal{V}_a \times \mathcal{F}_b \times \mathcal{V}_b &\rightarrow \mathcal{F}_a \times \mathcal{V}_a \times \mathcal{V}_a \times \mathcal{F}_b \times \mathcal{V}_b \times \mathcal{V}_b \\ (f_a, v_a, f_b, v_b) &\mapsto (f_a, v_a, v_a, f_b, v_b, v_b) \\ \psi : \mathcal{F}_a \times \mathcal{V}_a \times \mathcal{F}_b \times \mathcal{V}_b &\rightarrow \mathcal{F}_a \times \mathcal{F}_b \\ (f_a, v_a, f_b, v_b) &\mapsto (f_a, f_b) \end{aligned}$$

Then for the maximally monotone subspace

$$\mathcal{M}_I = \{(v_a, v_b, v_a^*, v_b^*) \in \mathcal{V}_a \times \mathcal{V}_b \times \mathcal{V}_a^* \times \mathcal{V}_b^* \mid v_a = -v_b, v_a^* = v_b^*\},$$

it can be readily checked that

$$\mathcal{M}_a \circ \mathcal{M}_b = f_\psi(b_\phi(\mathcal{M}_a \times \mathcal{M}_I \times \mathcal{M}_b)),$$

where $\mathcal{M}_a \times \mathcal{M}_I \times \mathcal{M}_b$ is clearly maximally monotone. Then the proof finishes by applying Lemma 19. \square

We immediately have the following corollary.

Corollary 21 Consider a Dirac structure $\mathcal{D} \subset \mathcal{X} \times \mathcal{F}_R \times \mathcal{X}^* \times \mathcal{F}_R^*$, together with a nonnegative Lagrangian subspace $\mathcal{R} \subset \mathcal{F}_R \times \mathcal{F}_R^*$. Then the composition of \mathcal{D} and \mathcal{R} defined via

$$\mathcal{D} \circ \mathcal{R} := \{(f, e) \in \mathcal{X} \times \mathcal{X}^* \mid \text{there exists } f_R \in \mathcal{F}_R, e_R \in \mathcal{F}_R^* \text{ such that} \\ (f, -f_R, e, e_R) \in \mathcal{D}, \text{ and } (f_R, e_R) \in \mathcal{R}\}$$

is maximally monotone. In particular, for any $(f, e) \in \mathcal{D} \circ \mathcal{R}$, one has

$$e^\top f = e_R^\top f_R \geq 0.$$

Remark 22 We conjecture that conversely any maximally monotone subspace \mathcal{M} can be generated this way, i.e., as the composition of a certain Dirac structure \mathcal{D} and a certain nonnegative Lagrangian subspace \mathcal{R} .

The presented analysis of maximally monotone subspaces leads to the following geometric definition of an *extended dHDAE* system, covering both dHDAE systems (2) and extended HDAE systems (10), see also [20] for a similar construction using maximally dissipative linear relations.

Definition 23 Consider a linear state space \mathcal{X} with coordinates x , a maximally monotone subspace $\mathcal{M} \subset \mathcal{X} \times \mathcal{X}^*$, and a Lagrange structure $\mathcal{L} \subset \mathcal{X} \times \mathcal{X}^*$. Then an extended dHDAE system is a system $(\mathcal{X}, \mathcal{M}, \mathcal{L})$ satisfying

$$\{(\dot{x}, x) \mid \text{there exists } e \in \mathcal{X}^* \text{ such that } (-\dot{x}, e) \in \mathcal{M}, (x, e) \in \mathcal{L}\}. \quad (25)$$

A coordinate representation of an extended dHDAE system is obtained as follows. Consider a coordinate expression (23) of the maximally monotone subspace \mathcal{M} (with M, N satisfying (24)). This means that any element $(f, e) \in \mathcal{M}$ can be represented as

$$\begin{bmatrix} f \\ e \end{bmatrix} = \begin{bmatrix} N^\top \\ M^\top \end{bmatrix} v$$

for some $v \in \mathbb{R}^n$. Furthermore, any $(x, e) \in \mathcal{L}$ can be represented as in (20). Substituting $-f = \dot{x} = P\dot{z}$ this yields

$$\begin{bmatrix} -P\dot{z} \\ Sz \end{bmatrix} = \begin{bmatrix} N^\top \\ M^\top \end{bmatrix} v$$

Now construct matrices C, D satisfying

$$\ker \begin{bmatrix} C & D \end{bmatrix} = \text{im} \begin{bmatrix} N^\top \\ M^\top \end{bmatrix}. \quad (26)$$

Then pre-multiplication by such a maximal annihilator $\begin{bmatrix} C & D \end{bmatrix}$ eliminates the auxiliary variables v , and one obtains a coordinate representation

$$CP\dot{z} = DSz. \quad (27)$$

Remark 24 The geometric construction of extended dissipative Hamiltonian system can be immediately generalized to extended dissipative port-Hamiltonian DAE (dpHDAE) systems *with external port variables* (inputs and outputs), by extending the maximally monotone subspace $\mathcal{M} \subset \mathcal{X} \times \mathcal{X}^*$ to a maximally monotone subspace $\mathcal{M}_e \subset \mathcal{X} \times \mathcal{X}^* \times \mathcal{F}_p \times \mathcal{F}_p^*$, where $\mathcal{F}_p \times \mathcal{F}_p^*$ is the space of port variables.

Two particular cases of Definition 23 are of special interest. The first one is where the maximally monotone subspace \mathcal{M} is actually a Dirac structure as in (6) with K, L satisfying (14). In this case $\begin{bmatrix} C & D \end{bmatrix} = \begin{bmatrix} K & L \end{bmatrix}$, and thus the extended dHDAE system reduces to the extended HDAE system

$$KP\dot{z} = LSz. \quad (28)$$

The other special case is where the maximally monotone subspace \mathcal{M} in (23) is such that M is invertible. In this case, without loss of generality M^\top can be taken to be the identity matrix, and the maximal annihilator $\begin{bmatrix} C & D \end{bmatrix}$ can be taken to be of the form $\begin{bmatrix} I & D \end{bmatrix}$. Hence $D = -N^\top$, and thus (27) reduces to

$$P\dot{z} = -N^\top Sz.$$

Furthermore, $MN^\top + NM^\top \geq 0$ reduces to $N^\top + N \geq 0$, and hence

$$N^\top = -\frac{1}{2}(N - N^\top) + \frac{1}{2}(N + N^\top) =: -J + R$$

with $J = -J^\top$ and $R = R^\top \geq 0$. Thus in this case the extended dpHDAE system takes the familiar form (2) with $E = P$, $S = Q$ expressed as

$$E\dot{z} = (J - R)Qz, \quad Q^\top E = E^\top Q, J = -J^\top, R = R^\top \geq 0.$$

Remark 25 Similar to the theory exposed in [38] for HDAE systems (10), the *algebraic constraints* of the dpHDAE system (27) can be split into two classes: one corresponding to singularity of P (Lagrange algebraic constraints in [38]), and one corresponding to singularity of C . In case of (10) the second class of algebraic constraints are called Dirac algebraic constraints in [38], but now they correspond to the maximally monotone subspace.

Furthermore, mimicking the developments in [38], one can transform algebraic constraints associated with index one belonging to one class into algebraic constraints in the other, by the use of additional state variables (serving as Lagrange multipliers).

3 Representation of DAE systems generated by Dirac and Lagrange structures in the state variables x

The representation (10) of an extended HDAE system as discussed in the previous sections does not use the state variables x of the state space \mathcal{X} , but instead an equally dimensioned vector $z \in \mathcal{Z}$ parameterizing the Lagrange structure, cf. (9) and (15). In this section we show how a *different* DAE representation involving the original state vector $x \in \mathcal{X}$ can be obtained. Furthermore we discuss in what sense the representation in x is equivalent with the representation (10) involving z .

3.1 A coordinate representation in the original state variables x

Consider a Dirac structure $\mathcal{D} \subset \mathcal{X} \times \mathcal{X}^*$, a Lagrange structure $\mathcal{L} \subset \mathcal{X} \times \mathcal{X}^*$, and the resulting dynamics (in coordinate-free form) specified as $\mathcal{D} \circ \mathcal{L} \subset \mathcal{X} \times \mathcal{X}$. Let x be coordinates for the state space \mathcal{X} and let the Dirac structure represented by a pair of matrices K, L and

the Lagrange structure by a pair of matrices P, S . To derive a coordinate representation employing directly the state vector x , we first consider the combined representations of \mathcal{D} and \mathcal{L} , both in kernel representation, i.e.,

$$\begin{bmatrix} K & L & 0 \\ 0 & -P^\top & S^\top \end{bmatrix} \begin{bmatrix} -\dot{x} \\ e \\ x \end{bmatrix} = 0, \quad (29)$$

where e are dual coordinates for \mathcal{X}^* . In order to obtain a DAE system only involving x we need to eliminate the variables e . This can be done by considering a *maximal annihilator* (left null-space) $[M \ N]$ of $\begin{bmatrix} L \\ -P^\top \end{bmatrix}$, i.e.,

$$\ker [M \ N] = \text{im} \begin{bmatrix} L \\ -P^\top \end{bmatrix}, \quad (30)$$

and thus, in particular,

$$ML = NP^\top. \quad (31)$$

Since

$$[M \ N] \begin{bmatrix} K & L & 0 \\ 0 & -P^\top & S^\top \end{bmatrix} = [MK \ 0 \ NS^\top],$$

premultiplication of the equations (29) by $[M \ N]$ thus yields

$$\mathcal{D} \circ \mathcal{L} = \ker [MK \ NS^\top] \subset \mathcal{X} \times \mathcal{X}.$$

Hence the resulting DAE system is given by

$$MK\dot{x} = NS^\top x, \quad (32)$$

where M, N satisfy (30).

Remark 26 Also for extended dHDAE systems (including *dissipation*) we can consider, instead of the coordinate representation (27) involving the parametrizing vector z , a representation that is using the original state x . In fact, let as before, cf. (26), $[C \ D]$ denote a maximal annihilator of $[N \ M]^\top$, i.e., $\ker [C \ D] = \text{im} [N \ M]^\top$. Then consider, similarly to (29), the stacked matrix

$$\begin{bmatrix} C & D & 0 \\ 0 & -P^\top & S^\top \end{bmatrix}$$

and a maximal annihilator $[V \ W]$ to $[D^\top \ -P]^\top$, that is $\ker [V \ W] = \text{im} [D^\top \ -P]^\top$. Then premultiplication by $[V \ W]$ yields the representation

$$VC\dot{x} = WS^\top x$$

The analysis performed in the current subsection for (32) can be performed, *mutatis mutandis*, for (26) as well.

Example 27 Consider Example 13 and compute a maximal rank solution M, N to

$$0 = [M \quad N] \begin{bmatrix} 0 & 0 & 1 & 0 \\ 0 & 0 & 0 & 1 \\ -1 & 0 & 0 & 0 \\ 0 & 0 & 0 & 1 \\ \hline 0 & 0 & 0 & 0 \\ -1 & -1 & 0 & 0 \\ 0 & 0 & -1 & 1 \\ 0 & 0 & -\frac{1}{2} & -\frac{1}{2} \end{bmatrix}.$$

This yields

$$[M \quad N] = \left[\begin{array}{cccc|cccc} 2 & 0 & 0 & 0 & 0 & 0 & 1 & 2 \\ 0 & 2 & 0 & 0 & 0 & 0 & -1 & 2 \\ 0 & 0 & 0 & 0 & 1 & 0 & 0 & 0 \\ 0 & -1 & 0 & 1 & 0 & 0 & 0 & 0 \end{array} \right],$$

and a resulting DAE system is given by

$$\begin{bmatrix} 2 & 0 & 0 & 0 \\ 0 & 2 & 0 & 0 \\ 0 & 0 & 0 & 0 \\ 0 & -1 & 0 & 0 \end{bmatrix} \begin{bmatrix} \dot{x}_1 \\ \dot{x}_2 \\ \dot{x}_3 \\ \dot{x}_4 \end{bmatrix} = \begin{bmatrix} 0 & 0 & 2 & 0 \\ 0 & 0 & 0 & 2 \\ 1 & -1 & 0 & 0 \\ 0 & 0 & 0 & 0 \end{bmatrix} \begin{bmatrix} x_1 \\ x_2 \\ x_3 \\ x_4 \end{bmatrix},$$

so that

$$\begin{aligned} \dot{x}_1 &= x_3, \\ \dot{x}_2 &= x_4, \\ 0 &= x_1 - x_3, \\ \dot{x}_2 &= 0. \end{aligned}$$

Recall that in the coordinate representation (10) we have the expression $\mathcal{H}^z(z) = \frac{1}{2}z^\top S^\top Pz$ for the Hamiltonian. In the representation (32) we do not yet have a Hamiltonian associated with the extended HDAE system. To define such a Hamiltonian \mathcal{H}^x in (32) we would need that P is invertible, in which case it is given by

$$\mathcal{H}^x(x) = \frac{1}{2}x^\top SP^{-1}x. \quad (33)$$

If P is invertible then there is a direct relation between the Hamiltonians (11) and (33). In fact, substituting $x = Pz$, we immediately obtain

$$\mathcal{H}^x(x) = \frac{1}{2}x^\top SP^{-1}x = \frac{1}{2}z^\top P^\top SP^{-1}Pz = \frac{1}{2}z^\top P^\top Sz = \mathcal{H}^z(z).$$

Alternatively, if S is invertible then one can use the *co-energy* (Legendre transform) of H^x given by

$$\mathcal{H}^e(e) = \frac{1}{2}e^\top PS^{-1}e \quad (34)$$

for which $\mathcal{H}^e(e) = \mathcal{H}^z(z)$ with $e = Sz$.

Note that if P is invertible, then also M is invertible. This follows, since then $ML = NP^\top$ implies that the columns of N are in $\text{im } M$, and since $\text{rank} [M \quad N] = n$ this means M is invertible. The converse that M invertible implies P invertible follows analogously. In a similar fashion, it follows that L is invertible if and only if N is invertible. These observations imply the following simplifications of the representation (32) under additional assumptions.

1. a) If P is invertible then $N = MLP^{-\top}$ and by multiplying (32) from the left by M^{-1} we obtain the system

$$K\dot{x} = LP^{-\top}S^{\top}x = L(SP^{-1})^{\top}x = LSP^{-1}x, \quad (35)$$

where the last equality follows from $S^{\top}P = P^{\top}S$. This is exactly the form of a Hamiltonian DAE system in case of a general Dirac structure and a Lagrangian structure that is given as the graph of a symmetric matrix $Q := SP^{-1}$, see [35, 36, 37, 40]. Indeed, the Lagrange structure simplifies to the gradient of the Hamiltonian function $\mathcal{H}^x(x) = \frac{1}{2}x^{\top}SP^{-1}x$.

- b) If in this case additionally K is invertible, then we obtain the *Poisson formulation* of Hamiltonian systems, see e.g. [2],

$$\dot{x} = (K^{-1}L)(SP^{-1})x = JQx, \quad (36)$$

with $J = -J^{\top} = K^{-1}L$, and $Q = Q^{\top}$.

2. a) If L and thus also N is invertible, then by (31) we have $M = NP^{\top}L^{-1}$ and multiplying with N^{-1} from the left we get the DAE

$$P^{\top}J\dot{x} = P^{\top}L^{-1}K\dot{x} = S^{\top}x \quad (37)$$

with $J := (L^{-1}K)^{\top} = -L^{-1}K$.

- b) If additionally P is invertible, then with $Q = SP^{-1} = P^{-\top}S^{\top}$ this may be rewritten as

$$J\dot{x} = Qx, \quad (38)$$

which is the standard *symplectic formulation* of a Hamiltonian system in case additionally J is invertible, see e.g. [2].

3.2 Relation between the representations (10) and (32)

An immediate question that arises is how the representations (10) and (32) are related. We have already seen that if P is *invertible* then the relationship is obvious, since in this case $x = Pz$ defines an ordinary state space transformation. However, if P is not invertible then the representations are *not* state space equivalent, as the following example demonstrates.

Example 28 For $P = [0]$, $S = [1]$, $K = [1]$, $L = [0]$, we have that (10) is the singular system $0 \cdot \dot{z} = 0 \cdot z$. On the other hand

$$\text{rank} \begin{bmatrix} L \\ -P^{\top} \end{bmatrix} = 0,$$

and $\mathcal{D} \circ \mathcal{L}$ is the origin in $\mathcal{X} \times \mathcal{X}$, defining the degenerate DAE system $\dot{x} = x = 0$.

However, representations (10) (in the parameterizing z variables) and (32) (in the original state variables x) can be shown to be equivalent in the following *generalized sense*.

First note that for any representation P, S of a Lagrange structure there exist nonsingular matrices V, W such that

$$\begin{aligned} V^{-1}PW &= V^{\top}PW = \begin{bmatrix} I_{n_1} & 0 \\ 0 & 0 \end{bmatrix}, \quad V^{\top}SW = \begin{bmatrix} S_{11} & 0 \\ 0 & I_{n_2} \end{bmatrix}, \\ KV &= \begin{bmatrix} K_{11} & K_{12} \\ K_{21} & K_{22} \end{bmatrix}, \quad LV^{-\top} = LV = \begin{bmatrix} L_{11} & L_{12} \\ L_{21} & L_{22} \end{bmatrix}. \end{aligned} \quad (39)$$

This is a direct consequence of Lemma 34 that will be presented in the next section. Setting $\begin{bmatrix} z_1 \\ z_2 \end{bmatrix} = W^{-1}z$ and $\begin{bmatrix} x_1 \\ x_2 \end{bmatrix} = V^{-1}x$, it follows that $z_1 = x_1$ and $z_2 = e_2$. After such a transformation the system $KP\dot{z} = LSz$ takes the form

$$\begin{bmatrix} K_{11} & K_{12} \\ K_{21} & K_{22} \end{bmatrix} \begin{bmatrix} I & 0 \\ 0 & 0 \end{bmatrix} \begin{bmatrix} \dot{x}_1 \\ \dot{e}_2 \end{bmatrix} = \begin{bmatrix} L_{11} & L_{12} \\ L_{21} & L_{22} \end{bmatrix} \begin{bmatrix} S_{11} & 0 \\ 0 & I \end{bmatrix} \begin{bmatrix} x_1 \\ e_2 \end{bmatrix}. \quad (40)$$

If we *add* to these equations the subvector x_2 , together with the original Lagrange algebraic constraint $x_2 = 0$, then the so extended system can be written as

$$\begin{bmatrix} K_{11} & K_{12} \\ K_{21} & K_{22} \\ 0 & 0 \end{bmatrix} \begin{bmatrix} I & 0 \\ 0 & 0 \end{bmatrix} \begin{bmatrix} \dot{x}_1 \\ \dot{x}_2 \end{bmatrix} = \begin{bmatrix} L_{11}S_{11}x_1 \\ L_{21}S_{11}x_1 \\ x_2 \end{bmatrix} + \begin{bmatrix} L_{12} \\ L_{22} \\ 0 \end{bmatrix} e_2. \quad (41)$$

On the other hand, as shown in Subsection 3.1, the extended dHDAE system defined by the Dirac structure \mathcal{D} and the Lagrangian structure \mathcal{L} in the state space variables x can be expressed as

$$\begin{bmatrix} K_{11} & K_{12} & L_{11} & L_{12} & 0 & 0 \\ K_{21} & K_{22} & L_{21} & L_{22} & 0 & 0 \\ 0 & 0 & -I & 0 & S_{11} & 0 \\ 0 & 0 & 0 & 0 & 0 & I \end{bmatrix} \begin{bmatrix} -\dot{x}_1 \\ -\dot{x}_2 \\ e_1 \\ e_2 \\ x_1 \\ x_2 \end{bmatrix} = 0, \quad (42)$$

with e_1, e_2 serving as *auxiliary variables*. Instead of eliminating e_1, e_2 from these equations, as discussed in Subsection 4.1, we can only eliminate e_1 by premultiplication of (42) by the full row rank matrix

$$[M \quad N] = \begin{bmatrix} I & 0 & L_{11} & 0 \\ 0 & I & L_{21} & 0 \\ 0 & 0 & 0 & I \end{bmatrix},$$

which directly leads to the system (41). This extended equivalence between (10) and (32) is summarized in the following proposition.

Proposition 29 *Consider the pHDAE representations (10) and (32) defined by the same Lagrange structure \mathcal{L} represented by matrices P, S , and by the same Dirac structure \mathcal{D} represented by K, L . Consider a transformation such that P, S and K, L are transformed into the form (39) with corresponding partitioning*

$$x = \begin{bmatrix} x_1 \\ x_2 \end{bmatrix}, \quad z = \begin{bmatrix} z_1 \\ z_2 \end{bmatrix},$$

where $x_1 = z_1$. Adding to (10) the Lagrange algebraic constraint $x_2 = 0$ corresponding to $x = Pz$, the resulting dHDAE system is given by (41). This system is equivalent to the representation (29) of (32) after elimination of the variables e_1 .

Note that the subvector $e_2 = z_2$ can be regarded as the *Lagrange multiplier vector* corresponding to the constraint $x_2 = 0$. As such, $e_2 = z_2$ does not contribute to the expression of the Hamiltonian $\mathcal{H}^z(z)$.

Let us illustrate the previous discussion with some further examples.

Example 30 Consider a system in the form (10) with $K = \begin{bmatrix} I & 0 \\ 0 & I \end{bmatrix}$, $L = \begin{bmatrix} 0 & I \\ -I & 0 \end{bmatrix}$,
 $P = \begin{bmatrix} I & 0 \\ 0 & 0 \end{bmatrix}$, $S = \begin{bmatrix} I & 0 \\ 0 & I \end{bmatrix}$ which is the general DAE

$$\begin{bmatrix} I & 0 \\ 0 & 0 \end{bmatrix} \begin{bmatrix} \dot{z}_1 \\ \dot{z}_2 \end{bmatrix} = \begin{bmatrix} 0 & I \\ -I & 0 \end{bmatrix} \begin{bmatrix} z_1 \\ z_2 \end{bmatrix}$$

In order to compute the representation (32), we solve

$$0 = [M \quad N] \begin{bmatrix} 0 & I \\ -I & 0 \\ -I & 0 \\ 0 & 0 \end{bmatrix},$$

and with

$$[M \quad N] = \begin{bmatrix} 0 & 0 & 0 & I \\ 0 & I & -I & 0 \end{bmatrix}$$

we get the system

$$\begin{bmatrix} 0 & 0 \\ 0 & I \end{bmatrix} \begin{bmatrix} \dot{x}_1 \\ \dot{x}_2 \end{bmatrix} = \begin{bmatrix} 0 & I \\ -I & 0 \end{bmatrix} \begin{bmatrix} x_1 \\ x_2 \end{bmatrix}.$$

Example 31 Consider the system of the form (10) with $K = 0$, $L = I$, $P = I$, $S = I$, i.e., $0 \cdot \dot{z} = z$. Solving

$$0 = [M \quad N] \begin{bmatrix} I \\ -I \end{bmatrix},$$

yields $M = I$, $N = I$, and we obtain the system (32) given by $0 \cdot \dot{x} = x$.

Example 32 Consider the system of the form (10) with $K = 0$, $L = I$, $P = 0$, $S = I$, i.e. $0 \cdot \dot{z} = z$. Solving

$$0 = [M \quad N] \begin{bmatrix} I \\ 0 \end{bmatrix}$$

yields $M = 0$, $N = I$, and thus the representation (32) is $0 \cdot \dot{x} = x$.

Example 33 Consider the system of the form (10) with $K = 0$, $L = \begin{bmatrix} 0 & I \\ -I & 0 \end{bmatrix}$, $P = I$, $S = I$,

i.e., $0 \cdot \dot{z} = \begin{bmatrix} 0 & I \\ -I & 0 \end{bmatrix} z$. Solving

$$0 = [M \quad N] \begin{bmatrix} 0 & I \\ -I & 0 \\ -I & 0 \\ 0 & -I \end{bmatrix}$$

yields $M = I$, $N = \begin{bmatrix} 0 & I \\ -I & 0 \end{bmatrix}$, and thus the representation (32) is given by

$$0 \cdot \dot{x} = \begin{bmatrix} 0 & I \\ -I & 0 \end{bmatrix} x.$$

4 Equivalence transformations and condensed forms

To characterize the properties of extended dHDAEs we use transformations to condensed forms from which the properties can be read off.

For general DAEs (1) given by matrix pairs (E, A) (or the representation via matrix pencils $\lambda E - A$) we can perform equivalence transformations of the coefficients of the form

$$(\tilde{E}, \tilde{A}) = (U^\top E W, U^\top A W), \quad (43)$$

with $U \in \mathbb{R}^{\ell, \ell}$, $W \in \mathbb{R}^{n, n}$ nonsingular. This corresponds to a scaling of the equation with U^\top and a change of variables $z = W\tilde{z}$. Under such transformations there is a one-to-one relationship between the solution spaces, see [23] and the canonical form is the Kronecker canonical form presented in Appendix A.

For structured systems of the form (2), the associated equivalence transformation that preserves the structure is of the form

$$(\tilde{E}, (\tilde{J} - \tilde{R})\tilde{Q}) = (U^\top E W, (U^\top (J - R) U) U^{-1} Q W),$$

with $U \in \mathbb{R}^{\ell, \ell}$, $W \in \mathbb{R}^{n, n}$ nonsingular. A condensed form for this case has been presented in [27].

Finally for systems of the form (10), the equivalence transformations have the form

$$\tilde{K} = U^\top K V, \quad \tilde{L} = U^\top L V^{-T}, \quad \tilde{P} = V^{-1} P W, \quad \tilde{S} = V^\top S W, \quad (44)$$

where $U \in \mathbb{R}^{\ell, \ell}$, $V \in \mathbb{R}^{n, n}$, $W \in \mathbb{R}^{m, m}$ are nonsingular.

The geometric interpretation of the set of transformations in (44) is clear: V defines a coordinate transformation on the state space \mathcal{X} while $V^{-\top}$ is the corresponding dual transformation on the dual state space \mathcal{X}^* . Also note that the combination of V and $V^{-\top}$ on the product space $\mathcal{X} \times \mathcal{X}^*$ leaves the canonical bilinear forms defined by the matrices Π_- and Π_+ invariant. (In fact, it can be shown that any transformation on $\mathcal{X} \times \mathcal{X}^*$ that leaves both canonical bilinear forms invariant is necessarily of this form for some invertible V .) Finally, U^\top is an invertible transformation on the equation space for the kernel representation of the Dirac structure \mathcal{D} , while W is an invertible transformation on the parametrization space \mathcal{Z} for the Lagrange structure \mathcal{L} .

In all three cases, in view of an implementation of the transformations as numerically stable procedures, we are also interested in the case that U, V, W are real orthogonal matrices. We then have that $V^{-1} = V^\top$ and for both pairs (K, L) and (P, S) this is a classical orthogonal equivalence transformation.

Using the described equivalence transformations we can derive condensed forms for pencils $\lambda P - S$ with $P^\top S = S^\top P$ associated with Lagrange subspaces (or *isotropic subspaces* if the dimension is not n , see e.g. [27]). Here we slightly modify the representation and also give a constructive proof that can be implemented as numerically stable algorithm in Appendix B.

Lemma 34 *Let $P, S \in \mathbb{R}^{n, m}$ be such that $P^\top S = S^\top P$. Then there exist invertible matrices $V \in \mathbb{R}^{n, n}$, $W \in \mathbb{R}^{m, m}$ such that*

$$V^{-1} P W = \begin{bmatrix} I_{m_1} & 0 & 0 & 0 & 0 \\ 0 & I_{m_2} & 0 & 0 & 0 \\ 0 & 0 & I_{m_3} & 0 & 0 \\ 0 & 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 & 0 \end{bmatrix}, \quad V^\top S W = \begin{bmatrix} I_{m_1} & 0 & 0 & 0 & 0 \\ 0 & -I_{m_2} & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & I_{m_4} & 0 \\ S_{51} & S_{5,2} & S_{5,3} & 0 & 0 \\ 0 & 0 & 0 & 0 & 0 \end{bmatrix}, \quad (45)$$

with $\begin{bmatrix} S_{5,1} & S_{5,2} & S_{5,3} \end{bmatrix}$ of full row rank n_5 . (Note that block sizes may be zero). Moreover, if the pencil $\lambda P - S$ is regular then the condensed form is unique, except for the order of blocks, and just contains the first four block rows and columns.

Proof. See Appendix B. \square

Note that the condensed form is in general not unique in the fifth block row, but the block sizes m_1, m_2, m_3, m_4 and the row dimension n_5 are.

Corollary 35 *Let $P, S \in \mathbb{R}^{n,m}$ be such that $P^\top S = S^\top P$. Then there exist real orthogonal matrices $V \in \mathbb{R}^{n,n}$, $W \in \mathbb{R}^{m,m}$ such that*

$$V^\top P W = \begin{bmatrix} P_{11} & 0 & 0 & 0 \\ P_{21} & P_{22} & 0 & 0 \\ 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 \end{bmatrix}, V^\top S W = \begin{bmatrix} S_{11} & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 \\ S_{31} & S_{32} & S_{33} & 0 \\ S_{41} & S_{42} & 0 & 0 \\ 0 & 0 & 0 & 0 \end{bmatrix}, \quad (46)$$

with $P_{11}, S_{11} \in \mathbb{R}^{m_1+m_2, m_1+m_2}$, $P_{22} \in \mathbb{R}^{m_3, m_3}$, $S_{33} \in \mathbb{R}^{m_4, m_4}$ invertible, $\begin{bmatrix} S_{41} & S_{42} \end{bmatrix}$ of full row rank n_5 , and $P_{11}^\top S_{11} = S_{11}^\top P_{11}$. Here the block sizes $m_1 + m_2$, m_3 , m_4 , and m_5 are as in (45).

Proof. The proof follows by performing Steps 1. and 2. of the proof of Lemma 34, see Appendix B, which yields

$$V_2^\top V_1^\top P W_1 W_2 = \begin{bmatrix} \hat{P}_{11} & 0 & 0 \\ 0 & 0 & 0 \\ 0 & 0 & 0 \end{bmatrix}, V_2^\top V_1^\top S W_1 W_2 = \begin{bmatrix} \hat{S}_{11} & 0 & 0 \\ \hat{S}_{21} & \hat{S}_{22} & 0 \\ \hat{S}_{31} & 0 & 0 \end{bmatrix},$$

followed by a singular value decomposition $\hat{V}_3^\top \hat{S}_{11} \hat{W}_3 = \begin{bmatrix} \check{S}_{11} & 0 \\ 0 & 0 \end{bmatrix}$ with \check{S}_{11} nonsingular diagonal and a full rank decomposition $\check{V}_4^\top \hat{S}_{31} \hat{W}_3 = \begin{bmatrix} S_{41} & S_{42} \end{bmatrix}$. \square

Corollary 35 shows that the characteristic quantities $m_1 + m_2$, m_3 and m_4 , as well as n_5 can be obtained by purely real orthogonal transformations. The quantities m_1, m_2 can then be determined from the real orthogonal staircase form of the symmetric pencil $\lambda P_{11}^\top S_{11} - S_{11}^\top P_{11}$ which has been presented in [8] and implemented as production software in [7].

There is an analogous condensed form for pencils of the form $\lambda K - L$ satisfying $KL^\top = -LK^\top$. For the case of regular pairs this directly follows from the canonical form presented in [11], but again we present the construction so that it can be directly implemented as a numerical method, see Appendix C.

Lemma 36 *Let $K, L \in \mathbb{R}^{\ell, n}$ be such that $KL^\top = -LK^\top$. Then there exist invertible matrices $U \in \mathbb{R}^{\ell, \ell}$, $V \in \mathbb{R}^{n, n}$ such that*

$$U^\top K V = \begin{bmatrix} I_{\ell_1} & 0 & 0 & 0 & 0 & 0 \\ 0 & I_{\ell_1} & 0 & 0 & 0 & 0 \\ 0 & 0 & I_{\ell_3} & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 & 0 & 0 \end{bmatrix}, U^\top L V^{-\top} = \begin{bmatrix} 0 & I_{\ell_1} & 0 & 0 & L_{15} & 0 \\ -I_{\ell_1} & 0 & 0 & 0 & L_{25} & 0 \\ 0 & 0 & 0 & 0 & L_{35} & 0 \\ 0 & 0 & 0 & I_{\ell_4} & 0 & 0 \\ 0 & 0 & 0 & 0 & 0 & 0 \end{bmatrix}, \quad (47)$$

with $\begin{bmatrix} L_{15} \\ L_{2,5} \\ L_{3,5} \end{bmatrix}$ of full column rank n_5 . (Note that block sizes may be zero). Moreover, if the pencil $\lambda K - L$ is regular then the condensed form is unique except for the order of blocks and just contains the first four block rows and columns.

Proof. See Appendix C. \square

Note again that the form (47) is not unique in general but the block sizes $\ell_1, \ell_2, \ell_3, \ell_4$ and the column dimension n_5 are.

Corollary 37 Let $K, L \in \mathbb{R}^{\ell, n}$ be such that $LK^\top = -KL^\top$. Then there exist real orthogonal matrices $U \in \mathbb{R}^{\ell, \ell}$, $V \in \mathbb{R}^{n, n}$ such that

$$U^\top KV = \begin{bmatrix} K_{11} & K_{12} & 0 & 0 & 0 \\ 0 & K_{22} & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 & 0 \end{bmatrix}, U^\top LV = \begin{bmatrix} L_{11} & 0 & L_{13} & L_{14} & 0 \\ 0 & 0 & L_{23} & L_{24} & 0 \\ 0 & 0 & L_{33} & 0 & 0 \\ 0 & 0 & 0 & 0 & 0 \end{bmatrix}. \quad (48)$$

with $K_{11}, L_{11} \in \mathbb{R}^{2\ell_1, 2\ell_1}$, $K_{22} \in \mathbb{R}^{\ell_3, \ell_3}$, $L_{33} \in \mathbb{R}^{\ell_4, \ell_4}$ invertible, $\begin{bmatrix} L_{14} \\ L_{2,4} \end{bmatrix}$ is of full column rank n_5 , and $K_{11}^\top L_{11} = -L_{11}^\top K_{11}$. Here the block-sizes ℓ_1, ℓ_3, ℓ_4 , and n_5 are as in (47).

Proof. The proof follows by performing Steps 1. and 2. of the proof of Lemma 36, which yields

$$U_2^\top U_1^\top KV_1V_2 = \begin{bmatrix} \hat{K}_{11} & 0 & 0 \\ 0 & 0 & 0 \\ 0 & 0 & 0 \end{bmatrix}, U_2^\top U_1^\top LV_1V_2 = \begin{bmatrix} \hat{L}_{11} & \hat{L}_{12} & \hat{L}_{13} \\ 0 & \hat{L}_{22} & 0 \\ 0 & 0 & 0 \end{bmatrix},$$

followed by a singular value decomposition $\hat{U}_3^\top \hat{L}_{11} \hat{V}_4 = \begin{bmatrix} \check{L}_{11} & 0 \\ 0 & 0 \end{bmatrix}$ with \check{L}_{11} nonsingular diagonal and a full rank decomposition $\hat{U}_3^\top \hat{L}_{13} \hat{V}_3 = \begin{bmatrix} L_{14} \\ L_{2,4} \end{bmatrix}$. \square

Corollary 37 shows that the characteristic quantities ℓ_1, ℓ_3, ℓ_4 , as well as n_5 can be obtained by purely real orthogonal transformations.

The presented condensed forms can now be used in generating a condensed form for systems of the form (10).

Lemma 38 Consider a system of the form (10) with $K, P, L, S \in \mathbb{R}^{n, n}$ and regular pencil $\lambda KP - LS$. Then there exists invertible matrices U, V, W as in (44) such that

$$\begin{aligned} \hat{K} &= U^\top KV = \begin{bmatrix} K_{11} & K_{12} \\ K_{21} & K_{22} \end{bmatrix}, \hat{L} = U^\top LV^{-\top} = \begin{bmatrix} L_{11} & 0 \\ 0 & I_{n_2} \end{bmatrix}, \\ \hat{P} &= V^{-1}PW = \begin{bmatrix} I_{n_1} & 0 \\ 0 & 0 \end{bmatrix}, \hat{S} = V^\top SW = \begin{bmatrix} S_{11} & 0 \\ 0 & I_{n_2} \end{bmatrix}, \end{aligned} \quad (49)$$

where $S_{11} = S_{11}^\top$ and $K_{11}L_{11}^\top = -L_{11}K_{11}^\top$.

Proof. Since the pencil $\lambda KP - LS$ is square and regular, it is square, and also the pencil $\lambda P - S$ is regular, otherwise by Lemma 34 there would be common kernel of P and S which would imply the pencil $\lambda KP - LS$ to be singular.

Thus, by Lemma 34 there exist nonsingular matrices $W_1, V_1 \in \mathbb{R}^{n,n}$ such that

$$\begin{aligned}\tilde{K} &= KV_1 = \begin{bmatrix} \tilde{K}_{11} & \tilde{K}_{12} \\ \tilde{K}_{21} & \tilde{K}_{22} \end{bmatrix}, \quad \tilde{L} = LV_1^{-\top} = \begin{bmatrix} \tilde{L}_{11} & \tilde{L}_{12} \\ \tilde{L}_{21} & \tilde{L}_{22} \end{bmatrix}, \\ \tilde{P} &= V_1^{-1}PW_1 = \begin{bmatrix} I_{n_1} & 0 \\ 0 & 0 \end{bmatrix}, \quad \tilde{S} = V_1^\top SW_1 = \begin{bmatrix} \tilde{S}_{11} & 0 \\ 0 & I_{n_2} \end{bmatrix},\end{aligned}$$

with $n_1 = m_1 + m_2 + m_3$, $n_2 = m_4$ and \tilde{S}_{11} symmetric. The regularity of the pencil $\lambda KP - LS$ implies that

$$\begin{bmatrix} \tilde{L}_{12} \\ \tilde{L}_{22} \end{bmatrix}$$

has full column rank and hence there exist invertible matrices $U_2 \in \mathbb{R}^{n,n}$, $\tilde{V}_2 \in \mathbb{R}^{n_2, n_2}$, and

$$V_2 = \begin{bmatrix} I_{n_1} & 0 \\ 0 & \tilde{V}_2 \end{bmatrix}$$

such that

$$U_2^\top \tilde{L} V_2 = \begin{bmatrix} \hat{L}_{11} & 0 \\ \hat{L}_{21} & I_{n_2} \end{bmatrix}.$$

With

$$V_3 = \begin{bmatrix} I_{n_1} & \hat{L}_{21}^\top \\ 0 & I_{n_2} \end{bmatrix},$$

we then get that

$$\begin{aligned}\hat{K} &= U_2^\top KV_1 V_2 V_3 = \begin{bmatrix} K_{11} & K_{12} \\ K_{21} & K_{22} \end{bmatrix}, \quad \hat{L} = U_2^\top LV_1^{-\top} V_2^{-\top} V_3^{-\top} = \begin{bmatrix} L_{11} & 0 \\ 0 & I_{n_2} \end{bmatrix}, \\ \hat{P} &= V_3^{-1} V_2^{-1} V_1^{-1} P W_1 = \begin{bmatrix} I_{n_1} & 0 \\ 0 & I_{n_2} \end{bmatrix}, \quad \hat{S} = V_3^\top V_2^\top V_1^\top S W_1 = \begin{bmatrix} S_{11} & 0 \\ 0 & I_{n_2} \end{bmatrix},\end{aligned}$$

has the desired form with $U = U_2$, $V = V_1 V_2 V_3$, $W = W_1$, and where $S_{11} = S_{11}^\top$ and $K_{11} L_{11}^\top = -L_{11} K_{11}^\top$. \square

Transforming the system as in (49) and setting

$$z = W \begin{bmatrix} z_1 \\ z_2 \end{bmatrix},$$

partitioned accordingly, from the first block row of the coefficient matrices we obtain a reduced system given by

$$\bar{K} \bar{P} \dot{z}_1 = \bar{L} \bar{S} z_1, \tag{50}$$

with $\bar{P} = I_{n_1}$, $\bar{S} = \bar{S}^\top = S_{11}$, $\bar{K} = K_{11}$ and $\bar{L} = L_{11}$, together with an equation $z_2 = K_{21} \dot{z}_1$, where z_2 does not contribute to the Hamiltonian $\mathcal{H}^z(z) = \frac{1}{2} z^\top P^\top S z$. Note that the second equation is an index two constraint, because it uses the derivative of z_1 , [23]. It arises from the Lagrange structure due to the singularity of P .

An analogous representation can be constructed from the condensed form of Lemma 36.

Lemma 39 Consider a system of the form (10) with $K, P, L, S \in \mathbb{R}^{n,n}$ and regular pencil $\lambda KP - LS$. Then there exist invertible matrices U, V, W as in (44) such that

$$\begin{aligned}\hat{K} &= U^\top KV = \begin{bmatrix} I_{n_1} & 0 \\ 0 & 0 \end{bmatrix}, \quad \hat{L} = U^\top LV^{-\top} = \begin{bmatrix} L_{11} & 0 \\ 0 & I_{n_2} \end{bmatrix}, \\ \hat{P} &= V^{-1}PW = \begin{bmatrix} P_{11} & P_{12} \\ P_{21} & P_{22} \end{bmatrix}, \quad \hat{S} = V^\top SW = \begin{bmatrix} S_{11} & 0 \\ 0 & I_{n_2} \end{bmatrix},\end{aligned}\quad (51)$$

where $L_{11} = -L_{11}^\top$ and $P_{11}^\top S_{11} = S_{11}^\top P_{11}$.

Proof. Since the pencil $\lambda KP - LS$ is square and regular, also the pencil $\lambda K - L$ is regular, otherwise by Lemma 36 there would be a common left nullspace of K and L which would imply the pencil $\lambda KP - LS$ to be singular.

Thus by Lemma 36, there exist nonsingular matrices $U_1, V_1 \in \mathbb{R}^{n,n}$ such that

$$\begin{aligned}\tilde{K} &= U_1KV_1 = \begin{bmatrix} I_{n_1} & 0 \\ 0 & 0 \end{bmatrix}, \quad \tilde{L} = U_1LV_1^{-\top} = \begin{bmatrix} \tilde{L}_{11} & 0 \\ 0 & I_{n_2} \end{bmatrix}, \\ \tilde{P} &= V_1^{-1}P = \begin{bmatrix} \tilde{P}_{11} & \tilde{P}_{12} \\ \tilde{P}_{21} & \tilde{P}_{22} \end{bmatrix}, \quad \tilde{S} = V_1^\top S = \begin{bmatrix} \tilde{S}_{11} & \tilde{S}_{12} \\ \tilde{S}_{21} & \tilde{S}_{22} \end{bmatrix},\end{aligned}$$

with $n_1 = 2\ell_1 + \ell_3$, $n_2 = \ell_4$ and \tilde{L}_{11} skew-symmetric. The regularity of the pencil $\lambda KP - LS$ implies that

$$\begin{bmatrix} \tilde{S}_{21} & \tilde{S}_{22} \end{bmatrix}$$

has full row rank and hence there exist invertible matrices $W_2 \in \mathbb{R}^{n,n}$, $\tilde{V}_2 \in \mathbb{R}^{n_2, n_2}$, and

$$V_2 = \begin{bmatrix} I_{n_1} & 0 \\ 0 & \tilde{V}_2 \end{bmatrix}$$

such that

$$V_2^\top \tilde{S} W_2 = \begin{bmatrix} \hat{S}_{11} & \hat{S}_{12} \\ 0 & I_{n_2} \end{bmatrix}.$$

With

$$V_3 = \begin{bmatrix} I_{n_1} & -\hat{S}_{12} \\ 0 & I_{n_2} \end{bmatrix},$$

we then get that

$$\begin{aligned}\hat{K} &= U_1^\top KV_1V_2V_3 = \begin{bmatrix} I_{n_1} & 0 \\ 0 & 0 \end{bmatrix}, \quad \hat{L} = U_1^\top LV_1^{-\top}V_2^{-\top}V_3^{-\top} = \begin{bmatrix} L_{11} & 0 \\ 0 & I_{n_2} \end{bmatrix}, \\ \hat{P} &= V_3^{-1}V_2^{-1}V_1^{-1}PW_2 = \begin{bmatrix} P_{11} & P_{12} \\ P_{21} & P_{22} \end{bmatrix}, \quad \hat{S} = V_3^\top V_2^\top V_1^\top SW_2 = \begin{bmatrix} S_{11} & 0 \\ 0 & I_{n_2} \end{bmatrix},\end{aligned}$$

has the desired form with $W = W_2$, $V = V_1V_2V_3$, $U = U_1$, and where $L_{11} = -L_{11}^\top$ and $P_{11}^\top S_{11} = S_{11}^\top P_{11}$. \square

Transforming $KPz = LSz$ as in (51) and setting

$$z = W \begin{bmatrix} z_1 \\ z_2 \end{bmatrix},$$

partitioned accordingly, from the first block row of the coefficient matrices we obtain a reduced system given by

$$\bar{K}\bar{P}\dot{z}_1 = \bar{L}\bar{S}z_1, \quad (52)$$

with $\bar{P} = P_{11}$, $\bar{S} = S_{11}$, $\bar{K} = I_{n_1}$ and $\bar{L} = L_{11} = -L_{11}^\top$, together with a differential algebraic equation $0 = z_2$, so that z_2 does not contribute to the Hamiltonian.

Remark 40 System (50) is a dHDAE of the form (35) in which the Lagrange structure is spanned by the columns of

$$\begin{bmatrix} I_{n_1} \\ \bar{S}_{11} \end{bmatrix}.$$

See also [28, 30] for similar constructions in the context of removing the factor Q in systems of the form (2).

Similarly, System (52) is a phDAE of the form (2) (with $R = 0$) and the Dirac structure is spanned by the columns of

$$\begin{bmatrix} I_{n_1} \\ \bar{L}_{11} \end{bmatrix}.$$

We also perform a similar construction for systems of the form (27). Since C and D are chosen to be a maximal annihilator such that $CN^\top + DM^\top = 0$ in (26) and $MN^\top + NM^\top \geq 0$ with $\text{rank} \begin{bmatrix} N & M \end{bmatrix} = n$ we can use the same construction as in the proof of Lemma 36 to first transform N and M in such a way that

$$N = \begin{bmatrix} I_{n_1} & 0 \\ 0 & 0 \end{bmatrix}, \quad M = \begin{bmatrix} M_{11} & 0 \\ 0 & I_{n_2} \end{bmatrix}.$$

This implies that we may choose C and D such that

$$C = \begin{bmatrix} -M_{11}^\top & 0 \\ 0 & I_{n_2} \end{bmatrix}, \quad D = \begin{bmatrix} I_{n_1} & 0 \\ 0 & 0 \end{bmatrix}.$$

If $\lambda CP - DS$ is regular, then it follows that the last n_2 rows of CP have full row rank and hence altogether we have the following condensed form.

Lemma 41 *Consider a system of the form (27) with $C, P, L, S \in \mathbb{R}^{n,n}$ and regular pencil $\lambda CP - DS$ and $\begin{bmatrix} C & D \end{bmatrix}$ a maximal annihilator as in (26). Then there exist invertible matrices U, V, W as in (44) such that*

$$\begin{aligned} \hat{C} &= U^\top CV = \begin{bmatrix} C_{11} & 0 \\ 0 & I_{n_2} \end{bmatrix}, \quad \hat{D} = U^\top DV^{-\top} = \begin{bmatrix} I_{n_1} & 0 \\ 0 & 0 \end{bmatrix}, \\ \hat{P} &= V^{-1}PW = \begin{bmatrix} P_{11} & P_{12} \\ 0 & I_{n_2} \end{bmatrix}, \quad \hat{S} = V^\top SW = \begin{bmatrix} S_{11} & S_{12} \\ S_{21} & S_{22} \end{bmatrix}, \end{aligned} \quad (53)$$

where $C_{11} = -C_{11}^\top$ and $P_{11}^\top S_{11} = S_{11}^\top P_{11}$.

As a consequence, by transforming $CP\dot{z} = DSz$ as in (53) and setting

$$z = W \begin{bmatrix} z_1 \\ z_2 \end{bmatrix},$$

partitioned accordingly, from the second block row of the coefficient matrices we obtain $\dot{z}_2 = 0$, i.e. z_2 is a constant function and the first block row gives an inhomogeneous reduced system

$$\bar{C}\bar{P}\dot{z}_1 = \bar{D}\bar{S}z_1 + S_{12}z_2, \quad (54)$$

with $\bar{P} = P_{11}$, $\bar{S} = S_{11}$, $\bar{P}^\top \bar{S} = \bar{S}^\top \bar{P}$, $\bar{C} = -M_{11}^\top$ and $\bar{D} = I_{n_1}$. It will then depend on the initial condition for z_2 whether $z_2 = 0$ in which case it does not contribute to the Hamiltonian, otherwise the Hamiltonian is still a quadratic function in z_1 plus some linear and constant terms.

Remark 42 The condensed forms in this section require rank decisions. Even if they are done in a numerically stable way using singular value decompositions, they can give wrong decisions in finite precision arithmetic. It is a common strategy to use in the case of doubt the worst case scenario. In the case of condensed forms this would be to assume that the problem is a DAE of index two.

In this section we have derived structured condensed forms and shown that these can also be used to identify a subsystem which is of one of the well-established forms plus an algebraic constraint whose solution does not contribute to the Hamiltonian. In the next section we analyze, when general DAEs can be transformed to the forms (2) or (10).

5 Representation of general DAEs in the form $KP\dot{z} = LSz$ or $E\dot{z} = (J - R)Qz$

For general DAE systems of the form $E\dot{x} = Ax$ it has been characterized in [28] when they are equivalent to a dHDAE system of the form (2). We present here a simplified result for the regular case.

Theorem 43

i) A regular pencil $L(\lambda) = \lambda\hat{E} - \hat{A}$ is equivalent to a pencil of the form $\lambda E - (J - R)Q$ as in (2) with $\lambda E - Q$ being regular if and only if the following conditions are satisfied:

1. *The spectrum of $L(\lambda)$ is contained in the closed left half plane.*
2. *The finite nonzero eigenvalues on the imaginary axis are semisimple and the partial multiplicities of the eigenvalue zero are at most two.*
3. *The index of $L(\lambda)$ is at most two.*

ii) A regular pencil $L(\lambda) = \lambda\hat{E} - \hat{A}$ is equivalent to a pencil of the form $\lambda E - (J - R)$ as in (2) (i.e., with $Q = I$) if and only if the following conditions are satisfied:

1. *The spectrum of $L(\lambda)$ is contained in the closed left half plane.*
2. *The finite eigenvalues on the imaginary axis (including zero) are semisimple.*
3. *The index of $L(\lambda)$ is at most two.*

As a Corollary for the case without dissipation we have the following result.

Corollary 44 *A regular pencil $L(\lambda) = \lambda\hat{E} - \hat{A}$ is equivalent to a pencil of the form $\lambda E - J$ as in (2) (with $Q = I, R = 0$) if and only if the following conditions are satisfied:*

1. *All finite eigenvalues are on the imaginary axis and semisimple.*
2. *The index of $L(\lambda)$ is at most two.*

To study when general regular DAEs of the form (1) can be expressed as extended dHDAEs of the form (10) we first consider a condensed form under orthogonal equivalence.

Theorem 45 *Consider a regular pencil $\lambda E - A$ with $E, A \in \mathbb{R}^{n,n}$ of index at most two. Then there exist real orthogonal matrices $U \in \mathbb{R}^{n,n}$ and $V \in \mathbb{R}^{n,n}$ such that*

$$U^\top EV = \begin{bmatrix} E_{11} & E_{12} & 0 & 0 \\ E_{21} & E_{22} & 0 & 0 \\ 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 \end{bmatrix}, \quad U^\top AV = \begin{bmatrix} A_{11} & A_{12} & A_{13} & A_{14} \\ A_{21} & A_{22} & A_{23} & 0 \\ A_{31} & A_{32} & A_{33} & 0 \\ A_{41} & 0 & 0 & 0 \end{bmatrix}, \quad (55)$$

with $A_{14} \in \mathbb{R}^{n_1, n_1}$, $A_{41} \in \mathbb{R}^{n_1, n_1}$, $E_{22} \in \mathbb{R}^{n_2, n_2}$, and $A_{33} \in \mathbb{R}^{n_3, n_3}$ invertible.

Proof. The proof is presented in Appendix D. \square

Transforming the DAE (1) as $U^\top EVV^\top \dot{x} = U^\top AVV^\top x$ and setting $V^\top x = [x_1^\top, \dots, x_4^\top]^\top$, it follows that $x_1 = 0$, x_2 is determined from the implicit ordinary differential equation (note that E_{22} is invertible)

$$E_{22}\dot{x}_2 = (A_{22} - A_{23}A_{33}^{-1}A_{32})x_2, \quad (56)$$

$x_3 = -A_{33}^{-1}A_{32}x_2$, and x_4 is uniquely determined in terms of x_2, \dot{x}_2, x_3 . Initial conditions can be prescribed freely for x_2 only.

Corollary 46 *Consider a general regular pencil $\lambda E - A$ with $E, A \in \mathbb{R}^{n,n}$ that is of index at most two and for which all finite eigenvalues are in the closed left half plane and those on the imaginary axis are semi-simple. Then there exist invertible matrices $U \in \mathbb{R}^{n,n}$ and $V \in \mathbb{R}^{n,n}$ such that*

$$U^\top EV = \begin{bmatrix} I_{\hat{n}_1} & 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 & 0 \\ 0 & 0 & E_{33} & 0 & 0 \\ 0 & 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 & 0 \end{bmatrix}, \quad U^\top AV = \begin{bmatrix} 0 & 0 & 0 & I_{\hat{n}_1} & 0 \\ 0 & 0 & 0 & 0 & I_{\hat{n}_2} \\ 0 & 0 & A_{33} & 0 & 0 \\ 0 & 0 & 0 & I_{\hat{n}_4} & 0 \\ -I_{\hat{n}_1} & 0 & 0 & 0 & 0 \\ 0 & -I_{\hat{n}_2} & 0 & 0 & 0 \end{bmatrix}, \quad (57)$$

where

$$E_{33} = E_{33}^\top > 0, \quad A_{33} = J_{33} - R_{33}, \quad J_{33} = -J_{33}^\top, \quad R_{33}^\top = R_{33} \geq 0.$$

Proof. The proof follows by considering the condensed form (55), and using block elimination with the invertible matrices $A_{33}, A_{14}, A_{41}, E_{22}$ to transform pencil in (55) to the form

$$\lambda \begin{bmatrix} \tilde{E}_{11} & 0 & 0 & 0 \\ 0 & I_{n_2} & 0 & 0 \\ 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 \end{bmatrix} - \begin{bmatrix} 0 & 0 & 0 & I_{n_1} \\ 0 & \tilde{A}_{22} & 0 & 0 \\ 0 & 0 & I_{n_3} & 0 \\ -I_{n_1} & 0 & 0 & 0 \end{bmatrix}. \quad (58)$$

Let $U_1^\top \tilde{E}_{11} V_1 = \begin{bmatrix} I_{\hat{n}_1} & 0 \\ 0 & 0 \end{bmatrix}$ be the echelon form of \tilde{E}_{11} . We scale the first block row of with U_1^\top , the fourth block row with V_1^{-1} , the first block column by V_1 , and the fourth block column by $U_1^{-\top}$ and obtain a form

$$U^\top EV = \begin{bmatrix} I_{\hat{n}_1} & 0 & 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 & 0 & 0 \\ 0 & 0 & I_{n_3} & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 & 0 & 0 \end{bmatrix}, \quad U^\top AV = \begin{bmatrix} 0 & 0 & 0 & 0 & I_{\hat{n}_1} & 0 \\ 0 & 0 & 0 & 0 & 0 & I_{\hat{n}_2} \\ 0 & 0 & \hat{A}_{33} & 0 & 0 & 0 \\ 0 & 0 & 0 & I_{\hat{n}_4} & 0 & 0 \\ -I_{\hat{n}_1} & 0 & 0 & 0 & 0 & 0 \\ 0 & -I_{\hat{n}_2} & 0 & 0 & 0 & 0 \end{bmatrix},$$

For any positive definite solution X of the Lyapunov inequality

$$-\tilde{A}_{33}^\top X - X \tilde{A}_{33} \geq 0 \quad (59)$$

one can multiply the second block row by X and obtain that $E_{33} = X$ and $A_{33} = X \hat{A}_{33}$ has the desired form, see e.g. [1, 3]. \square

Note that the transformation to a system of the form (2) can also be achieved in a similar way for singular pencils with zero minimal indices.

If there is no dissipation, i.e. if $R_{33} = 0$, then A_{33} is skew-symmetric.

In Corollary 46 we have shown that general systems $E\dot{x} = Ax$ can be transformed to a very special canonical form and the following remark shows that for the case $R_{33} = 0$ each of the blocks in the canonical form can be expressed as a pencil of the form $\lambda KP - LS$.

Remark 47 Consider a regular pencil $\lambda E - A$ in the form (57) then after a permutation one gets four blocks which all can be written in the form $\lambda KP - LS$ as in (10).

1) We have

$$\begin{bmatrix} I_{\hat{n}_1} & 0 \\ 0 & 0 \end{bmatrix} \begin{bmatrix} \dot{z}_1 \\ \dot{z}_5 \end{bmatrix} - \begin{bmatrix} 0 & I_{\hat{n}_1} \\ -I_{\hat{n}_1} & 0 \end{bmatrix} \begin{bmatrix} z_1 \\ z_5 \end{bmatrix} = K_1 P_1 \begin{bmatrix} \dot{z}_1 \\ \dot{z}_5 \end{bmatrix} - L_1 S_1 \begin{bmatrix} z_1 \\ z_5 \end{bmatrix}$$

with

$$K_1 = \begin{bmatrix} I_{\hat{n}_1} & 0 \\ 0 & I_{\hat{n}_1} \end{bmatrix}, \quad L_3 = \begin{bmatrix} 0 & I_{\hat{n}_1} \\ -I_{\hat{n}_1} & 0 \end{bmatrix}, \quad P_3 = \begin{bmatrix} I_{\hat{n}_1} & 0 \\ 0 & 0 \end{bmatrix}, \quad S_3 = \begin{bmatrix} I_{\hat{n}_1} & 0 \\ 0 & I_{\hat{n}_1} \end{bmatrix}$$

and Hamiltonian $\mathcal{H}_1 = \frac{1}{2} \begin{bmatrix} z_1 \\ z_5 \end{bmatrix}^\top \begin{bmatrix} I_{\hat{n}_1} & 0 \\ 0 & 0 \end{bmatrix} \begin{bmatrix} z_1 \\ z_5 \end{bmatrix} = \frac{1}{2} z_1^2$ which is actually 0.

In this case we can insert the derivative of the second equation into the first (index reduction) and obtain

$$\begin{bmatrix} 0 & 0 \\ 0 & 0 \end{bmatrix} \begin{bmatrix} \dot{z}_1 \\ \dot{z}_5 \end{bmatrix} = \begin{bmatrix} 0 & I_{\hat{n}_1} \\ -I_{\hat{n}_1} & 0 \end{bmatrix} \begin{bmatrix} z_1 \\ z_5 \end{bmatrix}$$

without changing the Hamiltonian.

2) We have

$$\begin{bmatrix} 0 & 0 \\ 0 & 0 \end{bmatrix} \begin{bmatrix} \dot{z}_2 \\ \dot{z}_6 \end{bmatrix} = \begin{bmatrix} 0 & I_{\hat{n}_2} \\ -I_{\hat{n}_2} & 0 \end{bmatrix} \begin{bmatrix} z_2 \\ z_6 \end{bmatrix} = K_2 P_2 \begin{bmatrix} \dot{z}_2 \\ \dot{z}_6 \end{bmatrix} - L_2 S_2 \begin{bmatrix} z_2 \\ z_6 \end{bmatrix}$$

with different possibilities of representation, e.g.

a)

$$K_2 = \begin{bmatrix} I_{\hat{n}_2} & 0 \\ 0 & I_{\hat{n}_2} \end{bmatrix}, L_3 = \begin{bmatrix} 0 & I_{\hat{n}_2} \\ -I_{\hat{n}_2} & 0 \end{bmatrix}, P_2 = \begin{bmatrix} 0 & 0 \\ 0 & 0 \end{bmatrix}, S_3 = \begin{bmatrix} I_{\hat{n}_1} & 0 \\ 0 & I_{\hat{n}_1} \end{bmatrix}$$

and Hamiltonian $\mathcal{H}_2 = \frac{1}{2} \begin{bmatrix} z_2 \\ z_6 \end{bmatrix}^\top \begin{bmatrix} 0 & 0 \\ 0 & 0 \end{bmatrix} \begin{bmatrix} z_2 \\ z_6 \end{bmatrix} = 0$, or

b)

$$K_2 = \begin{bmatrix} 0 & 0 \\ 0 & 0 \end{bmatrix}, L_2 = \begin{bmatrix} 0 & I_{\hat{n}_2} \\ -I_{\hat{n}_2} & 0 \end{bmatrix}, P_2 = \begin{bmatrix} 0 & 0 \\ 0 & 0 \end{bmatrix}, S_2 = \begin{bmatrix} I_{\hat{n}_2} & 0 \\ 0 & I_{\hat{n}_2} \end{bmatrix}$$

and Hamiltonian $\mathcal{H}_2 = \frac{1}{2} \begin{bmatrix} z_2 \\ z_6 \end{bmatrix}^\top \begin{bmatrix} 0 & 0 \\ 0 & 0 \end{bmatrix} \begin{bmatrix} z_2 \\ z_6 \end{bmatrix} = 0$.

- 3) We have $\lambda E_{33} - A_{33} = \lambda K_3 P_3 - L_3 S_3$ with $K_3 = I_{\hat{n}_3}$, $P_3 = E_{33}$, $L_3 = A_{33}$, $S_3 = I_{\hat{n}_3}$. Here the Hamiltonian is $\mathcal{H}_3 = \frac{1}{2} z_3^\top E_{33} z_3$.
- 4) We have $\lambda 0 - I_{\hat{n}_4} = \lambda K_4 P_4 - L_4 S_4$ with $K_4 = 0$, $P_4 = I_{\hat{n}_4}$, $L_4 = I_{\hat{n}_4}$, $S_4 = I_{\hat{n}_4}$. Here the Hamiltonian is $\mathcal{H}_4 = \frac{1}{2} z_4^\top z_4$.

Note that the presented representations are in no way unique, but if the condensed form is available or computable, and the properties of Theorem 45 hold then we can express the general DAE in the representation (10) or (2)

Conclusions

Different definitions of (extended dissipative) Hamiltonian or port Hamiltonian differential-algebraic systems lead to different representations. We have collected all the known representations as well as a few new ones and analyzed them from a geometric as well as an algebraic point of view. The latter leads to condensed forms that can be directly implemented in numerical algorithms to compute the structural properties of the systems. We have also studied the effect that the different representations have on the index of the differential-algebraic system as well as the associated Hamilton function. In general it can be seen that certain algebraic constraints do not contribute to the Hamiltonian and therefore can be separated from the system in an appropriate coordinate system. We have also characterized when a general differential-algebraic system can be transformed to the different representations.

References

- [1] F. Achleitner, A. Arnold, and V. Mehrmann. Hypocoercivity and controllability in linear semi-dissipative ODEs and DAEs. *ZAMM Z. Angew. Math. Mech.*, 2021.

- [2] V.I. Arnol'd. *Mathematical methods of classical mechanics*, volume 60. Springer Science & Business Media, 2013.
- [3] C. Beattie, V. Mehrmann, and P. Van Dooren. Robust port-Hamiltonian representations of passive systems. *Automatica J. IFAC*, 100:182–186, 2019.
- [4] C. Beattie, V. Mehrmann, H. Xu, and H. Zwart. Port-Hamiltonian descriptor systems. *Math. Control Signals Systems*, 30(17):1–27, 2018.
- [5] P. Benner, R. Byers, H. Faßbender, V. Mehrmann, and D. Watkins. Cholesky-like factorizations of skew-symmetric matrices. *Electron. Trans. Numer. Anal.*, 11:85–93, 2000.
- [6] P. C. Breedveld. *Modeling and Simulation of Dynamic Systems using Bond Graphs*, pages 128–173. EOLSS Publishers Co. Ltd./UNESCO, Oxford, UK, 2008.
- [7] T. Brüll and V. Mehrmann. STCSSP: A FORTRAN 77 routine to compute a structured staircase form for a (skew-)symmetric/(skew-)symmetric matrix pencil. Preprint 31-2007, Institut für Mathematik, TU Berlin, 2007.
- [8] R. Byers, V. Mehrmann, and H. Xu. A structured staircase algorithm for skew-symmetric/symmetric pencils. *Electron. Trans. Numer. Anal.*, 26:1–13, 2007.
- [9] M. K. Camlibel and A. van der Schaft. Incrementally port-hamiltonian systems. In *52nd IEEE Conference on Decision and Control*, pages 2538–2543. IEEE, 2013.
- [10] M. K. Camlibel and A. van der Schaft. Port-hamiltonian systems and monotonicity. Technical report, 2022.
- [11] Theodore James Courant. Dirac manifolds. *Transactions of the American Mathematical Society*, 319(2):631–661, 1990.
- [12] L. Dai. *Singular Control Systems*, volume 118 of *Lecture Notes in Control and Inform. Sci.* Springer-Verlag, Berlin, Heidelberg, 1989.
- [13] V. Duindam, A. Macchelli, S. Stramigioli, and H. Bruyninckx. *Modeling and control of complex physical systems: the port-Hamiltonian approach*. Springer-Verlag, Berlin, Heidelberg, 2009.
- [14] H. Egger and T. Kugler. Damped wave systems on networks: Exponential stability and uniform approximations. *Numer. Math.*, 138(4):839–867, 2018.
- [15] H. Egger, T. Kugler, B. Liljegren-Sailer, N. Marheineke, and V. Mehrmann. On structure preserving model reduction for damped wave propagation in transport networks. *SIAM J. Sci. Comput.*, 40:A331–A365, 2018.
- [16] E. Eich-Soellner and C. Führer. *Numerical Methods in Multibody Dynamics*. Vieweg+Teubner Verlag, Wiesbaden, 1998.
- [17] E. Emmrich and V. Mehrmann. Operator differential-algebraic equations arising in fluid dynamics. *Comput. Methods Appl. Math*, 13(4):443–470, 2013.

- [18] R. W. Freund. The SPRIM algorithm for structure-preserving order reduction of general RLC circuits. In P. Benner, M. Hinze, and E. J. W. ter Maten, editors, *Model reduction for circuit simulation*, pages 25–52. Springer-Verlag, Dordrecht, 2011.
- [19] F.R. Gantmacher. *Theory of Matrices*, volume 1. Chelsea, New York, 1959.
- [20] H. Gernandt, F.R. Haller, and T. Reis. A linear relation approach to port-Hamiltonian differential-algebraic equations. *SIAM J. Matrix Anal. Appl.* 42(2):1011–1044, 2021.
- [21] G. Golo, A. J. van der Schaft, P. C. Breedveld, and B. M. Maschke. Hamiltonian formulation of bond graphs. In A. Rantzer R. Johansson, editor, *Nonlinear and Hybrid Systems in Automotive Control*, pages 351–372. Springer, Heidelberg, 2003.
- [22] B. Jacob and H. Zwart. *Linear port-Hamiltonian systems on infinite-dimensional spaces*. Operator Theory: Advances and Applications. Birkhäuser, Basel, 2012.
- [23] P. Kunkel and V. Mehrmann. *Differential-Algebraic Equations. Analysis and Numerical Solution*. European Mathematical Society, Zürich, 2006.
- [24] P. Kunkel and V. Mehrmann. Formal adjoints of linear DAE operators and their role in optimal control. *Electron. J. Linear Algebra*, 22:672–693, 2011.
- [25] J. Liesen and V. Mehrmann. *Linear Algebra*. Springer Undergraduate Mathematics Series. Springer-Verlag, Cham, 2015.
- [26] B. M. Maschke and A. van der Schaft. Port-controlled Hamiltonian systems: Modelling origins and system theoretic properties. *IFAC Proceedings Volumes*, 25(13):359–365, 1992.
- [27] C. Mehl, V. Mehrmann, and M. Wojtylak. Linear algebra properties of dissipative Hamiltonian descriptor systems. *SIAM J. Matrix Anal. Appl.*, 39(3):1489–1519, 2018.
- [28] C. Mehl, V. Mehrmann, and M. Wojtylak. Distance problems for dissipative Hamiltonian systems and related matrix polynomials. *Linear Algebra Appl.*, pages 335–366, 2021.
- [29] V. Mehrmann and R. Morandin. Structure-preserving discretization for port-Hamiltonian descriptor systems. In *58th IEEE Conference on Decision and Control (CDC), Nice, France*, pages 6863–6868, 2019.
- [30] V. Mehrmann and B. Unger. Control of port-hamiltonian differential-algebraic systems and applications. Technical report, 2022. <http://arxiv.org/abs/2201.06590>.
- [31] R. Ortega, A. J. van der Schaft, Y. Mareels, and B. M. Maschke. Putting energy back in control. *Control Syst. Mag.*, 21:18–Å±33, 2001.
- [32] A. J. van der Schaft. Port-Hamiltonian systems: network modeling and control of non-linear physical systems. In *Advanced Dynamics and Control of Structures and Machines*, CISM Courses and Lectures, Vol. 444. Springer Verlag, New York, N.Y., 2004.
- [33] A. J. van der Schaft. Port-Hamiltonian systems: an introductory survey. In J. L. Verona M. Sanz-Sole and J. Verdura, editors, *Proc. of the International Congress of Mathematicians, vol. III, Invited Lectures*, pages 1339–1365, Madrid, Spain, 2006.

- [34] L. Scholz. Condensed forms for linear port-Hamiltonian descriptor systems. Preprint 09–2017, Institut für Mathematik, Technische Universität Berlin, 2017.
- [35] A. van der Schaft. *L₂-gain and passivity techniques in nonlinear control*. Springer-Verlag, 2000.
- [36] A. van der Schaft. Port-Hamiltonian differential-algebraic systems. In A. Ilchmann and T. Reis, editors, *Surveys in Differential-Algebraic Equations I*, Differential-Algebraic Equations Forum, pages 173–226. Springer-Verlag, Berlin, Heidelberg, 2013.
- [37] A. van der Schaft and D. Jeltsema. Port-Hamiltonian systems theory: An introductory overview. *Foundations and Trends in Systems and Control*, 1(2-3):173–378, 2014.
- [38] A. van der Schaft and B. Maschke. Generalized port-Hamiltonian DAE systems. *Systems Control Lett.*, 121:31–37, 2018.
- [39] A. van der Schaft and B. Maschke. Dirac and lagrange algebraic constraints in nonlinear port-hamiltonian systems. *Vietnam Journal of Mathematics*, 48(4):929–939, 2020.
- [40] A. J. van der Schaft and B. M. Maschke. The Hamiltonian formulation of energy conserving physical systems with external ports. *Arch. Elektron. Übertragungstech.*, 45:362–371, 1995.
- [41] A. J. van der Schaft and B. M. Maschke. Port-Hamiltonian systems on graphs. *SIAM J. Cont.*, 51(2):906–937, 2013.

Appendix

A: The Kronecker canonical form

For completeness we recall the Kronecker canonical form, see e.g. [19].

Theorem 48 *Let $E, A \in \mathbb{C}^{n,m}$. Then there exist nonsingular matrices $U \in \mathbb{C}^{n,n}$ and $W \in \mathbb{C}^{m,m}$ such that*

$$U(\lambda E - A)W = \text{diag}(\mathcal{L}_{\epsilon_1}, \dots, \mathcal{L}_{\epsilon_p}, \mathcal{L}_{\eta_1}^\top, \dots, \mathcal{L}_{\eta_q}^\top, \mathcal{J}_{\rho_1}^{\lambda_1}, \dots, \mathcal{J}_{\rho_r}^{\lambda_r}, \mathcal{N}_{\sigma_1}, \dots, \mathcal{N}_{\sigma_s}), \quad (60)$$

where the block entries have the following properties:

- (i) Every entry \mathcal{L}_{ϵ_j} is a bidiagonal block of size $\epsilon_j \times (\epsilon_j + 1)$, $\epsilon_j \in \mathbb{N}_0$, of the form

$$\lambda \begin{bmatrix} 1 & 0 & & \\ & \ddots & \ddots & \\ & & 1 & 0 \end{bmatrix} - \begin{bmatrix} 0 & 1 & & \\ & \ddots & \ddots & \\ & & 0 & 1 \end{bmatrix}.$$

- (ii) Every entry $\mathcal{L}_{\eta_j}^\top$ is a bidiagonal block of size $(\eta_j + 1) \times \eta_j$, $\eta_j \in \mathbb{N}_0$, of the form

$$\lambda \begin{bmatrix} 1 & & & \\ 0 & \ddots & & \\ & \ddots & 1 & \\ & & & 0 \end{bmatrix} - \begin{bmatrix} 0 & & & \\ 1 & \ddots & & \\ & \ddots & 0 & \\ & & & 1 \end{bmatrix}.$$

(iii) Every entry $\mathcal{J}_{\rho_j}^{\lambda_j}$ is a Jordan block of size $\rho_j \times \rho_j$, $\rho_j \in \mathbb{N}$, $\lambda_j \in \mathbb{C}$, of the form

$$\lambda \begin{bmatrix} 1 & & & \\ & \ddots & & \\ & & \ddots & \\ & & & 1 \end{bmatrix} - \begin{bmatrix} \lambda_j & 1 & & \\ & \ddots & \ddots & \\ & & \ddots & 1 \\ & & & \lambda_j \end{bmatrix}.$$

(iv) Every entry \mathcal{N}_{σ_j} is a nilpotent block of size $\sigma_j \times \sigma_j$, $\sigma_j \in \mathbb{N}$, of the form

$$\lambda \begin{bmatrix} 0 & 1 & & \\ & \ddots & \ddots & \\ & & \ddots & 1 \\ & & & 0 \end{bmatrix} - \begin{bmatrix} 1 & & & \\ & \ddots & & \\ & & \ddots & \\ & & & 1 \end{bmatrix}.$$

The Kronecker canonical form is unique up to permutation of the blocks.

For real matrices there exists a real Kronecker canonical form which is obtained under real transformation matrices U, W . Here, the blocks $\mathcal{J}_{\rho_j}^{\lambda_j}$ with $\lambda_j \in \mathbb{C} \setminus \mathbb{R}$ are in real Jordan canonical form instead, but the other blocks have the same structure as in the complex case.

The sizes η_j , and ϵ_i of the rectangular blocks are called the *left and right minimal indices* of $\lambda E - A$, respectively. Furthermore, a value $\lambda_0 \in \mathbb{C}$ is called a (finite) eigenvalue of \mathcal{P}_{EA} if

$$\text{rank}(\lambda_0 E - A) < \max_{\alpha \in \mathbb{C}} \text{rank}(\alpha E - A).$$

Furthermore, $\lambda_0 = \infty$ is said to be an eigenvalue of \mathcal{P}_{EA} if zero is an eigenvalue of $\lambda A - E$. It is obvious from Theorem 48 that the blocks \mathcal{J}_{ρ_j} as in (iii) correspond to finite eigenvalues of $\lambda E - A$, whereas blocks \mathcal{N}_{σ_j} as in (iv) correspond to the eigenvalue ∞ . The sum of all sizes of blocks that are associated with a fixed eigenvalue $\lambda_0 \in \mathbb{C} \cup \{\infty\}$ is called the *algebraic multiplicity* of λ_0 . The size of the largest block \mathcal{N}_{σ_j} is called the *index* ν of the pencil \mathcal{P}_{EA} , where, by convention, $\nu = 0$ if E is invertible.

The matrix pencil $\mathcal{P}_{EA} \in \mathbb{F}^{n,m}[\lambda]$ is called *regular* if $n = m$ and $\det(\lambda_0 E - A) \neq 0$ for some $\lambda_0 \in \mathbb{C}$, otherwise it is called *singular*. A pencil is singular if and only if it has blocks of at least one of the types \mathcal{L}_{ϵ_j} or $\mathcal{L}_{\eta_j}^\top$ in the Kronecker canonical form.

Note that if $\lambda E - A$ is regular then the Kronecker canonical form is usually called the *Weierstraß canonical form*.

Appendix B: Proof of Lemma 34

Proof. We present a proof in form of an algorithmic procedure that can be implemented as a numerical algorithm.

Step 1. Let V_1 and W_1 be real orthogonal matrices such that

$$V_1^\top P W_1 = \begin{bmatrix} \tilde{P}_{11} & 0 \\ 0 & 0 \end{bmatrix}, \quad V_1^\top S W_1 = \begin{bmatrix} \tilde{S}_{11} & \tilde{S}_{12} \\ \tilde{S}_{21} & \tilde{S}_{22} \end{bmatrix},$$

where $\tilde{P}_{11} \in \mathbb{R}^{\tilde{m}_1, \tilde{m}_1}$ is diagonal with positive diagonal elements. This transformation can be constructed via a singular value decomposition of P and a numerical rank decision.

Then, using the structure (16), it follows that $\tilde{P}_{11}^\top \tilde{S}_{11} = \tilde{S}_{11}^\top \tilde{P}_{11}$ and $\tilde{S}_{12} = 0$.
Step 2. Let \tilde{V}_2, \tilde{W}_2 be real orthogonal matrices such that

$$\tilde{V}_2^\top \tilde{S}_{22} W_2 = \begin{bmatrix} \hat{S}_{22} & 0 \\ 0 & 0 \end{bmatrix}$$

where $\hat{S}_{22} \in \mathbb{R}^{m_4, m_4}$ is diagonal with positive diagonal elements. This transformation can be constructed again via a singular value decomposition and a numerical rank decision. Set

$$V_2 = \begin{bmatrix} I_{\tilde{m}_1} & 0 \\ 0 & \tilde{V}_2^\top \end{bmatrix}, \quad W_2 = \begin{bmatrix} I_{\tilde{m}_1} & 0 \\ 0 & \tilde{W}_2 \end{bmatrix}$$

and form

$$V_2^\top V_1^\top P W_1 W_2 = \begin{bmatrix} \hat{P}_{11} & 0 & 0 \\ 0 & 0 & 0 \\ 0 & 0 & 0 \end{bmatrix}, \quad V_2^\top V_1^\top S W_1 W_2 = \begin{bmatrix} \hat{S}_{11} & 0 & 0 \\ \hat{S}_{21} & \hat{S}_{22} & 0 \\ \hat{S}_{31} & 0 & 0 \end{bmatrix},$$

with $\hat{P}_{11}^\top = \tilde{P}_{11}$.

Step 3. Let

$$V_3 = \begin{bmatrix} \hat{P}_{11} & 0 & 0 \\ 0 & \hat{S}_{22}^{-\top} & 0 \\ 0 & 0 & I_{n-\tilde{m}_1-m_4} \end{bmatrix}, \quad W_3 = \begin{bmatrix} I_{\tilde{m}_1} & 0 & 0 \\ -\hat{S}_{22}^{-1} \hat{S}_{21} & I_{m_4} & 0 \\ 0 & 0 & I_{m-\tilde{m}_1-m_4} \end{bmatrix},$$

and form

$$V_3^{-1} V_2^\top V_1^\top P W_1 W_2 W_3 = \begin{bmatrix} I_{\tilde{m}_1} & 0 & 0 \\ 0 & 0 & 0 \\ 0 & 0 & 0 \end{bmatrix}, \quad V_3^\top V_2^\top V_1^\top S W_1 W_2 W_3 = \begin{bmatrix} \check{S}_{11} & 0 & 0 \\ 0 & I_{m_4} & 0 \\ \check{S}_{31} & 0 & 0 \end{bmatrix},$$

where by the structure (16) now \check{S}_{11} is symmetric. Note that although we are working with nonorthogonal transformation matrices in this step the numerical errors can be controlled, since we are inverting diagonal matrices.

Step 4. Let

$$\check{V}_{11}^\top \check{S}_{11} \check{V}_{11} = \begin{bmatrix} I_{m_1} & 0 & 0 \\ 0 & -I_{m_2} & 0 \\ 0 & 0 & 0 \end{bmatrix}$$

be the canonical form of the skew-symmetric matrix \check{S}_{11} under congruence which can be obtained by first computing the spectral decomposition and then scaling the nonsingular diagonal parts by congruence to be $\pm I$, see e.g. [25].

Furthermore let

$$\check{S}_{31} = \check{V}_4 \begin{bmatrix} S_{51} & S_{5,2} & S_{5,3} \\ 0 & 0 & 0 \end{bmatrix}$$

be a full rank decomposition partitioned accordingly, with \check{V}_3 real orthogonal. Then set

$$V_4 = \begin{bmatrix} \check{V}_{11}^{-\top} & 0 & 0 \\ 0 & I_{m_4} & 0 \\ 0 & 0 & \check{V}_4 \end{bmatrix}, \quad W_4 = \begin{bmatrix} \check{V}_{11} & 0 & 0 \\ 0 & I_{m_4} & 0 \\ 0 & 0 & I_{m-\tilde{m}_1-m_4} \end{bmatrix},$$

and form

$$\begin{aligned}
V_4^{-1}V_3^{-1}V_2^{-1}V_1^{-1}PW_1W_2W_3W_4 &= \begin{bmatrix} I_{m_1} & 0 & 0 & 0 & 0 \\ 0 & I_{m_2} & 0 & 0 & 0 \\ 0 & 0 & I_{m_3} & 0 & 0 \\ 0 & 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 & 0 \end{bmatrix}, \\
V_4^{-1}V_3^{-1}V_2^{-1}V_1^{-1}SW_1W_2W_3 &= \begin{bmatrix} I_{m_1} & 0 & 0 & 0 & 0 \\ 0 & -I_{m_2} & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & I_{m_4} & 0 \\ S_{51} & S_{5,2} & S_{5,3} & 0 & 0 \\ 0 & 0 & 0 & 0 & 0 \end{bmatrix},
\end{aligned}$$

which is as claimed. \square

Appendix C: Proof of Lemma 36

Proof. The proof is similar to that of Lemma 34 just adapting to the different symmetries and transformation structure. The following algorithmic procedure can be directly implemented as a numerical algorithm.

Step 1. Let U_1 and V_1 be real orthogonal matrices such that

$$U_1^\top KV_1 = \begin{bmatrix} \tilde{K}_{11} & 0 \\ 0 & 0 \end{bmatrix}, \quad U_1^\top LV_1^{-\top} = \begin{bmatrix} \tilde{L}_{11} & \tilde{L}_{12} \\ \tilde{L}_{21} & \tilde{L}_{22} \end{bmatrix},$$

where $\tilde{K}_{11} \in \mathbb{R}^{\tilde{\ell}_1, \tilde{\ell}_1}$ is diagonal with positive diagonal elements. This transformation can be constructed via a singular value decomposition of K and a numerical rank decision.

Then, using the structure (14), it follows that $\tilde{K}_{11}^\top \tilde{L}_{11} = \tilde{L}_{11}^\top \tilde{K}_{11}$ and $\tilde{L}_{21} = 0$.

Step 2. Let \tilde{U}_2, \tilde{V}_2 be real orthogonal matrices such that

$$\tilde{U}_2^\top \tilde{L}_{22} \tilde{V}_2^{-\top} = \begin{bmatrix} \hat{L}_{22} & 0 \\ 0 & 0 \end{bmatrix},$$

where $\hat{L}_{22} \in \mathbb{R}^{\ell_4, \ell_4}$ is diagonal with positive diagonal elements. This transformation can be constructed again via a singular value decomposition and a numerical rank decision. Set

$$U_2 = \begin{bmatrix} I_{\tilde{\ell}_1} & 0 \\ 0 & \tilde{U}_2 \end{bmatrix}, \quad V_2 = \begin{bmatrix} I_{\tilde{\ell}_1} & 0 \\ 0 & \tilde{V}_2 \end{bmatrix}$$

and form

$$U_2^\top U_1^\top KV_1 V_2 = \begin{bmatrix} \hat{K}_{11} & 0 & 0 \\ 0 & 0 & 0 \\ 0 & 0 & 0 \end{bmatrix}, \quad U_2^\top U_1^\top LV_1^{-\top} V_2^{-\top} = \begin{bmatrix} \hat{L}_{11} & \hat{L}_{12} & \hat{L}_{13} \\ 0 & \hat{L}_{22} & 0 \\ 0 & 0 & 0 \end{bmatrix},$$

with $\hat{K}_{11} = \tilde{K}_{11}$.

Step 3. Let

$$U_3 = \begin{bmatrix} I_{\tilde{\ell}_1} & -\hat{L}_{22}^{-\top} \hat{L}_{12}^\top & 0 \\ 0 & \hat{L}_{22}^{-\top} & 0 \\ 0 & 0 & I_{\ell - \tilde{\ell}_1 - \ell_4} \end{bmatrix}, \quad V_3 = \begin{bmatrix} \hat{K}_{11}^{-1} & 0 & 0 \\ 0 & I_{\ell_4} & 0 \\ 0 & 0 & I_{n - \tilde{\ell}_1 - \ell_4} \end{bmatrix},$$

and form

$$U_3^\top U_2^\top U_1^\top K V_1 V_2 V_3 = \begin{bmatrix} I_{\tilde{\ell}_1} & 0 & 0 \\ 0 & 0 & 0 \\ 0 & 0 & 0 \end{bmatrix}, \quad U_3^\top U_2^\top U_1^\top L V_1^{-\top} V_2^{-\top} V_3^{-\top} = \begin{bmatrix} \check{L}_{11} & 0 & \check{L}_{13} \\ 0 & I_{\ell_4} & 0 \\ \check{0} & 0 & 0 \end{bmatrix},$$

where by the structure (14) now \check{L}_{11} is skew-symmetric. Note that although we are working with nonorthogonal transformation matrices in this step, the numerical errors can be controlled since we are inverting diagonal matrices.

Step 4. Let

$$\check{U}_{11}^\top \check{L}_{11} \check{U}_{11} = \begin{bmatrix} 0 & I_{\ell_1} & 0 \\ -I_{\ell_1} & 0 & 0 \\ 0 & 0 & 0 \end{bmatrix}$$

be the canonical form of the skew-symmetric matrix \check{L}_{11} under congruence which can be obtained by first computing the spectral decomposition and then scaling the nonsingular diagonal parts by congruence to be $\pm I$. This procedure is implemented in a numerically robust way in [5]. Furthermore let

$$\check{L}_{13} = \begin{bmatrix} L_{15} & 0 \\ L_{25} & 0 \\ L_{35} & 0 \end{bmatrix} \check{V}_3$$

be a full rank decomposition partitioned accordingly, with \check{V}_3 real orthogonal. Then set

$$U_4 = \begin{bmatrix} \check{U}_{11} & 0 & 0 \\ 0 & I_{\ell_4} & 0 \\ 0 & 0 & I_{\ell - \tilde{\ell}_1 - \ell_4} \end{bmatrix}, \quad V_4 = \begin{bmatrix} \check{U}_{11}^{-\top} & 0 & 0 \\ 0 & I_{\ell_4} & 0 \\ 0 & 0 & \check{V}_3 \end{bmatrix},$$

and form

$$U_4^\top U_3^\top U_2^\top U_1^\top K V_1 V_2 V_3 V_4 = \begin{bmatrix} I_{\ell_1} & 0 & 0 & 0 & 0 \\ 0 & I_{\ell_1} & 0 & 0 & 0 \\ 0 & 0 & I_{\ell_3} & 0 & 0 \\ 0 & 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 & 0 \end{bmatrix},$$

$$U_4^\top U_3^\top U_2^\top U_1^\top L V_1^{-\top} V_2^{-\top} V_3^{-\top} V_4^{-\top} = \begin{bmatrix} 0 & I_{\ell_1} & 0 & 0 & L_{15} & 0 \\ -I_{\ell_1} & 0 & 0 & 0 & L_{25} & 0 \\ 0 & 0 & 0 & 0 & L_{35} & 0 \\ 0 & 0 & 0 & I_{\ell_4} & 0 & 0 \\ 0 & 0 & 0 & 0 & 0 & 0 \end{bmatrix},$$

which is as claimed. \square

Appendix D: Proof of Theorem 45

Proof. We again present a proof that can be implemented as a numerical algorithm.

Step 1. Let U_1 and V_1 be real orthogonal matrices such that

$$U_1^\top E V_1 = \begin{bmatrix} \tilde{E}_{11} & 0 \\ 0 & 0 \end{bmatrix}, \quad U_1^\top A V_1 = \begin{bmatrix} \tilde{A}_{11} & \tilde{A}_{12} \\ \tilde{A}_{21} & \tilde{A}_{22} \end{bmatrix},$$

where $\tilde{E}_{11} \in \mathbb{R}^{\tilde{n}_1, \tilde{n}_1}$ is diagonal with positive diagonal elements. This transformation can be constructed via a singular value decomposition of E and a numerical rank decision.

Step 2. Let \tilde{U}_2, \tilde{V}_2 be real orthogonal matrices such that

$$\tilde{U}_2^\top \tilde{A}_{22} \tilde{V}_2 = \begin{bmatrix} \hat{A}_{22} & 0 \\ 0 & 0 \end{bmatrix},$$

where $\hat{A}_{22} \in \mathbb{R}^{n_3, n_3}$ is diagonal with positive diagonal elements. This transformation can be constructed again via a singular value decomposition and a numerical rank decision. Set

$$U_2 = \begin{bmatrix} I_{\tilde{n}_1} & 0 \\ 0 & \tilde{U}_2 \end{bmatrix}, \quad V_2 = \begin{bmatrix} I_{\tilde{n}_1} & 0 \\ 0 & \tilde{V}_2 \end{bmatrix}$$

and form

$$U_2^\top U_1^\top E V_1 V_2 = \begin{bmatrix} \hat{E}_{11} & 0 & 0 \\ 0 & 0 & 0 \\ 0 & 0 & 0 \end{bmatrix}, \quad U_2^\top U_1^\top A V_1^{-\top} V_2 = \begin{bmatrix} \hat{A}_{11} & \hat{A}_{12} & \hat{A}_{13} \\ A_{21} & \hat{A}_{22} & 0 \\ A_{31} & 0 & 0 \end{bmatrix},$$

with $\hat{E}_{11} = \tilde{E}_{11}$.

The regularity of the pencil implies that A_{13} has full column rank $n_1 = \tilde{n}_1 - n_3$ and that A_{31} has full row rank $n_1 = \tilde{n}_1 - n_3$, because otherwise there would be common right or left nullspace, respectively.

Step 3. Let $\tilde{U}_{31}, \tilde{V}_{31}, \tilde{U}_{13}, \tilde{V}_{13}$ be real orthogonal matrices of appropriate dimensions such that

$$\tilde{U}_{13}^\top \tilde{A}_{13} \tilde{V}_{13} = \begin{bmatrix} \hat{A}_{14} \\ 0 \end{bmatrix}, \quad \tilde{U}_{31}^\top \tilde{A}_{31} \tilde{V}_{31} = \begin{bmatrix} \hat{A}_{41} & 0 \end{bmatrix}$$

where $\hat{A}_{41} \in \mathbb{R}^{n_1, n_1}$ and $\hat{A}_{14} \in \mathbb{R}^{n_1, n_1}$ are diagonal with positive diagonal elements. This transformation can be constructed again via a singular value decomposition and numerical rank decisions. Set

$$U_3 = \begin{bmatrix} \tilde{U}_{13} & 0 & 0 \\ 0 & I_{\ell_3} & 0 \\ 0 & 0 & \tilde{U}_{31} \end{bmatrix}, \quad V_3 = \begin{bmatrix} \tilde{V}_{31} & 0 & 0 \\ 0 & I_{\ell_3} & 0 \\ 0 & 0 & \tilde{V}_{13} \end{bmatrix},$$

then $U_3^\top U_2^\top U_1^\top E V_1 V_2 V_3$ and $U_3^\top U_2^\top U_1^\top A V_1 V_2 V_3$ are as claimed in (55). The invertibility of E_{22} then follows from the assumption that the pencil has index at most two, see [23]. \square