

The reproducing kernel Hilbert spaces underlying linear SDE Estimation, Kalman filtering and their relation to optimal control

Pierre-Cyril Aubin-Frankowski*

INRIA-Département d'Informatique de l'École Normale Supérieure,
PSL, Research University, Paris, France

Alain Bensoussan[†]

International Center for Decision and Risk Analysis
Jindal School of Management, University of Texas at Dallas

August 16, 2022

Abstract

It is often said that control and estimation problems are in duality. Recently, in Aubin-Frankowski (2021a), we found new reproducing kernels in Linear-Quadratic optimal control by focusing on the Hilbert space of controlled trajectories, allowing for an elegant handling of state constraints and meeting points. We now extend this view to estimation problems where it is known that kernels are the covariances of stochastic processes. Here, the Markovian Gaussian processes stem from the linear stochastic differential equations describing the continuous-time dynamics and observations. Taking extensive care to require minimal invertibility requirements on the operators, we give novel explicit formulas for these covariances. We also determine their reproducing kernel Hilbert spaces, stressing the symmetries between a space of forward-time trajectories and a space of backward-time information vectors. We then recover the Kalman filter and smoother formulas. Extension to discrete-time observations or infinite-dimensional state, tough technical, would be straightforward.

Keywords: Reproducing kernels, Kalman filtering, Markovian Gaussian processes, Optimal control.

2020 Mathematics Subject Classification: 46E22; 60G35; 62M20.

1 INTRODUCTION

Context. In preceding papers (Aubin-Frankowski, 2021a,b; Aubin-Frankowski and Bensoussan, 2022), connections have been made between the theory of reproducing kernel Hilbert spaces and control theory. Framing control problems as optimizing over vector spaces of functions with a dynamic constraint was already written in Luenberger (1968, p255). However, in the linear-quadratic case, Hilbertian structures actually emerge, the quadratic cost defining a norm over the vector space of linearly controlled trajectories. The latter has then an explicit reproducing kernel which is completely determined by the cost and dynamics. Conversely, this kernel

*pierre-cyril.aubin@inria.fr

[†]axb046100@utdallas.edu

[‡]also with the School of Data Science, City University Hong Kong. Research supported by the National Science Foundation under grant NSF-DMS-1905449 and grant from the SAR Hong Kong RGC GRF 14301321.

summarizes all the information about the system, and was shown in some cases to coincide with the inverse of the solution of the time-backward differential Riccati equation or with the controllability Gramian. Note that this approach does not rely on the value function, which does not live in a vector space but rather in a max-plus one, and has thus ties with tropical kernels (Aubin-Frankowski and Gaubert, 2022).

Another very related field is the problem of estimation. Its duality with control theory has been studied extensively since the seminal paper by Kálmán and Bucy (1961) (see e.g. Kailath et al., 2000, Chapter 15 for a discrete-time formalization). Unlike in control theory, kernels have been known in estimation problems since the origin of the field. Indeed reproducing kernels are the covariances of stochastic processes in this context (Parzen, 1961; Berlinet and Thomas-Agnan, 2004), and, in the Gaussian case, summarize all the information. In this Bayesian field of Gaussian process regression, kernels are ubiquitous, forming the deterministic counterpart of the stochastic processes (Rasmussen and Williams, 2005; Kanagawa et al., 2018). This regression framework was in particular applied to stochastic differential equations (see Särkkä and Solin, 2019, for an introduction and recent review) in close relation with Kalman filtering. Nevertheless the reproducing kernel Hilbert spaces (RKHSs) associated with the continuous-time Gaussian processes stemming from linear stochastic differential equations (SDEs) have not to the best of our knowledge been written explicitly.

Main results. We prove that the linear SDEs define two vector-valued RKHSs over the time interval: one, forward, for the reconstructible trajectories, and one, backward, for the information vectors. Specific values of the trajectory kernel coincide with the covariance of the minimal estimation error, and thus with the Kalman filter and Rauch-Tung-Striebel Smoother. For the information kernel, the connection is with the Gramian of observability. We provide new formulas for the covariance kernels of these Markovian Gaussian processes. By drawing upon the connection between covariance and RKHSs, we also generalize the kernel formulas obtained previously for optimal control. Since we work in an estimation context, extensive care was taken to provide minimal invertibility requirements on the matrices involved. To simplify a little, we limit ourselves to finite-dimensional systems, but generalization to infinite-dimensional systems (i.e. nonstationary spatiotemporal Gaussian processes, Sarkka et al. (2013); Lindgren et al. (2022)) can be done in the spirit of Aubin-Frankowski and Bensoussan (2022).

Related work. For discrete-time differential equations, the benefits and limitations of kernel regression, defined over the time axis, were discussed in Steinke and Scholkopf (2008). This contrasts with the wider use of kernels, defined over observation and state spaces, as off-the-shelf tools for estimation as in Kanagawa et al. (2016). Our setting is closer to the former, with all our kernels defined over time. Characterization of Markovian Gaussian processes by the form of their kernel was recalled in Neveu (1968, Chapter 3.2) and Berlinet and Thomas-Agnan (2004, Example 2, p58), and further studied in Eisenbaum and Kaspi (2006). The formulas for the covariance kernel of a linear SDE over the state variable but without an observation process were given in Särkkä and Solin (2019, Section 6.4, p.89). Up to our knowledge, while every linear SDE leads to a Markovian Gaussian process, the converse is not known in the general case.

The paper is structured as follows. The filtering and smoothing settings and their linear estimators are presented in Section 2 and related to a general perturbed two-point boundary value problem. Section 3 gives the formulas of the Green kernels for this problem, based on impulse-response. In Section 4, these kernels are shown to be the reproducing kernels of two functional spaces, of controlled trajectories and of information vectors respectively. In Section 5, for completeness, we rederive various known formulas for the Kalman filter and RTS smoothing. The results are finally summarized in Section 6 and compared to those previously obtained by the authors in optimal control. We provide in the Appendix implementable formulas to compute the kernels based on the Hamiltonian matrix.

2 KALMAN FILTERING AND RTS SMOOTHING IN CONTINUOUS TIME

2.1 STATEMENT OF THE PROBLEM

We consider on a probability space (Ω, \mathcal{A}, P) a filtration \mathcal{F}^t and two independent standard Wiener spaces $w(t)$, $b(t)$ with values in \mathbb{R}^p and \mathbb{R}^m , and respective covariances Q and R in the sense that the following correlation formulas hold

$$\mathbb{E}[w(s)w(t)^*] = \int_{t_0}^{\min(s,t)} Q(\tau)d\tau, \quad \mathbb{E}[b(s)b(t)^*] = \int_{t_0}^{\min(s,t)} R(\tau)d\tau \quad (2.1)$$

where $w(t)^* \in \mathbb{R}^{p,*}$ denotes the transpose and in which $Q(\cdot) \in L^1([t_0, T], \mathcal{L}(\mathbb{R}^{d,*}; \mathbb{R}^d))$, $R(\cdot) \in L^2([t_0, T], \mathcal{L}(\mathbb{R}^{m,*}; \mathbb{R}^m))$ and, for some $r > 0$, $R(\cdot) \succcurlyeq r \text{Id}$ a.e. The processes are assumed adapted to the filtration \mathcal{F}^t . We observe a dynamic system with partial information. The dynamic system is characterized by its state $x(t) \in \mathbb{R}^n$, which evolves according to the model

$$dx(t) = (F(t)x(t) + f(t))dt + G(t)dw(t), \quad x(t_0) = x_0 + \xi, \quad \xi \sim \mathcal{N}(0, \Pi_0) \quad (2.2)$$

in which $F(\cdot) \in L^1([t_0, T], \mathcal{L}(\mathbb{R}^n; \mathbb{R}^n))$, $G(\cdot) \in L^2([t_0, T], \mathcal{L}(\mathbb{R}^d; \mathbb{R}^n))$ and $f(\cdot) \in L^1([t_0, T], \mathbb{R}^n)$ are fixed deterministic functions, which are known, and $x_0 \in \mathbb{R}^n$, is a deterministic known vector. The random variable ξ has values in \mathbb{R}^n , and is assumed Gaussian with zero mean and covariance matrix Π_0 such that ξ , $w(\cdot)$, $b(\cdot)$ are mutually independent. Note that we require R to be invertible but do not require it for Q or Π_0 . The state $x(t)$ is not observed, we have instead a continuous-time observation process $y(t)$ with values in \mathbb{R}^m , related to $x(t)$ by the following relation¹

$$dy(t) = (H(t)x(t) + h(t))dt + db(t), \quad y(t_0) = y_0 \quad (2.3)$$

in which $H(\cdot) \in L^2([t_0, T], \mathcal{L}(\mathbb{R}^n; \mathbb{R}^m))$, $h(\cdot) \in L^1([t_0, T], \mathbb{R}^m)$. At any final time T , the available information is the trajectory $(y(t))_{t \in [t_0, T]}$ and we want to estimate the value of $x(s)$ for $s \in [t_0, T]$. When $s < T$, the best estimate is called the RTS smoother, and when $s = T$, it is the Kalman filter.

2.2 BEST ESTIMATE

From (2.2) and (2.3), we deduce that the processes $x(t)$ and $y(t)$ are Gaussian, with mean $\bar{x}(t)$ and $\bar{y}(t)$ given by the equations

$$\frac{d\bar{x}}{dt}(t) = F(t)\bar{x}(t) + f(t), \quad \bar{x}(t_0) = x_0, \quad (2.4)$$

$$\frac{d\bar{y}}{dt}(t) = H(t)\bar{x}(t) + h(t), \quad \bar{y}(t_0) = y_0. \quad (2.5)$$

We introduce the processes $\tilde{x}(t)$ and $\tilde{y}(t)$ with zero mean, $\tilde{x}(t) := x(t) - \bar{x}(t)$, $\tilde{y}(t) := y(t) - \bar{y}(t)$. They are solutions of the SDEs

$$d\tilde{x}(t) = F(t)\tilde{x}(t)dt + G(t)dw(t), \quad \tilde{x}(t_0) = \xi, \quad (2.6)$$

$$d\tilde{y}(t) = H(t)\tilde{x}(t)dt + db(t), \quad \tilde{y}(t_0) = 0. \quad (2.7)$$

¹A discrete-time observation process $y(t_i) = H(t_i)x(t_i) + \varepsilon_i$ could easily be considered, without changing formalism, with the same operator H and independent Gaussian noises $\varepsilon_i \sim \mathcal{N}(0, R_i)$.

The formal problem is to estimate $x(s)$ with the σ -algebra $\mathcal{Y}^T = \sigma(y(\tau), 0 \leq \tau \leq T)$. For the minimum mean square estimator, the solution is well-known (Neveu, 1968), it is the conditional expectation:

$$\hat{x}(s|T) = E[x(s)|\mathcal{Y}^T]. \quad (2.8)$$

The random variable $\hat{x}(s|T)$, for $s < T$, is the RTS smoother estimate, while $\hat{x}(T|T)$ is the Kalman filter estimate. However the expression (2.8) is not operational and we need more implementable formulas. The most important element we want to exploit is that, thanks to the fact that the processes $x(\cdot)$ and $y(\cdot)$ are Gaussian, the conditional expectation coincides with the best unbiased linear estimate, a.k.a. the minimum variance linear estimator. A linear unbiased estimate is characterized by an operator $S(t) \in \mathcal{L}(\mathbb{R}^m; \mathbb{R}^n)$. We estimate $x(s)$ by the minimum variance linear estimator $x_S(s|T)$ defined by the formula, related to Wiener filtering,

$$x_S(s|T) := \bar{x}(s) + \int_{t_0}^T S_s(t|T) d\tilde{y}(t) \quad (2.9)$$

which is obviously unbiased. The estimation error $\epsilon_S(s|T)$ thus satisfies

$$\epsilon_S(s|T) := x(s) - x_S(s|T) = \tilde{x}(s) - \int_{t_0}^T S_s(t|T) d\tilde{y}(t). \quad (2.10)$$

The objective is to find $\hat{S}_s(\cdot|T)$ minimizing the covariance matrix of the error

$$\hat{S}_s(\cdot|T) \in \operatorname{argmin}_{S(\cdot|T)} \Gamma_S(s|T) = \mathbb{E}[\epsilon_S(s|T)(\epsilon_S(s|T))^*]. \quad (2.11)$$

This minimization must be interpreted in the sense of the operator norm of positive matrices. The fact that this problem has a solution is a fundamental result of Kalman smoothing and filtering theory. In this work we obtain a new expression for the optimal operator $\hat{S}_s(\cdot|T)$ by finding a closed-form formula for the following proper covariance function,

$$K(s, t|T) = \mathbb{E}[\epsilon_{\hat{S}_s}(s|T)(\epsilon_{\hat{S}_t}(t|T))^*] \in \mathcal{L}(\mathbb{R}^{n,*}, \mathbb{R}^n) \quad (2.12)$$

We show below in Corollary 2.1 that $\hat{S}_s(t|T) = K(s, t|T)H^*(t)R^{-1}(t)$. From a Gaussian process perspective, K can be interpreted as the posterior covariance given \tilde{y} with the Π_0 prior over $x(0)$. The fact that covariances K are also reproducing kernels is well-known since Parzen (1961). Berlinet and Thomas-Agnan (2004, Chapter 2) summarized the deep relations between positive semidefinite kernels and stochastic processes, albeit only in the real-valued case. Kanagawa et al. (2018) also reviewed the connections between kernel methods and Gaussian processes. We meet here a similar relation to the classical “duality” between estimation and control in the Linear-Quadratic-Gaussian setting.

2.3 A DETOUR THROUGH ESTIMATORS

In this section only, we consider infinite-dimensional operators to give the high-level idea before introducing the various quantities studied in the next sections. We will proceed formally, following the introduction of Bensoussan (2018, Chapter 4.5) on finite-dimensional best estimators and the short presentation of Berlinet and Thomas-Agnan (2004, Chapter 2.4) of Hilbert spaces generated by a process with finite second order moments.² For such a process $X = (X_t)_{t \in [0, T]}$, we write \mathcal{C}_X its covariance operator. For simplicity, we

²We voluntarily do not make explicit the set Ω or $[t_0, T]$ over which the processes and functions are defined. The latter can be understood from the context and we refer to the quoted references for the full description.

consider only zero mean processes X, Y and only quantities having finite second order moments. The (Bayesian) minimum mean square estimator is defined as

$$\min_{\hat{X} \in L^2, \Phi \text{ meas.}, \hat{X} = \Phi(Y)} \mathbb{E}((X - \hat{X})^\top (X - \hat{X})). \quad (2.13)$$

where Φ is a measurable function, whence \hat{X} belongs to the space $\bar{\mathcal{N}}(Y)$ of nonlinear functionals of Y . The minimum variance linear estimator instead restricts the search space to the space $\bar{\mathcal{L}}(Y)$ of linear functionals of the process Y

$$\min_{\hat{X} \in L^2, \mathcal{S} \in L^2, \hat{X} = \mathcal{S}Y} \mathbb{E}((X - \hat{X})^\top (X - \hat{X})). \quad (2.14)$$

Gaussian process regression further restricts the search space, by introducing the canonical congruence ψ_Y between the process Y and its RKHS \mathcal{H}_Y , i.e. the linear isomorphism satisfying $\psi_Y((v^\top Y_t)v)(s) = \mathbb{E}[Y_s Y_t^\top]v$ for all $v \in \mathbb{R}^m$

$$\min_{\hat{X} \in L^2, g \in \mathcal{H}_Y, \hat{X} = \psi_Y^{-1}(g)} \mathbb{E}((X - \hat{X})^\top (X - \hat{X})). \quad (2.15)$$

By convex duality, introducing a process Λ which acts as a Lagrange multiplier, the dual problem of (2.14) can be written as

$$\max_{\Lambda \in L^2} \min_{\hat{X} \in L^2, \mathcal{S} \in \bar{\mathcal{L}}(Y)} \mathbb{E}((X - \hat{X})^\top (X - \hat{X})) + \langle \Lambda, \hat{X} - \mathcal{S}Y \rangle_{L^2}. \quad (2.16)$$

Minimizing over \mathcal{S} imposes $\Lambda \in \bar{\mathcal{L}}(Y)^\perp$, the orthogonal space of $\bar{\mathcal{L}}(Y)$ in L^2 . Minimizing over \hat{X} gives $\hat{\Lambda} = \text{proj}_{\Lambda \in \bar{\mathcal{L}}(Y)^\perp} X^\top$. This covector or adjoint process does not exist in the Gaussian process framework because the duality is not taken in L^2 but in \mathcal{H}_Y , seen as self-adjoint. For such orthogonal spaces to appear, one has to work in a larger space than \mathcal{H}_Y , such as L^2 . Similarly, in optimal control, working in the space of absolutely continuous trajectories leads to defining a covector function. Working in the RKHS of linearly controlled trajectories as in Aubin-Frankowski (2021a) bypasses the need of such covector.³

Coming back to (2.14), the first order optimality condition writes as the orthogonality criterion $\mathbb{E}((X - \hat{X})Y^\top) = 0$ which gives that $\hat{\mathcal{S}} = \mathcal{C}_{XY}\mathcal{C}_Y^{-1}$ if \mathcal{C}_Y is invertible. If $Y = \mathcal{H}X + Z$, with invertible $\mathcal{C}_Z = \mathcal{R}$, then \mathcal{C}_Y has an inverse and, setting $\mathcal{C}_\epsilon = \mathcal{C}_X - \mathcal{C}_{\hat{X}, \hat{\mathcal{S}}}$, further assuming \mathcal{C}_X to be invertible and using the Woodbury identity, we obtain that $\hat{\mathcal{S}} = \mathcal{C}_\epsilon \mathcal{H}^\top \mathcal{R}^{-1}$. We note also that for any deterministic $\bar{\lambda}(\cdot) \in L^2([t_0, T], \mathbb{R}^n)$, $\hat{\mathcal{S}}$ also minimizes

$$\min_{\hat{X} \in L^2, \mathcal{S} \in L^2, \hat{X} = \mathcal{S}Y} \mathbb{E}(\|\bar{\lambda}(\cdot)^\top (X - \hat{X})\|_{L^2}^2). \quad (2.17)$$

Defining the deterministic $v(\cdot) = \mathcal{S}^\top \bar{\lambda}(\cdot)$, $\hat{\mathcal{S}}$ minimizes a ‘‘control’’ problem over v , with a specific rewriting for $Y = \mathcal{H}X + Z$,

$$\min_{\mathcal{S} \in L^2, v(\cdot) = \mathcal{S}^\top \bar{\lambda}(\cdot)} \underbrace{\langle \bar{\lambda}(\cdot), \mathcal{C}_X \bar{\lambda}(\cdot) \rangle_{L^2} + \langle v(\cdot), \mathcal{C}_Y v(\cdot) \rangle_{L^2} - 2 \langle \bar{\lambda}(\cdot), \mathcal{C}_{XY} v(\cdot) \rangle_{L^2}}_{\langle \bar{\lambda}(\cdot) - \mathcal{H}^\top v(\cdot), \mathcal{C}_X (\bar{\lambda}(\cdot) - \mathcal{H}^\top v(\cdot)) \rangle_{L^2} + \langle v(\cdot), \mathcal{R} v(\cdot) \rangle_{L^2}}. \quad (2.18)$$

³Note also that the theory of Gaussian processes (GPs), despite being a subfield of Bayesian statistics, does not require to manipulate a proper likelihood function to solve a regression problem. Uncannily we can draw another parallel with linear-quadratic (LQ) optimal control, where introducing value function is not necessary to derive the solution. In a nutshell, the GP (resp. kernel) approach to estimation (resp. control) in the Gaussian (resp. LQ) case does not involve a larger space of functions to work in, but restricts the analysis to the space generated by the process (resp. RKHS). In our context, we will see that one can formally move from stochastic Bayesian GPs to deterministic frequentist kernels by replacing the Brownian noise $dw(t)$ by a control $u(t)dt$. This formal change is related to moving from Itô to Stratonovitch calculus and allows to derive exact properties of the stochastic system such as set invariance based on the deterministic counterpart (Da Prato and Frankowska, 2004), introducing a Stratonovitch drift in case of nonlinear diffusion terms.

Another approach would have been to consider a Bayesian posterior estimate when considering jointly Gaussian processes X, Y . However, as recalled in Kanagawa et al. (2018, p.9 and 16), Bayes' rule is more involved in infinite dimensions and the likelihood may be degenerate as, for \mathcal{C}_X non-invertible, X does not have a density w.r.t. the Lebesgue measure. For invertible joint covariance $\mathcal{C}_{X,Y}$, we have that \mathcal{C}_Y and $\mathcal{C}_\epsilon = \mathcal{C}_X - \mathcal{C}_{XY}\mathcal{C}_Y^{-1}\mathcal{C}_{YX}$ are invertible. The maximum likelihood estimator for a realization $y(\cdot)$ of Y is then obtained through a least squares problem

$$\min_{\hat{x}(\cdot) \in L^2} \left\langle (\hat{x}(\cdot), y(\cdot)), \mathcal{C}_{X,Y}^{-1}(\hat{x}(\cdot), y(\cdot)) \right\rangle_{L^2} = \underbrace{\left\langle \hat{x}(\cdot) - \mathcal{C}_{XY}\mathcal{C}_Y^{-1}y(\cdot), \mathcal{C}_\epsilon^{-1}(\hat{x}(\cdot) - \mathcal{C}_{XY}\mathcal{C}_Y^{-1}y(\cdot)) \right\rangle_{L^2}}_{\left\langle \hat{x}(\cdot), \mathcal{C}_X^{-1}\hat{x}(\cdot) \right\rangle_{L^2} + \left\langle \hat{x}(\cdot) - \mathcal{H}y(\cdot), \mathcal{R}^{-1}(\hat{x}(\cdot) - \mathcal{H}y(\cdot)) \right\rangle_{L^2}} + \left\langle y(\cdot), \mathcal{C}_Y^{-1}y(\cdot) \right\rangle_{L^2}. \quad (2.19)$$

The problem with this approach is that manipulating abstract covariances and continuous linear maps over L^2 can be cumbersome and is not operable. Instead, Schwartz kernel theorem allows us to consider kernels for all these operators. Thus, in the following, we will see formulas very similar to the ones derived in this section, but written explicitly on the time axis and with recursive versions. Formally one can consider in (2.17) the test function $\bar{\lambda}(\cdot) = \delta_s(\cdot)\bar{\lambda}$ for some $\bar{\lambda} \in \mathbb{R}^{n,*}$ to recover (2.11), but we will see that choosing $\bar{\lambda}(\cdot)$ based on the adjoint process $\hat{\Lambda}$ will avoid having to manipulate \mathcal{C}_X in (2.18).

2.4 A RELATED OPTIMAL CONTROL PROBLEM

We return to the formulas of Section 2.2 and start by expressing $\langle \Gamma_S(s|T)\bar{\lambda}, \bar{\lambda} \rangle$ more explicitly,

$$\langle \bar{\lambda}, \epsilon_{\hat{S}_s}(s|T) \rangle = \langle \bar{\lambda}, \tilde{x}(s) \rangle - \int_{t_0}^T \left\langle S_s^*(t|T)\bar{\lambda}, d\tilde{y}(t) \right\rangle = \langle \bar{\lambda}, \tilde{x}(s) \rangle - \int_{t_0}^T \left\langle S_s^*(t|T)\bar{\lambda}, H(t)\tilde{x}(t)dt + db(t) \right\rangle.$$

We seek an expression where \tilde{x} does not appear. We thus introduce the following adjoint equation over an adjoint variable λ_s , a.k.a. the information vector,

$$-\frac{d\lambda_s}{dt} = F^*(t)\lambda_s(t) - H^*(t)S_s^*(t|T)\bar{\lambda}, \quad \lambda_s(T) = \begin{cases} 0 & \text{if } s < T \\ \bar{\lambda} & \text{if } s = T \end{cases}, \quad \lambda_s(s) - \lambda_s(s^+) = \bar{\lambda}, \text{ if } s < T, \quad (2.20)$$

where $\lambda_s(s^+) = \lim_{h \rightarrow s^+} \lambda_s(h)$ with the convention $\lambda_s(T^+) = 0$. Then a simple calculation shows that

$$\begin{aligned} \langle \bar{\lambda}, \epsilon_{\hat{S}_s}(s|T) \rangle &= \langle \bar{\lambda}, \tilde{x}(s) \rangle + \int_{t_0}^T \left\langle -\frac{d\lambda}{dt} - F^*(t)\lambda_s(t), \tilde{x}(t)dt \right\rangle - \int_{t_0}^T \left\langle S_s^*(t|T)\bar{\lambda}, db(t) \right\rangle \\ &= \langle \lambda_s(s) - \lambda_s(s^+), \tilde{x}(s) \rangle + \int_{t_0}^T \left\langle -\frac{d\lambda}{dt}, \tilde{x}(t)dt \right\rangle + \int_{t_0}^T \langle \lambda_s(t), -d\tilde{x}(t) + G(t)dw(t) \rangle - \int_{t_0}^T \left\langle S_s^*(t|T)\bar{\lambda}, db(t) \right\rangle \\ &= \underbrace{\langle \lambda_s(s) - \lambda_s(s^+), \tilde{x}(s) \rangle - [(\lambda_s(\tau), \tilde{x}(\tau))]_0^s - [(\lambda_s(\tau), \tilde{x}(\tau))]_{s^+}^T}_{= \langle \lambda_s(t_0), \xi \rangle} + \int_{t_0}^T \langle G^*(t)\lambda_s(t), dw(t) \rangle - \int_{t_0}^T \left\langle S_s^*(t|T)\bar{\lambda}, db(t) \right\rangle \end{aligned}$$

and therefore

$$\langle \Gamma_S(s|T)\bar{\lambda}, \bar{\lambda} \rangle = \langle \Pi_0\lambda_s(t_0), \lambda_s(t_0) \rangle + \int_{t_0}^T \langle G(t)Q(t)G^*(t)\lambda_s(t), \lambda_s(t) \rangle dt + \int_{t_0}^T \left\langle R(t)S_s^*(t|T)\bar{\lambda}, S_s^*(t|T)\bar{\lambda} \right\rangle dt \quad (2.21)$$

More generally, beyond linear feedbacks ($S_s^*(\cdot|T)\bar{\lambda}$), for a general control input $v(\cdot)$ with $R(\cdot)^{\frac{1}{2}}v(\cdot) \in L^2(t_0, T; \mathbb{R}^m)$, it is natural to consider the following control problem

$$-\frac{d\lambda_s}{dt} = F^*(t)\lambda_s(t) + H^*(t)v(t), \quad \lambda_s(T) = \begin{cases} 0 & \text{if } s < T \\ \bar{\lambda} & \text{if } s = T \end{cases}, \quad \lambda_s(s) - \lambda_s(s^+) = \bar{\lambda}, \text{ if } s < T; \quad (2.22)$$

$$J(v(\cdot)) = \langle \Pi_0 \lambda_s(t_0), \lambda_s(t_0) \rangle + \int_{t_0}^T \langle G(t)Q(t)G^*(t)\lambda_s(t), \lambda_s(t) \rangle dt + \int_{t_0}^T \langle R(t)v(t), v(t) \rangle dt. \quad (2.23)$$

The classical way to solve such a problem is through Pontryagin's Maximum Principle (see e.g. Bensoussan, 2018, Chapter 10), i.e. by using Lagrange-Fenchel duality, which effectively leads to a Hamiltonian system, taking the form of a two-point boundary value problem:

$$\begin{aligned} \frac{d\hat{\gamma}_s}{dt} &= F(t)\hat{\gamma}_s(t) - G(t)Q(t)G^*(t)\hat{\lambda}_s(t) \\ -\frac{d\hat{\lambda}_s}{dt} &= F^*(t)\hat{\lambda}_s(t) + H^*(t)R^{-1}(t)H(t)\hat{\gamma}_s(t) \\ \hat{\gamma}_s(t_0) &= -\Pi_0\hat{\lambda}_s(t_0), \quad \lambda_s(T) = \begin{cases} 0 & \text{if } s < T \\ \bar{\lambda} & \text{if } s = T \end{cases}, \quad \lambda_s(s) - \lambda_s(s^+) = \bar{\lambda}, \text{ if } s < T. \end{aligned} \quad (2.24)$$

and where the optimal control of problem (2.22)-(2.23) is given by

$$\hat{v}_s(t) = R^{-1}(t)H(t)\hat{\gamma}_s(t). \quad (2.25)$$

Since the pair $(\hat{\lambda}_s(t), \hat{\gamma}_s(t))$ depends linearly on $\bar{\lambda}$, we obtain immediately that there exists a single $\hat{S}(t)$ which minimizes (2.21) for any λ , namely

$$\hat{S}_s^*(t|T)\bar{\lambda} = -R^{-1}(t)H(t)\hat{\gamma}_s(t). \quad (2.26)$$

This suggests that one has to solve (2.24) to get an expression of $\hat{S}^*(s, t|T)$.

2.5 A GENERAL TWO-POINT BOUNDARY VALUE PROBLEM

At this stage, rather than coping with the difficulty of dealing with jumps as in (2.24), we consider another two-point boundary value problem similar to (2.24) but which crucially does not depend on s . We also had not so far considered the possibility of having a Gaussian prior with covariance $\Sigma_T \in \mathcal{L}(\mathbb{R}^n, \mathbb{R}^{n,*})$ on the terminal information $\lambda_s(T)$, so we introduce it here for greater generality. Consider the pair $(\hat{\mu}(t), \hat{\nu}(t))$ solution of the coupled system

$$\begin{aligned} \frac{d\hat{\mu}}{dt} &= F(t)\hat{\mu}(t) - G(t)Q(t)G^*(t)\hat{\nu}(t) + l_\mu(t) \\ -\frac{d\hat{\nu}}{dt} &= F^*(t)\hat{\nu}(t) + H^*(t)R^{-1}(t)H(t)\hat{\mu}(t) - l_\nu(t) \\ \hat{\mu}(t_0) &= -\Pi_0\hat{\nu}(t_0), \quad \hat{\nu}(T) = \Sigma_T\hat{\mu}(T). \end{aligned} \quad (2.27)$$

where $\hat{\mu}$ (resp. $\hat{\nu}$) play the role of γ_s (resp. λ_s) and $l_\mu(\cdot) \in L^2(t_0, T; \mathbb{R}^n)$ and $l_\nu(\cdot) \in L^2(t_0, T; \mathbb{R}^{n,*})$ are two test functions acting as perturbations of the differential equations. Notice that, for $l_\mu(\cdot) \equiv 0$ and $l_{\nu,s}(\tau) = -\bar{\lambda}\delta_s(\tau)$, the system (2.24) with a jump condition corresponds precisely to the two-point boundary system (2.27). The important result is the following

Proposition 1. For $\Sigma_T = 0$, $l_\mu(\cdot) \equiv 0$ and $l_\nu(t) = H^*(t)R^{-1}(t)g(t)$ with $g(\cdot) \in L^2(t_0, T; \mathbb{R}^m)$, we have the formula

$$\hat{\mu}(s) = \int_{t_0}^T \hat{S}_s(t|T)g(t)dt. \quad (2.28)$$

Proof. From (2.26) we have

$$\left\langle \bar{\lambda}, \int_{t_0}^T \hat{S}_s(t|T)g(t)dt \right\rangle = - \int_{t_0}^T \left\langle \hat{\gamma}_s(t), H^*(t)R^{-1}(t)g(t) \right\rangle dt$$

We use the second equation of (2.27) and proceed with integration by parts between the systems (2.24) and (2.27). Note that $\hat{\mu}$, $\hat{\nu}$, $\hat{\gamma}_s$ are all continuous functions, but that $\hat{\lambda}_s$ is not, so that we have to split some integrals to take care of the singularity at s as we did before to derive (2.21).

$$\begin{aligned} \left\langle \bar{\lambda}, \int_{t_0}^T \hat{S}_s(t|T)g(t)dt \right\rangle &= \int_{t_0}^T \left\langle \hat{\gamma}_s(t), -\frac{d\hat{\nu}}{dt} - F^*(t)\hat{\nu}(t) - H^*(t)R^{-1}(t)H(t)\hat{\mu}(t) \right\rangle dt \\ &= \int_{t_0}^T \left\langle \hat{\gamma}_s(t), -\frac{d\hat{\nu}}{dt} \right\rangle dt - \int_{t_0}^T \left\langle \frac{d\hat{\gamma}_s}{dt} + G(t)Q(t)G^*(t)\hat{\lambda}_s(t), \hat{\nu}(t) \right\rangle dt + \int_{t_0}^T \left\langle \frac{d\hat{\lambda}_s}{dt} + F^*(t)\hat{\lambda}_s(t), \hat{\mu}(t) \right\rangle dt \\ &= -[\langle \hat{\gamma}_s(t), \hat{\nu}(t) \rangle]_{t=0}^T + \int_{t_0}^T \left\langle \hat{\lambda}_s(t), \frac{d\hat{\mu}}{dt} - F(t)\hat{\mu}(t) \right\rangle dt + \int_{t_0}^T \left\langle \frac{d\hat{\lambda}_s}{dt} + F^*(t)\hat{\lambda}_s(t), \hat{\mu}(t) \right\rangle dt \\ &= - \left\langle \hat{\gamma}_s(T), \underbrace{\hat{\nu}(T)}_{=\Sigma_T \hat{\mu}(T)} = 0 \right\rangle + \langle \hat{\gamma}_s(t_0), \hat{\nu}(t_0) \rangle + \left\langle \hat{\lambda}_s(T), \hat{\mu}(T) \right\rangle \mathbb{1}_{s < T} - \left\langle \hat{\lambda}_s(s^+) - \hat{\lambda}_s(s), \hat{\mu}(s) \right\rangle - \left\langle \hat{\lambda}_s(t_0), \hat{\mu}(t_0) \right\rangle \\ &= \left\langle \hat{\lambda}_s(s) - \hat{\lambda}_s(s^+), \hat{\mu}(s) \right\rangle = \left\langle \bar{\lambda}, \hat{\mu}(s) \right\rangle \end{aligned}$$

□

To derive another formula for $\hat{S}_s(t|T)$, we are now going to find another matrix satisfying (2.28) for all $g(\cdot)$ with $\hat{\mu}(\cdot)$ defined as per (2.27).

3 SOLUTION THROUGH RICCATI EQUATIONS AND KERNELS

3.1 DERIVING THE KERNELS

When $l_\mu(\cdot) \equiv 0$ and $l_\nu(\cdot) \equiv 0$, the classical approach to solve (2.27) is by variation of constants, introducing two matrices $\Sigma(t)$ and $\Pi(t)$ satisfying $\hat{\mu}(t) = -\Pi(t)\hat{\nu}(t)$ and $\hat{\nu}(t) = \Sigma(t)\hat{\mu}(t)$. It is then straightforward to show that they must satisfy two (dual) differential Riccati equations

$$-\frac{d}{dt}\Sigma = \Sigma(t)F(t) + F^*(t)\Sigma(t) - \Sigma(t)G(t)Q(t)G^*(t)\Sigma(t) + H^*(t)R^{-1}(t)H(t), \quad \Sigma(T) = \Sigma_T; \quad (3.1)$$

$$\frac{d}{dt}\Pi = F(t)\Pi(t) + \Pi(t)F^*(t) - \Pi(t)H^*(t)R^{-1}(t)H(t)\Pi(t) + G(t)Q(t)G^*(t), \quad \Pi(t_0) = \Pi_0. \quad (3.2)$$

The information filter matrix $\Sigma(t)$ satisfies a backward equation depending on T whereas the estimation filter matrix $\Pi(t)$ satisfies a forward one and depends on t_0 . The solutions for these equations exist at all times on $[t_0, T]$. This is a classical result which proof we give in Lemma 7 in Appendix A.1.

When $l_\mu(\cdot) \not\equiv 0$ or $l_\nu(\cdot) \not\equiv 0$, we are going instead to follow a Green kernel approach, related to Wiener filtering, and look for kernel integral operators satisfying respectively:⁴

$$\hat{\mu}(s) = \int_{t_0}^T K(s, t|T) l_\nu(t) dt \quad \text{for } l_\mu(\cdot) \equiv 0, \quad (3.3)$$

$$\hat{\nu}(s) = \int_{t_0}^T \Lambda(s, t|T) l_\mu(t) dt \quad \text{for } l_\nu(\cdot) \equiv 0. \quad (3.4)$$

These formulas may recall the ones appearing in the innovations approach (Kailath et al., 2000, Section 16.4.2); however we do not consider cross-covariances between trajectories and observations and will show that K satisfying (3.3) is precisely the covariance of the optimal error (2.12) (see Proposition 5 below). On the other hand Λ as in (3.4) is related to observability problems. To solve (2.27) in general, we can compute the distortion w.r.t. the zero solutions, introducing two variables:

$$r(t) = \hat{\mu}(t) + \Pi(t)\hat{\nu}(t), \quad \eta(t) = \hat{\nu}(t) - \Sigma(t)\hat{\mu}(t) \quad (3.5)$$

From (2.27), (3.1) and (3.2), we deduce that they satisfy the following differential equations⁵

$$\frac{d}{dt}r = (F(t) - \Pi(t)H^*(t)R^{-1}(t)H(t))r(t) + \Pi(t)l_\nu(t) + l_\mu(t), \quad r(t_0) = 0; \quad (3.6)$$

$$-\frac{d}{dt}\eta = (F^*(t) - \Sigma(t)G(t)Q(t)G^*(t))\eta(t) + \Sigma(t)l_\mu(t) - l_\nu(t), \quad \eta(T) = 0. \quad (3.7)$$

This suggests to introduce semigroups associated with the matrix function $F(t) - G(t)Q(t)G^*(t)\Sigma(t)$ denoted $\Phi_{F,\Sigma}(s, t)$ (resp. $F(s) - \Pi(s)H^*(s)R^{-1}(s)H(s)$, denoted $\Phi_{F,\Pi}(s, t)$)

$$\frac{d}{d\tau}\Phi_{F,\Sigma}(\tau, t) = (F(\tau) - G(\tau)Q(\tau)G^*(\tau)\Sigma(\tau))\Phi_{F,\Sigma}(\tau, t), \quad \Phi_{F,\Sigma}(t, t) = \text{Id}; \quad (3.8)$$

$$-\frac{d}{dt}\Phi_{F,\Sigma}^*(\tau, t) = (F^*(t) - \Sigma(t)G(t)Q(t)G^*(t))\Phi_{F,\Sigma}^*(\tau, t), \quad \Phi_{F,\Sigma}^*(t, t) = \text{Id}; \quad (3.9)$$

$$\frac{d}{d\tau}\Phi_{F,\Pi}(\tau, t) = (F(\tau) - \Pi(\tau)H^*(\tau)R^{-1}(\tau)H(\tau))\Phi_{F,\Pi}(\tau, t), \quad \Phi_{F,\Pi}(t, t) = \text{Id}; \quad (3.10)$$

$$-\frac{d}{dt}\Phi_{F,\Pi}^*(\tau, t) = (F^*(t) - H^*(t)R^{-1}(t)H(t)\Pi(\tau t))\Phi_{F,\Pi}^*(\tau, t), \quad \Phi_{F,\Pi}^*(\tau, \tau) = \text{Id}. \quad (3.11)$$

Note that if $Q(\cdot) \equiv 0$ and $\Pi_0 = 0$, then $\Pi(\cdot) \equiv 0$ and $\Phi_{F,\Pi}(t, s) = \Phi_F(t, s)$, the semi-group associated with the operator $F(t)$, i.e. $\partial_t\Phi_F(t, s) = F(t)\Phi_F(t, s)$ and $\Phi_F(t, t) = \text{Id}$. Similarly, if $H(\cdot) \equiv 0$ and $\Sigma_T = 0$, then $\Phi_{F,\Sigma}(t, s) = \Phi_F(t, s)$.

⁴An alternative scheme would be to consider exponentials of the Hamiltonian matrix as in Speyer and Jacobson (2010, Chapter 5). We use and recall this approach in the Appendix A.2 to give a numerical method to evaluate the kernel $K(s, t|T)$.

⁵We give below the computation for (3.6), eq.(3.7) is obtained similarly

$$dr/dt = F\hat{\mu} - GQG^*\hat{\nu} + l_\mu + (F\Pi + \Pi F^* - \Pi H^*R^{-1}H\Pi + GQG^*)\hat{\nu} - \Pi(F^*\hat{\nu} + H^*R^{-1}H\hat{\mu} - l_\nu)$$

Theorem 2. *The kernels K and Λ satisfying (3.3) and (3.4) are given by*

$$K(s, t|T) = \Phi_{F, \Sigma}(s, t_0) \Pi_0^{\frac{1}{2}} (\text{Id} + \Pi_0^{\frac{1}{2}} \Sigma(t_0) \Pi_0^{\frac{1}{2}})^{-1} \Pi_0^{\frac{1}{2}} \Phi_{F, \Sigma}^*(t, t_0) + \int_{t_0}^{\min(s, t)} \Phi_{F, \Sigma}(s, \tau) G(\tau) Q(\tau) G^*(\tau) \Phi_{F, \Sigma}^*(t, \tau) d\tau \quad (3.12)$$

$$\Lambda(s, t|T) = \Phi_{F, \Pi}^*(T, s) \Sigma_T^{\frac{1}{2}} (\text{Id} + \Sigma_T^{\frac{1}{2}} \Pi(T) \Sigma_T^{\frac{1}{2}})^{-1} \Sigma_T^{\frac{1}{2}} \Phi_{F, \Pi}(T, t) + \int_{\max(s, t)}^T \Phi_{F, \Pi}^*(\tau, s) H^*(\tau) R^{-1}(\tau) H(\tau) \Phi_{F, \Pi}(\tau, t) d\tau \quad (3.13)$$

Remark. The matrix inverses we consider always exist since Π_0 , Σ_T , $\Sigma(t_0)$ and $\Pi(T)$ are all positive semidefinite. Note that if Π_0 is invertible, then the first term in K is merely $(\Pi_0^{-1} + \Sigma(t_0))^{-1}$. If $\Sigma_T = 0$, then the first term in Λ vanishes. If furthermore $H(\cdot) \equiv 0$, the observations are then pure Brownian noise independent from the state, and thus dispensable. We hence recover the formula of Särkkä and Solin (2019, Section 6.4, p.89) for the (prior) covariance of a linear SDE. In Kailath et al. (2000, Example 3.3), the case $G(\cdot) \equiv 0$ was further discussed (see also Section 4.2) as it makes the second term in K vanish. Both kernels satisfy a Hermitian symmetry, i.e. $K(s, t|T) = K(t, s|T)^\top$. In Appendix A.2, we give a numerical method to evaluate the kernel $K(s, t|T)$ through the Hamiltonian semigroup. For time-invariant systems, this boils down to matrix exponentials.

Proof. Let us first identify K . By the variation of constants formula, (3.7) yields

$$\hat{\nu}(t) - \Sigma(t) \hat{\mu}(t) = \eta(t) = \int_t^T \Phi_{F, \Sigma}^*(\tau, t) (\Sigma(\tau) l_\mu(\tau) - l_\nu(\tau)) d\tau. \quad (3.14)$$

Consequently (2.27) becomes

$$\frac{d\hat{\mu}}{dt} = F(t) \hat{\mu}(t) - G(t) Q(t) G^*(t) \left(\Sigma(t) \hat{\mu}(t) + \int_t^T \Phi_{F, \Sigma}^*(\tau, t) (\Sigma(\tau) l_\mu(\tau) - l_\nu(\tau)) d\tau \right) + l_\mu(t) \quad (3.15)$$

Now consider the case where $l_\mu(\cdot) \equiv 0$. Introducing the square root $\Pi_0^{\frac{1}{2}}$, the variation of constants formula gives

$$\begin{aligned} \hat{\mu}(s) &= \Phi_{F, \Sigma}(s, t_0) \hat{\mu}(t_0) + \int_{t_0}^s \Phi_{F, \Sigma}(s, t) G(t) Q(t) G^*(t) \int_t^T \Phi_{F, \Sigma}^*(\tau, t) l_\nu(\tau) d\tau dt \\ &= -\Phi_{F, \Sigma}(s, t_0) \Pi_0^{\frac{1}{2}} \Pi_0^{\frac{1}{2}} \hat{\nu}(t_0) + \int_{t_0}^T \int_{t_0}^{\min(s, t)} \Phi_{F, \Sigma}(s, \tau) G(\tau) Q(\tau) G^*(\tau) \Phi_{F, \Sigma}^*(t, \tau) l_\nu(t) d\tau dt. \end{aligned} \quad (3.16)$$

To compute $\hat{\nu}(t_0)$, we use (3.14)

$$(\text{Id} + \Pi_0^{\frac{1}{2}} \Sigma(t_0) \Pi_0^{\frac{1}{2}}) \Pi_0^{\frac{1}{2}} \hat{\nu}(t_0) = \Pi_0^{\frac{1}{2}} (\hat{\nu}(t_0) + \Sigma(t_0) \Pi_0 \hat{\nu}(t_0)) = -\Pi_0^{\frac{1}{2}} \int_0^T \Phi_{F, \Sigma}^*(\tau, t_0) l_\nu(\tau) d\tau. \quad (3.17)$$

Inserting (3.17) in (3.16), we then identify K through (3.3) which yields (3.12).

Now for Λ , the procedure is the same, (3.6) and (2.27) yield

$$\hat{\mu}(t) + \Pi(t) \hat{\nu}(t) = r(t) = \int_{t_0}^t \Phi_{F, \Pi}(t, \tau) (\Pi(\tau) l_\nu(\tau) + l_\mu(\tau)) d\tau, \quad (3.18)$$

$$-\frac{d\hat{\nu}}{dt} = F^*(t) \hat{\nu}(t) + H^*(t) R^{-1}(t) H(t) \left(-\Pi(t) \hat{\nu}(t) + \int_{t_0}^t \Phi_{F, \Pi}(t, \tau) (\Pi(\tau) l_\nu(\tau) + l_\mu(\tau)) d\tau \right) - l_\nu(t). \quad (3.19)$$

Now consider the case where $l_\nu(\cdot) \equiv 0$,

$$\begin{aligned}\hat{\nu}(s) &= \Phi_{F,\Pi}^*(T, s)\hat{\nu}(T) + \int_t^T \Phi_{F,\Pi}^*(t, s)H^*(t)R^{-1}(t)H(t) \int_{t_0}^t \Phi_{F,\Pi}(t, \tau)l_\mu(\tau)d\tau dt \\ &= \Phi_{F,\Pi}^*(T, s)\Sigma_T^{\frac{1}{2}}\Sigma_T^{\frac{1}{2}}\hat{\mu}(T) + \int_{t_0}^T \int_{\max(s,t)}^T \Phi_{F,\Pi}^*(\tau, s)H^*(\tau)R^{-1}(\tau)H(\tau)\Phi_{F,\Pi}(\tau, t)d\tau l_\mu(t)dt.\end{aligned}\quad (3.20)$$

To compute $\hat{\mu}(T)$, we use (3.18)

$$(\text{Id} + \Sigma_T^{\frac{1}{2}}\Pi(T)\Sigma_T^{\frac{1}{2}})\Sigma_T^{\frac{1}{2}}\hat{\mu}(T) = \Sigma_T^{\frac{1}{2}}(\hat{\mu}(T) + \Pi(T)\Pi_0\hat{\mu}(T)) = -\Sigma_T^{\frac{1}{2}} \int_0^T \Phi_{F,\Pi}(\tau, t_0)l_\nu(\tau)d\tau.\quad (3.21)$$

Inserting (3.21) in (3.20), we then identify Λ through (3.4) which yields (3.13). \square

By Proposition 1, we have shown (2.28) which matches with (3.3) and should hold for all test functions $g(\cdot) \in L^2(t_0, T; \mathbb{R}^m)$, so we deduce immediately that:

Corollary 2.1. *If $\Sigma_T = 0$, then, for all $s, t \in [t_0, T]$, we have the formula*

$$\hat{S}_s(t|T) = K(s, t|T)H^*(t)R^{-1}(t).\quad (3.22)$$

3.2 CONTROL INTERPRETATION AS IMPULSE RESPONSE

A natural quantity to consider in (3.3) is the impulse-response for $l_\nu(\tau) = z\delta_t(\tau)$ and some $z \in \mathbb{R}^{n,*}$, which gives $x_{zt}(s) = K(s, t|T)z$. Now (2.27) then writes as

$$\begin{aligned}\frac{d}{d\tau}x_{zt}(\tau) &= F(\tau)x_{zt}(\tau) - G(\tau)Q(\tau)G^*(\tau)\nu_{zt}(\tau) \\ -\frac{d}{d\tau}\nu_{zt}(\tau) &= F^*(\tau)\nu_{zt}(\tau) + H^*(\tau)R^{-1}(\tau)H(\tau)x_{zt}(\tau) - z\delta_t(\tau) \\ x_{zt}(t_0) &= -\Pi_0\nu_{zt}(t_0), \quad \nu_{zt}(T) = \Sigma_T x_{zt}(T),\end{aligned}\quad (3.23)$$

where the discontinuity occurs in the second line rather than the first. This, we are going to reverse through a change of variables. Considering the function $\chi_{zt}(\tau)$ solution of

$$-\frac{d}{d\tau}\chi_{zt}(\tau) = F^*(\tau)\chi_{zt}(\tau), \tau < t, \quad \chi_{zt}(t) = z\quad (3.24)$$

we can write formally that $\chi_{zt}(\tau)\mathbb{1}_{\tau < t}$ is solution of

$$-\frac{d}{d\tau}(\chi_{zt}(\tau)\mathbb{1}_{\tau < t}) = F^*(\tau)(\chi_{zt}(\tau)\mathbb{1}_{\tau < t}) + z\delta_t(\tau), \quad \chi_{zt}(T)\mathbb{1}_{T < t} = 0\quad (3.25)$$

With $l_\nu(\tau) = z\delta_t(\tau)$, we define $q_{zt}(\tau) = \psi(\tau) + \chi_{zt}(\tau)\mathbb{1}_{\tau < t}$, then from (3.23) the pair $x_{zt}(\tau), q_{zt}(\tau)$ is solution of the system

$$\begin{aligned}\frac{d}{d\tau}x_{zt}(\tau) &= F(\tau)x_{zt}(\tau) - G(\tau)Q(\tau)G^*(\tau)q_{zt}(\tau) + G(\tau)Q(\tau)G^*(\tau)\chi_{zt}(\tau)\mathbb{1}_{\tau < t} \\ -\frac{d}{d\tau}q_{zt}(\tau) &= F^*(\tau)q_{zt}(\tau) + H^*(\tau)R^{-1}(\tau)H(\tau)x_{zt}(\tau) \\ x_{zt}(t_0) &= -\Pi_0q_{zt}(t_0) + \Pi_0\chi_{zt}(t_0), \quad q_{zt}(T) = \Sigma_T x_{zt}(T).\end{aligned}\quad (3.26)$$

Similarly to (2.23), we interpret the system (3.26) as the necessary and sufficient optimality condition of the following control problem

$$\frac{d}{d\tau}\zeta(\tau) = F(\tau)\zeta(\tau) + G(\tau)Q^{\frac{1}{2}}(\tau)v(\tau) + G(\tau)Q(\tau)G^*(\tau)\chi_{zt}(\tau)\mathbb{1}_{\tau < t}, \quad \zeta(t_0) = \Pi_0^{\frac{1}{2}}\xi + \Pi_0\chi_{zt}(t_0) \quad (3.27)$$

in which $v(\cdot)$ and ξ are controls, and the objective to minimize is

$$J_x(\xi, v(\cdot)) = \|\xi\|^2 + \langle \Sigma_T \zeta(T), \zeta(T) \rangle + \int_{t_0}^T \|v(\tau)\|^2 d\tau + \int_{t_0}^T \langle H^*(\tau)R^{-1}(\tau)H(\tau)\zeta(\tau), \zeta(\tau) \rangle d\tau \quad (3.28)$$

If we call $x_{zt}(\tau)$ the optimal state and define $q_{zt}(\tau)$ as in (3.26) we obtain by standard methods that the optimal controls $\hat{\xi}$ and $\hat{v}(\cdot)$ are given by

$$\hat{\xi} = -\Pi_0^{\frac{1}{2}}q_{zt}(t_0), \quad \hat{v}(\tau) = -Q^{\frac{1}{2}}(\tau)G^*(\tau)q_{zt}(\tau) \quad (3.29)$$

and the pair $x_{zt}(\tau), q_{zt}(\tau)$ solves (3.26).

4 IDENTIFYING THE RKHS

We can draw a parallel between the above reasoning of Section 3.2 and going from a partial differential equation (PDE) to its calculus of variations formulation. Similarly, to solve a linear PDE one can look for its Green kernel, a.k.a. its fundamental solution. This is precisely what we have done in (2.5) for (2.27). Now we will take advantage of (3.28) to identify the spaces of functions we are optimizing over. This is the same thing as identifying the reproducing kernel Hilbert spaces of the kernels of Theorem 2. In general it is a hard task given a PDE to find its Green kernel and the vector space of functions where the solutions live (Saitoh and Sawano, 2016, Chapter 1). But this task will be made much simpler owing to the fact that we are not looking at any Hilbert space, but at an RKHS:

Definition 1. Let \mathcal{T} be a non-empty set. A Hilbert space $(\mathcal{H}_K(\mathcal{T}), \langle \cdot, \cdot \rangle_K)$ of \mathbb{R}^n -vector-valued functions defined on \mathcal{T} is called a vRKHS if there exists a matrix-valued kernel $K_{\mathcal{T}} : \mathcal{T} \times \mathcal{T} \rightarrow \mathcal{L}(\mathbb{R}^{n,*}, \mathbb{R}^n)$ such that the *reproducing property* holds: for all $t \in \mathcal{T}$, $\mathbf{p} \in \mathbb{R}^{n,*}$, we have $K_{\mathcal{T}}(\cdot, t)\mathbf{p} \in \mathcal{H}_K(\mathcal{T})$ and for all $\mathbf{f} \in \mathcal{H}_K(\mathcal{T})$, $\mathbf{p}^\top \mathbf{f}(t) = \langle \mathbf{f}, K_{\mathcal{T}}(\cdot, t)\mathbf{p} \rangle_K$.

Remark: It is well-known that by Riesz's theorem, an equivalent definition of a vRKHS is that, for every $t \in \mathcal{T}$ and $\mathbf{p} \in \mathbb{R}^n$, the evaluation functional $\mathbf{f} \in \mathcal{H}_K(\mathcal{T}) \mapsto \mathbf{p}^\top \mathbf{f}(t) \in \mathbb{R}$ is continuous. There is also a one-to-one correspondence between the kernel $K_{\mathcal{T}}$ and the vRKHS $(\mathcal{H}_K(\mathcal{T}), \langle \cdot, \cdot \rangle_K)$ (see e.g. Micheli and Glaunès, 2014, Theorem 2.6). Moreover, by symmetry of the scalar product, the matrix-valued kernel has a Hermitian symmetry, i.e. $K_{\mathcal{T}}(s, t) = K_{\mathcal{T}}(t, s)^\top$ for any $s, t \in \mathcal{T}$.

4.1 K: A PRIMAL RKHS OF TRAJECTORIES

We want to show that to the kernel $K(s, t|T)$ defined in (3.12),

$$K(s, t|T) = \Phi_{F, \Sigma}(s, t_0)\Pi_0^{\frac{1}{2}}(\text{Id} + \Pi_0^{\frac{1}{2}}\Sigma(t_0)\Pi_0^{\frac{1}{2}})^{-1}\Pi_0^{\frac{1}{2}}\Phi_{F, \Sigma}^*(t, t_0) + \int_{t_0}^{\min(s, t)} \Phi_{F, \Sigma}(s, \tau)G(\tau)Q(\tau)G^*(\tau)\Phi_{F, \Sigma}^*(t, \tau)d\tau \quad (4.1)$$

we can associate a Hilbert space, for which it is the reproducing kernel. As intuited from (3.27), it is a space of functions in $H^1(t_0, T; \mathbb{R}^n)$ defined as follows

$$\mathcal{S}_{[t_0, T]}^x = \{x(\cdot) \in H^1(t_0, T; \mathbb{R}^n) | \exists v(\cdot) \in L^2(t_0, T; \mathbb{R}^p), \xi \in \mathbb{R}^n \text{ s.t.} \\ \frac{d}{d\tau} x = F(\tau)x(\tau) + G(\tau)Q^{\frac{1}{2}}(\tau)v(\tau), x(t_0) = \Pi_0^{\frac{1}{2}}\xi\} \quad (4.2)$$

Recall that we only required $R(\cdot)$ to be invertible, improving over Aubin-Frankowski and Bensoussan (2022). For a given trajectory $x(\cdot)$, in case there are several pairs $(v(\cdot), \xi)$ which satisfy the relations (4.2) we call the representative of $x(\cdot)$ the pair with minimal norm $\int_{t_0}^T \|v(t)\|^2 dt + \|\xi\|^2$. It is uniquely defined. We can identify this representative as the unique pair $(v(\cdot), \xi)$ satisfying (4.2) for a given $x(\cdot)$ and

$$\int_{t_0}^T \langle v(s), \tilde{v}(s) \rangle ds = 0, \langle \xi, \tilde{\xi} \rangle = 0, \forall \tilde{v}(\cdot), \tilde{\xi} \text{ such that } G(s)Q^{\frac{1}{2}}(s)\tilde{v}(\cdot) = 0, \text{ a.e. } s \in (t_0, T), \Pi_0^{\frac{1}{2}}\tilde{\xi} = 0 \quad (4.3)$$

The vector space $\mathcal{S}_{[t_0, T]}^x$ is a subspace of the Sobolev space $H^1(t_0, T; \mathbb{R}^n)$. We equip $\mathcal{S}_{[t_0, T]}^x$ with a scalar product derived from (3.28)

$$\langle x^1(\cdot), x^2(\cdot) \rangle_{\mathcal{S}_{[t_0, T]}^x} = \langle \xi^1, \xi^2 \rangle + \langle \Sigma_T x^1(T), x^2(T) \rangle + \int_{t_0}^T \langle v^1(s), v^2(s) \rangle ds + \int_{t_0}^T \langle H^*(s)R^{-1}(s)H(s)x^1(s), x^2(s) \rangle ds \quad (4.4)$$

where $\xi^1, v^1(\cdot); \xi^2, v^2(\cdot)$ are the representatives of $x^1(\cdot), x^2(\cdot)$ respectively.

Theorem 3. *The vector space $(\mathcal{S}_{[t_0, T]}^x, \langle \cdot, \cdot \rangle_{\mathcal{S}_{[t_0, T]}^x})$ is a reproducing kernel Hilbert space, and $K(s, t|T)$ defined by (3.12) is its corresponding reproducing kernel.*

Proof. The vector space $(\mathcal{S}_{[t_0, T]}^x, \langle \cdot, \cdot \rangle_{\mathcal{S}_{[t_0, T]}^x})$ is a Hilbert space, since every Cauchy sequence converges within. Indeed, if we consider a Cauchy sequence $(x^k(\cdot))_{k \in \mathbb{N}}$ in $\mathcal{S}_{[t_0, T]}^x$, namely for which there exists $(v^k(\cdot), \xi^k)$, which is the representative of $x^k(\cdot)$, satisfying

$$\frac{d}{ds} x^k = F(s)x^k(s) + G(s)Q^{\frac{1}{2}}(s)v^k(s), \quad x^k(t_0) = \Pi_0^{\frac{1}{2}}\xi^k$$

and

$$\|\xi^k - \xi^l\|^2 + \|\Sigma_T^{\frac{1}{2}}(x^k(T) - x^l(T))\|^2 + \int_{t_0}^T \|v^k(s) - v^l(s)\|^2 ds \\ + \int_{t_0}^T \langle H^*(s)R^{-1}(s)H(s)(x^k(s) - x^l(s)), (x^k(s) - x^l(s)) \rangle ds \xrightarrow[k, l \rightarrow +\infty]{} 0.$$

Consequently $\xi^k, v^k(\cdot)$ are Cauchy sequences in $\mathbb{R}^n, L^2(t_0, T; \mathbb{R}^m)$ respectively, so $\xi^k \rightarrow \xi, v^k(\cdot) \rightarrow v(\cdot)$ and necessarily $x^k(\cdot) \rightarrow x(\cdot)$ in $H^1(t_0, T; \mathbb{R}^n)$ with

$$\frac{d}{ds} x = F(s)x(s) + G(s)Q^{\frac{1}{2}}(s)v(s), \quad x(t_0) = \Pi_0^{\frac{1}{2}}\xi$$

Since $(\xi^k, v^k(\cdot))$ are the representatives of $x^k(\cdot)$ they satisfy

$$\int_{t_0}^T \langle v^k(s), \tilde{v}(s) \rangle ds = 0, \quad \langle \xi^k, \tilde{\xi} \rangle = 0$$

for any pair $(\tilde{v}(\cdot), \tilde{\xi})$ such that $G(s)Q^{\frac{1}{2}}(s)\tilde{v}(s) = 0$, a.e. $s \in (t_0, T)$, $\Pi_0^{\frac{1}{2}}\tilde{\xi} = 0$. But then $(v(\cdot), \xi)$ satisfy also $\int_{t_0}^T \langle v(s), \tilde{v}(s) \rangle ds = 0$, $\langle \xi, \tilde{\xi} \rangle = 0$, which implies that $(v(\cdot), \xi)$ is the representative of $x(\cdot)$. Hence $x^n(\cdot) \rightarrow x(\cdot)$ in the sense of the norm of $\mathcal{S}_{[t_0, T]}^x$ and $\mathcal{S}_{[t_0, T]}^x$ is a Hilbert space. We now want to show that $\mathcal{S}_{[t_0, T]}^x$ is a RKHS and that its corresponding kernel is $K(s, t|T)$. We must check two facts as per Definition 1

$$K(\cdot, t|T)z \in \mathcal{S}_{[t_0, T]}^x \quad (4.5)$$

$$\langle x(\cdot), K(\cdot, t|T)z \rangle_{\mathcal{S}_{[t_0, T]}^x} = \langle x(t), z \rangle, \forall x(\cdot) \in \mathcal{S}_{[t_0, T]}^x, t \in [t_0, T], z \in \mathbb{R}^{n,*} \quad (4.6)$$

By definition, $K(\cdot, t)z = x_{zt}(\cdot)$. Now, from formulas (3.26) $x_{zt}(\cdot)$ belongs to $\mathcal{S}_{[t_0, T]}^x$, with

$$v_{zt}(\tau) = -Q^{\frac{1}{2}}(\tau)G^*(\tau)q_{zt}(\tau) + Q^{\frac{1}{2}}(\tau)G^*(\tau)\chi_{zt}(\tau)\mathbb{1}_{\tau < t}, \quad \xi_{zt} = -\Pi_0^{\frac{1}{2}}q_{zt}(t_0) + \Pi_0^{\frac{1}{2}}\chi_{zt}(t_0) \quad (4.7)$$

We claim that $(v_{zt}(\cdot), \xi_{zt})$ is the representative of $x_{zt}(\cdot)$. Indeed the pair $(v_{zt}(\cdot), \xi_{zt})$ satisfies (4.3) by using a transposition. It remains to check (4.6). Consider $x(\cdot) \in \mathcal{S}_{[t_0, T]}^x$, such that

$$\frac{d}{d\tau}x = F(\tau)x(\tau) + G(\tau)Q^{\frac{1}{2}}(\tau)v(\tau), x(t_0) = \Pi_0^{\frac{1}{2}}\xi$$

assuming that $(v(\cdot), \xi)$ is the representative. We have

$$\begin{aligned} \langle x(\cdot), x_{zt}(\cdot) \rangle_{\mathcal{S}_{[t_0, T]}^x} &= \left\langle \xi, (-\Pi_0^{\frac{1}{2}}q_{zt}(t_0) + \Pi_0^{\frac{1}{2}}\chi_{zt}(t_0)) \right\rangle + \langle \Sigma_T x(T), x_{zt}(T) \rangle \\ &+ \int_{t_0}^T \left\langle v(\tau), -Q^{\frac{1}{2}}(\tau)G^*(\tau)q_{zt}(\tau) + Q^{\frac{1}{2}}(\tau)G^*(\tau)\chi_{zt}(\tau)\mathbb{1}_{\tau < t} \right\rangle d\tau + \int_{t_0}^T \left\langle H^*(\tau)R^{-1}(\tau)H(\tau)x(\tau), x_{zt}(\tau) \right\rangle d\tau \end{aligned}$$

Using relations (3.26) and the equation for $x(\cdot)$ with integration by parts, it is easy to conclude that

$$\begin{aligned} \langle x(\cdot), x_{zt}(\cdot) \rangle_{\mathcal{S}_{[t_0, T]}^x} &= \langle x(t_0), \chi_{zt}(t_0) - q_{zt}(t_0) \rangle + \langle x(T), q_{zt}(T) \rangle + \int_{t_0}^T \left\langle \frac{d}{d\tau}x(\tau) - F(\tau)x(\tau), \chi_{zt}(\tau)\mathbb{1}_{\tau < t} - q_{zt}(\tau) \right\rangle d\tau \\ &+ \int_{t_0}^T \left\langle x(\tau), -\frac{d}{d\tau}q_{zt}(\tau) - F^*(\tau)q_{zt}(\tau) \right\rangle d\tau \\ &= [\langle x(\tau), q_{zt}(\tau) \rangle]_{\tau=T}^{t_0} + \langle x(T), q_{zt}(T) \rangle + \int_{t_0}^t \left\langle \frac{d}{d\tau}x(\tau), \chi_{zt}(\tau) \right\rangle d\tau + \int_{t_0}^t \left\langle x(\tau), \frac{d}{d\tau}\chi_{zt}(\tau) \right\rangle d\tau = \langle x(t), z \rangle \end{aligned}$$

which proves (4.6) and concludes the proof of the theorem. \square

Remark (No measurements and Gramian of controllability). In the simpler case where $\Sigma_T = 0$, $H(\cdot) \equiv 0$, we have that $\Sigma(\cdot) \equiv 0$. For $\Pi_0 = 0$ and $Q(\cdot) \equiv \text{Id}$, (3.28) becomes $J_x(\xi, v(\cdot)) = \int_{t_0}^T \|v(\tau)\|^2 d\tau$ and we obtain

$$K(T, T|T) = \int_{t_0}^T \Phi_F(T, \tau)G(\tau)Q(\tau)G^*(\tau)\Phi_F^*(T, \tau)d\tau$$

which is precisely the Gramian of controllability. Its straightforward relation with kernels for optimal control was further discussed in Aubin-Frankowski (2021a, p8).

4.2 Λ : A DUAL RKHS OF INFORMATION VECTORS

We have seen with formula (2.26) that the optimal operator $\hat{S}_s(t|T)$ is directly related to an optimal control problem (2.22),(2.23). This problem concerns a backward evolution. Similarly, formula (2.28) has been related to a two-point boundary value problem (2.27). This one is easily interpreted as the necessary and sufficient conditions of optimality of another control problem, namely

$$-\frac{d}{dt}\lambda(t) = F^*(t)\lambda(t) + H^*(t)v(t), \quad \lambda(T) = \Sigma_T^{\frac{1}{2}}z \quad (4.8)$$

and the payoff to minimize is a slight variation of (2.23),

$$J_\lambda(z, v(\cdot)) = \langle \Pi_0 \lambda(t_0), \lambda(t_0) \rangle + \|z\|^2 + \int_{t_0}^T \langle G(t)Q(t)G^*(t)\lambda(t), \lambda(t) \rangle dt + \int_{t_0}^T \langle R(t)v(t), v(t) \rangle dt \quad (4.9)$$

Recall that we did not require Σ_T to be invertible but that $R(t)$ is invertible. These problems lead to the kernel

$$\Lambda(s, t|T) = \Phi_{F,\Pi}^*(T, s) \Sigma_T^{\frac{1}{2}} (\text{Id} + \Sigma_T^{\frac{1}{2}} \Pi(T) \Sigma_T^{\frac{1}{2}})^{-1} \Sigma_T^{\frac{1}{2}} \Phi_{F,\Pi}(T, t) + \int_{\max(s,t)}^T \Phi_{F,\Pi}^*(\tau, s) H^*(\tau) R^{-1}(\tau) H(\tau) \Phi_{F,\Pi}(\tau, t) d\tau \quad (4.10)$$

and a space of information vectors $\mathcal{S}_{[t_0, T]}^\lambda$

$$\mathcal{S}_{[t_0, T]}^\lambda = \{ \lambda(\cdot) \in H^1(t_0, T; \mathbb{R}^n) \mid v(\cdot) \in L^2(t_0, T; \mathbb{R}^m), z \in \mathbb{R}^n \text{ s.t.} \\ -\frac{d}{dt}\lambda(t) = F^*(t)\lambda(t) + H^*(t)v(t), \lambda(T) = \Sigma_T^{\frac{1}{2}}z \} \quad (4.11)$$

Again if there are several $v(\cdot)$ for the same trajectory $\lambda(\cdot)$, we define the representative of $\lambda(\cdot)$ as the unique $v(\cdot)$ satisfying (4.11) which minimizes $\int_{t_0}^T \langle R(t)v(t), v(t) \rangle dt$. We then equip $\mathcal{S}_{[t_0, T]}^\lambda$ with the inner product derived from the quadratic form (4.9).

Theorem 4. *The Hilbert space $(\mathcal{S}_{[t_0, T]}^\lambda, \langle \cdot, \cdot \rangle_{\mathcal{S}_{[t_0, T]}^\lambda})$ is a reproducing kernel Hilbert space and the corresponding kernel is $\Lambda(s, t|T)$.*

Proof. The proof is exactly the same as that of Theorem 3, noticing that the RKHS $\mathcal{S}_{[t_0, T]}^x$ corresponds to $\mathcal{S}_{[t_0, T]}^\lambda$ when considering the permutations $t \leftrightarrow T - (t - t_0)$, $F(t) \leftrightarrow F^*(t)$, $\Pi_0 \leftrightarrow \Sigma_T$, $G(t)Q^{\frac{1}{2}}(t) \leftrightarrow H^*(t)R^{-\frac{1}{2}}(t)$. \square

Remark (No plant noise and Gramian of observability). In the simpler case where $\Pi_0 = 0$, $G(\cdot) \equiv 0$, we have that $\Pi(\cdot) \equiv 0$ (and a finite-dimensional $\mathcal{S}_{[t_0, T]}^x$). For $\Sigma_T = 0$ and $R(\cdot) \equiv \text{Id}$, (4.9) becomes $J_\lambda(z, v(\cdot)) = \int_{t_0}^T \|v(t)\|^2 dt$ and we obtain

$$\Lambda(t_0, t_0|T) = \int_{t_0}^T \Phi_F^*(\tau, t_0) H^*(\tau) H(\tau) \Phi_F(\tau, t_0) d\tau$$

which is precisely the Gramian of observability. This setting is discussed in Kailath et al. (2000, Example 16.3.3). The covector $\lambda(\cdot)$, through its interpretation as a Lagrange multiplier as in Section 2.3, is related to a notion of sensitivity of the solution \hat{x} to the ‘‘constraints’’ $(y_t)_{t \in [0, T]}$, and thus here to the ability to recover x_0 from the observations.

4.3 K AS ERROR COVARIANCE, FORMULAS RELATING K AND Λ

We can now prove the claimed result (2.12) stating that the kernel K corresponds to the covariance of the error. We can also relate through a simple formula the two kernels K and Λ .

Proposition 5. *Let $\Sigma_T = 0$ and recall that $\epsilon_{\hat{S}_s}(s|T) = x(s) - \hat{x}(s|T)$, then*

$$K(s, t|T) = \mathbb{E}[\epsilon_{\hat{S}_s}(s|T)(\epsilon_{\hat{S}_t}(t|T))^*] \quad (4.12)$$

Moreover, we have, for all $s, t \in [0, T]$,

$$K(s, t|T) = \Pi(s)\Phi_{F,\Pi}^*(t, s)\mathbb{1}_{s \leq t} + \Phi_{F,\Pi}(s, t)\Pi(t)\mathbb{1}_{s > t} - \Pi(s)\Lambda(s, t|T)\Pi(t). \quad (4.13)$$

In particular $K(T, T|T) = \Pi(T)$.

Equation (4.13) can be seen as an extension to $s \neq t$ of Bryson-Frazier formulas (Kailath et al., 2000, Theorem 16.5.1). For $s = t$, it gives that $\mathbb{E}[\epsilon_{\hat{S}_s}(s|T)(\epsilon_{\hat{S}_s}(s|T))^*] \preceq \Pi(s) = \mathbb{E}[\epsilon_{\hat{S}_s}(s|s)(\epsilon_{\hat{S}_s}(s|s))^*]$. In other words, observations on the interval $[s, T]$ allow to lower the variance of the error at time s . For $t = T$ and $\Sigma_T = 0$, $\Lambda(s, T|T) = 0$ and we recover the result of Kailath et al. (2000, Lemma 16.5.1).

Proof. Since for $l_\mu(\cdot) \equiv 0$ and $l_{\nu,s}(\tau) = -\bar{\lambda}\delta_s(\tau)$, the system (2.24) with a jump condition corresponds to the two-point boundary system (2.27). With the same computations that led to (2.21), using (2.26) then integration by parts, we obtain that

$$\begin{aligned} \left\langle \mathbb{E}[\epsilon_{\hat{S}_s}(s|T)(\epsilon_{\hat{S}_s}(t|T))^*]\bar{\lambda}, \bar{\lambda} \right\rangle &= \langle \Pi_0 \lambda_s(t_0), \lambda_t(t_0) \rangle + \int_{t_0}^T \langle G(\tau)Q(\tau)G^*(\tau)\lambda_s(\tau), \lambda_t(\tau) \rangle d\tau \\ &\quad + \int_{t_0}^T \left\langle H^*(\tau)R^{-1}(\tau)H(\tau)\hat{\gamma}_s(\tau)\bar{\lambda}, \hat{\gamma}_t(\tau) \right\rangle d\tau \\ &\stackrel{(2.24)}{=} -\langle \lambda_s(t_0), \hat{\gamma}_t(t_0) \rangle + \int_{t_0}^T \left\langle \lambda_s(\tau), F(\tau)\hat{\gamma}_s(\tau) - \frac{d\hat{\gamma}_s}{du} \right\rangle d\tau - \int_{t_0}^T \left\langle \frac{d\hat{\lambda}_s}{du} + F^*(\tau)\hat{\lambda}_s(\tau), \hat{\gamma}_t(\tau) \right\rangle d\tau \\ &= -\langle \lambda_s(t_0), \hat{\gamma}_t(t_0) \rangle - [\langle \lambda_s(\tau), \hat{\gamma}_t(\tau) \rangle]_0^s - [\langle \lambda_s(\tau), \hat{\gamma}_t(\tau) \rangle]_{s^+}^T \stackrel{(2.24)}{=} -\langle \bar{\lambda}, \hat{\gamma}_t(s) \rangle \stackrel{(3.3)}{=} \langle \bar{\lambda}, K(s, t|T)\bar{\lambda} \rangle \end{aligned}$$

This proves (4.12). For (4.13), define $r_t(\tau) = \hat{\gamma}_t(\tau) + \Pi(\tau)\lambda_t(\tau)$ as in (3.5). Then similarly to (3.18)-(3.19)

$$r_t(\tau) = -\int_{t_0}^\tau \Phi_{F,\Pi}(\tau, u)(\Pi(u)\bar{\lambda}\delta_t(u))du = -\Phi_{F,\Pi}(\tau, t)\Pi(t)\mathbb{1}_{\tau > t}\bar{\lambda}. \quad (4.14)$$

$$-\frac{d}{d\tau}\lambda_t = (F^*(\tau) - H^*(\tau)R^{-1}(\tau)H(\tau))\lambda_t(\tau) + \bar{\lambda}\delta_t(\tau) - H^*(\tau)R^{-1}(\tau)H(\tau)\Phi_{F,\Pi}(\tau, t)\Pi(t)\mathbb{1}_{\tau > t}\bar{\lambda}. \quad (4.15)$$

Consequently, by the variation of constants formula,

$$\lambda_t(s) = \Phi_{F,\Pi}^*(t, s)\bar{\lambda}\mathbb{1}_{s \leq t} - \int_{\max(s,t)}^T \Phi_{F,\Pi}^*(\tau, s)H^*(\tau)R^{-1}(\tau)H(\tau)\Phi_{F,\Pi}(\tau, t)\Pi(t)\bar{\lambda}d\tau. \quad (4.16)$$

Since $\langle \bar{\lambda}, K(s, t|T)\bar{\lambda} \rangle = -\langle \bar{\lambda}, \hat{\gamma}_t(s) \rangle = \langle \bar{\lambda}, \Pi(s)\lambda_t(s) - r_t(s) \rangle$, (4.14)-(4.16) yield (4.13). \square

Remark (Relation with Fisher information). From (4.12), we know that the kernel K is the optimal error covariance for linear estimators. The Fisher information matrix of estimating $(x_t)_{t \in [0, T]}$ given $(y_t)_{t \in [0, T]}$ is well-defined if the unknown $(x_t)_{t \in [0, T]}$ is deterministic. In that case, since $(y_t)_{t \in [0, T]}$ is a Gaussian process and the measurements are linear, the integral operator with kernel K thus saturates the Cramér-Rao inequality and coincides with the inverse of the Fisher information matrix. For random $(x_t)_{t \in [0, T]}$, defining properly the Bayesian posterior analogue of the Cramér-Rao lower bound (Van Trees, 1968) in this infinite-dimensional context would require an undue level of generality, as hinted at in Section 2.3. However, for a deterministic $(x_t)_{t \in [0, T]}$, we have $G(\cdot) \equiv 0$ and $\Pi_0 = 0$ as considered previously. The only parameter of $(x_t)_{t \in [0, T]}$ to identify is x_0 , so the Fisher information matrix writes as $\int_{t_0}^T \frac{\partial \tilde{y}(t)}{\partial x_0} \frac{\partial \tilde{y}(t)}{\partial x_0}^\top dt$ which through simple calculations is shown to be equal to the Gramian of observability (already noticed in Kálmán and Bucy (1961, Remark (h))). The fact that the Fisher information defines a kernel was unveiled by Jaakkola and Haussler (1998). Since the posterior Cramér-Rao lower bound of our estimation problem does not seem to have been written yet, much remains to be done in this direction of research to draw connections with information theory. Applications would already exist in sensor placement and D-optimal design.

5 COMPLEMENTS ON THE FILTER AND SMOOTHER

In this section, for completeness, we derive the expression of the Kalman filter in continuous time and the expression of the smoother based on innovations, both being well-known. We take $\Sigma_T = 0$ and $l_\nu(t) = H^*(t)R^{-1}(t)g(t)$ with $g(\cdot) \in L^2(t_0, T; \mathbb{R}^m)$, and later $g(t)dt = d\tilde{y}(t)$. Going back to the expression (2.9) of the best estimate, and the expression (3.22) of the operator $\hat{S}_s(t|T)$, we can write the formula

$$\hat{x}(s|T) = \bar{x}(s) + \int_{t_0}^T K(s, t|T)H^*(t)R^{-1}(t)d\tilde{y}(t), \quad (5.1)$$

which gives for $s = T$ the Kalman filter formula

$$\hat{x}(T|T) = \bar{x}(T) + \int_{t_0}^T K(T|T, t)H^*(t)R^{-1}(t)d\tilde{y}(t). \quad (5.2)$$

We want to show that the smoother at s can be recursively expressed in terms of the sequence of filters between s and T . As we deal with Linear-Quadratic-Gaussian estimation problems, we naturally find ourselves in a very thoroughly explored field and some expressions below are well-known, and we point out to where they could be found in textbooks (Kailath et al., 2000; Bensoussan, 2018). General kernel formulas are in any case new, and so is the connection of Kalman filtering and smoothing with explicit RKHSs.

5.1 REDERIVING THE KALMAN FILTER

Recall that we defined $r(t) = \hat{\mu}(t) + \Pi(t)\hat{\nu}(t)$ in (3.5). By (3.18)

$$\frac{dr}{dt} = (F(t) - \Pi(t)H^*(t)R^{-1}(t)H(t))r(t) + \Pi(t)H^*(t)R^{-1}(t)g(t), \quad r(t_0) = 0. \quad (5.3)$$

The importance of $r(t)$ is that, like $\Pi(t)$, it satisfies a forward differential equation and thus it does not depend on T . On the other hand, since $\hat{\nu}(T) = 0$, $\hat{\mu}(T) = r(T)$. But then from (3.18) we can write

$$r(T) = \int_{t_0}^T K(T|T, t)H^*(t)R^{-1}(t)g(t)dt = \int_{t_0}^T \hat{S}(T|T, t)g(t)dt. \quad (5.4)$$

If in (5.4) we substitute $g(t)dt$ by $d\tilde{y}(t)$ we obtain the stochastic differential equation (SDE) as given in Bensoussan (2018, Chapter 7)

$$dr = (F(t) - \Pi(t)H^*(t)R^{-1}(t)H(t))r(t)dt + \Pi(t)H^*(t)R^{-1}(t)d\tilde{y}(t), \quad r(t_0) = 0. \quad (5.5)$$

and

$$r(T) = \int_{t_0}^T \hat{S}(T|T, t)d\tilde{y}. \quad (5.6)$$

From (5.2) it follows that the Kalman filter, denoted to simplify notation $\hat{x}(T) = \hat{x}(T|T) = \bar{x}(T) + r(T)$, thus satisfies the SDE

$$d\hat{x}(t) = (F(t)\hat{x}(t) + f(t))dt + \Pi(t)H^*(t)R^{-1}(t)(d\tilde{y}(t) - H(t)r(t)dt).$$

Finally, we obtain the classical Kalman filter equation

$$d\hat{x}(t) = (F(t)\hat{x}(t) + f(t))dt + \Pi(t)H^*(t)R^{-1}(t)(dy(t) - (H(t)\hat{x}(t) + h(t))), \quad \hat{x}(t_0) = x_0. \quad (5.7)$$

5.2 EXPRESSION OF THE SMOOTHER IN TERMS OF INNOVATION

From (3.19), we know that

$$-\frac{d}{d\tau}\hat{v}(\tau) = (F^*(\tau) - H^*(\tau)R^{-1}(\tau)H(\tau)\Pi(\tau))\hat{v}(\tau) - H^*(\tau)R^{-1}(\tau)(g(\tau) - H(\tau)r(\tau)), \quad \hat{v}(T) = 0 \quad (5.8)$$

and thus, by the variation of constants formula,

$$\hat{v}(s) = - \int_s^T \Phi_{F,\Pi}^*(t, s)H^*(t)R^{-1}(t)(g(t) - H(t)r(t))dt. \quad (5.9)$$

Therefore, we have

$$\hat{\mu}(s) = r(s) + \Pi(s) \int_s^T \Phi_{F,\Pi}^*(t, s)H^*(t)R^{-1}(t)(g(t) - H(t)r(t))dt. \quad (5.10)$$

If we replace in the equation $g(t)dt$ by $d\tilde{y}(t)$ we must interpret $r(t)$ as the solution of the SDE (5.5). We then have

$$\begin{aligned} \hat{x}(s|T) &= \bar{x}(s) + \hat{\mu}(s) \\ \hat{x}(s) &= \bar{x}(s) + r(s). \end{aligned} \quad (5.11)$$

From (5.10), we deduce that

$$\hat{x}(s|T) = \hat{x}(s) + \Pi(s) \int_s^T \Phi_{F,\Pi}^*(t, s)H^*(t)R^{-1}(t)(dy(t) - (H(t)\hat{x}(t) + h(t))dt). \quad (5.12)$$

Define the innovation process $e(\cdot)$ as follows

$$e(t) = y(t) - \int_{t_0}^t (H(\tau)\hat{x}(\tau) + h(\tau))d\tau. \quad (5.13)$$

It is well-known that the innovation process is a \mathcal{Y}^t Wiener process with covariance matrix $R(t)$ (see e.g. Bensoussan, 2018, Lemma 7.1). In a nutshell we obtained that

Proposition 6. *The Kalman smoother can be written as follows*

$$\hat{x}(s|T) = \hat{x}(s) + \Pi(s) \int_s^T \Phi_{F,\Pi}^*(t,s) H^*(t) R^{-1}(t) de(t) \quad (5.14)$$

This result is well-known and can be found in Kailath et al. (2000, Lemma 16.5.1). Consequently, the error of the Kalman smoother is given by

$$\hat{\epsilon}(s|T) = x(s) - \hat{x}(s) - \Pi(s) \int_s^T \Phi_{F,\Pi}^*(t,s) H^*(t) R^{-1}(t) de(t) = \tilde{\epsilon}(s|s) - \Pi(s) \int_s^T \Phi_{F,\Pi}^*(t,s) H^*(t) R^{-1}(t) de(t) \quad (5.15)$$

It is obvious that, for $s < t$, the random variables $\tilde{\epsilon}(s|s)$ and $e(t)$ are independent. From (5.15), one can then compute $K(s, s|T) = \mathbb{E}[\tilde{\epsilon}(s|T)\tilde{\epsilon}^*(s|T)]$ and obtain (4.13) for the special case of $s = t$, as in Kailath et al. (2000, Theorem 16.5.1).

6 SUMMARY OF RESULTS

In this section we summarize the findings and key expressions of the article. We also highlight the improvements made over previous formulas for kernels and controlled linear systems. Our problem was to find the operator $\hat{S}_s(t|T)$ minimizing the variance of the error (6.2).

$$\epsilon_S(s|T) = x(s) - x_S(s|T) = \tilde{x}(s) - \int_{t_0}^T S_s(t|T) d\tilde{y}(t). \quad (6.1)$$

$$\hat{S}_s(\cdot|T) \in \underset{S_s(\cdot|T)}{\operatorname{argmin}} \Gamma_S(s|T) = \mathbb{E}[\epsilon_S(s|T)(\epsilon_S(s|T))^*]. \quad (6.2)$$

The latter is related to the posterior covariance through $\hat{S}_s(t|T) = K(s, t|T)H^*(t)R^{-1}(t)$ with

$$K(s, t|T) = \mathbb{E}[\epsilon_{\hat{S}}(s|T)(\epsilon_{\hat{S}}(t|T))^*] \in \mathcal{L}(\mathbb{R}^{n,*}, \mathbb{R}^n). \quad (6.3)$$

The explicit formula for K can be obtained by finding the Green functions of a two-point boundary value problem:

$$\begin{aligned} \frac{d\hat{\mu}}{dt} &= F(t)\hat{\mu}(t) - G(t)Q(t)G^*(t)\hat{\nu}(t) + l_\mu(t) \\ -\frac{d\hat{\nu}}{dt} &= F^*(t)\hat{\nu}(t) + H^*(t)R^{-1}(t)H(t)\hat{\mu}(t) - l_\nu(t) \\ \hat{\mu}(t_0) &= -\Pi_0\hat{\nu}(t_0), \quad \hat{\nu}(T) = \Sigma_T\hat{\mu}(T). \end{aligned} \quad (6.4)$$

The canonical resolution proceeds by introducing two Riccati differential equations

$$-\frac{d}{dt}\Sigma = \Sigma(t)F(t) + F^*(t)\Sigma(t) - \Sigma(t)G(t)Q(t)G^*(t)\Sigma(t) + H^*(t)R^{-1}(t)H(t), \quad \Sigma(T) = \Sigma_T; \quad (6.5)$$

$$\frac{d}{dt}\Pi = F(t)\Pi(t) + \Pi(t)F^*(t) - \Pi(t)H^*(t)R^{-1}(t)H(t)\Pi(t) + G(t)Q(t)G^*(t), \quad \Pi(t_0) = \Pi_0. \quad (6.6)$$

which we complement by looking for matrix-valued kernels K and Λ satisfying

$$\hat{\mu}(s) = \int_{t_0}^T K(s, t|T) l_\nu(t) dt \quad \text{for } l_\mu(\cdot) \equiv 0, \quad (6.7)$$

$$\hat{v}(s) = \int_{t_0}^T \Lambda(s, t|T) l_\mu(t) dt \quad \text{for } l_\nu(\cdot) \equiv 0. \quad (6.8)$$

where K corresponds to the covariance (6.3) as shown in Proposition 5. Introducing a semigroup associated with the matrix function $F(t) - G(t)Q(t)G^*(t)\Sigma(t)$ denoted $\Phi_{F,\Sigma}(s, t)$ (resp. $F(s) - \Pi(s)H^*(s)R^{-1}(s)H(s)$, denoted $\Phi_{F,\Pi}(s, t)$), we obtain two symmetric formulas (Theorem 2):

$$K(s, t|T) = \Phi_{F,\Sigma}(s, t_0) \Pi_0^{\frac{1}{2}} (\text{Id} + \Pi_0^{\frac{1}{2}} \Sigma(t_0) \Pi_0^{\frac{1}{2}})^{-1} \Pi_0^{\frac{1}{2}} \Phi_{F,\Sigma}^*(t, t_0) + \int_{t_0}^{\min(s,t)} \Phi_{F,\Sigma}(s, \tau) G(\tau) Q(\tau) G^*(\tau) \Phi_{F,\Sigma}^*(t, \tau) d\tau \quad (6.9)$$

$$\Lambda(s, t|T) = \Phi_{F,\Pi}^*(T, s) \Sigma_T^{\frac{1}{2}} (\text{Id} + \Sigma_T^{\frac{1}{2}} \Pi(T) \Sigma_T^{\frac{1}{2}})^{-1} \Sigma_T^{\frac{1}{2}} \Phi_{F,\Pi}(T, t) + \int_{\max(s,t)}^T \Phi_{F,\Pi}^*(\tau, s) H^*(\tau) R^{-1}(\tau) H(\tau) \Phi_{F,\Pi}(\tau, t) d\tau \quad (6.10)$$

For which we proved (Theorem 3), that K was the reproducing kernel of a space of controlled trajectories equipped with a quadratic cost

$$\mathcal{S}_{[t_0, T]}^x = \{x(\cdot) \in H^1(t_0, T; \mathbb{R}^n) \mid \exists v(\cdot) \in L^2(t_0, T; \mathbb{R}^p), \xi \in \mathbb{R}^n \text{ s.t.} \\ \frac{d}{d\tau} x = F(\tau)x(\tau) + G(\tau)Q^{\frac{1}{2}}(\tau)v(\tau), x(t_0) = \Pi_0^{\frac{1}{2}}\xi\} \quad (6.11)$$

$$J_x(\xi, v(\cdot)) = \|\xi\|^2 + \langle \Sigma_T x(T), x(T) \rangle + \int_{t_0}^T \|v(\tau)\|^2 d\tau + \int_{t_0}^T \langle H^*(\tau)R^{-1}(\tau)H(\tau)x(\tau), x(\tau) \rangle d\tau. \quad (6.12)$$

Similarly, Λ is associated with a Hilbert space of information vectors (Theorem 4)

$$\mathcal{S}_{[t_0, T]}^\lambda = \{\lambda(\cdot) \in H^1(t_0, T; \mathbb{R}^n) \mid v(\cdot) \in L^2(t_0, T; \mathbb{R}^m), z \in \mathbb{R}^n \text{ s.t.} \\ -\frac{d}{dt}\lambda(t) = F^*(t)\lambda(t) + H^*(t)v(t), \lambda(T) = \Sigma_T^{\frac{1}{2}}z\} \quad (6.13)$$

$$J_\lambda(z, v(\cdot)) = \langle \Pi_0 \lambda(t_0), \lambda(t_0) \rangle + \|z\|^2 + \int_{t_0}^T \langle G(t)Q(t)G^*(t)\lambda(t), \lambda(t) \rangle dt + \int_{t_0}^T \langle R(t)v(t), v(t) \rangle dt \quad (6.14)$$

The two kernels are related by the following formula (Proposition 5)

$$K(s, t|T) = \Pi(s)\Phi_{F,\Pi}^*(t, s)\mathbb{1}_{s \leq t} + \Phi_{F,\Pi}(s, t)\Pi(t)\mathbb{1}_{s > t} - \Pi(s)\Lambda(s, t|T)\Pi(t). \quad (6.15)$$

In previous articles, we presented various related results for LQ optimal control:

- Aubin-Frankowski (2021a) first introduced the idea of considering the vector space $(\mathcal{S}_{[t_0, T]}^x, \langle \cdot, \cdot \rangle_{\mathcal{S}_{[t_0, T]}^x})$ as a reproducing kernel Hilbert space in the case $\Sigma_T = 0$. A two-point boundary system to obtain K was given but not solved explicitly. The closed form formula were only given for $\Pi_0 = \text{Id}$ and $H \equiv 0$;
- Aubin-Frankowski (2021b) observed that, for $\Sigma_T \neq 0$ and $\Pi_0 \rightarrow \infty$, the map $t_0 \mapsto K(t_0, t_0|[t_0, T])$ satisfied a forward Riccati equation and was the inverse of the usual backward Riccati matrix considered in LQ optimal control;

- Aubin-Frankowski and Bensoussan (2022) gave a closed form formula for K , for $\Sigma_T = 0$, in the general case of an infinite-dimensional state with values in a Hilbert space to tackle linear PDE control.

To summarize, the kernels considered appear in linear-quadratic optimal control because of Hilbertian vector spaces of trajectories, while, for estimation problems, they appear through covariances of Gaussian processes.

Conclusion. We improved on our previous results by considering the dual RKHS $(\mathcal{S}_{[t_0, T]}^\lambda, \langle \cdot, \cdot \rangle_{\mathcal{S}_{[t_0, T]}^\lambda})$ of covectors/information vectors, by relaxing as much as possible the invertibility requirements on the matrices Q, Π_0, Σ_T , and most of all by considering an estimation, rather than optimal control, problem and consequently defining the kernel K as the covariance of the estimation error. This way, we derived novel formulas for the covariances of the Markovian Gaussian processes of linear SDEs. The kernels presented should also in principle allow for incorporating constraints or considering various sampling times of observations, and are computable through the matrix exponential formulas given in Appendix A.2. We considered here a continuous-time observation process, the extension to discrete-time measurement should be straightforward by replacing integrals with finite sums when dealing with the observation operator H . We could not discuss here the question of duality as a formal change of variables as in Kálmán and Bucy (1961); Todorov (2008), as well as the relation between value function and likelihood. We leave these interesting directions to future work.

Appendix

A.1 Existence of the solution of the Riccati equation

Lemma 7. *The Riccati equation (3.1) has a solution $\Sigma(t)$ which is symmetric and positive semi-definite on the interval $[t_0, T]$.*

Proof. The differential equation (3.1) has a unique local solution on an interval $[t_1, T]$ for t_1 sufficiently close to T . The solution is symmetric, since the transpose satisfies the equation. We can then consider the differential equation

$$\frac{d\gamma}{dt} = (F(t) - G(t)Q(t)G^*(t)\Sigma(t))\gamma(t), \quad \gamma(t_1) = \gamma_0. \quad (6.16)$$

We can then compute

$$\begin{aligned} \frac{d\langle \gamma(t), \Sigma(t)\gamma(t) \rangle}{dt} &= 2 \left\langle \gamma(t), \Sigma(t) \frac{d\gamma(t)}{dt} \right\rangle + \left\langle \gamma(t), \frac{d\Sigma(t)}{dt} \gamma(t) \right\rangle \\ &= - \left\langle \gamma(t), \left(\Sigma(t)G(t)Q(t)G^*(t)\Sigma(t) + H^*(t)R^{-1}(t)H(t) \right) \gamma(t) \right\rangle \leq 0 \end{aligned}$$

and since $\Sigma(T) = 0$, by integration between t_1 and T , we obtain $\langle \gamma_0, \Sigma(t_1)\gamma_0 \rangle \geq 0$. Since γ_0 is arbitrary, we obtain $\Sigma(t_1) \geq 0$. We could have started in (6.16) at any point on the interval (t_1, T) . Therefore the local solution satisfies $\Sigma(t) \geq 0$. Consider next the semi group $\Phi_F(t, t_1)$, on the interval $t \in (t_1, T)$ defined by the differential equation

$$\frac{d}{dt}\Phi_F(t, t_1) = F(t)\Phi_F(t, t_1), \quad \Phi_F(t_1, t_1) = \text{Id} \quad (6.17)$$

If we consider

$$\frac{d\langle \Phi_F(t, t_1)\gamma_0, \Sigma(t)\Phi_F(t, t_1)\gamma_0 \rangle}{dt} = \left\langle \Phi_F(t, t_1)\gamma_0, \left(F^*(t)\Sigma(t) + \Sigma(t)F(t) + \frac{d}{dt}\Sigma(t) \right) \Phi_F(t, t_1)\gamma_0 \right\rangle,$$

from the Riccati equation, we obtain

$$\frac{d \langle \Phi_F(t, t_1) \gamma_0, \Sigma(t) \Phi_F(t, t_1) \gamma_0 \rangle}{dt} \geq - \langle \Phi_F(t, t_1) \gamma_0, H^*(t) R^{-1}(t) H(t) \Phi_F(t, t_1) \gamma_0 \rangle$$

Integrating between t_1 and T , we get

$$\langle \gamma_0, \Sigma(T) \gamma_0 \rangle \leq \int_{t_1}^T \langle \Phi_F(t, t_1) \gamma_0, H^*(t) R^{-1}(t) H(t) \Phi_F(t, t_1) \gamma_0 \rangle \leq C \|\gamma_0\|^2 \quad (6.18)$$

for some constant $C > 0$. It follows that the solution $\Sigma(t)$ can be extended beyond t_1 and finally up to t_0 . This completes the proof. \square

A.2 Computation of kernels of linear SDEs through exponentials of the Hamiltonian matrix

The following method to compute Gramians can be traced at least back to Van Loan (1978) in the time-invariant case and was mentioned in Kalman (1960, Section 8) as a periodically rediscovered way to solve differential Riccati equations. It made its way in the linear SDE literature (see e.g. Särkkä and Solin, 2019, Section 6.3, p.84) where $H \equiv 0$ and $\Sigma \equiv 0$. However a more systematic presentation through the Hamiltonian matrix can be found in Speyer and Jacobson (2010) for linear-quadratic control. In particular this allows to consider the important case of $GQG^* \neq 0$ and $H \neq 0$. We focus below on computing K but similar operations can be performed to obtain Λ by changing variables, as was done in the proof of Theorem 4. Consider the equations

$$\begin{aligned} \frac{d\hat{\mu}}{dt} &= F(t)\hat{\mu}(t) - G(t)Q(t)G^*(t)\hat{\nu}(t), & \hat{\mu}(t_0) &= x_0 \\ \frac{d\hat{\nu}}{dt} &= -F^*(t)\hat{\nu}(t) - H^*(t)R^{-1}(t)H(t)\hat{\mu}(t), & \hat{\nu}(T) &= \Sigma_T \hat{\mu}(T) \end{aligned}$$

and write them in matrix form introducing the Hamiltonian $\mathbb{H}(t)$

$$\frac{d}{dt} \begin{pmatrix} \hat{\mu}(t) \\ \hat{\nu}(t) \end{pmatrix} = \underbrace{\begin{pmatrix} F(t) & -G(t)Q(t)G^*(t) \\ -H^*(t)R^{-1}(t)H(t) & -F^*(t) \end{pmatrix}}_{\mathbb{H}(t)} \begin{pmatrix} \hat{\mu}(t) \\ \hat{\nu}(t) \end{pmatrix}. \quad (6.19)$$

Denote by $\Phi_{\mathbb{H}}(T, t)$ the transition matrix $\frac{d}{dt} \Phi_{\mathbb{H}}(T, t) = -\mathbb{H}(t) \Phi_{\mathbb{H}}(T, t)$, $\Phi_{\mathbb{H}}(T, T) = \text{Id}$ and set as in Speyer and Jacobson (2010, eq.(5.72))

$$\Phi_{\mathbb{H}}(T, t) := \begin{pmatrix} \Phi_{11}(T, t) & \Phi_{12}(T, t) \\ \Phi_{21}(T, t) & \Phi_{22}(T, t) \end{pmatrix} \quad \bar{\Phi}_{\mathbb{H}}(T, t) := \begin{pmatrix} \bar{\Phi}_{11}(T, t) & \bar{\Phi}_{12}(T, t) \\ \bar{\Phi}_{21}(T, t) & \bar{\Phi}_{22}(T, t) \end{pmatrix} = \begin{pmatrix} \text{Id} & 0 \\ -\Sigma_T & \text{Id} \end{pmatrix} \cdot \Phi_{\mathbb{H}}(T, t).$$

Assume that $\bar{\Phi}_{22}(T, t)$ is invertible, then through some calculations one can show that (see Speyer and Jacobson, 2010, Chapter 5, eq.(5.77, 5.160, 5.163))

$$\begin{aligned} \Sigma(t) &= -\bar{\Phi}_{22}^{-1}(T, t) \bar{\Phi}_{21}(T, t), \\ \Phi_{F, \Sigma}(t, T) &= \bar{\Phi}_{22}^*(T, t), \\ \int_T^s \Phi_{F, \Sigma}(T, \tau) G(\tau) Q(\tau) G^*(\tau) \Phi_{F, \Sigma}^*(T, \tau) d\tau &= \bar{\Phi}_{12}(T, s) \bar{\Phi}_{22}^{-1}(T, s). \end{aligned}$$

where $\Sigma(t)$ is the solution of the Backward Riccati equation and $\Phi_{F,\Sigma}(s, t)$ the semigroup associated with $F(t) - G(t)Q(t)G^*(t)\Sigma(t)$. Define two auxiliary kernels which we will compute independently.

$$K(s, t|T) = \underbrace{\Phi_{F,\Sigma}(s, t_0)\Pi_0^{\frac{1}{2}}(\text{Id} + \Pi_0^{\frac{1}{2}}\Sigma(t_0)\Pi_0^{\frac{1}{2}})^{-1}\Pi_0^{\frac{1}{2}}\Phi_{F,\Sigma}^*(t, t_0)}_{=:K_0(s,t)} + \underbrace{\int_{t_0}^{\min(s,t)} \Phi_{F,\Sigma}(s, \tau)G(\tau)Q(\tau)G^*(\tau)\Phi_{F,\Sigma}^*(t, \tau)d\tau}_{=:K_1(s,t)} \quad (6.20)$$

By the above expressions, we have for $s \leq t$

$$K_0(s, t) = \bar{\Phi}_{22}^*(T, s)\bar{\Phi}_{22}^{-1,*}(T, t_0)\Pi_0^{\frac{1}{2}}(\text{Id} + \Pi_0^{\frac{1}{2}}\bar{\Phi}_{22}^{-1}(T, t_0)\bar{\Phi}_{21}(T, t_0)\Pi_0^{\frac{1}{2}})^{-1}\Pi_0^{\frac{1}{2}}\bar{\Phi}_{22}^{-1}(T, t_0)\bar{\Phi}_{22}(T, t)$$

$$K_1(s, t) = \bar{\Phi}_{22}^*(T, s)[\bar{\Phi}_{12}(T, s)\bar{\Phi}_{22}^{-1}(T, s) - \bar{\Phi}_{12}(T, t_0)\bar{\Phi}_{22}^{-1}(T, t_0)]\bar{\Phi}_{22}(T, t)$$

Formulas for $s > t$ can be obtained by Hermitian symmetry, $K(s, t|T) = K(t, s)^*$. These formulas simplify drastically when $H(\cdot) \equiv 0$ and $\Sigma_T = 0$, so $\Sigma(\cdot) \equiv 0$, $\bar{\Phi}_{22}^*(T, t) = \Phi_F(t, T)$ (alternative computations could be done in this case with $\Phi_{\mathbb{H}}(t, t_0)$) which inverse are easily computable. Otherwise every inversion should be computed numerically. In the time-invariant case, we have $\Phi_{\mathbb{H}}(T, t) = e^{(T-t)\mathbb{H}}$ and all quantities can be computed through matrix exponentials.

References

- Pierre-Cyril Aubin-Frankowski. Linearly constrained linear quadratic regulator from the viewpoint of kernel methods. *SIAM Journal on Control and Optimization*, 59(4):2693–2716, 2021a. doi: 10.1137/20m1348765.
- Pierre-Cyril Aubin-Frankowski. Interpreting the dual Riccati equation through the LQ reproducing kernel. *Comptes Rendus. Mathématique*, 359(2):199–204, 2021b.
- Pierre-Cyril Aubin-Frankowski and Alain Bensoussan. Operator-valued kernels and control of infinite dimensional dynamic systems. In *Control and Decision Conference (CDC)*, 2022. (<https://arxiv.org/abs/2206.09419>).
- David Luenberger. *Optimization by vector space methods*. Wiley, New York, 1968.
- Pierre-Cyril Aubin-Frankowski and Stéphane Gaubert. Tropical reproducing kernels and optimization. Technical report, 2022. (<https://arxiv.org/abs/2202.11410>).
- Rudolf E. Kálmán and Richard S. Bucy. New results in linear filtering and prediction theory. *Journal of Basic Engineering*, 83:95–108, 1961.
- Thomas Kailath, Ali H Sayed, and Babak Hassibi. *Linear Estimation*. Prentice Hall information and system sciences series. Pearson, 2000.
- Emanuel Parzen. An approach to time series analysis. *The Annals of Mathematical Statistics*, 32(4):951–989, 1961.
- Alain Berlinet and Christine Thomas-Agnan. *Reproducing Kernel Hilbert Spaces in Probability and Statistics*. Kluwer, 2004.
- Carl Edward Rasmussen and Christopher K I Williams. *Gaussian processes for machine learning*. Adaptive Computation and Machine Learning series. MIT Press, 2005.

- Motonobu Kanagawa, Philipp Hennig, Dino Sejdinovic, and Bharath K Sriperumbudur. Gaussian processes and kernel methods: A review on connections and equivalences, 2018. URL <https://arxiv.org/abs/1807.02582>.
- Simo Särkkä and Arno Solin. *Applied Stochastic Differential Equations*. Cambridge University Press, 2019.
- Simo Sarkka, Arno Solin, and Jouni Hartikainen. Spatiotemporal learning via infinite-dimensional Bayesian filtering and smoothing: A look at Gaussian process regression through Kalman filtering. *IEEE Signal Processing Magazine*, 30(4):51–61, Jul 2013.
- Finn Lindgren, David Bolin, and Håvard Rue. The SPDE approach for Gaussian and non-Gaussian fields: 10 years and still running. *Spatial Statistics*, 50:100599, 2022.
- Florian Steinke and Bernhard Scholkopf. Kernels, regularization and differential equations. *Pattern Recognition*, 41(11):3271–3286, 2008.
- Motonobu Kanagawa, Yu Nishiyama, Arthur Gretton, and Kenji Fukumizu. Filtering with state-observation examples via kernel Monte Carlo filter. *Neural Comput.*, 28(2):382–444, 2016.
- Jacques Neveu. *Processus aléatoires gaussiens*. Seminaire Math. Sup., Les presses de l’Université de Montréal., 1968.
- Nathalie Eisenbaum and Haya Kaspi. A characterization of the infinitely divisible squared Gaussian processes. *The Annals of Probability*, 34(2), 2006.
- Alain Bensoussan. *Estimation and Control of Dynamical Systems*. Springer International Publishing, 2018.
- Giuseppe Da Prato and Helene Frankowska. Invariance of stochastic control systems with deterministic arguments. *Journal of Differential Equations*, 200(1):18–52, 2004.
- Jason L. Speyer and David H. Jacobson. *Primer on Optimal Control Theory*. Society for Industrial and Applied Mathematics, USA, 2010.
- Saburo Saitoh and Yoshihiro Sawano. *Theory of Reproducing Kernels and Applications*. Springer Singapore, 2016.
- Mario Micheli and Joan A. Glaunès. Matrix-valued kernels for shape deformation analysis. *Geometry, Imaging and Computing*, 1(1):57–139, 2014.
- Harry L. Van Trees. *Detection, estimation, and modulation theory. 1: Detection, estimation, and linear modulation theory*. Wiley, New York, 1968.
- Tommi Jaakkola and David Haussler. Exploiting generative models in discriminative classifiers. In *In Advances in Neural Information Processing Systems 11*, pages 487–493. MIT Press, 1998.
- Emanuel Todorov. General duality between optimal control and estimation. In *IEEE Conference on Decision and Control (CDC)*, pages 4286–4292, 2008.
- Charles Van Loan. Computing integrals involving the matrix exponential. *IEEE Transactions on Automatic Control*, 23(3):395–404, June 1978. ISSN 1558-2523.
- Rudolf Kalman. Contribution to the theory of optimal control. *Bol. Soc. Mat. Mexicana*, 5:102–119, 02 1960.