

Use of indicator functions to enumerate cross-array designs without direct product structure

Satoshi Aoki* and Masayuki Noro†

Abstract

Use of polynomial indicator functions to enumerate fractional factorial designs with given properties is first introduced by Fontana, Pistone and Rogantin (2000) for two-level factors, and generalized by Aoki (2019) for multi-level factors. In this paper, we apply this theory to enumerate cross-array designs. For the experiments of several control factors and noise factors, use of the cross-array designs with direct product structure is widespread as an effective robust strategy in Taguchi method. In this paper, we relax this direct product structure to reduce the size of the designs. We obtain 24-runs cross-array designs without direct product structure with some desirable properties for 6 control factors and 3 noise factors, each with two-levels, instead of 32-runs design that is widely used.

Keywords: Computational algebraic statistics, Cross-array designs, Fractional factorial designs, Gröbner bases, Indicator functions, Taguchi methods.

1 Introduction

Suppose we plan to conduct designs of experiment for several control factors and several noise factors. In the theory of quality engineering, which is one of the important fields in designs of experiments, use of *cross-array designs* is recommended as an effective robust strategy. For example, suppose we have 6 control factors x_1, \dots, x_6 and 3 noise factors y_1, \dots, y_3 , each with 2 levels $\{-1, 1\}$. In this case, we can allocate the control factors to the orthogonal array L_8 and the noise factors to the orthogonal array L_4 , and obtain a cross-array design shown in Table 1. In Table 1, we denote each observation by the symbol “o”. Use of the cross-array designs is a popular strategy in the context of robust parameter designs in Taguchi methods. See Chapter 15 of [7] or Chapter 11 of [8]. We can also find various orthogonal arrays such as L_8 and L_4 in these textbooks. In this field, the cross-array design is also called an inner-outer array design (or an inner-outer layout), where the array for the control factors (L_8 in Table 1) is called an inner array, and the array for the noise factors (L_4 in Table 1) is called an outer array. From the observations obtained in the cross-array design, we can estimate all main effects of the control factors and the noise factors, and all interaction effects between the control factors and the noise

*Graduate School of Science, Faculty of Science, Kobe University.

†Department of Mathematics, College of Science, Rikkyo University

Table 1: Cross-array design for 6 control factors and 3 noise factors.

						y_1	-1	-1	1	1
						y_2	-1	1	-1	1
x_1	x_2	x_3	x_4	x_5	x_6	y_3	-1	1	-1	1
-1	-1	-1	1	1	1		o	o	o	o
-1	-1	1	1	-1	-1		o	o	o	o
-1	1	-1	-1	1	-1		o	o	o	o
-1	1	1	-1	-1	1		o	o	o	o
1	-1	-1	-1	-1	1		o	o	o	o
1	-1	1	-1	1	-1		o	o	o	o
1	1	-1	1	-1	-1		o	o	o	o
1	1	1	1	1	1		o	o	o	o

factors. This is the principle merit to use the cross-array designs. See textbooks such as [7] or [8] for detail.

Obviously the cross-array designs have a direct product structure between the inner array and the outer array. In this paper, we relax this direct product structure to reduce the size of the designs. Note that the reduction in size of the designs is always of interest for cost saving. To understand the idea in this paper clearly, we rewrite Table 1 as Table 2 and emphasize the direct product structure. In this study, instead of this 32-runs design,

Table 2: Same cross-array design of Table 1.

						y_1	-1	-1	-1	-1	1	1	1	1
						y_2	-1	-1	1	1	-1	-1	1	1
						y_3	-1	1	-1	1	-1	1	-1	1
x_1	x_2	x_3	x_4	x_5	x_6									
-1	-1	-1	1	1	1			o	o		o			o
-1	-1	1	1	-1	-1			o	o		o			o
-1	1	-1	-1	1	-1			o	o		o			o
-1	1	1	-1	-1	1			o	o		o			o
1	-1	-1	-1	-1	1			o	o		o			o
1	-1	1	-1	1	-1			o	o		o			o
1	1	-1	1	-1	-1			o	o		o			o
1	1	1	1	1	1			o	o		o			o

we try to construct 24-runs designs with some desirable properties. As we see in Section 3, we construct 24-runs designs such as Table 3 using tools of algebraic statistics. In fact, this (and *only this*) 24-runs design has some desirable properties we consider, which we show in Section 3.

To construct designs with some given properties, we make use of *polynomial indicator functions of designs*. This algebraic technique is first introduced in [4] for designs of two-level factors, and is generalized to multi-level cases in [1]. By the generalization by [1],

Table 3: 24-runs cross-array designs for 6 control factors and 3 noise factors.

						y_1	y_2	y_3							
						-1	-1	-1	-1	1	1	1	1		
						-1	-1	1	1	-1	-1	1	1		
						-1	1	-1	1	-1	1	-1	1		
x_1	x_2	x_3	x_4	x_5	x_6										
-1	-1	-1	1	1	1	○	○							○	
-1	-1	1	1	-1	-1			○			○	○			
-1	1	-1	-1	1	-1			○		○				○	
-1	1	1	-1	-1	1		○		○	○					
1	-1	-1	-1	-1	1				○	○			○		
1	-1	1	-1	1	-1	○			○		○				
1	1	-1	1	-1	-1		○	○			○				
1	1	1	1	1	1	○								○	○

we can construct designs with given properties for any number of factors with any set of levels *in theory*. However, in practice, the computational feasibility becomes a problem. For example, we enumerate all orthogonal fractions of $2^4 \times 3$ designs with strength 3 in [1], but fail to enumerate all orthogonal fractions of $2^4 \times 3$ designs with strength 2. (We give a definition of a strength of orthogonality in Section 3.) The latter problem is solved in [2] using technique of a primary decomposition of polynomial ideals. These problems correspond to solving algebraic equations for $2^4 \times 3 = 48$ variables with some constraints ([1] and [2]). In the same way, we can define the polynomial ideal for the problems of 6 control factors and 3 noise factors as an ideal with $2^9 = 512$ variables. Obviously, such a naive approach fail to solve in realistic time. As we see in Section 3, we define the ideal with $2^6 = 64$ variables for this problem, which we can solve by an usual laptop PC.

The content of this paper is as follows. In Section 2, we summarize the theory of the indicator function and its use to construct designs. Because we apply this theory to the cross-array designs, we summarize the general theory given by [1] in the cross-array settings. In Section 3, we consider the problem for 6 control factors and 3 noise factors. We show the properties of 24-runs designs such as Table 3 and show how to construct them.

2 Constructing fractions using indicator functions

In this section, we summarize the theory on the indicator function of designs and its use to construct designs. The arguments are based on the theory of the interpolatory polynomials on designs, which is one of the first applications of Gröbner bases to statistics by [6]. The arguments in this section are given in [1] in general settings. We give the arguments in the setting of the cross-array designs in this section.

Let x_1, \dots, x_p be p control factors. Let $A_j \subset \mathbb{Q}$ be a level set of a control factor x_j for $j = 1, \dots, p$, where \mathbb{Q} denotes the field of rational numbers. A full factorial design of the control factors x_1, \dots, x_p is $D_x = A_1 \times \dots \times A_p$. A subset of D_x , $F_x \subset D_x$, is called

a fractional factorial design of the control factors. We also define similar materials for q noise factors y_1, \dots, y_q , i.e., let $B_j \subset \mathbb{Q}$ be a level set of a noise factor y_j for $j = 1, \dots, q$, $D_y = B_1 \times \dots \times B_q$ be a full factorial design, and $F_y \subset D_y$ be a fractional factorial design for the noise factors y_1, \dots, y_q .

For fractional factorial designs $F_x \subset D_x$ and $F_y \subset D_y$, $F_x \times F_y$ is a cross-array design with a direct product structure. In the theory of Taguchi method, use of direct product type cross-array designs $F_x \times F_y$ is recommended for *regular* fractional factorial designs F_x and F_y . In this paper, we consider general fractional factorial designs of $F_x \times D_y$ for a regular fractional factorial design $F_x \subset D_x$ as follows. We assume that the levels of the r ($r < p$) control factors x_{p-r+1}, \dots, x_p are determined from the levels of the remaining $p - r$ ($= s$) control factors x_1, \dots, x_s by

$$x_{s+j} = g_j(x_1, \dots, x_s), \quad j = 1, \dots, r, \quad (1)$$

where $g_j \in \mathbb{Q}[x_1, \dots, x_s]$ for $j = 1, \dots, r$. Under this relation, the fractional factorial design

$$\{(x_1, \dots, x_s, g_1(x_1, \dots, x_s), \dots, g_r(x_1, \dots, x_s)) \mid (x_1, \dots, x_s) \in A_1 \times \dots \times A_s\} \subset D_x$$

is called a regular fractional factorial design of D_x with the defining relation g_1, \dots, g_r .

Remark 2.1. In the textbooks such as [8] or [7], the regular fractional factorial design is mainly explained for two or three level factors. For two-level cases, which we also consider in this paper, it is common to define such as $x_4 = g_1(x_1, x_2, x_3) = x_1x_2$ for the level $\{-1, 1\}$. For three-level cases, it is also common to define by “mod 3 operation” such as

$$x_4 = x_1 + x_2 + x_3 \pmod{3}$$

for the level set $\{0, 1, 2\}$. Though our definition of the regular designs by (1) seems different from the conventional definition given in the textbooks in this field, our definition is more general and holds for factors with different number of levels. Note that it is also possible to represent the above x_4 by the polynomial in $\mathbb{Q}[x_1, x_2, x_3]$ as the interpolation function on $\{0, 1, 2\}^3$ with the response x_4 .

We write the full factorial design of x_1, \dots, x_s as $D_x^* = A_1 \times \dots \times A_s$ and consider fractional factorial designs of $D_x^* \times D_y$ in this paper. Now we introduce an indicator function on $D_x^* \times D_y$.

Definition 2.2 ([4]). The indicator function of $F \subset D_x^* \times D_y$ is a response function f on $D_x^* \times D_y$ satisfying

$$f(x_1, \dots, x_s, y_1, \dots, y_q) = \begin{cases} 1, & \text{if } (x_1, \dots, x_s, y_1, \dots, y_q) \in F, \\ 0, & \text{if } (x_1, \dots, x_s, y_1, \dots, y_q) \in (D_x^* \times D_y) \setminus F. \end{cases}$$

To show the existence, uniqueness and construction of the polynomial indicator function below, we prepare the set $L \subset \mathbb{Z}_{\geq 0}^{s+q}$ by

$$L = \left\{ (a_1, \dots, a_s, b_1, \dots, b_q) \mid \begin{array}{l} 0 \leq a_i \leq |A_i| - 1, \quad i = 1, \dots, s, \\ 0 \leq b_j \leq |B_j| - 1, \quad j = 1, \dots, q \end{array} \right\},$$

where $\mathbb{Z}_{\geq 0}$ be the set of nonnegative integers, and $|A_i|$ and $|B_j|$ be the cardinality of A_i and B_j , respectively. By ordering the points of $D_x^* \times D_y$, we write

$$D_x^* \times D_y = \{\mathbf{d}_1, \dots, \mathbf{d}_m\},$$

where $m = \left(\prod_{j=1}^s |A_j|\right) \left(\prod_{j=1}^q |B_j|\right)$ is the size of $D_x^* \times D_y$, and

$$\mathbf{d}_i = (x_{i1}, \dots, x_{is}, y_{i1}, \dots, y_{iq}), \quad i = 1, \dots, m,$$

where x_{ij} and y_{ij} are the levels of the factors x_j and y_j in the i th design point (i.e., i th run), respectively. For each $\mathbf{c} = (a_1, \dots, a_s, b_1, \dots, b_q) \in L$, write the monomial as

$$\mathbf{d}_i^{\mathbf{c}} = x_{i1}^{a_1} \cdots x_{is}^{a_s} y_{i1}^{b_1} \cdots y_{iq}^{b_q}$$

for $i = 1, \dots, m$. By ordering the elements of L , we define a model matrix of $D_x^* \times D_y$ by

$$X = [\mathbf{d}_i^{\mathbf{c}}]_{i=1, \dots, m; \mathbf{c} \in L}.$$

Note that X is called a design matrix in Definition 26 of [5], and is an $m \times m$ non-singular matrix (Theorem 26 of [5]). For the variables $\mathbf{z} = (x_1, \dots, x_s, y_1, \dots, y_q)$ and $\mathbf{c} = (a_1, \dots, a_s, b_1, \dots, b_q) \in L$, we also write the monomial as

$$\mathbf{z}^{\mathbf{c}} = x_1^{a_1} \cdots x_s^{a_s} y_1^{b_1} \cdots y_q^{b_q},$$

and write the indicator function of $F \subset D_x^* \times D_y$ as

$$f(x_1, \dots, x_s, y_1, \dots, y_q) = f(\mathbf{z}) = \sum_{\mathbf{c} \in L} \theta_{\mathbf{c}} \mathbf{z}^{\mathbf{c}}.$$

Then the $m \times 1$ column vector $\boldsymbol{\theta} = [\theta_{\mathbf{c}}]_{\mathbf{c} \in L}$ is given by $\boldsymbol{\theta} = X^{-1} \mathbf{u}$, where $\mathbf{u} = [u_1, \dots, u_m]^T \in \{0, 1\}^m$ is an $m \times 1$ column vector of a response on $D_x^* \times D_y = \{\mathbf{d}_1, \dots, \mathbf{d}_m\}$ satisfying

$$u_i = \begin{cases} 1, & \text{if } \mathbf{d}_i \in F, \\ 0, & \text{if } \mathbf{d}_i \in (D_x^* \times D_y) \setminus F. \end{cases} \quad (2)$$

See Theorem 26 of [5] for detail. An important fact is that the set $\{\mathbf{z}^{\mathbf{c}} \mid \mathbf{c} \in L\}$ is a basis of $\mathbb{Q}[\mathbf{z}]/I(D_x^* \times D_y)$ as a \mathbb{Q} -vector space, where $I(D_x^* \times D_y)$ is the design ideal of $D_x^* \times D_y$, i.e., the set of polynomials in $\mathbb{Q}[\mathbf{z}]$ which are 0 at every point of $D_x^* \times D_y$. This fact guarantees the existence and the uniqueness of the polynomial indicator function of $F \subset D_x^* \times D_y$. See Theorem 15 of [5] for detail.

The fractional factorial designs with given properties can be characterized as the zero points of the 0-dimensional ideal defined for the coefficients of the corresponding indicator function. Let \mathcal{G} be the reduced Gröbner basis of $I(D_x^* \times D_y)$ for some monomial order on \mathbf{z} . Then a polynomial $f(\mathbf{z}) = \sum_{\mathbf{c} \in L} \theta_{\mathbf{c}} \mathbf{z}^{\mathbf{c}}$ is an indicator function of some fractional factorial design of $D_x^* \times D_y$ if and only if the system of the algebraic equations

$$\theta_{\mathbf{c}} = \mu_{\mathbf{c}}, \quad \mathbf{c} \in L \quad (3)$$

hold, where $\sum_{\mathbf{c} \in L} \mu_{\mathbf{c}} \mathbf{z}^{\mathbf{c}}$ is the standard form of $\sum_{\mathbf{c}_1 \in L} \sum_{\mathbf{c}_2 \in L} \theta_{\mathbf{c}_1} \theta_{\mathbf{c}_2} \mathbf{z}^{\mathbf{c}_1 + \mathbf{c}_2}$ with respect to \mathcal{G} (Proposition 3.1 of [1]). Therefore, if we give some properties for the fractional factorial designs as k constraints in the form of $C\mathbf{u} = \mathbf{h}$ for the corresponding response vector \mathbf{u} of (2), where C is a $k \times m$ matrix and \mathbf{h} is a $k \times 1$ column vector, we can define a polynomial ideal of $\mathbb{Q}[\boldsymbol{\theta}]$ by

$$I = \langle \{\theta_{\mathbf{c}} - \mu_{\mathbf{c}}, \mathbf{c} \in L\}, CX\boldsymbol{\theta} - \mathbf{h} \rangle, \quad (4)$$

and the variety defined by the polynomial ideal I ,

$$V(I) = \{\boldsymbol{\theta} \in \mathbb{Q}^m \mid f(\boldsymbol{\theta}) = 0, \forall f \in I\},$$

corresponds to the set of the coefficients of the indicator functions of the fractional factorial designs with the given properties. Note that $V(I)$ is finite, i.e., I is a 0-dimensional ideal. See [1] and [2] for detail.

3 24-runs cross-array designs for 6 control factors and 3 noise factors with two-levels

In this section, we use the theory given in the previous section to the problem of 24-runs designs for 6 control factors and 3 noise factors. Therefore the problem we consider corresponds to the case

$$p = 6, q = 3, s = 3, A_1 = \cdots = A_6 = B_1 = \cdots = B_3 = \{-1, 1\}, m = 2^3 \cdot 2^3 = 64.$$

The defining relation (1) is given by

$$x_4 = g_1(x_1, x_2, x_3) = x_1 x_2, x_5 = g_2(x_1, x_2, x_3) = x_1 x_3, x_6 = g_3(x_1, x_2, x_3) = x_2 x_3.$$

Because we consider two-level cases, the algebraic equations (3) reduce to

$$\theta_{\mathbf{c}} = \sum_{\mathbf{c}' \in L} \theta_{\mathbf{c}'} \theta_{\mathbf{c} \Delta \mathbf{c}'} \quad \mathbf{c} \in L, \quad (5)$$

where we denote by Δ the symmetric difference for $I, I' \in L$, i.e., $I \Delta I' = (I \cup I') \setminus (I \cap I')$. See Proposition 3.7 of [4] for detail.

To consider the constraints on \mathbf{u} , we introduce notations of *contingency tables* as follows. For each response $\mathbf{u} \in \{0, 1\}^{64}$ on $D_x^* \times D_y = \{-1, 1\}^3 \times \{-1, 1\}^3$, we treat \mathbf{u} as a 2^6 contingency table with the set of cells $\mathcal{I} = \{1, 2\}^6$ and write $\mathbf{u} = (u(\mathbf{i}))_{\mathbf{i} \in \mathcal{I}}$. We specify each cell $\mathbf{i} \in \mathcal{I}$ by $\mathbf{i} = (i_1, i_2, i_3, j_1, j_2, j_3)$. For each subset T of $\{1, \dots, 6\}$, we define T -marginal table $\mathbf{u}_T = (u_T(\mathbf{i}_T))_{\mathbf{i}_T \in \mathcal{I}_T}$ by

$$u_T(\mathbf{i}_T) = \sum_{\mathbf{i}_{T^C} \in \mathcal{I}_{T^C}} u(\mathbf{i}_T, \mathbf{i}_{T^C}),$$

where D^C denotes the complement of T , and \mathcal{I}_T be the set of T -marginal cells $\mathcal{I}_T = \prod_{i \in T} \{1, 2\}$. Note that in $u(\mathbf{i}_T, \mathbf{i}_{T^C})$, the indices in \mathcal{I}_T are collected to the left for notation simplicity. These notations are somewhat unnecessarily exaggerated for our problem,

but since they are common in the literatures of contingency tables, we will use them. The notations we use in this section are the one-dimensional marginal tables such as $\mathbf{u}_1 = (u_1(i_1))_{i_1 \in \{1,2\}}$ where

$$u_1(i_1) = \sum_{i_2=1}^2 \sum_{i_3=1}^2 \sum_{j_1=1}^2 \sum_{j_2=1}^2 \sum_{j_3=1}^2 u(i_1, i_2, i_3, j_1, j_2, j_3), \quad i_1 \in \{1, 2\},$$

the two-dimensional marginal tables such as $\mathbf{u}_{24} = (u_{24}(i_2, j_1))_{(i_2, j_1) \in \{1,2\}^2}$ where

$$u_{24}(i_2, j_1) = \sum_{i_1=1}^2 \sum_{i_3=1}^2 \sum_{j_1=1}^2 \sum_{j_3=1}^2 u(i_1, i_2, i_3, j_1, j_2, j_3), \quad (i_2, j_1) \in \{1, 2\}^2$$

and the three-dimensional marginal tables such as $\mathbf{u}_{236} = (u_{236}(i_2, i_3, j_3))_{(i_2, i_3, j_3) \in \{1,2\}^3}$ where

$$u_{236}(i_2, i_3, j_3) = \sum_{i_1=1}^2 \sum_{j_1=1}^2 \sum_{j_2=1}^2 u(i_1, i_2, i_3, j_1, j_2, j_3), \quad (i_2, i_3, j_3) \in \{1, 2\}^3$$

and so on.

For each response $\mathbf{u} \in \{0, 1\}^{64}$ on $D_x^* \times D_y$, we also treat \mathbf{u} as a response on $D_x \times D_y = \{-1, 1\}^6 \times \{-1, 1\}^3$ to take the effects of the control factors x_4, x_5, x_6 into consideration. In that case, we write \mathbf{u}^* instead of \mathbf{u} and treat it as a 2^9 contingency table. Though somewhat abusing notations, each element of \mathbf{u}^* is written as $u^*(i_1, i_2, i_3, i_4, i_5, i_6, j_1, j_2, j_3)$, and the meaning of the subscripts of marginal tables \mathbf{u}_T^* changes from \mathbf{u}_T . For example, the three-dimensional marginal table $\mathbf{u}_{236}^* = (u_{236}^*(i_2, i_3, i_6))_{(i_2, i_3, i_6) \in \{1,2\}^3}$ means

$$u_{236}^*(i_2, i_3, i_6) = \sum_{i_1=1}^2 \sum_{i_4=1}^2 \sum_{i_5=1}^2 \sum_{j_1=1}^2 \sum_{j_2=1}^2 \sum_{j_3=1}^2 u^*(i_1, i_2, i_3, i_4, i_5, i_6, j_1, j_2, j_3), \quad (i_2, i_3, i_6) \in \{1, 2\}^3.$$

Now we consider constraints for the fractions. First, the constraints for the size of the designs, i.e., the constraints meaning that “for each $(x_1, x_2, x_3) \in \{-1, 1\}^3$, 3 design points are contained in the fractions”, are represented as

$$u_{123}(i_1, i_2, i_3) = 3 \quad \text{for } (i_1, i_2, i_3) \in \{1, 2\}^3. \quad (6)$$

For late use, we prepare the definition on the uniformity of the marginal tables.

Definition 3.1. We define T -marginal table $\mathbf{u}_T = (u_T(\mathbf{i}_T))_{\mathbf{i}_T \in \mathcal{I}_T}$ is *uniform* if all of $\{u_T(\mathbf{i}_T), \mathbf{i}_T \in \mathcal{I}_T\}$ coincides.

Therefore the constraint (6) is also written as “ \mathbf{u}_{123} is uniform”, under the constraint that the size of the design is 24, i.e., $\mathbf{u}_\emptyset = \mathbf{u}_\emptyset^* = 24$.

Now we consider the properties our 24-runs designs should have. Our strategy is to construct 24-runs designs with uniform marginal tables that hold for 32-runs direct product type design of Table 2 as much as possible. Therefore first we summarize the uniformity of the marginal tables for the 32-runs direct product type design.

Proposition 3.2. For the cross-array design with direct product structure given in Table 2, all the two-dimensional marginals of \mathbf{u}^* are uniform, and the three-dimensional marginals except for \mathbf{u}_{124}^* , \mathbf{u}_{135}^* , \mathbf{u}_{236}^* , \mathbf{u}_{456}^* and \mathbf{u}_{789}^* are uniform.

Proof. It is easily checked. \square

Proposition 3.2 means that the design of Table 2 is an orthogonal design of strength 2, but not of strength 3. Note that a design F is *orthogonal of strength t* , if for any t factors, all possible combinations of levels appear equally often in F . See Chapter 7 of [8] for detail. As we have stated in Section 1, we can estimate all the interaction effects between the control factors and the noise factors for this design, which is the principle merit of the direct product type cross-array design. This important property is guaranteed by the uniformity of $\mathbf{u}_{\ell_1\ell_2\ell_3}^*$ for $1 \leq \ell_1 < \ell_2 \leq 6$, $7 \leq \ell_3 \leq 9$ under the orthogonality of strength 2.

Our strategy is to construct designs that have the similar properties to Proposition 3.2 as much as possible as 24-runs designs. Unfortunately, however, it is impossible to construct 24-runs designs that can estimate all the interaction effects between the control factors and the noise factors, along with the main effects. This fact is obvious since the design size 24 is less than the number of parameters $1 + 9 + 6 \times 3 = 28$, i.e., the parameters for interception, main effects, and interaction effects. For the uniformity of the marginal tables, we have the following results.

Proposition 3.3. For 24-runs designs of 6 control factors and 3 noise factors with two-levels,

- (a) all of $\mathbf{u}_{\ell_1\ell_2\ell_3}^*$ for $1 \leq \ell_1 < \ell_2 \leq 6$, $7 \leq \ell_3 \leq 9$ cannot be uniform, and
- (b) all of $\mathbf{u}_{\ell_1\ell_2\ell_3}^*$ for $1 \leq \ell_1 \leq 6$, $7 \leq \ell_2 < \ell_3 \leq 9$ cannot be uniform.

Proof. Suppose \mathbf{u}_{127}^* and \mathbf{u}_{137}^* are uniform. Then the four-dimensional marginal table \mathbf{u}_{1237}^* satisfies

$$\sum_{i_3=1}^2 u_{1237}(i_1, 1, i_3, j_1) = \sum_{i_3=1}^2 u_{1237}(i_1, 2, i_3, j_1) = \sum_{i_2=1}^2 u_{1237}(i_1, i_2, 1, j_1) = \sum_{i_2=1}^2 u_{1237}(i_1, i_2, 2, j_1) = 3$$

for $(i_1, j_1) \in \{1, 2\}^2$. On the other hand, the entries of the three-dimensional marginal table \mathbf{u}_{167}^* is given as

$$u_{167}^*(i_1, 1, j_1) = u_{1237}^*(i_1, 1, 2, j_1) + u_{1237}^*(i_1, 2, 1, j_1)$$

and

$$u_{167}^*(i_1, 2, j_1) = u_{1237}^*(i_1, 1, 1, j_1) + u_{1237}^*(i_1, 2, 2, j_1)$$

for $(i_1, j_1) \in \{1, 2\}^2$ from the defining relation $x_6 = x_2x_3$. Therefore we have

$$(u_{167}^*(i_1, 1, j_1), u_{167}^*(i_1, 2, j_1)) \in \{(6, 0), (4, 2), (2, 4), (0, 6)\},$$

i.e., \mathbf{u}_{167}^* cannot be uniform and (a) is proved. (b) is proved in the same way. \square

From Proposition 3.3, we have a choice as to which three-dimensional marginals are uniform. Of course, \mathbf{u}_{124}^* , \mathbf{u}_{135}^* , \mathbf{u}_{236}^* and \mathbf{u}_{456}^* cannot be uniform from the defining relation. We consider the constraints for the remaining three-dimensional marginals summarized as follows.

Proposition 3.4. 24-runs designs of 6 control factors and 3 noise factors with two-levels satisfying the following constraints exist.

- (a) All two-dimensional marginal tables of \mathbf{u}^* is uniform.
- (b) $\mathbf{u}_{124}^*, \mathbf{u}_{135}^*, \mathbf{u}_{236}^*, \mathbf{u}_{456}^*, \mathbf{u}_{16\ell}^*, \mathbf{u}_{25\ell}^*, \mathbf{u}_{34\ell}^*, \mathbf{u}_{4\ell_1\ell_2}^*, \mathbf{u}_{5\ell_1\ell_2}^*, \mathbf{u}_{6\ell_1\ell_2}^*, \ell = 7, 8, 9, 7 \leq \ell_1 < \ell_2 \leq 9$ are not uniform. All the other three-dimensional marginal tables are uniform.

Proof. Straightforward from Proposition 3.3. □

The reason to consider the constraints of this type is revealed below. We can show that the designs satisfying the conditions of Proposition 3.4 can be characterized as the orthogonal fractions of strength 3 for $x_1, x_2, x_3, y_1, y_2, y_3$.

Theorem 3.5. 24-runs designs of 6 control factors and 3 noise factors with two-levels satisfy the constraints of Proposition 3.4 if and only if all three-dimensional marginal tables of \mathbf{u} are uniform.

Proof. By calculating the summations, it is straightforward to show that \mathbf{u}^* satisfies the constraints of Proposition 3.4 if all three-dimensional marginal tables of \mathbf{u} are uniform. To show the reverse direction, we show that the uniformity of \mathbf{u}_{267}^* can be removed from the constraints of Proposition 3.4. From the uniformity of \mathbf{u}_{237}^* , the four-dimensional marginal tables \mathbf{u}_{2367}^* satisfies

$$\sum_{i_6=1}^2 u_{2367}^*(i_2, i_3, i_6, i_7) = 3, \quad (i_2, i_3, i_7) \in \{1, 2\}^3.$$

From the defining relation $x_2x_3 = x_6$, the four-dimensional marginal tables \mathbf{u}_{2367}^* also satisfies

$$\begin{aligned} \sum_{i_7=1}^2 u_{2367}^*(i_2, i_3, 1, i_7) = 6, \quad \sum_{i_7=1}^2 u_{2367}^*(i_2, i_3, 2, i_7) = 0, \quad (i_2, i_3) \in \{(1, 2), (2, 1)\}, \\ \sum_{i_7=1}^2 u_{2367}^*(i_2, i_3, 1, i_7) = 0, \quad \sum_{i_7=1}^2 u_{2367}^*(i_2, i_3, 2, i_7) = 6, \quad (i_2, i_3) \in \{(1, 1), (2, 2)\}. \end{aligned}$$

These relation determines \mathbf{u}_{2367}^* uniquely as

$$\begin{aligned} u_{2367}^*(i_2, i_3, 1, i_7) = 3, \quad u_{2367}^*(i_2, i_3, 2, i_7) = 0, \quad (i_2, i_3) \in \{(1, 2), (2, 1)\}, i_7 = 1, 2, \\ u_{2367}^*(i_2, i_3, 1, i_7) = 0, \quad u_{2367}^*(i_2, i_3, 2, i_7) = 3, \quad (i_2, i_3) \in \{(1, 1), (2, 2)\}, i_7 = 1, 2, \end{aligned}$$

which yields that \mathbf{u}_{267}^* is uniform. All the constraints including x_4, x_5, x_6 , i.e., $\mathbf{u}_{14\ell}^*, \mathbf{u}_{15\ell}^*, \mathbf{u}_{24\ell}^*, \mathbf{u}_{26\ell}^*, \mathbf{u}_{35\ell}^*, \mathbf{u}_{36\ell}^*, \mathbf{u}_{45\ell}^*, \mathbf{u}_{46\ell}^*$ and $\mathbf{u}_{56\ell}^*$ for $\ell = 7, 8, 9$, can be removed similarly. □

Now we can define the ideal to enumerate designs as the coefficients of the corresponding indicator functions. From Theorem 3.5, it is sufficient to consider the algebraic equations for $2^6 = 64$ variables, not for $2^9 = 512$ variables. Because our problem is for two-level factors, the algebraic equations to solve is given by (5) with constraints. The

constraints of Theorem 3.5 is written in the form of $C\mathbf{u} = CX\boldsymbol{\theta} = \mathbf{h}$. For example, the constraint that \mathbf{u}_{123} is uniform, i.e., $u_{123}(i_1, i_2, i_3) = 3$ for $(i_1, i_2, i_3) \in \{1, 2\}^3$, is written in the form of $CX\boldsymbol{\theta} = \mathbf{h}$ for $C = E_8 \otimes \mathbf{1}_8^T$ and $\mathbf{h} = 3\mathbf{1}_8$, where E_8 denote an 8×8 identity matrix, $\mathbf{1}_8 = (1, 1, 1, 1, 1, 1, 1, 1)^T$ and \otimes denote a Kronecker product.

Remark 3.6. We express the constraints as $CX\boldsymbol{\theta} = \mathbf{h}$ with the general cases in mind. Since our problem is the two-level case, the structure of the indicator functions for two-level cases given by [4] can be used. In fact, the constraints of Theorem 3.5 is simply written as

$$\theta_{000000} = \frac{3}{8}, \theta_{a_1 a_2 a_3 b_1 b_2 b_3} = 0 \text{ for } a_1 + a_2 + a_3 + b_1 + b_2 + b_3 = 1, 2, 3. \quad (7)$$

In addition, by substituting (7) to (5), we also obtain

$$\theta_{a_1 a_2 a_3 b_1 b_2 b_3} = 0 \text{ for } a_1 + a_2 + a_3 + b_1 + b_2 + b_3 = 5, 6.$$

We can also check these results from the output of the algebraic computation.

Remark 3.7. From an application point of view, the constraint of the uniformity for \mathbf{u}_{456} is not so important, since the interaction effects between the noise factors are usually ignored. However, by actual computation, we find that all the solutions without the uniformity of \mathbf{u}_{456} also satisfy the uniformity of \mathbf{u}_{456} .

The calculations are done by Singular ([3]) installed in MacBook Pro, 2.3 GHz, Quad-Core, Intel Core i7. We use the command `minAssGTZ` to compute minimal primes of the ideal. After calculations within one minute, we find 192 solutions. We also find that all the solutions are classified into the same equivalence class for sign changes of levels and permutations of factors within control factors and within noise factors. One of the solutions is already shown in Table 3, with the indicator function

$$\begin{aligned} f(x_1, x_2, x_3, y_1, y_2, y_3) = & \frac{3}{8} + \frac{1}{8} (x_1 x_2 x_3 y_1 + x_1 x_2 x_3 y_2 - x_1 x_2 x_3 y_3 + x_1 x_2 y_1 y_2 + x_1 x_2 y_1 y_3 \\ & - x_1 x_2 y_2 y_3 + x_1 x_3 y_1 y_2 + x_1 x_3 y_1 y_3 + x_1 x_3 y_2 y_3 + x_2 x_3 y_1 y_2 \\ & - x_2 x_3 y_1 y_3 + x_2 x_3 y_2 y_3 - x_1 y_1 y_2 y_3 + x_2 y_1 y_2 y_3 - x_3 y_1 y_2 y_3). \end{aligned}$$

Although redundant, we also show some other solutions. By permuting noise factors and their levels, all the solution can be converted so that two points $(x_1, x_2, x_3, y_1, y_2, y_3) = (-1, -1, -1, -1, -1, -1)$ and $(-1, -1, -1, -1, -1, 1)$ are included in the design. We find there are 12 such solutions of Table 4, where F_1 is the design shown in Table 3.

Finally in this paper, we consider estimable parameters under the 24-runs design F_1 . By the calculation of a reduced Gröbner basis of the design ideal $I(F_1)$, we find a basis of $\mathbb{Q}[x_1, x_2, x_3, x_4, x_5, x_6, y_1, y_2, y_3]/I(F_1)$ as follows.

$$\begin{aligned} & 1, \quad x_1, \quad x_2, \quad x_3, \quad x_4, \quad x_5, \quad x_6, \quad y_1, \\ & y_2, \quad y_3, \quad x_1 y_2, \quad x_1 y_3, \quad x_2 y_2, \quad x_2 y_3, \quad x_3 y_3, \quad x_4 y_3, \\ & x_5 y_1, \quad x_5 y_3, \quad x_5 y_2, \quad x_6 y_2, \quad x_6 y_3, \quad y_1 y_2, \quad y_1 y_3, \quad y_2 y_3 \end{aligned}$$

This basis is derived from the reduced Gröbner basis under the reverse lexicographic term order. Since our interest is to estimate interaction effect between the control factors and

Table 4: The list of the indicator functions of 24-runs designs including $(x_1, x_2, x_3, y_1, y_2, y_3) = (-1, -1, -1, -1, -1, -1)$ and $(-1, -1, -1, -1, -1, 1)$. (All the other coefficients are zero. F_1 is displayed in Table 3.)

	F_1	F_2	F_3	F_4	F_5	F_6	F_7	F_8	F_9	F_{10}	F_{11}	F_{12}
θ_{000000}	$3/8$	$3/8$	$3/8$	$3/8$	$3/8$	$3/8$	$3/8$	$3/8$	$3/8$	$3/8$	$3/8$	$3/8$
θ_{111100}	$1/8$	$1/8$	$1/8$	$1/8$	$1/8$	$1/8$	$1/8$	$1/8$	$1/8$	$1/8$	$1/8$	$1/8$
θ_{111010}	$1/8$	$1/8$	$1/8$	$1/8$	$1/8$	$1/8$	$1/8$	$1/8$	$1/8$	$1/8$	$1/8$	$1/8$
θ_{111001}	$-1/8$	$1/8$	$-1/8$	$1/8$	$-1/8$	$1/8$	$-1/8$	$1/8$	$-1/8$	$-1/8$	$1/8$	$1/8$
θ_{110110}	$1/8$	$1/8$	$1/8$	$1/8$	$1/8$	$1/8$	$1/8$	$1/8$	$1/8$	$1/8$	$1/8$	$1/8$
θ_{110101}	$1/8$	$-1/8$	$-1/8$	$-1/8$	$1/8$	$-1/8$	$1/8$	$1/8$	$-1/8$	$1/8$	$-1/8$	$1/8$
θ_{110011}	$-1/8$	$-1/8$	$1/8$	$-1/8$	$1/8$	$1/8$	$1/8$	$-1/8$	$1/8$	$-1/8$	$1/8$	$-1/8$
θ_{101110}	$1/8$	$1/8$	$1/8$	$1/8$	$1/8$	$1/8$	$1/8$	$1/8$	$1/8$	$1/8$	$1/8$	$1/8$
θ_{101101}	$1/8$	$-1/8$	$1/8$	$1/8$	$-1/8$	$-1/8$	$1/8$	$-1/8$	$1/8$	$-1/8$	$1/8$	$-1/8$
θ_{101011}	$1/8$	$1/8$	$1/8$	$-1/8$	$1/8$	$-1/8$	$-1/8$	$-1/8$	$-1/8$	$1/8$	$-1/8$	$1/8$
θ_{011110}	$1/8$	$1/8$	$1/8$	$1/8$	$1/8$	$1/8$	$1/8$	$1/8$	$1/8$	$1/8$	$1/8$	$1/8$
θ_{011101}	$-1/8$	$1/8$	$1/8$	$-1/8$	$1/8$	$1/8$	$-1/8$	$-1/8$	$1/8$	$1/8$	$-1/8$	$-1/8$
θ_{011011}	$1/8$	$-1/8$	$-1/8$	$1/8$	$-1/8$	$-1/8$	$1/8$	$1/8$	$1/8$	$1/8$	$-1/8$	$-1/8$
θ_{100111}	$-1/8$	$1/8$	$-1/8$	$1/8$	$-1/8$	$1/8$	$-1/8$	$1/8$	$1/8$	$1/8$	$-1/8$	$-1/8$
θ_{010111}	$1/8$	$1/8$	$1/8$	$1/8$	$-1/8$	$-1/8$	$-1/8$	$-1/8$	$-1/8$	$-1/8$	$1/8$	$1/8$
θ_{001111}	$-1/8$	$-1/8$	$-1/8$	$-1/8$	$1/8$	$1/8$	$1/8$	$1/8$	$-1/8$	$-1/8$	$1/8$	$1/8$

Therefore the parameters in the corresponding statistical model

$$\begin{aligned} \mu + \sum_{i=1}^6 \alpha_i x_i + \sum_{j=1}^3 \beta_j y_j + \gamma_{11} x_1 y_1 + \gamma_{12} x_1 y_2 + \gamma_{13} x_1 y_3 + \gamma_{21} x_2 y_1 + \gamma_{22} x_2 y_2 + \gamma_{23} x_2 y_3 \\ + \gamma_{31} x_3 y_1 + \gamma_{32} x_3 y_2 + \gamma_{41} x_4 y_1 + \gamma_{42} x_4 y_2 + \gamma_{43} x_4 y_3 + \gamma_{51} x_5 y_1 + \gamma_{52} x_5 y_2 + \gamma_{61} x_6 y_1 \end{aligned} \quad (10)$$

are estimable.

4 Discussion

In this paper, we consider using the indicator functions to enumerate cross-array designs with some desirable properties. Although the theory of the indicator functions to enumerate designs is already given in previous papers, the computational feasibility becomes a problem in practice. In this paper, to avoid calculation for $2^9 = 512$ variables in a naive approach, we define the ideal for $2^6 = 64$ variables by considering constraints to have in the designs. It is true that our result is not general, i.e., we consider only one setting, 24-runs designs for 6 control factors and 3 noise factor. However, we think that our approach can be applicable to other settings. As another contribution, the 24-runs design obtained in this paper is valuable in application. By the obtained 24-runs design, we can estimate all the parameters in the statistical model with (up to) 14 interaction effects and all the main effects such as (10).

Somewhat interestingly, looking at Table 3, we find the “point symmetry” for the symbol \circ . It is easy to check that the group action for level changes and permutations of factors preserve this point symmetry. Therefore, all the 192 solutions have this point symmetry.

References

- [1] S. Aoki. (2019). Characterizations of indicator functions and contrast representations of fractional factorial designs with multi-level factors, *Journal of Statistical Planning and Inference*, **203**, 91–105.
- [2] S. Aoki and M. Noro. (2022). Use of primary decomposition of polynomial ideals arising from indicator functions to enumerate orthogonal fractions. *Japanese Journal of Statistics and Data Science*, **5**, 165–179.
- [3] W. Decker, G. -M. Greuel, G. Pfister and H. Schönemann. (2022). SINGULAR 4-3-1 — A computer algebra system for polynomial computations. <https://www.singular.uni-kl.de>.
- [4] R. Fontana, G. Pistone and M. P. Rogantin. (2000). Classification of two-level factorial fractions. *Journal of Statistical Planning and Inference*, **87**, 149–172.
- [5] G. Pistone, E. Riccomagno and H. P. Wynn. (2001). *Algebraic Statistics: Computational Commutative Algebra in Statistics*. Chapman & Hall, London.

- [6] G. Pistone and H. P. Wynn. (1996). Generalised confounding with Gröbner bases. *Biometrika*, **83**, 653–666.
- [7] G. Taguchi, S. Chowdhury and Y. Wu. (2005). *Taguchi's Quality Engineering, Handbook*. John Wiley & Sons Inc. New Jersey.
- [8] C. F. Jeff Wu and M. S. Hamada. (2009). *Experiments: Planning, analysis, and parameter design optimization*. 2nd ed. Wiley Series in Probability and Statistics: Texts and References Section. John Wiley & Sons Inc., New York. A Wiley-Interscience Publication.