

Nonorthogonal coding in spectrally-entangled photons

N.-Y Tsai¹ and H. H. Jen^{2,3,*}

¹*Department of Physics, National Taiwan University, Taipei 10617, Taiwan*

²*Institute of Atomic and Molecular Sciences, Academia Sinica, Taipei 10617, Taiwan*

³*Physics Division, National Center for Theoretical Sciences, Taipei 10617, Taiwan*

(Dated: November 22, 2022)

Controlling and engineering continuous spectral modes of entangled photons represents one of the promising approaches toward secure quantum communications. By using the telecom bandwidth generated from a cascade-emitted biphoton in atomic ensembles, a fiber-based long-distance quantum communication can be feasible owing to its low transmission loss. With multiplexed photon pairs, we propose to implement a nonorthogonal coding scheme in their spectral modes and present an architecture of multiple channels enabling a high-capacity transfer of codewords. Using the measures of the second-order correlations and associated visibility and contrast, we further quantify the performance of the proposed nonorthogonal coding scheme. Our results demonstrate the capability to encode and decode quantum information beyond the orthogonal coding scheme. The proposed scheme here can be applicable to a large-scale and multiuser quantum communication and pave the way toward an efficient and functional quantum information processing.

I. INTRODUCTION

A secure quantum communication can be ensured by use of quantum cryptography [1] and quantum key distributions [2, 3]. This complete security relies on the fundamental characteristics of quantum mechanics, where the uncertainty principle posits a limit on the accurate determination of conjugate observables simultaneously and the communication system cannot be found undisturbed under a measurement. The former allows two parties to share a random secret key, while the latter enables them to detect any eavesdropping from another party. To facilitate such secure communication, photons are great candidates to carry quantum information, while atoms are best serving as local storage of it. An efficient quantum interface between light and matter [4] thus provides the foundation to relay quantum information as in quantum repeaters [5, 6], which further promises a large-scale quantum network [7, 8] and scalable quantum computation.

One essential aspect of scalability in quantum science and technology using flying photonic qubits, in addition to the number of them, regards the multiple degrees of freedom that can be accessed in photons. These degrees of freedom for encoding and decoding quantum information can be discrete as light polarizations [9–13] or continuous as transverse momenta [14, 15], space [16], orbital angular momenta [17–23], and spectral modes of light [24–31]. With continuous-variable entanglement of optical modes in a multiplexing architecture [32, 33], a potential high-capacity quantum resource can be feasible, which gives rise to an enhanced performance in multimode quantum communication and high-dimensional quantum information processing [34].

In spite of using continuous modes of light as high-capacity quantum channels in quantum communication, an efficient light transmission is as well crucial and demanded, for example, in a fiber-based communication network [35–37]. This can be achieved by utilizing the telecommunication band-

width of light to minimize its transmission loss, which can be acquired in a cascade-emitted biphoton generated from an atomic ensemble [38–40], serving as an excellent frequency-entangled state between the telecom and infrared bandwidths. The telecom photon suffices long-distance quantum communication, while the infrared can be stored locally as a collective spin wave [41, 42] with high efficiency [43–45]. In this highly-correlated biphoton source, an almost pure single photons can be heralded by removing continuous frequency entanglement among them [46–48], which is useful and can be applied in quantum computation with linear optics [49], optical quantum network implementation [50], and realizing photon–photon quantum logic gates [51].

Here we propose to implement a nonorthogonal coding scheme in spectrally-entangled photons, where the biphoton source can be generated from an atomic diamond configuration under a four-wave mixing process [39, 48, 52]. The orthogonal coding of Hadamard codes has been implemented spectrally in the broadband entangled photons through spontaneous parametric down conversion, where a matched code recovers a sharp and narrow correlation peak [27]. To further go beyond the orthogonal coding scheme, we utilize the quasi-orthogonal space–time block code [54–56], a well developed technique in wireless classical communication. This block code is originally designed to transmit multiple and redundant copies of data stream across many antennas in a reliable manner even under an influence of channel transmission issues or data corruptions. Under the conditions of high transmission rates with low signal-to-noise ratios, the quasi-orthogonal code can outperform the orthogonal one in reducing the transmission bit-error rates [56]. This nonorthogonal coding scheme can be facilitated in a multiplexing platform of biphotons from multiple atomic ensembles, where the information of codewords is encoded in the spectral modes determined by Schmidt decompositions. We further propose a design of multiple R channels within each M photon pairs are multiplexed to encode the nonorthogonal codes. We quantify its performance by calculating the second-order correlation functions along with useful measures of visibility and contrast, up to a capacity of coding space dimension of M^R . We

* sappyjen@gmail.com

find that there can be a balance between the contrasts in the correlation functions and the code space dimensions, where a potentially best design can be identified in our multi-channel nonorthogonal coding scheme. Our results can shed new light on multiuser long-distance quantum communication with high capacity of coding channels and provide insights to a blueprint of scalable quantum network.

II. CORRELATION FUNCTION OF ENTANGLED PHOTON PAIRS

We first introduce the spectral function of the entangled photon pairs generated via the four-wave mixing process. These photon pairs can be generated in a cold atomic ensemble with a four-level structure as shown in Fig. 1. Two classical excitation pulses drive the atoms and lead to the cascaded emissions of signal and idler photons, which are highly correlated in their propagating directions. The Hamiltonian in interaction picture can be written as [28, 52]

$$V_I = - \sum_{m=1,2} \Delta_m \sum_{\mu=1}^N |m\rangle_\mu \langle m| - \sum_{m=a,b} \left(\frac{\Omega_m}{2} \hat{P}_m^\dagger + \text{H.c.} \right) - i \sum_{m=s,i} \left\{ \sum_{k_m, \lambda_m} g_m \hat{a}_{k_m, \lambda_m} \hat{Q}_m^\dagger e^{-i\Delta\omega_m t} - \text{H.c.} \right\}, \quad (1)$$

where we set $\hbar = 1$ and define the detunings as $\Delta_1 = \omega_a - \omega_1$, $\Delta_2 = \omega_a + \omega_b - \omega_2$. $\omega_{a,b,s,i}$ are central frequencies of the pump and emitted photon fields with corresponding wave vectors $\mathbf{k}_{a,b,s,i}$. The collective dipole operators with a number of atoms N are defined as $\hat{P}_a^\dagger \equiv \sum_{\mu=1}^N |1\rangle_\mu \langle 0| e^{i\mathbf{k}_a \cdot \mathbf{r}_\mu}$, $\hat{P}_b^\dagger \equiv \sum_{\mu=1}^N |2\rangle_\mu \langle 1| e^{i\mathbf{k}_b \cdot \mathbf{r}_\mu}$, $\hat{Q}_s^\dagger \equiv \sum_{\mu=1}^N |2\rangle_\mu \langle 3| e^{i\mathbf{k}_s \cdot \mathbf{r}_\mu}$, $\hat{Q}_i^\dagger \equiv \sum_{\mu=1}^N |3\rangle_\mu \langle 0| e^{i\mathbf{k}_i \cdot \mathbf{r}_\mu}$, respectively. The coupling constant g_m has absorbed $(\epsilon_{\mathbf{k}_m, \lambda_m} \cdot \hat{d}_m^*)$, which involves the polarizations of quantized bosonic fields $\bar{\lambda}_m$ and the unit direction of the dipole operators \hat{d}_m .

Under the four-wave fixing condition $\Delta\mathbf{k} \equiv \mathbf{k}_a + \mathbf{k}_b - \mathbf{k}_s - \mathbf{k}_i = 0$ and the weak excitation limit, the state function of the system can be obtained as

$$|\Psi\rangle \approx |0\rangle^{\otimes N} + \frac{\tilde{\Omega}_a \tilde{\Omega}_b g_s^* g_i^* \sum_{\mu=1}^N e^{i\Delta\mathbf{k} \cdot \mathbf{r}_\mu}}{4\Delta_1 \Delta_2 \sqrt{2\pi\tau}} \times \frac{e^{-(\Delta\omega_s + \Delta\omega_i)\tau^2/8}}{\Gamma_3^N/2 - i\Delta\omega_i} |1_{\mathbf{k}_s}, 1_{\mathbf{k}_i}\rangle, \quad (2)$$

where the detail of the above derivation can be found in Appendix, and we have defined the pulse areas of Gaussian wave packets as $\tilde{\Omega}_a, \tilde{\Omega}_b$, their common pulse durations τ , a super-radiant decay rate Γ_3^N depending on system density and geometry [38], and the respective detunings for signal and idler photons $\Delta\omega_s \equiv \omega_s - \omega_2 + \omega_3 - \Delta_2$, $\Delta\omega_i \equiv \omega_i - \omega_3$. The overall constant of the biphoton state in Eq. (2) represents the probability related to its generation rate, which can be expressed in continuous frequency spaces,

$$|\Psi_b\rangle = \frac{1}{\mathcal{N}} \int \int f(\omega_s, \omega_i) \hat{a}_s^\dagger \hat{a}_i^\dagger |0, 0\rangle d\omega_s d\omega_i, \quad (3)$$




FIG. 1. A multiplexed coding scheme. A number of n atomic ensembles are illustrated to generate n photon pairs, where an inset plot shows the four-level atomic configuration with a single- and two-photon detuning, Δ_1 and Δ_2 , respectively. The pump fields drive the atomic transitions $|0\rangle \rightarrow |1\rangle$ and $|1\rangle \rightarrow |2\rangle$, respectively, which lead to subsequently and spontaneously emitted signal photon \hat{a}_s and idler photon \hat{a}_i . The encoding operations H_1^c to H_n^c act on individual signal photons, which are frequency-multiplexed together with the corresponding idler photons by frequency shifters (FS), followed by the decoding operations H_{s1}^d to H_{sk}^d and H_{i1}^d to H_{ik}^d on the signal and idler photons, respectively. A single-channel scheme represents the case when $k = k' = n$, while in general a multi-channel scheme allows $k \neq k'$ and $k, k' < n$, leading to a huge code space in the nonorthogonal coding scheme.

with a normalization factor \mathcal{N} and an effective biphoton spectral function of

$$f(\omega_s, \omega_i) = \frac{e^{-(\Delta\omega_s + \Delta\omega_i)\tau^2/8}}{\Gamma_3^N/2 - i\Delta\omega_i}. \quad (4)$$

The joint Gaussian distribution in the above conserves the signal and idler photon energies as $\omega_s + \omega_i = \omega_a + \omega_b$ with a spectral width approximately determined by $1/\tau$, which indicates an entangling origin in contrast to a separate idler distribution in a Lorentzian profile with a width of Γ_3^N .

The continuous entanglement entropy in the biphoton state can be analyzed through Schmidt decompositions [25, 26], where the state can be reinterpreted as $|\Psi_b\rangle = \sum_{n=1}^{\infty} \sqrt{\lambda_n} b_n^\dagger c_n^\dagger |0, 0\rangle$ with a probability λ_n under the orthogonal Schmidt modes $\psi_n(\omega_s)$ and $\phi_n(\omega_i)$, that is $b_n^\dagger = \int \psi_n(\omega_s) \hat{a}_s^\dagger(\omega_s) d\omega_s$ and $c_n^\dagger = \int \phi_n(\omega_i) \hat{a}_i^\dagger(\omega_i) d\omega_i$, respectively. A normalization of $\sum_{n=1}^{\infty} \lambda_n = 1$ should be satisfied and the entanglement entropy can be calculated as $S = -\sum_{n=1}^{\infty} \lambda_n \ln \lambda_n$, which leads to an entangled bipartite source as long as $\lambda_1 \neq 1$, otherwise it suggests a separable state with $S = 0$.

Next we obtain the second-order correlation function, which is proportional to the coincidence rate and is essential in determining the outcome of the performance in the encoding and decoding scheme we propose here. It can be calculated as

[53]

$$g^{(2)}(\tau) = \frac{\langle \hat{E}_s^{(-)}(t) \hat{E}_i^{(-)}(t+\tau) \hat{E}_i^{(+)}(t+\tau) \hat{E}_s^{(+)}(t) \rangle}{\langle \hat{E}_s^{(-)}(t) \hat{E}_s^{(+)}(t) \rangle \langle \hat{E}_i^{(-)}(t) \hat{E}_i^{(+)}(t) \rangle}, \quad (5)$$

$$\hat{E}_s^{(+)}(t) = \sum_{k_s, \lambda_s} \sqrt{\frac{\hbar \omega_s}{2\epsilon_0 V}} \hat{a}_{k_s, \lambda_s} \vec{\epsilon}_{k_s, \lambda_s} e^{-i\omega_s t}, \quad (6)$$

$$\hat{E}_i^{(+)}(t) = \sum_{k_i, \lambda_i} \sqrt{\frac{\hbar \omega_i}{2\epsilon_0 V}} \hat{a}_{k_i, \lambda_i} \vec{\epsilon}_{k_i, \lambda_i} e^{-i\omega_i t}. \quad (7)$$

We assume that the photon pairs are transmitted through single-mode fibers. Therefore the spatial correlations can be neglected and we focus only on their frequency correlations. Here we consider $t \rightarrow \infty$ and choose $\tau = 0$. We then obtain $g^{(2)}(0)$ under the Schmidt bases as

$$g^{(2)}(0) = \int \left| \sum_{n=1}^{\infty} \sqrt{\lambda_n} (\psi_n * \phi_n)(\omega) \right|^2 d\omega, \quad (8)$$

$$(\psi_n * \phi_n)(\omega) = \int \psi_n(\omega_s) \phi_n(\omega - \omega_s) d\omega_s,$$

where the zero-time second-order correlation function is equivalent to the integral of convolutions between the signal and idler photon eigenmodes in frequency spaces.

III. MAIN RESULTS

Here we show our main results of the second-order correlations $g^{(2)}(0)$ from the proposed scheme as shown in Fig. 1, where we can quantify its performance by the contrast of $g^{(2)}(0)$. For both a single-channel and multi-channel nonorthogonal coding scheme, we multiplex the signal and idler photon pairs by frequency shifters, leading to well-separated spectral modes which are feasible for individual mode addressing. The multiplexed spectral function by frequency shifters can be expressed in general as

$$f_M(\omega_s, \omega_i) = \sum_{n=1}^{N_{\text{ph}}} H_n \frac{e^{-(\Delta\omega_s + \Delta\omega_i + \delta_{qn})^2 \tau^2 / 8}}{\Gamma_3^N / 2 - i(\Delta\omega_i - \delta_{pn})}, \quad (9)$$

$$\equiv \sum_{n=1}^{N_{\text{ph}}} H_n f_n(\omega_s, \omega_i), \quad (10)$$

where H_n represents the multiplexed weights on the individual photon pairs with δ_{pn} the frequency shift in the idler photon and δ_{qn} the joint frequency shift in the signal and idler photons. H_n can be controlled by external laser driving parameters as in Eq. (2), which can be treated further as the encoding operations $H_n = H_n^e$ in Fig. 1. Throughout the paper, we arrange the multiplexed photon pairs in parallel with an energy-conserved axis satisfying $\Delta\omega_s + \Delta\omega_i = 0$, corresponding to anti-correlated signal and idler photons without loss of generality.

Under this frequency-separated multiplexed scheme, the first N_{ph} eigenmodes determined by Schmidt decompositions in a descending order of λ_n become almost degenerate and

dominate over the other modes. We then can approximate the eigenmodes in Eq. (8) by using the integrated profiles of signal and idler photons, respectively,

$$\psi_n(\omega_s) \propto \int_{-\infty}^{\infty} f_n(\omega_s, \omega_i) d\omega_i, \\ = -\frac{1}{N_s} e^{-(\Delta\omega_s + \delta_{pn} + \delta_{qn} + i\Gamma_3^N / 2)^2 \tau^2 / 8}, \quad (11)$$

$$\phi_n(\omega_i) \propto \int_{-\infty}^{\infty} f_n(\omega_s, \omega_i) d\omega_s, \\ = \frac{1}{N_i} \frac{1}{\Gamma_3^N / 2 - i(\Delta\omega_i - \delta_{pn})}, \quad (12)$$

where N_s, N_i are normalization factors for these N_{ph} signal and idler eigenmodes with frequency shifts $-(\delta_{pn} + \delta_{qn})$ and δ_{pn} in Gaussian and Lorentzian profiles, respectively. The convolution in Eq. (8) can further be obtained as

$$(\psi_n * \phi_n)(\omega) = \frac{1}{N_s N_i} e^{-(\omega + \delta_{qn})^2 \tau^2 / 8}, \quad (13)$$

which depends only on the joint frequency shift δ_{qn} . This leads to $g^{(2)}(0) = 2\sqrt{\pi}/(N_s^2 N_i^2 \tau)$ in a well-separated multiplexed scheme as $\delta_{qn} \gg \delta_{qn'}$. Next we introduce the nonorthogonal coding under this multiplexed scheme.

A. Nonorthogonal multiplexed coding scheme

First, we consider the multiplexed photon pairs under $\delta_{qn} = 0$, where spectrally-entangled signal and idler photons locate along the energy-conservation axis and we denote it as a single channel coding scheme. In this way, the encoding operations are denoted as H_m^e on the signal photons, and the decoding ones on the idler photons are represented by H_{im}^d for $m = [1, N_{\text{ph}}]$ with $H_{sm}^d = 1$ in Fig. 1. The coding operations in general involve both the phase and amplitude modulations on the respective photon pairs, which can be facilitated by a phase imprinting technique and beam splitters. We can approximate $g^{(2)}(0)$ by considering only the first N_{ph} modes as in Eq. (13), and from Eq. (8) we obtain

$$g^{(2)}(0) \approx \frac{2\sqrt{\pi}}{N_s^2 N_i^2 \tau N_{\text{ph}}} \left| \sum_{n=1}^{N_{\text{ph}}} H_{in}^d H_n^e \right|^2, \quad (14)$$

where $\lambda_n \approx 1/N_{\text{ph}}$. When the encoding and decoding codes are matched, $g^{(2)}(0)$ manifests a maximum, while it drops significantly in the mismatched case, for example in the orthogonal Hadamard codes [27].

To go beyond the orthogonal coding scheme, here we introduce the quasi-orthogonal space-time block codes, which have been useful in multiuser antenna systems. This nonorthogonal code can be constructed from the so-called Alamouti 2×2 codes [54–56],

$$C_{1,2} = \begin{pmatrix} c_1 & c_2 \\ -c_2^* & c_1^* \end{pmatrix}, \quad (15)$$

from which Alamouti $N_a \times N_a$ codes can be generated by an extension of Alamouti form with arbitrary c_1 and c_2 . We take $N_a = 4$ as an example, which reads

$$C_{1,4} = \begin{pmatrix} C_{1,2} & C_{3,4} \\ -C_{3,4}^* & C_{1,2}^* \end{pmatrix} = \begin{pmatrix} c_1 & c_2 & c_3 & c_4 \\ -c_2^* & c_1^* & -c_4^* & c_3^* \\ -c_3^* & -c_4^* & c_1^* & c_2^* \\ c_4 & -c_3 & -c_2 & c_1 \end{pmatrix}. \quad (16)$$

In the above, the orthogonal relations only hold between the columns (1, 2), (1, 3), (2, 4), and (3, 4), and again c_3 and c_4 are arbitrary. In general, the nonorthogonal codes can be constructed as

$$C_{1,N} = \begin{pmatrix} C_{1,N/2} & C_{N/2+1,N} \\ -C_{N/2+1,N}^* & C_{1,N/2}^* \end{pmatrix}, \quad (17)$$

with an even N .

We can then implement the encoding H_m^e and decoding operations H_m^d using the column vectors of Eq. (17) as the nonorthogonal coding scheme. We note that the choice of $\vec{c} = (c_1, c_2, \dots, c_N)$ from $c_l = ar^{l-1}$ with arbitrary a and r , for example, can lead to an orthogonal coding scheme. Therefore, in general the nonorthogonal coding scheme involves an orthogonal one as a special case. To quantify the coding performance in terms of contrasts in correlations, we define the visibility $V = (g_{\max}^{(2)} - g_{\min}^{(2)}) / (g_{\max}^{(2)} + g_{\min}^{(2)})$ and the off-diagonal contrast $C_{\text{od}} = (g_{\max}^{(2)} - g_{\text{od}}^{(2)}) / (g_{\max}^{(2)} + g_{\text{od}}^{(2)})$, where we neglect the zero-time dependence for concise expressions. $g_{\max}^{(2)}$ and $g_{\min}^{(2)}$ are global maximum and minimum in $g^{(2)}(0)$, respectively, while $g_{\text{od}}^{(2)}$ represents the largest correlation element in the mismatched cases in the odd-diagonal (od) $g^{(2)}(0)$. This provides a way for distinguishing coding capability and its performance, under different choices of \vec{c} and various system parameters which we can control and manipulate in our proposed multiplexing scheme.

In Fig. 2, we present the second-order correlations in a single-channel nonorthogonal coding scheme. In Figs. 2(a) and 2(b), we implement the nonorthogonal coding scheme, where \vec{c} is chosen as to be N_{ph} equally-spaced points between $[1, h = 2]$. In the ideal case when δ_{pn} is large enough that the encoding operates on the well-separated spectral modes, we utilize Eq. (14) to demonstrate the ultimate high correlations when the codes are matched and their dependence on the number of entangled photon pairs in Figs. 2(a) and 2(b). To further demonstrate the effect of free parameters \vec{c} in the nonorthogonal coding scheme, we show V and C_{od} in Fig. 2(c) as h varies. At $h = 1$, $\vec{c} = (1, 1, \dots, 1)$, which reduces the nonorthogonal codes to the orthogonal ones as Hadamard codes. V stays maximized since $g_{\min}^{(2)}$ can be vanishing in the nonorthogonal coding scheme owing to its quasi-orthogonality property. On the other hand, C_{od} is maximized for the Hadamard codes, whereas the nonorthogonal codes can still maintain significant contrasts within our considered range of $h > 1$. Below $h = 1$ in Fig. 2(c), \vec{c} is chosen within $[h, 1]$ and is more prone to the nonorthogonal nature than in the range of $h > 1$. Therefore, C_{od} suffers from and decreases more for a larger N_{ph} . We note that the overall scaling of \vec{c}




FIG. 2. Second-order correlation $g^{(2)}(0)$ in a single-channel nonorthogonal coding scheme. The ideal spectral decoding performance of $g^{(2)}(0)$ for (a) $N_{\text{ph}} = 4$ and (b) 16, respectively, where $\delta_{pn} \rightarrow \infty$ and $\lambda_{n \in [1, N_{\text{ph}}]} = 1/\sqrt{N_{\text{ph}}}$. The parameters of \vec{c} is chosen by setting $h = 2$. As a comparison in the ideal case, V (blue- \square and $-o$) and C_{od} (red- \square and $-o$) are plotted as h varies in (c), where $N = 4$ (\square) and 16 ($-o$), respectively. In (d), V (blue- \square and $-x$) and C_{od} (red- \square and $-x$) are plotted as δ varies for $N = 4$ and $h = 1$, with the frequency shifts of photon pairs $\delta_{p1} = -1.5\delta$, $\delta_{p2} = -0.5\delta$, $\delta_{p3} = 0.5\delta$, $\delta_{p4} = 1.5\delta$. The excitation pulse durations are chosen as $\Gamma\tau = 0.25$ (o) and 0.4 (x), respectively, for comparisons. We consider $\Gamma/2\pi = 6\text{MHz}$ as an example for D_1 transition of rubidium atoms and $\Gamma_3^N/\Gamma = 5$.

does not matter in the contrasts, and therefore C_{od} would be the same according to the condition of $hh' = 1$ for \vec{c} chosen between $[h' < 1, 1]$ and $[1, h > 1]$, respectively. This can be seen and expected in Fig. 2(c).

In Fig. 2(d), we further investigate the impact from the spectral interferences between each multiplexed spectral modes. We take $N_{\text{ph}} = 4$ as an example with a frequency coding bin with a range of δ . As δ increases, the multiplexed modes approach the ideal case for C_{od} as in Fig. 2(c), where $C_{\text{od}} \rightarrow 1$. When δ is finite, these multiplexed modes are subject to finite spectral interferences, leading to a suppression of C_{od} . This can be attributed to imperfect encoding and decoding operations in frequency spaces, contrary to the assumption of well-separated frequency modes. As we vary the excitation pulse duration τ , a shorter pulse manifests a broader spread of frequency correlations, which enhances the spectral interferences and gives rise to the suppression of C_{od} . The visibility V here stays maximized in our considered large range of δ , which is less sensitive to the effect of spectral interferences than C_{od} .

B. Multiple channels

Here we extend the previous single-channel setup to a multi-channel platform by releasing the requirement of $\delta_{qn} = 0$. Multiple channels can then be constructed by well sepa-




FIG. 3. The decoding operations in multiple channels. Yellow filled circles represent the photon pairs encoded by $H_n^e = H_{rm}^e$ where $n = r + (m - 1)R$, under the multiplexed scheme in a frequency-separated domain. The decoding operations H_{sk}^d and $H_{ik'}^d$ on the signal and idler photons, respectively, result in effectively the decoding operation $H_{rm}^d = H_{sk}^d H_{ik'}^d$ on the spectrally-entangled modes of the photon pairs. The numbers in blue circles in (a) indicate how many degrees of freedom left in H_{sk}^d or $H_{ik'}^d$ that can be added for decoding operations. The photon pairs cannot be placed at the multiplexed domain with the number equal to 0, giving the constraint for the multiplexed photon pairs in a multi-channel structure. In (b), an example of $M = 4$ photon pairs each for $R = 2$ channels shows one of the dense structures of code spaces with only one redundant degree of freedom in either H_{sk}^d or $H_{ik'}^d$.

rating $\delta_{qn} = \delta_r$ as shown in Eq. (13), where each channel with specific δ_r does not crosstalk with each other when δ_r is large enough with vanishing spectral interferences. Under this ideal condition, the correlation function for R channels and M multiplexed photon pairs in each channel in general can be obtained as

$$g^{(2)}(0) = \frac{1}{N_s^2 N_i^2} \int \left| \sum_{r=1}^R \sum_{m=1}^M \sqrt{\lambda_{rm}} e^{-(\omega + \delta_r)^2 \tau^2 / 8} \right|^2 d\omega, \quad (18)$$

$$= \frac{2\sqrt{\pi}}{N_s^2 N_i^2 \tau M} \sum_{r=1}^R \left| \sum_{m=1}^M H_{rm}^e H_{rm}^d \right|^2,$$

where the decoding operation H_{rm}^d requires both signal and idler coding operations H_{sk}^d and $H_{ik'}^d$, respectively, as shown in Fig. 3. The encoding and decoding operations H_{rm}^e and H_{rm}^d correspond to $H_{n=(r-1)M+m}^e$ and $H_{sk}^d H_{ik'}^d$, respectively. The total number of photon pairs are RM , and each code subspace in the r th channel can be constructed by the nonorthogonal code with a size M . In this design, spectrally-entangled modes in different channels allow for overlapped spectral coding, with an advantage of saving the limited frequency spaces. When encoding and decoding operations are matched in respective channels, $g^{(2)}(0)$ will reach its maximum. If R' channels are considered, $g^{(2)}(0)$ will be enhanced R' times as the matched case in a single-channel setup. In the multi-channel design in Fig. 3, the code space dimension will become M^R . This dimension grows exponentially to reach a maximum when an even M is chosen as 2.

There are some constraints on the frequency-multiplexed photon pairs in the design of Fig. 3. To achieve the encoding on the entangled modes which overlap in the signal or idler spectra, the design should ensure that any decoding operations H_{rm}^d can successfully reflect the nonorthogonal coding




FIG. 4. Multi-channel structure and $g^{(2)}(0)$. Three possible dense designing arrangements of photon pairs for $N_{\text{ph}} = 16$ are shown in (a-c), where $R = 2, 4$, and 8 with $M = 8, 4$, and 2 , respectively. We plot schematically by using $\delta = 100\Gamma$ to avoid significant C_{non} caused by spectral interferences from adjacent photon pairs. Corresponding correlations $g^{(2)}(0)$ are calculated in (d), (e), and (f), respectively, under the ideal spectral decoding scheme. The code space dimensions are 64, 256, and 256, respectively. The $\Gamma\tau$ is chosen as 0.5.

sequences. Therefore, in Fig. 3(a), we present a constraint on placing or multiplexing the photon pairs for encoding and decoding operations. The numbers in empty sites of potentially multiplexed photon pairs show the degrees of freedom that can be allowed by adding extra operations of H_{sk}^d and $H_{ik'}^d$. The place with a null number presents a forbidden scenario in the design that the nonorthogonal codes we utilize cannot be achieved. One of the dense structures in frequency spaces for photon pairs is shown in Fig. 3(b) for an even M , where we denote it as the staircase designing structure.

In Fig. 4, we demonstrate the multi-channel platform with 16 photon pairs in a multiplexing scheme in three different arrangements, which are the dense forms within the same frequency domains. We illustrate 2, 4, and 8 channels with 8, 4, and 2 photon pairs in each channel, respectively. Each channel encodes the nonorthogonal code subspaces C_{1M} with $\vec{c} = (1, M/(M-1), \dots, 2)$. δ_r are chosen as 100Γ to avoid the spectral interference as shown in Eq. (18) with the FWHM $\approx 9\Gamma$ under a short pulse duration $\Gamma\tau = 0.5$.

Figures 4(a), 4(b), and 4(c) with $\delta = 100\Gamma$ ensure that the spectral coding is well separated. This leads to the ideal coding operations in Figs. 4(d), 4(e), and 4(f), where we obtain $g^{(2)}(0)$ for comparisons. The same color legend indicates the same number of matched channel for our nonorthogonal codes. For example, in Fig. 4(d), $g^{(2)}(0)$ involves three kinds of finite values, which respectively correspond to 2, 1, and 0 channels matched cases. As a result, an increase of number of channel will lead to $g^{(2)}(0)$ with more distinctive finite values. A comparison between Figs. 4(e) and 4(f) shows that although they can both achieve the capacity of codes to a dimension of 256, the arrangement of 4 channels case has less number of finite values involved in $g^{(2)}(0)$ than that of 8 channels case. For more channels involved, the contrast $C_{non} = 1/(2R-1)$ becomes less significant. This can be

seen in Fig. 4(f), where a reduced contrast emerges compared to the cases in Figs. 4(d) and 4(e). Therefore, it would be optimal to have minimal possible channels in a multi-channel scheme with a greater contrast, as well as requiring the largest code space dimension that can be achieved for high-capacity transmission. As a demonstration, Fig. 4(b) stands out as the best design in the balance between the contrasts in $g^{(2)}(0)$ and the code space dimensions. In the results of $g^{(2)}(0)$, they can reach approximately the maximum of 6400, 3200, and 1600 under the matched cases in Figs. 4(d), 4(e), and 4(f), respectively, which can be explained by Eq.(18) associated with the normalization factor M . For a fixed number of photon pairs in each channel, a code space capacity can grow exponentially as M^R with an increasing channel number R , but nonetheless with a price of a reduced contrast in overall $g^{(2)}(0)$.

IV. CONCLUSION AND DISCUSSION

Our results demonstrate the realization of encoding and decoding nonorthogonal codes on the spectrally-entangled photons in a multiplexing scheme. The photon pairs can be generated from the atomic cascade emissions with an advantageous telecom bandwidth which is best for an application of long-distance quantum communication. We specifically utilize a quasi-orthogonal space-time block code, which is a well developed technique in wireless classical communication and is useful for transmitting multiple copies of data sequences across many users. This nonorthogonal coding scheme can be applied in a multiplexing platform of entangled biphotons, where we show the performance of the codewords in terms of the second-order correlations. We further propose a multi-channel design to encode the nonorthogonal codes, where a high capacity of coding space is feasible.

We have shown that the staircase structure of multiplexed photon pairs in a frequency-separated regime is the best dense structure that has the highest code space capacity with a limited frequency space. This design is particularly applicable in quantum information processing and transmission, and is ready for multi-user quantum key distribution [1]. Moreover, our schemes can potentially integrate with a reconfigurable bandwidth allocation among multiple users [57], which can further establish a practical scalable quantum networks, essential for an application of large-scale quantum computation.

ACKNOWLEDGMENTS

We acknowledge support from the Ministry of Science and Technology (MOST), Taiwan, under the Grant No. MOST-109-2112-M-001-035-MY3 and No. MOST-111-2119-M-001-002. We are also grateful for support from TG 1.2 and TG 3.2 of NCTS at NTU.

Appendix A: Biphoton state

To generate a spectrally-entangled photon pair [38], the system is driven under weak excitations that $\sqrt{N}|\Omega_a| \ll \Delta_1$. We then can express the state of the system using singly-excited Hilbert space [28, 52], which reads

$$|\psi(t)\rangle = \varepsilon(t)|0, vac\rangle + \sum_{\mu=1}^N A_{\mu}(t)|1_{\mu}, vac\rangle + \sum_{\mu=1}^N B_{\mu}(t)|2_{\mu}, vac\rangle + \sum_{\mu=1}^N \sum_s C_s^{\mu}(t)|3_{\mu}, 1_{\mathbf{k}_s, \lambda_s}\rangle + \sum_{s,i} D_{s,i}(t)|0, 1_{\mathbf{k}_s, \lambda_s}, 1_{\mathbf{k}_i, \lambda_i}\rangle, \quad (\text{A1})$$

where single excitation states and vacuum states are $|m_{\mu}\rangle = |m_{\mu}\rangle|0\rangle_{v \neq \mu}^{\otimes N-1}$ and $|vac\rangle$, respectively. By applying Schrodinger equation $i\hbar \frac{\partial}{\partial t} |\psi\rangle = V_I |\psi\rangle$, we obtain the equations of motion in a self-consistent form,

$$\begin{aligned} i\dot{\varepsilon} &= -\frac{\Omega_a^*}{2} \sum_{\mu=1}^N e^{-i\mathbf{k}_a \cdot \mathbf{r}_{\mu}} A_{\mu}, \\ i\dot{A}_{\mu} &= -\frac{\Omega_a}{2} e^{i\mathbf{k}_a \cdot \mathbf{r}_{\mu}} \varepsilon - \frac{\Omega_b^*}{2} e^{-i\mathbf{k}_b \cdot \mathbf{r}_{\mu}} B_{\mu} - \Delta_1 A_{\mu}, \\ i\dot{B}_{\mu} &= -\frac{\Omega_b}{2} e^{i\mathbf{k}_b \cdot \mathbf{r}_{\mu}} A_{\mu} - \Delta_2 B_{\mu} - i \sum_{\mathbf{k}_s, \lambda_s} e^{i\mathbf{k}_s \cdot \mathbf{r}_{\mu}} e^{-i\Delta\omega_s t} C_s^{\mu}, \\ \dot{C}_s^{\mu} &= i g_s^* e^{-i\mathbf{k}_s \cdot \mathbf{r}_{\mu}} e^{i\Delta\omega_s t} B_{\mu} - i \sum_{\mathbf{k}_i, \lambda_i} g_i e^{-i\mathbf{k}_i \cdot \mathbf{r}_{\mu}} e^{i\Delta\omega_i t} D_{s,i}, \\ i\dot{D}_{s,i} &= i g_i^* \sum_{\mu=1}^N e^{-i\mathbf{k}_i \cdot \mathbf{r}_{\mu}} e^{i\Delta\omega_i t} C_s^{\mu}, \end{aligned}$$

where a system generates a strongly-correlated biphoton state under the four-wave mixing process with a generation rate $\propto |D_{s,i}|^2$.

Under the large detuning condition, $|\Delta_{1,2}| \gg |\Omega_{a,b}|$, we can solve the equations of motion under the adiabatic approximation and obtain the steady-state solutions. Then we further obtain,

$$\begin{aligned} A_{\mu} &\approx -\frac{\Omega_a(t)}{2\Delta_1} e^{i\mathbf{k}_a \cdot \mathbf{r}_{\mu}}, \\ B_{\mu} &\approx \frac{\Omega_a \Omega_b}{4\Delta_1 \Delta_2} e^{i(\mathbf{k}_a + \mathbf{k}_b) \cdot \mathbf{r}_{\mu}}. \end{aligned} \quad (\text{A2})$$

C_s^{μ} can be solved by the probability amplitude C_{s, \mathbf{k}_i} in a momentum space of \mathbf{k}_i , where $C_{s, \mathbf{k}_i} = \sum_{\mu} C_s^{\mu} e^{-i\mathbf{k}_i \cdot \mathbf{r}_{\mu}}$. This leads to

$$\begin{aligned} C_{s, \mathbf{k}_i} &= g_s^* \sum_{\mu} e^{i\Delta\mathbf{k} \cdot \mathbf{r}_{\mu}} \int_{-\infty}^t dt' e^{i\Delta\omega_s t'} \\ &\times e^{[-(\Gamma_3^N/2) + i\delta\omega_i](t-t')} b(t'), \end{aligned} \quad (\text{A3})$$

where $b(t) = \frac{\Omega_a(t)\Omega_b(t)}{4\Delta_1\Delta_2}$. $\Gamma_3^N = (N\bar{\mu} + 1)\Gamma_3$ represents the superradiant decay rate for $|3\rangle \rightarrow |0\rangle$ transition, where

$\bar{\mu}$ depends on the geometrical shape of the atomic ensemble. The cooperative Lamb shift is $\delta\omega_i = \int_0^\infty d\omega \frac{\Gamma}{2\pi} [P.V.(\omega - \omega_3)^{-1}] N\bar{\mu}(\mathbf{k})$, where $P.V.$ denotes a principal value and $\Gamma = |d|^2\omega^3/(3\pi\hbar\epsilon c^3)$ with d the dipole moment for the transition.

Finally the probability amplitude $D_{s,i}(t)$ can be solved as

$$D_{s,i}(t) = g_i^* g_s^* \sum_{\mu} e^{i\Delta\mathbf{k}\cdot\mathbf{r}_{\mu}} \int_{-\infty}^t \int_{-\infty}^{t'} dt'' dt' e^{i\Delta\omega_i t'} e^{i\Delta\omega_s t''} \times b(t'') e^{[-(\Gamma_3^N/2) + i\delta\omega_i](t' - t'')}. \quad (\text{A4})$$

When we choose the input pulses in Gaussian forms, $\Omega_a(t) = \frac{1}{\sqrt{\pi}\tau} \tilde{\Omega}_a e^{-t^2/\tau^2}$, $\Omega_b(t) = \frac{1}{\sqrt{\pi}\tau} \tilde{\Omega}_b e^{-t^2/\tau^2}$, the long-time limit integral as $t \rightarrow \infty$ gives

$$D_{s,i} = \frac{\tilde{\Omega}_a \tilde{\Omega}_b g_i^* g_s^* \sum_{\mu=1}^N e^{i\Delta\mathbf{k}\cdot\mathbf{r}_{\mu}} e^{-(\Delta\omega_s + \Delta\omega_i)\tau^2/8}}{4\Delta_1\Delta_2 \sqrt{2\pi}\tau \Gamma_3^N/2 - i\Delta\omega_i} \quad (\text{A5})$$

where $N^{-1} \sum_{\mu=1}^N e^{i\Delta\mathbf{k}\cdot\mathbf{r}_{\mu}}$ becomes one when $N \rightarrow \infty$, representing the four-wave mixing condition to generate highly-correlated biphoton state.

-
- [1] N. Gisin, G. Ribordy, W. Tittel, and H. Zbinden, Quantum cryptography, *Rev. Mod. Phys.* **74**, 145 (2002).
- [2] V. Scarani, H. Bechmann-Pasquinucci, N. J. Cerf, M. Dušek, N. Lütkenhaus, and M. Peev, The security of practical quantum key distribution, *Rev. Mod. Phys.* **81**, 1301 (2009).
- [3] F. Xu, X. Ma, Q. Zhang, H.-K. Lo, and J.-W. Pan, Secure quantum key distribution with realistic devices, *Rev. Mod. Phys.* **92**, 025002 (2020).
- [4] K. Hammerer, A. S. Sørensen, and E. S. Polzik, Quantum interface between light and atomic ensembles, *Rev. Mod. Phys.* **82**, 1041 (2010).
- [5] W. Dür, H.-J. Briegel, J. I. Cirac, and P. Zoller, Quantum repeaters based on entanglement purification, *Phys. Rev. A* **59**, 169 (1999).
- [6] L.-M. Duan, M. Lukin, J. I. Cirac, and P. Zoller, Long-distance quantum communication with atomic ensembles and linear optics, *Nature (London)* **414**, 413 (2001).
- [7] J. I. Cirac, P. Zoller, H. J. Kimble, and H. Mabuchi, Quantum State Transfer and Entanglement Distribution among Distant Nodes in a Quantum Network, *Phys. Rev. Lett.* **78**, 3221 (1997).
- [8] H. J. Kimble, The quantum internet, *Nature (London)* **453**, 1023 (2008).
- [9] J. F. Clauser, M. A. Horne, A. Shimony, and B. A. Holt, Proposed experiment to test local hidden-variable theories, *Phys. Rev. Lett.* **23**, 880 (1969).
- [10] A. Aspect, P. Grangier and G. Roger, Experimental tests of realistic local theories via Bell's theorem, *Phys. Rev. Lett.* **47**, 460 (1981).
- [11] P. G. Kwiat, K. Mattle, H. Weinfurter, A. Zeilinger, A. V. Sergienko, and Y. Shih, New high-intensity source of polarization-entangled photon pairs, *Phys. Rev. Lett.* **75**, 4337 (1995).
- [12] A. Crespi, R. Ramponi, R. Osellame, L. Sansoni, I. Bongioanni, F. Sciarrino, G. Vallone, and P. Mataloni, Integrated photonic quantum gates for polarization qubits, *Nature communications* **2**, 566 (2011).
- [13] Y. Wang, J. Li, S. Zhang, K. Su, Y. Zhou, K. Liao, S. Du, H. Yan, and S.-L. Zhu, Efficient quantum memory for single-photon polarization qubits, *Nature Photonics* **13**, 346 (2019).
- [14] C. K. Law and J. H. Eberly, Analysis and interpretation of high transverse entanglement in optical parametric down conversion, *Phys. Rev. Lett.* **92**, 127903 (2004).
- [15] P.-A. Moreau, F. Devaux, and E. Lantz, Einstein-Podolsky-Rosen paradox in twin images, *Phys. Rev. Lett.* **113**, 160401 (2014).
- [16] A. Grodecka-Grad, E. Zeuthen, and A. S. Sørensen, High-capacity spatial multimode quantum memories based on atomic ensembles, *Phys. Rev. Lett.* **109**, 133601 (2012).
- [17] H. H. Arnaut and G. A. Barbosa, Orbital and intrinsic angular momentum of single photons and entangled pairs of photons generated by parametric down-conversion, *Phys. Rev. Lett.* **85**, 286 (2000).
- [18] A. Mair, A. Vaziri, G. Weihs, and A. Zeilinger, Entanglement of the orbital angular momentum states of photons, *Nature* **412**, 313 (2001).
- [19] G. Molina-Terriza, J. P. Torres, and L. Torner, Twisted photons, *Nat. Phys.* **3**, 305 (2007).
- [20] A. C. Dada, J. Leach, G. S. Buller, M. J. Padgett, and E. Andersson, Experimental high-dimensional two-photon entanglement and violations of generalized Bell inequalities, *Nat. Phys.* **7**, 677 (2011).
- [21] R. Fickler, R. Lapkiewicz, W. N. Plick, M. Krenn, C. Schaeff, S. Ramelow, A. Zeilinger, Quantum entanglement of high angular momenta, *Science* **338**, 640 (2012).
- [22] A. Nicolas, L. Veissier, L. Giner, E. Giacobino, D. Maxein, and J. Laurat, A quantum memory for orbital angular momentum photonic qubits, *Nat. Photonics* **8**, 234 (2014).
- [23] D.-S. Ding, W. Zhang, Z.-Y. Zhou, S. Shi, G.-Y. Xiang, X.-S. Wang, Y.-K. Jiang, B.-S. Shi, and G.-C. Guo, Quantum storage of orbital angular momentum entanglement in an atomic ensemble, *Phys. Rev. Lett.* **114**, 050502 (2015).
- [24] D. Branning, W. P. Grice, R. Erdmann, and I. A. Walmsley, Engineering the indistinguishability and entanglement of two photons, *Phys. Rev. Lett.* **83**, 955 (1999).
- [25] C. K. Law, I. A. Walmsley, and J. H. Eberly, Continuous frequency entanglement: Effective finite Hilbert space and entropy control, *Phys. Rev. Lett.* **84**, 5304 (2000).
- [26] S. Parker, S. Bose, and M. B. Plenio, Entanglement quantification and purification in continuous-variable systems, *Phys. Rev. A* **61**, 032305 (2000).
- [27] J. M. Lukens, A. Dezfouliyan, C. Langrock, M. M. Fejer, D. E. Leaird, and A. M. Weiner, Orthogonal spectral coding of entangled photons, *Phys. Rev. Lett.* **112**, 133602 (2014).
- [28] H. H. Jen and Y.-C. Chen, Spectral shaping of cascade emissions from multiplexed cold atomic ensembles, *Phys. Rev. A* **93**, 013811 (2016).
- [29] J. M. Lukens and P. Lougovski, Frequency-encoded photonic qubits for scalable quantum information processing, *Optica* **4**, 8 (2017).
- [30] H.-H. Lu, J. M. Lukens, N. A. Peters, B. P. Williams, A. M. Weiner, and P. Lougovski, Quantum interference and correlation control of frequency-bin qubits, *Optica* **5**, 1455 (2018).
- [31] M. Kues, C. Reimer, J. M. Lukens, W. J. Munro, A. M. Weiner, D. J. Moss, and R. Morandotti, Quantum optical microcombs, *Nature Photonics* **13**, 170 (2019).
- [32] Y.-F. Pu, N. Jiang, W. Chang, H.-X. Yang, C. Li, and L.-M.

- Duan. Experimental realization of a multiplexed quantum memory with 225 individually accessible memory cells, *Nat. Commun.* **8**, 15359 (2017).
- [33] S. Shi, L. Tian, Y. Wang, Y. Zheng, C. Xie, and K. Peng, Demonstration of Channel Multiplexing Quantum Communication Exploiting Entangled Sideband Modes, *Phys. Rev. Lett.* **125**, 070502 (2020).
- [34] S. L. Braunstein and P. van Loock, Quantum information with continuous variables, *Rev. Mod. Phys.* **77**, 513 (2005).
- [35] S.-K. Liao, W.-Q. Cai, W.-Y. Liu, L. Zhang, Y. Li, J.-G. Ren, J. Yin, Q. Shen, Y. Cao, Z.-P. Li, F.-Z. Li, X.-W. Chen, L.-H. Sun, J.-J. Jia, J.-C. Wu, X.-J. Jiang, J.-F. Wang, Y.-M. Huang, Q. Wang, Y.-L. Zhou *et al.*, Satellite-to-ground quantum key distribution, *Nature (London)* **549**, 43 (2017).
- [36] S.-K. Liao, W.-Q. Cai, J. Handsteiner, B. Liu, J. Yin, L. Zhang, D. Rauch, M. Fink, J.-G. Ren, W.-Y. Liu, Y. Li, Q. Shen, Y. Cao, F.-Z. Li, J.-F. Wang, Y.-M. Huang, L. Deng, T. Xi, L. Ma, T. Hu *et al.*, Satellite-Relayed Intercontinental Quantum Network, *Phys. Rev. Lett.* **120**, 030501 (2018).
- [37] Y.-A. Chen, Q. Zhang, T.-Y. Chen, W.-Q. Cai, S.-K. Liao, J. Zhang, K. Chen, J. Yin, J.-G. Ren, Z. Chen, S.-L. Han, Q. Yu, K. Liang, F. Zhou, X. Yuan, M.-S. Zhao, T.-Y. Wang, X. Jiang, L. Zhang, W.-Y. Liu *et al.*, An integrated space-to-ground quantum communication network over 4,600 kilometres, *Nature (London)* **589**, 214 (2021).
- [38] T. Chanelière, D. N. Matsukevich, S. D. Jenkins, T. A. B. Kennedy, M. S. Chapman, and A. Kuzmich, Quantum Telecommunication Based on Atomic Cascade Transitions, *Phys. Rev. Lett.* **96**, 093604 (2006).
- [39] A. G. Radnaev, Y. O. Dudin, R. Zhao, H. H. Jen, S. D. Jenkins, A. Kuzmich, and T. A. B. Kennedy, A quantum memory with telecom-wavelength conversion, *Nat. Phys.* **6**, 894 (2010).
- [40] H. H. Jen and T. A. B. Kennedy, Efficiency of light-frequency conversion in an atomic ensemble, *Phys. Rev. A* **82**, 023815 (2010).
- [41] T. Chanelière, D. N. Matsukevich, S. D. Jenkins, S.-Y. Lan, T. A. B. Kennedy, and A. Kuzmich, Storage and retrieval of single photons transmitted between remote quantum memories, *Nature* **438**, 833 (2005).
- [42] S. Chen, Y.-A. Chen, T. Strassel, Z.-S. Yuan, B. Zhao, J. Schmiedmayer, and J.-W. Pan, Deterministic and Storable Single-Photon Source Based on a Quantum Memory, *Phys. Rev. Lett.* **97**, 173004 (2006).
- [43] Y.-H. Chen, M.-J. Lee, I.-C. Wang, S. Du, Y.-F. Chen, Y.-C. Chen, and I. A. Yu, Coherent Optical Memory with High Storage Efficiency and Large Fractional Delay, *Phys. Rev. Lett.* **110**, 083601 (2013).
- [44] S.-J. Yang, X.-J. Wang, X.-H. Bao, and J.-W. Pan, An efficient quantum light-matter interface with sub-second lifetime, *Nat. Photonics* **10**, 381 (2016).
- [45] Y.-F. Hsiao, P.-J. Tsai, H.-S. Chen, S.-X. Lin, C.-C. Hung, C.-H. Lee, Y.-H. Chen, Y.-F. Chen, I. A. Yu, and Y.-C. Chen, Highly Efficient Coherent Optical Memory Based on Electromagnetically Induced Transparency, *Phys. Rev. Lett.* **120**, 183602 (2018).
- [46] M. A. Seidler, X. J. Yeo, A. Cerè, and C. Kurtsiefer, Spectral compression of narrowband single photons with a resonant cavity, *Phys. Rev. Lett.* **125**, 183603 (2020).
- [47] Y.-E. Wong, N.-Y. Tsai, W. S. Hiew, and H. H. Jen, Spectral compression and entanglement reduction in the cascaded biphoton state with cavities, *J. Phys. B: At. Mol. Opt. Phys.* **54**, 195501 (2021).
- [48] Y.-E. Wong, T. H. Chang, and H. H. Jen, Almost indistinguishable single photons via multiplexing cascaded biphotons with cavity modulation and phase compensation, *Phys. Rev. A* **105**, 063706 (2022).
- [49] E. Knill, R. Laflamme, and G. J. Milburn, A scheme for efficient quantum computation with linear optics, *Nature* **409**, 46 (2001).
- [50] L. Dusanowski, S.-H. Kwon, C. Schneider, and S. Höfling, Near-Unity Indistinguishability Single Photon Source for Large-Scale Integrated Quantum Optics, *Phys. Rev. Lett.* **122**, 173602 (2019).
- [51] J.-P. Li, X. Gu, J. Qin, D. Wu, X. You, H. Wang, C. Schneider, S. Höfling, Y.-H. Huo, C.-Y. Lu, N.-L. Liu, L. Li, and J.-W. Pan, Heralded Nondestructive Quantum Entangling Gate with Single-Photon Sources, *Phys. Rev. Lett.* **126**, 140501 (2021).
- [52] H. H. Jen, Cascaded cold atomic ensembles in a diamond configuration as a spectrally entangled multiphoton source, *Phys. Rev. A* **95**, 043840 (2017).
- [53] M. O. Scully and M. S. Zubairy, *Quantum Optics* (Cambridge University Press, 1997).
- [54] S. Alamouti, A simple transmit diversity technique for wireless communications, *IEEE Journal on Selected Areas in Communications* **16**, 1451 (1998).
- [55] V. Tarokh, H. Jafarkhani, and A. Calderbank, Spacetime block codes from orthogonal designs, *IEEE Transactions on Information Theory* **45**, 1456 (1999).
- [56] H. Jafarkhani, A quasi-orthogonal space-time block code, *IEEE Transactions on Communications* **49**, 1 (2001).
- [57] N. B. Lingaraju, H.-H. Lu, S. Seshadri, D. E. Leaird, A. M. Weiner, and J. M. Lukens, Adaptive bandwidth management for entanglement distribution in quantum networks, *Optica* **8**, 329 (2021).