

Qubit-Efficient Randomized Quantum Algorithms for Linear Algebra

Samson Wang¹, Sam McArdle^{2,3}, and Mario Berta^{4,5}

¹Department of Physics, Imperial College London, London, UK

²AWS Center for Quantum Computing, Pasadena, USA

³California Institute of Technology, Pasadena, USA

⁴Department of Computing, Imperial College London, London, UK

⁵Institute for Quantum Information, RWTH Aachen University, Aachen, Germany

Abstract

We propose a class of randomized quantum algorithms for the task of sampling from matrix functions, without the use of quantum block encodings or any other coherent oracle access to the matrix elements. As such, our use of qubits is purely algorithmic, and no additional qubits are required for quantum data structures. For $N \times N$ Hermitian matrices, the space cost is $\log(N) + 1$ qubits and depending on the structure of the matrices, the gate complexity can be comparable to state-of-the-art methods that use quantum data structures of up to size $O(N^2)$, when considering equivalent end-to-end problems. Within our framework, we present a quantum linear system solver that allows one to sample properties of the solution vector, as well as an algorithm for sampling properties of ground states of Hamiltonians. As a concrete application, we combine these two sub-routines to present a scheme for calculating Green's functions of quantum many-body systems.

1 Introduction

1.1 Overview

As improvements in hardware increase the number and quality of qubits, we seek quantum algorithms that are able to showcase practical quantum advantage in the earliest possible time-frame. Looking beyond NISQ technologies [1–3], it is reasonable to assume that, given continued progress in quantum hardware, so-called fault-tolerant algorithms will have an important place in the gamut of quantum computing applications. Thus, it is pertinent to ask how soon such algorithms can be useful for real-life applications, and how much can we accelerate this timeline by constructing algorithms with lower and more flexible quantum resource costs.

Quantum algorithms for manipulating matrices have been proposed for many problems, including factoring, linear systems, ground state energy estimation, simulation, and beyond (e.g. see Refs. [4–7] and references therein). These algorithms are often phrased in terms of a quantum oracle model from which elements of the matrix of interest can be coherently accessed. Since the seminal proposals, there have been extensive improvements and refinements to the asymptotic runtime for each of these algorithms, which is usually measured in the number of required queries to the oracle. For many problems, the state-of-the-art query complexities are optimal or close to optimal according to known complexity lower bounds. Moreover, many of these recent techniques are unified under the so-called quantum singular value transformation (QSVT) framework [8, 9], in which polynomial approximations are applied to the singular values of the desired matrix. Here, the oracle embeds the matrix in a larger unitary, commonly known as a block encoding.

Despite this promise, when considering end-to-end implementations of such quantum algorithms two major hurdles can arise.¹ First, the implementation of the quantum oracles can require costly additional quantum resources, both in the depth required for each call and the number of qubits consumed. Second, the quantum algorithm can come with certain conditions or caveats that need to be satisfied for efficient applications.

¹By “end-to-end” we mean that all relevant resources are accounted for in an implementation that solves the required task in full.




Figure 1: **Motivation of our work.** We reduce quantum hardware requirements for quantum algorithms on classical data by removing the need for quantum data structures or quantum oracles. This is achieved by replacing coherent access to the data with a classical description of the data in the Pauli basis, and utilizing a randomized algorithm that samples the outputs of many quantum circuits. These circuits are chosen independently and thus in theory can also be parallelized, trading reduced total runtime for additional space cost in the form of many quantum processors. Our approach uses circuits with at most $\log N + 1$ qubits when processing data from $N \times N$ Hermitian matrices. This can be compared to other algorithms that utilize quantum data access models which may have significantly greater qubit overhead overall.

As an example, consider the linear systems problem, for which the pioneering HHL algorithm was proposed [10]. The current state-of-the-art quantum linear systems solver (QLSS) presented in Ref. [11] uses $\mathcal{O}(\log(N))$ algorithmic qubits and a block encoding oracle to process $N \times N$ matrices. This algorithm only needs to make a small number of calls to the block encoding if the matrix is well-conditioned, compared to the runtime of classical linear systems algorithms. However, for general matrices an implementation of the block encoding using QRAM² in minimum depth $\mathcal{O}(\log(N))$ requires $\mathcal{O}(N^2)$ qubits [12, 15, 16].³ Thus, for general matrices the exponential savings in space resources are nullified. In order to circumvent this burden, one could search for specific classes of matrices for which the QRAM requirements are less costly than the algorithmic qubits. Indeed, for matrices that are L -sparse in an efficiently implementable unitary basis, block encodings can be implemented substantially more efficiently than in the general case [17–20] (see also [21] specifically for sparse matrices in the computational basis). However, this is still an additional resource cost that we argue could be minimized further when considering early implementations of fault-tolerant algorithms. Moreover, it is important to consider the exact problem that the quantum algorithm solves: the QLSS returns a quantum state in which the solution vector is encoded with some non-zero additive error, unlike textbook classical solvers that provide full classical vector exactly. Thus, in order to assess the utility of quantum linear systems solvers, full end-to-end applications including possible additional subroutines need to be carefully analyzed [22]. For instance, it may be more fair to compare the quantum algorithm to randomized classical solvers which allow for some error [23], or so-called “dequantized” approaches which operate with a classical data structure analogous to QRAM [24, 25]. We discuss various approaches to linear systems in more detail in Section 3.3.

In this work, we present a framework for constructing algorithms that sample properties of matrix functions which do not use quantum oracles to provide coherent access to the matrix in question (see Figure 1). Despite having no qubit overhead to implement quantum oracles, the asymptotic complexities of our algorithms can remain comparable with other algorithms in the literature whenever the considered matrices have an amenable structure in the Pauli basis (and when considering equivalent end-to-end problems). Hence, for physically motivated matrices, potential quantum advantages originally requiring QRAM could possibly be similarly obtained in our approach without using a quantum data structure, making them more applicable for the early fault-tolerant regime [26–31]. Specifically, given a Fourier series approximation to a function f , and an $N \times N$ Hermitian matrix A with known decomposition in the Pauli basis, we give algorithms to sample properties of $f(A)$ using a total of $\log(N) + 1$ qubits. Using this framework we present algorithms for sampling properties of the solution vector in the linear systems problem, as well as from ground states of a given Hamiltonian. We provide direct comparisons of the complexities of our algorithms with other classical and quantum algorithms for specific end-to-end tasks, and we present an

²Quantum Random Access Memory (QRAM): a widely-studied data access structure that allows for coherent access to classical data [12–14]

³The minimum qubit count implementation in Ref. [16] requires $\mathcal{O}(N)$ qubits and $\mathcal{O}(N)$ depth per call to the block encoding. Alternatively, a QROM (Quantum Read-Only Memory) can be implemented using $\mathcal{O}(\log N)$ qubits, but $\mathcal{O}(N^2)$ gates.

application of our algorithms for computing Green’s functions in many-body physics.

As our starting point we take inspiration from algorithms for quantum chemistry [27, 28, 32], where often quantum data structures are not needed. We trade quantum (coherent) access to the matrix A for classical access to the coefficients $a_\ell \in \mathbb{R}$ in its decomposition in the Pauli basis

$$A = \sum_{\ell=1}^L a_\ell P_\ell, \quad (1)$$

where P_ℓ are multi-qubit Pauli operators. We refer to this as the Pauli access model and note that it is a natural representation for data coming from physical problems, for instance, when the matrix comes from a Hamiltonian. The model also mathematically matches the physical intuition that running quantum sub-routines for “quantumly structured data” has possible potential for quantum speed-ups. Indeed, our algorithms are faster for matrices with small vector ℓ_1 -norm of Pauli coefficients $\lambda := \sum |a_\ell|$, which we refer to as the “Pauli weight”. Moreover, we remark that there is no explicit dependence on the sparsity, or the number of Pauli terms L (which we will call the “Pauli sparsity”) in the runtimes – both of which can be substantially larger than the Pauli weight, and appear in the runtime of other algorithms.

1.2 Related work

Applications for the early fault-tolerant era of quantum computing have recently begun to be explored, following the motivation to design algorithms that extract practical value out of fault-tolerant quantum algorithms as soon as possible [27–33]. In this spirit, algorithms have been designed to consume fewer quantum resources for Hamiltonian problems including phase estimation [27–30], ground state preparation [29], and computing ground state properties [31], by increasing the number of circuit samples required. Until now, these algorithms have predominantly aimed to reduce a proxy for the maximum circuit depth, in the form of the number of calls to a time evolution oracle for a prescribed Hamiltonian in one coherent run of a circuit. It then remains to choose an appropriate time evolution oracle for the intended setting, which can substantially affect the gate overhead or the number of qubits required. In Section 4.2 we discuss further the implications for various choices of time evolution oracle, and how the resulting implementations compare to our results for the ground state property estimation problem.

One distinctive approach is that of Ref. [28] for phase estimation which uses the Pauli access model, rather than a time evolution oracle. In this work an algorithm is proposed which randomly compiles the Heaviside function by sampling from a Fourier series approximation to the function. Ref. [33] also presents an algorithm to perform randomized sampling of a given observable after a time evolution of a given Hamiltonian. We extend these ideas in our work to sample observables of evolutions corresponding to different functions. This allows us to directly focus on reducing the qubit overhead, rather than optimize the number of calls to a time evolution oracle. Similar to previous works, this reduction of resources comes at a price of an increase in the number of circuit samples taken, which we assume to be a more accessible resource in an early fault-tolerant setting.

We remark that near-term approaches for the quantum linear systems problem have recently been proposed which use similar data access assumptions to our Pauli access model [34–36]. Namely, these works assume the matrix of interest has a known decomposition $A = \sum_t c_t U_t$, where U_t are efficiently implementable unitaries (such as the Pauli basis decomposition as in our work). These approaches use parameterized circuits whose depth can be tuned to whatever a near-term implementation allows. However, despite showing promising numerical performance for small problem sizes, they lack generic runtime guarantees. On the other hand, our algorithms give prescriptive circuits with runtime guarantees.

1.3 Outline

The rest of the manuscript is structured as follows. In Section 2 we present our general framework including a discussion on the classical power of our access model in Subsection 2.3. We then demonstrate applications of our framework: we present our algorithm for sampling properties of the solution vector in the linear systems problem in Section 3; we describe our algorithm for sampling properties of the ground state in Section 4; and we show how these algorithms can be used together to estimate single-particle Green’s functions in the context of many-body physics in Section 5. Finally, in Section 6 we present our concluding discussions and outlook. In the Appendices we present detailed analytical statements and all proofs thereof.

2 General approach

2.1 Warm-up problem

We start by demonstrating how to extend the ideas from Refs. [28] and [33] to sample properties of a Fourier series of a given matrix. This gives intuition for the core routine we will use for the rest of our results. Readers who want a summary of the results may skip ahead to Section 2.2 and the outlines of our specific algorithms in Sections 3, 4 & 5.

Our algorithms will make use of the Hadamard test circuit (see Fig. 2(a)), pioneered in Ref. [27] for use in the ground state energy estimation problem in the early fault-tolerant regime. We will also use the related circuit in Fig. 2(b), used in Ref. [33] to randomize multi-product formulas for Hamiltonian simulation. Our circuits will ask for elementary controlled unitary operations in the form of controlled Pauli gates and Pauli rotations.

Proposition 1 (Sampling from Fourier series). *Suppose that we have a Fourier series*

$$s(A) = \sum_{k \in F} \alpha_k \exp(it_k A), \text{ with } \ell_1\text{-norm of coefficients } \alpha := \sum_{k \in F} |\alpha_k|, \quad (2)$$

for an $N \times N$ Hermitian matrix A with known Pauli decomposition $A = \sum_{\ell} a_{\ell} P_{\ell}$ and Pauli weight $\lambda = \sum_{\ell} |a_{\ell}|$. Then, we find:

- (a) Given a procedure to prepare the pure states $|\psi\rangle, |\phi\rangle$ with respective unitaries U_{ψ}, U_{ϕ} and respective gate depths d_{ψ}, d_{ϕ} , we have a randomized quantum algorithm that uses $\log(N) + 1$ qubits to

$$\text{approximate } \langle \phi | s(A) | \psi \rangle \text{ up to additive error } \varepsilon, \quad (3)$$

with arbitrary constant success probability, using

$$\mathcal{C}_{\text{sample}}^{\phi} = \mathcal{O}(\alpha^2 / \varepsilon^2) \text{ circuit samples}, \quad (4)$$

where each circuit takes the form in Figure 2(a) with

$$\mathcal{C}_{\text{gate}}^{\phi} = \mathcal{O}(\lambda^2 t_{\max}^2 + d_{\psi} + d_{\phi}) \text{ gate depth}, \quad (5)$$

where we denote $t_{\max} := \max_{k \in F} t_k$.

- (b) Given a procedure to prepare the quantum state ρ in depth d_{ρ} and perform measurements with measurement operator O , we have a randomized quantum algorithm that uses $\log(N) + 1$ qubits to

$$\text{approximate } \text{Tr}[s(A)\rho s(A)O] \text{ up to additive error } \varepsilon, \quad (6)$$

with arbitrary constant success probability, using

$$\mathcal{C}_{\text{sample}}^O = \mathcal{O}(\|O\|^2 \alpha^4 / \varepsilon^2) \text{ circuit samples}, \quad (7)$$

where each circuit takes the form in Figure 2(b) with

$$\mathcal{C}_{\text{gate}}^O = \mathcal{O}(\lambda^2 t_{\max}^2 + d_{\rho}) \text{ gate depth}. \quad (8)$$

We see that various properties of the Fourier series determine the complexity of the quantum algorithm. Namely, the weight of the Fourier series α determines the sample complexity, whilst the time parameter t_{\max} determines the gate complexity. The gate complexity also depends on the Pauli weight λ of the matrix A . In certain cases, the Pauli weight of a matrix can be much smaller than its dimension, despite there being many non-zero Pauli terms. In these cases, we expect the above algorithms to be efficient. Note that, similar to the linear combinations of unitaries (LCU) [37–39] and QSVT [8, 9] frameworks for quantum algorithms, our framework enacts a general class of functions, which we will apply to different approximation problems in the rest of this manuscript. Unlike the aforementioned approaches, our framework does not need access to quantum oracles, or any additional coherent resources.



Figure 2: **Circuits used in our algorithms.** We sample strings of quantum gates, consisting of specified Pauli operators and Pauli rotations, and perform quantum circuit runs with controlled versions of these gates. (a) Hadamard test circuit, first used proposed for use in the early fault-tolerant regime by Lin and Tong [27]. Measuring the expectation value of Z on the first register returns $\text{Re}(\langle\psi|U|\psi\rangle)$ and $\text{Im}(\langle\psi|U|\psi\rangle)$ for choices of $G = \mathbb{1}$ and $G = S^\dagger := |0\rangle\langle 0| - i|1\rangle\langle 1|$ respectively. (b) Using the circuit considered in Ref. [33] to randomize multi-product formulas, one can apply controlled- U and anticcontrolled- V , followed by measurement of observable $X \otimes O$ to return $\frac{1}{2} (\langle\psi|U^\dagger O V|\psi\rangle + \langle\phi|V^\dagger O U|\psi\rangle)$.

We provide the proof of Proposition 1 in Appendix A.1. A key technical tool we use is the *random compiler lemma* of Ref. [28] which decomposes fractional time evolution operators into a probabilistic mixture of Pauli matrices and Pauli rotations. This leads to a decomposition of the full time evolution operator simply by taking the product of such fractional operators. Namely, for some time parameter $t \in \mathbb{R}$, for any choice $r \in \mathbb{N}$ and for Hermitian matrix A with known Pauli decomposition as in Eq. (1), Ref. [28] shows how one can obtain the decomposition

$$e^{iAt/r} = \gamma \sum_{\ell \in T'} p_\ell \cdot z_\ell P_\ell \exp(i\theta_\ell P'_\ell), \quad (9)$$

for some index set T' , where p_ℓ are probabilities, $z_\ell \in \{\pm 1, \pm i\}$ are phases, and P_ℓ, P'_ℓ are ($\lceil \log N \rceil$ qubit) Pauli operators, which all implicitly depend on t/r . Moreover, the weight of the mixture can be shown to satisfy $\gamma \leq \exp(\lambda^2 t^2 / r^2)$. This implies that one can express a full time evolution operator as a linear combination

$$e^{iAt} = \left(e^{iAt/r}\right)^r = \sum_{m \in T} \beta_m^{(r)} U_m^{(r)}, \quad (10)$$

where the weight of the coefficients satisfy $\sum_{m \in T} |\beta_m^{(r)}| = \mathcal{O}(1)$ for $r \in \Theta(\lambda^2 t^2)$, meaning that one can sample from the distribution with bounded variance. Each $U_m^{(r)}$ is a string of gates consisting of r pairs of controlled (multi-qubit) Pauli rotations and controlled Pauli gates. Thus, r can be considered to control the quantum runtime of the algorithm. Our algorithms sample from the strings of gates according to the linear combination in Eq. (10).

We provide pseudo-code for the algorithm presented in Proposition 1 to prepare $\langle\phi|s(A)|\psi\rangle$ in Algorithm 1. The algorithm for $\text{Tr}[s(A)\rho s(A)^\dagger O]$ is very similar and we present the pseudo-code for this in full in Algorithm 2 in Appendix A.1. These two algorithms will form the core quantum routine for the rest of our results.

We remark that in the pseudocode in Algorithm 1 we have left the runtime vector \vec{r} as a freely chosen algorithm parameter. In practice, one would likely choose each element of the runtime vector to be $r_k \propto \lambda^2 t_k^2$ for all k which leads to the runtime guarantees specified in Proposition 1. However, we note that one can still freely choose a proportionality constant, which will trade a constant factor improvement in the sample complexity for increased gate depth, or vice versa.

2.2 Main result

Using the results of the previous section, now we can demonstrate how to sample properties of matrix functions, starting from a sufficiently good Fourier series approximation to the function, and a decomposition of the matrix in the Pauli basis.

Given a real-valued function $f : \mathbb{R} \rightarrow \mathbb{R}$, we consider a scenario where we have a Fourier series approximation $s(\varepsilon, D_A) : \mathbb{R} \rightarrow \mathbb{R}$ which is ε -close to f on the domain D_A . More precisely, we suppose that

$$|f(x) - s(\varepsilon, D_A, x)| \leq \varepsilon, \quad \forall x \in D_A. \quad (11)$$

Algorithm 1 Fourier sampling of $\langle \phi | s(A) | \psi \rangle$

Problem input:

- $N \times N$ Hermitian matrix $A = \sum_{\ell} a_{\ell} P_{\ell}$, with $a_{\ell} \in \mathbb{R} \forall \ell$, and known Pauli weight $\lambda = \sum_{\ell} |a_{\ell}|$
- Fourier parameters $\{\alpha_k\}_{k \in F}$, $\{t_k\}_{k \in F}$ for series $s(A)$ according to Eq. (2)
- Unitary gates U_{ψ}, U_{ϕ} which respectively prepare $|\psi\rangle, |\phi\rangle$.

Parameters: (1) Approximation error $\varepsilon \in (0, 1)$; (2) Success probability $1 - \delta \in (0, 1)$; (3) Runtime vector $\vec{r} \in \mathbb{N}^{|F|}$.

Output: Approximation to $\langle \phi | s(A) | \psi \rangle$ with additive error at most ε and success probability at least $1 - \delta$.

1. Compute coefficients $\{\beta_{km}^{(\vec{r})}\}_{(k,m) \in F \times T}$ as in Eq. (10) (see Appendix A) for each time parameter $\{t_k\}_{k \in F}$.
 2. $R(\vec{r}) \leftarrow \sum_{(k,m) \in F \times T} |\alpha_k \beta_{km}^{(r_k)}|$.
 3. $M(\vec{r}) \leftarrow \left\lceil 4 \ln(2/\delta) (R(\vec{r})/\varepsilon)^2 \right\rceil$.
 4. **for** $j \in [M(\vec{r})]$:
 - (i) Sample indices (k', m') according to probability distribution $\{|\alpha_k \beta_{km}^{(r_k)}|/R(\vec{r})\}_{(k,m) \in F \times T}$ and select corresponding string of gates $U_{k'm'}^{(r_{k'})}$.
 - (ii) Run $n + 1$ qubit circuit in Figure 2(a) with input state $|0\rangle^{\otimes \lceil \log N \rceil + 1}$, $G = \mathbb{1}$, controlled $U_{\phi} U_{k'm'}^{(r_{k'})} U_{\psi}$ gates, and measurement operator Z on first register. Record measurement outcome o_j .
 - (iii) Run same circuit again with $G = S^{\dagger} := |0\rangle\langle 0| - i|1\rangle\langle 1|$. Record measurement outcome o'_j .
 - (iv) $z_j \leftarrow R(\vec{r})(o_j + io'_j)$.
 5. **end for**
 6. $\bar{z}^{(M)} \leftarrow \sum_j z_j / M(\vec{r})$. **return** \bar{z} .
-

We note that the condition in Eq. (11) is dependent on the maximum deviation of the Fourier approximation over the entire domain of interest – this is the property that will determine the rigorous worst case complexity of our algorithms – thus, it is important to find Fourier series approximations that are accurate even on the extremities of a domain, not just on average. The Fourier series can always be expressed as

$$s(\varepsilon, D_A, x) = \sum_{k \in F_{\varepsilon, D_A}} \alpha_k(\varepsilon, D_A) \exp(it_k(\varepsilon, D_A)x) \quad (12)$$

over some index set F_{ε, D_A} , where $\{\alpha_k(\varepsilon, D_A)\}_k$ and $\{t_k(\varepsilon, D_A)\}_k$ are Fourier parameters which in general have dependence on the approximation error ε and the domain of approximation D_A . This setting can be simply translated to matrix functions, if one considers a Hermitian matrix A whose spectrum lies in D_A . In this case ε then corresponds to closeness of matrix functions in operator norm.

Theorem 1 (Generalized sampling from Fourier approximations). *Suppose we have a matrix function $f(A)$ of an $N \times N$ Hermitian matrix A that is approximated by a Fourier series $s(\tilde{\varepsilon}, A)$ with tunable error parameter $\tilde{\varepsilon}$, and has a known Pauli decomposition of A with Pauli weight λ . Suppose further that we have unitary oracles U_{ψ} , U_{ϕ} , U_{ρ} to prepare $|\psi\rangle$, $|\phi\rangle$ and ρ respectively. Then, we give explicit randomized algorithms to*

$$\text{approximate } \frac{\langle \phi | f(A) | \psi \rangle}{q} \quad \& \quad \frac{\text{Tr}[f(A)\rho f(A)^{\dagger}O]}{q^2} \quad \text{to a given desired additive error } \varepsilon, \quad (13)$$

for small enough ε , using Algorithms 1 and 2 respectively on $\log(N) + 1$ qubits, where q is some arbitrary normalization factor.

We provide a more precise statement with exact complexities, and accompanying proofs accounting for constant factor terms, in Appendix A.2. Theorem 1 provides a general recipe for sampling from functions of $N \times N$ Hermitian matrices by using $\log(N) + 1$ qubits, given a Fourier series approximation and a Pauli decomposition of the matrix. In

particular, it specifies how to tune the Fourier approximation parameter $\tilde{\varepsilon}$ such that we can directly use Algorithms 1 and 2. We stress that as with the warm-up problem, we do not use any hidden quantum oracles and specify circuits explicitly in terms of controlled Pauli gates and controlled Pauli rotations.

Our randomized scheme allows for generic normalization of the answer by some factor q , with all complexities accounted for. So far, we have assumed that q is exactly given. However, the desired q may in general not be exactly known. One salient example is if we wish for $f(A)|\psi\rangle$ to be a normalized quantum state for some input state $|\psi\rangle$. In this case the relevant normalization quantity is $\|f(A)|\psi\rangle\|$. In Appendix A.3 we present a randomized subroutine to estimate quantities of this form, which can be directly integrated with our core result in Theorem 1. We summarize this with the following proposition.

Proposition 2 (Sampling normalization constant). *Under the conditions of Theorem 1, the quantities*

$$\frac{\langle\phi|f(A)|\psi\rangle}{\|f(A)|\psi\rangle} \ \& \ \frac{\text{Tr}[f(A)|\psi\rangle\langle\psi|f(A)^\dagger\mathcal{O}]}{\|f(A)|\psi\rangle^2}, \quad (14)$$

can be approximated to a given desired additive error ε , with the addition of a subroutine on $\log(N) + 1$ qubits to approximate $\|f(A)|\psi\rangle\|$.

Proposition 2 specifies how to approximate quantities in Eq. (14) by first running a subroutine to approximate $\|f(A)|\psi\rangle\|$ to a specified error, followed by the core algorithm using Theorem 1.

2.3 Classically easy functions

We briefly remark on the implications of our techniques for the power of randomized classical approaches using the Pauli access model. Namely, we show in the following proposition that sufficiently low-degree polynomials of matrices (such as for matrix multiplication) can be sampled from, if these matrices have low Pauli weight.

Proposition 3 (Classical polynomial sampling). *For stabilizer states $|s\rangle, |t\rangle$, Hermitian matrix A with known Pauli decomposition and Pauli weight λ , and p_d a d -degree polynomial, we give a classical randomized scheme to*

$$\text{approximate } \langle t|p_d(A)|s\rangle \text{ up to additive error } \varepsilon, \quad (15)$$

using

$$\mathcal{C}_{\text{sample}} = \tilde{\mathcal{O}}(\lambda^{2d}/\varepsilon^2) \text{ independent classical subroutines}, \quad (16)$$

each with time and space complexity

$$\mathcal{C}_{\text{time}} = \tilde{\mathcal{O}}(d \log^2(N)) \quad \& \quad \mathcal{C}_{\text{bits}} = \tilde{\mathcal{O}}(\log^2(N)), \quad (17)$$

respectively, where λ is the Pauli weight of A .

A more detailed statement, along with the proof can be found in Appendix A.5. Proposition 3 works simply by observing that the task in Eq. (15) can be obtained statistically via measurement outcomes of depth $\mathcal{O}(d)$ Clifford circuits, which are efficiently simulable. We note that, as with our previous specified algorithms, each sample can be parallelized, thus moving $\mathcal{C}_{\text{sample}}$ into the space complexity. Proposition 3 also trivially extends to polynomials of multiple matrices. Thus, our result implies that classically sampling from certain primitives such as matrix multiplication can be efficient, if the matrices have low Pauli weight.

Proposition 3 implies similar efficiency for quantum or classical algorithms for functions with low-degree polynomial approximations. However, in general we do not expect such low-degree approximations to always exist. For instance, we can investigate some implications for the linear systems problem and ground state property estimation problem. Ref. [40] gives a polynomial approximation to the inverse function with degree linear in the condition number. This implies a classical algorithm to sample an element of the solution vector or the linear systems problem with exponential sample complexity in the condition number. Likewise, one could use the power law method to approximately project to the ground state for Hamiltonians with negative spectra. However, this results in a classical algorithm with sampling complexity exponential in the inverse spectral gap (see Appendix B.2.1 for more details). These algorithms could be advantageous against other classical algorithms for very particular problems

with small condition number or inverse spectral gap respectively, as they only have logarithmic runtime dependence in the size of the problem (c.f. Table 1 where all classical approaches have at least linear runtime in the rank). However, these approaches would not be useful for general problems. It thus remains to see if there are problems of interest with low-degree polynomial approximations.

We comment also that our result bears loose resemblance to Theorem 3 of Ref. [41], which gives a classical algorithm “dequantizing” the quantum singular value transform (QSVT) for constant degree polynomials of sparse matrices, with the cost scaling exponentially in the degree of the polynomial in general (one can also compare to Ref. [42], which also shares some qualitative qualities but in the context of topological data analysis). The QSVT framework in general can apply polynomial transformations of high degree with cost scaling only linearly in the degree [8, 9]. In our setting, we leave it as an open question as to whether there are more efficient randomized early fault-tolerant quantum algorithms for high-degree polynomials.

3 Linear systems

3.1 Randomized quantum linear system solver

In this section we show how to apply Theorem 1 to sample from the inverse of a matrix, with applications for linear systems problems. We use the Fourier series approximation for the inverse function found in Ref. [40]. With this, we establish the following result.⁴

Corollary 1 (Linear systems). *Consider a Hermitian matrix A with known Pauli decomposition as in Eq. (1) with Pauli weight λ . Denote q as a freely chosen normalization parameter. Finally, suppose we have ability to prepare state $|\vec{b}\rangle$ in $\mathcal{O}(d_{\vec{b}})$ depth. Then, we find:*

(a). *Given ability to implement $|\psi\rangle$ via unitary U_{ψ} in gate depth d_{ψ} , we have a randomized quantum algorithm to*

$$\text{approximate } \frac{\langle \psi | A^{-1} | \vec{b} \rangle}{q} \text{ up to additive error } \varepsilon, \quad (18)$$

with arbitrary constant success probability, utilizing $\mathcal{C}_{\text{sample}}^{\psi}$ quantum circuits of the form in Figure 2(a) each consisting of $\mathcal{C}_{\text{gate}}^{\psi}$ layers of gates, where

$$\mathcal{C}_{\text{sample}}^{\psi} = \tilde{\mathcal{O}} \left(\frac{\|A^{-1}\|^2}{\varepsilon^2 q^2} \right), \quad \mathcal{C}_{\text{gate}}^{\psi} = \tilde{\mathcal{O}} (\|A^{-1}\|^2 \lambda^2 + d_{\psi} + d_{\vec{b}}). \quad (19)$$

(b). *Given ability to measure observable O ; $\|O\| \leq 1$, we have a randomized quantum algorithm to*

$$\text{approximate } \frac{\langle \vec{b} | A^{-1} O A^{-1} | \vec{b} \rangle}{q^2} \text{ up to additive error } \varepsilon, \quad (20)$$

with arbitrary constant probability, utilizing $\mathcal{C}_{\text{sample}}^O$ quantum circuits of the form in Figure 2(b) each consisting of $\mathcal{C}_{\text{gate}}^O$ layers of gates and one measurement of O , where

$$\mathcal{C}_{\text{sample}}^O = \tilde{\mathcal{O}} \left(\frac{\|A^{-1}\|^4}{\varepsilon^2 q^4} \right), \quad \mathcal{C}_{\text{gate}}^O = \tilde{\mathcal{O}} (\|A^{-1}\|^2 \lambda^2 + d_{\vec{b}}). \quad (21)$$

We detail a proof of this corollary in Appendix B.1 where we specify polylogarithmic contributions and account for constant factors. Corollary 1 provides an oracle-free quantum linear systems algorithm that only uses one ancillary qubit for Hermitian matrices. We note that we can consider non-Hermitian matrices for linear systems by embedding them in a larger Hermitian matrix via an additional qubit (details are provided in Appendix B.1).

⁴In the statement of results in the main text, for simplicity we write $\mathcal{C}_{\text{sample}} = \tilde{\mathcal{O}}(g)$ if $\mathcal{C}_{\text{sample}} = \mathcal{O}(g \log g \log h)$ and $\mathcal{C}_{\text{gate}} = \Omega(h)$, and vice versa for $\mathcal{C}_{\text{gate}}$. That is, with $\tilde{\mathcal{O}}(\cdot)$ notation we drop any terms that contribute logarithmically to the total (unparallelized) runtime.

Remark (Non-Hermitian matrices). *We can extend Corollary 1 to include non-Hermitian matrices by embedding the matrix in a larger Hermitian matrix with the aid of a single additional qubit. The algorithm then uses $\log(N) + 2$ qubits with a factor 2 increase in sample complexity.*

Further, we note that Proposition 2 allows the evaluation of the norm of the output vector $\|A^{-1}|\vec{b}\rangle\|$ via a subroutine with complexities equivalent to Eq. (21) up to logarithmic terms.

3.2 Statistical encoding of input vector

So far we have supposed that $|\vec{b}\rangle$ is provided via a quantum oracle. With the below proposition we demonstrate an approach to statistically encode the vector at a cost of classical preprocessing overhead and minimal gate overhead.

Proposition 4 (Statistical encoding of input vector). *Given a classical vector \vec{b} with sparsity s , we give a scheme to replace the quantum oracle for the input state $|\vec{b}\rangle$ in Theorem 1 and Corollary 1. This has overhead:*

- $\mathcal{O}(s)$ time for classical preprocessing.
- Sample complexity factor increase for problem (a) of $\mathcal{O}(\|\vec{b}\|_1^2 / \|\vec{b}\|_2^2)$ and for problem (b) of $\mathcal{O}(\|\vec{b}\|_1^4 / \|\vec{b}\|_2^4)$.
- 1 or 2 single-qubit controlled $\lceil \log N \rceil$ -qubit Pauli gates each circuit sample.

A key distinction is that this approach can return an encoding of \vec{b} that represents the true magnitude of the vector rather than a normalized quantum state which a standard quantum oracle would provide, simply by increasing the sample complexity. Moreover, this is a general scheme for our randomized approach that is applicable beyond the linear systems setting. We remark that our representation for the quantum state $|\vec{b}\rangle$ is similar to the so-called CQS states considered in the near-term quantum linear systems approach of Ref. [36]. More details are provided in Appendix A.4.

3.3 Comparison

3.3.1 Quantum linear systems solvers

The quantum linear systems solver (QLSS) is an algorithm that takes an encoding of a matrix A and vector \vec{b} , and returns the quantum state proportional to $A^{-1}|\vec{b}\rangle$, where $|\vec{b}\rangle := \sum_i b_i |i\rangle / \|\vec{b}\|$. Since the proposal of the original QLSS, known as the Harrow, Hassidim, and Lloyd (HHL) algorithm [10], many improved schemes have been proposed [8, 9, 11, 40, 43–46] utilizing $\mathcal{O}(\log(N))$ algorithmic qubits. Early algorithms made use of a time evolution oracle in the matrix of interest [40, 43, 46, 47]. More recently, approaches which use a block encoding have been proposed [8, 9, 11].

We remark that, in contrast to other fault-tolerant approaches to the QLSS, our algorithms do not require coherent access to the matrix of interest A and thus there are no additional hidden dimension dependencies. Thus, for a general $N \times N$ Hermitian matrix, only $\log(N) + 1$ logical qubits are required to carry out the full algorithm, with a runtime that does not explicitly depend on the dimension. We further note that our algorithm has the following additional distinctive features:

- In contrast to the QLSS, the error parameter ε in Corollary 1 is specified in terms of measurement errors in extracting information out of states of the form $A^{-1}|\vec{b}\rangle$. Thus, the QLSS is distinct from the problem our algorithm solves, as our algorithm returns a number rather than a state. If one wishes to extract out classical information from the QLSS one requires $\mathcal{O}(\varepsilon^{-2})$ circuit samples with incoherent measurements, or an additional factor of $\mathcal{O}(\varepsilon^{-1})$ runtime with coherent approaches [48, 49].
- Our complexities are determined by the operator norm $\|A^{-1}\|$, instead of the condition numbers $\kappa := \|A^{-1}\| \|A\|$ or $\kappa_F := \|A^{-1}\| \|A\|_F$. Moreover, there is no sparsity or explicit dimension dependence in the runtime. Instead, the runtime depends on the Pauli weight λ which for certain problems can be much smaller than the sparsity or dimension.

- We allow for arbitrary normalization by any normalization factor q , which rescales the asymptotic complexities by $\|A^{-1}\| \rightarrow \frac{1}{q}\|A^{-1}\|$. We recall that in the QLSS, the solution is given as a normalized quantum state, which may be undesired. Chakraborty et al. demonstrate how to obtain the state normalization to multiplicative error in $\tilde{\mathcal{O}}(\kappa\mu \text{polylog}(N)/\varepsilon)$ queries to a block encoding model, where μ is the block encoding factor [50]. Thus, if the effect of the unnormalized vector is needed for a particular end-to-end task, this additional complexity needs to be accounted for with the QLSS.

3.3.2 Complexity comparison

In Table 1 we compare the complexities of our linear systems algorithm with other classical and quantum algorithms in the literature for a specific task.⁵ The task we consider in Table 1 is to

$$\text{approximate the element } c \cdot \left(A^{-1}\vec{b}\right)_i \text{ to additive error } \varepsilon \text{ for any } i \in [N] \text{ and normalization } c \in \mathbb{R}. \quad (22)$$

We assume that the normalization constant c is whatever is natural to the algorithm at hand, and that we are querying the vector $A^{-1}\vec{b}$ in the computational basis. Thus, $c = 1$ for the classical setting, and $c = 1/\|A^{-1}|\vec{b}\rangle\|$ for the other quantum solvers. This is to allow a “middle ground” comparison with the other quantum and classical solvers, as relaxing these two assumptions incurs additional overhead for classical algorithms and other quantum algorithms, respectively.

We compare the space resources required to create the data access to A , and to perform the algorithm. We also compare the maximum coherent quantum runtime required (if applicable), and the total runtime. For our randomized scheme, we assume no parallelization, thus the total runtime is simply the product of the gate depth and the sample complexity. For all algorithms, we assume that the data starts in the most amenable *classical* format for that algorithm, such as in a sparse row representation, or in our classical Pauli access model. From there, we keep track of any additional *classical* or *quantum* overheads (both space and time) needed to provide any required data structures, for instance, the resources required to provide a block encoding.

Taking into account the aforementioned features, in Table 1 we consider the following algorithms:

- The Gaussian elimination “textbook” classical method, which returns the full exact solution vector. This has runtime dependent on the matrix multiplication exponent $\omega < 2.372$.
- A randomized classical Kaczmarz method [23], which returns an ε -approximation to the full solution vector.
- A “quantum-inspired” approach [25]. This starts from a classical data structure intended to mimic QRAM, which allows sampling from probability distributions with probabilities proportional to the magnitude of elements in a given row of A . The algorithm returns a classical data structure which allows one to sample from individual elements of an ε -approximation to the solution vector. In order to estimate the norm one needs to pay an extra $1/\varepsilon^2$ factor [25, 52].
- The HHL “textbook” quantum algorithm [10], which requires a time evolution oracle. In Table 1 we assume that this oracle is provided in a runtime-efficient manner via a block encoding [51]. We assume a Frobenius norm block encoding, with explicit construction via a QRAM in minimal depth as detailed in Ref. [16]. We note there are also other approaches which are more space efficient in quantum resources, but more costly in quantum runtime. Further, there is a choice of how to extract the classical information from the output of the HHL algorithm. We include two rows in Table 1, which quantifies resources required for performing standard incoherent measurements assuming no parallelization (first row), and for coherent approaches [48, 49], which has better overall runtime (second row).

⁵In the tables for each cell we write $f = \tilde{\mathcal{O}}(g)$ if $f = \mathcal{O}(g \log g)$. Thus, we include terms even if it has a logarithmic contribution to the total unparallelized runtime. This is to highlight the dependence of each parameter in each cell in isolation so that each dependency can be compared across different schemes.

Algorithm	Access Model	Data Access Space	Algorithmic Space	Quantum Gate Depth	Runtime
Textbook Classical	Comp. basis elements	$\mathcal{O}(N^2)$ bits	$\mathcal{O}(N^2)$ bits	-	$\mathcal{O}(N^\omega)$
Randomized Classical [23]	Sparse row	$\mathcal{O}(Ns)$ bits	$\mathcal{O}(\text{runtime})$ bits	-	$\mathcal{O}(s\kappa_F^2(A)\log(1/\varepsilon))$
Quantum-Inspired [25]	Sampling & query	$\mathcal{O}(N^2)$ bits	$\mathcal{O}(\kappa_F^2(A)\log(1/\varepsilon))$ bits	-	$\tilde{\mathcal{O}}(\kappa^2(A)\kappa_F^6(A)/\varepsilon^2)$
Textbook Quantum [10]	Block encoding time evol. [16, 51]	$\mathcal{O}(N^2)$ qubits	$\mathcal{O}(\log N)$ qubits	$\tilde{\mathcal{O}}(\kappa^2(A)\log(N)/\varepsilon^2)$	$\tilde{\mathcal{O}}(\kappa^2(A)\log(N)/\varepsilon^2)$
				$\tilde{\mathcal{O}}(\kappa^2(A)\log(N)/\varepsilon)$	$\tilde{\mathcal{O}}(\kappa^2(A)\log(N)/\varepsilon^3)$
Quantum Query-Optimal [11]	Frobenius norm block encoding [16]	$\mathcal{O}(N^2)$ qubits	$\log N + 6$ qubits	$\tilde{\mathcal{O}}(\kappa(A)\log(N)/\varepsilon)$	$\tilde{\mathcal{O}}(\kappa(A)\log(N)/\varepsilon)$
				$\tilde{\mathcal{O}}(\kappa(A)\log(N)\log(1/\varepsilon))$	$\tilde{\mathcal{O}}(\kappa(A)\log(N)/\varepsilon^2)$
Randomized Quantum (This Work)	Pauli coefficients	$\mathcal{O}(N^2)$ bits	$\log N + 2$ qubits	$\tilde{\mathcal{O}}(\ A^{-1}\ ^2\lambda^2(A)\log^2(1/\varepsilon))$	$\tilde{\mathcal{O}}(\ A^{-1}\ ^4\lambda^2(A)/\varepsilon^2)$

Table 1: End-to-end complexities for the task in Eq. (22) of querying one element of the solution vector in the linear systems problem to additive error ε . We consider a general $N \times N$ complex coefficient matrix A , with row sparsity s , which has Pauli decomposition (as in Eq. (1)) into up to N^2 Pauli terms with weight $\lambda(A)$. We denote $\kappa_F(A) := \|A^{-1}\| \|A\|_F$ where $\|\cdot\|$ denotes the operator norm and $\|\cdot\|_F$ denotes the Frobenius matrix norm, and note that $\kappa_F(A) \geq \sqrt{\text{rk}(A)}$. We also denote $\kappa(A) := \|A^{-1}\| \|A\|$. Under “data access space” we have listed the dominant classical or quantum resources needed in order to represent A in the required format for the algorithm at hand. One can also consider different schemes that may be advantageous for Pauli-sparse matrices or matrices which are sparse in the computational basis; we discuss this later in this section.

- A state-of-the-art quantum linear systems solver which achieves optimal query complexity [11], using a block encoding access model. As with HHL we assumed a Frobenius norm block encoding implemented in low depth via a QRAM, and detail complexities both for incoherent measurements (first row) and for coherent approaches [48, 49] (second row).
- Our algorithm using Corollary 1, assuming no parallelization. We remark that a particular artefact of the simplified task in Eq. (22) is that the runtime of our algorithm can be reduced by an arbitrary factor of q^2 as in Theorem 1. However, we do not include this additional freedom in Table 1 as we do not expect it to arise in more practical tasks. For instance, if one wished to compare two elements of $A^{-1}\vec{b}$ by estimating their ratio, q would not appear in the complexity.

The goal of our work is to reduce the quantum resources required for quantum approaches. This can be quantified by the three columns highlighted in Table 1: data access space, algorithmic space, and quantum gate depth. Our algorithm is clearly more efficient in space requirements compared to other quantum algorithms, and in particular it uses no qubits for data access. We further note that if the Pauli weight λ is small, there is scope that our algorithm has competitive gate depth with the best alternate option, which is to use the adiabatic quantum algorithm of Ref. [11] with incoherent measurements. If a coherent approach is used to extract the vector element, then our algorithm has exponentially better gate depth in the error parameter, but worse overall runtime.

For our algorithm to potentially be useful, it must also compete with classical algorithms. We remark that all the classical runtimes stated have at least linear dimension dependence for generic matrices, as $\kappa_F(A) \geq \sqrt{\text{rk}(A)}$, where we denote $\text{rk}(A)$ as the rank of A . Thus, for any of the quantum algorithms to display superpolynomial advantage for generic matrices, we require $\kappa(A) = \|A^{-1}\| \|A\| = \mathcal{O}(\text{polylog}(N))$. Further, one must consider a setting whether the significant difference in error dependence is also accounted for. Whilst our algorithm has significantly worse overall runtime in $\|A^{-1}\|$, we note the requirement for advantage on our algorithm is similar

($\|A^{-1}\| = \mathcal{O}(\text{polylog}(N))$), although for practical advantages the degree of this polynomial may need to be kept small. Thus, we expect our algorithm to potentially show quantum advantage if there is a setting where other quantum algorithms also show advantage, given that the Pauli weight $\lambda(A)$ is small. We remark that it is possible for matrices to have a small $\lambda(A)$, but large computational basis sparsity, Pauli sparsity $L(A)$, or rank $\text{rk}(A)$.

Pauli-sparse matrices. So far we have compared our algorithm against other quantum algorithms presuming that the Pauli sparsity L is large (note that $L \leq N^2$ in general). If L is small and the Pauli decomposition is known, then the **SELECT** + **PREPARE** oracles (previously studied in algorithms for quantum chemistry [17–20]) can implement a more efficient block encoding than the general construction with a QRAM considered in Table 1. We present the complexities for this block encoding in Table 2. The qualitative conclusions are similar; the block-encoded quantum algorithm requires more qubits, and our algorithm can have comparable gate depth if the Pauli weight $\lambda(A)$ is small compared to the Pauli sparsity $L(A)$.

Algorithm	Access Model	Data Access Space	Algorithmic Space	Quantum Gate Depth	Runtime
Quantum Query-Optimal [11]	SELECT + PREPARE [17–20]	$\mathcal{O}(\log L(A))$ qubits	$\log N + 6$ qubits	$\tilde{\mathcal{O}}(\kappa(A)L(A)/\varepsilon)$	$\tilde{\mathcal{O}}(\kappa(A)L(A)/\varepsilon)$
				$\tilde{\mathcal{O}}(\kappa(A)L(A) \log(1/\varepsilon))$	$\tilde{\mathcal{O}}(\kappa(A)L(A)/\varepsilon^2)$
Randomized Quantum (This Work)	Pauli coefficients	$\mathcal{O}(L(A))$ bits	$\log N + 2$ qubits	$\tilde{\mathcal{O}}(\ A^{-1}\ ^2 \lambda^2(A) \log^2(1/\varepsilon))$	$\tilde{\mathcal{O}}(\ A^{-1}\ ^4 \lambda^2(A)/\varepsilon^2)$

Table 2: End-to-end complexities for the task in Eq. (22) of querying one element of the solution vector in the linear systems problem to additive error ε . Here we have assumed that we start from a Pauli description of the matrix of interest A (as in Eq. (1)) where the number of terms $L(A)$ is small. In this case, it can be advantageous to use a **SELECT** + **PREPARE** block encoding for the query-optimal quantum algorithm.

Matrices sparse in the computational basis. For the quantum query-optimal algorithm one can also consider the quantum sparse access model,⁶ which can be efficiently converted into a block encoding model using $\mathcal{O}(\text{polylog}(N/\varepsilon))$ qubits and $\mathcal{O}(\text{polylog}(N/\varepsilon))$ elementary gates [8]. Thus, if this access model is naturally available, a significant space and time saving can be made. However, this access will typically arise because of structure in the matrix, which enables the computation of entries, given their indices. If this structure is not present, and we just have a generic sparse matrix, we still require QRAM for the most efficient block-encoding of the matrix. In this case, implementation of the quantum sparse access structure in minimal depth implementation uses $\tilde{\mathcal{O}}(Ns)$ qubits and $\mathcal{O}(\log N)$ overhead [13], where s is the minimization over the row sparsity and column sparsity. In this case, the block-encoded complexities would be similar to that quoted in Table 1, but with an up to quadratically more efficient qubit overhead. We remark that for specific classes of matrices there may also be more efficient ways to enact the sparse data access model [21], but we leave the comparison for such special cases to be beyond the scope of this work.

Finally, we remark that in Tables 1 and 2 we presume that the relevant data structure for the input vector \vec{b} is efficiently provided. In general, providing the input state $|\vec{b}\rangle$ also requires a QRAM. We recall that with our randomized scheme we can circumvent this quantum resources cost by providing additional classical pre-processing overhead (see Proposition 4).

In this section, we have compared resource costs only for one specific task. For other applications, various classical and quantum overheads need to be carefully considered which can vastly change the complexities. One end-to-end problem in which one does not expect to achieve superpolynomial quantum advantage is where one needs to read off the entire solution vector. In this case, the additional $\Omega(N)$ tomographic overhead can be compared to the polynomial scaling of the classical runtimes in $\kappa_F(A) \geq \sqrt{\text{rk}(A)}$. We remark that in this setting, one would

⁶This consists of oracles to coherently access the non-zero row and column entries, as well as an additional oracle to coherently access all matrix entries.

only hope to achieve approximately at most a quadratic speedup in total runtime to the best randomized classical solver in dimension dependence, ignoring dependencies on the approximation error ε .

4 Ground state sampling

4.1 Randomized quantum algorithm

In this section we consider the problem of sampling properties of the ground state of a given Hamiltonian. In order to approximately project to the ground state we use the Gaussian function $e^{-\frac{1}{2}\tau^2 x^2}$ for Hamiltonians with positive spectra. A Fourier series representation was found for this function in Ref. [53], which we use to establish the following corollary.

Corollary 2 (Ground state property estimation). *Consider a Hamiltonian $H = \sum_l E_l |E_l\rangle\langle E_l|$ with all eigenvalues $E_l \geq 0$, and known Pauli decomposition $H = \sum_{\ell=1}^L a_\ell P_\ell$; $\lambda = \sum_\ell |a_\ell|$. Assume the spectral gap of H is lower bounded by $\Delta \leq E_1 - E_0$. Additionally, we suppose that we have an initial trial state $|\psi_0\rangle$ with overlap with the ground state $\gamma := |\langle \psi_0 | E_0 \rangle|$. Finally, we assume that $E_0 \leq \Delta / \sqrt{2 \log \frac{\|O\|}{\varepsilon \gamma}}$ for some error parameter ε . Then, given ability to measure observable O , we give a randomized algorithm to*

$$\text{approximate } \langle E_0 | O | E_0 \rangle \text{ up to additive error } \varepsilon, \quad (23)$$

with arbitrary constant success probability, using

$$C_{\text{sample}}^O = \tilde{O} \left(\frac{\|O\|^2}{\varepsilon^2 \gamma^4} \right) \text{ circuit runs}, \quad (24)$$

each of the form in Figure 2(b), each using one instance of $|\psi_0\rangle$ with

$$C_{\text{gate}}^O = \tilde{O} \left(\frac{\lambda^2}{\Delta^2} \right) \text{ gate depth}. \quad (25)$$

Moreover, the assumption of the positivity of the spectrum can be dropped in place of a lower bound on the ground state energy, with no change to the computational complexity of the algorithm.

We provide a proof of this corollary, including the extension to non-positive spectra, and accounting of poly-logarithmic or constant factor contributions in Appendix B.2. Similar to our algorithms for linear systems, we emphasize that we do not ask for any quantum oracle or quantum subroutines encoding information about H . Additionally, if the trial state $|\psi_0\rangle$ is accessible as a classical description of vector amplitudes, or from a linear combination of gates, then the trial state can be prepared statistically as part of the randomized algorithm, with minimal depth requirements (see Proposition 4 and Appendix A.4). Our algorithm is particularly efficient when the Pauli weight λ is small, which can be the case for certain physically motivated problems. We discuss more detailed analysis of the complexities in Section 4.2. Finally, we remark that if a trial state is instead provided with bounded positive overlap $\tilde{\gamma} := \langle \psi_0 | E_0 \rangle$, then quantities of the form $\langle \phi | E_0 \rangle$ can be approximated with a reduced $\tilde{\gamma}^{-2}$ dependence in the sample complexity.

4.2 Comparison

Different approaches to quantum algorithms for ground state preparation have been previously studied in Refs. [29, 31, 53–57]. Recently, Ref. [31] also established an explicit algorithm for ground state property estimation. In Table 3 we compare the complexities of various algorithms for the task of estimating a given observable with respect to the ground state. Namely, we compare the following approaches:

- A linear combination of unitaries (LCU) ground state preparation algorithm [53], which requires a time evolution oracle. We detail the complexities required for both first order Trotter time evolution which has no additional quantum space requirements, as well as the quantum-runtime-efficient block encoding approach [51].

	Quantum Oracle	GSE/gap Assumptions	Data Access Space	Ancillary Algorithmic Space	Quantum Gate Depth	Runtime
LCU [53]	1 ^o Trotter time evol.	(B1)	$\mathcal{O}(L)$ bits	$\mathcal{O}\left(\log\left(\frac{1}{\Delta}\log\frac{1}{\gamma\varepsilon^2}\right)\right)$ qubits	$\tilde{\mathcal{O}}\left(\frac{L^3\Lambda^2}{\gamma\Delta^2}\frac{1}{\varepsilon}\right)$	$\tilde{\mathcal{O}}\left(\frac{L^3\Lambda^2}{\gamma\Delta^2}\frac{1}{\varepsilon^3}\right)$
	Block encoding time evol. [51]		$\mathcal{O}(L)$ bits + $\mathcal{O}(\log L)$ qubits		$\tilde{\mathcal{O}}\left(\frac{L\lambda}{\gamma\Delta^2}\log^{3/2}\frac{1}{\varepsilon}\right)$	$\tilde{\mathcal{O}}\left(\frac{L\lambda}{\gamma\Delta^2}\frac{1}{\varepsilon^2}\right)$
Near Query Optimal [54]	Block encoding	(B2)	$\mathcal{O}(L)$ bits + $\mathcal{O}(\log L)$ qubits	1 qubit	$\tilde{\mathcal{O}}\left(\frac{L\lambda}{\gamma\Delta}\log\frac{1}{\varepsilon}\right)$	$\tilde{\mathcal{O}}\left(\frac{L\lambda}{\gamma\Delta}\frac{1}{\varepsilon^2}\right)$
		none		$\mathcal{O}(\log(\frac{1}{\gamma}))$ qubits		
Early F.T. [31]	1 ^o Trotter time evol.	none	$\mathcal{O}(L)$ bits	1 qubit	$\tilde{\mathcal{O}}\left(\frac{L^3\Lambda^2}{\Delta^2}\frac{1}{\varepsilon}\log\frac{1}{\gamma}\right)$	$\tilde{\mathcal{O}}\left(\frac{L^3\Lambda^2}{\gamma^4\Delta^2}\frac{1}{\varepsilon^3}\right)$
	Block encoding time evol. [51]		$\mathcal{O}(L)$ bits + $\mathcal{O}(\log L)$ qubits		$\tilde{\mathcal{O}}\left(\frac{L\lambda}{\Delta}\log\frac{1}{\gamma^2\varepsilon}\right)$	$\tilde{\mathcal{O}}\left(\frac{L\lambda}{\gamma^4\Delta}\frac{1}{\varepsilon^2}\right)$
This Work (Randomized Quantum)	-	(B1)	$\mathcal{O}(L)$ bits	1 qubit	$\mathcal{O}\left(\frac{\lambda^2}{\Delta^2}\log^2\frac{1}{\gamma^2\varepsilon}\right)$	$\tilde{\mathcal{O}}\left(\frac{\lambda^2}{\gamma^4\Delta^2}\frac{1}{\varepsilon^2}\right)$

Table 3: End-to-end comparison of complexities to approximate the expectation value of an observable with respect to the ground state, up to ε -additive error. These algorithms presume access to a trial state approximating the ground state with overlap γ ; a spectral gap lower bound Δ , and possible further assumptions (B1): given $\mu_1 \leq E_0$ s.t. $E_0 - \mu_1 \leq \Delta/\sqrt{\log\frac{1}{\gamma\varepsilon}}$, and (B2): given $\mu_2 \geq E_0$ s.t. $\mu_2 - \Delta/2 \geq E_0$, $\mu_2 + \Delta/2 \leq E_1$. In all cases we assume that the Hamiltonian is given in terms of its Pauli decomposition (see Eq. (1)) with L Pauli terms, largest coefficient magnitude Λ and coefficient weight λ .

- The block encoding approaches of Ref. [54] to prepare the ground state, which is query optimal in $\gamma, \Delta, \varepsilon$ up to logarithmic factors. We note that Ref. [54] gives two approaches; one where there is an a priori bound for the ground state energy and spectral gap, and one where there is no such assumption which uses more ancillary qubits and has equivalent runtime up to dominant order.
- The early fault-tolerant approach of Ref. [31] to sample properties of the ground state, which again requires a time evolution oracle. As a caveat, this approach can only prepare unitary observables. Non-unitary observables can be taken into account with a block encoding, at the expense of more qubits and complexities augmented by the block encoding factor. For the sake of easy comparison, in Table 3 we assume that the observable is unitary.
- Our approach using Corollary 2, assuming no parallelization.

For the ground state preparation algorithms considered in Table 3, we assume that the observable is measured incoherently, in order to establish the most competitive gate depth with regards to our approach. However, we note that coherent estimation of observables yields a faster overall runtime, at the expense of $\mathcal{O}(\varepsilon^{-1})$ scaling in the gate depth [48, 49]. For all algorithms we assume that the Hamiltonian is provided classically in the form of its Pauli coefficients (as in Eq. (1)). If the total number of Pauli terms L is small, this allows for an efficient block encoding via the SELECT and PREPARE oracles, which is what we consider in Table 3. We also consider Trotterized time evolution, which gives additional dependencies on commutators between terms [58], which here we bound with the magnitude of the largest Pauli coefficient $\Lambda := \max_{\ell} a_{\ell}$ for simplicity. We note that some approaches to ground state preparation have implicit dependencies on $\|H\|$, which we here omit by assuming $\|H\| = 1$ for simplicity.

As with our linear systems algorithm, we focus on the quantum hardware requirements, which consists of the total number of logical qubits required for data access and to run the algorithm, as well as the gate depth. Similar to the linear systems task considered in Section 3.3, our approach has the smallest space requirement, and there is scope for our algorithm to have competitive gate depth if the Pauli weight λ is smaller than number of Pauli terms L . Our algorithm additionally has no runtime dependence on L at all, so there is scope for possible advantage over other approaches for problems with large L .

Finally, we note that in Table 3 we have not accounted for the runtime to prepare the trial state. Other coherent approaches require coherent calls to the unitary that prepares the trial state. Thus, if the runtime of this subroutine is significant, this would also cause discrepancies in the total runtimes listed.

5 Application: Estimation of Green's functions

So far we have seen that our algorithms are naturally suited to settings where the matrix of interest is already given in the Pauli basis. Thus, our algorithms are naturally suited to physically motivated problems. One natural application is the evaluation of single particle Green's functions in the context of many body physics. Green's functions are used to calculate single-particle expectation values such as the kinetic energy, as well as to determine the many-body density of states. For more detailed background we refer the reader to Refs. [59, 60]. Previous works have also constructed quantum algorithms for preparing Green's functions [53, 61–64].

We define the advanced and retarded Green's function (denoted as $G^{(+)}(\omega)$ and $G^{(-)}(\omega)$ respectively) as the matrix-valued functions with elements

$$G_{ij}^{(+)}(\omega) := \langle E_0 | \hat{a}_i (\hbar\omega - (H - E_0) + i\eta)^{-1} \hat{a}_j^\dagger | E_0 \rangle \quad (26)$$

$$G_{ij}^{(-)}(\omega) := \langle E_0 | \hat{a}_i^\dagger (\hbar\omega + (H - E_0) - i\eta)^{-1} \hat{a}_j | E_0 \rangle, \quad (27)$$

where E_0 is the ground state energy of H , η is a parameter that determines the resolution of the Green's function, and $\hat{a}_i^\dagger, \hat{a}_i$ are single-particle creation and annihilation operators. We note that these quantities are expectation values of an operator which contains the inverse of some matrix, where the expectation value is taken with respect to the ground state. Thus, our earlier results in Sections 3 and 4 can be readily applied. The creation and annihilation operators can be expressed using Pauli operators via the Jordan-Wigner transformation

$$\hat{a}_i = Z^{\otimes(i-1)} \otimes \frac{1}{2}(X + iY) \otimes I^{\otimes(N-i)}, \quad \hat{a}_i^\dagger = Z^{\otimes(i-1)} \otimes \frac{1}{2}(X - iY) \otimes I^{\otimes(N-i)}. \quad (28)$$

We now present our result for Green's function estimation. From hereon we denote $\Gamma^{(+)} = \hbar\omega - (H - E_0) + i\eta$ and $\Gamma^{(-)} = \hbar\omega + (H - E_0) - i\eta$. We remark that whilst it is possible to use the algorithms of Section 3 and 4 as separate subroutines to evaluate the Green's functions, it is beneficial to compile the ground state projection and matrix inversion all at once. This is the scheme we present in the following proposition.

Proposition 5 (Green's function estimation). *Consider a Hamiltonian $H = \sum_l E_l |E_l\rangle\langle E_l|$ with all eigenvalues $E_l \geq 0$, and known Pauli decomposition $H = \sum_\ell a_\ell P_\ell$; $\lambda_H := \sum_\ell |a_\ell|$. Assume the spectral gap is lower bounded as $\Delta \leq E_1 - E_0$. Additionally, we suppose that we can freely prepare an initial trial state $|\psi_0\rangle$ with overlap with the ground state $\gamma := |\langle \psi_0 | E_0 \rangle|$. Given parameters ω, η and the ground state energy E_0 , we give a random compiler to*

$$\text{approximate } G_{ij}^{(+)}(\omega) \text{ \& } G_{ij}^{(-)}(\omega) \text{ up to additive error } \varepsilon, \quad (29)$$

and arbitrary constant success probability, each utilizing

$$\tilde{O} \left(\frac{\|(\Gamma^{(\pm)})^{-1}\|^2}{\gamma^4 \varepsilon^2} \right) \text{ circuit runs}, \quad (30)$$

respectively, each consisting of at most

$$\tilde{O} \left(\frac{\lambda_H^2}{\Delta^2} + (|\hbar\omega \pm E_0| + \lambda_H + \eta)^2 \|\Gamma^{(\pm)}^{-1}\|^2 \right) \text{ gate depth}. \quad (31)$$

We provide a proof of this result in Appendix B.3. As with our previous algorithms, the scheme we use has an advantage that it does not have any explicit dependence on the number of Pauli terms L . We remark that in the algorithm of Proposition 5, the ground state energy is exactly as an input. If this is not available, the ground state energy may be approximated via the techniques of other early fault-tolerant schemes [27–30]. Moreover, if the ground state energy is approximated to sufficiently small precision, error contribution to the Green's functions can be constrained (see Appendix B.3 for more details).

6 Outlook

We presented a framework for sampling properties of general matrix Fourier series and applied this to give explicit algorithms for the linear systems problem and the ground state property estimation problem. By starting with a (classical) description of the matrix in the Pauli basis, we circumvent the need for coherent data structures, which adds to the hardware burden of other quantum algorithms. Another distinct feature of our approach is that there is no explicit dimension or sparsity dependence in our complexities; instead, the runtime depends on the norm of the Pauli coefficients for the matrix, which in principle can be much smaller than number of Pauli terms or the dimension of the system. As such, our framework is particularly suited to physically motivated matrices, where the Pauli description is readily available and of low weight.

There are immediate open questions that have yet to be explored:

- Is it possible for certain special classes of matrices to efficiently obtain the Pauli decomposition starting from a description in the computational basis? If the number of Pauli terms is known and small, up to a quadratic saving in the dimension can be made compared to the naïve approach, though this would still present a barrier to any possible superpolynomial quantum runtime advantage compared to classical schemes directly working in the computational basis. The question of obtaining the Pauli decomposition also has implications for near term schemes for linear systems that start with similar assumptions [34–36]. More broadly, this also leads into the question of what data structures or data sources are amenable to possible quantum speedups.
- We have considered worst-case performance guarantees for our algorithms, though it remains to see how practical performance behaves with increasing number of samples. Further, more precise numerical analysis of finite resource costs for concrete problems (such as the calculation of Green’s functions for a particular problem of interest) would be illuminating for the feasibility of our schemes in the early fault-tolerant regime.
- Our linear systems algorithm could possibly undergo further refinements, inspired by classical algorithms. For instance, it is general practice to use preconditioners for linear systems solvers to effectively reduce the effect of the condition number on the runtime (e.g. see Refs. [65–67]), and analogous quantum preconditioners have been studied [61, 68, 69]. We leave it as future work to investigate whether such techniques and beyond can be efficiently transported to the early fault-tolerant setting.
- We discussed in Section 2.1 various properties of the Fourier series that influences the complexities of our algorithms. In particular, in order to constrain the sample complexity the variance of the randomized schemes should be constrained. It remains to be seen whether there are other functions of interest beyond the inverse function and Gaussian function which have Fourier series approximations which can lead to algorithms with favorable complexities.

Acknowledgments

This project was started when MB and SW were additionally affiliated with the AWS Center for Quantum Computing, Pasadena, USA. We thank Earl Campbell for collaboration in the early stages of this project. We thank Leandro Aolita and his research group, Fernando Brandão, Chi-Fang (Anthony) Chen, Alexander M. Dalzell, Steven T. Flammia, and Kianna Wan for discussions (in alphabetical order). MB is supported by the EPSRC Grant number EP/W032643/1. SW is supported by the Samsung GRP grant.

References

- [1] J. Preskill. “Quantum Computing in the NISQ era and beyond”. In: *Quantum* 2 (2018), p. 79. DOI: [10.22331/q-2018-08-06-79](https://doi.org/10.22331/q-2018-08-06-79) (Cit. p. 1).
- [2] K. Bharti et al. “Noisy intermediate-scale quantum algorithms”. In: *Reviews of Modern Physics* 94.1 (2022), p. 015004. DOI: [10.1103/RevModPhys.94.015004](https://doi.org/10.1103/RevModPhys.94.015004). URL: <https://journals.aps.org/rmp/abstract/10.1103/RevModPhys.94.015004> (Cit. p. 1).

- [3] M. Cerezo et al. “Variational quantum algorithms”. In: *Nature Reviews Physics* 3.1 (2021), 625–644. DOI: [10.1038/s42254-021-00348-9](https://doi.org/10.1038/s42254-021-00348-9). URL: <https://www.nature.com/articles/s42254-021-00348-9> (Cit. p. 1).
- [4] A. Montanaro. “Quantum algorithms: an overview”. In: *npj Quantum Information* 2.1 (2016), pp. 1–8. URL: <https://www.nature.com/articles/npjqi201523> (Cit. p. 1).
- [5] R. De Wolf. “Quantum computing: Lecture notes”. In: *arXiv preprint arXiv:1907.09415* (2019). URL: <https://arxiv.org/abs/1907.09415> (Cit. p. 1).
- [6] B. Bauer, S. Bravyi, M. Motta, and G. K.-L. Chan. “Quantum algorithms for quantum chemistry and quantum materials science”. In: *Chemical Reviews* 120.22 (2020), pp. 12685–12717. URL: <https://pubs.acs.org/doi/10.1021/acs.chemrev.9b00829> (Cit. p. 1).
- [7] L. Lin. “Lecture notes on quantum algorithms for scientific computation”. In: *arXiv preprint arXiv:2201.08309* (2022). URL: <https://arxiv.org/abs/2201.08309> (Cit. p. 1).
- [8] A. Gilyén, Y. Su, G. H. Low, and N. Wiebe. “Quantum singular value transformation and beyond: exponential improvements for quantum matrix arithmetics”. In: *Proceedings of the 51st Annual ACM SIGACT Symposium on Theory of Computing* (2019), pp. 193–204. URL: <https://dl.acm.org/doi/10.1145/3313276.3316366> (Cit. pp. 1, 4, 8, 9, 12).
- [9] J. M. Martyn, Z. M. Rossi, A. K. Tan, and I. L. Chuang. “Grand Unification of Quantum Algorithms”. In: *PRX Quantum* 2.4 (2021), p. 040203. DOI: [10.1103/PRXQuantum.2.040203](https://doi.org/10.1103/PRXQuantum.2.040203) (Cit. pp. 1, 4, 8, 9).
- [10] A. W. Harrow, A. Hassidim, and S. Lloyd. “Quantum algorithm for linear systems of equations”. In: *Physical Review Letters* 103.15 (2009), p. 150502. DOI: [10.1103/PhysRevLett.103.150502](https://doi.org/10.1103/PhysRevLett.103.150502) (Cit. pp. 2, 9–11).
- [11] P. Costa, D. An, Y. R. Sanders, Y. Su, R. Babbush, and D. W. Berry. “Optimal scaling quantum linear systems solver via discrete adiabatic theorem”. In: *arXiv preprint arXiv:2111.08152* (2021). URL: <https://journals.aps.org/prxquantum/accepted/c2078Dc0Ze01ee0780c10715e4a4bec634bff9e47> (Cit. pp. 2, 9, 11, 12).
- [12] V. Giovannetti, S. Lloyd, and L. Maccone. “Quantum random access memory”. In: *Physical review letters* 100.16 (2008), p. 160501. URL: <https://journals.aps.org/prl/abstract/10.1103/PhysRevLett.100.160501> (Cit. p. 2).
- [13] O. Di Matteo, V. Gheorghiu, and M. Mosca. “Fault-tolerant resource estimation of quantum random-access memories”. In: *IEEE Transactions on Quantum Engineering* 1 (2020), pp. 1–13. URL: <https://ieeexplore.ieee.org/document/8962352> (Cit. pp. 2, 12).
- [14] C. T. Hann, G. Lee, S. Girvin, and L. Jiang. “Resilience of quantum random access memory to generic noise”. In: *PRX Quantum* 2.2 (2021), p. 020311. URL: <https://journals.aps.org/prxquantum/abstract/10.1103/PRXQuantum.2.020311> (Cit. p. 2).
- [15] C. T. Hann, C.-L. Zou, Y. Zhang, Y. Chu, R. J. Schoelkopf, S. M. Girvin, and L. Jiang. “Hardware-Efficient Quantum Random Access Memory with Hybrid Quantum Acoustic Systems”. In: *Physical Review Letters* 123.25 (2019), p. 250501. DOI: [10.1103/PhysRevLett.123.250501](https://doi.org/10.1103/PhysRevLett.123.250501) (Cit. p. 2).
- [16] B. D. Clader, A. M. Dalzell, N. Stamatopoulos, G. Salton, M. Berta, and W. J. Zeng. “Quantum Resources Required to Block-Encode a Matrix of Classical Data”. In: *arXiv preprint arXiv:2206.03505* (2022). URL: <https://arxiv.org/abs/2206.03505> (Cit. pp. 2, 10, 11).
- [17] A. M. Childs, D. Maslov, Y. Nam, N. J. Ross, and Y. Su. “Toward the first quantum simulation with quantum speedup”. In: *Proceedings of the National Academy of Sciences* 115.38 (2018), pp. 9456–9461. URL: <https://www.pnas.org/doi/abs/10.1073/pnas.1801723115> (Cit. pp. 2, 12).
- [18] R. Babbush, C. Gidney, D. W. Berry, N. Wiebe, J. McClean, A. Paler, A. Fowler, and H. Neven. “Encoding electronic spectra in quantum circuits with linear T complexity”. In: *Physical Review X* 8.4 (2018), p. 041015. URL: <https://journals.aps.org/prx/abstract/10.1103/PhysRevX.8.041015> (Cit. pp. 2, 12).
- [19] D. W. Berry, C. Gidney, M. Motta, J. R. McClean, and R. Babbush. “Qubitization of arbitrary basis quantum chemistry leveraging sparsity and low rank factorization”. In: *Quantum* 3 (2019), p. 208. URL: <https://quantum-journal.org/papers/q-2019-12-02-208/> (Cit. pp. 2, 12).
- [20] K. Wan. “Exponentially faster implementations of Select (H) for fermionic Hamiltonians”. In: *Quantum* 5 (2021), p. 380. URL: <https://quantum-journal.org/papers/q-2021-01-12-380/> (Cit. pp. 2, 12).

- [21] D. Camps, L. Lin, R. Van Beeumen, and C. Yang. “Explicit Quantum Circuits for Block Encodings of Certain Sparse Matrices”. In: *arXiv preprint arXiv:2203.10236* (2022). URL: <https://arxiv.org/abs/2203.10236> (Cit. pp. 2, 12).
- [22] S. Aaronson. “Read the fine print”. In: *Nature Physics* 11.4 (2015), pp. 291–293. URL: <https://www.nature.com/articles/nphys3272> (Cit. p. 2).
- [23] T. Strohmer and R. Vershynin. “A randomized Kaczmarz algorithm with exponential convergence”. In: *Journal of Fourier Analysis and Applications* 15.2 (2009), pp. 262–278. URL: <https://link.springer.com/article/10.1007/s00041-008-9030-4> (Cit. pp. 2, 10, 11).
- [24] A. Gilyén, Z. Song, and E. Tang. “An improved quantum-inspired algorithm for linear regression”. In: *Quantum* 6 (2022), p. 754. URL: <https://quantum-journal.org/papers/q-2022-06-30-754/> (Cit. p. 2).
- [25] C. Shao and A. Montanaro. “Faster quantum-inspired algorithms for solving linear systems”. In: *ACM Transactions on Quantum Computing* 3.4 (2022), pp. 1–23. URL: <https://dl.acm.org/doi/10.1145/3520141> (Cit. pp. 2, 10, 11).
- [26] E. T. Campbell. “Early fault-tolerant simulations of the Hubbard model”. In: *Quantum Science and Technology* 7.1 (2021), p. 015007. URL: <https://iopscience.iop.org/article/10.1088/2058-9565/ac3110/meta> (Cit. p. 2).
- [27] L. Lin and Y. Tong. “Heisenberg-Limited Ground-State Energy Estimation for Early Fault-Tolerant Quantum Computers”. In: *PRX Quantum* 3.1 (2022), p. 010318. DOI: [10.1103/PRXQuantum.3.010318](https://doi.org/10.1103/PRXQuantum.3.010318) (Cit. pp. 2–5, 15).
- [28] K. Wan, M. Berta, and E. T. Campbell. “Randomized Quantum Algorithm for Statistical Phase Estimation”. In: *Physical Review Letters* 129.3 (2022), p. 030503. DOI: [10.1103/PhysRevLett.129.030503](https://doi.org/10.1103/PhysRevLett.129.030503) (Cit. pp. 2–5, 15, 22).
- [29] Y. Dong, L. Lin, and Y. Tong. “Ground state preparation and energy estimation on early fault-tolerant quantum computers via quantum eigenvalue transformation of unitary matrices”. In: *arXiv preprint arXiv:2204.05955* (2022). URL: <https://arxiv.org/abs/2204.05955> (Cit. pp. 2, 3, 13, 15).
- [30] G. Wang, D. Stilck-França, R. Zhang, S. Zhu, and P. D. Johnson. “Quantum algorithm for ground state energy estimation using circuit depth with exponentially improved dependence on precision”. In: *arXiv preprint arXiv:2209.06811* (2022). URL: <https://arxiv.org/abs/2209.06811> (Cit. pp. 2, 3, 15).
- [31] R. Zhang, G. Wang, and P. Johnson. “Computing ground state properties with early fault-tolerant quantum computers”. In: *Quantum* 6 (2022), p. 761. URL: <https://quantum-journal.org/papers/q-2022-07-11-761/> (Cit. pp. 2, 3, 13, 14).
- [32] E. Campbell. “Random Compiler for Fast Hamiltonian Simulation”. In: *Physical Review Letters* 123.7 (2019), p. 070503. DOI: [10.1103/PhysRevLett.123.070503](https://doi.org/10.1103/PhysRevLett.123.070503) (Cit. p. 3).
- [33] P. K. Faehrmann, M. Steudtner, R. Kueng, M. Kieferová, and J. Eisert. “Randomizing multi-product formulas for Hamiltonian simulation”. In: *Quantum* 6 (2022), p. 806. URL: <https://quantum-journal.org/papers/q-2022-09-19-806/> (Cit. pp. 3–5, 24).
- [34] C. Bravo-Prieto, R. LaRose, M. Cerezo, Y. Subasi, L. Cincio, and P. J. Coles. “Variational quantum linear solver”. In: *arXiv preprint arXiv:1909.05820* (2019). URL: <https://arxiv.org/abs/1909.05820> (Cit. pp. 3, 16).
- [35] X. Xu, J. Sun, S. Endo, Y. Li, S. C. Benjamin, and X. Yuan. “Variational algorithms for linear algebra”. In: *Science Bulletin* 66.21 (2021), pp. 2181–2188. URL: <https://www.sciencedirect.com/science/article/pii/S2095927321004631> (Cit. pp. 3, 16).
- [36] H.-Y. Huang, K. Bharti, and P. Rebentrost. “Near-term quantum algorithms for linear systems of equations”. In: *arXiv preprint arXiv:1909.07344* (2019). URL: <https://arxiv.org/abs/1909.07344> (Cit. pp. 3, 9, 16).
- [37] D. W. Berry, A. M. Childs, R. Cleve, R. Kothari, and R. D. Somma. “Exponential improvement in precision for simulating sparse Hamiltonians”. In: *Proceedings of the forty-sixth annual ACM symposium on Theory of computing* (2014), pp. 283–292. URL: <https://dl.acm.org/doi/abs/10.1145/2591796.2591854> (Cit. p. 4).
- [38] D. W. Berry, A. M. Childs, and R. Kothari. “Hamiltonian simulation with nearly optimal dependence on all parameters”. In: *2015 IEEE 56th annual symposium on foundations of computer science* (2015), pp. 792–809. URL: <https://ieeexplore.ieee.org/document/7354428> (Cit. p. 4).

- [39] D. W. Berry, A. M. Childs, R. Cleve, R. Kothari, and R. D. Somma. “Simulating Hamiltonian dynamics with a truncated Taylor series”. In: *Physical review letters* 114.9 (2015), p. 090502. URL: <https://journals.aps.org/prl/abstract/10.1103/PhysRevLett.114.090502> (Cit. p. 4).
- [40] A. M. Childs, R. Kothari, and R. D. Somma. “Quantum Algorithm for Systems of Linear Equations with Exponentially Improved Dependence on Precision”. In: *SIAM Journal on Computing* 46.6 (2017), pp. 1920–1950. DOI: [10.1137/16M1087072](https://doi.org/10.1137/16M1087072) (Cit. pp. 7–9, 33).
- [41] S. Gharibian and F. Le Gall. “Dequantizing the quantum singular value transformation: Hardness and applications to quantum chemistry and the quantum PCP conjecture”. In: *Proceedings of the 54th Annual ACM SIGACT Symposium on Theory of Computing* (2022), pp. 19–32. URL: <https://dl.acm.org/doi/abs/10.1145/3519935.3519991> (Cit. p. 8).
- [42] S. Apers, S. Sen, and D. Szabó. “A (simple) classical algorithm for estimating Betti numbers”. In: *arXiv preprint arXiv:2211.09618* (2022). URL: <https://arxiv.org/abs/2211.09618> (Cit. p. 8).
- [43] A. Ambainis. “Variable time amplitude amplification and quantum algorithms for linear algebra problems”. In: *STACS’12 (29th Symposium on Theoretical Aspects of Computer Science)* 14 (2012), pp. 636–647. URL: <https://arxiv.org/abs/1010.4458> (Cit. p. 9).
- [44] Y. Subaşı, R. D. Somma, and D. Orsucci. “Quantum Algorithms for Systems of Linear Equations Inspired by Adiabatic Quantum Computing”. In: *Physical Review Letters* 122.6 (2019), p. 060504. DOI: [10.1103/PhysRevLett.122.060504](https://doi.org/10.1103/PhysRevLett.122.060504) (Cit. p. 9).
- [45] L. Lin and Y. Tong. “Optimal polynomial based quantum eigenstate filtering with application to solving quantum linear systems”. In: *Quantum* 4 (2020), p. 361. URL: <https://quantum-journal.org/papers/q-2020-11-11-361/> (Cit. p. 9).
- [46] D. An and L. Lin. “Quantum Linear System Solver Based on Time-Optimal Adiabatic Quantum Computing and Quantum Approximate Optimization Algorithm”. In: *ACM Transactions on Quantum Computing* 3.2 (2022). DOI: [10.1145/3498331](https://doi.org/10.1145/3498331) (Cit. p. 9).
- [47] Y. Subaşı, R. D. Somma, and D. Orsucci. “Quantum algorithms for systems of linear equations inspired by adiabatic quantum computing”. In: *Physical review letters* 122.6 (2019), p. 060504. URL: <https://journals.aps.org/prl/abstract/10.1103/PhysRevLett.122.060504> (Cit. p. 9).
- [48] E. Knill, G. Ortiz, and R. D. Somma. “Optimal quantum measurements of expectation values of observables”. In: *Physical Review A* 75.1 (2007), p. 012328. URL: <https://journals.aps.org/prl/abstract/10.1103/PhysRevA.75.012328> (Cit. pp. 9–11, 14).
- [49] D. Wang, O. Higgott, and S. Brierley. “Accelerated variational quantum eigensolver”. In: *Physical review letters* 122.14 (2019), p. 140504. URL: <https://journals.aps.org/prl/abstract/10.1103/PhysRevLett.122.140504> (Cit. pp. 9–11, 14).
- [50] S. Chakraborty, A. Gilyén, and S. Jeffery. “The Power of Block-Encoded Matrix Powers: Improved Regression Techniques via Faster Hamiltonian Simulation”. In: *46th International Colloquium on Automata, Languages, and Programming (ICALP 2019)* (2019). URL: <https://arxiv.org/abs/1804.01973> (Cit. p. 10).
- [51] G. H. Low. “Hamiltonian simulation with nearly optimal dependence on spectral norm”. In: *Proceedings of the 51st Annual ACM SIGACT Symposium on Theory of Computing* (2019), pp. 491–502. URL: <https://dl.acm.org/doi/10.1145/3313276.3316386> (Cit. pp. 10, 11, 13, 14).
- [52] N.-H. Chia, A. P. Gilyén, T. Li, H.-H. Lin, E. Tang, and C. Wang. “Sampling-based sublinear low-rank matrix arithmetic framework for dequantizing quantum machine learning”. In: *Journal of the ACM* 69.5 (2022), pp. 1–72. URL: <https://dl.acm.org/doi/10.1145/3357713.3384314> (Cit. p. 10).
- [53] T. Keen, E. Dumitrescu, and Y. Wang. “Quantum Algorithms for Ground-State Preparation and Green’s Function Calculation”. In: *arXiv preprint arXiv:2112.05731* (2021). URL: <https://arxiv.org/abs/2112.05731> (Cit. pp. 13–15, 35, 36).
- [54] L. Lin and Y. Tong. “Near-optimal ground state preparation”. In: *Quantum* 4 (2020), p. 372. DOI: [10.22331/q-2020-12-14-372](https://doi.org/10.22331/q-2020-12-14-372) (Cit. pp. 13, 14).
- [55] Y. Ge, J. Tura, and J. I. Cirac. “Faster ground state preparation and high-precision ground energy estimation with fewer qubits”. In: *Journal of Mathematical Physics* 60.2 (2019), p. 022202. DOI: [10.1063/1.5027484](https://doi.org/10.1063/1.5027484) (Cit. p. 13).

- [56] O. Kyriienko. “Quantum inverse iteration algorithm for programmable quantum simulators”. In: *npj Quantum Information* 6.1 (2020), pp. 1–8. URL: <https://www.nature.com/articles/s41534-019-0239-7> (Cit. p. 13).
- [57] T. A. Bespalova and O. Kyriienko. “Hamiltonian operator approximation for energy measurement and ground-state preparation”. In: *PRX Quantum* 2.3 (2021), p. 030318. URL: <https://journals.aps.org/prxquantum/abstract/10.1103/PRXQuantum.2.030318> (Cit. p. 13).
- [58] A. M. Childs, Y. Su, M. C. Tran, N. Wiebe, and S. Zhu. “Theory of trotter error with commutator scaling”. In: *Physical Review X* 11.1 (2021), p. 011020. URL: <https://journals.aps.org/prx/abstract/10.1103/PhysRevX.11.011020> (Cit. p. 14).
- [59] G. Giuliani and G. Vignale. *Quantum theory of the electron liquid*. Cambridge university press, 2005 (Cit. p. 15).
- [60] A. L. Fetter and J. D. Walecka. *Quantum theory of many-particle systems*. Courier Corporation, 2012 (Cit. p. 15).
- [61] Y. Tong, D. An, N. Wiebe, and L. Lin. “Fast inversion, preconditioned quantum linear system solvers, fast Green’s-function computation, and fast evaluation of matrix functions”. In: *Physical Review A* 104.3 (2021), p. 032422. DOI: [10.1103/PhysRevA.104.032422](https://doi.org/10.1103/PhysRevA.104.032422) (Cit. pp. 15, 16).
- [62] I. Rungger et al. “Dynamical mean field theory algorithm and experiment on quantum computers”. In: *arXiv preprint arXiv:1910.04735* (2019). URL: <https://arxiv.org/abs/1910.04735> (Cit. p. 15).
- [63] S. Endo, I. Kurata, and Y. O. Nakagawa. “Calculation of the Green’s function on near-term quantum computers”. In: *Physical Review Research* 2.3 (2020), p. 033281. URL: <https://journals.aps.org/prresearch/abstract/10.1103/PhysRevResearch.2.033281> (Cit. p. 15).
- [64] T. Kosugi and Y.-i. Matsushita. “Construction of Green’s functions on a quantum computer: Quasiparticle spectra of molecules”. In: *Physical Review A* 101.1 (2020), p. 012330. URL: <https://journals.aps.org/pr/abstract/10.1103/PhysRevA.101.012330> (Cit. p. 15).
- [65] J. W. Demmel. *Applied numerical linear algebra*. SIAM, 1997 (Cit. p. 16).
- [66] G. H. Golub and C. F. Van Loan. *Matrix computations, 4th*. 2013 (Cit. p. 16).
- [67] Y. Saad. *Iterative methods for sparse linear systems*. SIAM, 2003 (Cit. p. 16).
- [68] B. D. Clader, B. C. Jacobs, and C. R. Sprouse. “Preconditioned quantum linear system algorithm”. In: *Physical review letters* 110.25 (2013), p. 250504. URL: <https://journals.aps.org/prl/abstract/10.1103/PhysRevLett.110.250504> (Cit. p. 16).
- [69] C. Shao and H. Xiang. “Quantum circulant preconditioner for a linear system of equations”. In: *Physical Review A* 98.6 (2018), p. 062321. URL: <https://journals.aps.org/pr/abstract/10.1103/PhysRevA.98.062321> (Cit. p. 16).
- [70] S. Aaronson and D. Gottesman. “Improved simulation of stabilizer circuits”. In: *Physical Review A* 70.5 (2004), p. 052328. URL: <https://journals.aps.org/pr/abstract/10.1103/PhysRevA.70.052328> (Cit. p. 32).
- [71] C. Gidney. “Stim: a fast stabilizer circuit simulator”. In: *Quantum* 5 (2021), p. 497. URL: <https://quantum-journal.org/papers/q-2021-07-06-497/> (Cit. p. 32).
- [72] R. L. Stratonovich. “A method for the. computation of quantum distribution functions”. In: *Doklady Akademii Nauk* 115.6 (1957), pp. 1097–1100. URL: https://www.mathnet.ru/php/archive.phtml?wshow=paper&jrnid=dan&paperid=22296&option_lang=eng (Cit. p. 36).
- [73] J. Hubbard. “Calculation of partition functions”. In: *Physical Review Letters* 3.2 (1959), p. 77. URL: <https://journals.aps.org/prl/abstract/10.1103/PhysRevLett.3.77> (Cit. p. 36).

Contents

1	Introduction	1
1.1	Overview	1
1.2	Related work	3
1.3	Outline	3

2	General approach	4
2.1	Warm-up problem	4
2.2	Main result	5
2.3	Classically easy functions	7
3	Linear systems	8
3.1	Randomized quantum linear system solver	8
3.2	Statistical encoding of input vector	9
3.3	Comparison	9
3.3.1	Quantum linear systems solvers	9
3.3.2	Complexity comparison	10
4	Ground state sampling	13
4.1	Randomized quantum algorithm	13
4.2	Comparison	13
5	Application: Estimation of Green’s functions	15
6	Outlook	16
A	Fourier sampling	22
A.1	Sampling from a given Fourier series - proof of Proposition 1	22
A.2	Generalized Fourier sampling - proof of Theorem 1	25
A.3	Sampling normalization constant - proof of Proposition 2	27
A.4	Statistical encoding of classical vectors	30
A.5	Classical capability	31
B	Application-specific results	33
B.1	Linear systems	33
B.2	Ground state sampling	35
B.2.1	Power method	38
B.3	Evaluating Green’s functions	39

Appendices

In these appendices we present detailed statements for our theoretical results, as well as the proofs thereof:

In Appendix A we introduce the main technical results of the paper. Specifically, in Appendix A.1 we first show how to prove the result in the warm-up problem (Proposition 1) for sampling properties of a given Fourier series, before proving our main result (Theorem 1) for sampling properties of matrix functions in Appendix A.2. In Appendix A.3 we discuss the complexities of evaluating normalized quantities that correspond to normalized quantum states. Next, in Appendix A.4 we discuss how to statistically encode classical vectors as part of our randomized scheme (Proposition 4). We then discuss the classical power of our randomized scheme for sampling properties of low-degree polynomials in Appendix A.5 (Proposition 3).

In Appendix B we demonstrate how our algorithms for linear systems (Corollary 1) and ground state property estimation (Corollary 2) follow from our main results. We also show how these two algorithms allow for a scheme to evaluate Green’s functions in many body physics (Proposition 5).

A Fourier sampling

A.1 Sampling from a given Fourier series - proof of Proposition 1

We start by introducing the random compiling lemma of Ref. [28] which demonstrates how to decompose time evolution operators into Pauli gates and Pauli rotations.

Lemma 1 (*Random compiling lemma - adapted from Lemma 2 of Ref. [28]*). *Let $A = \sum_{\ell} a_{\ell} P_{\ell}$ be a Hermitian operator that is specified as a linear combination of Pauli operators with Pauli weight $\lambda := \sum_{\ell} |a_{\ell}|$ and real coefficients $a_{\ell} \in \mathbb{R}$. For any $t \in \mathbb{R}$ and any choice of $r \in \mathbb{N} := \{1, 2, \dots\}$, there exists a linear decomposition*

$$e^{iAt} = \sum_{m \in T} \beta_m^{(r)} U_m^{(r)}, \quad (32)$$

for some index set T , unitaries $\{U_m^{(r)}\}_m$, and real numbers $\{\beta_m^{(r)}\}_m$ such that $\sum_{m \in T} \beta_m^{(r)} \leq \exp(\lambda^2 t^2 / r)$. For all $m \in T$, the non-Clifford cost of controlled- $U_m^{(r)}$ is that of r controlled single-qubit Pauli rotations.

Proof. We note that Ref. [28] provided an explicit proof for operators with normalized Pauli weight and positive coefficients (i.e. the coefficients are probabilities). We leave the core proof to the Appendix C of Ref. [28], and for completeness here we explicitly demonstrate how the proof extends to the more general setting.

First we consider the scenario where $\lambda = 1$ but a_{ℓ} may not necessarily be positive. Ref. [28] expresses an r^{th} of the time evolution operator as

$$e^{iAt/r} = \sum_{n \text{ even}} \gamma_n(t/r) \sum_{\ell_1, \dots, \ell_n, \ell'} a_{\ell_1} \dots a_{\ell_n} a_{\ell'} P_{\ell_1} \dots P_{\ell_n} \exp(i\theta_n P_{\ell'}) \quad (33)$$

$$= \sum_{n \text{ even}} \gamma_n(t/r) \sum_{\ell_1, \dots, \ell_n, \ell'} |a|_{\ell_1} \dots |a|_{\ell_n} |a|_{\ell'} \cdot \text{sgn}(a_{\ell_1} \dots a_{\ell_n} a_{\ell'}) P_{\ell_1} \dots P_{\ell_n} \exp(i\theta_n P_{\ell'}), \quad (34)$$

where $\gamma_n(t/r)$ are coefficients satisfying $\sum_{(n \text{ even})} \gamma_n(t/r) \leq \exp(t^2/r^2)$. In the second line we see that we can proceed as if the coefficients were positive (probabilities), by absorbing their sign into the string of unitaries to implement $P_{\ell_1} \dots P_{\ell_n} \exp(i\theta_n P_{\ell'})$. By considering the product of such fractional time evolution operators $(e^{iAt/r})^r$ we can then sample strings of Pauli operators and r Pauli rotations (with an absorbed phase), with total weight $\leq (\exp(t^2/r^2))^r = \exp(t^2/r)$. This consists of r pairs of controlled (multi-qubit) Pauli rotation and a string of controlled Pauli gates, whose number is in theory unbounded. We remark, however, that the number of Pauli gates is with high probability zero with exponentially decaying probability for increasing gate number [28]. Further these gates can be efficiently compiled together classically into a single controlled (multi-qubit) Pauli gate using standard Pauli product rules.

Now we can consider how to deal with non-unit Pauli weight. For H with non-unit Pauli weight λ we can simply consider the equality $e^{iAt} = e^{i\hat{A}\lambda t}$, where $\hat{A} = A/\lambda$ now has unit Pauli weight. As Lemma 1 holds for all $t \in \mathbb{R}$, the steps of the original proof can follow, by considering an extended time parameter $t \rightarrow \lambda t$. \square

Algorithm 2 Fourier sampling of $\text{Tr} [s(A)\rho s(A)^\dagger O]$

Problem input:

- $N \times N$ Hermitian matrix $A = \sum_\ell a_\ell P_\ell$, with $a_\ell \in \mathbb{R} \forall \ell$, and known Pauli weight $\lambda = \sum_\ell |a_\ell|$
- Fourier parameters $\{\alpha_k\}_{k \in F}$, $\{t_k\}_{k \in F}$ for series $s(A)$ according to Eq. (2)
- Input state ρ and measurement operator O .

Parameters: (1) Approximation parameter ε ; (2) Success probability $1 - \delta$; (3) Runtime vector $\vec{r} \in \mathbb{N}^{|F|}$.

Output: Approximation to $\text{Tr} [s(A)\rho s(A)^\dagger O]$ with additive error at most ε and probability at least $1 - \delta$.

1. Compute coefficients $\{\beta_{km}^{(\vec{r})}\}_{(k,m) \in F \times T}$ as in Eq. (32) for each time parameter $\{t_k\}_{k \in F}$.
 2. $R(\vec{r}) \leftarrow \sum_{(k,m) \in F \times T} |\alpha_k \beta_{km}^{(r_k)}|$.
 3. $M(\vec{r}) \leftarrow \lceil 4 \ln(2/\delta) (R(\vec{r})/\varepsilon)^2 \rceil$.
 4. **for** $j \in [M(\vec{r})]$:
 - (i) Sample two strings of gates independently as:
 - (a) Sample indices (k', m') according to probability distribution $\{|\alpha_k \beta_{km}^{(r_k)}|/R(\vec{r})\}_k$ and select corresponding string of gates $U_{k'm'}^{(r_{k'})}$
 - (b) Repeat with new independent sample (k'', m'') , select $U_{k''m''}^{(r_{k''})}$.
 - (ii) Run $n + 1$ qubit circuit in Figure 2(b) with input state $|0\rangle\langle 0| \otimes \rho$, controlled $U_{k'm'}^{(r_{k'})}$ and anti-controlled $U_{k''m''}^{(r_{k''})}$, and measurement $X \otimes O$. Record measurement outcome o_j .
 - (iii) $z_j \leftarrow R(\vec{r})^2 o_j$.
 5. **end for**
 6. $\bar{z}^{(M)} \leftarrow \sum_j z_j / M(\vec{r})$. **return** $\bar{z}^{(M)}$.
-

With the above Lemma, we can now demonstrate how to solve our warm-up problem of sampling properties of a given Fourier series. In the following we present a more precise version of Proposition 1 from the main text.

Proposition 1 (Sampling from Fourier series – detailed version). *Suppose that we have a Fourier series*

$$s(A) = \sum_{k \in F} \alpha_k \exp(it_k A), \quad (35)$$

in some $N \times N$ Hermitian matrix A , and denote the ℓ_1 -norm of the coefficients as $\alpha := \sum_{k \in F} |\alpha_k|$. Suppose further that A has known Pauli decomposition $A = \sum_\ell a_\ell P_\ell$ with Pauli weight $\lambda = \sum_\ell |a_\ell|$. Then,

- (a). *Given a procedure to prepare the pure states $|\psi\rangle$, $|\phi\rangle$ with respective unitaries U_ψ , U_ϕ with respective gate depths d_ψ , d_ϕ , we have a randomized quantum algorithm that uses $\log(N) + 1$ qubits to approximate $\langle \phi | s(A) | \psi \rangle$ up to additive error ε with probability at least $1 - \delta$, using Algorithm 1 with*

$$\mathcal{C}_{\text{sample}}^\phi \in \mathcal{O} \left(\log \left(\frac{2}{\delta} \right) \frac{\alpha^2}{\varepsilon^2} \right), \quad (36)$$

circuit samples, where each circuit takes the form in Figure 2(a) and has depth

$$\mathcal{C}_{\text{gate}}^\phi = \mathcal{O}(\lambda^2 t_{\max}^2 + d_\psi + d_\phi), \quad (37)$$

where we denote $t_{\max} = \max_{k \in F} t_k$.

- (b). *Given a procedure to prepare the quantum state ρ in depth d_ρ and perform measurements with measurement operator O , we give a randomized quantum algorithm that uses $\log(N) + 1$ qubits to approximate*

$\text{Tr} [s(A)\rho s(A)^\dagger O]$ up to additive error ε with probability at least $1 - \delta$ using Algorithm 2 with

$$\mathcal{C}_{\text{sample}}^O = \mathcal{O} \left(\log \left(\frac{2}{\delta} \right) \frac{\|O\|^2 \alpha^4}{\varepsilon^2} \right), \quad (38)$$

circuit samples, where each circuit takes the form in Figure 2(b), and has depth

$$\mathcal{C}_{\text{gate}}^\phi = \mathcal{O} (\lambda^2 t_{\max}^2 + d_\psi + d_\phi). \quad (39)$$

Proof of Proposition 1. We note that from Lemma 1, $s(\varepsilon, A)$ can be decomposed via a linear combination as

$$s(A) = \sum_{k \in F} \alpha_k \exp(it_k A) = \sum_{(k,m) \in F \times T} \alpha_k \beta_{km}^{(r_k)} U_{km}^{(r_k)} \quad (40)$$

where $\sum_{m \in T} \beta_{km}^{(r_k)} \leq \exp(\lambda^2 t_k^2 / r_k)$ and $U_{km}^{(r_k)}$ consists of r_k non-Clifford operations. The above expression can further be seen as a quantity that is proportional to a probability distribution over unitaries

$$s(A) = R(\vec{r}) \sum_{(k,m) \in F \times T} \frac{|\alpha_k \beta_{km}^{(r_k)}|}{R(\vec{r})} \tilde{U}_{km}^{(r_k)} = \sum_{(k,m) \in F \times T} p_{km}^{(r_k)} \tilde{U}_{km}^{(r_k)}, \quad (41)$$

where $p_{km}^{(r_k)} = \frac{|\alpha_k \beta_{km}^{(r_k)}|}{R(\vec{r})}$ are probabilities, $\tilde{U}_{km}^{(r_k)} = U_{km}^{(r_k)} \frac{\alpha_k \beta_{km}^{(r_k)}}{|\alpha_k \beta_{km}^{(r_k)}|}$ are unitaries that absorb the phase of the coefficients, and $R(\vec{r})$ is the weight of the linear combination, which satisfies

$$R(\vec{r}) = \sum_{(k,m) \in F \times T} |\alpha_k \beta_{km}^{(r_k)}| \quad (42)$$

$$\leq \sum_{k \in F} |\alpha_k| \exp(\lambda^2 t_k^2 / r_k), \quad (43)$$

where in the last line we have denoted $\alpha := \sum_{k \in F} |\alpha_k|$. We note that one is free to tune $\vec{r} = (r_1, \dots, r_{|F|})$, and in doing so, change the gate depth of the circuit to apply each unitary, whilst also changing $R(\vec{r})$ which will feed into the sample complexity. One simple choice is to set $r_k = \lambda^2 t_k^2$ for all k , which gives $R(\vec{r}) \leq \alpha \varepsilon$, where we recall $\alpha := \sum_{k \in F} |\alpha_k|$. We now consider our two settings separately.

(i) *Preparation of $\text{Tr} [s(\varepsilon, A)\rho s(\varepsilon, A)^\dagger O]$.* Using Eq. (41) can now express this quantity as

$$\text{Tr} [s(A)\rho s(A)^\dagger O] = R(\vec{r})^2 \sum_{(k,m),(k',m') \in F \times T} p_{km}^{(r_k)} p_{k'm'}^{(r_{k'})} \text{Tr} \left[\tilde{U}_{km}^{(r_k)} \rho \left(\tilde{U}_{k'm'}^{(r_{k'})} \right)^\dagger O \right]. \quad (44)$$

As described in Ref. [33], given controlled access to $\tilde{U}_{km}^{(r_k)}$ and $\tilde{U}_{k'm'}^{(r_{k'})}$, the quantity $\text{Tr} [\tilde{U}_{km}^{(r_k)} \rho (\tilde{U}_{k'm'}^{(r_{k'})})^\dagger O]$ can be prepared with the quantum circuit in Figure 2(b). Moreover, according to Born's rule the individual measurement outcomes o_j take values in the interval $[-\|O\|, \|O\|]$. We now propose the following (informal) algorithm: for some choice of \vec{r} , (1) sample according to probability distribution $\{p_{km}^{(r_k)} p_{k'm'}^{(r_{k'})}\}_{kmk'm'}$; (2) prepare the circuit for $\text{Tr} [\tilde{U}_{km}^{(r_k)} \rho (\tilde{U}_{k'm'}^{(r_{k'})})^\dagger O]$ and collect measurement result z_j ; (3) multiply result by $R(\vec{r})^2$ to get z_j ; (4) repeat procedure and average over M samples. We present the full formal steps in Algorithm 2. As we are effectively sampling numbers in the interval $[-\|O\|R(\vec{r})^2, \|O\|R(\vec{r})^2]$, Hoeffding's inequality specifies that $\bar{z}^{(M)} := \frac{1}{M} \sum_{i=1}^M z_j$ satisfies

$$\text{Prob} \left(\left| \bar{z}^{(M)} - \text{Tr} [s(A)\rho s(A)^\dagger O] \right| \geq \varepsilon \right) \leq 2 \exp \left(-\frac{M\varepsilon^2}{2\|O\|^2 R(\vec{r})^4} \right). \quad (45)$$

This implies that, in order to guarantee $|\bar{z}^{(M)} - \text{Tr} [s(A)\rho s(A)^\dagger O]| \leq \varepsilon$ with probability at least $1 - \delta$, it is sufficient to perform

$$M \geq \log \left(\frac{2}{\delta} \right) \frac{2\|O\|^2 R(\vec{r})^4}{\varepsilon^2} \quad (46)$$

circuit samples.

We now impose the choice $r_k = \lambda^2 t_k^2$ for all k which sets $R = \mathcal{O}(\alpha)$. As specified by Lemma 1, this means each $\tilde{U}_{km}^{(r_k)}$ consists of layers of controlled Pauli gates in between $\lambda^2 t_k^2$ single-qubit controlled Pauli rotations. Thus in order to obtain an ε -close approximation with probability at least $1 - \delta$ it is sufficient to take number of samples and non-Clifford gates satisfying

$$\mathcal{C}_{sample}^O = 2e^4 \log\left(\frac{2}{\delta}\right) \frac{\|O\|^2 \alpha^4}{\varepsilon^2}, \quad \mathcal{C}_{gate}^O = 2\lambda^2 t_{max}^2 + d_\rho, \quad (47)$$

respectively, where we have denoted $t_{max} = \max_{k \in F} t_k$.

(ii) *Preparation of $\langle \phi | s(A) | \psi \rangle$.* We can express this quantity as

$$\langle \phi | s(A) | \psi \rangle = R(\vec{r}) \sum_{(k,m) \in F \times T} p_{km}^{(r_k)} \langle 0 | U_\phi^\dagger \tilde{U}_{km}^{(r_k)} U_\psi | 0 \rangle. \quad (48)$$

The real and imaginary parts of the quantity $\langle 0 | U_\phi^\dagger \tilde{U}_{km}^{(r_k)} U_\psi | 0 \rangle$ can be recovered separately by the circuit in Fig. 2(a). In both cases, individual measurement outcomes lie in the interval $[-1, 1]$. As before, Hoeffding's inequality tells us that

$$M \geq \log\left(\frac{2}{\delta}\right) \frac{4R(\vec{r})^2}{\varepsilon^2} \quad (49)$$

shots are required to recover both the imaginary and real parts with probability at least $1 - \delta$, to additive error ε . We can again choose $r_k = \lambda^2 t_k^2$ for all k , giving respective sample and gate counts:

$$\mathcal{C}_{sample}^\phi = 4e^2 \log\left(\frac{2}{\delta}\right) \frac{\alpha^2}{\varepsilon^2}, \quad \mathcal{C}_{gate}^\phi = \lambda^2 t_{max}^2 + d_\phi + d_\psi. \quad (50)$$

□

A.2 Generalized Fourier sampling - proof of Theorem 1

We first establish a Lemma relating the closeness of operators to the closeness of expectation values constructed from them.

Lemma 2 (Tightness of expectation values pt. 1). *Consider two operators Y and D that satisfy the closeness relation $\|Y - D\| \leq \varepsilon \leq 1$, $\|Y\| \geq 1$. Then we have*

$$|\text{Tr}[OY\rho Y^\dagger] - \text{Tr}[OD\rho D^\dagger]| \leq 3\|O\|\|Y\|\varepsilon. \quad (51)$$

Proof. We have

$$|\text{Tr}[OY\rho Y^\dagger] - \text{Tr}[OD\rho D^\dagger]| = |\text{Tr}[O(Y - D)\rho Y^\dagger] + \text{Tr}[O(D - Y)\rho(Y^\dagger - D^\dagger)] + \text{Tr}[OY\rho(Y^\dagger - D^\dagger)]| \quad (52)$$

$$\leq \|O\| (\|Y - D\|\|Y^\dagger\| + \|Y - D\|^2 + \|Y\|\|Y - D\|) \quad (53)$$

$$\leq \|O\| (2\|Y\|\varepsilon + \varepsilon^2) \quad (54)$$

$$\leq 3\|O\|\|Y\|\varepsilon, \quad (55)$$

where in the first line we have added and subtracted $\text{Tr}[OD\rho Y^\dagger] + \text{Tr}[OY\rho D^\dagger]$; the first inequality is due to the triangle inequality, Hölder's tracial matrix inequality and the sub-multiplicativity of the operator norm; and the second and third inequalities are due to our starting assumptions. □

We can now proceed with the proof of the main theorem (Theorem 1). We suppose we have a matrix function $f(A)$ that is approximated by a Fourier series as

$$\|f(A) - s(\varepsilon, A)\| \leq \varepsilon; \quad s(\varepsilon, A) = \sum_{k \in F_{\varepsilon, A}} \alpha_k(\varepsilon, A) \exp(it_k(\varepsilon, A)A), \quad (56)$$

for some set of Fourier parameters $\alpha_k(\varepsilon, A)$ and $t_k(\varepsilon, A)$, for any $\varepsilon \leq 1$. Denote the ℓ_1 -norm of the coefficients as $\alpha(\varepsilon) := \sum_k |\alpha_k(\varepsilon)|$. Suppose further that A has known Pauli decomposition $A = \sum_\ell a_\ell P_\ell$ with Pauli weight $\lambda = \sum_\ell |a_\ell|$, and that we are given some normalization constant q .

Theorem 1 (Generalized sampling from Fourier approximations – detailed version). *Suppose we have a matrix function $f(A)$ that is approximated by a Fourier series as*

$$\|f(A) - s(\tilde{\varepsilon}, A)\| \leq \tilde{\varepsilon} \leq 1; \quad s(\tilde{\varepsilon}, A) = \sum_{k \in F_{\tilde{\varepsilon}, A}} \alpha_k(\tilde{\varepsilon}, A) \exp(it_k(\tilde{\varepsilon}, A)A), \quad (57)$$

where A is some $N \times N$ Hermitian matrix, and for some set of Fourier parameters $\alpha_k(\tilde{\varepsilon}, A)$ and $t_k(\tilde{\varepsilon}, A)$ with tunable error parameter $\tilde{\varepsilon}$. Denote the ℓ_1 -norm of the coefficients as $\alpha(\tilde{\varepsilon}, A) := \sum_k |\alpha_k(\tilde{\varepsilon}, A)|$. Suppose further that A has known Pauli decomposition $A = \sum_\ell a_\ell P_\ell$ with Pauli weight $\lambda = \sum_\ell |a_\ell|$. Then,

- (a). Given unitaries U_ϕ, U_ψ to prepare $|\phi\rangle, |\psi\rangle$ respectively in depth d_ϕ, d_ψ , we give a randomized quantum algorithm that uses $\log(N) + 1$ qubits to approximate the quantity $\frac{1}{q} \langle \phi | f(A) | \psi \rangle$ up to additive error $\varepsilon \leq \frac{1}{q}$ with probability at least $1 - \delta$, using

$$\mathcal{C}_{\text{sample}}^\phi = \mathcal{O} \left(\log \left(\frac{2}{\delta} \right) \frac{[\alpha(\varepsilon q, A)]^2}{\varepsilon^2 q^2} \right), \quad \mathcal{C}_{\text{gate}}^\phi = \mathcal{O} \left(\lambda^2 [t_{\max}(\varepsilon q, A)]^2 + d_\phi + d_\psi \right), \quad (58)$$

circuit samples (each calling U_ϕ and U_ψ one time) and gate depth respectively, where each circuit takes the form in Figure 2(a).

- (b). Given a procedure to prepare the quantum state ρ in gate depth d_ρ and perform measurements with measurement operator O , and given normalization constant q , there exists a randomized quantum algorithm that uses $\log(N) + 1$ qubits to approximate $\frac{1}{q^2} \text{Tr} [f(A)\rho f(A)^\dagger O]$ up to additive error $\varepsilon \leq \frac{\|O\| \|f(A)\|}{q^2}$ with probability at least $1 - \delta$, using

$$\mathcal{C}_{\text{sample}}^O = \mathcal{O} \left(\log \left(\frac{2}{\delta} \right) \frac{\|O\|^2 \left[\alpha \left(\frac{\varepsilon q^2}{\|O\| \|f(A)\|}, A \right) \right]^4}{\varepsilon^2 q^4} \right), \quad \mathcal{C}_{\text{gate}}^O = \mathcal{O} \left(\lambda^2 \left[t_{\max} \left(\frac{\varepsilon q^2}{\|O\| \|f(A)\|}, A \right) \right]^2 + d_\rho \right), \quad (59)$$

circuit samples and non-Clifford gates respectively, where we denote $t_{\max}(\varepsilon, A) = \max_{k \in F_{\varepsilon, A}} t_k(\varepsilon, A)$ and each circuit takes the form in Figure 2(b).

Proof of Theorem 1 (Generalized sampling from Fourier approximations). We consider the two cases separately.

- (i) *Preparation of $\frac{1}{q^2} \text{Tr} [f(A)\rho f(A)^\dagger O]$.* We will use Proposition 1 to statistically approximate the quantity $\frac{1}{q^2} \text{Tr} [s(\tilde{\varepsilon}, A)\rho s(\tilde{\varepsilon}, A)^\dagger O]$. Using Lemma 2 we will then show that, for appropriately chosen $\tilde{\varepsilon}$, this leads to an ε -close approximation of $\frac{1}{q^2} \text{Tr} [f(A)\rho f(A)^\dagger O]$.

Recall we denote $\bar{z}^{(M)}$ as the statistical approximation to $\text{Tr} [s(\tilde{\varepsilon}, A)\rho s(\tilde{\varepsilon}, A)^\dagger O]$ using Algorithm 2 with M shots. We would like to find parameters such that

$$\left| \frac{1}{q^2} \bar{z}^{(M)} - \frac{1}{q^2} \text{Tr} [f(A)\rho f(A)^\dagger O] \right| \leq \varepsilon. \quad (60)$$

We first note that due to the triangle inequality, we can write

$$\left| \frac{1}{q^2} \bar{z}^{(M)} - \frac{1}{q^2} \text{Tr} [f(A)\rho f(A)^\dagger O] \right| \leq \left| \frac{1}{q^2} \bar{z}^{(M)} - \frac{1}{q^2} \text{Tr} [s(\tilde{\varepsilon}, A)\rho s(\tilde{\varepsilon}, A)^\dagger O] \right| + \left| \frac{1}{q^2} \text{Tr} [s(\tilde{\varepsilon}, A)\rho s(\tilde{\varepsilon}, A)^\dagger O] - \frac{1}{q^2} \text{Tr} [f(A)\rho f(A)^\dagger O] \right|. \quad (61)$$

This separates the approximation error into two components; the statistical contribution of sampling from the Fourier series, and the deterministic contribution from the quality of the Fourier series approximation. It is sufficient to satisfy Eq. (60) by requiring both terms on the right hand side of Eq. (61) to each be bounded by $\frac{1}{2}\varepsilon$.

From Lemma 2, we can see that the second term in Eq. (61) is bounded by $\frac{1}{2}\varepsilon$ by finding Fourier parameters such that $\|f(A) - s(\tilde{\varepsilon}, A)\| \leq \frac{1}{6}\varepsilon \frac{q^2}{\|O\| \|f(A)\|} \leq 1$. Thus, it is sufficient to pick $\tilde{\varepsilon} = \frac{1}{6}\varepsilon \frac{q^2}{\|O\| \|f(A)\|}$. From Proposition 1, the first term in Eq. (61) is bounded by $\frac{1}{2}\varepsilon$ by choosing $M \geq 8e^4 \log \left(\frac{2}{\delta} \right) \frac{\|O\|^2 \alpha(\varepsilon q^2/6\|O\| \|f(A)\|)^4}{\varepsilon^2 q^4}$, $\mathcal{C}_{\text{gate}} = 2\lambda^2 t_{\max}^2(\varepsilon q^2/6\|O\| \|f(A)\|) + d_\rho$.

(ii) *Preparation of $\frac{1}{q}\langle\phi|f(A)|\psi\rangle$.* Denote as $T^{(M')}$ the statistical approximation to $\langle\phi|f(A)|\psi\rangle$ using Algorithm 2 with M' shots. Again, we can split up the approximation error into respective statistical and deterministic contributions as

$$\left|\frac{1}{q}T^{(M')} - \frac{1}{q}\langle\phi|f(A)|\psi\rangle\right| \leq \left|\frac{1}{q}T^{(M')} - \frac{1}{q}\langle\phi|s(\tilde{\varepsilon}, A)|\psi\rangle\right| + \left|\frac{1}{q}\langle\phi|s(\tilde{\varepsilon}, A)|\psi\rangle - \frac{1}{q}\langle\phi|f(A)|\psi\rangle\right| \quad (62)$$

The second term in Eq. (62) (deterministic contribution) is simply bounded as

$$\left|\frac{1}{q}\langle\phi|s(\tilde{\varepsilon}, A)|\psi\rangle - \frac{1}{q}\langle\phi|f(A)|\psi\rangle\right| \leq \frac{1}{q}\|s(\tilde{\varepsilon}, A) - f(A)\|. \quad (63)$$

Thus, in order to bound the deterministic contribution by $\frac{1}{2}\varepsilon$, using Lemma 2, is sufficient to find Fourier parameters such that $\|s(\tilde{\varepsilon}, A) - f(A)\| \leq \varepsilon q/2 \leq 1$, and we can assign $\tilde{\varepsilon} = \varepsilon q/2$. The first term in Eq. (62) (statistical contribution) is then bounded by $\frac{1}{2}\varepsilon$ by choosing $M' \geq 8e^4 \log\left(\frac{2}{\delta}\right) \frac{\|O\|^2 \alpha(\varepsilon q/2)^4}{\varepsilon^2 q^2}$, $C_{gate} = 2\lambda^2 t_{max}^2(\varepsilon q/2) + d_\phi + d_\psi$. \square

We remark in the above proof we have split the error into statistical and deterministic contributions evenly. In some cases, $\alpha(\varepsilon, A)$ can have a logarithmic dependence on $1/\varepsilon$, such as for our linear systems algorithm. In this case by not distributing the error evenly one can make a small constant factor saving to the sample complexity.

A.3 Sampling normalization constant - proof of Proposition 2

In this section we investigate the complexity of sampling $q = \|f(A)|\phi\rangle\|$ for use as a normalization constant, where $|\phi\rangle$ is some given preparable input state. In the previous sections we found iid random variables z_j such that when averaged over M samples as $\bar{z}^{(M)} := \frac{1}{M} \sum_{j=1}^M z_j$ is ε -close to a desired expectation value. We similarly denote our statistical approximation to q^2 as $Q^{(M_q)}$. In the following lemma we establish how well $Q^{(M_q)}$ must approximate q^2 such that normalized quantities are additive ε -close.

Lemma 3 (Normalization precision). *Suppose we have some $\bar{z}^{(M)} \in \mathbb{R}$, pure state $|\phi\rangle$, and operators $O, f(A)$ that satisfy*

$$\left|\frac{1}{q^2}\bar{z}^{(M)} - \frac{1}{q^2}\langle\phi|f(A)Of(A)^\dagger|\phi\rangle\right| \leq \varepsilon \leq 1, \quad (64)$$

with $\|O\| \geq 1$. Further, denote $q = \|f(A)|\phi\rangle\|_2$. Then, if $Q^{(M_q)}$ is the statistical approximation of q^2 , one can achieve

$$\left|\frac{1}{Q^{(M_q)}}\bar{z}^{(M)} - \frac{1}{q^2}\langle\phi|f(A)Of(A)^\dagger|\phi\rangle\right| \leq 3\varepsilon \quad (65)$$

if $Q^{(M_q)}$ satisfies $|Q^{(M_q)} - q^2| \leq \frac{1}{2} \frac{\varepsilon q^2}{\|O\|}$.

Proof. First, we note that due to the triangle inequality and sub-multiplicativity we have

$$\left|\frac{1}{Q^{(M_q)}}\bar{z}^{(M)} - \frac{1}{q^2}\langle\phi|f(A)Of(A)^\dagger|\phi\rangle\right| \leq \left|\frac{1}{Q^{(M_q)}}\bar{z}^{(M)} - \frac{1}{q^2}\bar{z}^{(M)}\right| + \left|\frac{1}{q^2}\bar{z}^{(M)} - \frac{1}{q^2}\langle\phi|f(A)Of(A)^\dagger|\phi\rangle\right| \quad (66)$$

$$\leq \left|\frac{1}{Q^{(M_q)}} - \frac{1}{q^2}\right| |\bar{z}^{(M)}| + \varepsilon \quad (67)$$

$$\leq \left|\frac{1}{Q^{(M_q)}} - \frac{1}{q^2}\right| (q^2\|O\| + q^2\varepsilon) + \varepsilon, \quad (68)$$

assuming $\varepsilon \leq 1$, where in the penultimate inequality we have used the fact that $|\bar{z}^{(M)}| \leq \langle\phi|f(A)Of(A)^\dagger|\phi\rangle + q^2\varepsilon$ where $\langle\phi|f(A)Of(A)^\dagger|\phi\rangle \leq \|O\|_\infty \|f(A)|b\rangle\langle b|f(A)^\dagger\|_1 \leq \|O\|_\infty \|f(A)|\phi\rangle\|_2^2$. Denoting $|Q^{(M_q)} - q^2| \leq \nu$, we can

observe

$$\left| \frac{1}{Q^{(M_q)}} - \frac{1}{q^2} \right| \leq \frac{\nu}{Q^{(M_q)} q^2} \quad (69)$$

$$\leq \frac{\nu}{q^2(q^2 - \nu)} \quad (70)$$

$$= \frac{\nu}{q^4(1 - \frac{\nu}{q^2})} \quad (71)$$

$$\leq \frac{\nu}{q^4} \left(8 \left(\frac{\nu}{q^2} \right)^2 - 4 \frac{\nu}{q^2} + 2 \right). \quad (72)$$

Then one can check that $\nu = \frac{1}{2} \frac{\varepsilon q^2}{\|O\|}$ gives $\left| \frac{1}{Q^{(M_q)}} - \frac{1}{q^2} \right| \leq \frac{\varepsilon^2}{q^2 \|O\|^2} (\frac{\varepsilon}{\|O\|} - 1) + \frac{\varepsilon}{q^2 \|O\|} \leq \frac{\varepsilon}{q^2 \|O\|}$ and so, returning to Eq. (68), under this condition we have $\left| \frac{1}{Q^{(M_q)}} \bar{z}^{(M)} - \frac{1}{q^2} \langle \phi | f(A) O f(A)^\dagger | \phi \rangle \right| \leq 3\varepsilon$ for $\varepsilon \leq 1$, $\|O\| \geq 1$. \square

By similar reasoning, we also have the following lemma for quantities of the form of a state overlap, rather than expectation values of general measurement observables.

Lemma 4 (Normalization precision pt. 2). *Suppose we have some $\bar{z}^{(M)} \in \mathbb{R}$, pure states $|\phi\rangle, |\psi\rangle$, and an operator $f(A)$ that satisfy*

$$\left| \frac{1}{q} \bar{z}^{(M)} - \frac{1}{q} \langle \phi | f(A) | \psi \rangle \right| \leq \varepsilon \leq 1, \quad (73)$$

where we denote $q = \|f(A)|\phi\rangle\|_2$. Then, if $Q^{(M_q)}$ is the statistical approximation of q^2 , one can achieve

$$\left| \frac{1}{\sqrt{Q^{(M_q)}}} \bar{z}^{(M)} - \frac{1}{q} \langle \phi | f(A) | \psi \rangle \right| \leq 3\varepsilon \quad (74)$$

if $Q^{(M_q)}$ satisfies $|Q^{(M_q)} - q^2| \leq \frac{1}{2} \varepsilon q^2$.

Proof. Similar to the proof of Lemma 3 we have

$$\left| \frac{1}{\sqrt{Q^{(M_q)}}} \bar{z}^{(M)} - \frac{1}{q} \langle \phi | f(A) | \psi \rangle \right| \leq \left| \frac{1}{\sqrt{Q^{(M_q)}}} - \frac{1}{q} \right| q(1 + \varepsilon) + \varepsilon. \quad (75)$$

Moreover, if $|Q^{(M_q)} - q^2| \leq \nu$ then

$$\left| \sqrt{Q^{(M_q)}} - q \right| \leq \frac{\nu}{\sqrt{Q^{(M_q)}} + q} \leq \frac{\nu}{q}. \quad (76)$$

Thus,

$$\left| \frac{1}{\sqrt{Q^{(M_q)}}} - \frac{1}{q} \right| \leq \frac{|\sqrt{Q^{(M_q)}} - q|}{\sqrt{Q^{(M_q)}} q} \quad (77)$$

$$\leq \frac{\nu}{\sqrt{Q^{(M_q)}} q^2} \quad (78)$$

$$\leq \frac{\nu}{q^2(q - \nu/q)} \quad (79)$$

$$\leq \frac{\nu}{q^3} \left(8 \left(\frac{\nu}{q^2} \right)^2 - 4 \frac{\nu}{q^2} + 2 \right), \quad (80)$$

and the choice $\nu = \frac{1}{2} \varepsilon q^2$ gives

$$\left| \frac{1}{\sqrt{Q^{(M_q)}}} - \frac{1}{q} \right| \leq \frac{\varepsilon}{q}, \quad (81)$$

which leads to the desired result, under the assumption $\varepsilon \leq 1$. \square

We will also need the following lemma, which gives a tighter result than Lemma 2 for pure states.

Lemma 5 (Tightness of expectation values pt. 2). *Given two operators C and D , where C is Hermitian, and given a pure state $|\phi\rangle$, we have*

$$|\langle\phi|D^\dagger OD|\phi\rangle - \langle\phi|COC|\phi\rangle| \leq 3 \|C|\phi\rangle\|_2 \|C - D\|_\infty \|O\|_\infty, \quad (82)$$

where we have assumed that $\|C - D\|_\infty \leq \|C|\phi\rangle\|_2$.

Proof. We directly bound the difference in expectation values as

$$|\langle\phi|D^\dagger OD|\phi\rangle - \langle\phi|COC|\phi\rangle| = \left| \langle\phi|CO(D - C)|\phi\rangle + \langle\phi|(D^\dagger - C)OC|\phi\rangle + \langle\phi|(D^\dagger - C)O(D - C)|\phi\rangle \right| \quad (83)$$

$$\begin{aligned} &\leq \| |\phi\rangle\langle\phi| C \|_1 \|O(D - C)\|_\infty + \|C|\phi\rangle\langle\phi|\|_1 \|(D^\dagger - C)O\|_\infty + \\ &\quad + \| |\phi\rangle\langle\phi| \|_1 \|(D^\dagger - C)O(D - C)\|_\infty \end{aligned} \quad (84)$$

$$\begin{aligned} &\leq \| |\phi\rangle\langle\phi| \|_2 \| |\phi\rangle\langle\phi| C \|_2 \|O\|_\infty \|D - C\|_\infty + \|C|\phi\rangle\langle\phi|\|_2 \| |\phi\rangle\langle\phi| \|_2 \|D^\dagger - C\|_\infty \|O\|_\infty + \\ &\quad + \|D^\dagger - C\|_\infty \|O\|_\infty \|D - C\|_\infty \end{aligned} \quad (85)$$

$$= 2\|C|\phi\rangle\|_2 \|C - D\|_\infty \|O\|_\infty + \|C - D\|_\infty^2 \|O\|_\infty \quad (86)$$

$$\leq 3\|C|\phi\rangle\|_2 \|C - D\|_\infty \|O\|_\infty, \quad (87)$$

where in the first equality we have added and subtracted $\langle\phi|COD|\phi\rangle + \langle\phi|D^\dagger OC|\phi\rangle + \langle\phi|COC|\phi\rangle$, in the first inequality we have used the triangle inequality and the tracial matrix Hölder's inequality, in the second inequality we have used the Cauchy-Schwarz inequality and the sub-multiplicativity of the operator norm, in the subsequent equality we have used the definition of the vector 2-norm and the fact that C is Hermitian, and in the final inequality we have used our starting assumption that $\|C - D\|_\infty \leq \|C|\phi\rangle\|_2$. \square

We can now prove that there exists a randomized quantum algorithm that finds the quantum state normalization factor, as in Proposition 2 of the main text. Following previous sections we denote our matrix function of interest as $f(A)$, and denote its Fourier series approximation as $s(\varepsilon, A)$.

Proposition 2 (Sampling normalization constant – detailed version). *If $q = \|f(A)|\psi\rangle\|$ where $|\psi\rangle$ is a preparable input state in depth d_ψ with unitary U_ψ , then we give a randomized algorithm to approximate q for the two algorithms in Theorem 1 that has success probability at least $(1 - \delta)$ and complexity*

$$C_{\text{sample}} = \mathcal{O}\left(\log\left(\frac{2}{\delta}\right) \frac{c[\alpha(\varepsilon q, A)]^4}{\varepsilon^2 q^4}\right), \quad C_{\text{gate}} = \mathcal{O}(\lambda^2 [t_{\max}(\varepsilon q, A)]^2 + d_\psi), \quad (88)$$

where $c = 1$ for the algorithm that prepares $\frac{1}{q}|\psi\rangle U f(A) V |\psi\rangle$, and $c = \|O\|^2$ for the algorithm that prepares $\frac{1}{q^2} \text{Tr}[f(A)|\psi\rangle\langle\psi|f(A)^\dagger O]$.

Proof of Proposition 2. Lemmas 3 and 4 specify that, in order to statistically approximate the normalized expectation value up to 3ε , one requires a statistical approximation to q^2 using M_q shots, which we denote as $Q^{(M_q)}$, that satisfies $|Q^{(M_q)} - q^2| \leq \frac{1}{2}\varepsilon q^2$ for problem (a) and satisfies $|Q^{(M_q)} - q^2| \leq \frac{1}{2} \frac{\varepsilon q^2}{\|O\|}$ for problem (b). We thus hereon deal with problem (b), and note that problem (a) can be accounted for by setting $\|O\| \rightarrow 1$.

We propose to construct $Q^{(M_q)}$ by sampling $\langle\phi|s(\varepsilon, A)^\dagger s(\varepsilon, A)|\phi\rangle$ via Algorithm 1 and the Hadamard test circuit in Fig. 2(a). We require

$$\left| Q^{(M_q)} - \langle\phi|f(A)^2|\phi\rangle \right| \leq \left| Q^{(M_q)} - \langle\phi|s(\varepsilon, A)^\dagger s(\varepsilon, A)|\phi\rangle \right| + \left| \langle\phi|s(\varepsilon, A)^\dagger s(\varepsilon, A)|\phi\rangle - \langle\phi|f(A)^2|\phi\rangle \right|, \quad (89)$$

to be smaller than $\frac{1}{2} \frac{\varepsilon q^2}{\|O\|}$. The second term on the right hand side is bounded by Lemma 5 as

$$\left| \langle\phi|s(\varepsilon, A)^\dagger s(\varepsilon, A)|\phi\rangle - \langle\phi|f(A)^2|\phi\rangle \right| \leq 3q \|s(\varepsilon, A) - f(A)\|. \quad (90)$$

Thus, evenly distributing error across statistical and deterministic contributions, we require a Fourier series approximation that is tight up to $\|s(\varepsilon, A) - f(A)\| \leq \frac{1}{12}\varepsilon \frac{q}{\|O\|}$. Using Proposition 1, we can constrain the first term in Eq. (89) by the value $\frac{1}{4}\varepsilon q^2$ by using $M \geq 2e^4 \log\left(\frac{2}{\delta}\right) \frac{\alpha(\frac{1}{12}\varepsilon \frac{q}{\|O\|})^2}{(\frac{1}{4}\varepsilon q^2)^2} = 32e^4 \log\left(\frac{2}{\delta}\right) \frac{\alpha(\frac{1}{12}\varepsilon \frac{q}{\|O\|})^2}{\varepsilon^2 q^4}$ shots and gate depth $C_{\text{gate}} = 2\lambda^2 t_{\max}^2 (\frac{1}{12}\varepsilon \frac{q}{\|O\|})$. \square

A.4 Statistical encoding of classical vectors

In this section we show how to statistically “encode” a classical vector $\vec{b} = (b_1, \dots, b_N)$ to recover its properties when determining state overlaps and expectation values using our randomized algorithms. We show that with $\mathcal{O}(s)$ classical pre-processing steps one can start from classical access to a vector \vec{b} and invoke it as part of a larger randomized algorithm with a cost of increased circuit samples depending on $\|\vec{b}\|_1$, and minimal quantum gate overhead. This can then replace the usual (quantum) state oracle in linear algebra algorithms, such as in our statistical algorithm for linear systems as described in Proposition 4 in the main text. We note that, traditionally, quantum algorithms that act on classical data assume an encoding is given via a normalized input vector of the form $|\vec{b}\rangle := \frac{1}{\|\vec{b}\|_2} \sum_i b_i |i\rangle$. However, our compilation scheme allows for arbitrary normalization, thus we can recover the action of the true vector \vec{b} and take into account its magnitude.

Definition 1 (Classical sparse access model). *We say that a classical vector $\vec{b} = (b_1, \dots, b_N)$ is stored with sparse access if the following set of tuples is stored and accessible in classical memory:*

$$\mathcal{B} = \{(b_i, i) \mid b_i \neq 0\}. \quad (91)$$

We suppose that we wish to randomly compile properties of a matrix G decomposed into a linear combination of implementable unitaries $G = \sum_j g_j V_j$ with weight of coefficients $g := \sum_j |g_j|$. Using our randomized sampling scheme with the circuits in Figure 2 (a) and (b), we can prepare quantities of the form $\langle \psi | G | \vec{b} \rangle$ and $\langle \vec{b} | G^\dagger O G | \vec{b} \rangle$ with respective sample complexities $\mathcal{O}(g^2/\varepsilon^2)$ and $\mathcal{O}(g^4/\varepsilon^2)$ and gate depth scaling with the largest gate depth in $\{V_j\}_j$. This presumes that there is a procedure to prepare the states $|\psi\rangle, |\vec{b}\rangle$. If $|\vec{b}\rangle$ is not provided via an oracle, the following proposition shows how to statistically recover the encoding, and how the sample complexities change.

Proposition 3 (Random compiling classical input vector – detailed version). *Suppose that a vector $\vec{b} = (b_1, \dots, b_N)$ with sparsity s is stored classically with sparse access as defined in Definition 1. Suppose further that we have access to some measurement observable O and a unitary U_ψ to prepare state $|\psi\rangle$. Then, by providing classical pre-processing in $\mathcal{O}(s)$ time, there exists a randomized quantum algorithm that returns an approximation of (a) $\langle \psi | G | \vec{b} \rangle$; (b) $\langle \vec{b} | G^\dagger O G | \vec{b} \rangle$ to additive error ε and constant arbitrary probability, using*

$$C_{\text{sample}}^\psi = \mathcal{O}\left(\frac{g^2 \|\vec{b}\|_1^2}{\varepsilon^2 \|\vec{b}\|_2^2}\right), \quad C_{\text{sample}}^O = \mathcal{O}\left(\frac{g^4 \|\vec{b}\|_1^4}{\varepsilon^2 \|\vec{b}\|_2^4}\right), \quad (92)$$

for scenarios (a) and (b) respectively, where each circuit uses one application of U_ψ . The additional gate overhead for randomly compiling the input vector is a one or two controlled multi-qubit NOT gates.

Proof of Proposition 3. We first give an overview of the main steps of our idea, before giving more precise analysis of quantum and classical resources required. We express $|\vec{b}\rangle = \sum_{i=1}^N b_i |i\rangle / \|\vec{b}\|_2$ as a weighted probabilistic sum over states

$$|\vec{b}\rangle = \frac{\|\vec{b}\|_1}{\|\vec{b}\|_2} \sum_{i=1}^N p_i^{(\vec{b})} \cdot \text{sgn}(b_i) |i\rangle = \frac{\|\vec{b}\|_1}{\|\vec{b}\|_2} \sum_{i=1}^N p_i \cdot \text{sgn}(b_i) X_i |0\rangle, \quad (93)$$

where we denote the probabilities $p_i^{(\vec{b})} = |b_i| / \|\vec{b}\|_1$, we denote $\text{sgn}(b_i) = b_i / |b_i|$, and X_i is the $\lceil \log N \rceil$ -qubit Pauli operator in $\{\mathbb{1}, X\}^{\otimes \lceil \log N \rceil}$ that corresponds to the binary representation of i . If the description in Eq. (93) is classically accessible, then $|\vec{b}\rangle$ can be statistically encoded by sampling from this distribution as follows.

(a). *Recovering $\langle \psi | G | \vec{b} \rangle$.* We can express $\langle \psi | G | \vec{b} \rangle$ as the probabilistic sum

$$\langle \psi | G | \vec{b} \rangle = \frac{\|\vec{b}\|_1}{\|\vec{b}\|_2} \sum_{i=1}^N p_i^{(\vec{b})} \cdot \text{sgn}(b_i) \langle 0 | U_\psi^\dagger G X_i | 0 \rangle = \frac{\|\vec{b}\|_1}{\|\vec{b}\|_2} g \sum_{i=1}^N p_i^{(\vec{b})} p_j^{(G)} \cdot \text{sgn}(b_i g_j) \langle 0 | U_\psi^\dagger V_j X_i | 0 \rangle, \quad (94)$$

where in the first equality we have used the fact that $|\psi\rangle = U_\psi |0\rangle$ and Eq. (93), and in the second equality we have decomposed G into its constituent unitaries as $G = \sum_j g_j V_j$ with weight of coefficients $g := \sum_j |g_j|$. The quantity $\langle \psi | G | \vec{b} \rangle$ can then be statistically recovered as follows: (1) Sample indices i', j' from the probability distribution $\{p_i^{(\vec{b})} p_j^{(G)}\}_{i,j}$. (2) Run two Hadamaard test circuits (see Fig. 2(a)) to obtain one measurement sample each of

$\text{Re}(\langle 0|U_\psi^\dagger V_{j'} X_{i'}|0\rangle)$ and $\text{Im}(\langle 0|U_\psi^\dagger V_{j'} X_{i'}|0\rangle)$ respectively. (3) Classically multiply the result by $\|\vec{b}\|_1 g \text{sgn}(b_{i'} g_{j'}) / \|\vec{b}\|_2$ and store the result. (4) Repeat process $\mathcal{C}_{sample}^\phi$ times and average over results. Due to Hoeffding's inequality, it is sufficient to take

$$\mathcal{C}_{sample}^\phi = 8 \log \left(\frac{2}{\delta} \right) \frac{g^2 \|\vec{b}\|_1}{\varepsilon^2 \|\vec{b}\|_2} \quad (95)$$

samples to attain an answer within additive error ε and probability at least $(1 - \delta)$. (The additional factor of 4 comes from approximating $\text{Re}(\langle 0|U_\psi^\dagger V_j X_i|0\rangle)$ and $\text{Im}(\langle 0|U_\psi^\dagger V_j X_i|0\rangle)$ each to additive error $\varepsilon/\sqrt{2}$ separately.)

(b). *Recovering $\langle \vec{b}|G^\dagger O G|\vec{b}\rangle$.* Similar to the above, we can write

$$\langle \vec{b}|G^\dagger O G|\vec{b}\rangle = \frac{\|\vec{b}\|_1^2}{\|\vec{b}\|_2^2} \sum_{i,\ell} p_i^{(\vec{b})} p_\ell^{(\vec{b})} \cdot \text{sgn}(b_i b_\ell) \langle 0|X_i G^\dagger O G X_\ell|0\rangle. \quad (96)$$

$$= \frac{\|\vec{b}\|_1^2}{\|\vec{b}\|_2^2} g^2 \sum_{i,j,k,\ell} p_i^{(\vec{b})} p_j^{(G)} p_k^{(G)} p_\ell^{(\vec{b})} \cdot \text{sgn}(b_i g_j g_k b_\ell) \langle 0|X_i V_j^\dagger O V_k X_\ell|0\rangle. \quad (97)$$

We consider a very similar protocol to before: (1) Sample indices i', k', m', ℓ' from the probability distribution $\{p_i^{(\vec{b})} p_j^{(G)} p_k^{(G)} p_\ell^{(\vec{b})}\}_{ikm\ell}$. (2) Run the circuit in Fig. 2 to obtain one measurement sample of $\langle 0|X_i V_j^\dagger O V_k X_\ell|0\rangle$. (3) Classically multiply the result by $\|\vec{b}\|_1^2 g^2 \text{sgn}(b_i g_j g_k b_\ell) / \|\vec{b}\|_2^2$ and store the result. (4) Repeat process \mathcal{C}_{sample}^O times and average over results. Due to Hoeffding's inequality, it is sufficient to take

$$\mathcal{C}_{sample}^O = 2 \log \left(\frac{2}{\delta} \right) \frac{\|O\|^2 \|\vec{b}\|_1^4}{\varepsilon^2 \|\vec{b}\|_2^4} \quad (98)$$

shots to attain an answer within additive error ε and probability at least $(1 - \delta)$.

Now we consider the classical resources required to determine $\|\vec{b}\|_1, \|\vec{b}\|_2, \{p_i\}, \{\text{sgn}(b_i)\}$ given \mathcal{B} . As one can obtain the set of tuples $\vec{\mathcal{B}} = \{(b_i, i) \mid b_i \neq 0\}$ in $\mathcal{O}(s)$ steps from \mathcal{B} , it then follows that all four sets of quantities can be obtained in $\mathcal{O}(s)$ additional steps by first obtaining $\vec{\mathcal{B}}$, then combining quantities in \mathcal{B} and $\vec{\mathcal{B}}$. \square

Remark (Arbitrary normalization). *We can additionally consider arbitrarily normalized states with normalization constant m as $\frac{1}{m}|\vec{b}\rangle$ by changing the sample complexity by factor $\|\vec{b}\|_1 \rightarrow \frac{1}{m}\|\vec{b}\|_1$.*

A.5 Classical capability

In this section we show that, given a bounded degree polynomial series $h(A) = \sum_{k \in F_d} \alpha_k A^k$ in matrix A where A has known Pauli decomposition with bounded Pauli weight, then one can approximate quantities of the form $\langle t|h(A)|s\rangle$ efficiently classically by means of a randomized algorithm. This is a more detailed re-statement of Proposition 3 in the main text.

Proposition 4 (Sampling from polynomial series – detailed version). *Suppose that we have a polynomial series of degree d*

$$h(A) = \sum_{k \in F_d} \alpha_k A^k, \quad (99)$$

in some $N \times N$ Hermitian matrix A , where $F_d \subseteq [d]$, and denote the ℓ_1 -norm of the coefficients as $\alpha := \sum_{k \in F_d} |\alpha_k|$. Suppose further that A has known Pauli decomposition $A = \sum_\ell a_\ell P_\ell$ with Pauli weight $\lambda = \sum_\ell |a_\ell|$. Then, given pure states $|t\rangle$ and $|s\rangle$ which are implementable by initializing in the $|0\rangle$ state and performing $\mathcal{O}(m)$ Clifford gates, one can classically approximate $\langle t|h(A)|s\rangle$ up to additive error ε with probability at least $1 - \delta$, using

$$\mathcal{C}_{sample} = \mathcal{O} \left(\log \left(\frac{2}{\delta} \right) \frac{(\alpha \lambda^d)^2}{\varepsilon^2} \right), \quad (100)$$

calls to independent classical subroutines, each requiring $\mathcal{O}(\log^2(N))$ bits and at most $\mathcal{O}(d \log^2(N) + m \log(N))$ time.

Proof of Proposition 4. We first note that we can write

$$A = \lambda \sum_{\ell} p_{\ell} \cdot \text{sgn}(a_{\ell}) P_{\ell}, \quad (101)$$

where $\lambda = \sum_{\ell} |a_{\ell}|$ is the Pauli weight and we denote $p_{\ell} = \frac{|a_{\ell}|}{\lambda}$ and $\text{sgn}(a_{\ell}) = \frac{a_{\ell}}{|a_{\ell}|}$. We can then write

$$h(A) = \sum_{k \in F_d} \alpha_k \lambda^k \sum_{\ell_1, \dots, \ell_k} p_{\ell_1} \cdots p_{\ell_k} \text{sgn}(a_{\ell_1}) \cdots \text{sgn}(a_{\ell_k}) P_{\ell_1} \cdots P_{\ell_k} \quad (102)$$

$$= R_{h(A)} \sum_{k \in F_d} \sum_{\ell_1, \dots, \ell_k} q_k p_{\ell_1} \cdots p_{\ell_k} \phi(\alpha_k) \text{sgn}(a_{\ell_1}) \cdots \text{sgn}(a_{\ell_k}) P_{\ell_1} \cdots P_{\ell_k}, \quad (103)$$

where we denote $R_{h(A)} = \sum_{k \in F_d} |\alpha_k \lambda^k| \leq \alpha \lambda^d$, $q_k = \frac{|\alpha_k| \lambda^k}{R_{h(A)}}$, $\phi(\alpha_k) = \frac{\alpha_k}{|\alpha_k|}$. We note that $p_{\ell_1}, \dots, p_{\ell_k}$ and q_k are probabilities. This then allows us to statistically recover $h(A)$ with weight $R_{h(A)}$. For simplicity we subsume all indices and write

$$h(A) = G \sum_{i \in S} \tilde{p}_i \tilde{\phi}_i \tilde{P}_i, \quad (104)$$

where $\tilde{p}_i = q_k p_{\ell_1} \cdots p_{\ell_k}$ subsumes all probabilities, $\tilde{\phi}_i = \phi(\alpha_k) \text{sgn}(a_{\ell_1}) \cdots \text{sgn}(a_{\ell_k})$ subsumes all phases, $\tilde{P}_i = P_{\ell_1} \cdots P_{\ell_k}$ is a product of k Paulis.

Preparation of $\langle t|h(A)|s \rangle$. Denote the collection of Cliffords to prepare $|t\rangle$ and $|s\rangle$ as U_t and U_s respectively. Using Eq. (104) we can simply write

$$\langle t|h(A)|s \rangle = R_{h(A)} \sum_{i \in S} \tilde{p}_i \tilde{\phi}_i \langle 0|U_t^{\dagger} \tilde{P}_i U_s|0 \rangle. \quad (105)$$

Inspecting this, we can consider the following protocol: (1) sample from the above probability distribution, obtaining index i with probability \tilde{p}_i ; (2) sample one measurement result corresponding to $\langle 0|U_t^{\dagger} \tilde{P}_i U_s|0 \rangle$ by running the circuit in Figure 2(a); (3) multiply the result by $R_{h(A)} \tilde{\phi}_i$; (4) repeat M times and take mean over results.

We note that in step (2) one requires sampling one measurement result from a circuit that contains at most $2d$ controlled n -qubit Pauli operations plus $\mathcal{O}(m)$ other Clifford operations. The former part can simply be decomposed into at most $2dn$ controlled single qubit Pauli operations. In order to simulate the circuit overall one requires $\mathcal{O}(n^2)$ bits and $\mathcal{O}(dn^2 + mn)$ time [70, 71]. Due to Hoeffding's inequality, in order to recover $\langle t|h(A)|s \rangle$ to additive error ε with probability at least $(1 - \delta)$, it is sufficient to use M shots for any

$$M \geq 2 \log \left(\frac{2}{\delta} \right) \frac{R_{h(A)}^2}{\varepsilon^2}. \quad (106)$$

Using the upper bound $R_{h(A)} \leq \alpha \lambda^d$ we observe that it is sufficient to perform

$$\mathcal{C}_{\text{sample}} = 2 \log \left(\frac{2}{\delta} \right) \frac{(\alpha \lambda^d)^2}{\varepsilon^2} \quad (107)$$

shots.

Note that quantities of the form $\text{Tr} [h(A) \rho h(A)^{\dagger} O]$ (where ρ, O are implementable by Cliffords) can be obtained by taking the modulus squared of quantities of the form $\langle t|h(A)|s \rangle$. Alternatively, they can also be prepared by simulating the circuit in Figure 2(b).

□

The above proposition can be trivially extended to consider polynomials of multiple matrices. This implies that subroutines such as matrix multiplication can be efficiently sampled from, given the matrices have non-extensive Pauli weights.

B Application-specific results

B.1 Linear systems

In this section we detail our results for linear systems. We first summarize a result from Ref. [40]. In this work, the authors find an approximation of A^{-1} as a linear combination of unitaries $\sum_i \alpha_i \exp(-iAz_j)$. More precisely, they find a Fourier representation of the inverse function as

$$\frac{1}{x} = \frac{i}{\sqrt{2\pi}} \int_0^\infty dy \int_{-\infty}^\infty dz z e^{-z^2/2} e^{-ixyz}. \quad (108)$$

Further, They show that when truncating the integration range as

$$g(x) := \frac{i}{\sqrt{2\pi}} \int_0^{y_J} dy \int_{-z_K}^{z_K} dz z e^{-z^2/2} e^{-ixyz}, \quad (109)$$

we have

$$\left| g(x) - \frac{1}{x} \right| \leq \frac{1}{|x|} e^{-(xy_J)^2/2} + \frac{2}{|x|} e^{-z_K^2/2} \leq \varepsilon, \quad (110)$$

on the domain $D_b := [-1, -1/b] \cup [1/b, 1]$ for some $y_J(\varepsilon, b) = \Theta(b\sqrt{\log(b/\varepsilon)})$ and $z_K(\varepsilon, b) = \Theta(\sqrt{\log(b/\varepsilon)})$ (Ref. [40], Lemma 12). An important point is that this choice is totally independent of the upper limit of the domain, and is wholly dependent on b , that is, the same statement holds over the domain $[-a, -1/b] \cup [1/b, a]$ with arbitrary $a \geq 1/b$. This is due to the fact that the upper bound on the approximation error in Eq. (110) is a decreasing function in $|x|$. The integral in Eq. (109) can be discretized as

$$h(x) := \frac{i}{\sqrt{2\pi}} \sum_{j=0}^{J-1} \Delta_y \sum_{k=-K}^K \Delta_z z_k e^{-z_k^2/2} e^{-ixy_j z_k}, \quad (111)$$

where the integration range has been discretized into J and $2K+1$ steps of size Δ_y and Δ_z respectively. Moreover, taking step sizes $\Delta_y = \Theta(\varepsilon/\sqrt{\log(b/\varepsilon)})$ and $\Delta_z = \Theta((b\sqrt{\log(b/\varepsilon)})^{-1})$ guarantees that $h(x)$ is ε -close to $1/x$ on the domain D_b . Note, however, as we will only sample from this distribution, for our purposes the resolution of this discretization can be taken to be arbitrarily small. By inspecting Eq. (111), one can observe that this corresponds to a Fourier series with maximum time parameter

$$t_{\max} = \Theta(y_J(\varepsilon, b)z_K(\varepsilon, b)) = \Theta(b \log(b/\varepsilon)), \quad (112)$$

and coefficients with weight

$$\frac{1}{\sqrt{2\pi}} \sum_{j=0}^{J-1} \Delta_y \sum_{k=-K}^K \Delta_z |z_k| e^{-z_k^2/2} \in \Theta(y_J(\varepsilon, b)) = \Theta(b\sqrt{\log(b/\varepsilon)}). \quad (113)$$

By mapping the domain D_b to the spectrum of some matrix A , this allows us to establish the following lemma.

Lemma 6 (Fourier series approximation of inverse operator, adapted from Ref. [40]). *Given some matrix A with finite $\|A^{-1}\|$ we have*

$$\left\| A^{-1} - \sum_{i \in S_{\varepsilon, A}} \alpha_i(\varepsilon, A) \exp(-iAz_j(\varepsilon, A)) \right\| \leq \varepsilon, \quad (114)$$

where $S_{\varepsilon, A}$ is some index set, with maximum time parameter $t_{\max} := \max_{i \in S_{\varepsilon, A}}(z_j)$ satisfying

$$t_{\max}(\varepsilon, A) = \Theta\left(\|A^{-1}\| \log\left(\frac{\|A^{-1}\|}{\varepsilon}\right)\right), \quad (115)$$

and Fourier coefficients $\alpha_i(\varepsilon, A)$ with ℓ_1 -norm satisfying

$$\alpha(\varepsilon, A) := \sum_i |\alpha_i(\varepsilon, A)| = \Theta\left(\|A^{-1}\| \sqrt{\log\left(\frac{\|A^{-1}\|}{\varepsilon}\right)}\right). \quad (116)$$

Our result for linear systems (Corollary 1 in the main text) then follows directly from Theorem 1 and Proposition 2 as follows.

Corollary 1 (Linear systems – detailed version). *Consider a Hermitian matrix A with known Pauli decomposition $A = \sum_{\ell} a_{\ell} P_{\ell}$; $\lambda := \sum_{\ell} |a_{\ell}|$. Denote q as a freely chosen normalization parameter. Finally, suppose we have ability to prepare state $|\vec{b}\rangle$ in $\mathcal{O}(d_{\vec{b}})$ depth.*

- *Given ability to implement $U_{\psi}|0\rangle = |\psi\rangle$ in gate depth d_{ψ} , there exists a randomized quantum algorithm that returns $\frac{1}{q}\langle\psi|A^{-1}|\vec{b}\rangle$ up to additive error ε with probability at least $1-\delta$, utilizing $\mathcal{O}\left(\log\left(\frac{2}{\delta}\right)\frac{\|A^{-1}\|^2}{\varepsilon^2 q^2}\log\left(\frac{\|A^{-1}\|^2}{\varepsilon q^2}\right)\right)$ circuit runs each with gate depth $\mathcal{O}\left(\|A^{-1}\|^2\lambda^2\log^2\left(\frac{\|A^{-1}\|^2}{\varepsilon q^2}\right) + d_{\psi} + d_{\vec{b}}\right)$.*
- *Given ability to measure observable O ; $\|O\| \leq 1$, there exists a randomized quantum algorithm that returns $\frac{1}{q^2}\langle\vec{b}|A^{-1}OA^{-1}|\vec{b}\rangle$ up to additive error ε with probability at least $1-\delta$, utilizing $\mathcal{O}\left(\log\left(\frac{2}{\delta}\right)\frac{\|A^{-1}\|^4}{\varepsilon^2 q^4}\log^2\left(\frac{\|A^{-1}\|^2}{\varepsilon q^2}\right)\right)$ circuit runs each of gate depth $\mathcal{O}\left(\|A^{-1}\|^2\lambda^2\log^2\left(\frac{\|A^{-1}\|^2}{\varepsilon q^2}\right) + d_{\vec{b}}\right)$.*
- *In the case $q = \|A^{-1}|\vec{b}\rangle\|$ and whose value is not given, there exists an auxiliary algorithm that approximates the value of q for the above algorithms with the sample complexity $\mathcal{O}\left(\log\left(\frac{2}{\delta}\right)\frac{\|A^{-1}\|^4}{\varepsilon^2 q^4}\log^2\left(\frac{\|A^{-1}\|}{\varepsilon q}\right)\right)$ and gate depth $\mathcal{O}\left(\|A^{-1}\|^2\lambda^2\log^2\left(\frac{\|A^{-1}\|}{\varepsilon q}\right) + d_{\vec{b}}\right)$.*

Proof of Corollary 1 (Linear systems). In order to quantify the complexity of preparing $\frac{1}{q}\langle\psi|Uf(A)V|\psi\rangle$, we now require $\alpha(\varepsilon q, A)$ and $t_{max}(\varepsilon q, A)$, as specified by Eq. (58) of Theorem 1. Again inspecting Eqs. (115) and (116) of Lemma 6, these quantities scale as

$$t_{max}(\varepsilon q, A) = \Theta\left(\|A^{-1}\|\log\left(\frac{\|A^{-1}\|}{\varepsilon q}\right)\right), \quad (117)$$

and

$$\alpha(\varepsilon q, A) = \Theta\left(\|A^{-1}\|\sqrt{\log\left(\frac{\|A^{-1}\|}{\varepsilon q}\right)}\right). \quad (118)$$

Now, substituting the above into Eq. (58) of Theorem 1, we obtain the desired result.

Similarly, in order to quantify the complexity of preparing $\frac{1}{q^2}\text{Tr}[f(A)\rho f(A)^{\dagger}O]$, we need to evaluate the quantities $\alpha\left(\frac{\varepsilon q^2}{\|f(A)\|}, A\right)$ and $t_{max}\left(\frac{\varepsilon q^2}{\|f(A)\|}, A\right)$, as specified by Eq. (59) of Theorem 1. Inspecting Eqs. (115) and (116) of Lemma 6, we see that these quantities satisfy

$$t_{max}\left(\frac{\varepsilon q^2}{\|f(A)\|}, A\right) = \Theta\left(\|A^{-1}\|\log\left(\frac{\|A^{-1}\|^2}{\varepsilon q^2}\right)\right), \quad (119)$$

and

$$\alpha\left(\frac{\varepsilon q^2}{\|f(A)\|}, A\right) = \Theta\left(\|A^{-1}\|\sqrt{\log\left(\frac{\|A^{-1}\|^2}{\varepsilon q^2}\right)}\right). \quad (120)$$

Substituting these two expressions into Eq. (59) of Theorem 1, we obtain the desired result.

Finally, we can use Proposition 2 to characterize the complexity of approximating $\|A^{-1}|\vec{b}\rangle\|$. Eq. (88) of Proposition 2 is written in terms of $\alpha(\varepsilon q, A)$ and $t_{max}(\varepsilon q, A)$ whose scalings we have already quoted above. Substituting this into Eq. (88), we obtain the result in Corollary 1. \square

Remark (Non-Hermitian matrices). *Any non-Hermitian matrix B can be embedded in a larger Hermitian matrix A with the aid of a single qubit as*

$$A = \begin{bmatrix} 0 & B \\ B^{\dagger} & 0 \end{bmatrix}. \quad (121)$$

Then, one can verify that $A^{-1} \begin{pmatrix} \vec{b} \\ 0 \end{pmatrix} = B^{-1}\vec{b}$, $\|A\| = \|B\|$ and $\|A^{-1}\| = \|B^{-1}\|$. In Pauli representation, given respective Hermitian and anti-Hermitian components $H_1(B)$ and $iH_2(B)$ of B such that $B = H_1(B) + iH_2(B)$, this embedding can be explicitly written as

$$A = X \otimes H_1(B) - Y \otimes H_2(B) = \frac{1}{2}X \otimes (B + B^\dagger) - \frac{1}{2}Y \otimes (B - B^\dagger). \quad (122)$$

From this it is clear that the Pauli weight of A is bounded as $\lambda_A \leq 2\lambda_B$.

Using the above remark we see that the asymptotic complexities for the linear systems problem as stated in A can be simply be translated to B via the substitution $\lambda_A \rightarrow \lambda_B$ and $\|A^{-1}\| \rightarrow \|B^{-1}\|$.

B.2 Ground state sampling

In this section we study the task of sampling properties of the ground state of a given Hamiltonian. In order to establish our result the relevant function we consider is the Gaussian function $e^{-\frac{1}{2}\tau^2 x^2}$. We refer to the following lemmas which show how this can obtain approximations of ground state observables.

Lemma 7 (Ground state projection - adapted from Keen et al. [53]). *Suppose we have Hamiltonian $H = \sum_l E_l |E_l\rangle\langle E_l|$ with all eigenvalues $E_l \geq 0$. Assume the spectral gap is lower bounded by $\Delta \leq E_1 - E_0$. Additionally, we suppose that we have an initial trial state $|\psi_0\rangle$ with overlap with the ground state $\gamma := |\langle \psi_0 | E_0 \rangle|$. Then, the state $|\psi\rangle = |\tilde{\psi}\rangle / \|\tilde{\psi}\|$, where $|\tilde{\psi}\rangle = e^{-\frac{1}{2}\tau^2 H^2} |\psi_0\rangle$, satisfies*

$$1 - |\langle \psi | E_0 \rangle| \leq \frac{1}{2}\varepsilon^2 \quad (123)$$

for any $\tau \geq \tau_\varepsilon$ where τ_ε satisfies

$$\tau_\varepsilon = \frac{1}{\Delta} \sqrt{2 \log \frac{1}{\varepsilon \gamma}}. \quad (124)$$

With the following lemma we can see how this affects the closeness of expectation values.

Lemma 8 (Tightness of expectation values, pt. 3). *For some operator O and pure states $|\psi\rangle, |E_0\rangle$, we have*

$$\text{Tr}[|\psi\rangle\langle\psi|O] - \text{Tr}[|E_0\rangle\langle E_0|O] \leq 2\sqrt{2}\|O\|\sqrt{1 - |\langle\psi|E_0\rangle|}. \quad (125)$$

Proof. We have

$$\text{Tr}[|\psi\rangle\langle\psi|O] - \text{Tr}[|E_0\rangle\langle E_0|O] \leq \|O\|_\infty \|\psi\rangle\langle\psi| - |E_0\rangle\langle E_0|\|_1 \quad (126)$$

$$\leq 2\|O\|_\infty \sqrt{1 - |\langle\psi|E_0\rangle|^2} \quad (127)$$

$$= 2\|O\|_\infty \sqrt{(1 - |\langle\psi|E_0\rangle|)(1 + |\langle\psi|E_0\rangle|)} \quad (128)$$

$$\leq 2\sqrt{2}\|O\|_\infty \sqrt{1 - |\langle\psi|E_0\rangle|} \quad (129)$$

Where in the first line we use the tracial matrix Hölder's inequality, in the second line we use the relation between the trace distance and the fidelity for pure states, in the third line we complete the square, and in the final line we use the fact that $|\langle\psi|E_0\rangle| \leq 1$. \square

Lemma 9 (Ground state observable projection). *Under the conditions specified in Lemma 7 with $\tau \geq \tau_\varepsilon$, the normalized state $|\psi\rangle = e^{-\frac{1}{2}\tau^2 H^2} |\psi_0\rangle / \|e^{-\frac{1}{2}\tau^2 H^2} |\psi_0\rangle\|$ satisfies*

$$\text{Tr}[|\psi\rangle\langle\psi|O] - \text{Tr}[|E_0\rangle\langle E_0|O] \leq 2\|O\|\varepsilon, \quad (130)$$

for any measurement operator O .

Proof. This follows as a direct implication of Lemmas 7 and 8. \square

We now introduce the Hubbard-Stratonovich transformation [72, 73]. This gives us a way to decompose the operator $e^{-\frac{1}{2}\tau^2 H^2}$ into a linear combination of implementable unitaries. It states that, for Hermitian H , we have

$$e^{-\frac{1}{2}\tau^2 H^2} = \frac{1}{\sqrt{2\pi}} \int_{-\infty}^{\infty} dz e^{-\frac{1}{2}z^2} e^{-iz\tau H}. \quad (131)$$

The following lemma, adapted from Ref. [53], shows that the integral in the Hubbard-Stratonovich transformation can be discretized and truncated to give an approximate (discrete) Fourier series for the operator $e^{-\frac{1}{2}\tau^2 H^2}$.

Lemma 10 (Approximate Hubbard-Stratonovich transformation – adapted from Appendix A2 of Ref. [53]). *Truncating and discretizing the integral, and assuming $\|H\| \leq 1$, we have a Fourier series approximation*

$$\left\| \frac{1}{\sqrt{2\pi}} \sum_{k=-N_z}^{N_z} \Delta_z e^{-\frac{1}{2}z_k^2} e^{-iz_k\tau H} - e^{-\frac{1}{2}\tau^2 H^2} \right\| \leq \varepsilon, \quad (132)$$

for choice of $\Delta_z = \mathcal{O}\left(\frac{1}{\tau + \Delta_z N_z}\right)$ and $\Delta_z N_z = \sqrt{2 \log\left(\frac{2}{\varepsilon}\right)}$, where we have denoted $z_k = k\Delta_z$. This gives maximum time evolution parameter

$$t_{\max}(\varepsilon) := \max_k (z_k \tau) = \Delta_z N_z \tau = \tau \sqrt{2 \log\left(\frac{2}{\varepsilon}\right)}. \quad (133)$$

Further, the coefficients $\{\alpha_k(\varepsilon)\}_k = \left\{\frac{1}{\sqrt{2\pi}} \Delta_z e^{-\frac{1}{2}z_k^2}\right\}_k$ have weight

$$\alpha(\varepsilon) := \sum_k |\alpha_k(\varepsilon)| \leq 1 + \frac{1}{\sqrt{2\pi}} \Delta_z. \quad (134)$$

Proof. The bound on $\alpha(\varepsilon)$ can be seen by noting that

$$\sum_k |\alpha_k(\varepsilon)| = \frac{1}{\sqrt{2\pi}} \sum_{k=-N_z}^{N_z} \Delta_z e^{-\frac{1}{2}z_k^2} \leq \frac{1}{\sqrt{2\pi}} \sum_{k=-\infty}^{\infty} \Delta_z e^{-\frac{1}{2}z_k^2}, \quad (135)$$

is simply a discretized Gaussian integral, where the discretization error can be bounded by the step size Δ_z multiplied by the maximum value of the function $\frac{1}{\sqrt{2\pi}}$. We refer the reader to Appendix A2 of Ref. [53] for the rest of the proof of the claim on $t_{\max}(\varepsilon)$. \square

From hereon we will make the soft imposition that we choose $\Delta_z \leq 1$ for all problems. This gives an error-independent bound for Lemma 10 of $\alpha(\varepsilon) \leq 1 + \frac{1}{\sqrt{2\pi}} < 1.4$.

Remark (Hamiltonians with non-positive spectra). *For Hamiltonians with non-positive spectra and where we have upper bound on magnitude of ground state energy $\lambda_0 \geq |E_0|$, we can shift the spectrum $H' = H + E_0 \mathbb{1}$ without changing the weight of the coefficients or the Hamiltonian simulation problem. This is because in the Hubbard-Stratonovich transformation the Hamiltonian appears in the term $e^{-iz_k\tau H'} = e^{-iz_k\tau H} e^{-iz_k\tau E_0 \mathbb{1}} = e^{-iz_k\tau E_0} e^{-iz_k\tau H}$ and the phase factor $e^{-iz_k\tau E_0}$ can be absorbed into the coefficients α_k without changing the weight α . Further, the eigenstates of H' are clearly eigenstates of H , with shifted eigenenergies.*

We can now present our result for ground state property estimation (Corollary 2 in the main text).

Corollary 2 (Ground state property estimation). *Consider a Hamiltonian $H = \sum_l E_l |E_l\rangle\langle E_l|$ with all eigenvalues $E_l \geq 0$, and known Pauli decomposition $H = \sum_\ell a_\ell P_\ell$; $\lambda := \sum_\ell |a_\ell|$. Assume the spectral gap is lower bounded by $\Delta \leq E_1 - E_0$. Additionally, we suppose that we have an initial trial state $|\psi_0\rangle$ with overlap with the ground state $\gamma := |\langle \psi_0 | E_0 \rangle|$. Finally, we assume that $E_0 \leq \Delta / \sqrt{2 \log \frac{\|O\|}{\varepsilon \gamma}}$. Then, given ability to measure observable O , there exists a random algorithm that returns $\langle E_0 | O | E_0 \rangle$ up to additive error ε with probability at least $(1 - \delta)^2$, which consists of*

- A core routine that requires $\mathcal{O}\left(\log\left(\frac{2}{\delta}\right)\frac{\|O\|^2}{\varepsilon^2\gamma^4}\right)$ circuit runs of the form in Figure 2(a) each of non-Clifford depth at most $\mathcal{O}\left(\frac{\lambda^2}{\Delta^2}\log^2\left(\frac{2\|O\|}{\varepsilon\gamma^2}\right)\right)$.
- A subroutine that approximates the normalization constant, using $\mathcal{O}\left(\log\left(\frac{2}{\delta}\right)\frac{1}{\varepsilon^2\gamma^4}\right)$ circuit runs each of non-Clifford depth at most $\mathcal{O}\left(\frac{\lambda^2}{\Delta^2}\log\frac{\|O\|}{\varepsilon\gamma}\log\frac{4}{\varepsilon\gamma}\right)$.

Proof of Corollary 2. We first show how to obtain the complexities to recover the operator $e^{-\frac{1}{2}\tau^2 H^2}$. We then use Corollary 9 to connect this to sampling from the ground state. Finally, we use Proposition 2 to consider the overhead of approximating the state normalization constant $q = \|e^{-\frac{1}{2}\tau^2 H^2}|\psi_0\rangle\|$.

In order to quantify the complexity of preparing $\frac{1}{q^2}\langle\psi_0|e^{-\frac{1}{2}\tau^2 H^2}Oe^{-\frac{1}{2}\tau^2 H^2}|\psi_0\rangle$, we need to evaluate the quantities $\alpha\left(\frac{\varepsilon q^2}{\|O\|\|e^{-\frac{1}{2}\tau^2 H^2}\|}, H\right)$ and $t_{max}\left(\frac{\varepsilon q^2}{\|O\|\|e^{-\frac{1}{2}\tau^2 H^2}\|}, H\right)$, as specified by Eq. (59) of Theorem 1. Using Eq. (133) of Lemma (10) we have

$$t_{max}\left(\frac{\varepsilon q^2}{\|O\|\|e^{-\frac{1}{2}\tau^2 H^2}\|}, H\right) = \mathcal{O}\left(\tau\sqrt{\log\left(\frac{2\|O\|\|e^{-\frac{1}{2}\tau^2 H^2}\|}{\varepsilon q^2}\right)}\right) \quad (136)$$

$$= \mathcal{O}\left(\tau\sqrt{\log\left(\frac{2\|O\|}{\varepsilon\gamma^2}\right)}\right), \quad (137)$$

where in the second line we have used the fact that $q \geq \gamma e^{-\frac{1}{2}\tau^2 E_0^2}$ and that $e^{-\frac{1}{2}\tau^2 E_0^2} \geq 1 - \frac{1}{2}\tau^2 E_0^2 \geq \frac{1}{2}$ for $E_0\tau \leq 1$. We recall that by choosing that the step size in the Fourier series in Lemma 10 be less than 1, we fix $\alpha(\varepsilon) = \mathcal{O}(1)$ for any ε . We would like $\frac{1}{q^2}\langle\psi_0|e^{-\frac{1}{2}\tau^2 H^2}Oe^{-\frac{1}{2}\tau^2 H^2}|\psi_0\rangle$ to satisfy $|\frac{1}{q^2}\langle\psi_0|e^{-\frac{1}{2}\tau^2 H^2}Oe^{-\frac{1}{2}\tau^2 H^2}|\psi_0\rangle - \langle E_0|O|E_0\rangle| = \mathcal{O}(\varepsilon)$.

Corollary 9 specifies that, in order to satisfy this, it is sufficient to have $\tau = \tau_{\varepsilon/\|O\|} = \frac{1}{\Delta}\sqrt{2\log\frac{\|O\|}{\varepsilon\gamma}}$. Thus, overall we have

$$t_{max}\left(\frac{\varepsilon q^2}{\|O\|\|e^{-\frac{1}{2}\tau^2 H^2}\|}, H\right) = \mathcal{O}\left(\frac{1}{\Delta}\log\left(\frac{2\|O\|}{\varepsilon\gamma^2}\right)\right), \quad (138)$$

where we have used the fact that $\gamma \leq 1$. Substituting this into Eq. (59) of Theorem 1 we obtain the stated result for non-Clifford gate complexity. The sample complexity can be evaluated simply as

$$\mathcal{C}_{sample}^O = \mathcal{O}\left(\log\left(\frac{2}{\delta}\right)\frac{\|O\|^2}{\varepsilon^2 q^4}\right) = \mathcal{O}\left(\log\left(\frac{2}{\delta}\right)\frac{\|O\|^2}{\varepsilon^2 \gamma^4}\right), \quad (139)$$

by again noting that $\frac{1}{q} \leq \frac{1}{\gamma}e^{\frac{1}{2}\tau^2 E_0^2} \leq \frac{2}{\gamma}$ for $E_0\tau \leq 1$.

Finally, we consider the complexity of approximating the state norm $q = \|e^{-\frac{1}{2}\tau^2 H^2}|\psi_0\rangle\|$ by following Proposition 2. Eq. (88) of Proposition 2 expresses complexities in terms of $\alpha(\varepsilon q, H)$ and $t_{max}(\varepsilon q, H)$. From the above discussion we have that $\alpha(\varepsilon q, H) = \mathcal{O}(1)$. Using Eq. (133) and Corollary 2 we can assign

$$t_{max}(\varepsilon q, H) = \tau\sqrt{2\log\left(\frac{2}{\varepsilon q}\right)} \quad (140)$$

$$= \frac{1}{\Delta}\sqrt{2\log\frac{\|O\|}{\varepsilon\gamma}}\sqrt{2\log\left(\frac{2}{\varepsilon q}\right)} \quad (141)$$

$$= \mathcal{O}\left(\frac{1}{\Delta}\sqrt{\log\frac{\|O\|}{\varepsilon\gamma}\log\frac{4}{\varepsilon\gamma}}\right), \quad (142)$$

where in the final line we have used the fact that $\frac{1}{q} \leq \frac{2}{\gamma}$. This leads to the stated complexities for the normalization subroutine of

$$\mathcal{C}_{gate}^{norm} = \mathcal{O}\left(\log\left(\frac{2}{\delta}\right)\frac{1}{\gamma^4\varepsilon^2}\right), \quad \mathcal{C}_{sample}^{norm} = \mathcal{O}\left(\frac{\lambda^2}{\Delta^2}\log\frac{\|O\|}{\varepsilon\gamma}\log\frac{4}{\varepsilon\gamma}\right). \quad (143)$$

□

B.2.1 Power method

In this section we will explore the feasibility of using a randomized scheme based on the power method to find dominant eigenvalues. Given an observable of interest, the aim will be to approximate $\langle E_0|O|E_0\rangle$ with $\langle \psi_0|H^k O H^k|\psi_0\rangle / \|H^k|\psi_0\rangle\|^2$, where $|E_0\rangle$ is the ground state of Hamiltonian H , $|\psi_0\rangle$ is a given trial state with overlap $\gamma := |\langle E_0|\psi_0\rangle|$, and $\|H^k|\psi_0\rangle\|^2$. With this, we have the following Proposition:

Lemma 11 (Power method). *For Hamiltonians H with negative spectra and first excited energy $E_1 < 0$ we have*

$$\left| \frac{\langle \psi_0|H^k O H^k|\psi_0\rangle}{\|H^k|\psi_0\rangle\|^2} - \langle E_0|O|E_0\rangle \right| \leq \varepsilon, \quad (144)$$

for a given error parameter $\varepsilon \leq \frac{4\|O\|\sqrt{1-\gamma^2}}{\gamma}$ if k satisfies

$$k = \Omega\left(\frac{\log\left(\frac{\gamma\varepsilon}{\|O\|\sqrt{1-\gamma^2}}\right)}{\log\left(1 - \frac{\Delta}{|E_0|}\right)}\right) = \Omega\left(\frac{|E_0|}{\Delta} \log\left(\frac{\|O\|\sqrt{1-\gamma^2}}{\gamma\varepsilon}\right)\right). \quad (145)$$

Proof. Consider the decomposition of the trial state $|\psi_0\rangle$ in the energy eigenbasis of H as

$$|\psi_0\rangle = c_0|E_0\rangle + \sum_{j>0} c_j|E_j\rangle, \quad (146)$$

where $\{c_k\}_k$ are coefficients. Using this, we can express $H^k|\psi_0\rangle$ as

$$H^k|\psi_0\rangle = c_0 E_0^k |E_0\rangle + \sum_{j>0} c_j E_j^k |E_j\rangle, \quad (147)$$

and thus the overlap of the normalized power method approximation with the true ground state

$$1 - \left| \frac{\langle E_0|H^k|\psi_0\rangle}{\|H^k|\psi_0\rangle\|} \right| = 1 - \frac{|c_0 E_0^k|}{\sqrt{c_0^2 E_0^{2k} + \sum_{j>0} c_j^2 E_j^{2k}}} \quad (148)$$

$$= 1 - \left[1 + \sum_{j>0} \frac{c_j^2}{c_0^2} \left(\frac{E_j}{E_0}\right)^{2k} \right]^{-1/2} \quad (149)$$

$$\leq 1 - \left[1 + \frac{1-\gamma^2}{\gamma^2} \left(\frac{E_1}{E_0}\right)^{2k} \right]^{-1/2} \quad (150)$$

$$\leq 1 - \left[1 - \frac{1-\gamma^2}{2} \left(\frac{E_1}{E_0}\right)^{2k} \right] \quad (151)$$

$$= \frac{1-\gamma^2}{2\gamma^2} \left(\frac{E_1}{E_0}\right)^{2k}, \quad (152)$$

where in the first inequality we have used the fact that $\gamma = E_0^2$ and $\sum_{j>0} c_j^2 = 1 - \gamma^2$, and the second is due to the fact that $(1+x)^{1/2} \geq 1+x/2$ for $x \geq -1$. Thus, in order to constrain the state overlap $1 - \left| \frac{\langle E_0|H^k|\psi_0\rangle}{\|H^k|\psi_0\rangle\|} \right| = \varepsilon'$ each of the following conditions are sufficient

$$1 - \frac{|c_0 E_0^k|}{\sqrt{c_0^2 E_0^{2k} + \sum_{j>0} c_j^2 E_j^{2k}}} \leq \varepsilon', \quad (153)$$

$$\Rightarrow \left(1 - \frac{\Delta}{|E_0|}\right)^{2k} \leq \frac{2\gamma^2 \varepsilon'}{1-\gamma^2}, \quad (154)$$

$$\Rightarrow k \geq \frac{1}{2} \frac{\log\left(\frac{2\gamma^2 \varepsilon'}{1-\gamma^2}\right)}{\log\left(1 - \frac{\Delta}{|E_0|}\right)}. \quad (155)$$

We recall that Lemma 8 relates the overlap of pure state expectation values to the overlap of states, which specifies that the state overlap ε' must be at most $\frac{\varepsilon^2}{8\|O\|^2}$ in order to constrain the expectation value within additive error ε . Using this, we obtain the first equality of Eq. (145), where starting our assumption on ε ensures the bound on k is positive and thus meaningful. The second equality can be established by noting that

$$1 - \frac{|E_0|}{\Delta} \leq \frac{1}{\log\left(1 - \frac{\Delta}{|E_0|}\right)} \leq -\frac{|E_0|}{\Delta}, \quad (156)$$

for $E_1 < 0$. □

Now we suppose that we are given a recipe to prepare the trial state by a series of Clifford gates or we have access to the amplitudes (for which Proposition 3 can be used). The above lemma along with Proposition 4 implies that, in this setting, there is a classical algorithm that solves the ground state property estimation problem with exponential number of samples in Δ^{-1} and polynomial in all other parameters.

B.3 Evaluating Green's functions

In this section we present the detailed statement of our result for evaluating Green's functions as defined in Eqs. (26) and (27) (Proposition 5 in the main text).

Proposition 5 (Green's function estimation – detailed version). *Consider a Hamiltonian $H = \sum_l E_l |E_l\rangle\langle E_l|$ with all eigenvalues $E_l \geq 0$, and known Pauli decomposition $H = \sum_\ell a_\ell P_\ell$; $\lambda := \sum_\ell |a_\ell|$. Assume the spectral gap is lower bounded by $\Delta \leq E_1 - E_0$. Additionally, we suppose that we can freely prepare an initial trial state $|\psi_0\rangle$ with overlap with the ground state $\gamma := |\langle \psi_0 | E_0 \rangle|$. Given parameters ω, η and the ground state energy E_0 , there exists a random compiler that returns Eqs. (26) and (27) up to additive error ε with probability at least $(1 - \delta)^2$, utilizing $\mathcal{O}\left(\log\left(\frac{2}{\delta}\right) \frac{\|\Gamma^{(\pm)}\|^{-1}}{\gamma^4 \varepsilon^2} \log\left(\frac{\|\Gamma^{(\pm)}\|^{-1}}{\varepsilon}\right)\right)$ circuit runs respectively, each of non-Clifford depth at most $\mathcal{O}\left(\frac{\lambda_H^2}{\Delta^2} \log^2\left(\frac{2\|\Gamma^{(\pm)}\|^{-1}}{\varepsilon \gamma^2}\right) + (\hbar\omega \pm E_0 + \eta + \lambda_H)^2 \|\Gamma^{(\pm)}\|^{-1} \log^2\left(\frac{\|\Gamma^{(\pm)}\|^{-1}}{\varepsilon}\right)\right)$ with a normalization subroutine that has smaller complexities than the main algorithm.*

Proof of Proposition 5. We recall that, from Sections 3 and 4, we have decompositions of the matrix inverse function and Gaussian function in terms of Pauli gates and Pauli rotations, provided decomposition of the matrix in terms of Pauli operators.

Namely, by combining Lemma 2 and Lemma 10 we have for some Hamiltonian

$$\left\| e^{-\frac{1}{2}\tau^2 H^2} - f_{GS}(\varepsilon, H) \right\| \leq \varepsilon, \quad (157)$$

where $f_{GS}(\varepsilon, H) = \sum_{i \in \mathcal{S}_{\varepsilon, H}} h_i(\varepsilon, H) V_i(\varepsilon, H)$ is a linear combination of gates with weight $R_{GS} := \sum_{i \in \mathcal{S}_{\varepsilon, H}} |h_i(\varepsilon, H)|$. The weight of this linear combination satisfies $R_{GS} = \Theta(1)$ and each V_i has non-Clifford gate depth at most $\Theta\left(\lambda_H^2 \tau^2 \log\left(\frac{2}{\varepsilon}\right)\right)$ where $\lambda_H := \sum_\ell |a_\ell|$ is the Pauli weight of H . Moreover, we recount that Corollary 9 states that applying the operator $e^{-\frac{1}{2}\tau^2 H^2}$ (after normalization) with $\tau = \frac{1}{\Delta} \sqrt{2 \log \frac{1}{\varepsilon \gamma}}$ approximately projects to the ground state with $2\|O\|\varepsilon$ additive error when considering an expectation value of O .

Likewise, by combining Lemma 1 and Eq. (114) in Lemma 6, given some operator $\Gamma = \sum_l a_l P_l$ we have

$$\left\| \Gamma^{-1} - f_{inv}(\varepsilon, \Gamma) \right\| \leq \varepsilon, \quad (158)$$

where $f_{inv}(\varepsilon, \Gamma) = \sum_{i \in \mathcal{S}_{\varepsilon, \Gamma}} \gamma_i(\varepsilon, \Gamma) U_i(\varepsilon, \Gamma)$ is a linear combination of gates with weight $R_{inv} := \sum_{i \in \mathcal{S}_{\varepsilon, \Gamma}} |\gamma_i(\varepsilon, \Gamma)|$ satisfying

$$R_{inv} = \Theta\left(\|\Gamma^{-1}\| \sqrt{\log\left(\frac{\|\Gamma^{-1}\|}{\varepsilon}\right)}\right), \quad (159)$$

and each U_i has non-Clifford gate depth at most $\Theta\left(\lambda_\Gamma^2 \|\Gamma^{-1}\|^2 \log^2\left(\frac{\|\Gamma^{-1}\|}{\varepsilon}\right)\right)$, where λ_Γ is the Pauli weight of Γ .

We now specifically consider the Green's function problem. We wish to find the inverse of the (non-Hermitian) operator $\Gamma^{(\pm)} = (\hbar\omega \pm E_0)\mathbb{1} \mp H + i\eta\mathbb{1}$. Following the remark in Section 3, this can be embedded in a Hermitian operator by dilating the space and considering $Y^{(\pm)} = X \otimes ((\hbar\omega \pm E_0)\mathbb{1} \mp H) + Y \otimes \eta\mathbb{1}$. These operators have Pauli weight $\lambda_{Y^{(\pm)}} \leq |\hbar\omega \pm E_0| + \lambda_H + \eta$, and satisfy $\|Y^{(\pm)}\| = \|\Gamma^{(\pm)-1}\|$. We can then write the quantity we wish to prepare as

$$G^{(\pm)} = \langle 1, E_0 | \hat{a}_i \left(Y^{(\pm)} \right)^{-1} \hat{a}_j^\dagger | 0, E_0 \rangle. \quad (160)$$

In order to sample from the ground state, we will need to approximate the normalization constant $q^2 := \|e^{-\frac{1}{2}\tau^2 H^2} |\psi_0\rangle\|^2$, where $|\psi_0\rangle$ is the trial ground state. We denote the statistical approximation of this quantity with M_q shots as $Q^{(M_q)}$. We denote the statistical approximation of $\langle 1, \psi_0 | e^{-\frac{1}{2}\tau^2 H^2} \hat{a}_i (Y^{(\pm)})^{-1} \hat{a}_j^\dagger e^{-\frac{1}{2}\tau^2 H^2} | 0, \psi_0 \rangle$ as E^M . We can then express the full approximation error as

$$\left| \frac{1}{Q^{(M_q)}} E^M - \langle 1, E_0 | \hat{a}_i \left(Y^{(\pm)} \right)^{-1} \hat{a}_j^\dagger | 0, E_0 \rangle \right| \leq \quad (161)$$

$$\leq \left| \langle 1, E_0 | \hat{a}_i \left(Y^{(\pm)} \right)^{-1} \hat{a}_j^\dagger | 0, E_0 \rangle - \frac{1}{q^2} \langle 1, \psi_0 | e^{-\frac{1}{2}\tau^2 H^2} \hat{a}_i (Y^{(\pm)})^{-1} \hat{a}_j^\dagger e^{-\frac{1}{2}\tau^2 H^2} | 0, \psi_0 \rangle \right| \quad (162)$$

$$+ \frac{1}{q^2} \left| \langle 1, \psi_0 | e^{-\frac{1}{2}\tau^2 H^2} \hat{a}_i (Y^{(\pm)})^{-1} \hat{a}_j^\dagger e^{-\frac{1}{2}\tau^2 H^2} | 0, \psi_0 \rangle - \langle 1, \psi_0 | f_{GS}(\tilde{\varepsilon}_1, H)^\dagger \hat{a}_i (Y^{(\pm)})^{-1} \hat{a}_j^\dagger f_{GS}(\tilde{\varepsilon}_1, H) | 0, \psi_0 \rangle \right| \quad (163)$$

$$+ \frac{1}{q^2} \left| \langle 1, \psi_0 | f_{GS}(\tilde{\varepsilon}_1, H)^\dagger \hat{a}_i (Y^{(\pm)})^{-1} \hat{a}_j^\dagger f_{GS}(\tilde{\varepsilon}_1, H) | 0, \psi_0 \rangle - \langle 1, \psi_0 | f_{GS}(\tilde{\varepsilon}_1, H)^\dagger \hat{a}_i f_{inv}(\tilde{\varepsilon}_2, Y^{(\pm)}) \hat{a}_j^\dagger f_{GS}(\tilde{\varepsilon}_1, H) | 0, \psi_0 \rangle \right| \quad (164)$$

$$+ \frac{1}{q^2} \left| \langle 1, \psi_0 | f_{GS}(\tilde{\varepsilon}_1, H)^\dagger \hat{a}_i f_{inv}(\tilde{\varepsilon}_2, Y^{(\pm)}) \hat{a}_j^\dagger f_{GS}(\tilde{\varepsilon}_1, H) | 0, \psi_0 \rangle - \bar{z}^{(M)} \right| \quad (165)$$

$$+ \left| \frac{1}{q^2} - \frac{1}{Q^{(M_q)}} \right| \cdot \left| \bar{z}^{(M)} \right|, \quad (166)$$

where in the above we have used a chain of triangle inequalities. We now specify conditions so that the right hand side of the above is $\mathcal{O}(\varepsilon)$. Corollary 9 bounds (162) by 2ε with the choice $\tau = \frac{1}{\Delta} \sqrt{2 \log \frac{\|\hat{a}_i Y^{(\pm)-1} \hat{a}_j^\dagger\|}{\varepsilon \gamma}} \leq \frac{1}{\Delta} \sqrt{2 \log \frac{\|Y^{(\pm)-1}\|}{\varepsilon \gamma}} = \frac{1}{\Delta} \sqrt{2 \log \frac{\|\Gamma^{(\pm)-1}\|}{\varepsilon \gamma}}$. The term in (163) is bounded by 24ε by Eq. (157) and Lemma 2 under the condition that each V_i appearing in $f_{GS}(\tilde{\varepsilon}_1, H)$ has non-Clifford gate depth at most $2\lambda_H^2 \tau^2 \log \left(\frac{2\|\Gamma^{(\pm)-1}\|}{\varepsilon q^2} \right)$, which ensures that $\left\| e^{-\frac{1}{2}\tau^2 H^2} - f_{GS}(\tilde{\varepsilon}_1, H) \right\| \leq \frac{\varepsilon q^2}{\|\Gamma^{(\pm)-1}\|}$. The term in (164) can be bounded with Hölder's inequality as

$$(164) \leq \left\| Y^{(\pm)} - f_{inv}(\tilde{\varepsilon}_2, Y^{(\pm)}) \right\|_\infty \cdot \frac{1}{q^2} \left\| \hat{a}_j^\dagger f_{GS}(\tilde{\varepsilon}_1, H) | 1, \psi_0 \rangle \langle 0, \psi_0 | f_{GS}(\tilde{\varepsilon}_1, H)^\dagger \hat{a}_i \right\|_1 \quad (167)$$

$$= \left\| Y^{(\pm)} - f_{inv}(\tilde{\varepsilon}_2, Y^{(\pm)}) \right\|_\infty \cdot \frac{1}{q^2} \left\| f_{GS}(\tilde{\varepsilon}_1, H) | 1, \psi_0 \rangle \langle 0, \psi_0 | f_{GS}(\tilde{\varepsilon}_1, H)^\dagger \right\|_1 \quad (168)$$

$$\leq \left\| Y^{(\pm)} - f_{inv}(\tilde{\varepsilon}_2, Y^{(\pm)}) \right\|_\infty \cdot \frac{1}{q^2} \left\| f_{GS}(\tilde{\varepsilon}_1, H) | \psi_0 \rangle \langle \psi_0 | \right\|_2^2 \quad (169)$$

$$\leq \left\| Y^{(\pm)} - f_{inv}(\tilde{\varepsilon}_2, Y^{(\pm)}) \right\|_\infty \cdot \frac{1}{q^2} \left(\left\| e^{-\frac{1}{2}\tau^2 H^2} | \psi_0 \rangle \langle \psi_0 | \right\|_2 + \left\| \left(e^{-\frac{1}{2}\tau^2 H^2} - f_{GS}(\tilde{\varepsilon}_1, H) \right) | \psi_0 \rangle \langle \psi_0 | \right\|_2 \right)^2 \quad (170)$$

$$\leq \left\| Y^{(\pm)} - f_{inv}(\tilde{\varepsilon}_2, Y^{(\pm)}) \right\|_\infty \cdot \frac{1}{q^2} \left(\left\| e^{-\frac{1}{2}\tau^2 H^2} | \psi_0 \rangle \right\|_2 + \left\| \left(e^{-\frac{1}{2}\tau^2 H^2} - f_{GS}(\tilde{\varepsilon}_1, H) \right) \right\|_\infty \right)^2 \quad (171)$$

$$\leq \left\| Y^{(\pm)} - f_{inv}(\tilde{\varepsilon}_2, Y^{(\pm)}) \right\|_\infty \left(1 + 2 \frac{\varepsilon q}{\|\Gamma^{(\pm)-1}\|} + \frac{\varepsilon^2 q^2}{\|\Gamma^{(\pm)-1}\|^2} \right), \quad (172)$$

where in the equality we have used the unitary invariance of the Schatten norm, noting that \hat{a}_j^\dagger and \hat{a}_i can be expressed as probabilistic combinations of two unitaries. In the second inequality we have again used Hölder's inequality, and the third inequality is due to the triangle inequality. Thus, assuming $\varepsilon \leq \frac{\|\Gamma^{(\pm)-1}\|}{q}$ (of which we expect the right-hand-side to be much larger than 1), the term in (164) can be bounded by 4ε by setting $\tilde{\varepsilon}_2 = \varepsilon$ which sets $R_{inv} = \Theta \left(\|\Gamma^{(\pm)-1}\| \sqrt{\log \left(\frac{\|\Gamma^{(\pm)-1}\|}{\varepsilon} \right)} \right)$ and the non-Clifford gate depth of each U_i as being at most

$\Theta \left(\lambda_{Y^{(\pm)}}^2 \|\Gamma^{(\pm)-1}\|^2 \log^2 \left(\frac{\|\Gamma^{(\pm)-1}\|}{\varepsilon} \right) \right)$. The term in (165) can be bounded by ε with probability $(1 - \delta)$ by asking for number of shots

$$M \geq 2 \log \left(\frac{2}{\delta} \right) \frac{R_{inv}^2 R_{GS}^4}{\varepsilon q^4} = \mathcal{O} \left(\log \left(\frac{2}{\delta} \right) \frac{\|\Gamma^{(\pm)-1}\|^2}{\varepsilon^2 \gamma^4} \log \left(\frac{\|\Gamma^{(\pm)-1}\|}{\varepsilon} \right) \right), \quad (173)$$

where we have used the fact that $\frac{1}{q} \leq \frac{2}{\gamma}$. Finally, the term in (166) can be bounded by ε with probability at least $(1 - \delta)$ by using number of shots

$$M_q \geq 2 \log \left(\frac{2}{\delta} \right) \frac{\|Y^{(\pm)-1}\|^2 R_{GS}^4}{\varepsilon q^4} = \mathcal{O} \left(\log \left(\frac{2}{\delta} \right) \frac{\|\Gamma^{(\pm)-1}\|^2}{\varepsilon^2 \gamma^4} \right), \quad (174)$$

for the normalization subroutine.

Finally, we note the total gate complexity consists of the sum of the gate complexities for U_i and V_i respectively. From the above discussion, we see that the non-Clifford gate complexity of V_i is $\mathcal{O} \left(\frac{\lambda_H^2}{\Delta^2} \log \left(\frac{2\|\Gamma^{(\pm)-1}\|}{\varepsilon \gamma^2} \right) \right)$ and the non-Clifford gate complexity of U_i is $\mathcal{O} \left((|\hbar\omega \pm E_0| + \eta + \lambda_H)^2 \|\Gamma^{(\pm)-1}\|^2 \log^2 \left(\frac{\|\Gamma^{(\pm)-1}\|}{\varepsilon} \right) \right)$. The non-Clifford gate complexity for the normalization subroutine as given by Proposition 2 is $\mathcal{O} \left(\frac{\lambda_H^2}{\Delta^2} \log \left(\frac{\|\Gamma^{(\pm)-1}\|}{\varepsilon \gamma} \right) \log \left(\frac{1}{\varepsilon \gamma} \right) \right)$. \square

We now briefly remark on the scenario if we would like to evaluate the Green's function but the exact ground state energy is not given. In this case, an ε -additive approximation to E_0 would yield an additive error to the evaluation of the Green's functions by $\max(\varepsilon \|\Gamma^{(\pm)-1}\|, \|\Gamma^{(\pm)-1} \pm \varepsilon \mathbb{1}\|)$. This can be seen by noting that

$$\left\| \left(\Gamma^{(\pm)-1} \pm \varepsilon \mathbb{1} \right)^{-1} - \Gamma^{(\pm)-1} \right\| \leq \varepsilon \left\| \left(\Gamma^{(\pm)-1} \pm \varepsilon \mathbb{1} \right)^{-1} \Gamma^{(\pm)-1} \right\|. \quad (175)$$