

Parameter Estimation-Based Extended Observer for Linear Systems with Polynomial Overparametrization

Anton Glushchenko, *Member, IEEE* and Konstantin Lastochkin

Abstract—We consider a class of uncertain linear time-invariant overparametrized systems affected by bounded disturbances, which are described by a known exosystem with unknown initial conditions. For such systems an exponentially stable extended adaptive observer is proposed, which, unlike known solutions, simultaneously: (i) allows one to reconstruct original (physical) states of the system represented in arbitrarily chosen state-space form rather than virtual states of the observer canonical form; (ii) ensures convergence of the state observation error to zero under extremely weak requirement of the regressor finite excitation; (iii) does not include Luenberger correction gain and forms states estimate using algebraic rather than differential equation; (iv) additionally reconstructs the unmeasured external disturbance. Illustrative simulations support obtained theoretical results.

I. INTRODUCTION

Adaptive observers are recurrent algorithms that simultaneously reconstruct unmeasured states and identify unknown parameters [1]. Nowadays various methods of such observers design have been proposed for linear SISO and MIMO systems [1]–[4], and also very important and interesting results have been obtained concerning state reconstruction of the nonlinear systems [5], [6] and ones with time-varying parameters [7]–[9]. In this study we return again to a deeply investigated problem of joint estimation of linear SISO systems state and parameters.

Retrospective analysis of existing solutions to the problem under consideration is given below. In [2], [3] adaptive observers for simultaneous estimation of states and unknown parameters of a linear SISO system have been proposed for the first time. Kreisselmeier [10] proposed a parameterization that, unlike in [2], [3], allows one to completely separate the observer dynamics from the adaptive loop to make the design of suitable parameter adaptation schemes substantially simpler. Marino and Tomei in [11] generalized the result of [10] to linearizable nonlinear systems, and in [12] these results were additionally subjected to robustness stress tests. In [4], motivated by [10]–[12], an alternative observer with a simpler structure has been proposed. In [9] an exhaustive overview of some existing observer design algorithms for linearizable nonlinear systems with time-varying known parameters and time-invariant unknown parameters is given (see also the review [1]). The main drawbacks of all above-mentioned studies are two-fold:

- D1)** strict persistent excitation condition is required to guarantee convergence of the state observation and parameter errors;
- D2)** an appropriate state transformation is required to represent the system in a form without multiplications of unknown parameters and unmeasured states (observer canonical form, for example).

To overcome the first drawback (**D1**), two different approaches have been proposed recently. In [13], a modified observer [10] with exponential convergence of state observation and parameter errors under the weaker regressor finite excitation requirement is proposed. In [14], based on the results of [6], [7], a parameter estimation-based observer is developed, which, unlike existing ones, *i*) ensures the parameter error finite-time convergence when the regressor finite excitation condition is met, *ii*) reconstructs states using algebraic rather than differential equation.

The second problem (**D2**) is more complex in comparison with the first one, since it does not allow one to apply the existing adaptive observers to recover the physical states of the dynamical systems. Instead, virtual states of appropriately chosen state space form, which includes only products between unknown parameters and measured functions (mappings for output and input signals), are recovered. At the same time, to solve many real-world control problems (*e.g.* two-mass systems vibration suppressing [15]) it is required to measure the physical states rather than the virtual ones.

In recent studies [16], [17], two new adaptive observers of physical states of linear SISO systems with polynomial overparameterization have been proposed. The polynomial relation between the parameters of the observer canonical form and the original state space allows one to: (i) parameterize and solve the problem of identification of parameters related to unmeasured states, (ii) estimate the physical states of the system. The solution [16] is in line with the studies [2], [3], [9], [10], [13] and reconstructs the unmeasured state estimates using a differential equation, which is a copy of the system up to the Luenberger corrective feedback. Observer in [17] is based on a parameter estimation-based observer design procedure [6], [7], [14] and, unlike [16], forms states estimate using an algebraic equation and, unlike [14], allows one to reconstruct the physical states of the system. Both proposed observers overcome **D1** and guarantee exponential convergence of the state observation error under extremely weaker finite excitation condition. Comparing the observers from [16], [17] with each other, it should be noted that the solution in [17] does not use the Luenberger corrective feedback and, therefore, is not affected by the peaking

Financial support is in part provided by the Grants Council of the President of the Russian Federation (MD-1787.2022.4).

A. Glushchenko is with V.A. Trapeznikov Institute of Control Sciences of Russian Academy of Sciences, Moscow, Russia aiglush@ipu.ru

K. Lastochkin is with V.A. Trapeznikov Institute of Control Sciences of Russian Academy of Sciences, Moscow, Russia lastconst@ipu.ru

phenomenon in the course of transients (see Comparative Simulation in [16] and [17]).

In [18] the results of [16] are extended to the class of systems with external unmeasured disturbances generated by known exosystems with unknown initial conditions. In this study we extend the results of [17] in a similar way. The main advantages and salient features of the observer proposed in this research are summarized as follows:

- F1)** in comparison with [2]–[4], [8]–[14] physical states are reconstructed for a system represented in an arbitrary state space form rather than virtual states of the appropriately chosen state space form;
- F2)** the convergence of the unmeasured state estimates to their true values is guaranteed if the regressor finite excitation condition holds;
- F3)** in comparison with [16], [18], the Luenberger corrective feedback is not applied, and state estimates are formed using an algebraic rather than a differential equation;
- F4)** in addition to the state and unknown parameter estimates, an unmeasured external disturbance generated by a known exosystem with unknown initial conditions is also reconstructed.

The organization of this paper is as follows. Section II provides a rigorous problem statement. The design procedure for the proposed observer and its properties analysis are elucidated in Section III. Section IV presents some simulation results to validate the advantages of the proposed method in comparison with [16], [18]. The paper is wrapped up with conclusion and further research scope in Section V.

The below-given definitions of the heterogeneous mapping and the regressor finite excitation condition are used throughout the paper.

Definition 1. A mapping $\mathcal{F}(x): \mathbb{R}^{n_x} \rightarrow \mathbb{R}^{n_{\mathcal{F}} \times m_{\mathcal{F}}}$ is heterogeneous of degree $\ell_{\mathcal{F}} \geq 1$ if there exists $\Xi_{\mathcal{F}}(\omega(t)) = \Xi_{\mathcal{F}}(\omega(t))\omega(t) \in \mathbb{R}^{\Delta_{\mathcal{F}} \times n_x}$, $\Pi_{\mathcal{F}}(\omega(t)) \in \mathbb{R}^{n_{\mathcal{F}} \times n_{\mathcal{F}}}$, and a mapping $\mathcal{T}_{\mathcal{F}}(\Xi_{\mathcal{F}}(\omega(t))x): \mathbb{R}^{\Delta_{\mathcal{F}}} \rightarrow \mathbb{R}^{n_{\mathcal{F}} \times m_{\mathcal{F}}}$ such that for all $\omega(t) \in \mathbb{R}$ and $x \in \mathbb{R}^{n_x}$ the following conditions hold:

$$\begin{aligned} \Pi_{\mathcal{F}}(\omega(t))\mathcal{F}(x) &= \mathcal{T}_{\mathcal{F}}(\Xi_{\mathcal{F}}(\omega(t))x), \\ \det\{\Pi_{\mathcal{F}}(\omega(t))\} &\geq \omega^{\ell_{\mathcal{F}}}(t), \Xi_{\mathcal{F}ij}(\omega(t)) = c_{ij}\omega^{\ell}(t), \\ c_{ij} &\in \{0, 1\}, \ell > 0. \end{aligned} \quad (1)$$

For instance, the mapping $\mathcal{F}(x) = \text{col}\{x_1x_2, x_1\}$ with $\Pi_{\mathcal{F}}(\omega) = \text{diag}\{\omega^2, \omega\}$, $\Xi_{\mathcal{F}}(\omega) = \text{diag}\{\omega, \omega\}$ is heterogeneous of degree $\ell_{\mathcal{F}} = 3$.

Definition 2. The regressor $\varphi(t) \in \mathbb{R}^n$ is finitely exciting ($\varphi(t) \in \text{FE}$) over the time range $[t_r^+; t_e]$ if there exists $t_r^+ \geq 0$, $t_e > t_r^+$ and α such that the following inequality holds:

$$\int_{t_r^+}^{t_e} \varphi(\tau)\varphi^T(\tau) d\tau \geq \alpha I_n, \quad (2)$$

where $\alpha > 0$ is the excitation level, I_n is an identity matrix.

II. PROBLEM STATEMENT

A class of uncertain linear time-invariant overparametrized systems affected by bounded external disturbances are considered:¹

$$\begin{aligned} \dot{x}(t) &= A(\theta)x(t) + B(\theta)u(t) + D(\theta)\delta(t), \\ y(t) &= C^T x(t), x(t_0) = x_0, \end{aligned} \quad (3)$$

where $x(t) \in \mathbb{R}^n$ is the original (physical) system states with unknown initial conditions x_0 , $\delta(t) \in \mathbb{R}$ is a bounded external disturbance, $A: \mathbb{R}^{n_{\theta}} \rightarrow \mathbb{R}^{n \times n}$, $B: \mathbb{R}^{n_{\theta}} \rightarrow \mathbb{R}^n$, $D: \mathbb{R}^{n_{\theta}} \rightarrow \mathbb{R}^n$ denote known mappings with unknown parameter $\theta \in \mathbb{R}^{n_{\theta}}$, $C := C(\theta) \in \mathbb{R}^n$ stands for a known vector or a mapping that depends only on θ . The pair $(C^T, A(\theta))$ is completely observable and only control $u(t) \in \mathbb{R}$ and output $y(t) \in \mathbb{R}$ signals are measurable.

Considering the control signal and disturbances, the following assumptions are adopted.

Assumption 1. For all $t \geq t_0$ the control signal $u(t)$ ensures existence and boundedness of trajectories of the system (3).

Assumption 2. The disturbance $\delta(t)$ is bounded, continuous and generated by a time-invariant exosystem:

$$\begin{aligned} \dot{x}_{\delta}(t) &= \mathcal{A}_{\delta}x_{\delta}(t), x_{\delta}(t_0) = x_{\delta 0}, \\ \delta(t) &= h_{\delta}^T x_{\delta}(t), \end{aligned} \quad (4)$$

where $x_{\delta}(t) \in \mathbb{R}^{n_{\delta}}$ stands for an exosystem state with unknown initial conditions $x_{\delta 0}(t_0)$, $h_{\delta} \in \mathbb{R}^{n_{\delta}}$, $\mathcal{A}_{\delta} \in \mathbb{R}^{n_{\delta} \times n_{\delta}}$ are known vector and matrix such that the pair $(h_{\delta}^T, \mathcal{A}_{\delta})$ is observable.

The goal is to design an adaptive observer, which ensures that the following equalities hold:

$$\lim_{t \rightarrow \infty} \|\tilde{x}(t)\| = 0 \text{ (exp)}, \quad \lim_{t \rightarrow \infty} \|\tilde{\delta}(t)\| = 0 \text{ (exp)}, \quad (5)$$

where $\tilde{x}(t) = \hat{x}(t) - x(t)$ is a state observation error of the system (3), $\tilde{\delta}(t) = \hat{\delta}(t) - \delta(t)$ is a disturbance observation error.

III. MAIN RESULT

In accordance with the results from [2], for each completely observable linear system (3) there exist nonsingular matrices:

$$\begin{aligned} T_I(\theta) &= [A^{n-1}(\theta)\mathcal{O}_n(\theta) \quad A^{n-2}(\theta)\mathcal{O}_n(\theta) \quad \cdots \quad \mathcal{O}_n(\theta)], \\ \mathcal{O}_n(\theta) &= \mathcal{O}(\theta) [0_{1 \times (n-1)} \quad 1]^T, \\ \mathcal{O}^{-1}(\theta) &= [C(\theta) \quad (A(\theta))^T C(\theta) \quad \cdots \quad (A^{n-1}(\theta))^T C(\theta)]^T, \end{aligned}$$

which define the similarity transformation $\xi(t) = T(\theta)x(t)$ to rewrite the system (3) in the observer canonical form:

$$\dot{\xi}(t) = A_0\xi(t) + \psi_a(\theta)y(t) + \psi_b(\theta)u(t) + \psi_d(\theta)\delta(t), \quad (6)$$

$$y(t) = C_0^T \xi(t), \quad \xi(t_0) = \xi_0(\theta) = T(\theta)x_0, \quad (7)$$

¹Dependencies from θ and t can be further suppressed for the sake of brevity.

where

$$\begin{aligned} \psi_a(\theta) &= T(\theta) A(\theta) T^{-1}(\theta) C_0, \psi_b(\theta) = T(\theta) B(\theta), \\ \psi_d(\theta) &= T(\theta) D(\theta) \\ A_0 &= \begin{bmatrix} 0_n & I_{n-1} \\ 0_{1 \times (n-1)} & 1 \end{bmatrix}, C_0^T = C^T(\theta) T^{-1}(\theta) = \begin{bmatrix} 1 & 0_{n-1}^T \end{bmatrix}, \end{aligned}$$

$T_I(\theta) := T^{-1}(\theta)$, \mathcal{O}_n is the n^{th} column of the matrix that is inverse to $\mathcal{O}^{-1}(\theta)$, $\xi(t) \in \mathbb{R}^n$ denotes state vector of the observer canonical form with unknown initial conditions ξ_0 , the vector $C_0 \in \mathbb{R}^n$ and mappings $\psi_a, \psi_b, \psi_d: \mathbb{R}^{n_\theta} \rightarrow \mathbb{R}^n$ are known.

The similarity transformation $\xi(t) = T(\theta)x(t)$ and representation (6), (7) motivate to reconstruct the unmeasured states $x(t)$ in the following way:

$$\hat{x}(t) = \hat{T}_I(t) \hat{\xi}(t), \quad (8)$$

where $\hat{\xi}(t)$ is the estimate of observer canonical form (6) states, $\hat{T}_I(t)$ stands for the estimate of the matrix $T_I(\theta)$.

At the same time, the solution of the set of equations (4) is written as:

$$\begin{aligned} \dot{\Phi}_\delta(t) &= \mathcal{A}_\delta \Phi_\delta(t), \Phi_\delta(t_0) = I_{n_\delta}, \\ x_\delta(t) &= \Phi_\delta(t) x_{\delta 0}, \\ \delta(t) &= h_\delta^T \Phi_\delta(t) x_{\delta 0}, \end{aligned} \quad (9)$$

which motivate to estimate the external disturbance $\delta(t)$ as:

$$\hat{\delta}(t) = h_\delta^T \Phi_\delta(t) \hat{x}_{\delta 0}(t). \quad (10)$$

According to equations (8) and (10), the problem (5) of unmeasured signals estimation is transformed into the problem of identification of unknown parameters $x_{\delta 0}$, $T_I(\theta)$ and estimation of unmeasured states $\xi(t)$ of the observer canonical form (6). According to [6], [7], [14], the problem of $\xi(t)$ estimation can be reduced to the one of parameter identification. Thus, using the results [14], [18], [19], the following parameterizations are obtained for the unknown parameters $\eta(\theta) = \text{col}\{\psi_a(\theta), \psi_b(\theta)\}$ and states $\xi(t)$.

Lemma 1. *Let $t_\epsilon > t_0$ be a sufficiently large predefined time instant, then for all $t \geq t_\epsilon$ the unknown parameters $\eta(\theta)$ and unmeasured states $\xi(t)$ satisfy the following regression models:*

$$\mathcal{Y}(t) = \Delta(t) \eta(\theta), \quad (11)$$

$$\begin{aligned} \mathcal{Y}(t) &= k(t) \cdot \text{adj}\{\varphi(t)\} q(t), \Delta(t) = k(t) \cdot \det\{\varphi(t)\}, \\ \xi(t) &= z(t) + R^T(t) \kappa(\theta), \\ \kappa(\theta) &= [\psi_a^T(\theta) \quad \psi_b^T(\theta) \quad \psi_d^T(\theta)]^T, \\ R^T(t) &= [\Omega(t) \quad P(t) \quad U(t)], \end{aligned} \quad (12)$$

where

$$\begin{aligned} q(t) &= \int_{t_\epsilon}^t e^{-\sigma(\tau-t_\epsilon)} \bar{\varphi}_f(\tau) \left(\begin{array}{c} \bar{q}(\tau) - k_1 \bar{q}_f(\tau) - \\ -\beta^T (F_f(\tau) + l y_f(\tau)) \end{array} \right) d\tau, \\ q(t_\epsilon) &= 0_{2n}, \\ \varphi(t) &= \int_{t_\epsilon}^t e^{-\sigma(\tau-t_\epsilon)} \bar{\varphi}_f(\tau) \bar{\varphi}_f^T(\tau) d\tau, \\ \varphi(t_\epsilon) &= 0_{2n \times 2n}, \end{aligned} \quad (13)$$

$$\begin{aligned} \dot{\bar{q}}_f(t) &= -k_1 \bar{q}_f(t) + \bar{q}(t), \bar{q}_f(t_0) = 0, \\ \dot{\bar{\varphi}}_f(t) &= -k_1 \bar{\varphi}_f(t) + \bar{\varphi}(t), \bar{\varphi}_f(t_0) = 0_{2n}, \\ \dot{F}_f(t) &= -k_1 F_f(t) + F(t), F_f(t_0) = 0_{n_\delta}, \\ \dot{y}_f(t) &= -k_1 y_f(t) + y(t), y_f(t_0) = 0, \end{aligned} \quad (14)$$

$$\begin{aligned} \bar{q}(t) &= y(t) - C_0^T z, \bar{\varphi}(t) = \begin{bmatrix} \dot{\Omega}^T C_0 + N^T \beta \\ \dot{P}^T C_0 + H^T \beta \end{bmatrix}, \\ \dot{z}(t) &= A_K z(t) + K y(t), z(t_0) = 0_n, \\ \dot{\Omega}(t) &= A_K \Omega(t) + I_n y(t), \Omega(t_0) = 0_{n \times n}, \\ \dot{P}(t) &= A_K P(t) + I_n u(t), P(t_0) = 0_{n \times n}, \end{aligned} \quad (15)$$

$$\begin{aligned} \dot{U}(t) &= A_K U(t) + I_n \delta(t), U(t_0) = 0_{n \times n}, \\ \dot{F}(t) &= G F(t) + G l y(t) - l C_0^T \dot{z}(t), F(t_0) = 0_{n_\delta}, \\ \dot{H}(t) &= G H(t) - l C_0^T \dot{P}(t), H(t_0) = 0_{n_\delta \times n}, \\ \dot{N}(t) &= G N(t) - l C_0^T \dot{\Omega}(t), N(t_0) = 0_{n_\delta \times n}, \end{aligned}$$

and, if $\bar{\varphi}(t) \in \text{FE}$ over $[t_\epsilon; t_e]$, then for all $t \geq t_e$ it holds that $\Delta_{\max} \geq \Delta(t) \geq \Delta_{\min} > 0$.

Here $k(t) > k_{\min} > 0$ is a time-varying (or time-invariant) amplifier, $k_1 > 0$, $\sigma > 0$ are filters time constants, $A_K = A_0 - K C_0^T$, G stand for stable matrices of appropriate dimensions, $l \in \mathbb{R}^{n_\delta}$ denotes a vector such that the pair (G, l) is controllable, and G is chosen so as to satisfy the condition $\sigma\{\mathcal{A}_\delta\} \cap \sigma\{G\} = 0$, $\beta \in \mathbb{R}^{n_\delta}$ is a solution of the following set of equations:

$$\begin{aligned} M_\delta \mathcal{A}_\delta - G M_\delta &= l \bar{h}_\delta^T, \bar{h}_\delta^T = h_\delta^T \mathcal{A}_\delta, \\ \beta &= \bar{h}_\delta^T M_\delta^{-1}. \end{aligned}$$

Proof of Lemma is presented in Supplementary material [20].

Following parametrizations (8), (10), (12), in order to estimate the states $x(t)$, it is sufficient to obtain the estimates of $\kappa(\theta)$, $T_I(\theta)$ and $x_{\delta 0}$. However, the regression equation (11) allows one to find only the parameters $\eta(\theta)$. Therefore, it is required to: a) parametrize an equation with respect to (w.r.t.) $x_{\delta 0}$ and b) transform (11) into the regression equations w.r.t. the parameters $\kappa(\theta)$, $T_I(\theta)$.

If the existence condition (where $\mathcal{L}_{ab} \in \mathbb{R}^{n_\theta \times n}$ is a matrix to take handpicked "good" elements from $\eta(\theta)$):

$$\begin{aligned} \det^2 \{\nabla_\theta \psi_{ab}(\theta)\} &> 0, \\ \psi_{ab}(\theta) &= \mathcal{L}_{ab} \eta(\theta) : \mathbb{R}^{n_\theta} \rightarrow \mathbb{R}^{n_\theta} \end{aligned} \quad (16)$$

of the inverse transform $\theta = \mathcal{F}(\psi_{ab}) : \mathbb{R}^{n_\theta} \rightarrow \mathbb{R}^{n_\theta}$ is met, then, according to [16]–[18], there exists a theoretical possibility that $\kappa(\theta)$, $T_I(\theta)$ could be obtained using $\eta(\theta)$.

In subsection 3.1 a method is proposed to obtain the regression equations w.r.t. $\kappa(\theta)$, $T_I(\theta)$ and $x_{\delta 0}$ from (11). In subsection 3.2 an adaptive observer is proposed that uses the above-mentioned regression equations and allows one to achieve the stated goal (5).

Remark 1. *It should be noted that in the general case $\kappa(\theta)$, $T_I(\theta)$ do not satisfy the Lipschitz condition, so the problem (5) cannot be reduced to θ identification (the mappings $\kappa(\hat{\theta})$, $T_I(\hat{\theta})$ can become singular in the course of a transient process). The below-proposed approach overcomes this problem by a linear transformation and allows one to identify $\kappa(\theta)$, $T_I(\theta)$ without singularity burden operations.*

Remark 2. *Integration in filters (13) starts from a sufficiently large time instant t_ϵ in order to avoid negative effect of a possibly large exponentially decaying term (see the proof of Lemma 1).*

A. Parametrization of equations w.r.t. $\kappa(\theta)$, $T_I(\theta)$, $x_{\delta 0}$

First of all, we put forward several hypothesis that: a) the mapping $\mathcal{F}(\psi_{ab})$ can be transformed into a linear regression equation w.r.t θ , and b) using the parametrization w.r.t θ , the linear regression equations w.r.t. $\psi_d(\theta)$, $T_I(\theta)$ can be obtained.

Hypothesis 1. *There exist heterogeneous in the sense of (1) mappings $\mathcal{G}(\psi_{ab}): \mathbb{R}^{n_\theta} \rightarrow \mathbb{R}^{n_\theta \times n_\theta}$, $\mathcal{S}(\psi_{ab}): \mathbb{R}^{n_\theta} \rightarrow \mathbb{R}^{n_\theta}$ such that:*

$$\mathcal{S}(\psi_{ab}) = \mathcal{G}(\psi_{ab}) \mathcal{F}(\psi_{ab}) = \mathcal{G}(\psi_{ab}) \theta, \quad (17)$$

$$\Pi_\theta(\Delta(t)) \mathcal{G}(\psi_{ab}) = \mathcal{T}_G(\Xi_G(\Delta(t)) \psi_{ab}): \mathbb{R}^{\Delta_G} \rightarrow \mathbb{R}^{n_\theta \times n_\theta},$$

$$\Pi_\theta(\Delta(t)) \mathcal{S}(\psi_{ab}) = \mathcal{T}_S(\Xi_S(\Delta(t)) \psi_{ab}): \mathbb{R}^{\Delta_S} \rightarrow \mathbb{R}^{n_\theta},$$

where $\det\{\Pi_\theta(\Delta(t))\} \geq \Delta^{\ell_\theta}(t)$, $\text{rank}\{\mathcal{G}(\psi_{ab})\} = n_\theta$, $\ell_\theta \geq 1$, $\Xi_G(\Delta(t)) \in \mathbb{R}^{\Delta_G \times n_\theta}$, $\Xi_S(\Delta(t)) \in \mathbb{R}^{\Delta_S \times n_\theta}$, and all mappings are known.

Having introduced the notation

$$\mathcal{Y}_{ab}(t) = \mathcal{L}_{ab} \mathcal{Y}, \quad \mathcal{M}_\theta(t) := \det\{\mathcal{T}_G(\Xi_G(\Delta) \mathcal{Y}_{ab})\},$$

the hypothesis is put forward that (17) can be transformed into regression equations w.r.t $\psi_d(\theta)$, $T_I(\theta)$.

Hypothesis 2. *There exist heterogenous in the sense of (1) mappings $\mathcal{Q}(\theta): \mathbb{R}^{n_\theta} \rightarrow \mathbb{R}^{n \times n}$, $\mathcal{P}(\theta): \mathbb{R}^{n_\theta} \rightarrow \mathbb{R}^{n \times n}$ such that:*

$$\mathcal{Q}(\theta) = \mathcal{P}(\theta) T_I(\theta), \quad (18)$$

$$\Pi_{T_I}(\mathcal{M}_\theta) \mathcal{P}(\theta) = \mathcal{T}_P(\Xi_P(\mathcal{M}_\theta) \theta): \mathbb{R}^{\Delta_P} \rightarrow \mathbb{R}^{n \times n},$$

$$\Pi_{T_I}(\mathcal{M}_\theta) \mathcal{Q}(\theta) = \mathcal{T}_Q(\Xi_Q(\mathcal{M}_\theta) \theta): \mathbb{R}^{\Delta_Q} \rightarrow \mathbb{R}^{n \times n},$$

where $\Xi_Q(\mathcal{M}_\theta(t)) \in \mathbb{R}^{\Delta_Q \times n_\theta}$, $\Xi_P(\mathcal{M}_\theta(t)) \in \mathbb{R}^{\Delta_P \times n_\theta}$, $\text{rank}\{\mathcal{P}(\theta)\} = n$, $\ell_{T_I} \geq 1$, $\det\{\Pi_{T_I}(\mathcal{M}_\theta(t))\} \geq \mathcal{M}_\theta^{\ell_{T_I}}(t)$, and all mappings are known.

Hypothesis 3. *There exist heterogeneous in the sense of (1) mappings $\mathcal{W}(\theta): \mathbb{R}^{n_\theta} \rightarrow \mathbb{R}^n$, $\mathcal{R}(\theta): \mathbb{R}^{n_\theta} \rightarrow \mathbb{R}^{n \times n}$ such that:*

$$\mathcal{W}(\theta) = \mathcal{R}(\theta) \psi_d(\theta), \quad (19)$$

$$\Pi_{\psi_d}(\mathcal{M}_\theta(t)) \mathcal{R}(\theta) = \mathcal{T}_R(\Xi_R(\mathcal{M}_\theta(t)) \theta): \mathbb{R}^{\Delta_R} \rightarrow \mathbb{R}^{n \times n},$$

$$\Pi_{\psi_d}(\mathcal{M}_\theta(t)) \mathcal{W}(\theta) = \mathcal{T}_W(\Xi_W(\mathcal{M}_\theta(t)) \theta): \mathbb{R}^{\Delta_W} \rightarrow \mathbb{R}^n,$$

where, $\Xi_W(\mathcal{M}_\theta(t)) \in \mathbb{R}^{\Delta_W \times n_\theta}$, $\Xi_R(\mathcal{M}_\theta(t)) \in \mathbb{R}^{\Delta_R \times n_\theta}$, $\det\{\Pi_{\psi_d}(\mathcal{M}_\theta(t))\} \geq \mathcal{M}_\theta^{\ell_{\psi_d}}(t)$, $\text{rank}\{\mathcal{R}(\theta)\} = n$, $\ell_{\psi_d} \geq 1$, and all mappings are known.

As it is thoroughly discussed in [16]–[18], the hypotheses (17)–(19) hold in case if the mappings $\mathcal{F}(\psi_{ab})$, $\psi_d(\theta)$, $T_I(\theta)$ are polynomials w.r.t. θ , which is quite common situation as far as practical scenarios are concerned. The fact that (17)–(19) are met and the property $\Xi_{(\cdot)}(\omega(t)) = \bar{\Xi}_{(\cdot)}(\omega(t)) \omega(t)$ of heterogenous mappings (1) allow one to transform the regression equation w.r.t. $\eta(\theta)$ into the linear regression equation w.r.t. $\kappa(\theta)$, $T_I(\theta)$, $x_{\delta 0}$ without application of singularity burden operations (particularly, without division).

Lemma 2. *The unknown parameters $\kappa(\theta)$, $T_I(\theta)$ and $x_{\delta 0}$ for all $t \geq t_e$ satisfy measurable regression equations:*

$$\mathcal{Y}_\kappa(t) = \mathcal{M}_\kappa(t) \kappa(\theta), \quad (20)$$

$$\mathcal{Y}_\kappa(t) = \text{adj}\{\text{blkdiag}\{\Delta(t) I_{2n}, \mathcal{M}_{\psi_d}(t) I_n\}\} \begin{bmatrix} \mathcal{Y}(t) \\ \mathcal{Y}_{\psi_d}(t) \end{bmatrix},$$

$$\mathcal{M}_\kappa(t) = \det\{\text{blkdiag}\{\Delta(t) I_{2n}, \mathcal{M}_{\psi_d}(t) I_n\}\},$$

$$\mathcal{Y}_{T_I}(t) = \mathcal{M}_{T_I}(t) T_I(\theta), \quad (21)$$

$$\mathcal{Y}_{T_I}(t) = \text{adj}\{\mathcal{T}_P(\bar{\Xi}_P(\mathcal{M}_\theta) \mathcal{Y}_\theta)\} \mathcal{T}_Q(\bar{\Xi}_Q(\mathcal{M}_\theta) \mathcal{Y}_\theta),$$

$$\mathcal{M}_{T_I}(t) = \det\{\mathcal{T}_P(\bar{\Xi}_P(\mathcal{M}_\theta) \mathcal{Y}_\theta)\},$$

$$\mathcal{Y}_{x_{\delta 0}}(t) = \mathcal{M}_{x_{\delta 0}}(t) x_{\delta 0}, \quad (22)$$

$$\mathcal{Y}_{x_{\delta 0}}(t) = \text{adj}\{V_f(t)\} p_f(t), \quad \mathcal{M}_{x_{\delta 0}}(t) = \det\{V_f(t)\},$$

where

1) the regression $\mathcal{Y}_\theta(t) = \mathcal{M}_\theta(t) \theta$ is formed using the following equations:

$$\mathcal{Y}_\theta(t) = \text{adj}\{\mathcal{T}_G(\bar{\Xi}_G(\Delta) \mathcal{Y}_{ab})\} \mathcal{T}_S(\bar{\Xi}_S(\Delta) \mathcal{Y}_{ab}),$$

$$\mathcal{M}_\theta(t) = \det\{\mathcal{T}_G(\bar{\Xi}_G(\Delta) \mathcal{Y}_{ab})\}, \quad \mathcal{Y}_{ab}(t) = \mathcal{L}_{ab} \mathcal{Y}(t),$$

2) the regression $\mathcal{Y}_{\psi_d}(t) = \mathcal{M}_{\psi_d}(t) \psi_d(\theta)$ is formed using the following equations:

$$\mathcal{Y}_{\psi_d}(t) = \text{adj}\{\mathcal{T}_R(\bar{\Xi}_R(\mathcal{M}_\theta) \mathcal{Y}_\theta)\} \mathcal{T}_W(\bar{\Xi}_W(\mathcal{M}_\theta) \mathcal{Y}_\theta),$$

$$\mathcal{M}_{\psi_d}(t) = \det\{\mathcal{T}_R(\bar{\Xi}_R(\mathcal{M}_\theta) \mathcal{Y}_\theta)\}.$$

3) the signals $p_f(t)$ and $V_f(t)$ are obtained as follows:

$$p_f(t) = \int_{t_e}^t e^{-\sigma(\tau-t_e)} \left(\Delta(\tau) (I_{n_\delta} \otimes \mathcal{Y}_{\psi_d}(\tau))^\top V^\top(\tau) \times \right. \\ \left. \times C_0 \mathcal{M}_{\psi_d}(\tau) p(\tau) \right) d\tau, \quad p_f(t_e) = 0_{n_\delta}, \quad (23)$$

$$p(t) = \Delta(t) \bar{q}(t) - C_0^\top \Omega(t) \mathcal{L}_a \mathcal{Y}(t) - C_0^\top P(t) \mathcal{L}_b \mathcal{Y}(t),$$

$$\mathcal{L}_a \psi_{ab}(\theta) = \psi_a(\theta), \quad \mathcal{L}_b \psi_{ab}(\theta) = \psi_b(\theta),$$

$$V_f(t) = \int_{t_e}^t e^{-\sigma(\tau-t_e)} \left(\Delta^2(\tau) (I_{n_\delta} \otimes \mathcal{Y}_{\psi_d}(\tau))^\top V^\top(\tau) C_0 \times \right. \\ \left. \times C_0^\top V(\tau) (I_{n_\delta} \otimes \mathcal{Y}_{\psi_d}(\tau)) d\tau, \quad V_f(t_e) = 0_{n_\delta \times n_\delta}, \right. \\ \left. \dot{V}(t) = A_K V(t) + (h_\delta^\top \Phi_\delta(t) \otimes I_n), \quad V(t_0) = 0_{n \times n n_\delta}, \right.$$

and, if $\bar{\varphi}(t) \in \text{FE}$ and $(h_\delta^\top \Phi_\delta(t) \otimes I_n) \in \text{FE}$ over $[t_e; t_e]$, then for all $t \geq t_e$ it holds that:

$$|\mathcal{M}_\kappa(t)| \geq \underline{\mathcal{M}}_\kappa > 0, \quad |\mathcal{M}_{T_I}(t)| \geq \underline{\mathcal{M}}_{T_I} > 0,$$

$$|\mathcal{M}_{x_{\delta 0}}(t)| \geq \underline{\mathcal{M}}_{x_{\delta 0}} > 0.$$

Proof of Lemma 2 is given in Supplementary material [20].

Remark 3. *The elements of the matrices $\mathcal{G}(\psi_{ab})$, $\mathcal{P}(\theta)$, $\mathcal{R}(\theta)$ are handpicked as the denominators of the mappings $\mathcal{F}(\psi_{ab})$, $T_I(\theta)$, $\psi_d(\theta)$, respectively. In their turn, $\mathcal{S}(\psi_{ab})$, $\mathcal{Q}(\theta)$, $\mathcal{W}(\theta)$ are obtained as the result of direct multiplication – see their definitions in (17)–(19).*

B. Adaptive Observer Design

Based on the regression equations (20)–(22) obtained in section 3.1 and using parameterizations (8)–(12), the estimates of states and external disturbances are obtained as:

$$\hat{x}(t) = \hat{T}_I(t) \hat{\xi}(t) = \hat{T}_I(t) \left(z(t) + \hat{R}^\top(t) \hat{\kappa}(t) \right),$$

$$\hat{\delta}(t) = h_\delta^\top \Phi_\delta(t) \hat{x}_{\delta 0}(t), \quad (24)$$

$$\hat{U}(t) = A_K \hat{U}(t) + I_n \hat{\delta}(t), \quad \hat{U}(t_0) = 0_{n \times n},$$

where $\hat{R}^T(t) = [\Omega(t) \ P(t) \ \hat{U}(t)]$, and estimates $\hat{\kappa}(t)$, $\hat{T}_I(t)$, $\hat{x}_{\delta 0}(t)$ are obtained with the help of the following differential equations:

$$\begin{aligned} \dot{\hat{\kappa}}(t) &= \dot{\tilde{\kappa}}(t) = -\gamma_{\kappa} \mathcal{M}_{\kappa}(t) (\mathcal{M}_{\kappa}(t) \hat{\kappa}(t) - \mathcal{Y}_{\kappa}(t)), \\ \dot{\hat{x}}_{\delta 0}(t) &= \dot{\tilde{x}}_{\delta 0}(t) = \\ &= -\gamma_{x_{\delta 0}} \mathcal{M}_{x_{\delta 0}}(t) (\mathcal{M}_{x_{\delta 0}}(t) \hat{x}_{\delta 0}(t) - \mathcal{Y}_{x_{\delta 0}}(t)), \end{aligned} \quad (25)$$

$$\begin{aligned} \dot{\hat{T}}_I(t) &= \dot{\tilde{T}}_I(t) = -\gamma_{T_I} \mathcal{M}_{T_I}(t) (\mathcal{M}_{T_I}(t) \hat{T}_I(t) - \mathcal{Y}_{T_I}(t)), \\ \gamma_{\kappa} &> 0, \gamma_{x_{\delta 0}} > 0, \gamma_{T_I} > 0, \end{aligned}$$

where $\tilde{\kappa}(t) = \hat{\kappa}(t) - \kappa(\theta)$, $\tilde{x}_{\delta 0}(t) = \hat{x}_{\delta 0}(t) - x_{\delta 0}$, $\tilde{T}_I(t) = \hat{T}_I(t) - T_I(\theta)$ are parametric errors.

With the stated goal (5) in mind, the properties of the adaptive observer (24), (25) are analyzed in Theorem.

Theorem. *Let Assumptions 1 and 2, condition (16) and Hypotheses (17)-(19) be met, then, if $\bar{\varphi}(t) \in \text{FE}$ and $(h_{\delta}^T \Phi_{\delta}(t) \otimes I_n) \in \text{FE}$, the observer (24), (25) ensures that the goal (5) is achieved and additionally guarantees that:*

$$\begin{aligned} \lim_{t \rightarrow \infty} \|\tilde{x}_{\delta 0}(t)\| &= 0 \text{ (exp)}, \quad \lim_{t \rightarrow \infty} \|\tilde{\kappa}(t)\| = 0 \text{ (exp)}, \\ \lim_{t \rightarrow \infty} \|\tilde{T}_I(t)\| &= 0 \text{ (exp)}, \\ \lim_{t \rightarrow \infty} \|\hat{U}(t) - U(t)\| &= \lim_{t \rightarrow \infty} \|\tilde{U}(t)\| = 0 \text{ (exp)}. \end{aligned} \quad (26)$$

Proof of Theorem is given in Supplementary material [20].

Thus, to solve the problem (5), first of all, using the signals measured from system (3) and transformations (13)-(15), the regression equations (11), (12) are formed w.r.t. the unknown parameters $\eta(\theta)$ and states $\xi(t)$ of the observer canonical form (6). After that, if conditions (16)-(19) of polynomial overparametrization of system (3) are met, then the obtained regression equation is transformed via (20)-(22) into linear regression equations w.r.t. similarity matrix $T_I(\theta)$, parameters $\kappa(\theta)$ and initial conditions $x_{\delta 0}$, respectively. Then, based on the obtained regression equations, the identification laws (25) are derived, and an algebraic state observer (24) is introduced. In accordance with the results of the theorem, the obtained observer guarantees that the goal (5) is achieved if extremely weak conditions $\bar{\varphi}(t) \in \text{FE}$ and $(h_{\delta}^T \Phi_{\delta}(t) \otimes I_n) \in \text{FE}$ are met. Moreover, the condition $\bar{\varphi}(t) \in \text{FE}$ can be: *i)* verified online by checking that eigenvalues of $\varphi(t)$ are non-zero, *ii)* met by dither signal injection, and the condition $(h_{\delta}^T \Phi_{\delta}(t) \otimes I_n) \in \text{FE}$ can be verified offline because signal $h_{\delta}^T \Phi_{\delta}(t)$ is *a priori* known in accordance with Assumption 2.

IV. NUMERICAL EXPERIMENTS

The system from the experimental section of [18] has been considered:

$$\begin{aligned} \dot{x} &= \begin{bmatrix} 0 & \theta_1 + \theta_2 & 0 \\ -\theta_2 & 0 & \theta_2 \\ 0 & -\theta_3 & 0 \end{bmatrix} x + \begin{bmatrix} 0 \\ 0 \\ \theta_3 \end{bmatrix} u + \begin{bmatrix} \theta_1 \theta_2 \\ 0 \\ 0 \end{bmatrix} \delta, \\ y &= [0 \ 0 \ 1] x. \end{aligned} \quad (27)$$

Being transformed into the observer canonical form (6), the system (27) was described by the following vectors:

$$\psi_a = \begin{bmatrix} 0 \\ -(\theta_1 + \theta_2 + \theta_3) \theta_2 \\ 0 \end{bmatrix}, \quad \psi_b = \begin{bmatrix} \theta_3 \\ 0 \\ \theta_3 \theta_2 (\theta_2 + \theta_1) \end{bmatrix}, \\ \psi_d = [0 \ 0 \ \theta_1 \theta_2^2 \theta_3]^T$$

where

$$\psi_{ab}(\theta) = \text{col} \{ -(\theta_1 + \theta_2 + \theta_3) \theta_2, \theta_3, \theta_3 \theta_2 (\theta_2 + \theta_1) \}.$$

The exosystem (4) parameters were set as:

$$\mathcal{A}_{\delta} = \begin{bmatrix} 0 & 1 \\ -10 & -0.01 \end{bmatrix}, \quad h_{\delta}^T = [1 \ 0].$$

The transformations $\mathcal{T}_i(\cdot)$, $i \in \{\mathcal{S}, \mathcal{G}, \mathcal{P}, \mathcal{Q}, \mathcal{R}, \mathcal{W}\}$ were implemented as (for more details see [16]–[18]):

$$\begin{aligned} \mathcal{T}_{\mathcal{S}}(\bar{\Xi}_{\mathcal{S}}(\Delta) \mathcal{Y}_{ab}) &= \begin{bmatrix} \mathcal{Y}_{2ab}(\mathcal{Y}_{1ab} \mathcal{Y}_{2ab} + \Delta \mathcal{Y}_{3ab})^2 - \mathcal{Y}_{2ab}^4 \mathcal{Y}_{3ab} \\ -\mathcal{Y}_{1ab} \mathcal{Y}_{2ab} - \Delta \mathcal{Y}_{3ab} \\ \mathcal{Y}_{2ab} \mathcal{Y}_{1ab} \end{bmatrix}, \\ \mathcal{T}_{\mathcal{G}}(\bar{\Xi}_{\mathcal{G}}(\Delta) \mathcal{Y}_{ab}) &= \text{diag} \left\{ \begin{array}{c} \mathcal{Y}_{2ab}^3 (\mathcal{Y}_{1ab} \mathcal{Y}_{2ab} + \Delta \mathcal{Y}_{3ab}), \\ \mathcal{Y}_{2ab}^2, \\ \Delta \mathcal{Y}_{1ab} \end{array} \right\}, \\ \mathcal{T}_{\mathcal{Q}}(\bar{\Xi}_{\mathcal{Q}}(\mathcal{M}_{\theta}) \mathcal{Y}_{\theta}) &= \begin{bmatrix} -\mathcal{Y}_{2\theta} (\mathcal{Y}_{1\theta} + \mathcal{Y}_{2\theta}) & 0 & \mathcal{M}_{\theta}^2 \\ 0 & -\mathcal{M}_{\theta} & 0 \\ \mathcal{M}_{\theta} & 0 & 0 \end{bmatrix}, \end{aligned}$$

$$\mathcal{T}_{\mathcal{P}}(\bar{\Xi}_{\mathcal{P}}(\mathcal{M}_{\theta}) \mathcal{Y}_{\theta}) = \text{diag} \{ \mathcal{Y}_{2\theta} \mathcal{Y}_{3\theta}, \mathcal{Y}_{3\theta}, \mathcal{M}_{\theta} \},$$

$$\mathcal{T}_{\mathcal{W}}(\bar{\Xi}_{\mathcal{W}}(\mathcal{M}_{\theta}) \mathcal{Y}_{\theta}) = \begin{bmatrix} 0 \\ 0 \\ \mathcal{Y}_{1\theta} \mathcal{Y}_{2\theta}^2 \mathcal{Y}_{3\theta} \end{bmatrix},$$

$$\mathcal{T}_{\mathcal{R}}(\bar{\Xi}_{\mathcal{R}}(\mathcal{M}_{\theta}) \mathcal{Y}_{\theta}) = \text{diag} \{ 1, 1, \mathcal{M}_{\theta}^4 \}.$$

The control signal was defined as a P-controller $u = -75(r - y)$. The reference signal r and parameters of the system (27) were chosen as:

$$\begin{aligned} r &= 100 + 2.5e^{-\int_{t_{\epsilon}}^t 1d\tau} \sin(10t), \\ \theta_1 &= \theta_2 = 1, \theta_3 = -1. \end{aligned} \quad (28)$$

The initial conditions of the system (27), (4), parameters of filters (13)-(15), (23) and identification laws (25) were set as:

$$\begin{aligned} K &= [3 \ 3 \ 1]^T, \quad G = \begin{bmatrix} -4 & 1 \\ -2 & 0 \end{bmatrix}, \quad l = \begin{bmatrix} 1 \\ 2 \end{bmatrix}, \quad \beta = \begin{bmatrix} 20 \\ -8 \end{bmatrix}, \\ x_0 &= [-1 \ 0 \ 2]^T, \quad x_{\delta 0} = [500 \ 100]^T, \\ \hat{\kappa}(0) &= 0_9, \quad \hat{T}_I(0) = 0_{3 \times 3}, \\ \hat{x}_{\delta 0}(0) &= 0_2, \quad k_1 = 25, \quad k = 10^{19}, \quad \sigma = 1, \quad t_{\epsilon} = 25, \\ \gamma_{x_{\delta 0}} &= 5 \cdot 10^{-82}, \quad \gamma_{\kappa} = 10^{-74}, \quad \gamma_{T_I} = 10^{-23}. \end{aligned}$$

The parameters of the adaptive laws (25) were chosen so as to ensure rate of convergence, which coincided with the one for the adaptive laws in [18].

Figure 1 for all $t \geq 25$ depicts transients of $\tilde{x}(t)$ and $\tilde{\delta}(t)$ for experiments when the observer (24) and the one from [18] were used.




Fig. 1. Behavior of state $\tilde{x}(t)$ and disturbance $\tilde{\delta}(t)$ observation errors




Fig. 2. Behavior of $\|\tilde{U}(t)\|$ and parametric errors $\tilde{\kappa}(t)$, $\tilde{x}_{\delta 0}(t)$, $\tilde{T}_I(t)$

Figure 2 for all $t \geq 25$ presents transients of parametric errors $\tilde{\kappa}(t)$, $\tilde{x}_{\delta 0}(t)$, $\tilde{T}_I(t)$ and the norm $\|\tilde{U}(t)\|$.

Therefore, when the parameter identification process had been completed, the unmeasured state and disturbance observation errors exponentially converged to zero. As the estimates were obtained using the algebraic equations (24), then, in comparison with the observer from [18], there was no significant overshoot in the course of the transients.

V. CONCLUSION

For a class of uncertain linear time-invariant over-parametrized systems an extended adaptive observer was proposed that, if the regressor finite excitation condition held, allowed one to reconstruct unmeasured states and bounded external disturbance generated by a known linear exosystem with unknown initial conditions.

In contrast to solutions [2], [3], [8], [10], [13], [14], the proposed observer: *i*) allowed one to reconstruct physical states $x(t)$ of the system (3) rather than virtual ones $\xi(t)$ of the observer canonical form (6), *ii*) provided exponential convergence of the unmeasured state and disturbance observation errors if the regressor finite excitation condition

was met. In contrast to the earlier result [18], the proposed adaptive observer: (a) formed unmeasured states and external perturbation estimates using the algebraic rather than the differential equation, and (b) was not affected by the peaking phenomenon (significant overshoot in the course of transients of $\tilde{x}(t)$ and $\tilde{\delta}(t)$).

REFERENCES

- [1] Bernard P., Andrieu V., Astolfi D., "Observer design for continuous-time dynamical systems," Annual Reviews in Control, vol. 53, pp. 224–248, 2022.
- [2] Carroll R., Lindorff D., "An adaptive observer for single-input single-output linear systems," IEEE Transactions on Automatic Control, vol. 18, no. 5, pp. 428–435, 1973.
- [3] Luders G., Narendra K. S., "An adaptive observer and identifier for a linear system," IEEE Transactions on Automatic Control, vol. 18, no. 5, pp. 496–499, 1973.
- [4] Zhang Q., Delyon B., "A new approach to adaptive observer design for MIMO systems," Proceedings of the 2001 American Control Conference, vol. 2, pp. 1545–1550, 2001.
- [5] Kazantzis N., Kravaris C., "Nonlinear observer design using Lyapunov's auxiliary theorem," Systems & Control Letters, vol. 34, no. 5, pp. 241–247, 1998.
- [6] Ortega R., Bobtsov A., Nikolaev N., Schiffer J., Dochain D., "Generalized parameter estimation-based observers: Application to power systems and chemical–biological reactors," Automatica, vol. 129, pp. 109635, 2021.
- [7] Bobtsov A., Ortega R., Yi B., Nikolaev N., "Adaptive state estimation of state-affine systems with unknown time-varying parameters," International Journal of Control, vol. 95, no. 9, pp. 2460–2472, 2022.
- [8] Zhang Q., "Adaptive observer for multiple-input-multiple-output (MIMO) linear time varying systems," IEEE Transactions on Automatic Control, vol. 47, no. 3, pp. 525–529, 2002.
- [9] Zhang Q., "Revisiting different adaptive observers through a unified formulation," in Proc. 44th Conference on Decision and Control, pp. 3067–3072, 2005.
- [10] Kreisselmeier G., "Adaptive observers with exponential rate of convergence," IEEE Transactions on Automatic Control, vol. 22, no. 1, pp. 2–8, 1977.
- [11] Marino R., Tomei P., "Adaptive observers with arbitrary exponential rate of convergence for nonlinear systems," IEEE Transactions on Automatic Control, vol. 40, no. 7, pp. 1300–1304, 1995.
- [12] Marino R., Santosuosso G. L., Tomei P., "Robust adaptive observers for nonlinear systems with bounded disturbances," IEEE Transactions on Automatic Control, vol. 46, no. 6, pp. 967–972, 2001.
- [13] Katiyar A., Roy S. B., Bhasin S., "Initial Excitation Based Robust Adaptive Observer for MIMO LTI Systems," IEEE Transactions on Automatic Control, 2022. Early access.
- [14] Bobtsov A., Pyrkin A., Vedyakov A., Vediakova A., Aranovskiy S., "A Modification of Generalized Parameter-Based Adaptive Observer for Linear Systems with Relaxed Excitation Conditions," in IFAC PapersOnLine, vol. 55, no. 12, pp.324–329, 2022.
- [15] Szabat K., Orłowska-Kowalska T., "Vibration suppression in a two-mass drive system using PI speed controller and additional feedbacks – Comparative study," IEEE Transactions on Industrial Electronics, vol. 54, no. 2, pp.1193–1206, 2007.
- [16] Glushchenko A., Lastochkin K., "Exponentially Stable Adaptive Observation without System Representation in Observable Form," arXiv preprint arXiv:2212.08405, pp.1–6, 2022.
- [17] Glushchenko A., Lastochkin K., "Parameter Estimation-Based Observer for Linear Systems with Polynomial Overparametrization," arXiv preprint arXiv:2301.07342, pp.1–6, 2023.
- [18] Glushchenko A., Lastochkin K., "Extended Adaptive Observer for Linear Systems with Overparametrization," arXiv preprint arXiv:2301.06169, pp.1–5, 2023.
- [19] Nikiforov V. O., "Observers of external deterministic disturbances. II. Objects with unknown parameters," Automation and Remote Control, vol. 65, no.11, pp.1724–1732, 2004.
- [20] Glushchenko A., Lastochkin K., "Supplement to "Parameter Estimation-Based Extended Observer for Linear Systems with Polynomial Overparametrization," arXiv preprint arXiv:2302.13705, pp.1–6, 2023. https://arxiv.org/src/2302.13705v3/anc/CDC_PBB0_supp.pdf.