

RESEARCH ARTICLE

Sparse Feedback Controller: From Open-loop Solution to Closed-loop Realization

Zhicheng Zhang and Yasumasa Fujisaki

Graduate School of Information Science and Technology, Osaka University, Japan

ARTICLE HISTORY

Compiled March 28, 2023

ABSTRACT

In this paper, we explore the discrete time sparse feedback control for a linear invariant system, where the proposed optimal feedback controller enjoys input sparsity by using a dynamic linear compensator, i.e., the components of feedback control signal having the smallest possible nonzero values. The resulting augmented dynamics ensures closed-loop stability, which infers sparse feedback controller from open-loop solution to closed-loop realization. In particular, we show that the implemented sparse feedback (closed-loop) control solution is equivalent to the original sparse (open-loop) control solution under a specified basis. We then extend the dynamic compensator to a feedforward tracking control problem. Finally, numerical examples demonstrate the effectiveness of proposed control approach.

KEYWORDS

input sparsity; dynamic linear compensator; closed-loop solution; tracking control

1. Introduction

Sparse control is closely related to sparse optimization [1], which penalizes sparsity on controller so as to schedule resource-aware allocation. In control design, the sparsity-promoting idea has thrived in various directions to distributed control [2–4], tracking control [5], and predictive control [6–8]. When the sparsity is imposed on the control structure (i.e., structured sparsity) whose controller depends on a *static* state feedback [9–11], then the sparse control is recast into a distributed control, which attempts to *reduce the number of communication links* [2] in networked control system. An appealing alternative is to penalize sparsity on control signal (i.e., input sparsity) to implement a sparse control that *maximizes the time duration over which the control value is exactly zero* [12]. In this paper, we are interested in the generation of control signal, which emphasizes on the latter sparse control, namely, reducing control effort or fuel consumption, also known as “ ℓ_1 optimal control” or “maximum hands-off control” [6,13].

The optimal control design of sparse input is of great significance for control system and directly affects the dynamic process of the system. Many practical systems of interest are dependent on a feedback mechanism to achieve closed-loop stability. However, closed-loop realization is more challenging to *optimal control problem* because *determining the feedback gain (matrix)* is a non-trivial task [14]. Indeed, in

closed-loop sparse control scenarios, almost all existing literature has been focused on discussing “structured sparsity” by optimizing linear quadratic state feedback cost [2–4,9–11] rather than pursuing our expected sparse control inputs (i.e., ℓ_1 optimal control) [6,15]. Furthermore, most successful stories on sparse control taking ℓ_1 cost of discrete and continuous systems have been extensively treated in *open-loop solutions* [6,12,13,16]. These recent advances motivate us to study the *closed-loop ℓ_1 optimal control* problem.

Although “real-time control” bridges the gap between the open-loop and closed-loop solutions, schemes such as self-triggered sparse control [12, Sec. VI] and sparse predictive control [6–8,17] can, and often do, emerge feedback solutions. On the other hand, these iterative feedback algorithms perform *online optimization*, leading to the computationally burden, especially when the decision variable is high dimension. Neither exploring sparsity on the structure of feedback gain matrix or exploiting real-time control, we immediately promotes sparsity on the control inputs with a closed-loop response, called *sparse feedback control realization*. Inspired by seminal works [14,18], a relatively optimal control technique paves the way towards the open-loop solution to the closed-loop solution by means of linear implementation.

In this paper, we focus on sparse feedback control design for a discrete linear time invariant system, where the controller is *linear dynamic*, and enjoys sparse control input to achieve feedback realization. We become aware of the result in [19] that induces a desired sparse control input by taking a *row-sparsity* on the *static* state feedback gain, which implies a structured sparsity on channels. In contrast, we here leverage a *dynamic state feedback* controller and keep the standard optimal control framework. We believe that such a direct sparse optimization of control signal is more convenient to synthesizing sparse feedback control. One of its benefits is that it relies solely on *offline optimization*. Thus, the proposed controller can often offer a significant computational saving and control effort minimization. Encouraged by simple theoretical and numerical results by a position paper [20] of the present authors, we extend the results to a more comprehensive version, including problem setup, proofs, tracking control, and simulations. The main contributions of this article are summarized as follows.

- This paper breaks into a paradigm in which feedback realization of sparse optimal control is always possible following the implementation of a *dynamic linear compensator*. Besides, we propose the computationally tractable analytical and explicit feedback solution for the sparse control problem (Problems 1 and 2).
- We provide the stability, optimality, and sparsity for the closed-loop augmented system, and display that the designed sparse feedback control is essentially a deadbeat control (Theorem 3.1 and Corollary 3.3).
- In particular, we show that an equivalence for the open-loop sparse control and the closed-loop sparse control under a specified basis (Corollary 3.2).
- Furthermore, we demonstrate that the sparse feedback control can in fact be extended successfully for tracking problem (Lemma 4.1 and Proposition 4.2).

This paper is organized as follows. In Section 2, we introduce the problem formulation and the basic preliminaries. Section 3 gives the main result for stabilizing sparse feedback control using a dynamic linear compensator, which can be divided into two steps, that is, sparse optimization and feedback realization, respectively. Section 4 extends the result to a tracking problem by devising a dynamic tracking controller. The numerical examples are illustrated in Section 5. Section 6 concludes this paper.

Notation. Throughout this paper, let \mathbb{R} , \mathbb{R}^n , and $\mathbb{R}^{n \times m}$ denote the sets of real numbers, n dimension of real vectors, and $n \times m$ size real matrices, respectively. We

use I_n (or 0_n) to denote the identity (or zero) matrix of size $n \times n$, $0_{n \times m}$ to denote the zero matrix of size $n \times m$; and for brevity, we sometimes abbreviate I (or 0) to represent the identify (or zero) matrix with appropriate size. Let $\mathbf{1}_n = [1 \ \cdots \ 1]^\top \in \mathbb{R}^n$ be the all one vector, and $e_i \in \mathbb{R}^n$ stands for an n -tuple basis vector whose all entries equal to 0, except the i th, which is 1. Given a vector $x = [x_1 \ x_2 \ \cdots \ x_n]^\top \in \mathbb{R}^n$, we define the ℓ_1 and ℓ_2 norms, respectively, by $\|x\|_1 = \sum_{i=1}^n |x_i|$, $\|x\|_2 = \sqrt{\sum_{i=1}^n |x_i|^2}$. Similarity, the ℓ_1 norm of a matrix $X \in \mathbb{R}^{n \times m}$ is defined by $\|X\|_1 = \sum_{i=1}^n \sum_{j=1}^m |x_{ij}|$.

2. Problem formulation

2.1. Review of sparse optimal control

Consider a discrete linear time invariant (LTI) system described by

$$\begin{aligned} x(t+1) &= Ax(t) + Bu(t), & x(0) &= x_0, \\ y(t) &= Cx(t) + Du(t), \end{aligned} \tag{1}$$

where $u(t) \in \mathbb{R}^m$ is the control input with $m \leq n$, $x(t) \in \mathbb{R}^n$ is the state with an initial value x_0 , $y(t) \in \mathbb{R}^p$ is the output, and A , B , C , and D are real constant matrices of appropriate sizes. Throughout this paper, we assume that the pair (A, B) is *reachable*.

In this paper, we are interested in sparse optimal control problem, and the control objective is to seek a control sequence $\{u(0), u(1), \dots, u(N-1)\}$ such that it drives the resultant state $x(t)$ from an initial state $x(0) = x_0$ to the origin in a finite N steps (i.e., zero terminal state $x(N) = 0$) with minimum or sparse control effort.

As indicated in [1], a common method for generating sparse solution is to minimize an ℓ_1 norm *convex optimization* subject to constraints. In our context, we shift the idea from compressed sensing to sparse control problem, which seeks an ‘‘open-loop’’ ℓ_1 optimal control action u^* in control system [6,13] defined as

$$u^* = \arg \min_{u \in \mathcal{U}} \|u\|_1 = \arg \min_{u \in \mathcal{U}} \sum_{i=1}^m \sum_{t=0}^{N-1} |u_i(t)|, \tag{2}$$

where $u = [u^\top(0) \ u^\top(1) \ \cdots \ u^\top(N-1)]^\top \in \mathbb{R}^{mN}$, and $\|u\|_1$ indicates the ℓ_1 norm of input vector u that sums the absolute values of its elements. Meanwhile, a feasible control set is described by $\mathcal{U} = \{u \in \mathbb{R}^{mN} : \Phi_N u = -A^N x_0\}$, in which $\Phi_N \doteq [A^{N-1}B \ \cdots \ AB \ B] \in \mathbb{R}^{n \times mN}$ is an N step reachability matrix and satisfies $\text{rank}(\Phi_N) = n$ (i.e., full row rank). Occasionally, the state and input constraints are necessarily taken into account, for instance, $y(t) \in \mathcal{Y} \subseteq \mathcal{U}$, where \mathcal{Y} is a convex and closed set. Besides, the horizon N should be sufficiently long so that the admissible control set \mathcal{U} is *nonempty*.

2.2. Dynamic linear compensator

In this paper, a compensator \mathcal{K} which we intend to design is a *dynamic* and *linear* state feedback controller

$$\mathcal{K} : \begin{aligned} z(t+1) &= Fz(t) + Gx(t), & z(0) &= 0, \\ u(t) &= Hz(t) + Kx(t), \end{aligned} \tag{3}$$

where $z(t)$ is the state of the compensator and F , G , H , and K are real matrices of compatible sizes. Note that we set the initial state $z(0)$ of the compensator as *zero* (i.e., $z(0) = 0$). The advantages of such a dynamic compensator \mathcal{K} (3) are threefold. First, it brings a *linear dynamic* fashion to the sparse feedback controller that is computationally tractable for compensator's gain matrices. Second, it promotes *input/temporal* sparsity [6,12,13] rather than the structured/spatial sparsity for the controller [2–4,9–11]. Correspondingly, we refer the designed sparse feedback control to as “maximum hands-off feedback control” or “closed-loop ℓ_1 optimal control”. Finally, it ensures an internally *stability* of the studied closed-loop system.

3. Sparse feedback control realization

In this section, we focus on optimal sparse feedback control synthesis *from open-loop solution to closed-loop realization*. Determining the explicit matrices of F, G, H, K for dynamic compensator (3) is of primary interest in designing sparse feedback controller.

3.1. Closed-loop augmented system

In the celebrated works [14,18], the authors performed the linear implementation built from the relatively optimal technique. This oracle suggests us to investigate an augmented closed-loop system composed of the discrete dynamics (1) and the dynamic compensator (3) of the form

$$\begin{aligned} \psi(t+1) &= (\mathcal{A} + \mathcal{BK})\psi(t), & \psi(0) &= \psi_0, \\ y(t) &= (\mathcal{C} + \mathcal{DK})\psi(t), \end{aligned} \tag{4}$$

where the corresponding state and the gain matrices are given by

$$\begin{aligned} \psi(t) &\doteq \begin{bmatrix} x(t) \\ z(t) \end{bmatrix}, & \psi_0 &\doteq \begin{bmatrix} x_0 \\ 0 \end{bmatrix} \\ \mathcal{A} &= \begin{bmatrix} A & 0 \\ 0 & 0 \end{bmatrix}, & \mathcal{B} &= \begin{bmatrix} B & 0 \\ 0 & I \end{bmatrix}, & \mathcal{K} &= \begin{bmatrix} K & H \\ G & F \end{bmatrix}, \\ \mathcal{C} &= [C \ 0], & \mathcal{D} &= [D \ 0]. \end{aligned}$$

To utilize the dynamic compensator \mathcal{K} in a compact way, we accordingly introduce a stable matrix $P \in \mathbb{R}^{N \times N}$, which is an N -Jordan block associated with 0 eigenvalue, defined by

$$P = \begin{bmatrix} 0 & 0 \\ I_{N-1} & 0 \end{bmatrix}. \tag{5}$$

In what follows, we devote to realizing the sparse feedback control by using a dynamic linear compensator (3), which can be divided into two steps. The first step is to address a constrained *sparse optimization*. Subsequently, the second procedure is to carry out a *feedback realization*.

Let us first revise ℓ_1 optimal control problem by sparse optimization, which stems from an open-loop sparse control program (2) discussed in [6,13]. Different from the above results, we further consider a more general scenario, where the initial condition

is extended to be simultaneously satisfied for all initial state $x_0 \in \{e_1, e_2, \dots, e_n\}$ so as to generate all n possible input-state trajectories, here $e_i \in \mathbb{R}^N$, $i = 1, \dots, n$ is the so-called standard basis vector, for instance, $e_1 = [1 \ 0 \ \dots \ 0] \in \mathbb{R}^N$. As a result, the initial state x_0 is not fixed in advance when we design the controller \mathcal{K} , but the desired steady-state value is a priori knowledge taking $\psi_\infty = 0$.

In addition, we impose the state and input (or output) constraints on the control system (1) as

$$y(t) \in \mathcal{Y}, \quad \forall x_0 \in \{e_1, e_2, \dots, e_n\}, \quad (6)$$

where $\mathcal{Y} = \{y \in \mathbb{R}^p : -s \leq y(t) \leq s\}$ is a convex and compact set and $s \in \mathbb{R}^p$ dominates the magnitudes of the state and input.

Based on the previous setup, we formulate the constrained sparse optimal control problem as the following sparse optimization.

Problem 1 (Sparse Optimization). Find the matrices $X \in \mathbb{R}^{n \times nN}$ and $U \in \mathbb{R}^{m \times nN}$ such that the obtained U is sparse, which amounts to solve a constrained ℓ_1 norm input matrix optimization

$$\begin{aligned} \min_{X, U} \quad & \|U\|_1 \\ \text{s.t.} \quad & AX + BU = X(P \otimes I_n), \\ & I_n = X(e_1 \otimes I_n), \\ & \text{abs}(CX + DU) \leq s(\mathbf{1}_n \otimes \mathbf{1}_N)^\top, \end{aligned}$$

where $\text{abs}(\cdot)$ returns the absolute value of each element in a matrix.

It is mentioned that Problem 1 is a convex optimization, and hence the solution is computationally tractable by means of the off-the-shelf packages, such as CVX [21] or YALMIP [22] in MATLAB. Once the open-loop optimal solution (X, U) of Problem 1 is attained, we then proceed the second step, that is to say, we move on to tackling the following sparse feedback realization problem.

Problem 2 (Feedback Realization). Based on the solution (X, U) of Problem 1, solve a linear equation

$$\begin{bmatrix} K & H \\ G & F \end{bmatrix} \begin{bmatrix} X \\ Z \end{bmatrix} = \begin{bmatrix} U \\ V \end{bmatrix} \quad (7)$$

with respect to (K, H, G, F) and determine the compensator's gain matrices, where

$$Z = [0_{n(N-1) \times n} \quad I_{n(N-1)}], \quad V = Z(P \otimes I_n). \quad (8)$$

3.2. Stability analysis

The approach to sparse feedback control design makes use of the above discussed sparse optimization (Problem 1) and feedback realization (Problem 2), where the dynamic compensator ensures the internally stability of the closed-loop augmented system (4). The result is summarized in the following theorem and corollary.

Theorem 3.1 (Sparse Feedback Control Realization). *Suppose that Problem 1 has the minimizer (X, U) . Then the equation (7) has the unique solution (K, H, G, F) and the resulting compensator (3) with $z(0) = 0$ generates the input sequence $u(t) = U(e_{t+1} \otimes x_0)$, $t = 0, 1, \dots, N-1$, which drives the plant state $x(t)$ from $x(0) = x_0$ to $x(N) = 0$ under the output constraint (6). Furthermore, the closed-loop system (4) is internally stable.*

Proof. We first describe the matrices X and U as

$$\begin{aligned} X &= [X_0 \quad X_1 \quad \cdots \quad X_{N-1}], \\ U &= [U_0 \quad U_1 \quad \cdots \quad U_{N-1}], \end{aligned}$$

where $X_t \in \mathbb{R}^{n \times n}$, $U_t \in \mathbb{R}^{m \times n}$, and $t = 0, 1, \dots, N-1$. Notice that checking the second constraint of Problem 1 gives rise to the result $X_0 = I_n$. With this fact, it admits that the matrix Ψ is *non-singular*. In other words, we claim that

$$\det \Psi \neq 0, \quad \Psi = \begin{bmatrix} X \\ Z \end{bmatrix} = \begin{bmatrix} I_n & \vdots & X_1 & \cdots & X_{N-1} \\ \hline 0_{n(N-1) \times n} & \vdots & I_{n(N-1)} & & \end{bmatrix}. \quad (9)$$

Since the matrix Ψ is invertible, it follows that the equation (7) has the unique solution (K, H, G, F) associated with the dynamic compensator (3). Therefore, the augmented system (4) with dynamic feedback control (3) has an augmented closed-loop matrix

$$\mathcal{A}_{cl} = \mathcal{A} + \mathcal{B}\mathcal{K} = \begin{bmatrix} A & 0 \\ 0 & 0 \end{bmatrix} + \begin{bmatrix} B & 0 \\ 0 & I \end{bmatrix} \begin{bmatrix} K & H \\ G & F \end{bmatrix} = \begin{bmatrix} A + BK & BH \\ G & F \end{bmatrix}. \quad (10)$$

Meanwhile, the second constraint of Problem 1 with (7) asserts that

$$\begin{aligned} \mathcal{A}_{cl}\Psi &= \left(\begin{bmatrix} A & 0 \\ 0 & 0 \end{bmatrix} + \begin{bmatrix} B & 0 \\ 0 & I \end{bmatrix} \begin{bmatrix} K & H \\ G & F \end{bmatrix} \right) \begin{bmatrix} X \\ Z \end{bmatrix} \\ &= \begin{bmatrix} AX \\ 0 \end{bmatrix} + \begin{bmatrix} B & 0 \\ 0 & I \end{bmatrix} \begin{bmatrix} U \\ V \end{bmatrix} \\ &= \begin{bmatrix} AX + BU \\ V \end{bmatrix} \\ &= \begin{bmatrix} X \\ Z \end{bmatrix} (P \otimes I_n) \\ &= \Psi(P \otimes I_n), \end{aligned}$$

which implies that the closed-loop matrix $\mathcal{A}_{cl} = \Psi(P \otimes I_n)\Psi^{-1}$, so that it is similar to a nilpotent matrix $(P \otimes I_n)$, hence, the closed-loop system (4) is internally stable and the zero terminal state $x(N) = 0$ is achieved for any initial state $\psi(0)$ of the system.

Moreover, we see that the sequences $x(t) = X(e_{t+1} \otimes x_0) = X_t x_0$, $u(t) = U(e_{t+1} \otimes x_0) = U_t x_0$, and $z(t) = Z(e_{t+1} \otimes x_0) = Z_t x_0$ are indeed generated by the system (1) with $x(0) = x_0$ and the controller (3) with $z(0) = 0$. As a matter of fact, apparently $x(0) = X(e_1 \otimes x_0) = X_0 x_0 = x_0$ and $z(0) = Z(e_1 \otimes x_0) = 0$. Furthermore, based on the fact that $(P \otimes I_n)(e_{t+1} \otimes x_0) = e_{t+2} \otimes x_0$, we have

$$Ax(t) + Bu(t) = (AX + BU)(e_{t+1} \otimes x_0)$$

$$\begin{aligned}
&= X(P \otimes I_n)(e_{t+1} \otimes x_0) \\
&= X(e_{t+2} \otimes x_0) \\
&= x(t+1),
\end{aligned} \tag{11}$$

$$\begin{aligned}
Fz(t) + Gx(t) &= (FZ + GX)(e_{t+1} \otimes x_0) \\
&= Z(P \otimes I_n)(e_{t+1} \otimes x_0) \\
&= Z(e_{t+2} \otimes x_0) \\
&= z(t+1),
\end{aligned} \tag{12}$$

$$\begin{aligned}
Hz(t) + Kx(t) &= (HZ + KX)(e_{t+1} \otimes x_0) \\
&= U(e_{t+1} \otimes x_0) \\
&= u(t).
\end{aligned} \tag{13}$$

We next consider the third constraint of Problem 1, whose validity can be inspected by assessing the inequality

$$-\text{abs}(CX + DU) \leq CX + DU \leq \text{abs}(CX + DU)$$

holds true. Therefore, for a given vector $s \in \mathbb{R}^p$, we have that

$$\begin{aligned}
(CX + DU)(e_{t+1} \otimes x_0) &\leq \text{abs}(CX + DU)(e_{t+1} \otimes x_0) \\
&\leq s(\mathbf{1}_n \otimes \mathbf{1}_N)^\top (e_{t+1} \otimes x_0) = s.
\end{aligned} \tag{14}$$

Notice that $Cx(t) + Du(t) = (CX + DU)(e_{t+1} \otimes x_0) = y(t)$, then the output constraint of the form $\{-s \leq y(t) \leq s\}$ in (6) is verified.

According to the above arguments, we claim that the sequences (11), (12), (13), and (14) indeed satisfy the input-state trajectories of LTI dynamics (1) under output constraint (6), which proves the theorem for realizing sparse feedback control. \square

Remark 1 (Offline vs. Online). It is clear that realizing sparse feedback control in Theorem 3.1 is based on *offline computation*, and hence the computational complexity is low. Compared with sparse predictive control [6,8,17], a real-time feedback iterations is employed to ensure closed-loop dynamics and *online optimization* is repeatedly performed as a feedback controller to calculate sparse solutions. Beyond all doubt, predictive feedback control naturally leads to computational burden when the sizes of controlled system is high (e.g., the curse of dimensionality), even for using a fast ADMM (alternating direction method of multipliers) algorithm [6,7].

Based on the proposed Theorem 3.1, we can directly give a corollary that establishes the connection between the open-loop sparse optimal control solution and the closed-loop sparse optimal control solution.

Corollary 3.2 (Equivalence). *Suppose that Problem 1 has the minimizer (X, U) . Let $u_{\mathcal{K}}^*$ be optimal sparse feedback control (i.e., closed-loop ℓ_1 optimal control) solution using a dynamic linear compensator \mathcal{K} (3), and u^* be open-loop ℓ_1 optimal control solution u^* of program (2) with output constraint (6), respectively. Then, for $x_0 \in$*




Figure 1. Feedforward tracking control system: $r(t)$ is reference signal; $y(t)$ is the performance output which must track a specified reference input $r(t)$; “Comp” represents a dynamic tracking compensator (18) applied to a discrete LTI plant (1).

$\{e_1, e_2, \dots, e_n\}$, it holds that

$$u^* = u_{\mathcal{K}}^* = Hz + Kx^*. \quad (15)$$

Corollary 3.3. *Suppose that Problems 1 and 2 have solved, then the implemented sparse (dynamic state) feedback controller $u_{\mathcal{K}}^* = Hz + Kx^*$ (i.e., closed-loop ℓ_1 optimal control) of discrete LTI plant (1) is essentially an N -step deadbeat controller.*

Remark 2 (Relation to deadbeat control). Regarding the deadbeat control, since the designed compensator \mathcal{K} brings the state $x(t)$ to the origin in N steps (satisfying $x(N) = 0$), which places all of the eigenvalues of the augmented closed-loop system matrix \mathcal{A}_{cl} at the origin in the complex plane.

4. Extension: Tracking problem

In this section, we extend the above result of sparse feedback controller to tracking problem [23, Chapter 8], as shown in Figure 1. This construction reminds us to propose a tracking compensator \mathcal{K}_r that combines a dynamic state feedback control \mathcal{K} (3) and an additional reference signal r .

We start by giving a step-type reference signal $r(t) \in \mathbb{R}^p$ as

$$r(t) = \begin{cases} r_-, & t < 0 \\ r_+, & t \geq 0, \end{cases} \quad (16)$$

where $r_- \in \mathbb{R}^p$ and $r_+ \in \mathbb{R}^p$ are constant vectors. The purpose of tracking problem is to design a dynamic tracking compensator such that the performance output tracks a reference input with zero steady-state error by using additional feedforward gains. For this reason, we define the tracking error by $e(t) = y(t) - r(t)$ that satisfies $\lim_{t \rightarrow \infty} \|e(t)\|_2 = 0$, where $y(t)$ is a performance output signal stated in the plant (1). Meanwhile, we make the following assumption before giving an effective tracking controller.

Assumption 1. *For a tracking problem, assume that the performance output signal $y(t) \in \mathbb{R}^p$ and the control signal $u(t) \in \mathbb{R}^m$ in LTI dynamics (1) be of the same size (i.e., $p = m$) and take the matrix $D = 0_m$.*

It is known that the performance output $y(t) \in \mathbb{R}^m$ can track any reference signal

$r(t) \in \mathbb{R}^m$ of (16) in the steady-state if

$$\text{rank} \begin{bmatrix} I - A & B \\ C & 0 \end{bmatrix} = n + m. \quad (17)$$

As already reported in Section 3, an analogous dynamic tracking compensator \mathcal{K}_r can be applied to the discrete LTI plant (1) by adding a prescribed reference input $r(t) \in \mathbb{R}^m$ to the control actuator (3). To this end, a dynamic tracking compensator \mathcal{K}_r for the plant can be designed as

$$\mathcal{K}_r : \quad \begin{aligned} z_r(t+1) &= Fz_r(t) + Gx(t) + Lr(t), & z_r(0) &= 0, \\ u(t) &= Hz_r(t) + Kx(t) + Mr(t), \end{aligned} \quad (18)$$

where L and M represent the feedforward gain matrices with suitable sizes, and $r(t) \in \mathbb{R}^m$ is a specific reference input (16). Notice that here the initial value $z_r(0)$ of tracking compensator \mathcal{K}_r is set to zero (i.e., $z_r(0) = 0$).

With the addition of the above dynamic tracking compensator (18), the closed-loop behavior can be described in an augmented description

$$\begin{aligned} \psi_r(t+1) &= \mathcal{A}_{cl}\psi_r(t) + \mathcal{M}_r r(t), & \psi_r(0) &= \psi_{r0} \\ y(t) &= \mathcal{C}\psi_r(t), \end{aligned} \quad (19)$$

where

$$\psi_r(t) = \begin{bmatrix} x(t) \\ z_r(t) \end{bmatrix}, \quad \mathcal{A}_{cl} = \begin{bmatrix} A + BK & BH \\ G & F \end{bmatrix}, \quad \mathcal{M}_r = \begin{bmatrix} BM \\ L \end{bmatrix}, \quad \mathcal{C} = [C \ 0].$$

For a preferable reference input tracking, the control index requires *the difference or variation of the control inputs* taking $\{u(t+1) - u(t)\}_{t=0}^{N-1}$ to calibrate the tracking command, which is referred to as *minimum attention control* [24–26]. We slightly relax the constraints in Problem 1 by removing the state and input constraints (6) without loss of generality, resulting in the following control problem.

Problem 3 (Minimum Attention Control). Find the matrices $X \in \mathbb{R}^{n \times nN}$ and $U \in \mathbb{R}^{m \times nN}$ such that the obtained U solves a minimum attention control problem

$$\begin{aligned} \min_{X, U} \quad & \|U(P \otimes I_n) - U\|_1 \\ \text{s.t.} \quad & AX + BU = X(P \otimes I_n) \\ & I_n = X(e_1 \otimes I_n). \end{aligned}$$

Looking for the solution (X, U) of Problem 3 is always accessible because, the above problem is a convex program. Then, with (K, H, G, F) of (7) and (8), the resultant closed-loop system (19) always assures internal stability, that is, the condition $\mathcal{A}_{cl} = \Psi(P \otimes I_n)\Psi^{-1}$ holds, as discussed in Section 3.

We next deal with tracking problem.

Due to the fact that the closed-loop augmented system (19) is internally stable with matrices (K, H, G, F) , it admits a unique steady-state $\psi_\infty = [x_\infty^\top \ z_\infty^\top]^\top$ for a desired reference input $r_+ \doteq \lim_{t \rightarrow \infty} r(t)$.

More precisely, we have the following matrix equation

$$\begin{bmatrix} \psi_\infty \\ y_\infty \end{bmatrix} = \begin{bmatrix} \mathcal{A}_{cl} & \mathcal{M}_r \\ \mathcal{C} & 0 \end{bmatrix} \begin{bmatrix} \psi_\infty \\ r_+ \end{bmatrix}. \quad (20)$$

If $y_\infty = Cx_\infty = r_+$ for any reference r_+ , the output $y(t)$ tracks reference $r(t)$ with no steady-state tracking error. If $z_\infty = 0$ for any r_+ , we can have $z(0) = 0$ whenever the reference signal changes again after a steady-state is achieved.

In what follows, we are going to achieve tracking error elimination with $z_\infty = 0$ by assigning feedforward tracking gains M and L , leading to the following lemma.

Lemma 4.1 (Steady-State Tracking). *Supposed that Assumption 1 and rank condition (17) of steady-state tracking hold, and Problem 3 has the miniminer (X, U) . Then, the priori gain matrices (K, H, G, F) of compensator \mathcal{K}_r (18) can be uniquely determined by feedback realization (7) and (8). In addition, if the following conditions hold*

- (i) $\det(I - (A + BK)) \neq 0$,
- (ii) $\det(I - F) \neq 0$,

then the feedforward tracking gain matrices (M, L) in compensator \mathcal{K}_r (18) can be derived by

$$M = (C(I - (A + BK))^{-1}B)^{-1}, \quad (21)$$

$$L = -G(I - (A + BK))^{-1}BM. \quad (22)$$

Based on the obtained matrices (K, H, G, F, M, L) , for all initial state $x_0 \in \mathbb{R}^n$ and any reference $r_+ \in \mathbb{R}^m$, there exist the unique steady-state values (x_∞, z_∞) such that $y_\infty = r_+$ and $z_\infty = 0$ are achieved in the steady-state.

Proof. Since the gain matrices (K, H, G, F) can previously be calculated by (7) and (8), the augmented closed-loop system (19) is internally stable, as reported in Theorem 3.1. We here reformulate the augmented system (20) as

$$\begin{bmatrix} x_\infty \\ z_\infty \end{bmatrix} = \begin{bmatrix} A + BK & BH \\ G & F \end{bmatrix} \begin{bmatrix} x_\infty \\ z_\infty \end{bmatrix} + \begin{bmatrix} BM \\ L \end{bmatrix} r_+. \quad (23)$$

Suppose that the zero steady-state $z_\infty = 0$, we then have

$$x_\infty = (A + BK)x_\infty + BMr_+.$$

This implies that, if the matrix $I - (A + BK)$ is invertible,

$$x_\infty = (I - (A + BK))^{-1}BMr_+. \quad (24)$$

Therefore, we see the result $y_\infty = Cx_\infty = r_+$ if M is selected as (21).

On the other hand, the steady-state of the tracking compensator z_∞ in (23) satisfies

$$z_\infty = Gx_\infty + Fz_\infty + Lr_+.$$

Consequently, we derive

$$\begin{aligned} z_\infty &= (I - F)^{-1}(Gx_\infty + Lr_+) \\ &= (I - F)^{-1}(G(I - (A + BK))^{-1}BM + L)r_+ \end{aligned} \quad (25)$$

when the matrix $(I - F)$ is invertible. Thus, we see that $z_\infty = 0$ if the feedforward gain matrix L meets (22). Therefore, the feedforward gains (21) and (22) make error cancellation for achieving tracking. \square

Remark 3 (Illustrative conditions). Checking determinant conditions (i) and (ii) in Lemma 4.1 can be equivalently formulated as confirming the non-singular properties of the following matrices

$$I_n - X_1, \quad I_{n(N-1)} - \left[\begin{array}{c|c} -X_1 \cdots -X_{N-2} & -X_{N-1} \\ \hline I_{n(N-2)} & 0_{n(N-2) \times n} \end{array} \right], \quad (26)$$

hold or not, which establish the connects with optimal solution X to Problem 3. To see this, notice that $\mathcal{A}_{cl} = \Psi(P \otimes I_n)\Psi^{-1}$. Thus, the matrices $A + BK$ and F can be recast as

$$A + BK = X_1, \quad F = \left[\begin{array}{c|c} -X_1 \cdots -X_{N-2} & -X_{N-1} \\ \hline I_{n(N-2)} & 0_{n(N-2) \times n} \end{array} \right].$$

Proposition 4.2. *Under Assumption 1 and Lemma 4.1, the output $y(t)$ tracks reference $r(t)$ with no steady-state error via dynamic tracking compensator (18), where the tracking control input realizes minimum attention.*

5. Numerical simulations

In this section, we perform several numerical examples to illustrate the effectiveness of the designed sparse feedback control, which gives a closed-loop optimal solution by using a dynamic linear compensator.

5.1. Single input

Let us first consider a single-input control system modeled as a linearized cart-pole system, and the parameters benchmark are similar to [14, Sec. VI], in which the mass of the cart is 0.29 [kg], mass of the pole is 0.1 [kg], length of the pole is 1 [m], gravity acceleration is 9.81 [m/s²], and friction is neglected.

We then execute a time-discretization of this continuous system using zero-order-hold (ZoH) with sampling $\Delta t = 0.3$ [s], then the system matrices of form (1) are given by

$$A = \begin{bmatrix} 1 & 0.3 & 0.1377 & 0.0143 \\ 0 & 1 & 0.8256 & 0.1377 \\ 0 & 0 & 0.4628 & 0.2441 \\ 0 & 0 & -3.2198 & 0.4628 \end{bmatrix}, \quad B = \begin{bmatrix} 0.1514 \\ 0.9850 \\ -0.1404 \\ -0.8416 \end{bmatrix}.$$




Figure 2. Single input case: optimal sparse feedback control $u^*(t)$ (top) and the regarding optimal state trajectories $x^*(t)$ (bottom). The red dot line represents the constraint on the pole angle $|x_3| \leq 1$.

Meanwhile, the output matrices with respect to state-input constraints (6) are set to

$$C = \begin{bmatrix} 0 & 0 & 1 & 0 \\ 0 & 0 & 0 & 0 \end{bmatrix}, \quad D = \begin{bmatrix} 0 \\ 1 \end{bmatrix},$$

then we have $y^\top(t) = [x_3(t) \ u(t)]$, which means that the enforced constrained state is only third component of the state $x_3(t)$ and the imposed constrained input is $u(t)$. By selecting the suitable variable s , it gives state and input constraints as follows

$$|x_3(t)| \leq 1, \quad |u(t)| \leq 1.$$

Next, we simulate the discrete-time controlled system, the target is to drive the cart state from a non-zero initial state $x_0^\top = [0.9453, 0.7465, 0.7506, 0.4026]$ to the zero terminal state $x(N) = 0$ in a finite $N = 40$ steps (i.e, taking $T_{\text{final}} = (5 * N * \Delta t)/4 = 15$ [s] in a state-space representation). In order to realize the sparse feedback controller, we need to solve Problem 1 and Problem 2 to seek the closed-loop ℓ_1 optimal solution. By computing, the total CPU time in PC is 0.38 [s] in MATLAB R2020b using CVX [21], and the found optimal value $\|U^*\|_1 = 6.4204$.

Figure 2 illustrates the related closed-loop optimal input and state trajectories, respectively. It reflects the input sparsity on sparse feedback control, in which the control sequence is with less active components, and the optimal control meets constraint $|u(t)| \leq 1$. In addition, it plots the optimal state trajectories, where the pole angle x_3 fluctuates between the bounds -1 and 1 , satisfying the prescribed state constraint




Figure 3. The pattern of dynamic linear Compensator \mathcal{K} .




Figure 4. Multiple control inputs case: optimal sparse feedback control inputs $u_{\mathcal{K}}^*(t)$ (top) and the corresponding optimal state trajectories $x^*(t)$ (bottom).

$|x_3(t)| \leq 1$. Meanwhile, the trajectories of four different states start from an initial state x_0 and eventually converge to zero state as time tends to a fixed steps under the dynamic compensator (3), this implies that the closed-loop stabilization is achieved.

5.2. Multiple inputs numerical benchmark

As a second numerical simulation, we show the result that the synthesized dynamic controller (3) is useful for sparse feedback control of multi-input control system. We

here consider a discretized version of third-order system with two control inputs. Using a ZoH sampling time of $\Delta t = 0.1$ [s], the discrete system matrices are given by

$$A = \begin{bmatrix} 1.1133 & 0.0177 & -0.1478 \\ 0.0177 & 1.4517 & 0.2514 \\ 0.0418 & 0.2758 & 0.9208 \end{bmatrix}, \quad B = \begin{bmatrix} 0.0031 & 0.5218 \\ 0.0121 & 0.1486 \\ 0.0957 & 0.1202 \end{bmatrix},$$

and output matrices is chosen as $C = 0$ and $D = I$, which means that only the restriction on the control inputs $|u_i(t)| \leq 10$ by taking $s_i = 10$, $\forall i = 1, 2$. We now randomly generate initial data $x_0 \in [-1, 1]^3$ and each input channel of time length is $N = 4$, then the related final time in state-space is as $T_{\text{final}} = 0.5$ [s].

After the state-input matrix X and U were calculated (see (A.1) in Appendix), we obtained the optimal value $\|U^*\|_1 = 24.1544$. Due to the fact that the augmented matrix Ψ is invertible (9), then the dynamic linear compensator \mathcal{K} associated with real matrices (K, H, G, F) is computationally efficient. Figure 3 reveals the pattern of the compensator \mathcal{K} , in which the color-bar reports the level of real values of the correlation elements in matrix \mathcal{K} . In particular, Theorem 3.1 means that we require the knowledge of the matrices H and K (see (A.2) in Appendix) to synthesize the sparse feedback control as follows

$$\begin{aligned} u_{\mathcal{K}}^* &= Hz(t) + Kx^*(t) \\ &= \begin{bmatrix} 1.8798 & 0.0000 & -0.0000 & 2.8111 & 0.0000 & 0.0000 \\ -2.7970 & 0.0000 & -0.0000 & 1.7122 & -0.0000 & 0.0000 \end{bmatrix}. \end{aligned}$$

As shown in Figure 4, the optimal feedback control signals contain two components, where both control inputs are along the input constraints $|u_{\mathcal{K},i}(t)| \leq 10$, $\forall i = 1, 2$. Clearly, the synthesized feedback control sequences are sparse as desired. From this figure, it appears that the optimal state trajectories converge to zeros with minimum control effort.

5.3. Tracking problem

Finally, we show a numerical example to illustrate the effectiveness of our extended dynamic tracking compensator (18) in tracking problem (see Section 4). Let us consider a continuous second-order harmonic oscillator

$$\begin{aligned} \dot{x}(t) &= \begin{bmatrix} 0 & 1 \\ 1 & 0 \end{bmatrix} x(t) + \begin{bmatrix} -2 \\ 1 \end{bmatrix} u(t), \quad x(0) = \begin{bmatrix} 0.5 \\ -0.5 \end{bmatrix}, \\ y(t) &= \begin{bmatrix} 0 & 1 \end{bmatrix} x(t), \end{aligned}$$

and discretized it with a ZoH sampling with time period $\Delta t = 0.2$ [s]. The time step is set as $N = 5$. For convenience, we model a step reference signal (16) as $r_+ = 1$ for all $t \geq 0$. In this case, the default value of steady-state of reference is $r_+ = r_0 = 1$.

Focusing on the solution (X, U) determined by Problem 3, we then make use of the feedback realization technique to derive the feedback gain matrices (K, H, G, F) , where the relevant numerical results are shown in (A.3) in Appendix.

The problem at hand is to achieve tracking, we found that the determinants $\det(I - (A + BK)) = \det(I - X_1) = 0.2475 \neq 0$ and $\det(I - F) = 2.4902 \neq 0$, that is, the satisfaction of the two conditions in Lemma 4.1, and the related feedforward gains can




Figure 5. Minimum attention tracking control (i.e., the difference of control input) (top) and the tracking trajectories of performance y with respect to a step reference r (bottom).

be determined as

$$M = -3.0837, \quad L = [0.5 \quad -1 \quad 0 \quad 0 \quad 0 \quad 0]^\top.$$

Based on the above analysis, the implemented dynamic tracking compensator

$$\begin{aligned} u_{\mathcal{K}_r}^* &= Hz + Kx^* + Mr \\ &= [-3.6367 \quad -3.6367 \quad 4.4087 \quad 4.4087 \quad 0.5000 \quad 0.5000] \end{aligned}$$

can be easily applied to the discrete LTI plant so as to achieve tracking. Figure 5 depicts the evolution of minimum attention tracking control (top) and the corresponding tracking trajectories. It can be seen that the performance output signal $y(t)$ gradually tracks a step reference signal $r(t) = 1$ under the specified time steps.

6. Conclusion

In this paper, we have proposed a sparse feedback controller from open-loop solution to closed-loop realization. By means of implementing a dynamic linear compensator, the stability, optimality, and sparsity of the closed-loop ℓ_1 optimal control are ensured. Besides, we extended the result to a tracking problem to achieve the minimum attention control. Finally, the simulations illustrated the effectiveness of the proposed

sparse feedback control.

References

- [1] Donoho DL. Compressed sensing. *IEEE Trans Inform Theory*. 2006;52(4):1289–1306.
- [2] Jovanović MR, Dhingra NK. Controller architectures: Tradeoffs between performance and structure. *Eur J Contr*. 2016;30:76–91.
- [3] Matni N, Chandrasekaran V. Regularization for design. *IEEE Trans Automa Contr*. 2016; 61(12):3991–4006.
- [4] Furieri L, Zheng Y, Papachristodoulou A, et al. Sparsity invariance for convex design of distributed controllers. *IEEE Trans Contr Netw Syst*. 2020;7(4):1836–1847.
- [5] Zhang Z, Nagahara M. Linear quadratic tracking control with sparsity-promoting regularization. In: 2021 American Control Conference (ACC); IEEE; 2021. p. 3812–3817.
- [6] Nagahara M, Østergaard J, Quevedo DE. Discrete-time hands-off control by sparse optimization. *EURASIP J Adv Signal Proce*. 2016;2016(1):1–8.
- [7] Darup MS, Book G, Quevedo DE, et al. Fast hands-off control using ADMM real-time iterations. *IEEE Trans Autom Contr*. 2021;67(10):5416–5423.
- [8] Aguilera RP, Urrutia G, Delgado RA, et al. Quadratic model predictive control including input cardinality constraints. *IEEE Trans Autom Contr*. 2017;62(6):3068–3075.
- [9] Lin F, Fardad M, Jovanović MR. Design of optimal sparse feedback gains via the alternating direction method of multipliers. *IEEE Trans Autom Contr*. 2013;58(9):2426–2431.
- [10] Polyak B, Khlebnikov M, Shcherbakov P. An LMI approach to structured sparse feedback design in linear control systems. In: 2013 European control conference (ECC); IEEE; 2013. p. 833–838.
- [11] Babazadeh M, Nobakhti A. Sparsity promotion in state feedback controller design. *IEEE Trans Autom Contr*. 2016;62(8):4066–4072.
- [12] Nagahara M, Quevedo DE, Nešić D. Maximum hands-off control: a paradigm of control effort minimization. *IEEE Trans Automa Contr*. 2015;61(3):735–747.
- [13] Bakolas E. On the computation of sparse solutions to the controllability problem for discrete-time linear systems. *J Optim Theory Appl*. 2019;183(1):292–316.
- [14] Blanchini F, Pellegrino FA. Relatively optimal control and its linear implementation. *IEEE Trans Autom Contr*. 2003;48(12):2151–2162.
- [15] Caponigro M, Piccoli B, Rossi F, et al. Sparse Jurdjevic–Quinn stabilization of dissipative systems. *Automatica*. 2017;86:110–120.
- [16] Rao CV. Sparsity of linear discrete-time optimal control problems with l_1 objectives. *IEEE Trans Autom Contr*. 2017;63(2):513–517.
- [17] Iwata T, Oishi Y, Nagahara M. Realization of sparse control using the model predictive control scheme. *Transactions of the Society of Instrument and Control Engineers*. 2020; 56(3):74–80.
- [18] Blanchini F, Colaneri P, Fujisaki Y, et al. A Youla–Kučera parameterization approach to output feedback relatively optimal control. *Systems & Control Letts*. 2015;81:14–23.
- [19] Bykov A, Shcherbakov PS. Sparse feedback design in discrete-time linear systems. *Autom Rem Cont*. 2018;79(7):1175–1190.
- [20] Zhang Z, Fujisaki Y. Sparse feedback control realization using a dynamic linear compensator. In: SICE International Symposium on Control Systems; 2023.03. p. 3M1–4.
- [21] Grant M, Boyd S, Ye Y. CVX: Matlab software for disciplined convex programming ; 2008.
- [22] Lofberg J. Yalmip: A toolbox for modeling and optimization in matlab. In: 2004 IEEE international conference on robotics and automation (IEEE Cat. No. 04CH37508); IEEE; 2004. p. 284–289.
- [23] Lewis FL, Vrabie D, Syrmos VL. Optimal control. John Wiley & Sons; 2012.
- [24] Brockett W. Minimum attention control. In: Proceedings of the 36th IEEE Conference on Decision and Control; Vol. 3; IEEE; 1997. p. 2628–2632.

- [25] Nagahara M, Nešić D. An approach to minimum attention control by sparse derivative. In: 2020 59th IEEE Conference on Decision and Control (CDC); IEEE; 2020. p. 5005–5010.
- [26] Lee P, Park F. On the existence and computation of minimum attention optimal control laws. *IEEE Trans Automa Contr.* 2021;67(5):2576–2581.

Appendix A. Numerical results in Section 5

$$\begin{aligned}
 X &= \begin{bmatrix} 1.0000 & 0 & 0 & 1.1753 & -4.2597 & -0.7724 & 1.2898 & -4.5326 & -0.8472 & 1.4109 & -4.8391 & -0.9265 \\ 0 & 1.0000 & 0 & 0.0443 & 0.1526 & -0.0283 & 0.1183 & -0.2060 & -0.0772 & 0.2406 & -0.7377 & -0.1578 \\ 0 & 0 & 1.0000 & 0.1322 & -1.4008 & -0.0892 & 0.1830 & -1.4257 & -0.1222 & 0.2551 & -1.5589 & -0.1692 \end{bmatrix}, \\
 U &= \begin{bmatrix} 0.8012 & -7.2752 & -9.1168 & 0.0000 & -0.0000 & -0.0000 & -0.0000 & 0.0000 & 0.0000 & -0.0626 & 6.8408 & 0.0578 \\ 0.1140 & -8.1530 & -1.1419 & -0.0000 & 0.0000 & 0.0000 & -0.0000 & 0.0000 & 0.0000 & -2.9457 & 9.8661 & 1.9337 \end{bmatrix}.
 \end{aligned} \tag{A.1}$$

$$\begin{aligned}
 K &= \begin{bmatrix} 0.8012 & -7.2752 & -9.1168 \\ 0.1140 & -8.1530 & -1.1419 \end{bmatrix}, \\
 H &= \begin{bmatrix} 0.5857 & -8.2481 & -0.4003 & 1.4963 & -10.8652 & -0.9970 & 2.8829 & -8.8614 & -1.8905 \\ 0.3782 & 0.1298 & -0.2447 & 1.0268 & -2.7911 & -0.6724 & -0.8534 & 2.6232 & 0.5596 \end{bmatrix}.
 \end{aligned} \tag{A.2}$$

$$\begin{aligned}
 X &= \begin{bmatrix} 1.0000 & 0 & -0.8758 & -2.1177 & -2.5880 & -4.0772 & -1.2121 & -1.9096 \\ 0 & 1.0000 & 1.0001 & 1.9972 & 1.6427 & 2.5880 & 0.6924 & 1.0908 \end{bmatrix}, \\
 U &= [4.9553 \quad 6.0613 \quad 4.9553 \quad 6.0613 \quad -2.8673 \quad -4.5173 \quad -2.8673 \quad -4.5173], \\
 K &= [4.9553 \quad 6.0613], \\
 H &= [3.2331 \quad 4.4499 \quad 0.0000 \quad 0.0000 \quad -1.0576 \quad -1.6662] \\
 G &= \begin{bmatrix} 1 & 0 & 0 & 0 & 0 & 0 \\ 0 & 1 & 0 & 0 & 0 & 0 \end{bmatrix}^\top, \\
 F &= \begin{bmatrix} 0.8758 & 2.1177 & 2.5880 & 4.0772 & 1.2121 & 1.9096 \\ -1.0001 & -1.9972 & -1.6427 & -2.5880 & -0.6924 & -1.0908 \\ 1.0000 & 0 & 0 & 0 & 0 & 0 \\ 0 & 1.0000 & 0 & 0 & 0 & 0 \\ 0 & 0 & 1.0000 & 0 & 0 & 0 \\ 0 & 0 & 0 & 1.0000 & 0 & 0 \end{bmatrix}.
 \end{aligned} \tag{A.3}$$