W aveguide-based OPO source of entangled photon pairs

Enrico Pom arico¹, Bruno Sanguinetti¹, Nicolas Gisin¹, Robert Thew¹, Hugo Zbinden¹, Gerhard Schreiber², Abu Thom as² and Wolfgang Sohler².

¹G roup of Applied Physics, University of Geneva, 1211 Geneva, Switzerland. ²Angewandte Physik, University of Paderborn, 33095 Paderborn, Germany.

E-m ail: enrico.pomarico@unige.ch

A bstract. In this paper we present a compact source of narrow-band energy-time entangled photon pairs in the telecom regime based on a Ti-indi used Periodically Poled Lithium Niobate (PPLN) waveguide resonator, i.e. a waveguide with end-face dielectric multi-layer mirrors. This is a monolithic doubly resonant Optical Param etric Oscillator (OPO) far below threshold, which generates photon pairs by Spontaneous Param etric Down Conversion (SPDC) at around 1560 nm with a 117M Hz (0.91 pm)bandwidth. A coherence time of 2.7 ns is estimated by a time correlation measurement and a high quality of the entangled states is con rm ed by a Bell-type experiment. Since highly coherent energy-time entangled photon pairs in the telecom regime are suitable for long distance transmission and manipulation, this source is well suited to the requirements of quantum communication.

1. Introduction

Long distance quantum communication is based on the transmission of entangled photons between remote parties. The transmission distance is currently limited by photonic absorption in optical bre, which increases exponentially with distance. In order to overcome this limitation, quantum repeater protocols have been proposed [1, 2]. These protocols consist in the partition of the communication distance into smaller segments across which two quantum memories [3] can be e ciently entangled. By performing entanglem ent-swapping operations on the intermediate nodes, the entanglem ent is then transferred over the entire distance.

In such a scheme, a narrow-band entangled photon pair source is highly desirable. First of all, it allows the use of atom ic quantum memories, whose spectral linewidths are at the MHz level. A further advantage of photons with a coherence time larger than typical detector resolution is that entanglement swapping can be performed between cw sources, i.e. without the need of synchronization [4]. Moreover, a high photons' coherence time increases the tolerance of bre length uctuations and chromatic dispersion. In order to generate e cient sources of entangled photon pairs, SPDC in nonlinear crystals is more practical with respect to other techniques, such as intracavity atom ic ensembles [5] and bi-exciton cascade emission of quantum dots [6, 7]. However, since SPDC sources produce broad frequency spectra (of the order of THz), the photons' bandwidth needs to be reduced. Placing a nonlinear crystal inside an optical cavity, in order to realize OPO -based sources of narrow -band entangled photon pairs, is a recent approach for overcom ing the limits of SPDC ([8, 9, 10, 11, 12, 13, 14]). In these systems the bandwidth of the emitted photons is limited by the cavity and, at the same time, the down conversion process is enhanced with respect to the single pass scheme [8, 9].

The OPO sources reported so far produced photon pairs in the visible regime between 700 and 900 nm with bandwidths in the MHz level, comparable to the typical linewidth of atom ic quantum memories. In [13] a narrow band single-mode polarizationentangled photon source with a linewidth of 9.6MHz at 780 nm was reported. Only recently [14] the rst long-term stable photon pairs OPO source, with a linewidth of 3MHz at 894.3 nm, was made. The schemes reported so far generate polarization entangled photons in the visible spectrum, which are not suitable for long distance quantum communication.

In this paper we present a source of narrow band energy-time entangled photon pairs at telecom wavelength based on a Ti-indi used PPLN waveguide resonator, i.e. a waveguide with end-face dielectric multi-layer mirrors re ective at telecom wavelengths. Our system is the rst realization of a monolithic waveguide-based OPO far below threshold. The integrated optics approach has signi cant advantages with respect to bulk OPOs: due to the high intensity of the pumpel with a good overlap to signal and idler modes even over long distances without any di raction, a high non linear e ciency results, which may surpass that of a bulk source by orders of magnitude. M oreover, no cavity alignment is necessary and the resonant frequency can be kept stable by controlling the tem perature of the waveguide [15]. In the st part of this paper we describe in detail the photon source, paying attention to the features of the frequency spectrum of the generated photons and to the stabilization of the double resonance condition. Then, we describe the perform ance of the photon pair source and characterize the generated energy-tim e entangled photon pairs by perform ing a Bell-type experiment in the con guration proposed by Franson [6]. The results are discussed in the conclusion.

2. The source

2.1. The TipPLN waveguide resonator

A 3.6 cm long waveguide was fabricated by indi using (per 9 hours at a tem perature of 1060 C) a 6 m wide vacuum -deposited Ti-stripe of 98 nm thickness into the -Z-face of a Z-cut Lithium N iobate (LN) substrate [15]. These parameters were chosen to get a single mode waveguide (at around 1.55 m of wavelength) of low propagation losses (

W aveguide-based OPO source of entangled photon pairs



F igure 1. Features of the T iPPLN waveguide resonator. In the upper part a photograph of the surface of the waveguide and a photograph of the TM -m ode distribution are shown. On the lower left the transm ission spectra of the two m irrors, m easured on LN -substrates simultaneously coated with the waveguide end-faces, are reported. On the lower right the transm ission spectrum of the waveguide resonator is shown.

0.1 dB/cm) and a TM -m ode distribution (4.3 2.9 m², see Figure 1) of good overlap with the mode of standard telecom bres. The latter enables low loss bre coupling and would even allow bre butt coupling in the future.

A fler waveguide fabrication, the sample was periodically poled with a periodicity of = 16.6 m to get QuasiPhase-M atching (QPM) for SPDC at a pump wavelength of

780 nm and signal and idler wavelengths at 1.55 m. Figure 1 shows a photograph of the surface of such a waveguide; it is slightly etched to make the domain structure visible. The nearly 1:1 duty cycle of the domain pattern guarantees a high nonlinear e ciency.

Finally, a stable monolithic waveguide resonator was formed by depositing dielectric m innors on the waveguide end-faces. They consist of alternating SiO₂ and TiO₂-layers with thicknesses de ned by a Monte-Carlo optimization to get a high rejectivity at signal and idler wavelengths (here: 85%), but simultaneously a high transmission for the pump (here: 80%). Figure 1 shows on the lower left the two m innor characteristics m easured on LN -substrates simultaneously coated with the waveguide end-faces.

The resonator was investigated by m easuring its transm ission versus the frequency of a tunable extended cavity laser (1560 nm). Figure 1 shows on the lower right a corresponding result. We observe a Free SpectralRange (FSR) of 1.8 GHz (14 pm) and a FullW idth at HalfMaximum (FW HM) of 117 MHz (0.91 pm), resulting in a nesse of 15.4. This value allows to evaluate the waveguide propagation bases as = 0.06 dB/cm at 1560 nm. The frequency spectrum of the resonator can be simply tuned by changing its tem perature. In this way its length and the elective index of refraction are changed



Figure 2. Setup of the source. A cw mode laser at 780 nm, stabilized on a rubidium (Rb) transition, pumps a PPLN waveguide resonator. Pairs of photons at around 1560 nm are created by SPDC and em itted collinearly. Their frequencies correspond to resonant modes of the cavity. The remaining pump light is blocked by a silicon lter (Si). The photons, coupled into a single mode optical bre, are narrow ly ltered (10 pm - lter) before being detected by two InG aAs APDs. The lters select the wavelengths $_{\rm s}$ = 1559.5 nm and $_{\rm i}$ = 1561.5 nm for the signal and the idler photon respectively. Inset a): Internal scheme of the 10-pm lter (see text for details). Inset b): The folded Franson interferom eter inserted before the 10-pm lter for the characterization of the energy-time entangled states generated by the source.

leading to a signi cant shift of the spectrum. We estimate a wavelength change of 44.5 pm / C (5.7 GHz / C). In other words, the shift from one cavity mode to another in the telecom region implies a change of about 0.3 C at 1560 nm.

2.2. Setup

An external-cavity cw diode laser (Toptica DL100), stabilized on a Rubidium transition (D₂ of 85 Rb) at $_{p} = 780,027$ nm, is used as a pump for producing photon pairs by SPDC from the PPLN waveguide resonator (Figure 2).

At a tem perature of 128.6 C the conditions of QPM and energy conservation (for which $!_p = !_s + !_i$, where $!_j$ ($\neq p,s,i$) refers respectively to the pump, signal and idler frequency) are full led for the generation of photon pairs at around 1560 nm. Signal and idler photons are preferentially em itted only if their frequencies also m atch the resonant m odes of the cavity. C rucial for this goal is the possibility of properly adjusting the transm ission spectrum of the resonator by changing the tem perature of the sam ple. The

constraint of double resonance a ects the frequency spectrum of the photons emitted by the source. In the next subsection we shall describe in detail this spectrum and the m ethod for achieving the double resonance condition at around 1560 nm.

The pump and the created photons are vertically polarized (type I eee coupling) and exit the waveguide resonator collinearly. A bulk high-pass Silicon Iter (Si) is placed before coupling into the bre in order to block the remaining pump light and has a transm ission of 91% of the created photons. The signal and the idler photon are each in a distinct resonant cavity mode. We distinguish them using a Iter (AOS G m bH) which selects two wavelengths symm etrically around the SPDC degeneracy wavelength ($_{s}$ = 1559.5 nm and $_{i}$ = 1561.5 nm) with a bandwidth of 10 pm (1.2 G H z). This value allows us to select only one cavity mode, as the FSR between them is about 14 pm (1.8 G H z). For the selection of each wavelength (see Figure 2, inset a)) a standard F ibre B ragg G rating (FBG) recets the desired wavelength with a bandwidth of 1 nm and a circulator directs the receted light to a Phase-Shifted Fibre B ragg G rating (PSFBG), which transm its the wavelength with a 10 pm -bandwidth, as already explained in detail in [17]. The insertion bases of this Iter are 2.8 and 3.8 dB for the two selected wavelengths.

After being litered, the photons are detected by two InGaAs Avalanche PhotoD iodes (APD s). One APD is in a free-running mode with 2.1% quantum e ciency, at which it has 600 dark-counts s¹, and 30 s dead time for reducing after-pulses, whereas the other one operates in gated mode (ID 200, idQ uantique) with a quantum e ciency of 7.8% and a dark-count probability of 8.0 10^{6} ns¹. The detected signals are sent to a Time to D igital Converter (TDC) for measuring coincidences between them.

In order to characterize the energy-time entangled states generated by the source, both signal and idler photons pass through a single folded Franson interferom eter (see Figure 2, inset b)) before being separated by the liter and detected. The folded Franson interferom eter consists of one bre coupler (50:50 beam splitter) which splits photons into the two interferom etric arms which have Faraday m incors at the ends [18]. Only the signal coming from one output of the coupler is considered. The interferom eter is them ally isolated and its path di erence is L 2m, corresponding to a temporal delay of about 10 ns between the long and the short arm. This value is sm aller than the coherence time of the pump p_{pump} and larger than the coherence time of the photons interference is negligible.

2.3. The emitted frequency spectrum and the double resonance condition

The parametric radiation has to satisfy four dierent conditions (energy conservation, quasi phase-m atching and resonance for signal and idler photons), which a left the frequency spectrum of the degenerate photons emitted by the waveguide resonators. For an SPDC source, degenerate photons are spectrally emitted according to a bell-shape distribution around the frequency $!_p=2$. In an OPO system the emission of photons



F igure 3. The em itted frequency spectrum and the double resonance condition. (a) Above: Envelope of the unlitered frequency spectrum of photons produced by SPDC in the waveguide resonator characterized by cluster em ission. Below : G iordm aine and M iller diagram. The resonant modes for the signal and idler photons, whose dispersion is exaggerated, are represented along oppositely oriented axes. When they lie on a vertical line, double resonance is obtained and a corresponding cluster appears, as for the central cluster at around 1560 nm. (b), (c) D ouble resonance condition around 1560 nm. (b) At a certain tem perature T_1 the modes for the signal and the idler lie on the same vertical lines. A cluster at around 1560 nm appears. (c) By changing the tem perature to T_2 (f_2 - T_1j 0.07 C), the signal and idler are no longer aligned with the vertical lines and the double resonance disappears together with the central cluster. W hen the tem perature is such that signal and idler modes m ove half of the FSR (with about 0.15 C), double resonance is restored, as in b).

is instead allowed only within speci c spectral intervals. This e ect is called cluster em ission [19, 20, 21]. A typical envelope of the un litered frequency spectrum of em itted photons is shown in Figure 3 (a). Its asymmetry is essentially due to the decrease of the detection e ciency at wavelengths above 1600 nm.

Signal and idler photons can be emitted by the OPO if their frequencies are symmetric with respect to $!_p=2$ (condition of energy conservation) and also m atch two distinct modes of the resonator. Emission is thus possible only when the cavity modes for the signal and the idler are symmetric with respect to $!_p/2$. However, since the spectral range on which the photons can be emitted by SPDC is tens of nanom eters wide, it includes thousands of resonant modes. Their relative spacings can vary considerably within this spectral range because of dispersion. Thus, cavity modes for signal and idler photons are symmetric with respect to $!_p/2$ only in some spectral regions, called clusters [20]. Figure 3 (a) shows this elect for the cluster around 1560 nm. The G iordmaine and M iller diagram ([19, 20]) is also shown. The cavity resonances are plotted for the signal and the idler photon. The signal frequency increases from left to right, while the

idler goes in the opposite direction. W hen the transmitted modes of the resonator for the signal and the idler lie along a vertical line, energy conservation is satis ed and the corresponding pairs of photons can be emitted. This is possible only in some intervals, where a cluster is formed. By changing the temperature of the sample the sequence of the cavity modes moves and the resonance condition is automatically lost for certain clusters of frequencies, but it is obtained for others.

W e are interested in the stabilization of the double resonance condition in the region of frequencies around 1560 nm, at which photons are ltered. Figure 3 (b) and (c) show the bas of the double resonance in this spectral region by changing the temperature. In Figure 3(b) a situation of double resonance at a certain temperature T_1 is shown: resonant modes for idler and signal lie on the same vertical lines. The corresponding frequency spectrum, displaying a cluster in the region around 1560 nm, is shown on the right. If we change the tem perature to T_2 (such that $T_2-T_1j = 0.07$ C), them odes move to the left for the signal, and to the right for the idler (Figure 3 (c)). Their superposition on the same vertical lines is lost and double resonance disappears around 1560 nm. If the change of tem perature is such that signal and idler m odes m ove by half their FSR (about 0.15 C), the double resonance is restored and we again observe a cluster around 1560 nm . In order to m aintain the double resonance at 1560 nm , unlike previous sources, only an accurate control of the tem perature is required. A therm al stability of better than 10³ C is guaranteed by performing a P.I.D. regulation of the tem perature using feedback directly from the signal detected by the free-running detector. Since this is a side-of-fringe method, we can not lock on the maximum available signal.

3. Experim ental results

3.1. Features of the source

For measuring the coincidences between the photon pairs generated by the source, the free-running detector provides a start signal on the TDC and triggers the other detector, which gives the stop signal. By in jecting into the waveguide resonator an e ective pump power of 1.6 m W (power e ectively coupled in the waveguide), we registered 3400 counts s¹ on the st detector and 5.2 coincidences s¹. From these values we estimate 17 dB of overall losses for the photons directed to the second detector, in other words only 2% of the photons generated inside the resonator reach the second detector. The overall losses for the photons directed to the st detector are a little sm aller because of the di erent insertion losses in the 10-pm lter for the two selected wavelengths. The rst source of photons' losses is inside the waveguide resonator, which we will try to quantify later on. A fter being em itted, photons undergo 0.4 dB of losses because of the passage through the silicon Iter and 5.2 dB for the coupling into the single mode bre. The internal losses of the 10-pm lter are of 2.8 and 3.8 dB for the photons directed to the rst and the second detector respectively. We estimated supplementary losses of 2.4 dB because of how we lock the tem perature of the system . By sum m ing all the mentioned

photon exits the cavity can be calculated as:

values, we have 10.8 and 11.8 dB of losses for the photons directed respectively to the rst and the second detector.

Subtracting, for the second photon, the sum of the above mentioned bases (11.8 dB) from the total measured bases (17 dB), we estim ate that the bases due to the oscillation of the radiation inside the resonator are 5.2 dB, that is the 30% of the generated photons exit the waveguide resonator. In order to verify this quantity, we computed the probability that a photon, whose frequency matches one resonant mode of the cavity, exits the resonator. By assuming that photons are generated in the middle of the resonator, the probability of exiting after a certain number n of round-trips is given by $P \frac{P}{L} (1 - R) (LR)^2$, where L represents the absorption bases for a single pass inside the cavity and R the re-ectivity of the mirrors. Therefore, the probability that each

$$p_{out} = \frac{p_{L}(1 - R)}{1 - (LR)^{2}};$$
(1)

which gives a value of 0.43 for R = 0.85. This calculation takes in consideration only photons in perfect resonance with the cavity, negliging their lorentzian linewidth. This can explain the discrepancy between the calculated value and the one estimated by subtracting the overall losses.

K nowing the detection rates and the total losses in the system we calculate that the source generates 6.6 10^6 photon pairs per second in the 10-pm window. The photon coherence time is 2.7 ns (as we will see in the next paragraph), so the number of photons per coherence time is 0.02. We keep the pump power low in order to minimize the emission of double pairs [22]. The spectral brightness of the source, calculated considering the overall losses of the system, corresponds to 17 pairs of photons emitted per second, per M H z of bandwidth and per m W of elective pump power (2.2 10^6 pairs / (spm m W)) and coupled in a single mode bre. Therefore, the signal rate of the source is not limited by the pump power, but it is highly a lected by the overall losses of the system.

Part of the signal is lost because of the oscillation of the param etric radiation inside the waveguide resonator. These losses are related to the time the photons spend in the resonator before exiting from it. Unfortunately, the resonator bandwidth is related to this time, therefore we cannot reduce the total losses for a constant bandwidth. However, the signal rate can be increased without changing the bandwidth. For example, a single high rejectivity mirror could be used to reduce the signal which exits from the wrong side of the resonator. In this case the rejectivity of the second mirror should be reduced to keep the nesse, and so the bandwidth constant. O therwise, one can use a smaller resonator. In this way the FSR would be increased and, for keeping the bandwidth constant, the nesse should be increased properly by improving the mirror rejectivities, allowing to exploit the cavity enhancement of the signal [9].

A large part of the signal is also lost in the external optical components. The integrated optics approach could allow to drastically reduce these losses, by integrating liters directly in the wavequide and by bre butt coupling.



Figure 4. Coincidences as a function of the tem poral delay between the signal and idler detection. The FW HM of the peak provides a photons' coherence time of $(2.7 \quad 0.2)$ ns. Each bin of the histogram is 263 ps-wide. The red line indicates the level of accidental coincidences.

3.2. Detection of high coherence photons

In order to characterize our narrow-band photon pair source, we perform ed a time correlation measurement with a TDC. For a single-mode doubly resonant OPO the cross correlation function can be expressed, up to multiplicative factors, as $G^{(2)}(T) = e^{2} \int T^{j}[9]$, where T is the time delay between the idler and signal photons and

the bandwidth of the down-converted photons. By thing the coincidences peak, plotted in Figure 4, with the function mentioned above, we obtain = (117 7) MHz. Dening the correlation time between the idler and signal photons as the FW HM of the cross correlation function, that is $T_c = \frac{1:39}{2}$ [9], we not $T_c = (1:9 \quad 0:1)$ ns. The width of the cross correlation function can also be interpreted in terms of coherence of the down converted photons, which is con med by the interference measurement described in the following section. The coherence time is $_{\rm coh} = \frac{1}{2}$, corresponding to $_{\rm coh} = (2:7 \quad 0.2)$ ns. This value is almost an order of magnitude higher than previously reported sources in the telecom regime [17].

The red line in Figure 4 indicates the measured level of the accidental coincidences registered by the TDC, which is in good agreement with the base-line of the t. This is due to to three main factors. One is the contribution due to the noise of the detectors: accidental coincidences can be registered between the electronic signals corresponding to the dark-counts of the two detectors, between a dark-count of one detector and a real detection on the other detector and viceversa. A coidental coincidences can also arise because of after-pulses in the rst detector. A nother contribution is due to coincidences between photons of independent pairs. This term is related to the number of double photon pairs per mode that are generated inside the crystal. We measured accidental coincidences of 4.7 10² Hz ns¹ due to the noise of the detectors, 0.1 10² Hz ns¹



Figure 5. A histogram of the coincidences as a function of the signal - idler delay when photon pairs are analyzed by the folded Franson interferom eter. We select coincidences in the tem poral interval corresponding to the central peak, as shown by the dashed red window, for measuring the interference fringes in the coincidence count rate.

for after-pulses in the st detector and we estimated $3.4 \quad 10^2$ Hz ns¹ accidental coincidences for independent photon pairs.

3.3. Characterization of energy-tim e entangled states

Since our source is cw pumped, it generates energy-time entangled photon pairs. Photon pairs may be created at a random time twithin the coherence time of the pump, but the uncertainty in the dimension of the emission times of photons of the same pair is the coherence time of the photons ($_{coh} << _{pump}$). In other words, the individual energy values of the down-converted photons are unknown, but their sum is well de ned (within the bandwidth of the pump) by energy conservation.

The energy-time entangled states produced by the source can be characterized by performing a Bell-type experiment in the conguration proposed by Franson [6] and measuring the two-photon interference visibility. In our case, instead of sending the two photons to two separated analyzer systems based on equally unbalanced M ach-Zehnder type interferom eters, we send them, as shown in Figure 2 (inset b)), to only one interferom eter, after which they are litered and then detected. This scheme corresponds to a folded Franson interferom eter [18]. Figure 5 shows the number of coincidences as a function of the signal-idler delay. The three peaks have a temporal separation of approximately 10 ns, as expected from the value of L. The events corresponding to the cases where both the down-converted photons take the short or the long arm of the interferom eter give rise to coincidences in the central peak. The indistinguishability



Figure 6. Coincidences as a function of the time during which the temperature of the interferom eter is scanned. The measured raw fringe visibility is (81.2 5.5)%. The errors bars are calculated as the standard deviation of the coincidences values in 100 seconds of integration time for each point.

of these events provides an interference e ect. Side peaks correspond to coincidences between one photon of the pairs which takes the short arm while the other takes the long arm, and viceversa.

By selecting only the coincidences which fall in the tem poral interval corresponding to the central peak, as shown in Figure 5 by the dashed red 12ns wide window, and by scanning the tem perature of the interferom eter, we measure the interference fringes in the coincidence count rate (Figure 6). It is to be noticed that in the folded Franson interferom eter, if we change the tem perature we vary the sum of the phases of both the photons.

The integration time of each point in Figure 6 is 100 s. The raw fringe visibility is $(81.2 \ 5.5)$ %, su cient for violating the limit of $\frac{1}{2}$ given by Bell inequalities. If we subtract the accidental coincidences due to the noise of the detectors we obtain a fringe visibility of $(94.4 \ 5.8)$ %. These results con m the good quality of the energy-time entangled states generated by the source.

4. Conclusions

The source of energy-time entangled photon pairs presented in this paper consists of a monolithic doubly resonant OPO system based on a PPLN waveguide resonator that generates photons by SPDC at telecom wavelength with a 117M Hz-bandwidth. We measured a photons' coherence time of 2.7 ns and a spectral brightness of 17 em itted photon pairs per second, per MHz of bandwidth and per mW of e ective pump power $(2.2 \quad 10^3 \text{ pairs} / (\text{s pm mW}))$ coupled in a single mode bre. The good quality of

the energy-time entangled states we generate is con med by the raw visibility of the interference fringes in the coincidence rate after a folded Franson interferom eter. The signal rate of the source is highly a lected by the overall losses of the system. Losses due to external optical components could be, instead, drastically reduce by integrating

Iters directly in the waveguide and by bre butt coupling. A though waveguide-based OPO technology requires further optimization, this source represents the rst compact and OPO system at telecom wavelength and a rst step towards integrated narrow-band sources of entangled photon pairs.

A cknow ledgm ent

W ewould like to thank M ikaelA fzelius and H ugues de R iedm atten for useful discussions. This work was supported by the EU projects QAP and SINPHON TA and by the Swiss NCCR Quantum Photonics.

References

- [1] H.J.Briegel, W.Dur, J.I.Cirac, and P.Zoller. Quantum repeaters: The role of imperfect local operations in quantum communication. Physical Review Letters, 81 (26):5932 (5935, Dec 1998.
- [2] Christoph Sim on, Hugues de Riedmatten, Mikael Afzelius, Nicolas Sangouard, Hugo Zbinden, and Nicolas Gisin. Quantum repeaters with photon pair sources and multimode memories. Physical Review Letters, 98 (19):190503+, 2007.
- [3] Hugues de Riedmatten, Mikael Afzelius, Matthias U. Staudt, Christoph Simon, and Nicolas Gisin. A solid-state light-matter interface at the single-photon level. Nature, 456 (7223):773 (777, December 2008.
- [4] M atthaus Halder, A lexios B everatos, N icolas G isin, Valerio Scarani, Christoph Sim on, and Hugo Zbinden. Entangling independent photons by time m easurement. Nat Phys, 3(10):692{695, O ctober 2007.
- [5] Jam es K. Thompson, Jonathan Simon, Huanqian Loh, and Vladan Vuletic. A high-brightness source of narrowband, identical-photon pairs. Science, 313 (5783):74 {77, July 2006.
- [6] O liver Benson, Charles Santori, M atthew Pelton, and Yoshihisa Yamamoto. Regulated and entangled photons from a single quantum dot. Physical Review Letters, 84(11):2513{2516, M ar 2000.
- [7] R. M. Stevenson, R. J. Young, P. Atkinson, K. Cooper, D. A. Ritchie, and A. J. Shields. A sem iconductor source of triggered entangled photon pairs. Nature, 439 (7073):179 [182, January 2006.
- [8] Z. Y. Ou and Y. J. Lu. Cavity enhanced spontaneous parametric down-conversion for the prolongation of correlation time between conjugate photons. Physical Review Letters, 83 (13) 2556 (2559, Sep 1999.
- [9] Y.J.Lu and Z.Y.Ou. Optical parametric oscillator far below threshold: Experiment versus theory. Physical Review A, 62(3):033804+, Aug 2000.
- [10] Hayato Goto, Yasuo Yanagihara, Haibo Wang, Tomoyuki Horikiri, and Takayoshi Kobayashi. Observation of an oscillatory correlation function of multimode two-photon pairs. Physical Review A, 68 (1):015803+, Jul2003.
- [11] Christopher E. Kuklewicz, Franco N. C. Wong, and Je rey H. Shapiro. Time-bin-modulated biphotons from cavity-enhanced down-conversion. Physical Review Letters, 97 (22):223601+, 2006.

W aveguide-based OPO source of entangled photon pairs

- [12] J.S.Neergaard-Nielsen, B.M. Nielsen, H. Takahashi, A. I.Vistnes, and E.S.Polzik. High purity bright single photon source. Opt. Express, 15(13):7940{7949, June 2007.
- [13] Xiao H. Bao, Yong Qian, Jian Yang, Han Zhang, Zeng B. Chen, Tao Yang, and Jian W. Pan. Generation of narrow-band polarization-entangled photon pairs for atom ic quantum memories. Physical Review Letters, 101 (19):190501+, 2008.
- [14] M atthias Scholz, Lars K och, and O liver Benson. Statistics of narrow-band single photons for quantum memories generated by ultrabright cavity-enhanced parametric down-conversion. Physical Review Letters, 102 (6):063603+,2009.
- G. Schreiber, D. Hofmann, W. Grundkotter, Y. L. Lee, H. Suche, V. Quiring, R. Ricken, and W. Sohler. Nonlinear integrated optical frequency converters with periodically poledtilinbo3 waveguides. Proceedings SP IE, 4277:144+, 2001.
- [16] J.D.Franson. Bell inequality for position and time. Physical Review Letters, 62 (19) 2205 (2208, M ay 1989.
- [17] M atthaus Halder, A lexios B everatos, R obert T. Thew, C orentin Jorel, H ugo Zbinden, and N icolas G isin. H igh coherence photon pair source for quantum communication. New Journal of Physics, 10(2):023027+, February 2008.
- [18] R.T.Thew, S.Tanzilli, W.Tittel, H.Zbinden, and N.Gisin. Experim ental investigation of the robustness of partially entangled qubits over 11 km. Physical Review A, 66(6):062304+, Dec 2002.
- [19] J.A.G iordm aine and R.C.M iller. Optical parametric oscillation in linbo_3. In P.L.Kelley, B.Lax, and P.E.Tannenwald, editors, Physics of Quantum Electronics, 1966.
- [20] Robert C. Eckardt, C. D. Nabors, W illiam J. Kozlovsky, and Robert L. Byer. Optical parametric oscillator frequency tuning and control. J. Opt. Soc. Am. B, 8(3):646{667, M arch 1991.
- [21] A. Henderson. Doubly-resonant optical parametric oscillators: tuning behaviour and stability requirements. Optics Communications, 119(1-2):256{264, August 1995.
- [22] V. Scarani, H. de Riedmatten, I. Marcikic, H. Zbinden, and N. Gisin. Four-photon correction in two-photon bell experiments. The European Physical Journal D - Atomic, Molecular, Optical and Plasm a Physics, 32 (1):129 (138, January 2005.