

# All-loop group-theory constraints for color-ordered $SU(N)$ gauge-theory amplitudes

Stephen G. Naculich<sup>1</sup>

*Department of Physics  
Bowdoin College  
Brunswick, ME 04011, USA*

`naculich@bowdoin.edu`

## Abstract

We derive constraints on the color-ordered amplitudes of the  $L$ -loop four-point function in  $SU(N)$  gauge theories that arise solely from the structure of the gauge group. These constraints generalize well-known group theory relations, such as  $U(1)$  decoupling identities, to all loop orders.

---

<sup>1</sup> Research supported in part by the National Science Foundation under Grant No. PHY07-56518.

# 1 Introduction

An exciting recent development in the study of perturbative amplitudes is the discovery of color-kinematic duality of gauge theory amplitudes at both tree and loop level [1, 2]. This duality implies the existence of constraints on tree-level color-ordered amplitudes, which were proven in refs. [3–6]. The BCJ conjecture was also verified through three loops for the  $\mathcal{N} = 4$  supersymmetric Yang-Mills four- [2, 7] and five-point [8, 9] amplitudes. (See reviews in refs. [7, 10], which also contain references to related work on the subject.)

The BCJ constraints on tree-level color-ordered amplitudes hold in addition to various well-known  $SU(N)$  group theory relations, such as the  $U(1)$  decoupling or dual Ward identity [11, 12] and the Kleiss-Kuijf relations [13]. Group-theory relations also hold for one-loop [14, 15] and two-loop [16] color-ordered amplitudes. They can be elegantly derived by using an alternative color decomposition of the amplitude [17, 18].

The purpose of this note is extend the  $SU(N)$  group theory relations for four-point amplitudes to all loops. We develop a recursive procedure to derive constraints satisfied by any  $L$ -loop diagram (containing only adjoint fields) obtained by attaching a rung between two external legs of an  $(L - 1)$ -loop diagram. We assume that the most general  $L$ -loop color factor can be obtained from this subset using Jacobi relations, an assumption that has been proven through  $L = 4$ . Using this method, we find four independent group-theory constraints for color-ordered four-point amplitudes at each loop level (except for  $L = 0$  and  $L = 1$ , where there are one and three constraints respectively).

The color-ordered amplitudes of a gauge theory are the coefficients of the full amplitude in a basis using traces of generators in the fundamental representation of the gauge group. Color-ordered amplitudes have the advantage of being individually gauge-invariant. Four-point amplitudes of  $SU(N)$  gauge theories can be expressed in terms of single and double traces [14]

$$\begin{aligned} T_1 &= \text{Tr}(T^{a_1} T^{a_2} T^{a_3} T^{a_4}) + \text{Tr}(T^{a_1} T^{a_4} T^{a_3} T^{a_2}), & T_4 &= \text{Tr}(T^{a_1} T^{a_3}) \text{Tr}(T^{a_2} T^{a_4}), \\ T_2 &= \text{Tr}(T^{a_1} T^{a_2} T^{a_4} T^{a_3}) + \text{Tr}(T^{a_1} T^{a_3} T^{a_4} T^{a_2}), & T_5 &= \text{Tr}(T^{a_1} T^{a_4}) \text{Tr}(T^{a_2} T^{a_3}), \\ T_3 &= \text{Tr}(T^{a_1} T^{a_4} T^{a_2} T^{a_3}) + \text{Tr}(T^{a_1} T^{a_3} T^{a_2} T^{a_4}), & T_6 &= \text{Tr}(T^{a_1} T^{a_2}) \text{Tr}(T^{a_3} T^{a_4}). \end{aligned} \quad (1.1)$$

All other possible trace terms vanish in  $SU(N)$  since  $\text{Tr}(T^a) = 0$ . The color-ordered amplitudes can be further decomposed [19] in powers of  $N$  as

$$\mathcal{A}^{(L)} = \sum_{\lambda=1}^3 \left( \sum_{k=0}^{\lfloor \frac{L}{2} \rfloor} N^{L-2k} A_{\lambda}^{(L,2k)} \right) T_{\lambda} + \sum_{\lambda=4}^6 \left( \sum_{k=0}^{\lfloor \frac{L-1}{2} \rfloor} N^{L-2k-1} A_{\lambda}^{(L,2k+1)} \right) T_{\lambda} \quad (1.2)$$

where  $A_{\lambda}^{(L,0)}$  are leading-order-in- $N$  (planar) amplitudes, and  $A_{\lambda}^{(L,k)}$ ,  $k = 1, \dots, L$ , are subleading-order, yielding  $(3L + 3)$  color-ordered amplitudes at  $L$  loops.

Alternatively, amplitudes may be decomposed into a basis of color factors [17, 18]. It is in such a basis that color-kinematic duality is manifest [1, 2]. The number of linearly-independent  $L$ -loop color factors, however, is less than the number of elements of the  $L$ -loop trace basis, implying the

existence of constraints among  $A_\lambda^{(L,k)}$ . In this note we show that, for even  $L$ , the color-ordered amplitudes must satisfy

$$6 \sum_{\lambda=1}^3 A_\lambda^{(L,L-2)} - \sum_{\lambda=4}^6 A_\lambda^{(L,L-1)} = 0, \quad (1.3)$$

$$A_{\lambda+3}^{(L,L-1)} + A_\lambda^{(L,L)} = \text{independent of } \lambda, \quad (1.4)$$

$$\sum_{\lambda=1}^3 A_\lambda^{(L,L)} = 0, \quad (1.5)$$

while for odd  $L$ , the relations are

$$6 \sum_{\lambda=1}^3 A_\lambda^{(L,L-3)} - \sum_{\lambda=4}^6 A_\lambda^{(L,L-2)} + 2 \sum_{\lambda=1}^3 A_\lambda^{(L,L-1)} = 0, \quad (1.6)$$

$$6 \sum_{\lambda=1}^3 A_\lambda^{(L,L-1)} - \sum_{\lambda=4}^6 A_\lambda^{(L,L)} = 0, \quad (1.7)$$

$$A_\lambda^{(L,L)} = \text{independent of } \lambda. \quad (1.8)$$

These constraints generalize known group theory relations at tree-level [11,12], one loop [14], and two loops [16] to all loop orders. In particular, we note that eqs. (1.3), (1.5), (1.7), and (1.8) can alternatively be derived by expanding the amplitude in a  $U(N)$  trace basis and requiring that any amplitude containing one or more gauge bosons in the  $U(1)$  subgroup vanish. Such  $U(1)$  decoupling arguments, however, cannot be used to obtain eqs. (1.4) and (1.6).

Since the space of  $L$ -loop color factors is by construction at least  $(3L-1)$ -dimensional (for  $L \geq 2$ ), eqs. (1.3)-(1.8) are the maximal set of constraints on color-ordered amplitudes that follow from  $SU(N)$  group theory alone.<sup>2</sup> It is interesting that these constraints only involve the three or four most-subleading-in- $1/N$  color-ordered amplitudes at a given loop order; other amplitudes are not constrained at all by group theory. Of course, color-kinematic duality implies further relations among the amplitudes [1,2]. Other recent work on constraints among loop-level amplitudes includes refs. [20–22].

In sec. 2, we describe the relation between color and trace bases, and how to use this to derive constraints among color-ordered amplitudes. In sec. 3, we apply this to four-point amplitudes through two loops, and then develop and solve all-loop-order recursion relations yielding constraints for four-point color-ordered amplitudes. In the appendix, we provide details about the three- and four-loop cases.

## 2 Color and trace bases

In this section, we schematically outline the approach we use to obtain constraints among color-ordered amplitudes. This approach was used in ref. [23] for tree-level and one-loop five-point

---

<sup>2</sup>If our recursive procedure together with the Jacobi relations do not yield the entire space of  $L$ -loop color factors, then some of these constraints could be violated for  $L > 4$ , though we think this unlikely.

amplitudes.

The  $n$ -point amplitude in a gauge theory containing only fields in the adjoint representation of  $SU(N)$  (such as pure Yang-Mills or supersymmetric Yang-Mills theory) can be written in a loop expansion, with the  $L$ -loop contribution given by a sum of  $L$ -loop Feynman diagrams. Suppressing  $n$  and  $L$ , as well as all momentum and polarization dependence, we can express the  $L$ -loop amplitude in the “parent-graph” decomposition [24]

$$\mathcal{A} = \sum_i a_i c_i \quad (2.1)$$

where  $\{c_i\}$  represents a complete set of color factors of  $L$ -loop  $n$ -point diagrams built from cubic vertices with a factor of the  $SU(N)$  structure constants  $\tilde{f}^{abc}$  at each vertex. Contributions from Feynman diagrams containing quartic vertices with factors of  $\tilde{f}^{abe}\tilde{f}^{cde}$ ,  $\tilde{f}^{ace}\tilde{f}^{bde}$ , and  $\tilde{f}^{ade}\tilde{f}^{bce}$  can be parceled out among other diagrams containing only cubic vertices. The set of color factors may be overcomplete, in which case they satisfy relations of the form

$$\sum_i \ell_i c_i = 0. \quad (2.2)$$

In fact, it is often necessary to use an overcomplete basis to make color-kinematic duality manifest [1, 8]. Although the amplitude (2.1) is gauge invariant, the individual terms in the sum may not be. Any gauge-dependent pieces of the form  $a_i = \ell_i f$  (where  $f$  is independent of  $i$ ) will cancel out due to eq. (2.2).

The  $L$ -loop amplitude may alternatively be expressed in terms of a trace basis  $\{t_\lambda\}$  as

$$\mathcal{A} = \sum_\lambda A_\lambda t_\lambda \quad (2.3)$$

where  $A_\lambda$  are gauge-invariant color-ordered amplitudes. One can convert the amplitude (2.1) into the trace basis by writing

$$\tilde{f}^{abc} = i\sqrt{2}f^{abc} = \text{Tr}([T^a, T^b]T^c) \quad (2.4)$$

and using the  $SU(N)$  identities

$$\begin{aligned} \text{Tr}(PT^a)\text{Tr}(QT^a) &= \text{Tr}(PQ) - \frac{1}{N}\text{Tr}(P)\text{Tr}(Q) \\ \text{Tr}(PT^aQT^a) &= \text{Tr}(P)\text{Tr}(Q) - \frac{1}{N}\text{Tr}(PQ) \end{aligned} \quad (2.5)$$

to express the color factor  $c_i$  as a linear combination of traces

$$c_i = \sum_\lambda M_{i\lambda} t_\lambda. \quad (2.6)$$

The color-ordered amplitudes are then given by

$$A_\lambda = \sum_i a_i M_{i\lambda}. \quad (2.7)$$

Any constraints (2.2) among the color factors correspond to left null eigenvectors of the transformation matrix

$$\sum_i \ell_i M_{i\lambda} = 0. \quad (2.8)$$

The transformation matrix will also have a set of right null eigenvectors

$$\sum_\lambda M_{i\lambda} r_\lambda = 0. \quad (2.9)$$

Each right null eigenvector implies a constraint

$$\sum_\lambda A_\lambda r_\lambda = 0 \quad (2.10)$$

on the color-ordered amplitudes.

### 3 Constraints on color-ordered four-point amplitudes

In eq. (1.2), we decomposed the  $L$ -loop four-point amplitude in terms of the six-dimensional trace basis  $\{T_\lambda\}$  defined in eq. (1.1). The  $1/N$  expansion suggests enlarging the trace basis to the  $(3L+3)$ -dimensional basis  $\{t_\lambda^{(L)}\}$ :

$$\begin{aligned} t_{1+6k}^{(L)} &= N^{L-2k} T_1, & t_{4+6k}^{(L)} &= N^{L-2k-1} T_4, \\ t_{2+6k}^{(L)} &= N^{L-2k} T_2, & t_{5+6k}^{(L)} &= N^{L-2k-1} T_5, \\ t_{3+6k}^{(L)} &= N^{L-2k} T_3, & t_{6+6k}^{(L)} &= N^{L-2k-1} T_6, \end{aligned} \quad (3.1)$$

in terms of which eq. (1.2) becomes

$$\mathcal{A}^{(L)} = \sum_{\lambda=1}^{3L+3} A_\lambda^{(L)} t_\lambda^{(L)}, \quad \text{where} \quad A_{\lambda+6k}^{(L)} = \begin{cases} A_\lambda^{(L,2k)}, & \lambda = 1, 2, 3, \\ A_\lambda^{(L,2k+1)}, & \lambda = 4, 5, 6. \end{cases} \quad (3.2)$$

The decomposition (2.6) of color factors  $c_i$  into the trace basis  $\{t_\lambda^{(L)}\}$  shows that the number of independent  $L$ -loop color factors cannot exceed  $3L+3$ . The dimension of the space of color factors is actually less than this, being 2-dimensional at tree level, 3-dimensional at one loop, and  $(3L-1)$ -dimensional for  $L \geq 2$  (only proven for  $L \leq 4$ ). As we will illustrate below, this implies the existence of right null eigenvectors (2.9) of the transformation matrix  $M_{i\lambda}^{(L)}$  and corresponding constraints (2.10) among the color-ordered amplitudes  $A_\lambda^{(L)}$ .

At tree level, the space of color factors is spanned by the  $t$ -channel exchange diagram

$$C_{st}^{(0)} = \tilde{f}^{a_1 a_4 b} \tilde{f}^{a_3 a_2 b} = t_1^{(0)} - t_3^{(0)} \quad (3.3)$$

and the corresponding  $s$ -channel exchange diagram

$$C_{ts}^{(0)} = \tilde{f}^{a_1 a_2 b} \tilde{f}^{a_3 a_4 b} = t_1^{(0)} - t_2^{(0)}. \quad (3.4)$$

The  $u$ -channel diagram is related to these by the Jacobi identity. With  $\{c_1, c_2\} = \{C_{st}^{(0)}, C_{ts}^{(0)}\}$ , the transformation matrix (2.6) and its right null eigenvector (2.9) are

$$M_{i\lambda}^{(0)} = \begin{pmatrix} 1 & 0 & -1 \\ 1 & -1 & 0 \end{pmatrix}, \quad r^{(0)} = \begin{pmatrix} 1 \\ 1 \\ 1 \end{pmatrix} \quad (3.5)$$

which implies the U(1) decoupling identity among color-ordered tree amplitudes [11, 12]

$$A_1^{(0)} + A_2^{(0)} + A_3^{(0)} = 0. \quad (3.6)$$

This is eq. (1.5) for  $L = 0$ .

The color factor of the one-loop box diagram

$$C_{st}^{(1)} = C_{ts}^{(1)} = \tilde{f}^{ea_1b} \tilde{f}^{ba_2c} \tilde{f}^{ca_3d} \tilde{f}^{da_4e} = t_1^{(1)} + 2(t_4^{(1)} + t_5^{(1)} + t_6^{(1)}) \quad (3.7)$$

and its independent permutations  $C_{us}^{(1)}$  and  $C_{tu}^{(1)}$  span the space of one-loop color factors, giving

$$M_{i\lambda}^{(1)} = \begin{pmatrix} 1 & 0 & 0 & 2 & 2 & 2 \\ 0 & 1 & 0 & 2 & 2 & 2 \\ 0 & 0 & 1 & 2 & 2 & 2 \end{pmatrix}. \quad (3.8)$$

Alternatively, we can choose<sup>3</sup> for our basis  $NC_{st}^{(0)}$  and  $NC_{ts}^{(0)}$ , together with  $C_{st}^{(1)}$ , to give

$$M_{i\lambda}^{(1)} = \begin{pmatrix} 1 & 0 & -1 & 0 & 0 & 0 \\ 1 & -1 & 0 & 0 & 0 & 0 \\ 1 & 0 & 0 & 2 & 2 & 2 \end{pmatrix}. \quad (3.9)$$

In either case, the transformation matrix has three independent right null eigenvectors

$$r^{(1)} = \begin{pmatrix} 6u \\ -u \end{pmatrix}, \quad \begin{pmatrix} 0 \\ x \end{pmatrix}, \quad \begin{pmatrix} 0 \\ y \end{pmatrix}, \quad \text{where} \quad u \equiv \begin{pmatrix} 1 \\ 1 \\ 1 \end{pmatrix} \quad x \equiv \begin{pmatrix} 1 \\ -1 \\ 0 \end{pmatrix} \quad y \equiv \begin{pmatrix} 0 \\ 1 \\ -1 \end{pmatrix} \quad (3.10)$$

implying three relations among the one-loop color-ordered amplitudes [14]

$$A_4^{(1)} = A_5^{(1)} = A_6^{(1)} = 2(A_1^{(1)} + A_2^{(1)} + A_3^{(1)}). \quad (3.11)$$

These are eqs. (1.7) and (1.8) for  $L = 1$ .

At two loops, the ladder and non-planar diagrams<sup>4</sup> yield the color factors

$$C_{st}^{(2L)} = \tilde{f}^{ea_1b} \tilde{f}^{ba_2c} \tilde{f}^{cga_3d} \tilde{f}^{dfe} \tilde{f}^{ga_3h} \tilde{f}^{ha_4f} = t_1^{(2)} + 6t_6^{(2)} + 2t_7^{(2)} + 2t_8^{(2)} - 4t_9^{(2)}, \quad (3.12)$$

$$C_{st}^{(2NP)} = \tilde{f}^{ea_1b} \tilde{f}^{ba_2c} \tilde{f}^{cga_3d} \tilde{f}^{hfe} \tilde{f}^{ga_3h} \tilde{f}^{da_4f} = -2t_4^{(2)} - 2t_5^{(2)} + 4t_6^{(2)} + 2t_7^{(2)} + 2t_8^{(2)} - 4t_9^{(2)}. \quad (3.13)$$

---

<sup>3</sup>This makes sense since we can use the Jacobi identity to replace the one-loop box diagram with another box diagram with permuted legs plus a tree diagram with one of the vertices replaced by a triangle diagram. The latter is proportional to a tree diagram since  $\tilde{f}^{da_1b} \tilde{f}^{ba_2c} \tilde{f}^{ca_3d} = N \tilde{f}^{a_1a_2a_3}$ .

<sup>4</sup>It can be easily shown that any other two-loop diagram is related to these ones by Jacobi relations.

The non-planar color factors can be expressed in terms of the planar ones,

$$3C_{st}^{(2NP)} = C_{st}^{(2L)} - C_{ts}^{(2L)} - C_{us}^{(2L)} + C_{su}^{(2L)}, \quad (3.14)$$

and a linear relation exists among the planar color factor and its permutations,

$$0 = C_{st}^{(2L)} - C_{ts}^{(2L)} + C_{us}^{(2L)} - C_{su}^{(2L)} + C_{tu}^{(2L)} - C_{ut}^{(2L)}. \quad (3.15)$$

We could therefore choose five of the six permutations of the ladder diagram to span the space of two-loop color factors; alternatively, we can use  $N^2 C_{st}^{(0)}$ ,  $N^2 C_{ts}^{(0)}$ , and  $NC_{st}^{(1)}$ , together with  $C_{st}^{(2L)}$  and  $C_{ts}^{(2L)}$ , to obtain

$$M_{i\lambda}^{(2)} = \begin{pmatrix} 1 & 0 & -1 & 0 & 0 & 0 & 0 & 0 & 0 \\ 1 & -1 & 0 & 0 & 0 & 0 & 0 & 0 & 0 \\ 1 & 0 & 0 & 2 & 2 & 2 & 0 & 0 & 0 \\ 1 & 0 & 0 & 0 & 0 & 6 & 2 & 2 & -4 \\ 1 & 0 & 0 & 0 & 6 & 0 & 2 & -4 & 2 \end{pmatrix}. \quad (3.16)$$

The two-loop transformation matrix has four independent right null eigenvectors

$$r^{(2)} = \begin{pmatrix} 6u \\ -u \\ 0 \end{pmatrix}, \quad \begin{pmatrix} 0 \\ x \\ x \end{pmatrix}, \quad \begin{pmatrix} 0 \\ y \\ y \end{pmatrix}, \quad \begin{pmatrix} 0 \\ 0 \\ u \end{pmatrix} \quad (3.17)$$

implying four two-loop group-theory relations [16]

$$\begin{aligned} 0 &= A_4^{(2)} + A_7^{(2)} - 2(A_1^{(2)} + A_2^{(2)} + A_3^{(2)}) \\ 0 &= A_5^{(2)} + A_8^{(2)} - 2(A_1^{(2)} + A_2^{(2)} + A_3^{(2)}) \\ 0 &= A_6^{(2)} + A_9^{(2)} - 2(A_1^{(2)} + A_2^{(2)} + A_3^{(2)}) \\ 0 &= A_7^{(2)} + A_8^{(2)} + A_9^{(2)} \end{aligned} \quad (3.18)$$

equivalent to eqs. (1.3)-(1.5) for  $L = 2$ .

We now employ a recursive procedure to obtain null eigenvectors for higher-loop color factors. An  $(L+1)$ -loop diagram may be obtained from an  $L$ -loop diagram by attaching a rung between two of its external legs,  $i$  and  $j$ . This corresponds to contracting its color factor with  $\tilde{f}^{a_i a'_i b} \tilde{f}^{b a'_j a_j}$ . Note that if  $i$  and  $j$  are not adjacent, this will convert a planar diagram into a nonplanar diagram. First consider the effect of this procedure [25] on the trace basis (1.1)

$$T_\lambda \longrightarrow \sum_{\kappa=1}^6 G_{\lambda\kappa} T_\kappa, \quad \text{where} \quad G = \begin{pmatrix} NA & B \\ C & ND \end{pmatrix} \quad (3.19)$$

with

$$\begin{aligned} A &= \begin{pmatrix} e_{12} + e_{14} & 0 & 0 \\ 0 & e_{12} + e_{13} & 0 \\ 0 & 0 & e_{13} + e_{14} \end{pmatrix}, & B &= \begin{pmatrix} 0 & 2e_{14} - 2e_{13} & 2e_{12} - 2e_{13} \\ 2e_{13} - 2e_{14} & 0 & 2e_{12} - 2e_{14} \\ 2e_{13} - 2e_{12} & 2e_{14} - 2e_{12} & 0 \end{pmatrix}, \\ C &= \begin{pmatrix} 0 & e_{12} - e_{14} & e_{14} - e_{12} \\ e_{12} - e_{13} & 0 & e_{13} - e_{12} \\ e_{14} - e_{13} & e_{13} - e_{14} & 0 \end{pmatrix}, & D &= \begin{pmatrix} 2e_{13} & 0 & 0 \\ 0 & 2e_{14} & 0 \\ 0 & 0 & 2e_{12} \end{pmatrix}, \end{aligned} \quad (3.20)$$

where the coefficient of  $e_{1j}$  corresponds to connecting legs 1 and  $j$ . On the expanded basis (3.1), the same procedure yields

$$t_\lambda^{(L)} \rightarrow \sum_{\kappa=1}^{3L+6} g_{\lambda\kappa} t_\kappa^{(L+1)} \quad (3.21)$$

where  $g$  is the  $(3L+3) \times (3L+6)$  matrix

$$g = \begin{pmatrix} A & B & 0 & 0 & 0 & \dots \\ 0 & D & C & 0 & 0 & \dots \\ 0 & 0 & A & B & 0 & \dots \\ 0 & 0 & 0 & D & C & \dots \\ \vdots & \vdots & \vdots & \vdots & \vdots & \ddots \end{pmatrix}. \quad (3.22)$$

Next, given some  $L$ -loop diagram with color factor  $c_i^{(L)}$ , we can connect two of its external legs with a rung to obtain an  $(L+1)$ -loop diagram with color factor

$$c_i^{(L+1)} = \sum_{\kappa=1}^{3L+6} M_{i\kappa}^{(L+1)} t_\kappa^{(L+1)} \quad (3.23)$$

where

$$M_{i\kappa}^{(L+1)} = \sum_{\lambda=1}^{3L+3} M_{i\lambda}^{(L)} g_{\lambda\kappa}, \quad \text{with} \quad c_i^{(L)} = \sum_{\lambda=1}^{3L+3} M_{i\lambda}^{(L)} t_\lambda^{(L)}. \quad (3.24)$$

Now, suppose we possess a complete set of  $L$ -loop color factors  $\{c_i^{(L)}\}$  and a maximal set of right null eigenvectors  $\{r_\lambda^{(L)}\}$ :

$$\sum_{\lambda=1}^{3L+3} M_{i\lambda}^{(L)} r_\lambda^{(L)} = 0. \quad (3.25)$$

Then the color factors of all  $(L+1)$ -loop diagrams obtained by connecting two external legs of any  $L$ -loop diagram will have a right null eigenvector

$$\sum_{\kappa=1}^{3L+6} M_{i\kappa}^{(L+1)} r_\kappa^{(L+1)} = 0 \quad (3.26)$$

provided that  $r_\kappa^{(L+1)}$  satisfies

$$\sum_{\kappa=1}^{3L+6} g_{\lambda\kappa} r_\kappa^{(L+1)} = \text{linear combination of } \{r_\lambda^{(L)}\}. \quad (3.27)$$

We can now solve eq. (3.27) recursively, beginning with the set of  $L=2$  right null eigenvectors (3.17), the first case with four independent eigenvectors. The maximal set of right null



eigenvectors satisfying eq. (3.27) is

$$\{r^{(2\ell+1)}\} = \begin{pmatrix} \vdots \\ 0 \\ 6u \\ -u \\ 2u \\ 0 \end{pmatrix}, \quad \begin{pmatrix} \vdots \\ 0 \\ 0 \\ 0 \\ 6u \\ -u \end{pmatrix}, \quad \begin{pmatrix} \vdots \\ 0 \\ 0 \\ 0 \\ 0 \\ x \end{pmatrix}, \quad \begin{pmatrix} \vdots \\ 0 \\ 0 \\ 0 \\ 0 \\ y \end{pmatrix}, \quad \{r^{(2\ell)}\} = \begin{pmatrix} \vdots \\ 0 \\ 6u \\ -u \\ 0 \end{pmatrix}, \quad \begin{pmatrix} \vdots \\ 0 \\ 0 \\ x \\ x \end{pmatrix}, \quad \begin{pmatrix} \vdots \\ 0 \\ 0 \\ y \\ y \end{pmatrix}, \quad \begin{pmatrix} \vdots \\ 0 \\ 0 \\ 0 \\ u \end{pmatrix}. \quad (3.28)$$

The constraints on color-ordered amplitudes

$$\sum_{\lambda} A_{\lambda}^{(L)} r_{\lambda}^{(L)} = 0 \quad (3.29)$$

that follow from the set of right null eigenvectors (3.28) can be written in terms of eq. (3.2) to yield the constraints (1.3)-(1.8) given in the introduction.

Since there are generally four<sup>5</sup> linearly-independent null eigenvectors in a  $(3L+3)$ -dimensional trace space, the space of  $L$ -loop color factors satisfying eq. (3.25) is generally  $(3L-1)$ -dimensional.<sup>6</sup> Since there are no further independent solutions of eq. (3.27), we have shown that the full space of  $L$ -loop color factors is *at least*  $(3L-1)$ -dimensional.

We have not strictly shown that eq. (3.28) are null eigenvectors for *any* possible color factor associated with an  $L$ -loop diagram, but rather only for those that can be obtained from an  $(L-1)$ -loop diagram by attaching a rung between two external legs. It is therefore conceivable (but we think unlikely) that the space of *all*  $L$ -loop color factors could be greater than  $(3L-1)$ -dimensional. However, for  $L=3$  and  $L=4$ , it has been shown [24] that, despite the fact that many diagrams cannot be obtained by attaching a rung to the external legs of lower-loop diagrams, all color factors can be related to these using Jacobi relations (see the appendix for further discussion of  $L=3$  and  $L=4$ ). It would be nice to have a proof of this for all  $L$ , however.

## 4 Conclusions

In this note, we have extended known group theory identities for four-point color-ordered amplitudes in  $SU(N)$  gauge theories to all loop orders. We have shown that color-ordered amplitude generally must satisfy four independent relations at each loop order (except for  $L=0$  and  $L=1$ , where there are one and three constraints respectively). This was achieved via a recursive procedure that derives the constraints on  $L$ -loop color factors generated by attaching a rung between two external legs of an  $(L-1)$ -loop color factor. Assuming that all  $L$ -loop color factors are linear combinations of those just described (i.e., via Jacobi relations), then the constraints derived apply to all  $L$ -loop color-ordered amplitudes. Although this has been established through four loops, it would clearly be desirable to have an all-orders proof of this assumption.

---

<sup>5</sup>One for  $L=0$  and three for  $L=1$ .

<sup>6</sup>Two-dimensional for  $L=0$  and three-dimensional for  $L=1$ .

The recursive method employed in this note can also be extended to  $n$ -point functions with  $n > 4$  to yield constraints on the color-ordered amplitudes beyond those already known at tree- [13] and one-loop [14, 15] level, although the size of the color basis grows quickly with  $n$ .

## Acknowledgments

It is a pleasure to thank L. Dixon for valuable correspondence.

## A Appendix

In appendix B of ref. [24], bases for the space of all three- and four-loop color factors were identified. In this appendix, we explicitly check that the right null eigenvectors of these spaces coincide with our recursive solution (3.28), and therefore that all three- and four-loop color-ordered amplitudes indeed satisfy the group theory constraints eqs. (1.3)-(1.8).

The basis for three-loop color factors can be chosen as  $N^3 C_{st}^{(0)}$ ,  $N^3 C_{ts}^{(0)}$ ,  $N^2 C_{st}^{(1)}$ ,  $N C_{st}^{(2L)}$ , and  $N C_{ts}^{(2L)}$ , plus the color factor for the three-loop ladder diagram

$$C_{st}^{(3L)} = t_1^{(3)} + 14t_6^{(3)} + 2t_7^{(3)} + 2t_8^{(3)} + 8t_{10}^{(3)} + 8t_{11}^{(3)} + 8t_{12}^{(3)} \quad (\text{A.1})$$

and two of its permutations,<sup>7</sup>  $C_{ts}^{(3L)}$  and  $C_{us}^{(3L)}$ , yielding the transformation matrix

$$M_{i\lambda}^{(3)} = \begin{pmatrix} 1 & 0 & -1 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 \\ 1 & -1 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 \\ 1 & 0 & 0 & 2 & 2 & 2 & 0 & 0 & 0 & 0 & 0 & 0 \\ 1 & 0 & 0 & 0 & 0 & 6 & 2 & 2 & -4 & 0 & 0 & 0 \\ 1 & 0 & 0 & 0 & 6 & 0 & 2 & -4 & 2 & 0 & 0 & 0 \\ 1 & 0 & 0 & 0 & 0 & 14 & 2 & 2 & 0 & 8 & 8 & 8 \\ 1 & 0 & 0 & 0 & 14 & 0 & 2 & 0 & 2 & 8 & 8 & 8 \\ 0 & 1 & 0 & 14 & 0 & 0 & 0 & 2 & 2 & 8 & 8 & 8 \end{pmatrix}. \quad (\text{A.2})$$

The four independent right null eigenvectors of this matrix

$$r^{(3)} = \begin{pmatrix} 6u \\ -u \\ 2u \\ 0 \end{pmatrix}, \quad \begin{pmatrix} 0 \\ 0 \\ 6u \\ -u \end{pmatrix}, \quad \begin{pmatrix} 0 \\ 0 \\ 0 \\ x \end{pmatrix}, \quad \begin{pmatrix} 0 \\ 0 \\ 0 \\ y \end{pmatrix} \quad (\text{A.3})$$

agree with those in eq. (3.28), and imply the four constraints among the color-ordered amplitudes given by eqs. (1.6)-(1.8) with  $L = 3$ .

---

<sup>7</sup> Only  $C_{st}^{(3L)}$  is used in ref. [24], but the authors also include  $N C_{st}^{(0)}$  and  $N C_{ts}^{(0)}$  in their basis, which in our approach are independent of  $N^3 C_{st}^{(0)}$  and  $N^3 C_{ts}^{(0)}$ .

The four-loop color basis can be chosen as ( $N$  times) the three-loop basis plus three color factors from the four-loop ladder diagram and two<sup>8</sup> permutations,  $C_{st}^{(4L)}$ ,  $C_{ts}^{(4L)}$ , and  $C_{us}^{(4L)}$ , yielding

$$M_{i\lambda}^{(4)} = \begin{pmatrix} 1 & 0 & -1 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 \\ 1 & -1 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 \\ 1 & 0 & 0 & 2 & 2 & 2 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 \\ 1 & 0 & 0 & 0 & 0 & 6 & 2 & 2 & -4 & 0 & 0 & 0 & 0 & 0 & 0 \\ 1 & 0 & 0 & 0 & 6 & 0 & 2 & -4 & 2 & 0 & 0 & 0 & 0 & 0 & 0 \\ 1 & 0 & 0 & 0 & 0 & 14 & 2 & 2 & 0 & 8 & 8 & 8 & 0 & 0 & 0 \\ 1 & 0 & 0 & 0 & 14 & 0 & 2 & 0 & 2 & 8 & 8 & 8 & 0 & 0 & 0 \\ 0 & 1 & 0 & 14 & 0 & 0 & 0 & 2 & 2 & 8 & 8 & 8 & 0 & 0 & 0 \\ 1 & 0 & 0 & 0 & 0 & 30 & 2 & 2 & 0 & 0 & 0 & 24 & 8 & 8 & 16 \\ 1 & 0 & 0 & 0 & 30 & 0 & 2 & 0 & 2 & 0 & 24 & 0 & 8 & 16 & 8 \\ 0 & 1 & 0 & 30 & 0 & 0 & 0 & 2 & 2 & 24 & 0 & 0 & 16 & 8 & 8 \end{pmatrix}. \quad (\text{A.4})$$

The four independent right null eigenvectors of this matrix

$$r^{(4)} = \begin{pmatrix} 0 \\ 0 \\ 6u \\ -u \\ 0 \end{pmatrix}, \quad \begin{pmatrix} 0 \\ 0 \\ 0 \\ x \\ x \end{pmatrix}, \quad \begin{pmatrix} 0 \\ 0 \\ 0 \\ y \\ y \end{pmatrix}, \quad \begin{pmatrix} 0 \\ 0 \\ 0 \\ 0 \\ u \end{pmatrix}, \quad (\text{A.5})$$

agree with those in eq. (3.28). The right null eigenvalues imply the four relations among color-ordered amplitudes given by eqs. (1.3)-(1.5) for  $L = 4$ .

## References

- [1] Z. Bern, J. J. M. Carrasco and H. Johansson, “*New Relations for Gauge-Theory Amplitudes*”, Phys. Rev. D78, 085011 (2008), [arxiv:0805.3993](#).
- [2] Z. Bern, J. J. M. Carrasco and H. Johansson, “*Perturbative Quantum Gravity as a Double Copy of Gauge Theory*”, Phys. Rev. Lett. 105, 061602 (2010), [arxiv:1004.0476](#).
- [3] N. E. J. Bjerrum-Bohr, P. H. Damgaard and P. Vanhove, “*Minimal Basis for Gauge Theory Amplitudes*”, Phys. Rev. Lett. 103, 161602 (2009), [arxiv:0907.1425](#).
- [4] S. Stieberger, “*Open and Closed vs. Pure Open String Disk Amplitudes*”, [arxiv:0907.2211](#).
- [5] B. Feng, R. Huang and Y. Jia, “*Gauge Amplitude Identities by On-shell Recursion Relation in S-matrix Program*”, Phys. Lett. B695, 350 (2011), [arxiv:1004.3417](#).
- [6] Y.-X. Chen, Y.-J. Du and B. Feng, “*A Proof of the Explicit Minimal-basis Expansion of Tree Amplitudes in Gauge Field Theory*”, JHEP 1102, 112 (2011), [arxiv:1101.0009](#).

---

<sup>8</sup> Only  $C_{st}^{(4L)}$  and  $C_{ts}^{(4L)}$  are used in ref. [24], but the authors also include  $NC_{st}^{(1)}$ , which in our approach counts as independent from  $N^3C_{st}^{(1)}$ .

- [7] J. J. M. Carrasco and H. Johansson, “*Generic multiloop methods and application to  $N=4$  super-Yang-Mills*”, [arxiv:1103.3298](#).
- [8] J. J. M. Carrasco and H. Johansson, “*Five-Point Amplitudes in  $N=4$  Super-Yang-Mills Theory and  $N=8$  Supergravity*”, [arxiv:1106.4711](#).
- [9] Z. Bern, C. Boucher-Veronneau and H. Johansson, “ *$N \geq 4$  Supergravity Amplitudes from Gauge Theory at One Loop*”, [arxiv:1107.1935](#).
- [10] T. Sondergaard, “*Perturbative Gravity and Gauge Theory Relations – A Review*”, [arxiv:1106.0033](#).
- [11] M. B. Green, J. H. Schwarz and L. Brink, “ *$N=4$  Yang-Mills and  $N=8$  Supergravity as Limits of String Theories*”, Nucl. Phys. B198, 474 (1982).
- [12] M. L. Mangano and S. J. Parke, “*Multi-Parton Amplitudes in Gauge Theories*”, Phys. Rept. 200, 301 (1991), [hep-th/0509223](#).
- [13] R. Kleiss and H. Kuijf, “*Multi-gluon cross-sections and five jet production at hadron colliders*”, Nucl. Phys. B312, 616 (1989).
- [14] Z. Bern and D. A. Kosower, “*Color decomposition of one loop amplitudes in gauge theories*”, Nucl.Phys. B362, 389 (1991).
- [15] Z. Bern, L. J. Dixon, D. C. Dunbar and D. A. Kosower, “*One-Loop  $n$ -Point Gauge Theory Amplitudes, Unitarity and Collinear Limits*”, Nucl. Phys. B425, 217 (1994), [hep-ph/9403226](#).
- [16] Z. Bern, A. De Freitas and L. J. Dixon, “*Two loop helicity amplitudes for gluon-gluon scattering in QCD and supersymmetric Yang-Mills theory*”, JHEP 0203, 018 (2002), [hep-ph/0201161](#).
- [17] V. Del Duca, A. Frizzo and F. Maltoni, “*Factorization of tree QCD amplitudes in the high-energy limit and in the collinear limit*”, Nucl. Phys. B568, 211 (2000), [hep-ph/9909464](#).
- [18] V. Del Duca, L. J. Dixon and F. Maltoni, “*New color decompositions for gauge amplitudes at tree and loop level*”, Nucl. Phys. B571, 51 (2000), [hep-ph/9910563](#).
- [19] Z. Bern, J. S. Rozowsky and B. Yan, “*Two-loop four-gluon amplitudes in  $N = 4$  super-Yang-Mills*”, Phys. Lett. B401, 273 (1997), [hep-ph/9702424](#).
- [20] N. E. J. Bjerrum-Bohr, P. H. Damgaard, H. Johansson and T. Sondergaard, “*Monodromy-like Relations for Finite Loop Amplitudes*”, JHEP 1105, 039 (2011), [arxiv:1103.6190](#).
- [21] B. Feng, Y. Jia and R. Huang, “*Relations of loop partial amplitudes in gauge theory by Unitarity cut method*”, Nucl.Phys. B854, 243 (2012), [arxiv:1105.0334](#).
- [22] R. H. Boels and R. S. Isermann, “*New relations for scattering amplitudes in Yang-Mills theory at loop level*”, [arxiv:1109.5888](#).
- [23] S. G. Naculich and H. J. Schnitzer, “*One-loop SYM-supergravity relation for five-point amplitudes*”, [arxiv:1108.6326](#).
- [24] Z. Bern, J. J. M. Carrasco, L. J. Dixon, H. Johansson and R. Roiban, “*The Complete Four-Loop Four-Point Amplitude in  $N=4$  Super- Yang-Mills Theory*”, Phys. Rev. D82, 125040 (2010), [arxiv:1008.3327](#).
- [25] E. W. N. Glover, C. Oleari and M. E. Tejeda-Yeomans, “*Two-loop QCD corrections to gluon gluon scattering*”, Nucl. Phys. B605, 467 (2001), [hep-ph/0102201](#).