

Demonstration of quantum permutation algorithm with a single photon ququart

Feiran Wang, Yunlong Wang, Ruifeng Liu, Dongxu Chen, Pei Zhang,* Hong Gao, and Fuli Li
*MOE Key Laboratory for Nonequilibrium Synthesis and Modulation of Condensed Matter,
and Department of Applied Physics,
Xi'an Jiaotong University, Xi'an 710049, China.*

Abstract

We report an experiment to demonstrate a quantum permutation determining algorithm with linear optical system. By employing photon polarization and spatial modes, we realize the quantum ququart states and all the essential permutation transformations. Compared with the classical case, this work determines the parity of the permutation in only one step of evaluation and displays the remarkable speedup of quantum algorithm. This experiment is accomplished in single photon level and exhibits strong universality in quantum computation.

Permutation problem, Quantum algorithm, Quantum computation

* zhangpei@mail.ustc.edu.cn

Introduction

As quantum counterpart of classical computer, quantum computer reveals incredible efficiency to execute arithmetic tasks and threatens the security of classical communication. Quantum algorithm is the sole of quantum computation, and it shows the amazing power of quantum parallelism and utilizes quantum interference to get the expected result, therefore it attracts particular concern to develop new quantum algorithm in recent years. The concept of simulating physics progresses with quantum computers was originated in Richard Feynman's observation that computers built from quantum mechanical components would be ideally suited to simulating quantum mechanics [1]. Since then, the first efficient quantum algorithm was proposed by Deutsch in 1985 [2] and generalized by Deutsch and Jozsa in 1987 [3]. Lately, an increasing number of practical programs are presented, such as factoring large integer [4], Grover's searching algorithm for database [5] and Simon's exponential acceleration algorithm for the black box problem [6]. What's more, Harrow *et al.* in Bristol came up with a quantum scheme to decrease the computational complexity of solving linear system of equations from $O(n)$ to $\log(n)$, and this is the first quantum algorithm to work out the most fundamental problems in engineering science [7]. Some quantum algorithms have been demonstrated in different physical systems, such as ion traps [8–11], superconducting devices [12–14], optical lattices [15, 16], quantum dots [17, 18], and linear optics [19–23]. Linear optical system is potential to realize quantum computer, due to its good scalability, easy-handling and high stability, and it is a good candidate for implementing quantum algorithms.

A new algorithm based on quantum Fourier transformation has been proposed to identify the parity of a permutation recently [24]. The permutation problem can be described as a black box problem, which is to determine the parity of the permutation based on the n input and output states of black box. For example, in a set of six different possible permutations (1,2,3), (2,3,1), (3,1,2), (3,2,1), (2,1,3) and (1,3,2), the first three are positive cyclic or even permutations while the last three are negative cyclic or odd permutations. If we treat permutation operation as a function $f(x)$ defined on the set $x \in \{1, 2, 3\}$, determination of parity requires the evaluation of $f(x)$ for at least two different input values of x with classical algorithm.

In this article, we consider four orthonormal states, i.e., $|1\rangle = (1, 0, 0, 0)^T$, $|2\rangle = (0, 1, 0, 0)^T$, $|3\rangle = (0, 0, 1, 0)^T$, and $|4\rangle = (0, 0, 0, 1)^T$, and the bijection is $f: \{1, 2, 3, 4\} \rightarrow$

$\{1, 2, 3, 4\}$. For the input state $(1, 2, 3, 4)$, there are eight different possible output states. These eight states and the corresponding transformations are divided into two categories as mentioned above. The positive cyclic permutations and the corresponding unitary transformations are:

$$f_1 = \begin{pmatrix} 1 & 2 & 3 & 4 \\ 1 & 2 & 3 & 4 \end{pmatrix}, f_2 = \begin{pmatrix} 1 & 2 & 3 & 4 \\ 2 & 3 & 4 & 1 \end{pmatrix}, f_3 = \begin{pmatrix} 1 & 2 & 3 & 4 \\ 3 & 4 & 1 & 2 \end{pmatrix}, f_4 = \begin{pmatrix} 1 & 2 & 3 & 4 \\ 4 & 1 & 2 & 3 \end{pmatrix},$$

$$U_1 = \begin{pmatrix} 1 & 0 & 0 & 0 \\ 0 & 1 & 0 & 0 \\ 0 & 0 & 1 & 0 \\ 0 & 0 & 0 & 1 \end{pmatrix}, U_2 = \begin{pmatrix} 0 & 1 & 0 & 0 \\ 0 & 0 & 1 & 0 \\ 0 & 0 & 0 & 1 \\ 1 & 0 & 0 & 0 \end{pmatrix}, U_3 = \begin{pmatrix} 0 & 0 & 1 & 0 \\ 0 & 0 & 0 & 1 \\ 1 & 0 & 0 & 0 \\ 0 & 1 & 0 & 0 \end{pmatrix}, U_4 = \begin{pmatrix} 0 & 0 & 0 & 1 \\ 1 & 0 & 0 & 0 \\ 0 & 1 & 0 & 0 \\ 0 & 0 & 1 & 0 \end{pmatrix}, \quad (1)$$

and the negative cyclic permutations and the corresponding unitary transformations are:

$$f_5 = \begin{pmatrix} 1 & 2 & 3 & 4 \\ 4 & 3 & 2 & 1 \end{pmatrix}, f_6 = \begin{pmatrix} 1 & 2 & 3 & 4 \\ 3 & 2 & 1 & 4 \end{pmatrix}, f_7 = \begin{pmatrix} 1 & 2 & 3 & 4 \\ 2 & 1 & 4 & 3 \end{pmatrix}, f_8 = \begin{pmatrix} 1 & 2 & 3 & 4 \\ 1 & 4 & 3 & 2 \end{pmatrix},$$

$$U_5 = \begin{pmatrix} 0 & 0 & 0 & 1 \\ 0 & 0 & 1 & 0 \\ 0 & 1 & 0 & 0 \\ 1 & 0 & 0 & 0 \end{pmatrix}, U_6 = \begin{pmatrix} 0 & 0 & 1 & 0 \\ 0 & 1 & 0 & 0 \\ 1 & 0 & 0 & 0 \\ 0 & 0 & 0 & 1 \end{pmatrix}, U_7 = \begin{pmatrix} 0 & 1 & 0 & 0 \\ 1 & 0 & 0 & 0 \\ 0 & 0 & 0 & 1 \\ 0 & 0 & 1 & 0 \end{pmatrix}, U_8 = \begin{pmatrix} 1 & 0 & 0 & 0 \\ 0 & 0 & 0 & 1 \\ 0 & 0 & 1 & 0 \\ 0 & 1 & 0 & 0 \end{pmatrix}. \quad (2)$$

The black box can be considered as a special device which can realize the corresponding operation for a given permutation task.

To determine the parity, a direct running of the operator on the eigen states of ququart will not work. Therefore at least twice runnings are needed to evaluate the box parity as in the classical case. For example, if we input a state $|2\rangle$ and get the output state $|4\rangle$, this progress corresponds to two possible permutation transformations f_3 and f_8 . So to determine the parity of permutation, we need at least another running.




FIG. 1. **Quantum circuit to realize the permutation algorithm.** U_{FT} denotes the Fourier transformation. The black box contains all the eight permutation operators in the algorithm and U_{FT}^\dagger is the inverse Fourier transformation.

Fig. 1 gives the quantum circuit to realize the permutation algorithm. Considering the quantum algorithm of this task, we start from a superposition state:

$$|\psi_{in}\rangle = |\psi_2\rangle = (|1\rangle + i|2\rangle - |3\rangle - i|4\rangle) / 2, \quad (3)$$

here $|\psi_j\rangle = U_{FT}|j\rangle$, ($j = 1, 2, 3, 4$) which is generated by quantum Fourier transform U_{FT} :

$$U_{FT} = \frac{1}{2} \begin{pmatrix} 1 & 1 & 1 & 1 \\ 1 & i & -1 & -i \\ 1 & -1 & 1 & -1 \\ 1 & -i & -1 & i \end{pmatrix}. \quad (4)$$

Then the input state get through the black box, and the output states can be written as

$$|\psi_{out}\rangle_{f_k} \equiv U_k |\psi_{in}\rangle = \frac{(|f_k(1)\rangle + i|f_k(2)\rangle - |f_k(3)\rangle - i|f_k(4)\rangle)}{2}, \quad (5)$$

where $k = 1, 2, \dots, 8$ label eight permutation transformations. Application of U_k on the input state $|\psi_{in}\rangle$ gives $|\psi_2\rangle$ for even f_k and it gives $|\psi_4\rangle$ for odd f_k . By employing the inverse Fourier transform U_{FT}^\dagger and checking the final state, we will know the parity of permutation is even (odd) when we acquire the state $|2\rangle$ ($|4\rangle$). Thus, the quantum algorithm allows us to determine the parity of a cyclic permutation with single evaluation of the permutation function instead of two.

Reviewing this algorithm, the Fourier transform U_{FT} and inverse Fourier transform U_{FT}^\dagger are not necessary if we can directly prepare the superposition state $|\psi_2\rangle$ and discriminate the output state $|\psi_2\rangle$ and $|\psi_4\rangle$. Luckily, by employing the photon's polarization and spatial mode, we can easily realize the ququart $|\psi_2\rangle$ and distinguish $|\psi_2\rangle$ and $|\psi_4\rangle$ in our experiment. We should address that $|\psi_4\rangle$ is also a proper input state for the permutation discrimination, and in our experiment, we demonstrate the algorithm for both $|\psi_2\rangle$ and $|\psi_4\rangle$.

Results

In this context, we utilize photon's polarization and spatial mode to code the ququart [22], and we carry out the whole eight different permutations in a black box which is composed by Dove prism (DP) and half wave plates (HWP). Combining the polarization and spatial mode as composite quantum state, the four states of ququart can be defined as

$$|H, l\rangle \rightarrow |1\rangle, |H, r\rangle \rightarrow |2\rangle, |V, l\rangle \rightarrow |3\rangle, |V, r\rangle \rightarrow |4\rangle, \quad (6)$$

where H (V) represents horizontal (vertical) polarization and r (l) represents right (left) spatial mode. The input state $|\psi_2\rangle$ can be written in the form

$$|\psi_2\rangle = |H, l\rangle + i|H, r\rangle - |V, l\rangle - i|V, r\rangle. \quad (7)$$

Then the black box will carry out the permutation transformation on $|\psi_2\rangle$. For example, suppose the operation is f_2 , the output state after black box can be expressed as $|H, r\rangle + i|V, l\rangle - |V, r\rangle - i|H, l\rangle$, which is equal to $-i|\psi_2\rangle$.




FIG. 2. Experimental setup of permutation algorithm. (a) The single photon source is achieved by deeply attenuating coherent light into single photon level. P denotes the polarizer for preparing horizontal polarization state. HWP3 are used for initial polarization state preparation. Two beam splitters (BS) and four mirrors (M) are used to set up a Mach-Zehnder interferometer. The piezo transmitter (PZT) actuator is used to modulate the phase φ between l and r paths. The black box is used to realize eight permutation transformations. Two detectors (D1 and D2) are single-photon counting module (SPCM-AQRH-14-FC) used to record the count of photons. (b) The black box consists of a DP at 0° and two HWPs at 45° . Different permutation transformation can be achieved by different combination of DP and HWPs.

The sketch of the experimental setup is shown in Fig. 2(a). The source is achieved by deeply attenuating coherent light into single photon level (coherent parameter $\alpha \approx 0.1$). Polarizer (P) and HWP3 are placed to prepare the initial input polarization state and beam

splitter (BS1) is to prepare spatial state. The black box consists of a DP and two HWPs as shown in Fig. 2(b), the dove prism is located at an angle 0° relative to the horizontal plane. Photons with different spatial modes r and l pass through DP will swap their spatial modes, and the polarization will be altered by HWP at 45° succinctly. To realize the permutation transformations with black box, what we need is adding or removing the DP and HWPs.

In this scheme, we prepare the initial polarization state of photon in a superposition state $(|H\rangle - |V\rangle)/\sqrt{2}$, then we transform the spatial mode into $(|l\rangle + |r\rangle)/\sqrt{2}$ by BS1. The relative phase φ between two spatial modes can be adjusted by a PZT mounted on the first reflecting mirror (M1). Thus the input state for the black box can be written as

$$\begin{aligned} |\psi_{in}\rangle &= (|H\rangle - |V\rangle) (|l\rangle + e^{i\varphi}|r\rangle) / 2 \\ &= (|H, l\rangle + e^{i\varphi}|H, r\rangle - |V, l\rangle - e^{i\varphi}|V, r\rangle) / 2. \end{aligned} \quad (8)$$

Especially, when $\varphi = \pi/2$, the initial state $|\psi_{in}\rangle$ turns to be $|\psi_2\rangle$ which is expressed in Eq. (7); when $\varphi = 3\pi/2$, the initial state $|\psi_{in}\rangle$ turns to be $|\psi_4\rangle$. Then the state is injected into the black box to carry out the permutation transformations. The states of $|\psi_2\rangle$ and $|\psi_4\rangle$ in our definition can be discriminated directly by the phase of spatial mode. So different spatial states interfere at the second beam splitter (BS2), and the parity of permutation can be determined by checking which single photon detector (D1 or D2) clicks.

TABLE I. Experimental implementation of eight different permutations

State		H,l	H,r	V,l	V,r	Implementation			Parity
Code		1	2	3	4	DP	HWP1	HWP2	
Bijection	f_1	H,l	H,r	V,l	V,r	No	No	No	even
	f_2	H,r	V,l	V,r	H,l	Yes	Yes	No	even
	f_3	V,l	V,r	H,l	H,r	No	Yes	Yes	even
	f_4	V,r	H,l	H,r	V,l	Yes	No	Yes	even
	f_5	V,r	V,l	H,r	H,l	Yes	Yes	Yes	odd
	f_6	V,l	H,r	H,l	V,r	No	Yes	No	odd
	f_7	H,r	H,l	V,r	V,l	Yes	No	No	odd
	f_8	H,l	V,r	V,l	H,r	No	No	Yes	odd

Implementation of positive cyclic permutation. For the identity operation f_1 , we

remove the DP and HWPs, the input states pass through the setup remain unchanged and we achieve the f_1 operation. For the f_2 operation, DP and HWP1 are required in the setup. When the photons in different paths pass through the DP, they will exchange their paths ($l \rightarrow r$ and $r \rightarrow l$), and the state $|\psi_{in}\rangle$ changes into $|H, r\rangle + e^{i\varphi}|H, l\rangle - |V, r\rangle - e^{i\varphi}|V, l\rangle$. After that, HWP1 at an angle 45° is located at the l path, it will alter horizontal polarization to vertical polarization and vice versa. So far we get the final state $|H, r\rangle + e^{i\varphi}|V, l\rangle - |V, r\rangle - e^{i\varphi}|H, l\rangle$ which is equal to $-i|\psi_2\rangle$ when $\varphi = \pi/2$ and achieve the mapping operation f_2 . The f_3 operation can be carried out similarly by removing the DP and putting HWP1 and HWP2. Analogous to the action above, the last positive cyclic permutation f_4 can be accomplished by inserting DP and HWP2. When photons pass through the device for the positive cyclic permutation, a simple calculation shows the output state $|\psi_{out}\rangle = U_k|\psi_{in}\rangle$ ($k = 1, 2, 3, 4$) as follows:

$$\begin{aligned} |\psi_{out}\rangle_{f_1} &= \left(\frac{|H\rangle - |V\rangle}{\sqrt{2}}\right) \left(\frac{|l\rangle + e^{i\varphi}|r\rangle}{\sqrt{2}}\right); \quad |\psi_{out}\rangle_{f_2} = -e^{i\varphi} \left(\frac{|H\rangle - |V\rangle}{\sqrt{2}}\right) \left(\frac{|l\rangle + e^{i(\pi-\varphi)}|r\rangle}{\sqrt{2}}\right) \\ |\psi_{out}\rangle_{f_3} &= -\left(\frac{|H\rangle - |V\rangle}{\sqrt{2}}\right) \left(\frac{|l\rangle + e^{i\varphi}|r\rangle}{\sqrt{2}}\right); \quad |\psi_{out}\rangle_{f_4} = e^{i\varphi} \left(\frac{|H\rangle - |V\rangle}{\sqrt{2}}\right) \left(\frac{|l\rangle + e^{i(\pi-\varphi)}|r\rangle}{\sqrt{2}}\right). \end{aligned} \quad (9)$$

Implementation of negative cyclic permutation. Firstly we place both DP and HWPs into the optical route to exchange the spatial mode and the polarization. This will be the f_5 gate. If we remove the DP and only place HWP1, when the photons pass this setup, it will go through an f_6 transformation. For the purpose of carrying out f_7 operation, it is easy to obtain that only a DP is needed. The last operation can be achieved by only employing HWP2 to change the polarization mode on the right route. Similarly, we arrive the final output states:

$$\begin{aligned} |\psi_{out}\rangle_{f_5} &= -e^{i\varphi} \left(\frac{|H\rangle - |V\rangle}{\sqrt{2}}\right) \left(\frac{|l\rangle - e^{i(\pi-\varphi)}|r\rangle}{\sqrt{2}}\right); \quad |\psi_{out}\rangle_{f_6} = -\left(\frac{|H\rangle - |V\rangle}{\sqrt{2}}\right) \left(\frac{|l\rangle - e^{i\varphi}|r\rangle}{\sqrt{2}}\right) \\ |\psi_{out}\rangle_{f_7} &= e^{i\varphi} \left(\frac{|H\rangle - |V\rangle}{\sqrt{2}}\right) \left(\frac{|l\rangle - e^{i(\pi-\varphi)}|r\rangle}{\sqrt{2}}\right); \quad |\psi_{out}\rangle_{f_8} = \left(\frac{|H\rangle - |V\rangle}{\sqrt{2}}\right) \left(\frac{|l\rangle - e^{i\varphi}|r\rangle}{\sqrt{2}}\right). \end{aligned} \quad (10)$$

From the above discussion, we carry out all the eight essential transformations for the parity determining algorithm. All the transformations and corresponding implementation approaches are summarized in Table I. In particular, when $\varphi = \frac{\pi}{2}$, the output states in

Eqs. (9) and (10) are equal to $|\psi_2\rangle$ and $|\psi_4\rangle$, respectively. The Eqs. (9) and (10) clearly show that the polarization of output states are same while the relative phase between two spatial modes are different for two types of parity. This means that we can accomplish the identify progress of permutation through the spatial bits without the inverse Fourier transform. After the spatial modes interfered on BS2, we can determine the parity is odd (even) when detector D1 (D2) clicks. With similar analysis, when the input state is $|\psi_4\rangle$ (relative phase $\varphi = \frac{3\pi}{2}$), we can determine the parity is odd (even) when detector D2 (D1) clicks.

We record the photon counts of the two detectors D1 and D2 with 0.5 V a step of the PZT voltage synchronously. Our experimental results are shown in Fig. 3. Figure 3(a) shows the results of positive cyclic permutation transformations from f_1 to f_4 , and Fig. 3(b) gives the results of the remaining four odd operations. The black square spots represent the counts of D1, and the red triangular spots corresponding to the counts of D2. As we discussed above, when the relative phase φ is equal to $(2N + 1/2)\pi$, where N is an integer, only detector D1 clicks for the odd parity and D2 clicks for the even parity. These special points are pointed out by the green dashed line, and from these points we can get the parity information of the permutation evidently. Analogously, when the relative phase φ is equal to $(2N + 3/2)\pi$, we still can determine the parity by the blue dashed line labelled in Fig. 3.

Discussion

We define $\eta = |C_{D1} - C_{D2}|/|C_{D1} + C_{D2}|$ as the contrast ratio to evaluate the accuracy of our experiment, where C_{D1} and C_{D2} denote the photon counts of D1 and D2, respectively. Theoretically, the contrast ratio η is equal to 1. In our experiment, The contrast ratio is up to $96 \pm 2\%$ for all eight cases in Fig. 3. The error and the small shift of the dashed line for different permutations mainly comes from the imperfection of optical devices and moving or adding DP and HWPs.

In conclusion, we briefly introduce the quantum permutation algorithm and put forward a scheme to implement this algorithm by employing linear optical element. The main point to achieve the parity determining algorithm is the bijection operator and recognize the parity through the output states from the two detectors. By using composite quantum bit to realize ququart, our experiment is greatly simplified both in state preparation and




FIG. 3. **Experimental data of the parity determining algorithm.** (a) positive cyclic permutation operation, (b) negative cyclic permutation operation. Black square dots show the photon counts of D1 , and red triangle points show the photon counts of D2. Fitting lines are also shown. Green (blue) dashed vertical lines are used to mark the proper points (phases) of the initial states $|\psi_2\rangle$ ($|\psi_4\rangle$), which can be used to perfectly discriminate the two kinds of functions.

state discrimination, where Fourier transformations U_{FT} and U_{FT}^\dagger are saved. Although this algorithm only provide a two to one speed-up towards classical case, it shows the power of quantum parallelism and quantum computation validly, and expand our thinking for more efficient algorithms. We noticed that this scheme has also been realized in spin- $\frac{3}{2}$ NMR quadrupolar system with four energy levels [25, 26].

Method

Figure 2 displays the setup needed in the experimental progress. For the specific operation such as f_2 , we only need one HWP at 45° in the left route, however, this HWP gives an additional phase because of the intrinsic thickness. With the purpose of eliminating this extra effects, we put another HWP at 0° in the right path to compensate phase without changing the polarization. We also need to calibrate the voltage of PZT to confirm the initial state is proper prepared before the experiment proper starts.

-
- [1] Feynman, R. P. Simulating Physics with Computers, *Int. J. Theor. Physics.* **21**, 467-488 (1982).
 - [2] Deutsch, D. Quantum Theory, the Church-Turing Principle and the Universal Quantum Computer. *Proc. R. Soc. Lond. A.* **400**, 97-117 (1985).
 - [3] Deutsch, D., & Jozsa, R. Rapid solution of problems by quantum computation. *Proc. R. Soc. A* **439**, 553 (1992).
 - [4] Shor, P. W. Algorithms for quantum computation: discrete logarithms and factoring. *IEEE Comp. Soc.* **11**, 124-134 (1994).
 - [5] Grover, L. K. A fast quantum mechanical algorithm for database search. *Proceedings of the Twenty-Eighth Annual Symposium on the Theory of Computing, 1996, Philadelphia, Pennsylvania.* 212-218 (1996).
 - [6] Simon, D.R. On the power of quantum computation. *Foundations of Computer Science, 1994 Proceedings., 35th Annual Symposium on:* 116-123 (1994).
 - [7] Harrow, A. W., Hassidim, A., & Lloyd, S. Quantum algorithm for linear systems of equations. *Phys. Rev. Lett.* **103**, 150502 (2009).
 - [8] Cirac, J.I., & Zoller, P. Quantum computations with cold trapped ions. *Phys. Rev. Lett.* **74**, 4091 (1995).
 - [9] Blatt, R., & Wineland, D. Entangled states of trapped atomic ions. *Nature* **453**, 1008-1015 (2008).
 - [10] Lanyon, B. P. *et al.* Universal digital quantum simulation with trapped ions. *Science* **334**, 57 (2011).
 - [11] Lanyon, B. P. *et al.* Measurement-based quantum computation with trapped ions *Phys. Rev.*

- Lett.* **111**, 210501 (2013).
- [12] Nakamura, Y., Pashkin, Y. A., & Tsai J. S. Coherent control of macroscopic quantum states in a single-Cooper-pair box. *Nature* **398**, 786-788 (1999).
 - [13] DiCarlo, L. *et al.* Demonstration of two-qubit algorithms with a superconducting quantum processor. *Nature* **460**, 240-244 (2009).
 - [14] Bialczak, R. C. *et al.* Quantum process tomography of a universal entangling gate implemented with Josephson phase qubits. *Nat. Phys.* **6**, 409 (2010).
 - [15] Jaksch, D. Optical lattices, ultracold atoms and quantum information processing. *Contemp. Phys.* **45**, 367 (2004).
 - [16] Bloch, I. Quantum coherence and entanglement with ultracold atoms in optical lattices. *Nature* **453**, 1016-1022 (2008).
 - [17] Berezovsky, J., Mikkelsen, M. H., Stoltz, N. G., Coldren, L. A., & Awschalom, D. D. Picosecond coherent optical manipulation of a single electron spin in a quantum dot. *Science* **320**, 349-352 (2008).
 - [18] Fushman, I. *et al.* Controlled phase shifts with a single quantum dot. *Science* **320**, 769-772 (2008).
 - [19] Knill, E., Laflamme, R., & Milburn, G. J. A scheme for efficient quantum computation with linear optics. *Nature* **409**, 46-52 (2001).
 - [20] O'Brien, J. L., Pryde, G. J., White, A. G., Ralph, T. C. & Branning, D. Demonstration of an all-optical quantum controlled-NOT gate. *Nature* **426**, 264-267 (2003).
 - [21] Mohseni, M., Lundeen, J. S., Resch, K. J., & Steinberg, A. M. Experimental application of decoherence-free subspaces in an optical quantum-computing algorithm. *Phys. Rev. Lett.* **91**, 187903 (2003).
 - [22] Zhang, P., Liu, R. F., Huang, Y. F., Gao, H. & Li, F. L. Demonstration of Deutsch's algorithm on a stable linear optical quantum computer. *Phys. Rev. A* **82**, 064302 (2010).
 - [23] Tame, M. S., Bell, B. A., Di Franco, C., Wadsworth, W. J. , & Rarity, J. G. Experimental Realization of a One-Way Quantum Computer Algorithm Solving Simon's Problem. *Phys. Rev. Lett.* **113**, 200501 (2014).
 - [24] Gedik, Z. Computational Speed-up with a Single Qutrit. *arXiv*: 1403. 5861v2 (2014).
 - [25] Dogra, S., Arvind, & Dorai, K. Determining the parity of a permutation using an experimental NMR qutrit. *arXiv*: 1406. 5026v1 (2014).

- [26] Silva, I. A., Vidoto, E. L. G., Soares-Pinto, D. O., deAzevedo, E. R., Cakmak, B., Karpat, G., Fanchini, F. F. & Gedik, Z. Experimental demonstration of computational speed-up with a single ququart. *arXiv*: 1406. 3579v1 (2014).

Acknowledgements

This work is supported by the Fundamental Research Funds for the Central Universities and the National Natural Science Foundation of China (Grant Nos. 11374008, 11374238 and 11374239).

Author contributions

P.Z. conceived and designed the experiment. F.W. and Y.W. performed the experiment and collected the data. F.W., R.L. and D.C. carried out theoretical calculations. F.W., Y.W., R.L., P.Z. H.G. and F.L. contributed to writing the manuscript.