Quantum communication protocols based on entanglement swapping

Guillermo Morales-Luna

Computer Science Department, CINVESTAV-IPN, Mexico City, Mexico

E-mail: gmorales@cs.cinvestav.mx

January 2015

Abstract. We recall several cryptographic protocols based on entanglement alone and also on entanglement swapping. We make an exposition in terms of the geometrical aspects of the involved Hilbert spaces, and we concentrate on the formal nature of the used transformations.

1. Introduction

Entanglement has been widely exploited in the design of protocols and procedures for communication, cryptography and computation within quantum contexts. Quantum codes guarantee that information has been transmitted without any alteration. Cryptographic protocols aid for key agreement of for secure communication, namely unconditionally secure information exchange. Entanglement has been used to implement and to speed-up paradigmatic quantum algorithms (Gisin, Ribordy, Tittel and Zbinden, 2002; Lanyon, Weinhold, Langford, Barbieri, James, Gilchrist and White, 2007).

Entanglement swapping may entangle two quantum systems without direct interaction among them, and this fact is exploited within several quantum cryptography schemes.

Here, we recall several well known cryptographic protocols using entanglement, alone, and entanglement swapping: the *Quantum Secure Direct Communication Protocol* (see table 3 below) communicates securely bit strings with an even length, the *Quantum Bidirectional Communication Protocol* (see table 4 below) is a generalization of the above protocol in which the communicating parts exchange simultaneously messages of even bit length, the *Quantum Multidirectional Communication Protocol* (see table 8 below) allows the message exchange among three parts using the maximally entangled GHZ states, at table 9 we recall a three parties protocol in which two correspondents communicate securely just after the authorisation of a third party (who does not catch the message exchange), and finally, the *Key Agreement Protocol Using Entanglement Swapping* is sketched at table 10 in order to illustrate the use of entanglement swapping in cryptographic protocols.

	$ 0\rangle$	$ 1\rangle$	\mathbf{h}_0	\mathbf{h}_1
σ_0	$ 0\rangle$	$ 1\rangle$	\mathbf{h}_0	\mathbf{h}_1
σ_1	$ 1\rangle$	$ 0\rangle$	\mathbf{h}_0	$-\mathbf{h}_1$
σ_2	$-i 1\rangle$	$i 0\rangle$	$i\mathbf{h}_1$	$-i \mathbf{h}_0$
σ_3	$ 0\rangle$	$- 1\rangle$	\mathbf{h}_1	\mathbf{h}_0

Table 1. Action of the Pauli operators on basis vectors

We emphasise the algebraic aspect of the Hilbert space nature of all the involved protocols. We establish a correspondence among unitary transforms, obtained as tensor products of Pauli maps, and permutations of basic vectors in the Hilbert spaces. These correspondence are summarised at tables 2 and 6. Also, explicit expressions of the Bell basis, in terms of the Hadamard basis are given.

For any two integer numbers $i, j \in \mathbb{Z}^+$, with $i \leq j$, let us write

$$[[i, j]] = \{i, i+1, \dots, j-1, j\}.$$

2. Qubits and Pauli transforms

Let $\mathbb{H}_1 = \mathbb{C}^2$ be the two-dimensional complex Hilbert space. The unit sphere of \mathbb{H}_1 is the set of *qubits*. The *canonical basis* consists of the vectors $\mathbf{e}_0 = [1 \ 0]^T$ and $\mathbf{e}_1 = [0 \ 1]^T$. Usually, it is written $|0\rangle = \mathbf{e}_0$ and $|1\rangle = \mathbf{e}_1$. Let $\mathbf{h}_0 = \frac{1}{\sqrt{2}}(|0\rangle + |1\rangle)$ and $\mathbf{h}_1 = \frac{1}{\sqrt{2}}(|0\rangle - |1\rangle)$ be the vectors forming the *Hadamard basis* at \mathbb{H}_1 .

Let us consider the Pauli operators

$$\sigma_0 = \begin{pmatrix} 1 & 0 \\ 0 & 1 \end{pmatrix}, \quad \sigma_x = \begin{pmatrix} 0 & 1 \\ 1 & 0 \end{pmatrix}$$
$$\sigma_y = \begin{pmatrix} 0 & -i \\ i & 0 \end{pmatrix}, \quad \sigma_z = \begin{pmatrix} 1 & 0 \\ 0 & -1 \end{pmatrix}$$
(1)

and let us number them as $[\sigma_0 \ \sigma_1 \ \sigma_2 \ \sigma_3] = [\sigma_0 \ \sigma_x \ \sigma_y \ \sigma_z]$. The action of these operators over the vectors at the canonical and the Hadamard basis is sketched at table 1. At each entry is located the value of σ_i at the vector labeling the corresponding column. We see that, up to a factor which is an unitary complex number, the canonical basis remains fixed by σ_0 and σ_3 and is switched by σ_1 and σ_2 while the Hadamard basis remains fixed by σ_0 and σ_1 and is switched by σ_2 and σ_3 . Thus, the operator σ_2 is switching both basis.

Let $\mathbb{H}_2 = \mathbb{H}_1 \otimes \mathbb{H}_1$ be the Hilbert space containing the 2-quregisters. Any 2quregister **x** has two components \mathbf{x}_0 and \mathbf{x}_1 , each at the factor space \mathbb{H}_1 , they are qubits. Let for $i, j \in [0, 1]$,

$$\mathbf{b}_{ij} = \frac{1}{\sqrt{2}} \left(|0i\rangle + (-1)^j \left| 1\overline{i} \right\rangle \right),$$

ℓ	eta_ℓ	$A_2^{-1}(\beta_\ell)$
0	$\begin{bmatrix} 0 & 1 & 2 & 3 \end{bmatrix}$	$\{\sigma_{00}, \sigma_{01}, \sigma_{02}, \sigma_{03}\}$
1	$[2 \ 3 \ 0 \ 1]$	$\{\sigma_{01}, \sigma_{00}, \sigma_{03}, \sigma_{02}\}$
2	$\begin{bmatrix} 3 & 2 & 1 & 0 \end{bmatrix}$	$\{\sigma_{02}, \sigma_{03}, \sigma_{00}, \sigma_{01}\}$
3	$[1 \ 0 \ 3 \ 2]$	$\{\sigma_{03}, \sigma_{02}, \sigma_{01}, \sigma_{00}\}$

Table 2. Correspondence on permutations of the Bell basis and tensor products ofPauli operators

here the overline denotes complement modulus 2. Then $B = (\mathbf{b}_{ij})_{i,j \in [0,1]}$ is the Bell basis of \mathbb{H}_2 and consists of four maximally entangled states. In terms of the Hadamard basis, the Bell vectors are expressed as follows:

$$\mathbf{b}_{00} = \frac{1}{\sqrt{2}} (\mathbf{h}_0 \otimes \mathbf{h}_0 + \mathbf{h}_1 \otimes \mathbf{h}_1)$$
$$\mathbf{b}_{01} = \frac{1}{\sqrt{2}} (\mathbf{h}_1 \otimes \mathbf{h}_0 + \mathbf{h}_0 \otimes \mathbf{h}_1)$$
$$\mathbf{b}_{10} = \frac{1}{\sqrt{2}} (\mathbf{h}_0 \otimes \mathbf{h}_0 - \mathbf{h}_1 \otimes \mathbf{h}_1)$$
$$\mathbf{b}_{11} = \frac{1}{\sqrt{2}} (\mathbf{h}_1 \otimes \mathbf{h}_0 - \mathbf{h}_0 \otimes \mathbf{h}_1)$$

Any sequence $C = (\mathbf{c}_k)_{k \ge 0}$ whose terms are elements of B determines two sequences of qubits $C_0 = (\mathbf{c}_{k0})_{k>0}$ and $C_1 = (\mathbf{c}_{k1})_{k>0}$.

Through the radix expression of an index in base 2, we may number the Bell basis as $B = (\mathbf{b}_k)_{k \in [0,2^2-1]}$. The tensor products $\sigma_{ij} = \sigma_i \otimes \sigma_j$ determine bijections $\alpha_{ij} : B \to B$, such that

$$\forall (i,j) \in \llbracket 0,3 \rrbracket^2 \; \forall k \in \llbracket 0,2^2-1 \rrbracket : \quad \sigma_{ij}(\mathbf{b}_k) \in \mathcal{L}(\mathbf{b}_{\alpha_{ij}(k)}). \tag{2}$$

Let $A_2 : \sigma_{ij} \mapsto \alpha_{ij}$ be the map that associates to each tensor product σ_{ij} the corresponding permutation that it defines at the Bell basis. The image of A_2 consists of just $4 = 2^2$ permutations $(\beta_\ell)_{\ell \in [0, 2^3 - 1]}$, and each permutation is defined by 4 tensor products σ_{ij} as summarized at the table 2: the first column displays the index ℓ , the second column the permutation β_ℓ and the third column the list of tensor product maps σ_{ij} producing β_ℓ under the map A_2 .

The table 2 can in turn be summarized as

$$\forall i \in [\![0,3]\!]: \quad A_2(\sigma_{i\beta_0(i)}) = \beta_0, \quad A_2(\sigma_{i\beta_3(i)}) = \beta_1, \\ A_2(\sigma_{i\beta_1(i)}) = \beta_2, \quad A_2(\sigma_{i\beta_2(i)}) = \beta_3.$$
(3)

By looking at relation (2), we see that if *i* and *k* remain fixed, then the index *j* can be encoded by the value $\alpha_{ij}(k)$. This property can be exploited for secure communication purposes.

In table 3 a *Quantum Secure Direct Communication Protocol* (Deng, Long and Liu, 2003) is sketched. The purpose of this protocol is to communicate securely a word

Alice		Bob
pads the message $[\mu_{\kappa}]_{\kappa=0}^{m-1}$ into a		
sequence $[j_{\kappa}]_{\kappa=0}^{n-1}$ by inserting the		
message into the positions at J		
codifies the message $[j_{\kappa}]_{\kappa=0}^{n-1}$ by		
calculating $D_1 = (\sigma_{j_{\kappa}}(\mathbf{c}_{\kappa 1}))_{\kappa=0}^{n-1}$		
sends D_1 through a quantum	$\xrightarrow{D_1}$	receives D_1
channel		
		calculates $D_0 = (\sigma_i(\mathbf{c}_{\kappa 0}))_{\kappa=0}^{n-1}$,
		which actually com-
		pletes the calculation of
		$D = \left((\sigma_i \otimes \sigma_{j_{\kappa}}) (\mathbf{c}_{\kappa}) \right)_{\kappa=0}^{n-1}$
		calculates E by measuring each
		term at D with respect to the Bell
		basis
		recovers the sequence
		$(\alpha_{ij\kappa}(k))_{\kappa=0}^{n-1},$ consequently
		the padded sequence $[j_{\kappa}]_{\kappa=0}^{n-1}$, and
		the original message $[\mu_{\kappa}]_{\kappa=0}^{m-1}$

 Table 3. Quantum Secure Direct Communication Protocol

in $[\![0,3]\!]^*$. Alice should communicate a message $[\mu_{\kappa}]_{\kappa=0}^{m-1} \in [\![0,3]\!]^m$. Alice and Bob fix a Pauli transform σ_i , a Bell quregister $\mathbf{b}_k \in B$, an integer n > m and an index set $J \in [\![0,n-1]\!]^{(m)}$. They share initially a constant sequence $C = (\mathbf{c}_{\kappa})_{\kappa=0}^{n-1}$ whose terms coincide with $\mathbf{b}_k \in B$.

Using sequences of entangled quregisters it is also possible to build bidirectional communication protocols. In table 4 a *Quantum Bidirectional Communication Protocol* is sketched (Gao Fei, 2008). The purpose of this protocol is to communicate securely two words in $[0,3]^*$, one going from Alice to Bob and the other in the opposite direction. Alice and Bob should interchange messages in $[0,1]^{2n}$, and they share initially a constant sequence $C = (\mathbf{c}_{\kappa})_{\kappa=0}^{n-1}$.

3. Entanglement swapping

Entanglement swapping is a phenomenon which allows to put two particles into entangled states although these particles have not been close at any time. Departing from two pairs of entangled particles, a particle is chosen from each pair, then the joint pair of selected particles is measured with respect to the Bell basis, resulting in an entangled state. As a consequence, the pair consisting of the two partner particles is also entangled. This last pair is the result of the entanglement swapping beginning from the original two pairs.

In two 2-quregisters there are involved 4 qubits, let us identify them with the four

Alice		Bob
by taking pairs of contiguous bits,		by taking pairs of contiguous bits,
she writes her message as a word		he writes his message as a word
$(i_{\kappa})_{\kappa=0}^{n-1} \in [\![0,3]\!]^n$		$(j_{\kappa})_{\kappa=0}^{n-1} \in [\![0,3]\!]^n$
codifies her message by calculat-		codifies his message by calculat-
$\inf D_0 = (\sigma_{i_{\kappa}}(\mathbf{c}_{\kappa 0}))_{\kappa=0}^{n-1}$		$\inf D_1 = (\sigma_{j_{\kappa}}(\mathbf{c}_{\kappa 1}))_{\kappa=0}^{n-1}$
sends D_0 through a quantum	$\xrightarrow{D_0}$	receives D_0
channel		
receives D_1	$\overleftarrow{D_1}$	sends D_1 through a quantum
		channel
for each $\kappa \in [\![0,n-1]\!]$ she mea-		for each $\kappa \in [\![0,n{-}1]\!]$ he measures
sures the entangled quregister \mathbf{d}_{κ}		the entangled quregister \mathbf{d}_{κ} with
with respect to the Bell basis		respect to the Bell basis
since she knows i_{κ} , using (2), she		since he knows j_{κ} , using (2), he
recovers j_{κ}		recovers i_{κ}

 Table 4. Quantum Bidirectional Communication Protocol

indexes in the integer interval [0,3]. Let us write $|\varepsilon\rangle_{\mu}$, for $\varepsilon \in \{0,1\}$, $\mu \in [0,3]$, to denote the state of the μ -th qubit. For any two different indexes $\mu, \nu \in [0,3]$, let the respective Bell basis of the Hilbert space \mathbb{H}_2 be

$$\left(\mathbf{b}_{ij}^{(\mu\nu)} = \frac{1}{\sqrt{2}} \left(|0i\rangle_{\mu\nu} + (-1)^j \left| 1\overline{i} \right\rangle_{\mu\nu} \right) \right)_{i,j \in [\![0,1]\!]}$$

Let us assume that the 2-quregister consisting of the qubits 0 and 1 is entagled as well as the pair of qubits 2 and 3. Then a basis of the space \mathbb{H}_4 is

$$B_{(01)(23)} = \left(\mathbf{z}_{i_0 j_0 i_1 j_1} = \mathbf{b}_{i_0 j_0}^{(01)} \otimes \mathbf{b}_{i_1 j_1}^{(23)}\right)_{i_0, j_0, i_1, j_1 \in \llbracket 0, 1 \rrbracket},\tag{4}$$

•

where $\forall i_0, j_0, i_1, j_1 \in [[0, 1]]$:

$$\mathbf{z}_{i_0 j_0 i_1 j_1} = \frac{1}{2} \left(\begin{array}{c} |0i_0 0i_1\rangle_{0123} + (-1)^{j_1} |0i_0 1\overline{i_1}\rangle_{0123} + \\ (-1)^{j_0} |1\overline{i_0} 0i_1\rangle_{0123} + (-1)^{j_0+j_1} |1\overline{i_0} 1\overline{i_1}\rangle_{0123} \right).$$
(5)

By rearranging the pairs and considering the pairs (0,2) and (1,3), we have that a second basis of \mathbb{H}_4 is

$$B_{(02)(13)} = \left(\mathbf{b}_{i_0 j_0}^{(02)} \otimes \mathbf{b}_{i_1 j_1}^{(13)}\right)_{i_0, j_0, i_1, j_1 \in [\![0,1]\!]},\tag{6}$$

where $\forall i_0, j_0, i_1, j_1 \in [[0, 1]]$:

$$\mathbf{b}_{i_{0}j_{0}}^{(02)} \otimes \mathbf{b}_{i_{1}j_{1}}^{(13)} = \frac{1}{2} \left(\begin{array}{c} |0i_{0}0i_{1}\rangle_{0213} + (-1)^{j_{1}} |0i_{0}1\overline{i_{1}}\rangle_{0213} + \\ (-1)^{j_{0}} |1\overline{i_{0}}0i_{1}\rangle_{0213} + (-1)^{j_{0}+j_{1}} |1\overline{i_{0}}1\overline{i_{1}}\rangle_{0213} \right).$$

By swapping the middle qubits, the following 4-quregisters result: $\forall i_0, j_0, i_1, j_1 \in [0, 1],$

$$\mathbf{y}_{i_{0}j_{0}i_{1}j_{1}} = \frac{1}{2} \left(\begin{array}{c} |00i_{0}i_{1}\rangle_{0123} + (-1)^{j_{1}} |01i_{0}\overline{i_{1}}\rangle_{0123} + \\ (-1)^{j_{0}} |10\overline{i_{0}}i_{1}\rangle_{0123} + (-1)^{j_{0}+j_{1}} |11\overline{i_{0}}i_{1}\rangle_{0123} \right).$$

$$(7)$$

Each 2-quregister $\mathbf{z}_{i_0j_0i_1j_1}$ given by relation (5) can be expressed in terms of the 2quregisters $\mathbf{y}_{i_0j_0i_1j_1}$ given by relation (7), namely:

$$\mathbf{z}_{i_0 j_0 i_1 j_1} = \frac{1}{2} \left(\mathbf{y}_{i_0 j_0 i_1 j_1} + (-1)^{j_1} \mathbf{y}_{i_0 \overline{j_0} i_1 \overline{j_1}} + (-1)^{j_0} \mathbf{y}_{\overline{i_0 j_0 \overline{i_1} j_1}} + (-1)^{j_0 + j_1} \mathbf{y}_{\overline{i_0 j_0 \overline{i_1} j_1}} \right),$$
(8)

and this relation is symmetric:

$$\mathbf{y}_{i_0 j_0 i_1 j_1} = \frac{1}{2} \left(\mathbf{z}_{i_0 j_0 i_1 j_1} + (-1)^{j_1} \mathbf{z}_{i_0 \overline{j_0} i_1 \overline{j_1}} + (-1)^{j_0} \mathbf{z}_{\overline{i_0 j_0} \overline{i_1 j_1}} + (-1)^{j_0 + j_1} \mathbf{z}_{\overline{i_0 j_0 i_1 j_1}} \right),$$
(9)

In this way, the entanglement of the 4-registers \mathbf{z} is reflected by the entanglement of the 4-registers \mathbf{y} , in other words, the entanglement of the pairs (0, 1) and (2, 3) is swapped into the entanglement of the pairs (0, 2) and (1, 3), and conversely.

4. Three-entanglement

Let us consider multi-party bidirectional protocols. In particular, we will illustrate these procedures with three communicating parties. A proper protocol considers maximally entangled 3-quregisters, members of $\mathbb{H}_3 = \mathbb{H}_1 \otimes \mathbb{H}_2$. Any 3-quregister **x** has three components \mathbf{x}_0 , \mathbf{x}_1 and \mathbf{x}_2 , each at the factor space \mathbb{H}_1 , they are qubits. For $\varepsilon_1, \varepsilon_2, \varepsilon_3 \in [0, 1]$ let

$$\mathbf{b}_{\varepsilon_1\varepsilon_2\varepsilon_3} = \frac{1}{\sqrt{2}} \left(|0\varepsilon_1\varepsilon_2\rangle + (-1)^{\varepsilon_3} |1\overline{\varepsilon_1\varepsilon_2}\rangle \right).$$

These vectors form a basis, B_3 , analogous to the Bell basis in \mathbb{H}_3 , but they are called *Greensberger-Horne-Zeilinger* (GHZ) *states*. In terms of the Hadamard vectors, the GHZ states are expressed as shown at the table 5.

Through the radix expression of an index in base 2, we may number the Bell basis as $B_3 = (\mathbf{b}_k)_{k \in [0,2^3-1]}$. The tensor products $\sigma_{ijk} = \sigma_i \otimes \sigma_j \otimes \sigma_k$ determine bijections $\alpha_{ijk} : B_3 \to B_3$ in an analogous way as in (2):

$$\forall (i,j,k) \in \llbracket 0,3 \rrbracket^3 \ \forall \ell \in \llbracket 0,2^3-1 \rrbracket : \ \sigma_{ijk}(\mathbf{b}_\ell) \in \mathcal{L}(\mathbf{b}_{\alpha_{ijk}(\ell)}).$$
(10)

Let $A_3 : \sigma_{ijk} \mapsto \alpha_{ijk}$ be the map that associates to each tensor product σ_{ijk} the corresponding permutation at the Bell basis. The image of A_3 consists of just $8 = 2^3$ permutations $(\beta_{\mu})_{\mu \in [0,2^3-1]}$, and each permutation is defined by 8 tensor products σ_{ijk} as summarized in table 6. As seen at the beginning of section 2, the operator σ_2 switches the canonical and the Hadamard basis. Let us consider just operators of the form σ_{ijk} where $i \in [0,3], j, k \in \{0,2\}$. Then, the restriction of table 6 to operators at the set $S = \{\sigma_{ijk} | i \in [0,3], j, k \in \{0,2\}\}$ is shown at table 7.

damard basis of qubits.		
$-\mathbf{h}_1\otimes (\mathbf{h}_0\otimes \mathbf{h}_1+\mathbf{h}_1\otimes \mathbf{h}_0))$		
$+ \mathbf{h}_0 \otimes (\mathbf{h}_0 \otimes \mathbf{h}_1 + \mathbf{h}_1 \otimes \mathbf{h}_0))$		

Table 5. The GHZ states in terms of the Ha

$\mathbf{b}_{000} = rac{1}{2} \left(\mathbf{h}_0 \otimes \left(\mathbf{h}_0 \otimes \mathbf{h}_0 + \mathbf{h}_1 \otimes \mathbf{h}_1 ight) + \mathbf{h}_1 \otimes \left(\mathbf{h}_0 \otimes \mathbf{h}_1 + \mathbf{h}_1 \otimes \mathbf{h}_0 ight) ight)$
$\mathbf{b}_{001} = \frac{1}{2} \left(\mathbf{h}_1 \otimes \left(\mathbf{h}_0 \otimes \mathbf{h}_0 + \mathbf{h}_1 \otimes \mathbf{h}_1 \right) + \mathbf{h}_0 \otimes \left(\mathbf{h}_0 \otimes \mathbf{h}_1 + \mathbf{h}_1 \otimes \mathbf{h}_0 \right) \right)$
$\mathbf{b}_{010} = \frac{1}{2} \left(\mathbf{h}_0 \otimes \left(\mathbf{h}_0 \otimes \mathbf{h}_0 - \mathbf{h}_1 \otimes \mathbf{h}_1 \right) + \mathbf{h}_1 \otimes \left(-\mathbf{h}_0 \otimes \mathbf{h}_1 + \mathbf{h}_1 \otimes \mathbf{h}_0 \right) \right)$
$\mathbf{b}_{011} = \frac{1}{2} \left(\mathbf{h}_1 \otimes \left(\mathbf{h}_0 \otimes \mathbf{h}_0 - \mathbf{h}_1 \otimes \mathbf{h}_1 \right) + \mathbf{h}_0 \otimes \left(-\mathbf{h}_0 \otimes \mathbf{h}_1 + \mathbf{h}_1 \otimes \mathbf{h}_0 \right) \right)$
$\mathbf{b}_{100} = rac{1}{2} \left(\mathbf{h}_0 \otimes \left(\mathbf{h}_0 \otimes \mathbf{h}_0 - \mathbf{h}_1 \otimes \mathbf{h}_1 ight) + \mathbf{h}_1 \otimes \left(\mathbf{h}_0 \otimes \mathbf{h}_1 - \mathbf{h}_1 \otimes \mathbf{h}_0 ight) ight)$
$\mathbf{b}_{101} = rac{1}{2} \left(\mathbf{h}_1 \otimes \left(\mathbf{h}_0 \otimes \mathbf{h}_0 - \mathbf{h}_1 \otimes \mathbf{h}_1 ight) + \mathbf{h}_0 \otimes \left(\mathbf{h}_0 \otimes \mathbf{h}_1 - \mathbf{h}_1 \otimes \mathbf{h}_0 ight) ight)$
$\mathbf{b}_{110} = \frac{1}{2} \left(\mathbf{h}_0 \otimes (\mathbf{h}_0 \otimes \mathbf{h}_0 + \mathbf{h}_1 \otimes \mathbf{h}_1) + \mathbf{h}_1 \otimes (-\mathbf{h}_0 \otimes \mathbf{h}_1 - \mathbf{h}_1 \otimes \mathbf{h}_0) \right)$
$\mathbf{b}_{111} = rac{ar{1}}{2} \left(\mathbf{h}_1 \otimes (\mathbf{h}_0 \otimes \mathbf{h}_0 + \mathbf{h}_1 \otimes \mathbf{h}_1) + \mathbf{h}_0 \otimes (-\mathbf{h}_0 \otimes \mathbf{h}_1 - \mathbf{h}_1 \otimes \mathbf{h}_0) ight)$

Table 6. Correspondence on permutations of the Bell basis and tensor products of Pauli operators

μ	$eta_{m \mu}$	$A_3^{-1}(eta_\mu)$
0	$\begin{bmatrix} 0 & 1 & 2 & 3 & 4 & 5 & 6 & 7 \end{bmatrix}$	$\{\sigma_{000}, \sigma_{033}, \sigma_{111}, \sigma_{122}, \sigma_{212}, \sigma_{221}, \sigma_{303}, \sigma_{330}\}$
1	$[2 \ 3 \ 0 \ 1 \ 6 \ 7 \ 4 \ 5]$	$\{\sigma_{003}, \sigma_{030}, \sigma_{112}, \sigma_{121}, \sigma_{211}, \sigma_{222}, \sigma_{300}, \sigma_{333}\}$
2	$\begin{bmatrix} 3 & 2 & 1 & 0 & 7 & 6 & 5 & 4 \end{bmatrix}$	$\{\sigma_{001}, \sigma_{032}, \sigma_{110}, \sigma_{123}, \sigma_{213}, \sigma_{220}, \sigma_{302}, \sigma_{331}\}$
3	$\begin{bmatrix} 1 & 0 & 3 & 2 & 5 & 4 & 7 & 6 \end{bmatrix}$	$\{\sigma_{002}, \sigma_{031}, \sigma_{113}, \sigma_{120}, \sigma_{210}, \sigma_{223}, \sigma_{301}, \sigma_{332}\}$
4	[4 5 6 7 0 1 2 3]	$\{\sigma_{010}, \sigma_{023}, \sigma_{101}, \sigma_{132}, \sigma_{202}, \sigma_{231}, \sigma_{313}, \sigma_{320}\}$
5	$\begin{bmatrix} 6 & 7 & 4 & 5 & 2 & 3 & 0 & 1 \end{bmatrix}$	$\{\sigma_{013}, \sigma_{020}, \sigma_{102}, \sigma_{131}, \sigma_{201}, \sigma_{232}, \sigma_{310}, \sigma_{323}\}$
6	$[7 \ 6 \ 5 \ 4 \ 3 \ 2 \ 1 \ 0]$	$\{\sigma_{011}, \sigma_{022}, \sigma_{100}, \sigma_{133}, \sigma_{203}, \sigma_{230}, \sigma_{312}, \sigma_{321}\}$
7	$\begin{bmatrix} 5 \ 4 \ 7 \ 6 \ 1 \ 0 \ 3 \ 2 \end{bmatrix}$	$\{\sigma_{012}, \sigma_{021}, \sigma_{103}, \sigma_{130}, \sigma_{200}, \sigma_{233}, \sigma_{311}, \sigma_{322}\}$

In table 8 a Quantum Multidirectional Communication Protocol is sketched (Gao Fei, 2008; Chong and Hwang, 2011). The purpose of this protocol is to communicate securely four classical bits, two emitted by Alice, one by Bob and another by Claire. By repeating the protocol the parties may exchange longer bit-strings. Alice, Bob and Claire should interchange four classical bits, two emitted by Alice, one by Bob and another by Claire. The parties share two GHZ states, $\mathbf{c}_0 = \mathbf{c}_1 = \mathbf{b}_\ell \in \mathbb{H}_3$ with respective components $\mathbf{c}_{00}, \mathbf{c}_{10}, \mathbf{c}_{20}$ and $\mathbf{c}_{01}, \mathbf{c}_{11}, \mathbf{c}_{21}$. The components $\mathbf{c}_{0k}, \mathbf{c}_{1k}, \mathbf{c}_{2k}$ are in possession of Alice, Bob and Claire respectively, $k \in [0, 1]$. The quregister \mathbf{c}_0 is a record of the initial state \mathbf{b}_{ℓ} , while the quregister \mathbf{c}_1 is to be transformed during the protocol.

Another bidirectional protocol (Zhong-Xiao and Yun-Jie, 2006) consists of three participants: Alice and Bob are the correspondents and Claire is the controller. The

Table 7. Correspondence on permutations of the Bell basis and tensor products of Pauli operators at the set S, in alphabetical order according to the first element at $S \cap A_3^{-1}(\beta_{\mu})$. Observe that if one index i, j, k is known, the other two can be deduced form this index and the 3-quregister $\sigma_{ijk}(\mathbf{b}_{\ell})$.

μ	$S \cap A_3^{-1}(\beta_\mu)$
0	$\{\sigma_{000}, \sigma_{122}\}$
3	$\{\sigma_{002}, \sigma_{120}\}$
5	$\{\sigma_{020}, \sigma_{102}\}$
6	$\{\sigma_{022}, \sigma_{100}\}$
7	$\{\sigma_{200}, \sigma_{322}\}$
4	$\{\sigma_{202}, \sigma_{320}\}$
2	$\{\sigma_{220}, \sigma_{302}\}$
1	$\{\sigma_{222}, \sigma_{300}\}$

 Table 8. Quantum Multidirectional Communication Protocol

- (i) The two bits of Alice determine an index $i_A \in [0,3]$. She applies σ_{i_A} to her qubit \mathbf{c}_{01} .
- (ii) Bob applies either σ_0 or σ_2 to his qubit \mathbf{c}_{11} according to the value of his bit.
- (iii) Claire applies either σ_0 or σ_2 to her qubit \mathbf{c}_{21} according to the value of her bit.
- (iv) They take a measure of the transformed quregister with respect to the Bell basis.
- (v) Using table 7, since each participant knows his/her own message, they recover the transmitted bits.

correspondents are able to communicate only after the authorization of the controller, but their correspondence should be kept in secret against the controller. The protocol is sketched at table 9. Alice and Bob should interchange messages at $[0,3]^m$ after the authorization granted by Claire. The parties share a constant sequence $(\mathbf{c}_{\nu})_{\nu=0}^{n-1}$ whose entries coincide with a GHZ initial state \mathbf{b}_{ℓ} . The component sequence $(\mathbf{c}_{0\nu})_{\nu=0}^{n-1}$, let us say for ease of explanation, is owned by Claire, the component sequence $(\mathbf{c}_{1\nu})_{\nu=0}^{n-1}$ by Alice and the component sequence $(\mathbf{c}_{2\nu})_{\nu=0}^{n-1}$ by Bob.

A Key Agreement Protocol Using Entanglement Swapping is obtained (Gao, Guo, Wen and Zhu, 2010) as follows. Let $B_2^{(\mu\nu)}$ be the Bell basis considering two qubits $\mu, \nu \in [\![0,3]\!], \mu \neq \nu$.

Let $\mathbf{c}^{(01)}, \mathbf{c}^{(23)}$ be two Bell 2-quregisters with respective components $\mathbf{c}^{(0)}, \mathbf{c}^{(1)}$ and $\mathbf{c}^{(2)}, \mathbf{c}^{(3)}$.

Alice may act on the pair $(\mathbf{c}^{(01)}, \mathbf{c}^{(23)}) = [\mathbf{c}^{(0)}, \mathbf{c}^{(1)}, \mathbf{c}^{(2)}, \mathbf{c}^{(3)}]$ either by $(A_0:)$ doing nothing or by $(A_1:)$ swapping the middle qubits, obtaining thus $[\mathbf{c}^{(0)}, \mathbf{c}^{(2)}, \mathbf{c}^{(1)}, \mathbf{c}^{(3)}]$.

Bob may act on the pair $(\mathbf{c}^{(01)}, \mathbf{c}^{(23)}) = [\mathbf{c}^{(0)}, \mathbf{c}^{(1)}, \mathbf{c}^{(2)}, \mathbf{c}^{(3)}]$ either by $(B_0:)$ measuring

- (i) Alice and Bob agree a set $J \subset [\![0, n-1]\!]$ of m positions among the index set $[\![0, m-1]\!]$.
- (ii) Alice codifies her message $(a_{\mu})_{\mu=0}^{m-1} \in [0,3]^{m-1}$ by applying $\sigma_{a_{\mu}}$ to her correspondent qubit $\mathbf{c}_{1\nu_{\mu}}$, with $\nu_{\mu} \in J$, and she applies arbitrary Pauli operators at her qubits with indexes not in J. Alice sends her codified sequence to Claire.
- (iii) Bob codifies his message $(b_{\mu})_{\mu=0}^{m-1} \in [0,3]^{m-1}$ by applying $\sigma_{b_{\mu}}$ to his correspondent qubit $\mathbf{c}_{2\nu_{\mu}}$, with $\nu_{\mu} \in J$, and he applies arbitrary Pauli operators at his qubits with indexes not in J. Bob sends his codified sequence to Claire.
- (iv) Claire receives the component sequences $(\mathbf{c}_{1\nu\mu})_{\nu=0}^{n-1}$ and $(\mathbf{c}_{2\nu\mu})_{\nu=0}^{n-1}$, and she measures the whole sequence $(\mathbf{c}_{\nu\mu})_{\nu=0}^{n-1}$ with respect to the basis B_3 . She sends her results to Alice and Bob as an authorization to proceed the transaction.
- (v) Using the table 6, her knowledge of her own message and the index set J, Alice recovers Bob's message $(b_{\mu})_{\mu=0}^{m-1} \in [0,3]^{m-1}$.
- (vi) Using the table 6, his knowledge of his own message and the index set J, Bob recovers Alice's message $(a_{\mu})_{\mu=0}^{m-1} \in [\![0,3]\!]^{m-1}$.

 $[\mathbf{c}^{(0)}, \mathbf{c}^{(1)}]$ with respect to the Bell basis $B_2^{(01)}$ and measuring $[\mathbf{c}^{(1)}, \mathbf{c}^{(2)}]$ with respect to the Bell basis $B_2^{(23)}$ or $(B_1$:) by measuring $[\mathbf{c}^{(0)}, \mathbf{c}^{(2)}]$ with respect to the Bell basis $B_2^{(02)}$ and measuring $[\mathbf{c}^{(1)}, \mathbf{c}^{(3)}]$ with respect to the Bell basis $B_2^{(13)}$.

If the chosen actions are (A_0, B_0) or (A_1, B_1) , the actions are said to be *correlated*, otherwise, they are *anticorrelated*.

In the protocol, the agreed common key is the juxtaposition of the measures obtained at the positions in which correlated operators do occur. When looking for a greater efficiency it is possible to recover also not 4, for 2 bits at any block corresponding to an anti correlated operator.

References

- Chong, S.-K. and Hwang, T. (2011). The enhancement of three-party simultaneous quantum secure direct communication scheme with EPR pairs, Optics Communications 284(1): 515 – 518. URL: http://www.sciencedirect.com/science/article/pii/S0030401810008928
- Deng, F.-G., Long, G. L. and Liu, X.-S. (2003). Two-step quantum direct communication protocol using the Einstein-Podolsky-Rosen pair block, *Phys. Rev. A* 68: 042317. URL: http://link.aps.org/doi/10.1103/PhysRevA.68.042317
- Gao, F., Guo, F.-Z., Wen, Q.-Y. and Zhu, F.-C. (2010). Quantum key distribution by constructing nonorthogonal states with Bell states, *International Journal of Modern Physics B* 24(23): 4611– 4618.

URL: http://www.worldscientific.com/doi/abs/10.1142/S021797921005661X

Gao Fei, Guo FenZhuo, W. Q. Z. F. (2008). Revisiting the security of quantum dialogue and bidirectional quantum secure direct communication, *Science China Physics, Mechanics &*

Table 10. Key Agreement Protocol Using Entanglement Swapping

- (i) Alice selects a sequence $\mathbf{B} = (\mathbf{b}_{\alpha(k)})_{k=0}^{2m-1}$ of entangled states at the Bell basis. Each pair of two such states $(\mathbf{b}_{\alpha(2k)}, \mathbf{b}_{\alpha(2k+1)}), k \in [0, m-1]$, involves 4 qubits, say $[\mathbf{c}^{(0k)}, \mathbf{c}^{(1k)}, \mathbf{c}^{(2k)}, \mathbf{c}^{(3k)}]$
- (ii) For each $k \in [0, m-1]$, Alice applies an operation A_0 or A_1 to the current pair $(\mathbf{b}_{\alpha(2k)}, \mathbf{b}_{\alpha(2k+1)})$. She obtains the sequence **C** and she sends this sequence to Bob through a public quantum channel.
- (iii) Bob receives the sequence **C** and for any block of 4 consecutive qubits, say $[\mathbf{d}^{(0k)}, \mathbf{d}^{(1k)}, \mathbf{d}^{(2k)}, \mathbf{d}^{(3k)}]$, he selects randomly an operation B_0 or B_1 and he applies it to $[\mathbf{d}^{(0k)}, \mathbf{d}^{(1k)}, \mathbf{d}^{(2k)}, \mathbf{d}^{(3k)}]$.
- (iv) Alice and Bob exchange through a classic channel the lists of their corresponding selected operations.
- (v) The common key is established by selecting the 4 blocks measurements corresponding to the correlated pairs of operations.
- (vi) It is worth to remark that at the anticorrelated positions, both Alice and Bob may recover two common bits, corresponding to the initial state of Alice for the current 4-block.

Gisin, N., Ribordy, G., Tittel, W. and Zbinden, H. (2002). Quantum cryptography, Rev. Mod. Phys. 74: 145–195.

URL: http://link.aps.org/doi/10.1103/RevModPhys.74.145

Lanyon, B. P., Weinhold, T. J., Langford, N. K., Barbieri, M., James, D. F. V., Gilchrist, A. and White, A. G. (2007). Experimental demonstration of a compiled version of Shor's algorithm with quantum entanglement, *Phys. Rev. Lett.* **99**: 250505.

URL: http://link.aps.org/doi/10.1103/PhysRevLett.99.250505

Zhong-Xiao, M. and Yun-Jie, X. (2006). Controlled bidirectional quantum direct communication by using a GHZ state, *Chinese Physics Letters* 23(7): 1680. URL: http://stacks.iop.org/0256-307X/23/i=7/a=007

10

Astronomy 51(5): 559.

URL: http://phys.scichina.com:8083/sciGe/EN/abstract/article_408422.shtml