Strong negative nonlinear friction from induced two-phonon processes in vibrational systems

X. Dong^{1,2}, M. I. Dykman^{3**} and H. B. Chan^{1,2*}

¹ Department of Physics, the Hong Kong University of Science and Technology, Clear Water Bay, Kowloon, Hong Kong, China.

² William Mong Institute of Nano Science and Technology, the Hong Kong University of Science and Technology, Clear Water Bay, Kowloon, Hong Kong, China.

³ Department of Physics and Astronomy, Michigan State University, East Lansing, Michigan 48824, USA.

*email: <u>hochan@ust.hk</u>

**email: dykman@pa.msu.edu

Self-sustained vibrations in systems ranging from lasers to clocks to biological systems are often associated with the coefficient of linear friction, which relates the friction force to the velocity, becoming negative [1,2]. The runaway of the vibration amplitude is prevented by positive nonlinear friction that increases rapidly with the amplitude. Here we use a modulated electromechanical resonator to show that nonlinear friction can be made negative and sufficiently strong to overcome positive linear friction at large vibration amplitudes. The experiment involves applying a drive that simultaneously excites two phonons of the studied mode and a phonon of a faster decaying high-frequency mode. We study generic features of the oscillator dynamics with negative nonlinear friction. Remarkably, self-sustained vibrations of the oscillator need to be activated in this case. When, in addition, a resonant force is applied, a branch of large-amplitude forced vibrations can emerge, isolated from the branch of the ordinary small-amplitude response. Isolated branches of self-sustained and forced vibrations are advantageous for applications in sensing and control.

1

Nonlinear friction was first used by van der Pol to describe, phenomenologically, the operation of radio frequency generators [3]. In the van der Pol model, the energy gain is described by negative linear friction. The nonlinear friction is positive, corresponding to the rate of energy loss that increases superlinearly with the energy of the vibrations. This model has been broadly used in science and engineering. Recently, there has been renewed interest in positive nonlinear friction following its observations in various passive (rather than self-oscillating) nanomicro- and optomechanical systems [4-10]. Furthermore, such friction has also been engineered in microwave cavities in order to create long-lived coherent quantum states [11,12].

A simple microscopic mechanism of linear friction is a decay process where a single energy quantum (a phonon) of the vibrational mode goes into excitations of a thermal reservoir [13]. In contrast, positive nonlinear friction originates from the decay that involves two vibrational quanta of the mode [14]. For nonlinear friction of nanomechanical modes and cavity modes, the excitations of the reservoir can be, respectively, phonons [15,16] or propagating photons [11], see Fig. 1a. For the cavity mode studied by Leghtas et al. [11], the two-photon decay was stimulated by a pump. This process resembles the stimulated decay in optomechanics [17] where an input photon leads to the removal or addition of only one quantum of the mechanical mode. Provided that the cavity mode decays much faster than the mechanical mode, such process is induced by pumping at a sideband of the cavity eigenmode [18-20]. If the pump frequency is red-detuned by the frequency of the mechanical mode, the linear friction coefficient of the mechanical mode increases and the mode temperature decreases. This backaction mechanism enables observation of interesting quantum effects with nanomechanical systems [17,21,22]. On the other hand, blue-detuned pumping, if sufficiently strong, makes the linear friction coefficient negative, exciting self-sustained oscillations [23-30]. However, to our knowledge, friction that becomes negative only for sufficiently large vibration amplitudes, i.e., absolute negative nonlinear friction, has not been obtained in optomechanics.

We note that the decrease of losses with increasing vibration energy was reported for both microwave cavities [31,32] and nanomechanical systems [33]. It was attributed to absorption saturation in two-level systems that absorb the energy from the vibrations. By its nature, such nonlinear friction cannot make the overall energy loss negative. However, it plays an important role in providing a means to increase the quality factor of superconducting microwave cavities used in optomechanics [34,35].

In this work we show that a properly designed pumping generates strong negative nonlinear friction, and we study the qualitatively new features of vibrational dynamics that come with such friction. The experiment is done on a micromechanical resonator with two nonlinearly coupled vibrational modes of strongly differing frequencies $\omega_{1,2}$ and linear decay rates $\Gamma_{1,2}$, with $\omega_2 \gg \omega_1$ and $\Gamma_2 \gg \Gamma_1$. Pumping at the blue-detuned secondary sideband of the higher-frequency mode $\omega_2 + 2\omega_1$ opens a relaxation channel where two quanta of mode 1 and one quantum of mode 2 are simultaneously excited, see. Fig. 1b. The resulting negative nonlinear friction of mode 1 can be controlled and made strong enough to overcome the intrinsic positive linear friction. We find that the modes can then settle into a state of stable self-sustained vibrations. However, these vibrations have to be activated, i.e., require a sufficiently strong initial excitation. In contrast to self-sustained vibrations associated with negative linear friction [23-30], here the zero-amplitude state remains stable.

At weaker pump power where the negative nonlinear friction is not strong enough to make the full friction force negative even for larger amplitudes, it still significantly modifies the oscillator dynamics in the presence of resonant drive. On top of the ordinary Lorentzian-type dependence of the amplitude of forced vibrations on the drive frequency, there emerges an additional branch of large-amplitude vibrations. Unlike the familiar nonlinear response of vibrations with conservative nonlinearity, this branch is disconnected from the small-amplitude branch. It emerges already for a comparatively weak drive. When the frequency of the drive or the mode varies, there occur jumps to the small-amplitude branch at both ends of the high-amplitude branch, opening opportunities in detecting perturbations to the system of both polarity, in contrast to bifurcation amplifiers based on the conservative nonlinearity [36-38].

Results

The electromechanical resonator. Our resonator consists of three parts (Fig. 1c). The first is a polycrystalline silicon plate with dimension $100 \times 100 \times 3.5 \ \mu\text{m}$. It is supported on its opposite sides by two silicon beams (1.3 µm wide and 2 µm thick). The two beams have different lengths of 80 µm and 75 µm. Both of them are coated with 30 nm of gold. The plate performs vibrations normal to the substrate at eigenfrequency $\omega_1 = 272599.72 \text{ rad s}^{-1}$. As seen from Fig. 1d, the damping constant of this vibrational mode, which we call mode 1, is $\Gamma_1 = 3.26 \text{ rad s}^{-1}$. The system also has a mode in which the longer beam vibrates parallel to the substrate (Fig. 1e). We call it mode 2. It has a much higher frequency $\omega_2 = 9942136.19 \text{ rad s}^{-1}$ and a higher damping constant $\Gamma_2 = 187.57 \text{ rad s}^{-1}$.

Modes 1 and 2 are parametrically coupled. This coupling originates from the tension generated in the beam as the plate moves normal to the substrate, which in turn modifies the spring constant for the motion of the beam parallel to the substrate, and vice versa. As the plate vibrates, sidebands at frequencies $\omega_2 \pm n\omega_1$ with n = 1, 2, ... are created in the spectrum of the response of mode 2 (the beam mode) around its frequency ω_2 .



Figure 1| Two-phonon transfer between the plate and beam modes of the electromechanical resonator. (a) Ordinary positive nonlinear friction involves transferring two phonons of the vibrational mode 1 (shown by the wavy lines) to excitations of the reservoir (the dashed line). (b) External pump at frequency ω_F can create one phonon in fast decaying mode 2 and two phonons in mode 1, inducing negative nonlinear friction in mode 1. (c) Colorized scanning electron micrograph of the electromechanical resonator with a schematic of the measurement circuitry. The black scale bar at the lower right corner measures 20 µm. (d) The amplitude a_1 of the plate mode (mode 1) vs frequency ω_{d1} of a small probe voltage (Probe1). Inset: vibration profile of the plate mode. (e) A similar plot for the beam mode (mode 2). (f) A sketch of the spectra of the plate mode and the beam mode centered at the mode frequencies ω_1 and ω_2 , respectively. Pumping at the secondary high/low-frequency sidebands (red and blue arrows) generates negative/positive nonlinear friction in the plate mode.

The model. To induce nonlinear friction, we pump the system at the secondary sidebands, i.e., the combination frequencies $\omega_2 \pm 2\omega_1$, by applying an ac current to the beam in a magnetic field. Our system is in the deep resolved-sideband limit, with $\omega_1/\Gamma_2 = 1453$. The minimalistic model that captures the resonant behavior is described by equations

$$\ddot{q}_{1} + \omega_{1}^{2}q_{1} + 2\Gamma_{1}\dot{q}_{1} + (\gamma/m_{1})q_{1}q_{2}^{2} + (\gamma_{1}/m_{1})q_{1}^{3} = (F_{p}/m_{1})2q_{1}q_{2}\cos(\omega_{F}t)$$
$$\ddot{q}_{2} + \omega_{2}^{2}q_{2} + 2\Gamma_{2}\dot{q}_{2} + (\gamma/m_{2})q_{1}^{2}q_{2} + (\gamma_{2}/m_{2})q_{2}^{3} = (F_{p}/m_{2})q_{1}^{2}\cos(\omega_{F}t)$$
(1)

where $q_{1,2}$ are, respectively, the displacement of the plate and the midpoint of the beam, $m_{1,2}$ are the effective masses of the two modes, γ denotes the dispersive coupling coefficient (the coupling energy is $\frac{1}{2}\gamma q_1^2 q_2^2$) and $\gamma_{1,2}$ are the coefficients of the Duffing nonlinearity of the two modes. Parameter F_p determines the effective amplitude of near-resonant parametric pumping at frequency ω_F close to $\omega_2 \pm 2\omega_1$. It corresponds to the term $-F_p q_1^2 q_2 \cos(\omega_F t)$ in the modes Hamiltonian. This term effectively incorporates, in a standard way, the contribution from the linear force ($\propto \cos \omega_F t$) weighted with the parameters of the nonlinear non-resonant mode coupling.

For pumping frequencies close to the upper combination frequency, $|\omega_F - 2\omega_1 - \omega_2| \ll \omega_{1,2}$, we change from $q_{1,2}(t)$, $\dot{q}_{1,2}(t)$ to dimensionless complex amplitudes $v_{1,2}(t)$ defined as $v_1(t) = (m_1/2\omega_1C_{sc})^{1/2}[\omega_1q_1(t) - i\dot{q}_1(t)]\exp(-i\omega_1t), \quad v_2(t) = (m_2/2\omega_2C_{sc})^{1/2}[(\omega_F - 2\omega_1)q_2(t) - i\dot{q}_2(t)]\exp[-i(\omega_F - 2\omega_1)t]$. The scaling constant C_{sc} has the dimension of action and can be chosen as the energy of mode 1 divided by its frequency; we set $C_{sc} = 10^{-21}$ J·s, which corresponds to a characteristic displacement ~10 nm. The vibration amplitudes $A_{1,2}$ are expressed in terms of the variables $v_{1,2}$ as $A_i = (2C_{sc}/m_i\omega_i)^{1/2}|v_i|$ with i = 1,2. In the rotating wave approximation, equations for $v_{1,2}(t)$ read

$$\dot{v}_{1} + \Gamma_{1}v_{1} = i\partial H_{RWA}/\partial v_{1}^{*}, \qquad \dot{v}_{2} + \Gamma_{2}v_{2} = i\partial H_{RWA}/\partial v_{2}^{*},$$

$$H_{RWA} = -\Delta |v_{2}|^{2} + \Lambda_{12}|v_{1}|^{2}|v_{2}|^{2} + \frac{1}{2}\sum_{i=1,2}\Lambda_{ii}|v_{i}|^{4} - f_{p}(v_{1}^{2}v_{2} + \text{c. c.})$$
(2)

Here, H_{RWA} is the Hamiltonian of the driven modes in the rotating wave approximation. Parameter $\Delta = \omega_F - 2\omega_1 - \omega_2$ is the frequency detuning from the combination resonance, $|\Delta| \ll \omega_1$. Parameters f_p (18.332 s⁻¹), Λ_{11} (2.201s⁻¹), Λ_{22} (1627.7 s⁻¹) and Λ_{12} (33.234 s⁻¹) are related to F_p , γ , γ_1 and γ_2 in Eq. (1), respectively (Supplementary Note 2). However, in general they also have contributions from the cubic nonlinearity of the resonator modes disregarded in (1). Importantly, Λ_{ij} are the parameters that can be directly measured, for example, by applying periodic drives to the modes (Supplementary Note 1), whereas f_p is externally controlled.

In the case of driving close to the lower combination frequency, $|\omega_F - \omega_2 + 2\omega_1| \ll \omega_{1,2}$, one sets $v_2(t) = (m_2/2\omega_2C_{sc})^{1/2}[(\omega_F + 2\omega_1)q_2(t) - i\dot{q}_2(t)]\exp[-i(\omega_F + 2\omega_1)t]$. Equations for $v_{1,2}$ have the same form as Eq. (2), except that the last term in H_{RWA} now reads $-f_p(v_1^2v_2^* + c.c.)$ and $\Delta = \omega_F + 2\omega_1 - \omega_2$.

Nonlinear decay of mode 1 for weak to moderate nonlinear friction. We first explore the energy dissipation for not too large amplitudes of mode 1 (the plate mode), where the nonlinear friction is moderately strong. A familiar description of nonlinear friction [4-8,31,33] is obtained for $\Gamma_2 \gg \Gamma_1$ where mode 2 serves as a thermal reservoir for mode 1. The analysis simplifies if the

dispersive mode coupling and the internal nonlinearity of the modes are small, so that the nonlinearity-induced frequency shifts are small compared to $(\Gamma_2^2 + \Delta^2)^{1/2}$. Then after a short transient we have $|\dot{v}_1/v_1|$, $|\dot{v}_2/v_2| \ll (\Gamma_2 + \Delta^2)^{1/2}$, and we can apply a simple adiabatic approximation by setting $\dot{v}_2 = 0$ in Eq. (2) (a complete analysis is given in Supplementary Note 2). In this approximation Eq. (2) yields:

$$\dot{v}_1 \approx -v_1(\Gamma_1 + \alpha |v|^2) + i\beta v_1 |v_1|^2,$$
(3)

where $\alpha = -2f_p^2\Gamma_2 / (\Gamma_2^2 + \Delta^2)$ and $\beta = \Lambda_{11} + 2f_p^2\Delta / (\Gamma_2^2 + \Delta^2)$ ($\alpha = -1.509 \text{ s}^{-1}$ and $\beta = 0.4326 \text{ s}^{-1}$ for $\Delta = -35Hz$). In this case $\Gamma_{ad} = \Gamma_1 + \alpha |v_1|^2$ represents a decay rate for mode 1. For the negative nonlinear friction considered ($\alpha < 0$), this rate is decreased from Γ_1 by a parameter quadratic in the vibration amplitude. For driving at the lower secondary sideband, the sign of α is reversed, leading to the conventional positive nonlinear friction.

To measure the decay rate, we employ the standard ringdown technique. We first drive mode 1 into a steady state of vibrations with a resonant periodic force. Then we turn off the periodic force and record the decrease in vibration amplitude $A_1 = (m_1 \omega_1/2 C_{sc})^{-1/2} |v_1|$ as a function of time, as shown in Fig. 2a. When there is no sideband pumping, A_1 decays exponentially as expected (black dots). The slope of the semi-logarithmic plot gives the "instantaneous" (on the time scale $\gg \omega_1^{-1}$) decay rate $\Gamma_{inst} = d \log A_1/dt$ that is independent of the vibration amplitude, as shown in Fig. 2b. Weak nonlinear friction is induced by turning on the sideband pumping and choosing the detuning frequency Δ to be relatively large (~ -35 Hz). As shown by the blue/red curves in Figs. 2a and 2b for pumping at the upper/lower sidebands, the decay rate decreases/increases with vibration amplitude giving negative/positive nonlinear friction. At small vibration amplitudes, measurements agree well with the dashed lines that represent Eq. (3), $\Gamma_{inst} \approx \Gamma_1 (1 + \tilde{\alpha} A_1^2)$ with $\tilde{\alpha} = \alpha m_1 \omega_1 / 2C_{sc}$. Deviations become apparent at larger amplitudes, where the conservative nonlinearity of the modes and their dispersive coupling need to be taken into account (Supplementary Note 2).



Figure 2| Positive and negative nonlinear friction on the plate mode due to two-phonon processes. (a) Ringdown of the dimensional vibration amplitude A_1 of mode 1 with no sideband pumping (black) and pumping at the red/blue-detuned secondary sideband (red/blue) that leads to positive/negative nonlinear friction; $\Delta = -35$ Hz. (b) The instantaneous decay rate as a function of the squared vibration amplitude. Dashed lines are from Eq. (3), solid lines show the extended adiabatic theory (Supplementary Note 2). (c) and (d) Similar plots as (a) and (b), for larger initial vibration amplitude.

The decay significantly changes for larger initial vibration amplitudes. Here, the dependence of the instantaneous decay rate on vibration amplitude becomes non-monotonic. Figures 2c and 2d show respectively the measured decay in time and the corresponding

instantaneous decay rate as a function of the vibration amplitude. For pumping at the blue secondary sideband, Γ_{inst} attains a minimum and then approaches the zero-amplitude value Γ_1 as the amplitude further increases. This behavior is a consequence of the conservative nonlinearities of the coupled modes disregarded in Eq. (3). At large amplitudes, the amplitude-dependent frequencies $\omega_{1,2}(|v_1|^2, |v_2|^2)$ no longer satisfy the resonant condition for nonlinear friction $\omega_F \approx \omega_2 \pm 2\omega_1$. Therefore the decay rate approaches the linear decay rate Γ_1 , as shown in Fig. 2d. Calculations are plotted as solid lines and are in good agreement with measurement (Supplementary Note 2).

Self-sustained vibrations for strong negative nonlinear friction. When the pump detuning $|\Delta|$ at the blue-detuned secondary sideband is reduced, negative nonlinear friction becomes stronger. The minimum in the instantaneous decay rate as a function of $|v_1|$ becomes deeper and eventually drops below zero in a certain range of amplitudes. This leads to a novel type of self-sustained vibrations. They are qualitatively different from the self-sustained vibrations in optoand nano-mechanics that emerge when the pumping makes the coefficient of linear friction negative [18,23-30]. A major difference is that the excitation of self-sustained vibrations by negative nonlinear friction requires activation. Nonlinear friction has no effect when the vibration amplitude is small. If the initial vibration amplitude is zero, self-sustained vibrations cannot be excited by merely sweeping the pump power or the pump frequency. This behavior is seen from the lower branch of data in Fig. 3a. If, however, the vibration amplitude is perturbed beyond certain threshold, the system can settle into a state where it performs self-sustained vibrations. Their typical spectrum is shown in the inset of Fig. 3a. A change in the pump detuning Δ leads to a change in the vibration amplitude, as shown by the upper branch of data in Fig 3a. As Δ is decreased beyond the bifurcation point $\Delta_B (\approx -24.1 \text{ Hz})$, the vibration amplitude jumps discontinuously to zero. The system cannot return to the self-sustained vibration state unless the amplitude is perturbed sufficiently strongly from zero by a source different from the pump. This type of bistability qualitatively differs from the well-known bistability of resonantly or parametrically modulated Duffing oscillators [37-39] or coupled modes pumped close to the sum frequency [22-29].



Figure 3| Self-sustained vibrations associated with strong negative nonlinear friction. (a) Amplitude of vibrations of mode 1 as a function of pump detuning Δ . The stable branches are in red; they correspond to self-sustained vibrations and a zero-amplitude state. The light red dots represent the threshold amplitude for exciting self-sustained vibrations. The error bar is smaller than the dot size. Inset: Spectrum of the self-sustained vibrations. (b) The same plot for mode 2. (c) Depending on the initial amplitude, mode 1 decays to zero (purple) or settle into self-sustained vibrations (orange and dark red). (d) The instantaneous decay rate extracted from (c). The solid lines in all panels are theoretical predictions (Supplementary Notes 2 and 3).

Figure 3b shows that self-sustained vibrations of plate mode (mode 1) are accompanied by vibrations of the beam mode (mode 2). In the presence of fluctuations, the vibrations of the both modes undergo phase-diffusion, with remarkable properties associated with the discrete time-translation symmetry imposed by the pump [30,40] that are, however, outside the scope of this paper.

Figure 3c shows how the plate mode settles into the zero-amplitude state or the selfsustained vibration state (with amplitude A_{st}) depending on the initial vibration amplitude, with Δ fixed at 0 Hz. For the initial amplitude smaller than the threshold value A_{th} (purple circles), the negative nonlinear friction is smaller than the positive linear friction. Vibrations ring down towards zero in a non-exponential manner. For the initial amplitude lying between A_{th} and A_{st} , the negative nonlinear friction overcomes the positive linear friction. By absorbing energy from the pump through two-phonon processes, the plate mode rings up in amplitude towards A_{st} . For the initial amplitude larger than A_{st} (dark red circles), the overall friction is positive. The vibration amplitude decays, but towards A_{st} instead of zero. Thus A_{th} represents the threshold amplitude for self-sustained vibrations to develop. Different pump detuning yields different values of A_{th} . The measured value of this threshold is plotted in light red in Fig. 3(a). As the pump detune frequency Δ approaches the bifurcation value Δ_B , the amplitudes A_{st} and A_{th} merge, leading to a discontinuous jump of the vibration amplitude to zero.

Near the bifurcation point, the dynamics can be mapped onto a saddle-node bifurcation of the radius of the limit cycle (Supplementary Note 3). We note that the actual separation of the regions of attraction to the coexisting states of self-sustained vibrations and the zero-amplitude state occurs on a hypersurface in the 4-dimensional space of the dynamical variables of the

modes 1 and 2. The value of A_{th} is the projection of this hypersurface on the plane of variables of mode 1. In the experiment, it is obtained by exciting mode 2 and following the dynamics of mode 1 after the excitation is turned off; A_{th} is independent of the phase of mode 1, since ω_1 is incommensurate with the pump frequency.

Figure 3d illustrates the activated nature of self-sustained vibrations in an alternative way, by plotting the instantaneous decay rate Γ_{inst} as a function of the vibration amplitude A_1 . This plot bears resemblance to the blue curve in Fig. 2d recorded at larger $|\Delta|$, except that the minimum has dropped below zero due to strong negative nonlinear friction. The instantaneous decay rate in Fig. 3d crosses zero at two vibration amplitudes A_{th} and A_{st} that represent the threshold amplitude and the amplitude for stable self-sustained vibrations respectively. The theory is in excellent agreement with the measurements.

Forced vibrations in the presence of negative nonlinear friction. An important consequence of nonlinear friction is the change of the spectral response of the mode to a resonant periodic force $F_{d1} \cos \omega_{d1} t$ with $\omega_{d1} \approx \omega_1$ [14] and of the dependence of the response on the force amplitude F_{d1} (Methods). In the linear regime, the vibration amplitude attains maximum value a_{1max} when $\omega_{d1} = \omega_1$. With no nonlinear friction the ratio $\Gamma_{peak} = F_{d1}/4m_1\omega_1a_{1max}$ is constant even in the presence of Duffing nonlinearity [41] (black line in Fig. 4b). With negative nonlinear friction, but with no self-sustained oscillations initiated, the dependence of the vibration amplitude a_1 on ω_{d1} remains Lorentzian for small F_{d1} , see light blue curve in Fig. 4a, and a_{1max} is nearly proportional to F_{d1} . However, as F_{d1} increases by a factor of 2.28, this measured dependence (dark blue circles) becomes sharper than the Lorentzian, cf. dark blue curve in Fig. 4a. The blue data in Fig. 4b shows that Γ_{peak} decreases with F_{d1} . In other experiments [4-8,31,33], a nonlinear dependence of a_{1max} on F_{d1} was interpreted as the evidence of the presence of positive [4-9] and negative [33] nonlinear friction.



Figure 4| Effect of negative nonlinear friction on the resonant response of the plate mode. (a) The amplitude of forced vibrations a_1 vs the driving force frequency ω_{d1} for $\Delta = 0$ Hz and the driving force amplitudes $F_{d1} = 0.21$ pN (blue) and $F_{d1} = 0.48$ pN (dark blue). The blue line is a fit to the linear regime. The dark blue line is obtained by multiplying the blue line by the drive amplitudes ratio 2.28. Inset: 3D plot of the measured ratio a_1/F_{d1} . (b) The characteristic width Γ_{peak} of the spectral peak vs. drive amplitude for linear friction (black, no sideband pumping), and for positive/negative nonlinear friction (red/blue, pumping at the red/blue-detuned secondary sideband with $\Delta = 0$ Hz). The solid lines are the theory (Supplementary Note 4). (c) Bistability of forced vibrations due to negative nonlinear friction, $\Delta = -35$ Hz. The driving force amplitude is 0.70 pN. At the bifurcation points ω_L and ω_H , the amplitude jumps down from the upper branch. Inset: With $\Delta = -1000$ Hz, nonlinear friction is negligible. Mode 1 displays a standard Duffing hysteresis for $F_{d1} = 3.5$ pN (black); at $F_{d1}=0.70$ pN no hysteresis occurs (grey) (d) Measured (dots) and calculated stable (solid lines) and unstable (dashed lines) vibration amplitudes for $F_{d1} = 0.595$ pN (yellow) and 0.980 pN (green). Inset: Zoom in at the isolated branch

Next we detune the pump frequency so that $\Delta < \Delta_B$ and the overall friction remains positive albeit strongly amplitude-dependent. We find that, in this regime, negative nonlinear friction leads to a qualitatively new branch of the stable states of forced vibrations at the drive frequency ω_{d1} . These states are not straightforward to detect. Figure 4c plots the vibration amplitude of the plate (mode 1) as a function of ω_{d1} at $\Delta = -35$ Hz. The bottom part of the response resembles that of a driven harmonic oscillator, well–described by the square root of a Lorentzian. Here the vibration amplitude is small so that negative nonlinear friction has negligible effect on the lineshape. Interestingly, we observe another branch, as seen at the top of Fig. 4c, where negative nonlinear friction reduces the overall damping and leads to stable oscillations at the drive frequency ω_{d1} , but with much higher amplitude. The driving amplitude for this extra branch is identical to that of the resonance peak of the lower branch. In contrast to the nonlinear response of a Duffing oscillator with linear friction [41], this branch is isolated from the resonance peak at low amplitudes. It exists in the frequency range $\omega_L \leq \omega_{d1} \leq \omega_H$. If the driving frequency is swept beyond the bifurcation values $\omega_{L,H}$, the system jumps back to the low amplitude branch.

The high amplitude branch exists because the overall damping is decreased considerably by strong negative nonlinear friction. It cannot be accessed by sweeping the driving frequency alone. A sufficiently large perturbation of the amplitude is required. We used strong driving force to excite vibrations of large amplitude at driving frequencies between ω_L and ω_H . Upon decreasing the driving force back to value in Fig. 4c, the system settles onto the upper branch instead of the lower one.

Figure 4d plots the measured stable (dots) and calculated stable and unstable vibrational states (solid and dashed lines, respectively) for different values of the driving force F_{d1} . Our

calculations show that, within the isolated loop, the state at higher amplitude is stable, and this is the state that is measured. The intermediate-amplitude state is unstable. As the drive amplitude is increased, the loop increases in size. Eventually, the lower end of the loop touches the top of the lower branch of the frequency response and the two merge into a single curve that resembles the shape of the response of a Duffing oscillator. More data and a detailed discussion of this unusual response is given in Supplemental Note 4.

Discussion

Our findings show that, by pumping two nonlinearly coupled microscale vibrational modes at the appropriate frequency, one can open a channel of decay involving two phonons of the slowly decaying mode and generate negative nonlinear friction in this mode. Such friction is controlled by the pumping and can be made sufficiently strong, so that the overall friction force becomes negative in a certain range of vibration amplitudes. This opens a new hitherto unexplored regime of the dynamics for micro/nanoscale resonators. As we show, the resulting instability is qualitatively different from the familiar case where the coefficient of linear friction is made negative, while nonlinear friction remains positive. In this latter case, it is well-known that the zero-amplitude state becomes unstable and the system starts oscillating. In contrast, for negative nonlinear friction, the zero-amplitude state always remains stable. Only when the system is ``pushed'' by an extra pulse into a range of large amplitudes does it become unstable. It then settles into the regime of self-sustained vibrations with the amplitude at which the total friction force (averaged over the period) is zero.

Negative nonlinear friction qualitatively changes the dynamics of the mode even when it is not strong enough to lead to self-sustained vibrations. The effect is revealed in the response of the mode to a resonant driving force. Already for a relatively weak force, there emerges a largeamplitude branch of forced vibrations. As a function of the force frequency, this branch is disconnected from the coexisting Lorentzian-type small-amplitude branch. Accessing the largeamplitude branch requires activation to perturb the vibration amplitude to large values. Once the mode is on the large-amplitude branch, shifts in the mode frequency or the driving frequency can induce jumping back to the small-amplitude state. Unlike the driven Duffing oscillator, here jumping occurs for frequency changes in either directions.

The study of negative nonlinear friction is advantageous for distinguishing between the "true" relaxation that comes from the coupling to a thermal reservoir with a large number of degrees of freedom and a broad excitation spectrum, on the one hand, and the relaxation that comes from the coupling to a vibrational mode with a comparatively fast decay rate, on the other hand. Our experiment demonstrates that it is the dynamical nature of the fast-decaying mode that ultimately prevents the system from a runaway. Such runaway would have occurred if the negative nonlinear friction force came from pumping-induced coupling to a thermal reservoir and therefore kept increasing with the increasing vibration amplitude. For the coupled modes, the stabilization mechanism is the dependence of the mode eigenfrequencies on the vibration amplitudes. Because of this dependence, in combination with the finite spectral width of the fast-decaying mode, the coupled modes are eventually tuned away from resonance with the pump as their amplitudes increase. The pumping-induced negative nonlinear friction falls off, and for large vibration amplitudes the overall decay rate approaches the linear decay rate.

While the negative nonlinear friction in our experiment originates from the coupling to another mode in the same micromechanical resonator, the analysis applies to mechanical modes coupled to microwave or optical cavities as well. We emphasize that, in contrast to the drivinginduced linear friction [17], driving-induced nonlinear friction leads to a strongly non-Boltzmann distribution over the eigenstates of the mechanical modes. The quantum and classical nonequilibrium statistical physics associated with such distribution, including the possibility to significantly reduce or increase the relative population of higher-lying excited states, warrants further study. On the application side, the observed bidirectional jumping of the amplitude of resonant response due to negative nonlinear friction can be used to detect, with high sensitivity, small bipolar frequency perturbations. This suggests a qualitatively new type of a bifurcation amplifier. For the self-sustained vibrations that emerge for stronger negative nonlinear friction, an advantageous feature is the possibility to turn them on and off without changing system parameters, which leads to improved controllability. The frequency of the self-sustained vibrations can be made extremely stable using a feedback loop in which the phase of one of the modes is measured and the output is used to control the phase of the other mode, which extends the mechanism of stable frequency downconversion [30] to a different frequency range.

Methods

Transduction scheme. Measurement were performed at a temperature of 4 K, pressure of $< 10^{-5}$ torr and magnetic field of 5 T perpendicular to the substrate. Two electrodes are located underneath the plate. One way to excite mode 1 (the plate mode) is to apply an ac probe voltage (Probe1 in Fig. 1c) at frequency ω_{d1} close to ω_1 on one of the electrodes to generate a periodic

electrostatic force $F_{d1} \cos \omega_{d1} t$. This ac voltage is set to zero when studying self-sustained vibrations. Vibrations of the plate mode are measured by detecting the change in the capacitance between the top plate and the other electrode. A charge-sensitive amplifier is connected to the top plate, the output of which is connected to the input of a lockin amplifier. The vibration amplitudes of the in phase (X(t)) and out of phase (Y(t)) components with respect to the reference signal at ω_{d1} yields the complex vibration amplitude $v_1(t) = (C_{sc}/2m_1\omega_1)^{1/2}[X(t) + iY(t)]$. For mode 2 (the beam mode), vibrations in the plane of the substrate can be electrostatically excited by applying an ac probe voltage (Probe2) at frequency ω_{d2} to the side gates. Motion of the beam is detected by recording the ac current generated by the electromotive force as the beam vibrates in-plane in the presence of the perpendicular magnetic field.

Acknowledgements

This work is supported by the Research Grants Council of Hong Kong SAR (Project No. 16315116). M.I.D. is supported by the National Science Foundation (DMR-1514591 and CMMI-1661618).

Author Contributions

H.B.C. and M.I.D. conceived the idea of the work. H.B.C. designed the experiments. M.I.D. developed the theory. X.D. performed the experiments and analyzed the data. X.D., H.B.C. and M.I.D. co-wrote the paper.

Competing Financial Interests

The authors declare no competing financial interests.

Supplementary Note 1. Dispersive coupling between the plate mode and the beam mode.

The plate mode and the beam mode are nonlinearly coupled. This parametric coupling arises from the tension induced in the beam as it deforms due to motion of one of the modes, which in turn modifies the spring constant of the other mode. Figure S1a shows the linear dependence of the change in ω_1 on the square of the vibration amplitude A₂ of the beam mode. Figure S1b shows a similar plot for the change in ω_2 . The linear fits in Figs. S1a and S1b yield the parameters γ_{12} (9.80 × 10²² rad² s⁻² m⁻²) and γ_{21} (1.37 × 10²⁵ rad² s⁻² m⁻²) respectively.



Figure S1 (a) The dependence of the scaled shift of the resonance frequency of the plate mode $\Delta \omega_1/\Gamma_1$ on the vibration amplitude square of the beam mode A₂. The line represents a linear fit. Inset: spectra of the plate mode in response to a small probe voltage (Probe1 in Fig. 1a), with A₂² increased from 39.13 nm² in steps of 70.54 nm². (b) Same plot for the beam mode. In the inset, A₁² is increased from 223.93 nm² in steps of 406.47 nm².

Supplementary Note 2. Adiabatic approximation

The parameters of the effective Hamiltonian H_{RWA} are related to the parameters used in the equations of motion (1) as $\Lambda_{12} = \gamma C_{sc}/2m_1m_2\omega_1\omega_2$, $\Lambda_{ii} = 3\gamma_i C_{sc}/4m_i^2\omega_i^2$, $f_p = F_p C_{sc}^{1/2}/4(2m_{2\omega_2})^{1/2}m_1\omega_1$. All these parameters have dimension of frequency.

The instantaneous decay rates for small vibration amplitudes (Figs. 2a and 2b) in the main text are calculated with Eq. (3) and the expression for α based on the adiabatic approximation with conservative nonlinear terms neglected. To extend the adiabatic approximation to larger amplitudes (Fig. 2c and 2d), it is necessary to re-introduce the conservative nonlinear terms. We define variables $\tilde{v}_{1,2}$ and ϕ as

$$v_1(t) = \tilde{v}_1(t)e^{i\phi(t)}, \ v_2(t) = \tilde{v}_2(t)e^{-2i\phi(t)}$$
 (S2.1)

The phase $\phi(t)$ will be chosen self-consistently so that, in the adiabatic approximation that we develop, the decay of function \tilde{v}_1 is not accompanied by phase accumulation, which means that \tilde{v}_1 can be set real.

From Eq. (2) of the main text, equation for \tilde{v}_2 reads

$$\frac{d}{dt}\,\tilde{v}_2 = -D\tilde{v}_2 - if_p\,\tilde{v}_1^{*2}\,,\ D = \Gamma_2 + i\Delta - 2i\dot{\phi} - i\Lambda_{12}|\tilde{v}_1|^2 - i\Lambda_{22}|\tilde{v}_2|^2 \qquad(S2.2)$$

Here, $D \equiv D(\dot{\phi}, |\tilde{v}_1|^2, |\tilde{v}_2|^2)$. The adiabatic approximation means that we set $d\tilde{v}_2/dt = 0$. We will then have to check that, for \tilde{v}_2 obtained this way, $|d\log|\tilde{v}_2|/dt| \ll |D|$. If $dv_2/dt = 0$, then

$$\tilde{v}_2 \approx -if_p \tilde{v}_1^{*^2} / D. \tag{S2.3}$$

Substituting the result into the first Eq. (2) of the main text with the account taken of Eq.(S2.1), we find

$$\frac{d}{dt}\tilde{v}_{1} = -\Gamma_{ad}\tilde{v}_{1}, \quad \Gamma_{ad} \equiv \Gamma_{ad}(|\tilde{v}_{1}|^{2}) = \Gamma_{1} - 2f_{p}^{2}|\tilde{v}_{1}|^{2} \operatorname{Re} D^{-1},$$
$$\dot{\phi} = \Lambda_{12} |f_{p}\tilde{v}_{1}^{*^{2}} / D|^{2} + \Lambda_{11} |\tilde{v}_{1}|^{2} - 2f_{p}^{2}|\tilde{v}_{1}|^{2} \operatorname{Im} D^{-1}.$$
(S2.4)

Here $\dot{\phi}$ and parameter *D* are functions only of $|\tilde{v}_1|^2$. The numerical solution of the selfconsistent nonlinear equations (S2.2)-(S2.4) gives the adiabatic decay rate Γ_{ad} . From Eq. (S2.3), this solution applies provided $\Gamma_{ad} \ll |D|$, in which case $|d \log \tilde{v}_2/dt| \ll |D|$, as it was assumed in the derivation.

Supplementary Note 3. Frequency and amplitude of self-sustained vibrations for negative friction

The frequency and amplitude of self-sustained vibrations can be derived from Eq. (2) in the main text. By substituting $v_1 = c_1 e^{i\delta\omega t}$, $v_2 = c_2 e^{-2i\delta\omega t}$, we obtain

$$\dot{c}_{1} = -(\Gamma_{1} + i\delta\omega)c_{1} + i\Lambda_{11}c_{1}|c_{1}|^{2} + i\Lambda_{12}c_{1}|c_{2}|^{2} - 2if_{p}c_{1}^{*}c_{2}^{*},$$

$$\dot{c}_{2} = -(\Gamma_{2} + i\Delta - 2i\delta\omega)c_{2} + i\Lambda_{12}c_{2}|c_{1}|^{2} + i\Lambda_{22}c_{2}|c_{2}|^{2} - if_{p}c_{1}^{*2}$$
(S3.1)

For stationary self-sustained oscillations, $\dot{c}_1 = \dot{c}_2 = 0$. The relation between the amplitudes c_1 and c_2 and the value of $\delta \omega$ are given by equation

$$\Gamma_1 |c_1|^2 = 2\Gamma_2 |c_2|^2; \qquad \delta \omega = (2\Gamma_1 + \Gamma_2)^{-1} \left[\Gamma_1 \Delta - |c_1|^2 \left(\frac{1}{2} \Gamma_1 \Lambda_{12} + \frac{1}{2} (\Gamma_1^2 / \Gamma_2) \Lambda_{22} - \Gamma_2 \Lambda_{11} \right) \right] (S3.2)$$

where the squared amplitude of mode 1 is

$$|c_{1}|^{2} = (\Gamma_{2} / \Gamma_{1})G^{-2} \{\Gamma_{1}G \Delta + (2\Gamma_{1} + \Gamma_{2})^{2}f_{p}^{2} \pm (2\Gamma_{1} + \Gamma_{2})[2\Gamma_{1}f_{p}^{2}G\Delta + (2\Gamma_{1} + \Gamma_{2})^{2}f_{p}^{4} - \Gamma_{1}^{2}G^{2}]^{1/2}\}$$

$$G = (\Gamma_{1} + \Gamma_{2})\Lambda_{12} + 2\Gamma_{2}\Lambda_{11} + \frac{1}{2}\Gamma_{1}\Lambda_{22}$$
(S3.3)

The self-sustained oscillation frequency of the plate mode and the beam mode are $\omega_1 + \delta \omega$ and $\omega_F - 2\omega_1 - 2\delta \omega$ respectively.

Equations (S3.2) and (S3.3) describe two vibrational branches with different amplitudes and frequencies. Linearizing Eq. (S3.1) about the corresponding solutions one can show that the larger-amplitude branch is stable, whereas the smaller-amplitude branch is unstable. The periodic solutions exist in the range where the argument of the square root in Eq. (S3.3) for $|c_1|^2$ is positive, which imposes a constraint on the frequency and amplitude of the drive

$$2f_p^2 G(\omega_F - \omega_2 - 2\omega_1) + (2\Gamma_1 + \Gamma_2)^2 f_p^4 - \Gamma_1^2 G^2 > 0$$
(S3.4)

This condition allowed us to calibrate the pumping power from the measured value of ω_F where the periodic solutions first emerge, because all other quantities in Eq. (S3.4) are independently measured.

One can think of the birth of the stable and unstable limit cycles as a saddle-node bifurcation. There are limit cycles for the two modes, but since they are coupled, one can describe them near the bifurcation point by one variable, the effective radius of one of the cycles r. The equation for this radius near its bifurcational value r_0 is

$$\dot{r} = -(r - r_0)^2 + \epsilon$$
 (S3.5)

where ϵ is the control parameter; in the experiment, the control parameter is the frequency detuning of the pump $\Delta = \omega_F - \omega_2 - 2\omega_1$, and then $\epsilon \propto \Delta - \Delta_B$ where Δ_B is the bifurcational value of Δ where the left-hand side of Eq. (S3.4) is zero.

For $\epsilon < 0$ Eq. (S3.5) has no stationary solutions for the limit cycle radius with r close to r_0 . However, for $\epsilon > 0$ there are two stationary solutions, $r - r_0 = \pm \sqrt{\epsilon}$, which merge at $\epsilon = 0$. The solution with $r - r_0 = \sqrt{\epsilon}$ corresponds to a stable limit cycle, whereas the one with $r - r_0 = \sqrt{\epsilon}$ $-\sqrt{\epsilon}$ corresponds to an unstable limit cycle. In the considered system, the trajectories that start inside the unstable limit cycle (with respect to the variables of the both coupled modes) go to the zero-amplitude state.

Supplementary Note 4. Multi-valued resonant response

Resonant response of the plate mode (mode 1) to a periodic force is described by adding a term $F_{d1} \cos \omega_{d1} t$ to the first equation in Eq. (1), where F_{d1} is the driving amplitude and ω_{d1} is the resonant driving frequency with $|\omega_{d1} - \omega_1| \ll \omega_1$. Equations (2) of the main text are modified to:

$$\dot{v}_1 = -\Gamma_1 v_1 + i(\partial H_{RWA}/\partial v_1^*) - if_{d1} \exp[i(\omega_{d1} - \omega_1)t],$$
$$\dot{v}_2 = -\Gamma_2 v_2 + i(\partial H_{RWA}/\partial v_2^*)$$
(S4.1)

where $f_{d1} = (8m_1\omega_1C_{sc})^{-1/2}F_{d1}$ is the scaled extra force $(f_{d1} = 1.717s^{-1} \text{ for main plot of fig.}$ 4c).

To find periodic vibrations at frequency ω_d one solves Eq. (S4.1) by setting $v_1 = u_1 \exp[i(\omega_{d1} - \omega_1)t]$, $v_2 = u_2 \exp[-2i(\omega_{d1} - \omega_1)t]$ and assuming that $u_{1,2}$ are independent of time, which reduces the problem to a set of algebraic equations for the complex amplitudes $u_{1,2}$

$$[\Gamma_{1} + i(\omega_{d1} - \omega_{1})]u_{1} = i \,\partial H'_{RWA} / \partial u_{1}^{*} - if_{d1},$$

$$[\Gamma_{2} - 2i(\omega_{d1} - \omega_{1})]u_{2} = i \,\partial H'_{RWA} / \partial u_{2}^{*},$$
 (S4.2)

where H'_{RWA} is given by Eq.(2) of the main text for H_{RWA} in which v_1 is replaced by u_1 and v_2 is replaced by u_2 . The amplitude of forced vibrations is $a_1 = (2C_{sc}/m_1\omega_1)^{1/2}|u_1|$. Equations (S4.2) can be further reduced to a system of two equations for the scaled squared vibration amplitudes

$$|Z_{1} - 2|f_{p}|^{2} |u_{1}^{2}| / Z_{2}^{*}|^{2} |u_{1}^{2}| = |f_{d1}|^{2}, \quad |u_{2}^{2}| = |f_{p}^{2}| |u_{1}^{4}| / |Z_{2}^{2}|,$$

$$Z_{1} = \Gamma_{1} + i(\omega_{d1} - \omega_{1}) - i\Lambda_{12}|u_{2}^{2}| - i\Lambda_{11}|u_{1}^{2}|, \quad (S4.3)$$

$$Z_{2} = \Gamma_{2} - 2i(\omega_{d1} - \omega_{1}) + i\Delta - i\Lambda_{12}|u_{1}^{2}| - i\Lambda_{22}|u_{2}^{2}|$$

The phases of u_1 , u_2 in the stationary states of forced vibrations can be immediately found from Eqs. (S4.2) and (S4.3). The stability of the vibrational states is determined in the standard way by using Eqs. (S4.1) to write equations of motion for u_1 , u_2 and linearize these equations about the stationary values of u_1 , u_2 .

The response curves for negative friction are qualitatively different from the response curves of the Duffing oscillator, as shown in Fig.4c. This figure shows that the amplitude $|a_1|$ as function of the drive frequency can have disconnected branches in a certain range of the driving amplitude F_{d1} . As explained in the main text, reaching a disconnected branch in this case requires activation, e.g., a pulse that makes the vibration amplitude sufficiently large so that it approaches the large-amplitude value. In other words, mode 1 reaches the basin of attraction of the corresponding stable vibrational state. In Fig. S2 more detailed data on the response are shown and compared with the theoretical results described by Eqs. (S4.1) – (S4.3). As seen from panels (a)-(c), at the end points of the large-amplitude branches the stable and unstable states merge. The analysis shows that these are simple saddle-node bifurcation points.



Figure S2. Measured (dots) and calculated stable (solid lines) and unstable (dashed lines) vibration amplitudes for the driving force amplitude F_{d1} equal to 0.595 pN (a), 0.700 pN (b), 0.805 pN (c), 0.8213525 pN (d) (calculation only), 0.840 pN (e) and 0.980 pN (f). The isolated branch exists in a limited range of F_{d1} . As F_{d1} increases beyond a critical value, it merges with the lower branch [panel (d)] and disappears.

With increasing amplitude of the force F_{d1} , the frequency range where there exists the isolated large-amplitude branch expands, Fig. S2a-c. At the same time, the amplitude of the vibrations on the small-amplitude branch increases. Ultimately, the two branches merge (Fig.S2d), and for still stronger drive (Fig. S2e and S2f) the response curve becomes reminiscent

of the standard Duffing response curve for linear friction. The measurements and the theory are in good agreement.



Figure S3. (a) Calculated stable (solid lines) and unstable (dashed lines) vibration amplitudes for F_{d1} equal to 0.8212748 pN (green), 0.8213525 pN (purple, and 0.8213798 pN (yellow) showing the merging of the isolated branch with the lower branch. Individual curves are plotted in (b), (c) and (d).

The merging and restructuring of the branches is an example of a bifurcation of codimension 2. Panel (a) in Fig. S3 shows the summary plot of the evolution of the frequency response curve with increasing drive, whereas panels (b)-(d) show the individual response curves; the drive amplitude in panel (d) is larger than in panel (b) by only 0.013%. The results are obtained by numerically solving equations for u_1, u_2 . The overall evolution in the narrow range where the structure is changed can be mapped onto equation for an auxiliary variable x (a combination of u_1 and u_2) of the form $\dot{x} = x^2 - (\omega - \omega_c)^2 + \epsilon$, where ω_c is the value of $\omega_{d1} - \omega_1$ at the intersection of the curves in Fig. S3 (c) and ϵ is the scaled difference between F_{d1} and the value of F_{d1} in Fig. S3 (c).

<u>Supplementary Note 5. Bistability of the characteristic spectral width Γ_{peak} for strong negative nonlinear friction</u>

A sufficiently strong negative nonlinear friction gives rise to the isolated branch in the driven response of mode 1 as function of the drive frequency (Fig. 4c and Fig. 4d). The isolated branch and the lower branch have different maximum vibration amplitudes a_{1max} of forced vibrations. Figure S4 illustrates the effect of different strength of negative nonlinear friction on the quantity Γ_{peak} that is proportional to the ratio of the amplitude F_{d1} of the periodic driving force to a_{1max} . With large pump detuning Δ of -1000 Hz (black data), negative nonlinear friction is essentially absent and the frequency response has only one branch. It corresponds to the response of a Duffing oscillator with linear friction, and Γ_{peak} is independent of the drive amplitude F_{d1} even where the response to the resonant drive is significantly nonlinear [41]. When Δ is increased to -50 Hz (green data), the effects of negative nonlinear friction become important. As a consequence, Γ_{peak} decreases sharply at 1.12 pN, corresponding to a superlinear increase of the peak amplitude with drive amplitude. Upon further increase of Δ to -35 Hz and the respective increase of negative nonlinear friction, the response to the resonant drive displays two branches, as seen in Fig. 4c; see also Supplemental Note 4. We can define Γ_{peak} for each branch, and then it becomes multivalued for periodic driving amplitude between 0.57 pN and 0.82 pN (blue data). In particular, the two circles correspond to the maximum vibration amplitude for the two branches in Fig. 4c. Such bistability of Γ_{peak} does not occur for systems

with conservative nonlinearity such as Duffing or parametric resonators, nor in systems with weak nonlinear friction.



Figure S4. The dots show the dependence of $\Gamma_{peak} = F_{d1}/4m_1\omega_1a_{1\,max}$ on the drive amplitude for negligible nonlinear friction (the pump detuning $\Delta = -1000$ Hz, black) and increasingly strong negative nonlinear friction ($\Delta = -50$ Hz, green, and $\Delta = -35$ Hz, blue). The filled circles represent the peak amplitudes of the response a_{1max} for the two branches in Fig. 4c. The solid lines in this figure are theoretical predictions (Supplementary Note 4).

Supplementary Note 6. Hysteresis of the vibration amplitude with varying driving force amplitude.

The amplitude of forced vibrations of a nonlinear oscillator with linear friction is known to display hysteresis with varying amplitude of the driving resonant force [41]. Here we show that the character of the hysteresis changes qualitatively in the presence of negative nonlinear friction. In Fig. S5 we plot the amplitude of forced vibrations a_1 as a function of the driving force amplitude F_{d1} for a fixed driving frequency ω_{d1} . The data for red and purple curves in Fig. S5 are taken with large pump detuning $\Delta = -1000$ Hz, so that nonlinear friction effects are practically absent and the system behaves as a Duffing oscillator. For Duffing oscillators, the hysteretic response occurs only if the detuning $\delta \omega = \omega_{d1} - \omega_1$ of the driving frequency from the mode eigenfrequency exceeds the threshold value of $\sqrt{3} \Gamma_1$ (~0.9 Hz for our system). Figure S5 shows that when $\delta \omega$ is reduced from 1.1 Hz (blue curve) to 0.4 Hz (red curve), hysteresis indeed disappears. The red curve is obtained by changing the pump detuning to -35 Hz so that negative nonlinear friction becomes strong. The detuning of the driving force is set at $\delta \omega = 0.4$ Hz. It is thus $\langle \sqrt{3} \Gamma_1$. Still we observe hysteresis, because vibrations at high amplitudes are stabilized by negative nonlinear friction. We note that the dependence of the vibration amplitude a_1 on the force amplitude F_{d1} for fixed ω_{d1} does not display an isolated branch, in contrast to the dependence of a_1 on ω_{d1} for fixed F_{d1} .



Figure S5 Comparison of the dependence of the amplitude a_1 of forced vibrations on the drive amplitude F_{d1} for mode 1 with and without negative nonlinear friction. For a Duffing resonator with effectively linear friction (the pump detuning $\Delta = -1000$ Hz), hysteresis is seen on the blue curve, which refers to $\omega_{d1} - \omega_1 = 1.1$ Hz > $\sqrt{3}$ Γ_1 . For the purple curve with $\omega_{d1} - \omega_1 = 0.4$ Hz smaller than $\sqrt{3}$ Γ_1 , there is no hysteresis. In contrast, when negative nonlinear friction is strong ($\Delta = -35$ Hz), hysteresis is seen even for $\omega_{d1} - \omega_1 = 0.4$ Hz (the red curve). The calculated unstable states are shown as dashed lines.

Reference

- 1. L. Mandel and W. E. *Optical Coherence and Quantum Optics* (Cambirdge University Press, Cambridge, 1995).
- 2. A. H. Nayfeh and M. D. T. *Nonlinear oscillations* (Wiley-VCH, Weinheim, 2004).
- 3. B. Van der Pol, *A theory of the amplitude of free and forced triode vibrations*, Radio Review **1**, 701 (1920).
- 4. A. Eichler et al., *Nonlinear damping in mechanical resonators made from carbon nanotubes and graphene*, Nature Nanotechnology **6**, 339 (2011).
- 5. S. Zaitsev, O. Shtempluck, E. Buks and O. Gottlieb, *Nonlinear damping in a micromechanical oscillator*, Nonlinear Dynamics **67**, 859 (2012).
- 6. M. Imboden, O. A. Williams and P. Mohanty, *Observation of Nonlinear Dissipation in Piezoresistive Diamond Nanomechanical Resonators by Heterodyne Down-Mixing*, Nano Letters **13**, 4014 (2013).
- T. F. Miao, S. Yeom, P. Wang, B. Standley and M. Bockrath, *Graphene* Nanoelectromechanical Systems as Stochastic-Frequency Oscillators, Nano Letters 14, 2982 (2014).
- 8. I. Mahboob et al., *Dispersive and Dissipative Coupling in a Micromechanical Resonator Embedded with a Nanomechanical Resonator*, Nano Letters **15**, 2312 (2015).
- 9. P. M. Polunin, Y. S. Yang, M. I. Dykman, T. W. Kenny and S. W. Shaw, *Characterization of MEMS Resonator Nonlinearities Using the Ringdown Response*, Journal of Microelectromechanical Systems **25**, 297 (2016).
- 10. B. Rodenburg, L. P. Neukirch, A. N. Vamivakas and M. Bhattacharya, *Quantum model of cooling and force sensing with an optically trapped nanoparticle*, Optica **3**, 318 (2016).
- 11. Z. Leghtas et al., *Confining the state of light to a quantum manifold by engineered twophoton loss*, Science **347**, 853 (2015).
- 12. R. W. Heeres et al., *Implementing a universal gate set on a logical qubit encoded in an oscillator*, Nature Communications **8**, 94 (2017).
- 13. J. Schwinger, Brownian motion of a quantum oscillator, J. Math. Phys. 2, 407 (1961).
- M. I. Dykman and M. A. Krivoglaz, Spectral Distribution of Nonlinear Oscillators with Nonlinear Friction Due to a Medium, Physica Status Solidi B-Basic Research 68, 111 (1975).
- 15. A. Croy, D. Midtvedt, A. Isacsson and J. M. Kinaret, *Nonlinear damping in graphene resonators*, Physical Review B **86**, 235435 (2012).
- 16. J. Atalaya, T. W. Kenny, M. L. Roukes and M. I. Dykman, *Nonlinear damping and dephasing in nanomechanical systems*, Physical Review B **94**, 195440 (2016).
- 17. M. Aspelmeyer, T. J. Kippenberg and F. Marquardt, *Cavity optomechanics*, Reviews of Modern Physics **86**, 1391 (2014).
- 18. M. I. Dykman, *Heating and cooling of local and quasilocal vibrations by a nonresonance field*, Soviet Physics Solid State **20**, 1306 (1978).
- 19. F. Marquardt, J. P. Chen, A. A. Clerk and S. M. Girvin, *Quantum theory of cavityassisted sideband cooling of mechanical motion*, Physical Review Letters **99**, 093902 (2007).
- 20. I. Wilson-Rae, N. Nooshi, W. Zwerger and T. J. Kippenberg, *Theory of ground state cooling of a mechanical oscillator using dynamical backaction*, Physical Review Letters **99**, 093901 (2007).

- 21. J. M. Fink et al., *Quantum electromechanics on silicon nitride nanomembranes*, Nature Communications 7, 12396 (2016).
- 22. J. B. Clark, F. Lecocq, R. W. Simmonds, J. Aumentado and J. D. Teufel, *Sideband* cooling beyond the quantum backaction limit with squeezed light, Nature **541**, 191 (2017).
- 23. T. J. Kippenberg, H. Rokhsari, T. Carmon, A. Scherer and K. J. Vahala, *Analysis of radiation-pressure induced mechanical oscillation of an optical microcavity*, Physical Review Letters **95**, 033901 (2005).
- 24. T. Carmon, H. Rokhsari, L. Yang, T. J. Kippenberg and K. J. Vahala, *Temporal behavior* of radiation-pressure-induced vibrations of an optical microcavity phonon mode, Physical Review Letters **94**, 223902 (2005).
- 25. C. Metzger et al., *Self-induced oscillations in an optomechanical system driven by bolometric backaction*, Physical Review Letters **101**, 133903 (2008).
- 26. M. Bagheri, M. Poot, M. Li, W. P. H. Pernice and H. X. Tang, *Dynamic manipulation of nanomechanical resonators in the high-amplitude regime and non-volatile mechanical memory operation*, Nature Nanotechnology **6**, 726 (2011).
- 27. T. Faust, P. Krenn, S. Manus, J. P. Kotthaus and E. M. Weig, *Microwave cavityenhanced transduction for plug and play nanomechanics at room temperature*, Nature Communications **3**, 728 (2012).
- 28. F. M. Buters et al., *Experimental exploration of the optomechanical attractor diagram and its dynamics*, Physical Review A **92**, 013811 (2015).
- 29. H. Rokhsari, T. J. Kippenberg, T. Carmon and K. J. Vahala, *Radiation-pressure-driven micro-mechanical oscillator*, Optics Express **13**, 5293 (2005).
- F. Sun, X. Dong, J. Zou, M. I. Dykman and H. B. Chan, *Correlated anomalous phase diffusion of coupled phononic modes in a sideband-driven resonator*, Nature Communications 7, 12694 (2016).
- 31. J. Gao et al., A semiempirical model for two-level system noise in superconducting microresonators, Applied Physics Letters **92**, 212504 (2008).
- 32. J. S. Gao, J. Zmuidzinas, B. A. Mazin, H. G. LeDuc and P. K. Day, *Noise properties of* superconducting coplanar waveguide microwave resonators, Applied Physics Letters **90**, 102507 (2007).
- 33. V. Singh, O. Shevchuk, Y. M. Blanter and G. A. Steele, *Negative nonlinear damping of a multilayer graphene mechanical resonator*, Physical Review B **93**, 245407 (2016).
- K. W. Lehnert, Introduction to Microwave Cavity Optomechanics. In Cavity Optomechanics: Nano- and Micromechanical Resonators Interacting with Light (eds. M. Aspelmeyer, T. Kippenberg & F. Marquardt) 233-252 (Springer, Berlin, 2014).
- 35. J. Suh, A. J. Weinstein and K. C. Schwab, *Optomechanical effects of two-level systems in a back-action evading measurement of micro-mechanical motion*, Applied Physics Letters **103** (2013).
- 36. I. Siddiqi et al., *RF-driven Josephson bifurcation amplifier for quantum measurement*, Physical Review Letters **93**, 207002 (2004).
- 37. J. S. Aldridge and A. N. Cleland, *Noise-enabled precision measurements of a duffing nanomechanical resonator*, Phys. Rev. Lett. **94**, 156403 (2005).
- 38. A. Lupascu et al., *Quantum non-demolition measurement of a superconducting two-level system*, Nature Physics **3**, 119 (2007).
- 39. R. Vijay, M. H. Devoret and I. Siddiqi, *Invited Review Article: The Josephson bifurcation amplifier*, Review of Scientific Instruments **80**, 111101 (2009).

- 40. E. Kenig et al., *Passive Phase Noise Cancellation Scheme*, Physical Review Letters **108**, 264102 (2012).
- 41. L. Landau and E. Lifshitz. *Mechanics* (Elsevier, Amsterdam, 1969).