

A KINETIC TRAFFIC NETWORK MODEL AND ITS MACROSCOPIC LIMIT: DIVERGING LANES

R. BORSCHÉ* AND A. KLAR*[†]

Abstract. This paper is a continuation of the work in [10] on macroscopic limits of kinetic traffic networks. There, the case of merging lanes has been investigated. In the present work we propose coupling conditions for a kinetic two velocity model for vehicular traffic for junctions with diverging lanes. We consider cases with and without directional preferences and present corresponding kinetic coupling conditions. From this kinetic network model coupling conditions for a macroscopic traffic model are derived. We use as in [10] an analysis of the layer equations at the junction in combination with a suitable matching procedure with half-Riemann problems for the macroscopic model. In this way classical coupling conditions for scalar conservation laws for traffic flow on networks are derived from an underlying network problem.

1. Introduction. In the context of traffic flow on networks many models rely on hyperbolic partial differential equations ranging from scalar conservation laws over systems of conservation laws to kinetic models [19, 1, 2, 31, 32, 25]. For some of these equations hierarchies of such models have been established for single roads, e.g. deriving macroscopic equations from microscopic ones. Such hierarchies have been investigated for example in [1, 2, 6, 17]. Similarly macroscopic models can be obtained from kinetic descriptions, see e.g. [21, 27]. On the other hand there has been a continuous effort in extending such models onto networks of roads. Most of these approaches consider scalar conservation laws, see e.g. [26, 12, 19, 13]. Only few attempts have been made for second order or kinetic problems [22, 23]. In none of these works a hierarchy of such models on a network has been investigated and network models for macroscopic models derived from underlying kinetic or microscopic models.

In [10] such an investigation has been started for a basic kinetic model leading to scalar hyperbolic traffic models. There, we have only considered the case of merging junctions. The present paper aims to close this gap for diverging junctions, i.e. for junctions with one ingoing and two outgoing roads. Hereby we follow closely the strategy developed in [11, 8, 9, 10]. In [9] coupling conditions for the wave equation have been derived from an underlying linear kinetic description. For the wave equation this procedure involves an approximation of the layers arising at the junction [9]. Non linear problems, like the Burgers equation, further require a half Riemann problem to link the layer solution to the macroscopic states [8]. By a successive combination of these tools coupling conditions for the associated macroscopic problems can be derived from the kinetic models.

In the present paper we first propose coupling conditions on the kinetic level for a two velocity traffic model, derived in [7]. An important advantage, compared to the macroscopic equation, is, that for the two velocity model the required number of coupling condition remains constant. On each individual road the equations contain a scaling parameter ϵ and their solutions converge for $\epsilon \rightarrow 0$ to an associated scalar traffic flow model. If ϵ is sent to zero on the network, boundary layers at the junctions can arise. The structure of such layers can be studied by investigating the solutions of the associated half space problems. Similar approaches have been used in [4, 5, 20, 15, 33, 30, 3] in the context of kinetic equations and in [36, 34, 29, 35] for hyperbolic

[†]Technische Universität Kaiserslautern, Department of Mathematics, Erwin-Schrödinger-Straße, 67663 Kaiserslautern, Germany ({borsche, klar}@mathematik.uni-kl.de)

²Fraunhofer ITWM, Fraunhoferplatz 1, 67663 Kaiserslautern, Germany

relaxation systems. Since the equations under consideration are non linear, these half space problems have to be coupled to half Riemann problems of the macroscopic equation, as outlined in [8]. Combining all these, a non linear problem is established in terms of the macroscopic unknowns at the node. The solution to this coupling problem provides the required states at the junction for the scalar hyperbolic model and the limit of the kinetic traffic network problem as $\epsilon \rightarrow 0$.

The paper is organized as follows. First the two velocity traffic model is revisited and, shortly, the main features are collected. In section 3 coupling conditions for this kinetic equation are proposed for diverging junctions. The case of a junction with one ingoing and two outgoing roads is considered and drivers with or without directional preferences are discussed. Aside the conservation of mass at the node, the free space available in the exiting roads is an important quantity. In section 5 the resulting coupling conditions for the scalar variables as $\epsilon \rightarrow 0$ are presented. A detailed derivation of these results is given in section 7. Further, the obtained results are verified by numerical examples in section 6.

2. Kinetic and macroscopic traffic equations. We consider a minimal kinetic discrete velocity model [7] with just two velocities $v_0 = 0$ and $v_1 = 1$. The densities corresponding to these velocities are f_0 , which represents the stopped cars, and f_1 , which is the density of driving cars. Using these we can define the total density of cars as $\rho = f_0 + f_1 \in [0, 1]$ and the mean flux as $q = v_0 f_0 + v_1 f_1 = f_1$ or reversely

$$f_0 = \rho - q, \quad f_1 = q.$$

The dynamics of these quantities is governed by the discrete velocity model developed in [7]

$$\begin{aligned} \partial_t f_0 - \frac{1}{1-\rho} f_1 \partial_x f_0 &= -\frac{1}{\epsilon} (f_0 - \rho + F(\rho)) \\ \partial_t f_1 + \partial_x f_1 + \frac{1}{1-\rho} f_1 \partial_x f_0 &= -\frac{1}{\epsilon} (f_1 - F(\rho)) , \end{aligned} \tag{2.1}$$

where $F = F(\rho)$ is a given traffic density-flow function or fundamental diagram. We assume $F : [0, 1] \rightarrow [0, 1]$ to be a smooth function with $F(0) = 0 = F(1)$, $F'(\rho) \leq 1$ and its graph in the triangle $0 \leq \rho \leq 1, 0 \leq q \leq \rho$. In the following we restrict ourselves to strictly concave fundamental diagrams F . The point, where the maximum of F is attained we denote by ρ^* and the maximal value by $F(\rho^*) = \sigma$.

The two eigenvalues corresponding to (2.1) are $\lambda_1 = -\frac{q}{1-\rho} \leq 0 < \lambda_2 = 1$ with the respective eigenvectors $r_1 = (1, \lambda_1)^T, r_2 = (1, 1)$. The system is strictly hyperbolic and both characteristic families are linearly degenerate. The integral curves of the hyperbolic system are given by $q = q_L \frac{1-\rho}{1-\rho_L}$ for the 1-field and by $q = \rho - \rho_R + q_R$ for the 2-field. As the maximal velocity is set to 1 the region $0 \leq \rho \leq 1, 0 \leq q \leq \rho$ is an invariant region for the kinetic equations.

A Riemann invariant of the first characteristic family is

$$Z = \frac{q}{1-\rho+q} = \frac{q}{1-w} = \frac{f_1}{1-f_0} \in [0, 1].$$

As for q we have $0 \leq Z \leq \rho$. By using this variable Z the system (2.1) can be

transformed into conservative form

$$\begin{aligned}\partial_t \rho + \partial_x q &= 0 \\ \partial_t Z + \partial_x Z &= -\frac{(1-Z)}{\epsilon(1-\rho)}(q - F(\rho))\end{aligned}\tag{2.2}$$

with $q = \frac{Z}{1-Z}(1-\rho)$. Note that this change does not influence the speed of possible discontinuities, as both fields are linearly degenerate.

A Riemann invariant of the second characteristic family is

$$w = \rho - q = f_0 \in [0, 1] .$$

the quantity $1 - w$ can be interpreted as the free space available or the maximal possible number of driving cars. Z can be understood as the ratio between the actual number of driving cars and the maximal possible number of driving cars.

Similarly, equation (2.1) can be expressed in macroscopic variables ρ, q as

$$\begin{aligned}\partial_t \rho + \partial_x q &= 0 \\ \partial_t q + \frac{q}{1-\rho} \partial_x \rho + (1 - \frac{q}{1-\rho}) \partial_x q &= -\frac{1}{\epsilon}(q - F(\rho)) .\end{aligned}\tag{2.3}$$

Concerning the convergence of its solutions towards the solutions of the scalar conservation law $\partial_t \rho + \partial_x F(\rho) = 0$ as ϵ tends to 0 the subcharacteristic condition has to be satisfied [29]. Setting $q = F(\rho)$ in the eigenvalues, the subcharacteristic condition states

$$-\frac{F(\rho)}{1-\rho} \leq F'(\rho) \leq 1 \quad \text{for } 0 \leq \rho \leq 1 .$$

REMARK 1. *The condition is fulfilled for strictly concave fundamental diagrams F . For example, in the classical LWR case with $F(\rho) = \rho(1-\rho)$ and $F'(\rho) = 1-2\rho$ the above condition is*

$$-\rho \leq 1-2\rho \leq 1 \quad \text{for } 0 \leq \rho \leq 1 ,$$

which is obviously satisfied.

On a finite domain the kinetic problem (2.1) has to be equipped with boundary conditions. At the left boundary at $x = x_L$ a value for the 2- Riemann invariant $Z(x_L) = \frac{q(x_L)}{1-\rho(x_L)-q(x_L)} = \frac{f_1(x_L)}{1-f_0(x_L)}$ is set and for the right boundary $x = x_R$ the 1-Riemann invariant $w(x_R) = f_0(x_R)$. As the first eigenvalue is always non-positive and the second is constant, the number of boundary conditions does not alter.

3. Kinetic Coupling conditions. In this section we propose coupling conditions for the kinetic two-velocity model (2.1). As on each road there is exactly one outgoing characteristic family, we have to provide three conditions at a junction connecting three roads. In any case the conservation of mass will be imposed, i.e. all cars entering a junction via one of the incoming roads will exit on one of the outgoing roads. For the remaining two conditions we will analyze the maximal possible number of driving cars $1 - w = 1 - f_0$ on the exiting roads. Note that only the stopped cars $w = f_0$ on the outgoing roads can block the traffic, as the driving ones $f_1 = q$ will clear the space. Thus $1 - f_0$ is the available free space for driving cars.

From the mathematical point of view it is important to supply values for the correct characteristic variables. We denote with $\hat{\cdot}$ the known traces at the junction. The unknown characteristic variables as well as partially known quantities in the junctions do not have a superscript.

We consider junctions with one incoming and two outgoing roads. Road number 1 is the incoming one, see Figure 3.1.




Fig. 3.1: A junction with one incoming and two outgoing roads (1-2 node).

3.1. Junction with diverging lanes and no driver preferences. In this section we assume that the drivers have no priority which road to take. Drivers decide locally according to the free space which road they want to follow. Thus the free space in the exiting roads is the relevant quantity.

The free space observed by the drivers in road 1 when looking towards road 2 is the free space in road 2 plus the space occupied by the cars driving towards road 3

$$1 - w^1 = 1 - f_0^1 = 1 - f_0^2 + f_1^3 = 1 - w^2 + q^3 . \quad (3.1)$$

Similarly, we obtain

$$1 - w^1 = 1 - f_0^1 = 1 - f_0^3 + f_1^2 = 1 - w^3 + q^2 . \quad (3.2)$$

Finally the conservation of mass is

$$f_1^1 = q^1 = q^2 + q^3 = f_1^2 + f_1^3 . \quad (3.3)$$

Note that (3.1) and (3.2) not only specify the free space on road one, but also serve as condition for the distribution of the cars.

It is easy to see that these equations are only valid under further restrictions, e.g. if on road 2 there are no stopped cars, $f_0^2 = w^2 = 0$, and $f_1^3 > 0$ equation (3.1) will result in a free space larger than one.

Thus, these conditions have to be truncated such that all quantities remain within their physical bounds. They can be more easily determined expressing the equations (3.1-3.3) in characteristic variables or Riemann Invariants. We have

$$\begin{aligned} 1 - w^1 &= 1 - \hat{w}^2 + Z^3(1 - \hat{w}^3) \\ 1 - w^1 &= 1 - \hat{w}^3 + Z^2(1 - \hat{w}^2) \\ \hat{Z}^1(1 - w^1) &= Z^2(1 - \hat{w}^2) + Z^3(1 - \hat{w}^3). \end{aligned}$$

The above equations are solved by

$$1 - w^1 = \frac{2 - (\hat{w}^2 + \hat{w}^3)}{2 - \hat{Z}^1}$$

and

$$(1 - \hat{w}^2)Z^2 = \frac{1}{2 - \hat{Z}^1}(\hat{Z}^1(1 - \hat{w}^3) - (\hat{w}^2 - \hat{w}^3))$$

$$(1 - \hat{w}^3)Z^3 = \frac{1}{2 - \hat{Z}^1}(\hat{Z}^1(1 - \hat{w}^2) + (\hat{w}^2 - \hat{w}^3)) .$$

We obtain a valid expression for $0 \leq 1 - w^1 \leq 1$ if $2 - (\hat{w}^2 + \hat{w}^3) \leq 2 - \hat{Z}^1$ or $\hat{w}^2 + \hat{w}^3 \geq \hat{Z}^1$. Moreover, if additionally $\hat{Z}^1(1 - \hat{w}^3) \geq \hat{w}^2 - \hat{w}^3$ and $\hat{Z}^1(1 - \hat{w}^2) \geq \hat{w}^3 - \hat{w}^2$ we obtain admissible equations for $0 \leq Z^2, Z^3 \leq 1$. We note that the last conditions give $q^1 \geq |\hat{w}^2 - \hat{w}^3|$ due to the fact that $1 - w^1$ is larger than $1 - \hat{w}^2, 1 - \hat{w}^3$.

In this case we have

$$(1 - \hat{w}^2) + q^3 = (1 - \hat{w}^3) + q^2$$

and therefore using $q^1 = q^2 + q^3$ we obtain

$$\rho^2 = \rho^3 .$$

Moreover,

$$(1 - \rho^1 + q^1)(2 - \frac{q^1}{1 - \rho^1 + q^1}) = 2 - (\rho^2 + \rho^3) + q^1$$

gives $\rho^1 = \frac{\rho^2 + \rho^3}{2}$ and therefore the following conditions

$$\rho^1 = \rho^2 = \rho^3, q^1 = q^2 + q^3 .$$

Using $1 - w^1 = \frac{1}{2}(1 - \hat{w}^2 + 1 - \hat{w}^3 + q^1)$ a direct computation gives

$$q^2 = \frac{q^1}{2} - \frac{\hat{w}^2 - \hat{w}^3}{2}$$

$$q^3 = \frac{q^1}{2} + \frac{\hat{w}^2 - \hat{w}^3}{2} . \tag{3.4}$$

That means we have a linear distribution of the outgoing fluxes according to the difference in free space on the outgoing roads.

Finally, we have to discuss situations where the above conditions are not fulfilled.

First we consider the case where still, but $\hat{w}^2 + \hat{w}^3 \leq \hat{Z}^1$. We note that in this case $q^1 \geq |\hat{w}^2 - \hat{w}^3|$ is automatically satisfied, see Figure 3.2. In this case, we consider the interface $\hat{w}^2 + \hat{w}^3 = \hat{Z}^1$, where, $1 - w^1 = 1$. Thus, $w^1 = 0$ and then $\rho^1 = q^1$, which we choose as the first condition in this domain.

Moreover, we assume in this case that the above distribution of fluxes (3.4) is still valid which leads to

$$(1 - \hat{w}^2)Z^2 = \frac{1}{2}(\hat{Z}^1 - (\hat{w}^2 - \hat{w}^3))$$

$$(1 - \hat{w}^3)Z^3 = \frac{1}{2}(\hat{Z}^1 + (\hat{w}^2 - \hat{w}^3)) .$$

We note that the balance of fluxes is still guaranteed for this definition. We obtain directly $\rho^2 = \rho^3$.

Next, we consider the case, where $w^2 \geq w^3$ and $\hat{Z}^1(1-\hat{w}^3) \leq w^2 - w^3$. Considering again the interface to the first case, we have in this case

$$1 - w^1 = 1 - \hat{w}^3$$

and the original equations lead to

$$\begin{aligned} Z^2 &= 0 \\ Z^3 &= \frac{(1 - w^1)\hat{Z}^1}{1 - \hat{w}^3} = \hat{Z}^1 . \end{aligned}$$

This yields

$$q^2 = 0 , \quad q^3 = q^1 .$$

Finally, we consider the case $w^2 \leq w^3$ and $\hat{Z}^1(1 - \hat{w}^2) \leq w^3 - w^2$. This leads to

$$\begin{aligned} 1 - w^1 &= 1 - \hat{w}^2 \\ Z^2 &= \frac{(1 - w^1)\hat{Z}^1}{1 - \hat{w}^2} = \hat{Z}^1 \\ Z^3 &= 0 \end{aligned}$$

and equivalently

$$q^2 = 0 , \quad q^3 = q^1 .$$




Fig. 3.2: Domain of definition for coupling conditions without drivers preference.

3.1.1. Summary. In summary we have the following coupling conditions in characteristic variables distinguishing 4 cases, see Figure 3.2.

Case I: $\hat{Z}^1(1 - \hat{w}^3) \geq \hat{w}^2 - \hat{w}^3$ and $\hat{Z}^1(1 - \hat{w}^2) \geq \hat{w}^3 - \hat{w}^2$ and $\hat{w}^2 + \hat{w}^3 \geq \hat{Z}^1$:

$$\rho^1 = \rho^2 = \rho^3, \quad q^1 = q^2 + q^3 ,$$

Case II: $\hat{w}^2 + \hat{w}^3 \leq \hat{Z}^1$

$$\rho^1 = q^1, \rho^2 = \rho^3, q^1 = q^2 + q^3,$$

Case III: $\hat{Z}^1(1 - \hat{w}^3) \leq \hat{w}^2 - \hat{w}^3$ and $\hat{w}^2 \geq \hat{w}^3$:

$$q^2 = 0, q^3 = q^1, \rho^1 = \rho^3,$$

Case IV: $\hat{Z}^1(1 - \hat{w}^2) \leq \hat{w}^3 - \hat{w}^2$ and $\hat{w}^2 \leq \hat{w}^3$:

$$q^2 = q^1, q^3 = 0, \rho^1 = \rho^2.$$

One observes that the restrictions in the above cases in characteristic variables do lead to straightforward restrictions when writing them in macroscopic variables. Additionally, we have the physical constraints $0 \leq q^1 \leq \rho^1 \leq 1$. Writing the restrictions in macroscopic variables and using the above conditions in the respective cases, one obtains the following. For Case I one obtains with $\rho = \rho^1 = \rho^2 = \rho^3$ that

$$\hat{Z}^1(1 - \hat{w}^3) \geq \hat{w}^2 - \hat{w}^3$$

is equivalent to

$$(q^2 + q^3)(1 - \rho + q^3) \geq (q^3 - q^2)(1 - \rho + q^2 + q^3).$$

This gives

$$(q^2 + q^3)(1 - \rho + q^3) \geq (q^3 - q^2)(1 - \rho + q^2 + q^3)$$

and

$$q^2(2 + q^3 + q^2) \geq 0,$$

which is obviously fulfilled.

Moreover

$$\hat{w}^2 + \hat{w}^3 \geq \hat{Z}^1$$

gives

$$(2\rho - q^1)(1 - w^1) \geq q^1$$

or

$$\begin{aligned} (\rho^1 + w^1)(1 - w^1) &= \rho^1 + w^1 - \rho^1 w^1 - (w^1)^2 \\ &= 2w^1 + q^1 - \rho^1 w^1 - (w^1)^2 = w^1(2 - \rho^1 - w^1) + q^1 \geq q^1. \end{aligned}$$

This is again obvious from the physical bounds.

For Case II with $\rho^1 = q^1, \rho^2 = \rho^3 = \rho$ we have the constraint

$$\hat{w}^2 + \hat{w}^3 \leq \hat{Z}^1.$$

This is equivalent to

$$(2\rho - q^1) \leq \hat{q}^1$$

or

$$\rho \leq q^1 .$$

Case III with $q^2 = 0, q^3 = q^1, \rho^1 = \rho^3 = \rho$ has the constraints $\hat{Z}^1(1 - \hat{w}^3) \leq \hat{w}^2 - \hat{w}^3$ and $\hat{w}^2 \geq \hat{w}^3$. This is equivalent to

$$q^1(1 - \rho + q^1) \leq (1 - \rho + q^1)(\rho^2 - \rho + q^1), \quad \rho^2 \geq \rho - q^1$$

or

$$q^1 \leq \rho^2 - \rho + q^1, \quad \rho^2 - \rho + q^1 \geq 0 ,$$

which gives

$$\rho \leq \rho^2 .$$

Case IV is symmetric to case III.

Thus, the above 4 cases can be rewritten using macroscopic variables:

Case I:

$$\rho^1 = \rho^2 = \rho^3 \geq q^1 ,$$

Case II:

$$\rho^2 = \rho^3 \leq q^1 = \rho^1 ,$$

Case III:

$$q^1 \leq \rho^1 = \rho^3 \leq \rho^2 , \quad q^2 = 0 ,$$

Case IV:

$$q^1 \leq \rho^1 = \rho^2 \leq \rho^3 , \quad q^3 = 0 .$$

In all cases, we have additionally the balance of fluxes $q^1 = q^2 + q^3$.

REMARK 2. *We note that the expression for ρ^1 can be rewritten as*

$$\rho^1 = \max(q^1, \min(\rho^2, \rho^3)) .$$

3.2. Junction with diverging lanes and equal driver preferences. For this configuration several coupling conditions have been proposed for the macroscopic conservation law, see e.g. [12, 28, 17, 24]. These conditions rely on a given preference of the drivers, i.e. it is known a priori what percentage of the arriving cars will take road 2 and which ones road 3. We consider a simplified situation with an equal distribution of the percentage of cars which have a preference for road 2 or 3 respectively. This fixes already two equations at the junction

$$f_1^2 = \frac{f_1^1}{2} \quad \text{and} \quad f_1^3 = \frac{f_1^1}{2} . \quad (3.5)$$

The discussion of the free space on road 1 provides again the missing information. For example, in case the available space on road 2 is larger than on road 3, the free

space available for the drivers is the one on road 3 plus the space occupied by the cars driving towards road 2.

If $1 - \hat{w}^2 \geq 1 - w^3$ or $w^2 \leq w^3$ or $\rho^2 \leq \rho^3$:

$$1 - w^1 = 1 - f_0^1 = 1 - f_0^3 + q^2 = 1 - \hat{w}^3 + q^2 = 1 - \hat{w}^3 + \frac{q^1}{2} .$$

If $1 - \hat{w}^2 \leq 1 - w^3$ or $w^2 \geq w^3$ or $\rho^2 \geq \rho^3$:

$$1 - w^1 = 1 - f_0^1 = 1 - f_0^2 + q^3 = 1 - \hat{w}^2 + q^3 = 1 - \hat{w}^2 + \frac{q^1}{2} . \quad (3.6)$$

These three equations (3.5 - 3.6) form the coupling conditions, if they yield solutions within the physical bounds. Note that the conservation of mass is guaranteed by (3.5).

We consider them again in characteristic variables. This leads for $w^2 \leq w^3$ to

$$\begin{aligned} 1 - w^1 &= 1 - \hat{w}^3 + \frac{\hat{Z}^1}{2}(1 - w^1) \\ (1 - \hat{w}^2)Z^2 &= (1 - w^1)\frac{\hat{Z}^1}{2} \\ (1 - \hat{w}^3)Z^3 &= (1 - w^1)\frac{\hat{Z}^1}{2} \end{aligned}$$

or

$$\begin{aligned} 1 - w^1 &= \frac{1 - \hat{w}^3}{1 - \frac{\hat{Z}^1}{2}} , \\ Z^2 &= \frac{1 - \hat{w}^3}{1 - \hat{w}^2} \frac{\frac{\hat{Z}^1}{2}}{1 - \frac{\hat{Z}^1}{2}} , \quad Z^3 = \frac{\frac{\hat{Z}^1}{2}}{1 - \frac{\hat{Z}^1}{2}} . \end{aligned}$$

This is well defined as long as

$$1 - \hat{w}^3 \leq 1 - \frac{\hat{Z}^1}{2} \quad \text{and} \quad \frac{\hat{Z}^1}{2} \leq 1 - \hat{w}^2$$

or

$$\hat{w}^3 \geq \frac{\hat{Z}^1}{2} \quad \text{and} \quad \hat{w}^2 \leq 1 - \frac{\hat{Z}^1}{2} .$$

For $w^2 \geq w^3$ one has symmetrically

$$\begin{aligned} 1 - w^1 &= \frac{1 - \hat{w}^2}{1 - \frac{\hat{Z}^1}{2}} , \\ Z^2 &= \frac{\frac{\hat{Z}^1}{2}}{1 - \frac{\hat{Z}^1}{2}} , \quad Z^3 = \frac{1 - \hat{w}^2}{1 - \hat{w}^3} \frac{\frac{\hat{Z}^1}{2}}{1 - \frac{\hat{Z}^1}{2}} \end{aligned}$$

These expressions are well defined as long as

$$1 - \hat{w}^2 \leq 1 - \frac{\hat{Z}^1}{2} \quad \text{and} \quad \frac{\hat{Z}^1}{2} \leq 1 - \hat{w}^3$$

or

$$\hat{w}^2 \leq \frac{\hat{Z}^1}{2} \quad \text{and} \quad \hat{w}^3 \leq 1 - \frac{\hat{Z}^1}{2} .$$

To complete the coupling conditions we have to consider the remaining cases $0 \leq w^2, w^3 \leq \frac{\hat{Z}^1}{2}$ and $1 - \frac{\hat{Z}^1}{2} \leq w^2, w^3 \leq 1$ and truncate the coupling conditions in a suitable way. In the first case we use $1 - w^1 = 1$. In the second case the above expression for $1 - w^1$ can be used. This leads to

$$1 - w^1 = \begin{cases} \frac{1 - \hat{w}^3}{1 - \frac{\hat{Z}^1}{2}} , & \hat{w}^3 \geq \frac{\hat{Z}^1}{2}, \hat{w}^2 \leq \hat{w}^3 \\ \frac{1 - \hat{w}^2}{1 - \frac{\hat{Z}^1}{2}} , & \hat{w}^2 \geq \frac{\hat{Z}^1}{2}, \hat{w}^2 \geq \hat{w}^3 \\ 1 , & \hat{w}^2 \leq \frac{\hat{Z}^1}{2}, \hat{w}^3 \leq \frac{\hat{Z}^1}{2} . \end{cases}$$

and the associated Z^2, Z^3 as

$$\hat{Z}^2 = \frac{1 - w^1}{1 - \hat{w}^2} \frac{\hat{Z}^1}{2} , \quad \hat{Z}^3 = \frac{1 - w^1}{1 - \hat{w}^3} \frac{\hat{Z}^1}{2} .$$




Fig. 3.3: Domain of definition for coupling conditions with equal drivers preference.

In macroscopic variables ρ and q we obtain from the definition of $1 - w^1$ the following three cases, see Figure 3.3.

- Case I:** $\hat{w}^2 \leq \frac{\hat{Z}^1}{2}$ and $\hat{w}^3 \leq \frac{\hat{Z}^1}{2}$: $\rho^1 = q^1$,
- Case II:** $\hat{w}^2 \geq \frac{\hat{Z}^1}{2}$ and $\hat{w}^2 \geq \hat{w}^3$: $\rho^1 = \rho^3$,
- Case III:** $\hat{w}^3 \geq \frac{\hat{Z}^1}{2}$ and $\hat{w}^2 \leq \hat{w}^3$: $\rho^1 = \rho^2$.

A short computation shows that this is can be rewritten as

Case I:
$$\rho^2, \rho^3 \leq q^1 = \rho^1 ,$$

Case II:
$$q^1 \leq \rho^1 = \rho^3 \leq \rho^2 ,$$

Case III:

$$q^1 \leq \rho^1 = \rho^2 \leq \rho^3$$

together with the equations for the fluxes

$$q^2 = \frac{q^1}{2} = q^3.$$

REMARK 3. *This can be rewritten as*

$$\rho^1 = \max(q^1, \max(\rho^2, \rho^3)) ,$$

compare Remark 2 for the case without drivers preferences.

4. The layer equations and the half-Riemann problem for the conservation law. In this section we reconsider the kinetic layer equations and their asymptotic states and the half-Riemann problems for the conservation law, see [10] for more details.

4.1. Layer solutions for the kinetic equations.

4.1.1. Left layer. Let the left boundary of the domain be located at $x = x_L$. Starting from equation (2.3) and rescaling space as $y = \frac{x-x_L}{\epsilon}$ and neglecting higher order terms in ϵ we obtain the kinetic layer equations for the left boundary for (ρ_L, q_L) and $y \in [0, \infty)$ as

$$\begin{aligned} \partial_y q_L &= 0 \\ \frac{q_L}{1 - \rho_L} \partial_y \rho_L + (1 - \frac{q_L}{1 - \rho_L}) \partial_y q_L &= -(q_L - F(\rho_L)) . \end{aligned}$$

This yields

$$q_L = C , \quad \partial_y \rho_L = (1 - \rho_L) \frac{F(\rho_L) - C}{C} .$$

For $0 < C < F(\rho^*) = \sigma$, where ρ^* denotes the point where the maximum of F is attained. The above problem has two relevant fix-points

$$\rho_-(C) \leq \rho^* , \quad \rho_+(C) = \tau(\rho_-) \geq \rho^* .$$

Here, $\tau(\rho) \neq \rho$ is defined by $F(\tau(\rho)) = F(\rho)$. The point ρ_- is instable and ρ_+ is stable. The domain of attraction of the stable fixpoint ρ_+ is the interval $(\rho_-, 1)$.

The third fixpoint $\rho = 1$ is not relevant for the further matching procedure, since in the macroscopic limit the maximal density requires $C = 0$. In case $C = 0$ we have the instable fixpoint $\rho_+ = 1$ and the stable fixpoint $\rho_- = 0$ with domain of attraction $[0, 1)$. Further, for $C = F(\rho^*)$ both fixpoints coincide, i.e. $\rho_- = \rho_+ = \rho^*$, and all solutions with initial values above ρ^* converge towards ρ^* , all other solutions diverge.

REMARK 4. *In case of the LWR model with $F(\rho) = \rho(1 - \rho)$ we have with $C < \frac{1}{4}$*

$$\rho_{\pm}(C) = \frac{1}{2}(1 \pm \sqrt{1 - 4C}) .$$

In case $C = \frac{1}{4}$ it holds $\rho_- = \rho_+ = \frac{1}{2}$. Moreover, $\tau(\rho) = 1 - \rho$, as in Figure 4.1.




Fig. 4.1: Fundamental diagram, $F(\rho)$ and ρ_{\mp} .

4.1.2. Right layer. For the right boundary at x_R a similar scaling $y = \frac{x_R - x}{\epsilon}$ gives the layer equations for (ρ_R, q_R) and $y \in [0, \infty)$ as

$$\begin{aligned} q_R &= C \\ -\partial_y \rho_R &= (1 - \rho_R) \frac{F(\rho_R) - C}{C}. \end{aligned}$$

For $0 < C < F(\rho^*)$ the above problem has again two relevant fix points

$$\rho_-(C) \leq \rho^*, \quad \rho_+(C) = \tau(\rho_-) \geq \rho^*.$$

In this case ρ_- is stable, ρ_+ is unstable. The domain of attraction of the stable fixpoint ρ_- is $[0, \rho_+)$.

For $C = F(\rho^*) = \sigma$ we have $\rho_- = \rho_+ = \rho^*$ and all solutions with initial values below ρ^* converge towards ρ^* , all other solutions converge to not admissible states. For $C = 0$ the fixpoint $\rho_+ = 1$ is unstable and $\rho_- = 0$ is a stable fixpoint with domain of attraction $[0, 1)$.

4.1.3. Summary. In summary we have the following cases denoting with U the unstable fixpoints and with S the stable ones. Moreover, we use the notation ρ_K for the values ρ_L^∞ and ρ_R^∞ at infinity of the respective layers and the notation ρ_0 for the respective values at $y = 0$, i.e. $\rho_L(0)$ and $\rho_R(0)$.

Layer Problem at the left boundary.

$$\rho_K = \rho_-(C) \Rightarrow \rho_0 = \rho_-(C), \quad 0 \leq C < \sigma \quad \} \quad (U)$$

$$\left. \begin{aligned} \rho_K = \rho_+(C) &\Rightarrow \rho_0 \in (\rho_-(C), 1), & 0 < C < \sigma \\ \rho_K = \rho^* &\Rightarrow \rho_0 \in [\rho^*, 1), & C = \sigma \\ \rho_K = 1 &\Rightarrow \rho_0 \in (0, 1], & C = 0 \end{aligned} \right\} \quad (S)$$

The Layer Problem at the right boundary.

$$\rho_K = \rho_+(C) \Rightarrow \rho_0 = \rho_+(C), \quad 0 \leq C < \sigma \quad \} \quad (U)$$

$$\left. \begin{aligned} \rho_K = \rho_-(C) &\Rightarrow \rho_0 \in [0, \rho_+(C)), & 0 < C < \sigma \\ \rho_K = \rho^* &\Rightarrow \rho_0 \in [0, \rho^*], & C = \sigma \\ \rho_K = 0 &\Rightarrow \rho_0 \in [0, 1), & C = 0 \end{aligned} \right\} \quad (S)$$

In the following we use for the three cases of the stable fixpoint (S) the notation

$$\rho_K = \rho_+(C) \quad \Rightarrow \quad \rho(0) \in [\rho_-(C), 1], 0 \leq C \leq \sigma$$

for the left boundary and for the right boundary

$$\rho_K = \rho_-(C) \quad \Rightarrow \quad \rho(0) \in [0, \rho_+(C)], 0 \leq C \leq \sigma.$$

4.2. Half-Riemann problems for the limit conservation law. Assuming the conditions above on F the solution to a Riemann problem of the limit conservation law $\partial_t \rho + \partial_x F(\rho) = 0$ is easily obtained. The possible states ρ_K for a given value ρ_B of a half-Riemann problem with ingoing waves (shocks and rarefaction waves) at left and right boundary are summarized in the following:

The half-Riemann Problem at the left boundary.

$$\begin{aligned} \rho_B \leq \rho^* \text{ (RP 1)} & \quad \Rightarrow \quad \rho_K \in [0, \rho^*] \\ \rho_B > \rho^* \text{ (RP 2)} & \quad \Rightarrow \quad \rho_K \in [0, \tau(\rho_B)] \cup \{\rho_B\} \end{aligned}$$

The half-Riemann Problem at the right boundary.

$$\begin{aligned} \rho_B \geq \rho^* \text{ (RP 1)} & \quad \Rightarrow \quad \rho_K \in [\rho^*, 1] \\ \rho_B < \rho^* \text{ (RP 2)} & \quad \Rightarrow \quad \rho_K \in \{\rho_B\} \cup [\tau(\rho_B), 1] \end{aligned}$$

These set will allow waves to emerge from the junction into the domains.

5. Macroscopic coupling conditions: diverging lanes with no driver preferences. For the determination of the coupling conditions for the macroscopic equations we investigate first the kinetic layers at the nodes coupled to each other via the coupling conditions and determine their asymptotic states. Then, we match these results to Riemann solutions of the macroscopic problems on each of the roads.

Assuming the initial states $\rho_B^1, \rho_B^2, \rho_B^3$ on all three roads to be given, we have to determine the new states ρ_K^1, ρ_K^2 and ρ_K^3 at the node. On the one hand ρ_K^1, ρ_K^2 and ρ_K^3 are the asymptotic states of the respective layer problems, on the other hand they are the right (for road 1 and 2) or left (for road 3) states of the half-Riemann problems with $\rho_B^1, \rho_B^2, \rho_B^3$ as the corresponding left (road 1 and 2) or right state (road 3). We have to consider eight different configurations of Riemann problems. For each of them all possible combinations with stable or unstable layer solutions have to be discussed. Not admissible combinations are not listed. The proof of the following theorem is given in section 7. For the discussion of the coupling of the layer solutions we refer to 7.1 and for the matching of layer solutions and half Riemann problems to 7.2. One obtains

THEOREM 5.1. *Starting from the kinetic coupling conditions for drivers without preferences in subsection 3.1 the asymptotic derivation of the coupling conditions for the macroscopic equations gives the following cases using the notation RP1/2-1/2-1/2 for the respective combination of the half Riemann problems.*

Case 1, RP1-1-1 $\rho_B^1 \geq \rho^*, \rho_B^2 \leq \rho^*, \rho_B^3 \leq \rho^*$.

One obtains

$$C^1 = \sigma, C^2 = C^3 = \frac{\sigma}{2}.$$

Case 2, RP1-1-2 $\rho_B^1 \geq \rho^*, \rho_B^2 \leq \rho^*, \rho_B^3 \geq \rho^*$.

This gives for

$$\begin{aligned} 2F(\rho_B^3) &\leq \sigma : C^1 = \sigma, C^3 = F(\rho_B^3) \\ 2F(\rho_B^3) &\geq \sigma : C^1 = \sigma, C^2 = C^3 = \frac{\sigma}{2}. \end{aligned}$$

Case 3, RP1-2-1 $\rho_B^1 \geq \rho^*$, $\rho_B^2 \geq \rho^*$, $\rho_B^3 \leq \rho^*$.

This gives for

$$\begin{aligned} 2F(\rho_B^2) &\leq \sigma : C^1 = \sigma, C^2 = C^3 = \frac{\sigma}{2} \\ 2F(\rho_B^2) &\geq \sigma : C^1 = \sigma, C^2 = F(\rho_B^2). \end{aligned}$$

Case 4, RP2-1-1 $\rho_B^1 \leq \rho^*$, $\rho_B^2 \leq \rho^*$, $\rho_B^3 \leq \rho^*$.

This gives

$$C^1 = F(\rho_B^1) \text{ and } C^2 = C^3 = \frac{F(\rho_B^1)}{2}.$$

Case 5, RP1-2-2 $\rho_B^1 \geq \rho^*$, $\rho_B^2 \geq \rho^*$, $\rho_B^3 \geq \rho^*$.

This gives for

$$\begin{aligned} F(\rho_B^2) + F(\rho_B^3) &\leq \sigma : C^2 = F(\rho_B^2), C^3 = F(\rho_B^3), \\ F(\rho_B^2) &\geq \frac{\sigma}{2}, F(\rho_B^3) \geq \frac{\sigma}{2} : C^1 = \sigma, C^2 = \frac{\sigma}{2}, C^3 = \frac{\sigma}{2}, \\ F(\rho_B^2) + F(\rho_B^3) &\geq \sigma, F(\rho_B^2) \geq \frac{\sigma}{2} : C^1 = \sigma, C^2 = \sigma - F(\rho_B^3), C^3 = F(\rho_B^3), \\ F(\rho_B^2) + F(\rho_B^3) &\geq \sigma, F(\rho_B^3) \geq \frac{\sigma}{2} : C^1 = \sigma, C^2 = F(\rho_B^2), C^3 = \sigma - F(\rho_B^2). \end{aligned}$$

Case 6, RP2-1-2 $\rho_B^1 \leq \rho^*$, $\rho_B^2 \leq \rho^*$, $\rho_B^3 \geq \rho^*$.

This gives for

$$\begin{aligned} F(\rho_B^1) &\leq 2F(\rho_B^3) : C^1 = F(\rho_B^1), C^2 = C^3 = \frac{C^1}{2} = \frac{F(\rho_B^1)}{2}, \\ 2F(\rho_B^3) &\leq F(\rho_B^1) : C^1 = F(\rho_B^1), C^3 = F(\rho_B^3), C^2 = F(\rho_B^1) - F(\rho_B^3). \end{aligned}$$

Case 7, RP2-2-1 $\rho_B^1 \leq \rho^*$, $\rho_B^2 \geq \rho^*$, $\rho_B^3 \leq \rho^*$.

This gives for

$$\begin{aligned} F(\rho_B^1) &\leq 2F(\rho_B^2) : C^1 = F(\rho_B^1), C^2 = C^3 = \frac{C^1}{2} = \frac{F(\rho_B^1)}{2}, \\ 2F(\rho_B^2) &\leq F(\rho_B^1) : C^1 = F(\rho_B^1), C^2 = F(\rho_B^2), C^3 = F(\rho_B^1) - F(\rho_B^2). \end{aligned}$$

Case 8, RP2-2-2 $\rho_B^1 \leq \rho^*$, $\rho_B^2 \geq \rho^*$, $\rho_B^3 \geq \rho^*$.

This gives for

$$\begin{aligned} F(\rho_B^2) + F(\rho_B^3) &\leq F(\rho_B^1) : C^1 = F(\rho_B^2) + F(\rho_B^3), C^2 = F(\rho_B^2), C^3 = F(\rho_B^3), \\ \frac{F(\rho_B^1)}{2} &\leq \min(F(\rho_B^2), F(\rho_B^3)) : C^2 = C^3 = \frac{F(\rho_B^1)}{2}, C^1 = F(\rho_B^1), \\ F(\rho_B^2) + F(\rho_B^3) &\geq F(\rho_B^1) : \\ 2F(\rho_B^3) &\leq F(\rho_B^1) : C^1 = F(\rho_B^1), C^2 = F(\rho_B^1) - F(\rho_B^3), C^3 = F(\rho_B^3), \\ F(\rho_B^2) &\leq 2F(\rho_B^1) : C^1 = F(\rho_B^1), C^2 = F(\rho_B^2), C^3 = F(\rho_B^1) - F(\rho_B^2). \end{aligned}$$

5.1. Supply-Demand formulation of the coupling conditions. We use the supply-demand representation and denote the sets of valid resulting fluxes C^i by Ω^i , compare [12, 28, 16, 17, 23].

The sets Ω^i are for the incoming road $i = 1, 2$

$$\rho_B^i \leq \rho^* \Rightarrow \Omega^i = [0, F(\rho_B^i)] \quad \text{and} \quad \rho_B^i \geq \rho^* \Rightarrow \Omega^i = [0, \sigma] .$$

For the outgoing road $i = 3$

$$\rho_B^i \leq \rho^* \Rightarrow \Omega^i = [0, \sigma] \quad \text{and} \quad \rho_B^i \geq \rho^* \Rightarrow \Omega^i = [0, F(\rho_B^i)] .$$

We define c^i such that $\Omega^i = [0, c^i]$. Rewriting the above conditions using this notation gives the following.

Case 1, RP1-1-1. This is a case with $C^1 = c^1, C^2 = C^3 = \frac{c^1}{2}$.

Case 2, RP1-1-2. We have two cases. $C^1 = c^1, C^2 = C^3 = \frac{c^1}{2}$, if $c^3 \geq \frac{c^1}{2}$ and $C^1 = c^1, C^2 = c^1 - c^3, C^3 = c^3$, if $c^3 \leq \frac{c^1}{2}$.

Case 3, RP1-2-1 We have two cases. $C^1 = c^1, C^2 = c^2, C^3 = c^1 - c^2$, if $c^2 \leq \frac{c^1}{2}$ and $C^1 = c^1, C^2 = C^3 = \frac{c^1}{2}$, if $c^2 \geq \frac{c^1}{2}$.

Case 4, RP2-1-1 This is a case with $C^1 = c^1, C^2 = C^3 = \frac{c^1}{2}$.

Case 5, RP1-2-2 We have four cases:

$$\begin{aligned} & c^2 + c^3 \leq c^1 : C^2 = c^2, C^3 = c^3, C^1 = c^2 + c^3, \\ & c^2 + c^3 \geq c^1, c^2 \geq \frac{c^1}{2}, c^3 \geq \frac{c^1}{2} : C^1 = c^1, C^2 = C^3 = \frac{c^1}{2}, \\ & c^2 + c^3 \geq c^1, c^3, c^2 \geq \frac{c^1}{2}, c^3 \leq \frac{c^1}{2} : C^1 = c^1, C^2 = c^1 - c^3, C^3 = c^3, \\ & c^2 + c^3 \geq c^1, c^3, c^2 \leq \frac{c^1}{2}, c^2 \geq \frac{c^1}{2} : C^1 = c^1, C^2 = c^2, C^3 = c^1 - c^2. \end{aligned}$$

Case 6, RP2-1-2 This case is the same as Case 2.

Case 7, RP2-2-1 This is the same as Case 3.

Case 8, RP2-2-2 This is again Case 5.

Summarizing this leads to only 4 different cases:

Case A:

$$c^2 + c^3 \leq c^1 : C^1 = c^2 + c^3, C^2 = c^2, C^3 = c^3,$$

Case B:

$$c^2 + c^3 \geq c^1, c^1 \leq 2c^2, c^1 \leq 2c^3 : C^1 = c^1, C^2 = C^3 = \frac{c^1}{2},$$

Case C:

$$c^2 + c^3 \geq c^1, c^1 \geq 2c^2, c^1 \leq 2c^3 : C^1 = c^1, C^2 = c^2, C^3 = c^1 - c^2,$$

Case D:

$$c^2 + c^3 \geq c^1, c^1 \leq 2c^2, c^1 \geq 2c^3 : C^1 = c^1, C^2 = c^1 - c^3, C^3 = c^3.$$

The cases B)-D) can be rewritten as

$$C^1 = c^1, C^i = \min \left(c^i, c^1 - \min \left(c^2, c^3, \frac{c^1}{2} \right) \right) \quad i = 2, 3.$$

This yields the limit coupling conditions for the conservation law without drivers preferences at the node.

5.2. Macroscopic coupling conditions: diverging lanes with equal driver preferences. We use the same notation as in the previous section, i.e. we define C_i, c_i and the sets $\Omega_i = [0, c_i]$ as above, depending on whether incoming or outgoing roads are considered. The kinetic conditions for drivers with equal preferences for each of the two outgoing lanes from Section 3.2 lead in the limit to the macroscopic coupling conditions

$$C^1 = \min(c^1, 2c^2, 2c^3)$$

and

$$C^2 = C^3 = \frac{C^1}{2}.$$

We refer to [12, 16, 17] for scalar traffic models on networks with similar coupling conditions. For other conditions treating situations with drivers preferences, we refer to [28, 24]. Such models can be derived from suitable kinetic coupling conditions in a similar way.

6. Numerical results. In this section we show some numerical examples to confirm the analytically derived coupling conditions. In the examples we compare the numerical solution of the kinetic model (2.2) to the solution of the LWR model with the respective coupling conditions. Both equations are approximated with a Godunov scheme and each edge is discretized with 1000 cells. All solutions are shown at $T = 0.9$. The relaxation in the discrete velocity model is $\varepsilon = 0.001$. As initial conditions the densities are chosen constant on the edges for both models equally, Z in the kinetic model is set in equilibrium with the source term.

In the figures the solution on the edges are shown on the left, on the right hand side a zoom close to the junction displays the possible layers.

6.1. Diverging lanes without driver preferences. For the junction without driver preferences we consider the initial conditions $\rho^1 = 0.7$, $\rho^2 = 0.2$ and $\rho^3 = 0.1$. We are in the situation of Case 1 with $\rho_0^1 = 0.25$, $\rho_0^2 = \rho_0^3 = 0.1464$. In the incoming road the maximal flux at the junction generates a rarefaction wave, see Figure 6.1. This flux is distributed onto the outgoing roads, such that a small shock and a small rarefaction wave arise. On the right hand side we observe that a layer forms in the first road but not in the two exiting ones. We observe that the equality $\rho^2 = \rho^3$ is still valid on the macroscopic level. Furthermore we note that in the kinetic model the shock on road 2 is slightly behind the macroscopic one. It has the same speed as the macroscopic shock, but is slightly delayed, since the kinetic model needs a few time steps to establish the correct states at the junction. Such initial layer problems decrease with decreasing ε and increasing numerical resolution.

In the second example with the initial values $\rho^1 = 0.2$, $\rho^2 = 0.4$ and $\rho^3 = 0.6$ only few cars arrive at the junction. As shown in Figure 6.2 these cars are distributed equally onto the outgoing roads. Thus two shock waves form and move to the right. A layer forms only on road 1. In this case we are in the situation of Case 6, subcase 1 with $\rho_0^1 = F(\rho_B^1) = 0.16$ and $\rho_0^2 = \rho_0^3 = \rho_-(F(\rho_B^1)/2) = 0.087$.

In Figure 6.3 the results with the initial conditions $\rho^1 = 0.6$, $\rho^2 = 0.1$ and $\rho^3 = 0.95$ are shown. This is a situation as in Case 2, subcase 1 with $\rho_0^1 = \rho_0^2 = \rho_0^3 = \rho_-(\sigma - F(\rho_B^3)) = 0.2821$. Since the traffic on road 3 is dense only very few cars enter there. Most of the vehicles enter into road 2. In the kinetic solution we observe two layers, one interacting with the rarefaction wave on road 1 and one due to the




Fig. 6.1: Diverging lanes example 1: $\rho^1 = 0.7$, $\rho^2 = 0.2$, $\rho^3 = 0.1$




Fig. 6.2: Diverging lanes example 2: $\rho^1 = 0.2$, $\rho^2 = 0.4$, $\rho^3 = 0.6$

ingoing characteristics on road 3. Note that the kinetic solution is very close to the macroscopic ones although the layer in road 3 has to cover a range of more than 0.6.

6.2. Diverging lanes with driver preferences. For the junction with driver preferences we consider two slightly different examples. First, with the initial conditions $\rho^1 = 0.8$, $\rho^2 = 0.1$ and $\rho^3 = 0.3$ there is enough space in both outgoing roads such that the maximal flow can be established, as shown in Figure 6.4. We have $C^1 = c^1$. As the preferences for the two roads are equal, also the densities on road 2 and 3 are identical.

In Figure 6.5 the solutions corresponding to initial values $\rho^1 = 0.6$, $\rho^2 = 0.9$ and




Fig. 6.3: Diverging lanes example 3: $\rho^1 = 0.6$, $\rho^2 = 0.1$, $\rho^3 = 0.95$




Fig. 6.4: Diverging with driver preferences, example 1: $\rho^1 = 0.8$, $\rho^2 = 0.1$, $\rho^3 = 0.3$

$\rho^3 = 0.0$ are shown. Although road 3 is completely free, only few case can enter, as their way is blocked by cars waiting to enter road 2. In this case $C^1 = 2c^2$. Thus the high density on road 2 is causing a left going shock on the ingoing road. A layer forms only on road 2, since on the other two the macroscopic characteristics move away from the junction.

7. Technical details. In this section we give the proof of Theorem 5.1.

7.1. Coupling the layers (Diverging lanes with no driver preferences).

In the first step of the proof of Theorem 5.1 the combination of the kinetic coupling conditions with the layer equations has to be considered. Each layer can have either




Fig. 6.5: Diverging with driver preferences, example 2: $\rho^1 = 0.6$, $\rho^2 = 0.9$, $\rho^3 = 0.0$

a stable solution (S) or an unstable solution (U). Thus, for three edges we have eight possible combinations, which we denote by U/S-U/S-U/S.

Case 1, U-U-U. We have $\rho^1 = \rho_+(C^1)$, $\rho^2 = \rho_-(C^2)$, $\rho^3 = \rho_-(C^3)$ with $0 \leq C^1, C^2, C^3 < \sigma$. We consider the four different cases for the kinetic coupling conditions from section 3.1.1.

Case I:

$$\begin{aligned} \rho_+(C^1) &= \rho_-(C^2) = \rho_-(C^3) \\ C^1 &= C^2 + C^3. \end{aligned}$$

The first two equalities give $C^1 = C^2 = C^3 = \sigma$. This is not consistent with the range of C^i .

Case II:

$$\begin{aligned} \rho_+(C^1) &= C^1 \geq \rho_-(C^2) = \rho_-(C^3) \\ C^1 &= C^2 + C^3. \end{aligned}$$

The first equality has no solution, since $F(\rho) \leq \rho$ and F strictly concave gives $\sigma < \rho^* = \rho_+(\sigma)$.

Case III:

$$\begin{aligned} C^1 &\leq \rho_+(C^1) = \rho_-(C^3) \leq \rho_-(C^2) \\ C^2 &= 0, C^1 = C^2 + C^3. \end{aligned}$$

The first equality gives $C^1 = C^3 = \sigma$, which is not in the range of the C^1, C^3 .

Case IV:

$$\begin{aligned} C^1 &\leq \rho_+(C^1) = \rho_-(C^2) \leq \rho_-(C^3) \\ C^3 &= 0, C^1 = C^2 + C^3. \end{aligned}$$

The first equality gives $C^1 = C^2 = \sigma$, which is not in the range of C^1, C^2 .

Altogether this combination is not admissible.

Case 2, S-U-U

We have $\rho_0^1 \in [0, \rho_+(C^1))$, $\rho_0^2 = \rho_-(C^2)$, $\rho_0^3 = \rho_-(C^3)$ with $0 \leq C^1 \leq \sigma$, $0 \leq C^2, C^3 < \sigma$.

Case I:

$$\begin{aligned}\rho_0^1 &= \rho_-(C^2) = \rho_-(C^3) \geq C^1 \\ C^1 &= C^2 + C^3.\end{aligned}$$

The equalities give $C^2 = C^3 = \frac{C^1}{2}$. Moreover, $\rho_0^1 \in [0, \rho_+(C^1))$ is obviously consistent with the above conditions. Finally, we have the condition $\rho_-(\frac{C^1}{2}) \geq C^1$.

Case II:

$$\begin{aligned}C^1 &= \rho_0^1 \geq \rho_-(C^2) = \rho_-(C^3) \\ C^1 &= C^2 + C^3.\end{aligned}$$

The equalities give $C^2 = C^3 = \frac{C^1}{2}$. $\rho_0^1 \in [0, \rho_+(C^1))$ is consistent with the conditions. We have finally $C^1 \geq \rho_-(\frac{C^1}{2})$.

Case III:

$$\begin{aligned}C^1 &\leq \rho_0^1 = \rho_-(C^3) \leq \rho_-(C^2) \\ C^2 &= 0, \quad C^1 = C^2 + C^3.\end{aligned}$$

This leads to $0 \geq \rho_-(C^3)$ or $C^3 = 0$ and then $C^1 = 0$.

Case IV:

$$\begin{aligned}C^1 &\leq \rho_0^1 = \rho_-(C^2) \leq \rho_-(C^3) \\ C^3 &= 0, \quad C^1 = C^2 + C^3.\end{aligned}$$

This leads to $0 \geq \rho_-(C^2)$ or $C^2 = 0$ and then $C^1 = 0$.

Case 3, U-S-U

Here it is $\rho^1 = \rho_+(C^1)$, $\rho^2 \in (\rho_-(C^2), 1)$, $\rho^3 = \rho_-(C^3)$ with $0 \leq C^2 \leq \sigma$, $0 \leq C^1, C^3 < \sigma$.

Case I:

$$\begin{aligned}\rho_+(C^1) &= \rho_0^2 = \rho_-(C^3) \geq C^1 \\ C^1 &= C^2 + C^3.\end{aligned}$$

The equalities give $C^1 = C^3 = \sigma$ which is not in the range of C^1, C^3 .

Case II:

$$\begin{aligned}C^1 &= \rho_+(C^1) \geq \rho_0^2 = \rho_-(C^3) \\ C^1 &= C^2 + C^3.\end{aligned}$$

The first equation has no solution.

Case III:

$$\begin{aligned}C^1 &\leq \rho_+(C^1) = \rho_-(C^3) \leq \rho_0^2 \\ C^2 &= 0, \quad C^1 = C^2 + C^3.\end{aligned}$$

This leads to $C^1 = C^3 = \sigma$ which is not in the range of C^1, C^3 .

Case IV:

$$\begin{aligned}C^1 &\leq \rho_+(C^1) = \rho_0^2 \leq \rho_-(C^3) \\ C^3 &= 0, \quad C^1 = C^2 + C^3.\end{aligned}$$

$\rho_0^2 \in (\rho_-(C^2), 1)$ leads to $0 = \rho_-(C^3) \geq \rho_0^2 \geq \rho_-(C^2)$ or $C^2 = 0$ and $C^1 = 0$. This leads to a contradiction to $1 = \rho_+(0) \leq \rho_-(C^3) = 0$.

This case is not admissible.

Case 4, U-U-S

This case is symmetric to Case 3 and not admissible.

Case 5, U-S-S

We have $\rho^1 = \rho_+(C^1)$, $\rho^2 \in (\rho_-(C^2), 1)$, $\rho^3 \in (\rho_-(C^3), 1)$ with $0 \leq C^2, C^3 \leq \sigma$, $0 \leq C^1 < \sigma$.

Case I:

$$\begin{aligned} C^1 &\leq \rho_+(C^1) = \rho_0^2 = \rho_0^3 \\ C^1 &= C^2 + C^3 . \end{aligned}$$

The conditions are consistent with the requirements for ρ_0^2 and ρ_0^3 . We need $0 \leq C^2 + C^3 < \sigma$. One obtains $\rho_+(C^1) = \rho_0^1 = \rho_0^2 = \rho_0^3$.

Case II:

$$\begin{aligned} C^1 &= \rho_+(C^1) \geq \rho_0^2 = \rho_0^3 \\ C^1 &= C^2 + C^3 . \end{aligned}$$

The first equation has no solution.

Case III:

$$\begin{aligned} C^1 &\leq \rho_+(C^1) = \rho_0^3 \leq \rho_0^2 \\ C^2 &= 0 , \quad C^1 = C^2 + C^3 . \end{aligned}$$

We have $0 \leq C^1 = C^3 < \sigma$. We have $\rho_0^2 \geq \rho_+(C^1) = \rho_0^1 = \rho_0^3$.

Case IV:

$$\begin{aligned} C^1 &\leq \rho_+(C^1) = \rho_0^2 \leq \rho_0^3 \\ C^3 &= 0 , \quad C^1 = C^2 + C^3 . \end{aligned}$$

The conditions are consistent with the requirements for ρ_0^2 . We have $0 \leq C^1 = C^2 < \sigma$. We have $\rho_0^3 \geq \rho_+(C^1) = \rho_0^1 = \rho_0^2$.

Case 6, S-U-S

We have $\rho_0^1 \in [0, \rho_+(C^1))$, $\rho_0^2 = \rho_-(C^2)$, $\rho_0^3 \in (\rho_-(C^3), 1)$ with $0 \leq C^1, C^3 \leq \sigma$, $0 \leq C^2 < \sigma$.

Case I:

$$\begin{aligned} C^1 &\leq \rho_0^1 = \rho_-(C^2) = \rho_0^3 \\ C^1 &= C^2 + C^3 . \end{aligned}$$

The range of ρ_0^3 gives $\rho_-(C^2) \geq \rho_-(C^3)$ or $C^2 \geq C^3$ or $C^2 \geq C^1 - C^2$ or $C^1 \leq 2C^2$. In the same way, $C^1 \geq 2C^3$ and therefore $2C^3 \leq C^1 \leq 2C^2$. Moreover, we need $\rho_-(C^2) \geq C^1$.

We have then $\rho_0^1 = \rho_0^2 = \rho_0^3 = \rho_-(C^2)$.

Case II:

$$\begin{aligned} \rho_0^1 &= C^1 \geq \rho_-(C^2) = \rho_0^3 \\ C^1 &= C^2 + C^3 . \end{aligned}$$

The range of ρ_0^3 gives $\rho_-(C^2) \geq \rho_-(C^3)$ or $\rho_-(C^2) \geq \rho_-(C^1 - C^2)$ or $C^1 \leq 2C^2$ and similarly $C^1 \geq 2C^3$. Together $2C^3 \leq C^1 \leq 2C^2$. Moreover, we need $C^1 \geq \rho_-(C^2)$. Then $\rho_0^1 = C^1 \geq \rho_0^2 = \rho_0^3 = \rho_-(C^2)$.

Case III:

$$\begin{aligned} C^1 &\leq \rho_0^1 = \rho_0^3 \leq \rho_-(C^2) \\ C^2 &= 0 , \quad C^1 = C^2 + C^3 . \end{aligned}$$

The ranges of ρ_0^1 and ρ_0^3 lead to $\rho_+(C^1) \geq \rho_-(C^3)$ and $\rho_-(C^3) \leq \rho_-(C^2) = 0$ which gives $C^3 = 0$ and $C^1 = 0$. Moreover, we have $\rho_0^1 = 0$ and then $\rho_0^3 = \rho_0^1 = \rho_0^2 = 0$.

Case IV:

$$\begin{aligned} C^1 &\leq \rho_0^1 = \rho_-(C^2) \leq \rho_0^3 \\ C^3 &= 0 , \quad C^1 = C^2 + C^3 . \end{aligned}$$

We have $C^1 = C^2 < \sigma$. Moreover, $\rho_0^3 \geq \rho_0^2 = \rho_0^1 = \rho_-(C^2) \geq C^1$.

Case 7, S-S-U

The case is symmetric to case 6.

Case 8, S-S-S

We have $\rho_0^1 \in [0, \rho_+(C^1))$, $\rho^2 \in (\rho_-(C^2), 1)$, $\rho_0^3 \in (\rho_-(C^3), 1)$ with $0 \leq C^1, C^2, C^3 \leq \sigma$.

Case I:

$$\begin{aligned} C^1 &\leq \rho_0^1 = \rho_0^2 = \rho_0^3 \\ C^1 &= C^2 + C^3 . \end{aligned}$$

There is no constraint on the C^i except $0 \leq C^2 + C^3 \leq \sigma$.

We have $\max(C^1, \rho_-(C^2), \rho_-(C^3)) \leq \rho_0^i \leq \rho_+(C^1)$

Case II:

$$\begin{aligned} \rho_0^1 &= C^1 \geq \rho_0^2 = \rho_0^3 \\ C^1 &= C^2 + C^3 . \end{aligned}$$

We have $\rho_-(C^2), \rho_-(C^3) \leq C^1$. Then $\rho_0^1 = C^1 \geq \rho_0^2 = \rho_0^3 \geq \max(\rho_-(C^2), \rho_-(C^3))$.

Case III:

$$\begin{aligned} C^1 &\leq \rho_0^1 = \rho_0^3 \leq \rho_0^2 \\ C^2 &= 0, \quad C^1 = C^2 + C^3 . \end{aligned}$$

We have $C^1 = C^3$ and $\rho_-(C^3) \leq \rho_0^3 = \rho_0^1 \leq \min(\rho_0^2, \rho_+(C^1))$.

Case IV:

$$\begin{aligned} C^1 &\leq \rho_0^1 = \rho_0^2 \leq \rho_0^3 \\ C^3 &= 0, \quad C^1 = C^2 + C^3 . \end{aligned}$$

Then $C^1 = C^2$ and $\rho_+(C^1), \rho_0^3 \geq \rho_0^2 = \rho_0^1 \geq \rho_-(C^2)$.

7.1.1. Summary. Altogether we obtain

Case1, U-U-U. This combination is not admissible.

Case 2, S-U-U Only, if $C^2 = C^3 = \frac{C^1}{2}$.

If $\rho_-(\frac{C^1}{2}) > C^1$, then, $\rho_0^2 = \rho_0^3 = \rho_0^1 = \rho_-(\frac{C^1}{2})$.

If $\rho_-(\frac{C^1}{2}) < C^1$, then $\rho_0^1 = C^1$ and $\rho_0^2 = \rho_0^3 = \rho_-(\frac{C^1}{2})$.

Case 3, U-S-U This case is not admissible.

Case 4, U-U-S This case is not admissible.

Case 5, U-S-S If $0 \leq C^2 + C^3 < \sigma$ and $C^2 \neq 0 \neq C^3$ we have $\rho_+(C^1) = \rho_0^1 = \rho_0^2 = \rho_0^3$.

There are two special cases:

1. If $C^2 = 0$ and $0 \leq C^1 = C^3 < \sigma$, then ρ_0^2 is not uniquely determined with

$$\rho_0^2 \geq \rho_0^1 = \rho_0^3 = \rho_+(C^1).$$

2. If $C^3 = 0$, $0 \leq C^1, C^2 < \sigma$ then ρ_0^3 is not uniquely determined with

$$\rho_0^3 \geq \rho_0^1 = \rho_0^2 = \rho_+(C^1).$$

Case 6, S-U-S This case requires $2C^3 \leq C^1 \leq 2C^2$, $C^2 < \sigma$. We have two subcases:

1. If $\rho_-(C^2) \geq C^1$, $C^3 \neq 0$, then $\rho_0^1 = \rho_0^2 = \rho_0^3 = \rho_-(C^2)$. In the special case $C^3 = 0$ we have that ρ_0^3 is not uniquely determined with $\rho_0^3 \geq \rho_-(C^2) = \rho_0^2 = \rho_0^1 \geq C^1$.

2. If $\rho_-(C^2) \leq C^1$ one obtains $\rho_0^1 = C^1$ and $\rho_0^2 = \rho_0^3 = \rho_-(C^2)$.

Case 7, S-S-U The case is symmetric to case 6.

This case requires $2C^2 \leq C^1 \leq 2C^3$, $C^3 < \sigma$. We have two subcases:

1. If $\rho_-(C^3) \geq C^1$, $C^2 \neq 0$, then $\rho_0^1 = \rho_0^2 = \rho_0^3 = \rho_-(C^3)$. In the special case $C^2 = 0$ we have that ρ_0^2 is not uniquely determined with $\rho_0^2 \geq \rho_-(C^3) = \rho_0^3 = \rho_0^1 \geq C^1$.

2. If $\rho_-(C^3) \leq C^1$ one obtains $\rho_0^1 = C^1$ and $\rho_0^2 = \rho_0^3 = \rho_-(C^3)$.

Case 8, S-S-S We need $0 \leq C^2 + C^3 \leq \sigma$. $\rho_0^1, \rho_0^2, \rho_0^3$ are undetermined.

We have two subcases

1. If $C^1 \leq \max(\rho_-(C^2), \rho_-(C^3))$, $C^1 \neq C^2$ and $C^1 \neq C^3$, then
 $\max(\rho_-(C^2), \rho_-(C^3)) \leq \rho_0^3 = \rho_0^2 = \rho_0^1 \leq \rho_+(C^1)$.

We have two special cases:

For $C^1 = C^3$ one has $\rho_-(C^3) \leq \rho_0^3 = \rho_0^1 \leq \min(\rho_+(C^1), \rho_0^2)$.

For $C^1 = C^2$ one has $\rho_-(C^2) \leq \rho_0^2 = \rho_0^1 \leq \min(\rho_+(C^1), \rho_0^3)$.

2. For $\max(\rho_-(C^2), \rho_-(C^3)) \leq C^1$, one has
 $\max(\rho_-(C^2), \rho_-(C^3)) \leq \rho_0^2 = \rho_0^3 \leq \rho_0^1 = C^1$.

7.2. Matching layer solutions and half Riemann problems (Diverging lanes with no driver preferences). Assuming the initial states $\rho_B^1, \rho_B^2, \rho_B^3$ to be given, we have to determine the fluxes C^i and new states ρ_K^i at the node. As mentioned, on the one hand ρ_K^i are the asymptotic states of the respective layer problems and they and the corresponding fluxes C^i have to fulfill the conditions on the single kinetic layers, see section 4.1.3, and on the coupled layers, see section 7.1.1. On the other hand they are the left (road 1 and 2) or right hand (road 3) states of the half Riemann problems with ρ_B^i as corresponding states fulfilling the conditions in 4.2. We consider eight different configurations for the states ρ_B^i corresponding to combinations of different half Riemann problems. For each of them all possible combinations with stable or unstable layer solutions have to be discussed. Not admissible combinations are not listed. We use the notation

$$\rho_-^D(C) = \max(\rho_-(C), D), 0 \leq C, D \leq \sigma.$$

Case 1, RP1-1-1 $\rho_B^1 \geq \rho^*, \rho_B^2 \leq \rho^*, \rho_B^3 \leq \rho^*$. From section 4.1.3 we obtain

$$\begin{aligned} \rho_K^1 \in [\rho^*, 1] : & \quad (U) \text{ or } ((S) \text{ with } C^1 = \sigma) \\ \rho_K^2 \in [0, \rho^*] : & \quad (U) \text{ or } ((S) \text{ with } C^2 = \sigma) \\ \rho_K^3 \in [0, \rho^*] : & \quad (U) \text{ or } ((S) \text{ with } C^3 = \sigma) . \end{aligned}$$

The discussion in section 7.1.1 gives the following 5 different cases:

SUU with $C^1 = \sigma$ and $C^2 = C^3 = \frac{\sigma}{2}$, $\rho_0^1 = \rho_-^{C^1}(\frac{C^1}{2})$, $\rho_0^2 = \rho_0^3 = \rho_-(\frac{C^1}{2})$.

USS with $C^2 = C^3 = \sigma$ which contradicts the balance of fluxes.

SUS with $C^1 = C^3 = \sigma$ which contradicts $2C^3 \leq C^1$ and $C^1 = C^2$.

SSU with $C^1 = C^2 = \sigma$ and a contradiction to $2C^2 \leq C^1$ and $C^1 = C^3$.

SSS with $C^1 = C^2 = C^3 = \sigma$, which gives a contradiction to the balance of fluxes.

This gives

$$C^1 = \sigma \text{ and } C^2 = C^3 = \frac{\sigma}{2}, \rho_0^1 = \rho_-^{\sigma}(\frac{\sigma}{2}), \rho_0^2 = \rho_0^3 = \rho_-(\frac{\sigma}{2}) .$$

Case 2, RP1-1-2 $\rho_B^1 \geq \rho^*, \rho_B^2 \leq \rho^*, \rho_B^3 \geq \rho^*$.

$$\begin{aligned} \rho_K^1 \in [\rho^*, 1] : & \quad (U) \text{ or } ((S) \text{ with } C^1 = \sigma) \\ \rho_K^2 \in [0, \rho^*] : & \quad (U) \text{ or } ((S) \text{ with } C^2 = \sigma) \\ \rho_K^3 \in [0, \tau(\rho_B^3)] \cup \{\rho_B^3\} : & \quad ((U) \text{ with } C^3 \leq F(\rho_B^3)) \text{ or } ((S) \text{ with } C^3 = F(\rho_B^3)) \end{aligned}$$

SUU with $C^1 = \sigma$ and $C^2 = C^3 = \frac{\sigma}{2}$, if $C^3 = \frac{\sigma}{2} \leq F(\rho_B^3)$. Then $\rho_0^1 = \rho_-^{C^1}(\frac{C^1}{2})$, $\rho_0^2 = \rho_0^3 = \rho_-(\frac{C^1}{2})$.

USS with $C^2 = \sigma$. This contradicts $C^2 + C^3 < \sigma$.

SUS with $C^1 = \sigma, C^3 = F(\rho_B^3)$ and $F(\rho_B^3) \leq \frac{\sigma}{2}$. Then $\rho_0^1 = \rho_-^{C^1}(C^2)$, $\rho_0^2 = \rho_0^3 = \rho_-(C^2)$.

SSU with $C^1 = C^2 = \sigma$ and $0 = C^3$ and a contradiction to $C^1 \leq 2C^3$ and $C^1 = C^2 < \sigma$.

SSS with $C^1 = C^2 = \sigma, C^3 = F(\rho_B^3) = 0$. This is only possible, if $\rho_B^3 = 1$. Then $\rho_0^1 = \rho_0^2 = \rho_0^3 = \rho^*$.

This gives for

$$\begin{aligned} F(\rho_B^3) &\leq \frac{\sigma}{2} : C^1 = \sigma, C^3 = F(\rho_B^3), \\ \rho_0^1 &= \rho_-^\sigma(\sigma - F(\rho_B^3)), \rho_0^2 = \rho_0^3 = \rho_-(\sigma - F(\rho_B^3)) \\ \frac{\sigma}{2} &\leq F(\rho_B^3) : C^1 = \sigma, C^2 = C^3 = \frac{\sigma}{2}, \rho_0^1 = \rho_-^\sigma(\frac{\sigma}{2}), \rho_0^2 = \rho_0^3 = \rho_-(\frac{\sigma}{2}). \end{aligned}$$

Case 3, RP1-2-1 $\rho_B^1 \geq \rho^*, \rho_B^2 \geq \rho^*, \rho_B^3 \leq \rho^*$. Symmetric to Case 2.

$$\begin{aligned} \frac{\sigma}{2} &\geq F(\rho_B^2) : C^1 = \sigma, C^2 = F(\rho_B^2), \\ \rho_0^1 &= \rho_-^\sigma(\sigma - F(\rho_B^2)), \rho_0^2 = \rho_0^3 = \rho_-(\sigma - F(\rho_B^2)) \\ \frac{\sigma}{2} &\leq F(\rho_B^2) : C^1 = \sigma, C^2 = C^3 = \frac{\sigma}{2}, \rho_0^1 = \rho_-^\sigma(\frac{\sigma}{2}), \rho_0^2 = \rho_0^3 = \rho_-(\frac{\sigma}{2}). \end{aligned}$$

Case 4, RP2-1-1 $\rho_B^1 \leq \rho^*, \rho_B^2 \leq \rho^*, \rho_B^3 \leq \rho^*$.

$$\begin{aligned} \rho_K^1 &\in [1 - \rho_B^1, 1] \cup \{\rho_B^1\} : ((U) \text{ with } C^1 \leq F(\rho_B^1)) \text{ or } ((S) \text{ with } C^1 = F(\rho_B^1)) \\ \rho_K^2 &\in [0, \rho^*] : (U) \text{ or } ((S) \text{ with } C^2 = \sigma) \\ \rho_K^3 &\in [0, 1/2] : (U) \text{ or } ((S) \text{ with } C^3 = \sigma) \end{aligned}$$

SUU with $C^1 = F(\rho_B^1)$ and $C^2 = C^3 = \frac{F(\rho_B^1)}{2}$. Moreover, $\rho_0^1 = \rho_-^{F(\rho_B^1)}(\frac{F(\rho_B^1)}{2})$, $\rho_0^2 = \rho_0^3 = \rho_-(\frac{F(\rho_B^1)}{2})$.

USS with $C^2 = C^3 = \sigma$ and a contradiction to the balance of fluxes.

SUS with $C^1 = F(\rho_B^1), C^3 = \sigma$. $2C^3 \leq C^1$ gives a contradiction.

SSU with $C^1 = F(\rho_B^1)$ and $C^2 = \sigma$. $2C^2 \leq C^1$ gives a contradiction.

SSS with $C^1 = F(\rho_B^1), C^2 = C^3 = \sigma$ and a contradiction to the balance of fluxes.

This gives altogether

$$C^2 = C^3 = \frac{C^1}{2} = \frac{F(\rho_B^1)}{2}, \quad \rho_0^1 = \rho_-^{F(\rho_B^1)}(\frac{F(\rho_B^1)}{2}), \quad \rho_0^2 = \rho_0^3 = \rho_-(\frac{F(\rho_B^1)}{2}).$$

Case 5, RP1-2-2 $\rho_B^1 \geq \rho^*, \rho_B^2 \geq \rho^*, \rho_B^3 \geq \rho^*$.

$$\begin{aligned} \rho_K^1 &\in [\rho^*, 1] : (U) \text{ or } ((S) \text{ with } C^1 = \sigma) \\ \rho_K^2 &\in [0, 1 - \rho_B^2] \cup \{\rho_B^2\} : ((U) \text{ with } C^2 \leq F(\rho_B^2)) \text{ or } ((S) \text{ with } C^2 = F(\rho_B^2)) \\ \rho_K^3 &\in [0, 1 - \rho_B^3] \cup \{\rho_B^3\} : ((U) \text{ with } C^3 \leq F(\rho_B^3)) \text{ or } ((S) \text{ with } C^3 = F(\rho_B^3)) \end{aligned}$$

SUU with $C^1 = \sigma, C^2 \leq F(\rho_B^2)$ and $C^3 \leq F(\rho_B^3)$. With $C^2 = C^3 = \frac{C^1}{2}$ one obtains $F(\rho_B^2) + F(\rho_B^3) \geq \sigma$ and $F(\rho_B^2) \geq \frac{\sigma}{2}, F(\rho_B^3) \geq \frac{\sigma}{2}$. We have $\rho_0^1 = \rho_-^\sigma(\frac{\sigma}{2}), \rho_0^2 = \rho_0^3 = \rho_-(\frac{\sigma}{2})$.

USS with $C^2 = F(\rho_B^2), C^3 = F(\rho_B^3)$. With $C^2 + C^3 \leq \sigma$ or $F(\rho_B^2) + F(\rho_B^3) \leq \sigma$, $\rho_0^1 = \rho_0^2 = \rho_0^3 = \rho_+(F(\rho_B^2) + F(\rho_B^3))$

- SUS** with $C^1 = \sigma, C^2 \leq F(\rho_B^2), C^3 = F(\rho_B^3)$. Then $2C^3 \leq C^1$ gives $F(\rho_B^3) \leq \frac{\sigma}{2}$. Moreover, $F(\rho_B^2) + F(\rho_B^3) \geq \sigma$. We have $\rho_0^1 = \rho_-^\sigma(\sigma - F(\rho_B^3)), \rho_0^2 = \rho_0^3 = \rho_-(\sigma - F(\rho_B^3))$
- SSU** with $C^1 = \sigma$ and $C^2 = F(\rho_B^2), C^3 \leq F(\rho_B^3)$. $2C^2 \leq C^1$ gives $F(\rho_B^2) \leq \frac{\sigma}{2}$. Moreover, $F(\rho_B^2) + F(\rho_B^3) \geq \sigma$. $\rho_0^1 = \rho_-^\sigma(\sigma - F(\rho_B^2)), \rho_0^2 = \rho_0^3 = \rho_-(\sigma - F(\rho_B^2))$
- SSS** with $C^1 = \sigma$ and $C^2 = F(\rho_B^2), C^3 = F(\rho_B^3)$. This is only possible, if $F(\rho_B^2) + F(\rho_B^3) = \sigma$. We have $\max(\rho_-(C^2), \rho_-(C^3)) \leq \rho_0^2 = \rho_0^3 = \rho_0^1 \leq \rho_+(\sigma) = \rho^*$ for $\max(\rho_-(C^2), \rho_-(C^3)) \geq \sigma$ or $\max(\rho_-(C^2), \rho_-(C^3)) \leq \rho_0^2 = \rho_0^3 \leq \rho_0^1 = \sigma$ for $\max(\rho_-(C^2), \rho_-(C^3)) \leq \sigma$.

This gives altogether for

$$\begin{aligned}
& F(\rho_B^2) + F(\rho_B^3) \leq \sigma : C^2 = F(\rho_B^2), C^3 = F(\rho_B^3) , \\
& \quad \rho_0^1 = \rho_0^2 = \rho_0^3 = \rho_+(F(\rho_B^2) + F(\rho_B^3)) \\
& F(\rho_B^2) \geq \frac{\sigma}{2}, F(\rho_B^3) \geq \frac{\sigma}{2} : C^1 = \sigma, C^2 = \frac{\sigma}{2}, C^3 = \frac{\sigma}{2} , \\
& \quad \rho_0^1 = \rho_-^\sigma(\frac{\sigma}{2}), \rho_0^2 = \rho_0^3 = \rho_-(\frac{\sigma}{2}) , \\
& F(\rho_B^2) + F(\rho_B^3) \geq \sigma, F(\rho_B^3) \leq \frac{\sigma}{2} : C^1 = \sigma, C^2 = \sigma - F(\rho_B^3), C^3 = F(\rho_B^3) , \\
& \quad \rho_0^1 = \rho_-^\sigma(\sigma - F(\rho_B^3)), \rho_0^2 = \rho_0^3 = \rho_-(\sigma - F(\rho_B^3)) , \\
& F(\rho_B^2) + F(\rho_B^3) \geq \sigma, F(\rho_B^2) \leq \frac{\sigma}{2} : C^1 = \sigma, C^2 = F(\rho_B^2), C^3 = \sigma - F(\rho_B^2) , \\
& \quad \rho_0^1 = \rho_-^\sigma(\sigma - F(\rho_B^2)), \rho_0^2 = \rho_0^3 = \rho_-(\sigma - F(\rho_B^2)) .
\end{aligned}$$

REMARK 5. We note that at the interfaces between the different conditions we obtain values for the ρ_0^i which correspond to the range of values for the ρ_0^i -values in case (SSS).

Case 6, RP2-1-2 $\rho_B^1 \leq \rho^*, \rho_B^2 \leq \rho^*, \rho_B^3 \geq \rho^*$.

$$\begin{aligned}
\rho_K^1 & \in [1 - \rho_B^1, 1] \cup \{\rho_B^1\} : ((U) \text{ with } C^1 \leq F(\rho_B^1)) \text{ or } ((S) \text{ with } C^1 = F(\rho_B^1)) \\
\rho_K^2 & \in [0, \rho^*] : (U) \text{ or } ((S) \text{ with } C^2 = \sigma) \\
\rho_K^3 & \in [0, 1 - \rho_B^3] \cup \{\rho_B^3\} : ((U) \text{ with } C^3 \leq F(\rho_B^3)) \text{ or } ((S) \text{ with } C^3 = F(\rho_B^3))
\end{aligned}$$

- SUU** with $C^1 = F(\rho_B^1), C^3 \leq F(\rho_B^3)$. $C^2 = C^3 = \frac{C^1}{2} = \frac{F(\rho_B^1)}{2}$ leads to $F(\rho_B^1) \leq 2F(\rho_B^3)$, $\rho_0^1 = \rho_-^{F(\rho_B^1)}(\frac{F(\rho_B^1)}{2}), \rho_0^2 = \rho_0^3 = \rho_-(\frac{F(\rho_B^1)}{2})$.
- USS** with $C^1 = F(\rho_B^1), C^2 = \sigma, C^3 = F(\rho_B^3) = 0$ contradicts $C^2 < \sigma$.
- SUS** with $C^1 = F(\rho_B^1), C^3 = F(\rho_B^3)$. $2C^3 \leq C^1$ gives $2F(\rho_B^3) \leq F(\rho_B^1)$. $\rho_0^1 = \rho_-^{F(\rho_B^1)}(F(\rho_B^1) - F(\rho_B^3)), \rho_0^2 = \rho_0^3 = \rho_-(F(\rho_B^1) - F(\rho_B^3))$. In the special case $C^3 = 0$ we have $\rho_0^3 \geq \rho_-(F(\rho_B^1) - F(\rho_B^3)) = \rho_0^1 = \rho_0^2$.
- SSU** with $C^1 = F(\rho_B^1)$ and $C^2 = \sigma, C^3 \leq F(\rho_B^3)$. This requires $C^3 = 0$ which contradicts $C^2 \leq C^3$.
- SSS** with $C^1 = F(\rho_B^1)$ and $C^2 = \sigma, C^3 = F(\rho_B^3)$. Only possible if $C^1 = \sigma, C^3 = 0$. $\rho_0^1 = \rho_0^2 = \rho^* \leq \rho_0^3$.

This gives altogether for $F(\rho_B^3) > 0$ and

$$\begin{aligned} F(\rho_B^1) \leq 2F(\rho_B^3) : C^1 &= F(\rho_B^1), C^2 = C^3 = \frac{C^1}{2} = \frac{F(\rho_B^1)}{2}, \\ \rho_0^1 &= \rho_-^{F(\rho_B^1)}\left(\frac{F(\rho_B^1)}{2}\right), \rho_0^2 = \rho_0^3 = \rho_- \left(\frac{F(\rho_B^1)}{2}\right), \\ 2F(\rho_B^3) \leq F(\rho_B^1) : C^1 &= F(\rho_B^1), C^3 = F(\rho_B^3), C^2 = F(\rho_B^1) - F(\rho_B^3), \\ \rho_0^1 &= \rho_-^{F(\rho_B^1)}(F(\rho_B^1) - F(\rho_B^3)), \rho_0^2 = \rho_0^3 = \rho_-(F(\rho_B^1) - F(\rho_B^3)). \end{aligned}$$

In the special case $F(\rho_B^3) = 0$ the value of ρ_0^3 is not uniquely determined.

Case 7, RP2-2-1 $\rho_B^1 \leq \rho^*, \rho_B^2 \geq \rho^*, \rho_B^3 \leq \rho^*$. Symmetric to Case 6. For $F(\rho_B^2) > 0$ and

$$\begin{aligned} F(\rho_B^1) \leq 2F(\rho_B^2) : C^1 &= F(\rho_B^1), C^2 = C^3 = \frac{C^1}{2} = \frac{F(\rho_B^1)}{2}. \\ \rho_0^1 &= \rho_-^{F(\rho_B^1)}\left(\frac{F(\rho_B^1)}{2}\right), \rho_0^2 = \rho_0^3 = \rho_- \left(\frac{F(\rho_B^1)}{2}\right). \\ 2F(\rho_B^2) \leq F(\rho_B^1) : C^1 &= F(\rho_B^1), C^2 = F(\rho_B^2), C^3 = F(\rho_B^1) - F(\rho_B^2). \\ \rho_0^1 &= \rho_-^{F(\rho_B^1)}(F(\rho_B^1) - F(\rho_B^2)), \rho_0^2 = \rho_0^3 = \rho_-(F(\rho_B^1) - F(\rho_B^2)). \end{aligned}$$

In the special case $F(\rho_B^2) = 0$ the value of ρ_0^2 is not uniquely determined.

Case 8, RP2-2-2 $\rho_B^1 \leq \rho^*, \rho_B^2 \geq \rho^*, \rho_B^3 \geq \rho^*$.

$$\begin{aligned} \rho_K^1 &\in [1 - \rho_B^1, 1] \cup \{\rho_B^1\} : ((U) \text{ with } C^1 \leq F(\rho_B^1)) \text{ or } ((S) \text{ with } C^1 = F(\rho_B^1)) \\ \rho_K^2 &\in [0, 1 - \rho_B^2] \cup \{\rho_B^2\} : ((U) \text{ with } C^2 \leq F(\rho_B^2)) \text{ or } ((S) \text{ with } C^2 = F(\rho_B^2)) \\ \rho_K^3 &\in [0, 1 - \rho_B^3] \cup \{\rho_B^3\} : ((U) \text{ with } C^3 \leq F(\rho_B^3)) \text{ or } ((S) \text{ with } C^3 = F(\rho_B^3)) \end{aligned}$$

SUU with $C^1 = F(\rho_B^1)$, $C^2 \leq F(\rho_B^2)$. $C^3 \leq F(\rho_B^3)$. $C^2 = C^3 = \frac{C^1}{2}$ gives $C^2 = C^3 = \frac{F(\rho_B^1)}{2}$. We need $F(\rho_B^1) \leq 2F(\rho_B^2), F(\rho_B^1) \leq 2F(\rho_B^3)$. $\rho_0^1 = \rho_-^{F(\rho_B^1)}\left(\frac{F(\rho_B^1)}{2}\right), \rho_0^2 = \rho_0^3 = \rho_- \left(\frac{F(\rho_B^1)}{2}\right)$.

USS with $C^1 \leq F(\rho_B^1), C^2 = F(\rho_B^2), C^3 = F(\rho_B^3)$. With $C^2 + C^3 \leq \sigma$ we have $F(\rho_B^2) + F(\rho_B^3) \leq \sigma$. $\rho_0^1 = \rho_+(F(\rho_B^1)) = \rho_0^2 = \rho_0^3$.

SUS with $C^1 = F(\rho_B^1), C^2 \leq F(\rho_B^2), C^3 = F(\rho_B^3)$. $2C^3 \leq C^1$ gives $2F(\rho_B^3) \leq F(\rho_B^1)$ and $F(\rho_B^3) - F(\rho_B^1) \leq F(\rho_B^2)$ or $F(\rho_B^1) + F(\rho_B^2) \geq F(\rho_B^3)$. $\rho_0^1 = \rho_-^{F(\rho_B^1)}(F(\rho_B^2)), \rho_0^2 = \rho_0^3 = \rho_-(F(\rho_B^2))$.

SSU with $C^1 = F(\rho_B^1)$ and $C^2 = F(\rho_B^2), C^3 \leq F(\rho_B^3)$. $2C^2 \leq C^1$ gives $2F(\rho_B^2) \leq F(\rho_B^1)$. $\rho_0^1 = \rho_-^{F(\rho_B^1)}(F(\rho_B^3)), \rho_0^2 = \rho_0^3 = \rho_-(F(\rho_B^3))$.

SSS with $C^1 = F(\rho_B^1)$ and $C^2 = F(\rho_B^2), C^3 = F(\rho_B^3)$. Only possible if $F(\rho_B^1) = F(\rho_B^2) + F(\rho_B^3)$. We have $F(\rho_B^2) + F(\rho_B^3) \leq \max(\rho_-(F(\rho_B^2)), \rho_-(F(\rho_B^3))) \leq \rho_0^2 = \rho_0^3 = \rho_0^1 \leq \rho_+(F(\rho_B^2) + F(\rho_B^3))$ or $\max(\rho_-(F(\rho_B^2)), \rho_-(F(\rho_B^3))) \leq \rho_0^2 = \rho_0^3 \leq \rho_0^1 = F(\rho_B^2) + F(\rho_B^3)$.

Additionally, there are again special cases with $F(\rho_B^2) = 0$ or $F(\rho_B^3) = 0$.

This gives altogether for $F(\rho_B^2) > 0$ and $F(\rho_B^3) > 0$

$$\begin{aligned}
F(\rho_B^2) + F(\rho_B^3) &\leq F(\rho_B^1) : C^1 = F(\rho_B^2) + F(\rho_B^3), C^2 = F(\rho_B^2), \\
C^3 &= F(\rho_B^3), \rho_0^1 = \rho_+(F(\rho_B^1)) = \rho_0^2 = \rho_0^3, \\
F(\rho_B^1) &\leq 2 \min(F(\rho_B^2), F(\rho_B^3)) : C^2 = C^3 = \frac{F(\rho_B^1)}{2}, C^1 = F(\rho_B^1), \\
\rho_0^1 &= \rho_-^{F(\rho_B^1)}\left(\frac{F(\rho_B^1)}{2}\right), \rho_0^2 = \rho_0^3 = \rho_- \left(\frac{F(\rho_B^1)}{2}\right), \\
F(\rho_B^2) + F(\rho_B^3) &\geq F(\rho_B^1) : \\
2F(\rho_B^3) &\leq F(\rho_B^1) : C^1 = F(\rho_B^1), C^2 = F(\rho_B^1) - F(\rho_B^3), C^3 = F(\rho_B^3), \\
\rho_0^1 &= \rho_-^{F(\rho_B^1)}(F(\rho_B^2)), \rho_0^2 = \rho_0^3 = \rho_-(F(\rho_B^2)), \\
2F(\rho_B^2) &\leq F(\rho_B^1) : C^1 = F(\rho_B^1), C^2 = F(\rho_B^2), C^3 = F(\rho_B^1) - F(\rho_B^2), \\
\rho_0^1 &= \rho_-^{F(\rho_B^1)}(F(\rho_B^3)), \rho_0^2 = \rho_0^3 = \rho_-(F(\rho_B^3)).
\end{aligned}$$

REMARK 6. We note that at the interfaces between the different conditions we obtain values for the ρ_0^i which correspond to the range of values for the ρ_0^i -values in case (SSS).

8. Conclusions. We have introduced coupling conditions for junctions with diverging lanes for a kinetic two velocity traffic model, which is used as a relaxation model for scalar traffic flow equations. From these coupling conditions we have derived, via asymptotic analysis of the spatial layers at the nodes and a detailed investigation of the associated Riemann problems, coupling conditions for classical scalar macroscopic traffic models. The derivation shows that a classical condition for a non-linear scalar conservation law can be interpreted on the kinetic level as a combination of the balance of fluxes and a suitably modified equality of densities on all roads. This research is a continuation of the work in [10], where the case of merging lanes has been treated.

REFERENCES

- [1] A. Aw and M. Rascle, *Resurrection of second order models of traffic flow?*, SIAM J. Appl. Math., 60, 916–938, 2000.
- [2] A. Aw, A. Klar, T. Materne, M. Rascle, *Derivation of continuum flow traffic models from microscopic Follow the leader models*, SIAM J. Appl. Math. 63 (1), 259-278, 2002
- [3] D. Aregba-Driollet, V. Milisic, *Kinetic approximation of a boundary value problem for conservation laws*, Numer. Math. 97, 595-633, 2004
- [4] C. Bardos, R. Santos, and R. Sentis, *Diffusion approximation and computation of the critical size*, Trans. Amer. Math. Soc. 284, 2, 617-649, 1984
- [5] A. Bensoussan, J.L. Lions, and G.C. Papanicolaou, *Boundary-layers and homogenization of transport processes*, J. Publ. RIMS Kyoto Univ. 15, 53-157, 1979
- [6] F. Berthelin, P. Degond, V. Le Blanc, S. Moutari, J. Royer, M. Rascle, *A Traffic-Flow Model with Constraints for the Modeling of Traffic Jams*, Mathematical Models and Methods in Applied Sciences 18, 1269-1298, 2008
- [7] R. Borsche, A. Klar, *A nonlinear discrete velocity relaxation model for traffic flow*, SIAM J. Appl. Math. 78, 5, 2891-2917, 2018
- [8] R. Borsche, A. Klar, *Kinetic layers and coupling conditions for scalar equations on networks*, Nonlinearity, 31, 7, 3512-3541, 2018
- [9] R. Borsche, A. Klar, *Kinetic layers and coupling conditions for macroscopic equations on networks I: The wave equation*, SIAM J. Sci. Comput. 40, 3, A1784-A1808, 2018.

- [10] R. Borsche, A. Klar, *A kinetic traffic network model and its macroscopic limit: merging lanes*, arxiv <https://arxiv.org/abs/2002.05995>
- [11] R. Borsche, A. Klar, J. Kall, T.N.H. Pham, *Kinetic and related macroscopic models for chemotaxis on networks*, M3AS, 26, No. 6, 1219-1242, 2016
- [12] G.M. Coclite, M. Garavello, B. Piccoli, *Traffic flow on a road network*, SIAM J. Math. Anal. 36, 6, 1862-1886, 2005.
- [13] S. Cacace, F. Camilli, R. De Maio, A. Tosin, *A measure theoretic approach to traffic flow optimisation on networks*, European J. Appl. Math., 30, 6, 1187-1209, 2019.
- [14] R.M. Colombo, M. Garavello, *On the Cauchy problem for the p-system at a junction*, SIAM J. Math. Anal., 39, 1456-1471 2008.
- [15] F. Coron, F. Golse, C. Sulem, *A Classification of Well-posed Kinetic Layer Problems*, CPAM, Vol. 41, 409, 1988
- [16] C. F. Daganzo, *A behavioral theory of multi-lane traffic flow part I: Long homogeneous freeway sections*, Trans. Res. B, 36 (2002), pp. 131-158
- [17] C. F. Daganzo, *A behavioral theory of multi-lane traffic flow part II: Merges and the onset of congestion*, Trans. Res. B, 36 (2002), pp. 159-169.
- [18] M. Garavello, *A review of conservation laws on networks* NHM 5, 3, 565 - 581, 2010
- [19] M. Garavello, B. Piccoli, *Traffic flow on networks*, AIMS Series on Applied Mathematics, 1, American Institute of Mathematical Sciences (AIMS), Springfield, 2006.
- [20] F. Golse, *Analysis of the boundary layer equation in the kinetic theory of gases*, Bull. Inst. Math. Acad. Sin. 3, 1, 211-242, 2008.
- [21] D. Helbing, *Gas-kinetic derivation of Navier-Stokes-like traffic equation*, Physical Review E, 53 (1996), pp. 2366-2381.
- [22] M. Herty and S. Moutari, *A macro-kinetic hybrid model for traffic flow on road networks*, Comput. Methods Appl. Math., 9, 3, 238-252, 2009.
- [23] M. Herty, M. Rascole, *Coupling conditions for a class of second order models for traffic flow*, SIAM Math. Anal. 38, 2, 595-616, 2006.
- [24] M. Herty and A. Klar, *Modeling, simulation, and optimization of traffic flow networks*, SIAM J. Sci. Comput., 25 (2003), pp. 1066-1087.
- [25] M. Herty, G. Puppo, S. Roncoroni, G. Visconti, *The BGK approximation of kinetic models for traffic*, Kinetic & Related Models, 13, 279, 2020.
- [26] H. Holden, N.H. Risebro, *A mathematical model of traffic flow on a network of unidirectional roads*, SIAM J. Math. Anal. 26, 4, 999-1017, 1995.
- [27] A. Klar and R. Wegener, *Enskog-like kinetic models for vehicular traffic*, J. Stat. Phys., 87, 91-114, 1997.
- [28] J. P. Lebacque, *Les modeles macroscopiques du trafic*, Annales des Ponts, 67 (1993), pp. 2845.
- [29] J.-G. Liu, Z. Xin, *Boundary-layer behavior in the fluid-dynamic limit for a nonlinear model Boltzmann Equation*, Arch. Rational Mech. Anal. 135, 61-105, 1996.
- [30] A. Nouri, A. Omrane, J.P. Vila, *Boundary conditions for scalar conservation laws from a kinetic point of view*, J. Statist. Phys., 94(5-6), 779-804, 1999.
- [31] G. Puppo, M. Semplice, A. Tosin, G. Visconti, *Kinetic models for traffic flow resulting in a reduced space of microscopic velocities*, Kinet. Relat. Models 10(3), 823-854, 2017.
- [32] G. Puppo, M. Semplice, A. Tosin, G. Visconti, *Analysis of multi-population kinetic model for traffic flow*, Commun. Math. Sci. 15(2), 379-412, 2017.
- [33] S. Ukai, T. Yang, and S.-H. Yu, *Nonlinear boundary layers of the Boltzmann equation. I. Existence*, Comm. Math. Phys. 236, 3, 373-393, 2003
- [34] W.-C. Wang, Z. Xin, *Asymptotic limit of initial boundary value problems for conservation laws with relaxational extensions*, Communications on Pure and Applied Mathematics, 51, 5 505-535, 1998.
- [35] W.-Q. Xu, *Boundary conditions and boundary layers for a multi-dimensional relaxation model*, Journal of Differential Equations 197, 1, 10, 85-117, 2004.
- [36] W.-A. Yong, *Boundary conditions for hyperbolic systems with stiff relaxation*, Indiana University Mathematics Journal 48, 1, 115-137, 1999.