

Photon-instanton collider implemented by a superconducting circuit

Amir Burshtein,¹ Roman Kuzmin,² Vladimir E. Manucharyan,² and Moshe Goldstein¹

¹*Raymond and Beverly Sackler School of Physics and Astronomy, Tel Aviv University, Tel Aviv 6997801, Israel*

²*Department of Physics, University of Maryland, College Park, MD 20742, USA*

Instantons, spacetime-localized quantum field tunneling events, are ubiquitous in correlated condensed matter and high energy systems. However, their direct observation through collisions with conventional particles has not been considered possible. We show how recent advances in circuit quantum electrodynamics, specifically, the realization of galvanic coupling of a transmon qubit to a high-impedance transmission line, allows the observation of inelastic collisions of single microwave photons with instantons (phase slips). We develop a formalism for calculating the photon-instanton cross section, which should be useful in other quantum field theoretical contexts. In particular, we show that the inelastic scattering probability can significantly exceed the effect of conventional Josephson quartic anharmonicity, and reach order-unity values.

Introduction.— Instantons are time-localized solutions to a system’s imaginary time equations of motion, describing quantum tunneling events. They typically bridge between symmetry-related configurations and carry nontrivial topological indexes [1]. Instantons play important roles in many areas of physics, ranging from single-particle quantum-mechanical tunneling [1], through transport in low dimensional superconductors and superfluids (where they are also known as “phase slips”, and can be thought of as vortices crossing the system) [2–9], to determining the phase diagram [10] and breaking of classical conservation laws [11, 12] in gauge theories. Most of these studies concern thermodynamic or transport properties. A more direct way to probe such short-lived excitations would be through resonances they may induce in the scattering cross sections or decay rates of other more stable particles with which they interact. However, such questions received much less attention, in large part due to lack of relevant experiments.

Advances in the fabrication and control of superconducting circuits allow monitoring of the dynamics of single microwave photons. For example, recent experiments have exposed unusual relaxation dynamics in a uniform Josephson junction array, in which phase slips play an important role [13]. However, their interpretation is complicated due to the presence of disorder and offset charge fluctuations [14–16]. It has recently been realized theoretically [17–27] that controllable quantum simulation of many-body physics may be easier to achieve in “quantum impurity” setups, leading to initial experiments [28–32]. We thus study a single flux-tunable small Josephson junction in the regime where the Josephson energy still dominates (transmon qubit [33]), galvanically coupled to an array of large junctions. The array acts as a transmission line allowing microwave photons to controllably scatter off the small junction [30]. The large Josephson inductance makes the line wave impedance of the order of the resistance quantum, hence the array screens the effects of unwanted offset charges on the transmon without completely suppressing phase slips there. From a broader perspective, the large impedance amounts to an effective fine-structure constant of order unity [34],




FIG. 1. The studied system: (a) The full circuit; (b) A simplified version. See the text for details.

ushering in unprecedentedly strong correlations. We will show that a single photon propagating along the array may excite a phase slip at the transmon and inelastically convert into lower-frequency photons with a high probability, significantly larger than the conversion probability due to the usual Josephson quartic nonlinearity [35]; this effect could be measured via the resulting broadening of the array modes [13]. For this we develop an extension of the standard equilibrium instanton calculation [1] to a scattering scenario, which could be useful in other fields. We will now outline its main ingredients, deferring some technical details to the supplemental material [36].

Model.— We concentrate on the setup realized in a recent experiments [30, 37], corresponding to the electric circuit depicted in Fig. 1(a). It consists of a long (length $N \gg 1$) two-leg array of superconducting islands connected by strong Josephson junctions E_J^{line} with large junction capacitance C_{line} , negligible ground capacitance (not depicted), and intermediate inter-leg capacitance C_g . The large C_{line} suppresses phase slips along the arrays, allowing their treatment as classical transmission lines. Except for this, C_{line} could be ignored below the array plasma frequency. The small ground capacitance pushes the leg-even modes to high frequencies, decoupling them from the transmon. We may thus employ a simplified single-leg array model [Fig. 1(b)] for the leg-odd degrees of freedom. The array capacitance to the ground C_g and inductance L in Fig. 1(b) are the inter-leg capacitance and twice the intra-leg Josephson inductance

in Fig. 1(a), leading to a Lagrangian

$$\mathcal{L} = \frac{C_0 \dot{\phi}_0^2}{2} + E_J \cos(2\phi_0) + \sum_{n=1}^N \frac{C_g \dot{\phi}_n^2}{2} - \frac{(\phi_n - \phi_{n-1})^2}{2L}, \quad (1)$$

where ϕ_n is in units of flux and we employ units where $e = 1$ and $\hbar = 1$, hence the flux quantum is $\Phi_0 = h/2e = \pi$. The array spacing a will serve as the unit of length.

The array is terminated by a transmon qubit [33] (node $n = 0$, blue elements in Fig. 1), a small SQUID whose Josephson energy E_J is flux-tunable and much larger than its charging energy, $E_C = 1/2C_0$. Hence, to leading order we may approximate its Josephson cosine by a quadratic function [30]. Then Eq. (1) gives rise to eigenmodes with dispersion $\omega_k = 2v \sin(k/2) \approx vk$, where $v = 1/\sqrt{LC_g}$, the array wave velocity divided by the array spacing, is much larger than all other energy scales, i.e., for all relevant modes $k \ll \pi$. The eigenmodes are $\propto \sin(kn + \delta_k)$, where [36, Sec. SI.B]

$$\delta_k = \tan^{-1} \left(\frac{\Gamma_0 \omega_k}{\omega_0^2 - \omega_k^2} \right) \quad (2)$$

is the phase shift. Here $\omega_0 = \sqrt{8E_J E_C}$ is the transmon LC frequency and $\Gamma_0 = 1/ZC_0 = 4E_C/\pi z$ is its elastic broadening due to its coupling to the array, where $Z = \sqrt{L/C_g}$ is the array wave impedance and $z = Z/R_Q$ ($R_Q = h/(2e)^2 = \pi/2$ is the superconducting resistance quantum). For $N \gg 1$ the mode spacing is $\Delta = \pi v/N$, hence $\sum_k \rightarrow \int_0^\infty d\omega/\Delta$.

Upon increasing E_C/E_J the transmon nonlinearity starts becoming significant. We will concentrate on the regime where $\sqrt{E_C/E_J}$ is still small, and furthermore, $\Gamma_0/\omega_0 \ll 1$ (i.e., $\sqrt{E_C/E_J} \ll z$), so the transmon resonance is well-defined [30]. In this regime the nonlinearity manifests in two ways: (i) Expanding the Josephson cosine gives rise to quartic nonlinearity, shifting ω_0 by $-E_C$. It could also induce photon inelastic scattering, but we will show later on that for realistic device parameters this effect could be subleading; (ii) The periodicity of the cosine allows for instantons (phase slips). An incoming photon may excite a phase slip, and the resulting voltage and current pulse may give rise to the emission of photons with different frequencies. We will now study in detail the latter inelastic effect.

Instanton calculation.— For a disconnected transmon [first two terms of Eq. (1)] the classical instanton solution in imaginary time, describing a phase slip between $\phi_0(\tau \rightarrow -\infty) = 0$ and $\phi_0(\tau \rightarrow \infty) = \pm\Phi_0 = \pm\pi$, is $\phi_0^{(0)}(\tau) = \pm 2 \tan^{-1}(e^{\omega_0 \tau})$, or, in Fourier space, $\phi_0^{(0)}(\omega) = \pm \pi/i\omega \cosh(\pi\omega/2\omega_0)$ [1]. Here and below, the upper (lower) sign corresponds to an instanton (anti-instanton).

The classical action S_0 of the instanton, together with the contributions of Gaussian fluctuations around it, give rise to the transmon ground state charge dispersion λ_0 (half the width of the lowest Bloch band of the corresponding Mathieu equation [33, 38]) in the WKB approximation [36, Sec. SI.A],

$$\lambda_0 \approx \frac{8}{\sqrt{\pi}} (8E_J^3 E_C)^{1/4} e^{-\sqrt{8E_J/E_C}}. \quad (3)$$

We now incorporate the array to lowest order in Γ_0/ω_0 . Expanding the imaginary time action around the classical isolated instanton solution $[\phi_0^{(0)}(\tau)]$ as given above and $\phi_{n>0}^{(0)}(\tau) = 0$ to second order in the deviation $\delta\phi_n = \sum_k \delta\phi_k \sin(kn + \delta_k)$, one finds [36, Sec. SI.B]:

$$S = S_0 + \int \frac{d\omega}{2\pi} \left[\frac{|\phi_0^{(0)}(\omega)|^2}{2L} + \sum_k \frac{C_k}{2} (\omega^2 + \omega_k^2) |\delta\phi_k(\omega)|^2 - \frac{\sin(k + \delta_k) - \sin(\delta_k)}{L} \phi_0^{(0)}(-\omega) \delta\phi_k(\omega) \right] - \int d\tau \frac{8E_J}{\cosh^2(\omega_0 \tau)} \left[\sum_k \sin(\delta_k) \delta\phi_k(\tau) \right]^2, \quad (4)$$

where the capacitance of mode k is $C_k \approx NC_g/2$ for $N \gg 1$. The very last term contributes to higher orders in Γ_0/ω_0 and will be neglected henceforth. The classical equations of motion for $\delta\phi_k$ result in

$$\delta\phi_k(\omega) \approx \frac{1}{C_k(\omega^2 + \omega_k^2)} \frac{\omega_k \cos \delta_k}{Z} \phi_0^{(0)}(\omega), \quad (5)$$

to leading order in $k \ll 1$. Plugging this back into the action [39] gives [36, Sec. SI.B]

$$\delta S = \frac{1}{2} \sum_k \tilde{f}_k^2, \quad \tilde{f}_k = \sqrt{\frac{2\Delta}{z\omega_k}} \frac{1}{\cosh\left(\frac{\pi}{2} \frac{\omega_k}{\omega_0}\right)}, \quad (6)$$

leading to a renormalization $\lambda_0 \rightarrow \lambda_0 e^{-\sum_k \tilde{f}_k^2/2}$. For $z > 1$ instantons are relevant, resulting in an emergent scale, $\lambda_* \sim \lambda_0(\lambda_0/\omega_0)^{1/(z-1)}$, below which instanton effects are nonperturbative [2]; we limit ourselves to higher energies.

Within the approximations we employ, the contribution of a single instanton to a multipoint correlation of the ϕ_k is given by the corresponding classical solution [39], multiplied by $\lambda_0 e^{-\sum_k \tilde{f}_k^2/2}$. By the LSZ reduction formula [40, 41], this correlation with its external single-particle legs amputated gives the \mathcal{T} -matrix element between N_{in} incoming photons with momenta $k'_1, k'_2, \dots, k'_{N_{\text{in}}}$ and N_{out} outgoing photons with momenta $k_1, k_2, \dots, k_{N_{\text{out}}}$ [36, Sec. SI.C]:

$$\begin{aligned}
\mathcal{T}_{k_1, k_2, \dots, k_{N_{\text{out}}}}^{k'_1, k'_2, \dots, k'_{N_{\text{in}}}} &= \frac{\Delta}{2\pi} \lim_{\substack{\{\omega'_j \rightarrow i\omega_{k'_j}\} \\ \{\omega_j \rightarrow -i\omega_{k_j}\}}} \prod_{j=1}^{N_{\text{in}}} \frac{C_{k'_j} (\omega_j'^2 + \omega_{k'_j}^2)}{\sqrt{2C_{k'_j} \omega_{k'_j}}} \prod_{j=1}^{N_{\text{out}}} \frac{C_{k_j} (\omega_j^2 + \omega_{k_j}^2)}{\sqrt{2C_{k_j} \omega_{k_j}}} \left\langle \prod_{j=1}^{N_{\text{in}}} \phi_{k'_j}(\omega'_j) \prod_{j=1}^{N_{\text{out}}} \phi_{k_j}(\omega_j) \right\rangle_{1\text{-instanton}} \\
&= (\mp 1)^{N_{\text{in}}} (\pm 1)^{N_{\text{out}}} f_{k'_1} f_{k'_2} \dots f_{k'_{N_{\text{in}}}} f_{k_1} f_{k_2} \dots f_{k_{N_{\text{out}}}} \frac{\lambda_0}{2} e^{-\sum_k \tilde{f}_k^2/2}
\end{aligned} \tag{7}$$

with

$$f_k = \sqrt{\frac{2\Delta}{z\omega_k}} \frac{\omega_0^2 - \omega_k^2}{\sin\left(\frac{\pi}{2} \frac{\omega_0 - \omega_k}{\omega_0}\right) \sqrt{(\omega_0^2 - \omega_k^2)^2 + (\Gamma_0 \omega_k)^2}}, \tag{8}$$

being the “form factor” of the instanton in the photon modes basis. Note that it is finite at the resonance frequency ω_0 but still peaked there. It rises toward low frequencies (assumed higher than λ_*); this reflects the fact that an instanton involves a shift of phases along the entire array, and hence couples well to low- k modes. Thus, processes in which a nearly resonant photon scatters into one nearly resonant photon and several low energy photons (whose number is controlled by z) will play an important role. Note also that f_k diverges at higher odd multiples of ω_0 , which are nonlinear resonances broad-

ened only at higher order in Γ_0 . In relevant experiments [30] these will anyway be close to E_J , i.e., outside the instanton regime, hence we will limit ourselves here to lower frequencies. Adding up the contribution of the instantons and the anti-instantons eliminates processes involving an odd number of photons.

Let us consider processes in which an additional photon with the specific frequency ω_k is included among either the incoming or outgoing photons. Combining the square of the \mathcal{T} -matrix elements just obtained with the appropriate Bose-Einstein factors corresponding to spontaneous and stimulated emission as well as stimulated absorption, gives the total rate Γ_k^{in} of the inelastic decay (minus creation) of a single incoming photon at k [36, Sec. SI.D] (the inelastic scattering probability per collision is $2\pi\Gamma_k^{\text{in}}/\Delta$, while $\omega_k/\Gamma_k^{\text{in}}$ is the experimentally-measurable quality factor of mode k [30]) [42],

$$\begin{aligned}
\Gamma_k^{\text{in}} &= \frac{\lambda_0^2}{2} f_k^2 e^{-\sum_{k'} \tilde{f}_{k'}^2 - 2\sum_{k'} f_{k'}^2 n_B(\omega_{k'})} \sum_{N_{\text{out}}, N_{\text{in}}} \sum_{\substack{k_1 < \dots < k_{N_{\text{out}}}, \\ k'_1 < \dots < k'_{N_{\text{in}}}}} f_{k_1}^2 \dots f_{k_{N_{\text{out}}}}^2 f_{k'_1}^2 \dots f_{k'_{N_{\text{in}}}}^2 (1 + n_B(\omega_{k_1})) \dots (1 + n_B(\omega_{k_{N_{\text{out}}}})) \times \\
&\quad n_B(\omega_{k'_1}) \dots n_B(\omega_{k'_{N_{\text{in}}}}) 2\pi \left[\delta\left(\omega_k + \omega_{k'_1} + \dots + \omega_{k'_{N_{\text{in}}}} - \omega_{k_1} - \dots - \omega_{k_{N_{\text{out}}}}\right) - \{\omega_k \rightarrow -\omega_k\} \right],
\end{aligned} \tag{9}$$

The probability of a process not involving photons with frequency $\omega_{k'}$ decreases when such photons are present, due to the increased probability of their emission or absorption. This is accounted for by the factor $e^{-2\sum_{k'} f_{k'}^2 n_B(\omega_{k'})}$ [36, Sec. SI.D].

Upon expressing the delta functions via their Fourier representations, the summations over $N_{\text{in, out}}$ and the k s can be recognized as the Taylor series of an exponent. All in all we find that $\Gamma_k^{\text{in}} = 2f_k^2 \Im \Pi_R(\omega_k)$, where

$$\Pi_R(\omega) = -\lambda_0^2 \int_0^\infty dt \sin(\omega t) \exp\left(-\sum_{k'} \left\{ f_{k'}^2 [(1 + n_B(\omega_{k'}))(1 - e^{-i\omega_{k'} t}) + n_B(\omega_{k'})(1 - e^{i\omega_{k'} t})] + \tilde{f}_{k'}^2 - f_{k'}^2 \right\}\right), \tag{10}$$

is the photon retarded self energy, whose imaginary part gives the total inelastic conversion (absorption minus emission) rate of energy ω into any photon combination. Using it, one may write down more refined rates; for example, the net rate of creation of photons at k' due to processes involving an incoming photon at k is

$$\begin{aligned}
\Gamma_{k'|k}^{\text{in}} &= 2f_k^2 f_{k'}^2 \{ \Im \Pi_R(\omega_k - \omega_{k'}) [(1 + n_B(\omega_{k'}))(1 + n_B(\omega_k - \omega_{k'})) - n_B(\omega_{k'}) n_B(\omega_k - \omega_{k'})] \\
&\quad + \Im \Pi_R(\omega_k + \omega_{k'}) [(1 + n_B(\omega_{k'})) n_B(\omega_k + \omega_{k'}) - n_B(\omega_{k'})(1 + n_B(\omega_k + \omega_{k'}))] \},
\end{aligned} \tag{11}$$

which accounts for processes in which photons at k, k' are, respectively, absorbed-emitted, emitted-absorbed,




FIG. 2. Parameter dependence of the inelastic scattering probability of a single incoming photon with frequency ω_k by a single phase slip, Eqs. (10)–(11). (a) On-resonance (mode $k_0 = \omega_0/v$) total probability $2\pi\Gamma_{k_0}^{\text{in}}/\Delta$ as function of ω_0/Γ_0 for several values of z at $T = 0$ [using the full Mathieu expression for λ_0 [33, 38], rather than the approximate Eq. (3) [36, Sec. SI.A]]. (b) The distribution of inelastically generated photons $\Gamma_{k'|k}^{\text{in}}/\Gamma_k^{\text{in}}$ at $\omega_k = \omega_0, \omega_0 \pm \Gamma_0$ for $z = 2$ and $\Gamma_0/\omega_0 = 0.2$. (c,d) $T = 0$ resonance lineshape at (c) $z = 2$ and different Γ_0/ω_0 or (d) $\Gamma_0/\omega_0 = 0.2$ and different z . A simple Lorentzian with width Γ_0 is also plotted for comparison. (e) Temperature dependence of the on-resonance probability for $\Gamma_0/\omega_0 = 0.05$ and different z . (f) Ratio between the $T = 0$ on-resonance probabilities due to the instantons and due to the quartic nonlinearity, Eq. (16), showing that the former may dominate by several orders of magnitude for not-too-small Γ_0/ω_0 and $z \gtrsim 1$.

emitted-emitted, or absorbed-absorbed, with appropriate signs to obey an energy conservation sum rule, $\omega_k \Gamma_k^{\text{in}} = \sum_{k'} \omega_{k'} \Gamma_{k'|k}^{\text{in}}$. The last couple of equations are the central results of this work. To recap, they apply for any $\omega_k, \omega_{k'}$ between λ_* and $3\omega_0$, provided that $\lambda_* \ll \max(\Gamma_0, T) \ll \omega_0$ and $E_C \ll E_J$. The single-instanton approximation further requires $2\pi\Gamma_k^{\text{in}}/\Delta \lesssim 1$.

Inelastic rate behavior.— We exemplify the parameter dependence of the inelastic rate in Fig. 2. To better understand its behavior, it is useful to study some limits [36, Sec. SI.E]. First, at $T = 0$ and low frequencies $\omega \ll \omega_0$ one may approximate $f_q \approx \sqrt{2\Delta/z\omega_q}$ in Eq. (10), leading to [43]

$$\Pi_R(\omega) \approx \frac{\pi}{\Gamma(2/z)} \frac{\lambda_0^2}{\omega} \left(\frac{\omega}{\omega_c(z)} \right)^{2/z}, \quad (12)$$

where $\Gamma(x)$ is the gamma function [38], and the effective cutoff $\omega_c(z) \approx 0.9\omega_0$ is z independent for $z \gtrsim 1$.

Let us now turn to the scattering of nearly-resonant photons, $\omega_k \approx \omega_0$, starting with $T = 0$. As the spectrum of inelastically-emitted photons in Fig. 2(b) exemplifies, for $z \gtrsim 1$ and $\Gamma_0/\omega_0 \rightarrow 0$ the dominant process involves one emitted photon at $\omega_{k'} \approx \omega_k$, while the other photons

carry low energy of order Γ_0 , hence

$$\frac{2\pi\Gamma_{k'|k}^{\text{in}}}{\Delta^2} \approx \frac{2\lambda_1^2}{\Gamma(2/z)\omega_c} \left(\frac{\omega_k - \omega_{k'}}{\omega_c} \right)^{\frac{2-z}{z}} \prod_{q=k,k'} \frac{\Gamma_0/2}{(\omega_0 - \omega_q)^2 + (\Gamma_0/2)^2}, \quad (13)$$

where $\lambda_1 = -\sqrt{2^7 E_J/E_C} \lambda_0$ is the charge dispersion of the first excited level of an isolated transmon [33]. Summing over k' one obtains on resonance (mode $k_0 = \omega_0/v$),

$$\frac{2\pi\Gamma_{k_0}^{\text{in}}}{\Delta} \approx \frac{\pi(\omega_0/\omega_c)^{2/z}}{\Gamma(2/z) \sin(\pi/z)} \frac{\lambda_1^2}{(\Gamma_0/2)^2} \left(\frac{\Gamma_0/2}{\omega_0} \right)^{2/z}. \quad (14)$$

The charge dispersion λ_0 decreases fast with ω_0 , masking the corresponding increase in the number of possible decay channels contributing on-resonance [Fig. 2(a)]; this serves to distinguish this process from parasitic effects, such as dielectric loss, which display the opposite behavior [13]. We further see that the inelastic scattering probability can approach order unity in the recently-achieved regime of effective fine-structure constant $z \gtrsim 1$ [13, 30]. The increase in number of channels with frequency is seen in an asymmetry of the inelastic resonance lineshape [Fig. 2(c,d)]; For $|\omega_k - \omega_0| \ll \omega_0$ one has

$$\frac{\Gamma_{k_0}^{\text{in}}}{\Gamma_{k_0}^{\text{in}}} \approx \begin{cases} 2 \sin\left(\frac{\pi}{z}\right) \left(\frac{\Gamma_0/2}{\omega_k - \omega_0} \right)^{3-2/z}, & \omega_k - \omega_0 \gg \Gamma_0, \\ \frac{(\Gamma_0/2)^2}{(\omega_0 - \omega_k)^2 + (\Gamma_0/2)^2}, & |\omega_k - \omega_0| \lesssim \Gamma_0, \\ \frac{1-2/z}{\cos(\pi/z)} \left(\frac{\Gamma_0/2}{\omega_0 - \omega_k} \right)^{4-2/z}, & \omega_0 - \omega_k \gg \Gamma_0. \end{cases} \quad (15)$$

Finally, let us note that temperature suppresses coherent quantum phase slips (particularly for $z > 1$, when they are relevant [2]) but gives rise to scattering by thermal photons, and hence could either decrease or increase the decay rate, depending on z , as shown in Fig. 2(e). Similar expressions to Eqs. (13)–(15) can be obtained via an effective Hamiltonian tailored to describe this particular class of processes [44], though that approach cannot give the value of ω_c .

Quartic nonlinearity.— Let us now briefly discuss inelastic photon scattering by more mundane nonlinearities, coming from the Taylor expansion of the transmon Josephson cosine. To leading order in $\sqrt{E_C/E_J}$ it is dominated by the Fermi golden rule contribution of the quartic term in the expansion, which at $T = 0$ allows an incoming photon at k to split into three at k_i , $i = 1, 2, 3$. Expressing ϕ_0 in terms of the array modes, one finds [36, Sec. SIII]

$$\Gamma_k^{\text{in}} = \frac{4z^2 \omega_0^4 \Delta^4}{3\pi \Gamma_0^2} \frac{\sin^2(\delta_k)}{\omega_k} \sum_{k_i} \frac{\sin^2(\delta_{k_i})}{\omega_{k_i}} \times \frac{\sin^2(\delta_{k_2})}{\omega_{k_2}} \frac{\sin^2(\delta_{k_3})}{\omega_{k_3}} \delta(\omega_k - \omega_{k_1} - \omega_{k_2} - \omega_{k_3}). \quad (16)$$

As opposed to the instanton contribution, where f_k^2 increases toward low energies [Eq. (8)], here the factors $\sin^2(\delta_{k_i})/\omega_{k_i} \propto \omega_{k_i}$ [cf. Eq. (2)] suppress the contribution of low frequency photons, and severely limit the phase space for splitting of nearly-resonant photons. Summing over k_i we find the resulting total inelastic rate near resonance to scale as $\sim z^2 \Delta \Gamma_0^4 / \omega_0^4$. The suppression with Γ_0/ω_0 can make it significantly smaller than the instanton contribution, provided λ_1 is not too small

[cf. Eq. (14)]. The ratio between the corresponding rates is depicted in Fig. 2(f), which shows that instanton processes are stronger by several orders of magnitude in the experimentally-accessible regime of not-too-small Γ_0/ω_0 and $z \gtrsim 1$ [where the exponential factor in Eq. (3) does not dominate] [30].

Conclusions.— In this work we have developed a general formalism for the study of instanton-particle collisions, and applied it to a recently-realized [30] superconducting circuit in which a transmon qubit is strongly-coupled to a high impedance transmission line. We have shown that significant inelastic single-photon scattering by instantons can be controllably initiated and identified in such a setup: As opposed to the Josephson quartic nonlinearity, which only affects near-resonance photons and thus cannot split them into low frequency ones, an instanton shifts the phases along the entire array, hence couples well to low- k modes, and allows a near-resonant incoming photon to dissipate energy into them. An experiment has now appeared [37] demonstrating this effect, with favorable comparison to a simplified version of our theory [36, Sec. SII]. This paves the way toward the study of similar effects not only in various superconducting circuits [2, 3, 5–9, 17–29, 31, 32], but also in other condensed matter (e.g., atomtronic setups) [4, 45, 46] and particle physics [10–12] systems.

We thank L.I. Glazman and M. Houzet for very useful discussions and for sharing with us their unpublished results [44]. Our work has been supported by the U.S.-Israel Binational Science Foundation (Grants No. 2014262 and No. 2016224). In addition, R.V.K. and V.E.M. acknowledge support from US Department of Energy (Grant No. DE-SC0020160). V.E.M. was further supported by a U.S. DOE Early Career Award and M.G. by the Israel Science Foundation (Grant No. 227/15).

-
- [1] M. Mariño, *Instantons and Large N: An Introduction to Non-Perturbative Methods in Quantum Field Theory* (Cambridge University Press, Cambridge, UK, 2015).
 - [2] G. Schön and A. D. Zaikin, Quantum coherent effects, phase transitions, and the dissipative dynamics of ultra small tunnel junctions, *Physics Reports* **198**, 237 (1990).
 - [3] R. Fazio and H. van der Zant, Quantum phase transitions and vortex dynamics in superconducting networks, *Physics Reports* **355**, 235 (2001).
 - [4] A. J. Leggett, *Quantum Liquids* (Oxford University Press, Oxford, UK, 2006).
 - [5] A. M. Hriscu and Y. V. Nazarov, Model of a proposed superconducting phase slip oscillator: A method for obtaining few-photon nonlinearities, *Phys. Rev. Lett.* **106**, 077004 (2011).
 - [6] G. Rastelli, I. M. Pop, and F. W. J. Hekking, Quantum phase slips in Josephson junction rings, *Phys. Rev. B* **87**, 174513 (2013).
 - [7] A. Ergül, J. Lidmar, J. Johansson, Y. Azizoglu, D. Schaeffer, and D. B. Haviland, Localizing quantum phase slips in one-dimensional Josephson junction chains, *New Journal of Physics* **15**, 095014 (2013).
 - [8] N. Vogt, J. H. Cole, and A. Shnirman, De-pinning of disordered bosonic chains, *New Journal of Physics* **18**, 053026 (2016).
 - [9] M. Bard, I. V. Protopopov, I. V. Gornyi, A. Shnirman, and A. D. Mirlin, Superconductor-insulator transition in disordered Josephson-junction chains, *Phys. Rev. B* **96**, 064514 (2017).
 - [10] A. M. Polyakov, *Gauge Fields and Strings* (Harwood, Chur, Switzerland, 1987).
 - [11] S. Coleman, The uses of instantons, in *The Whys of Subnuclear Physics*, edited by A. Zichichi (Springer, Boston, 1979).
 - [12] D. J. Gross, R. D. Pisarski, and L. G. Yaffe, QCD and instantons at finite temperature, *Rev. Mod. Phys.* **53**, 43 (1981).
 - [13] R. Kuzmin, R. Mencia, N. Grabon, N. Mehta, Y.-H. Lin, and V. E. Manucharyan, Quantum electrodynamics of a superconductor-insulator phase transition, *Nature Physics* **15**, 930 (2019).
 - [14] M. Bard, I. V. Protopopov, and A. D. Mirlin, Decay of plasmonic waves in Josephson junction chains, *Phys. Rev. B* **98**, 224513 (2018).

- [15] M. Houzet and L. I. Glazman, Microwave spectroscopy of a weakly pinned charge density wave in a superinductor, *Phys. Rev. Lett.* **122**, 237701 (2019).
- [16] H.-K. Wu and J. D. Sau, Theory of coherent phase modes in insulating Josephson junction chains, *Phys. Rev. B* **99**, 214509 (2019).
- [17] S. Camalet, J. Schrieffer, P. Degiovanni, and F. Delduc, Quantum impurity approach to a coupled qubit problem, *Europhysics Letters (EPL)* **68**, 37 (2004).
- [18] J. J. García-Ripoll, E. Solano, and M. A. Martin-Delgado, Quantum simulation of Anderson and Kondo lattices with superconducting qubits, *Phys. Rev. B* **77**, 024522 (2008).
- [19] K. Le Hur, Kondo resonance of a microwave photon, *Phys. Rev. B* **85**, 140506(R) (2012).
- [20] M. Goldstein, M. H. Devoret, M. Houzet, and L. I. Glazman, Inelastic microwave photon scattering off a quantum impurity in a Josephson-junction array, *Phys. Rev. Lett.* **110**, 017002 (2013).
- [21] B. Peropadre, D. Zueco, D. Porras, and J. J. García-Ripoll, Nonequilibrium and nonperturbative dynamics of ultrastrong coupling in open lines, *Phys. Rev. Lett.* **111**, 243602 (2013).
- [22] I. Snyman and S. Florens, Robust Josephson-Kondo screening cloud in circuit quantum electrodynamics, *Phys. Rev. B* **92**, 085131 (2015).
- [23] N. Gheeraert, S. Bera, and S. Florens, Spontaneous emission of Schrödinger cats in a waveguide at ultrastrong coupling, *New Journal of Physics* **19**, 023036 (2017).
- [24] J. Leppäkangas, J. Braumüller, M. Hauck, J.-M. Reiner, I. Schwenk, S. Zanker, L. Fritz, A. V. Ustinov, M. Weides, and M. Marthaler, Quantum simulation of the spin-boson model with a microwave circuit, *Phys. Rev. A* **97**, 052321 (2018).
- [25] N. Gheeraert, X. H. H. Zhang, T. Sépulcre, S. Bera, N. Roch, H. U. Baranger, and S. Florens, Particle production in ultrastrong-coupling waveguide qed, *Phys. Rev. A* **98**, 043816 (2018).
- [26] T. Yamamoto and T. Kato, Microwave scattering in the subohmic spin-boson systems of superconducting circuits, *Journal of the Physical Society of Japan* **88**, 094601 (2019).
- [27] R. Belyansky, S. Whitsitt, R. Lundgren, Y. Wang, A. Vrajitoarea, A. A. Houck, and A. V. Gorshkov, Frustration-induced anomalous transport and strong photon decay in waveguide QED, *arXiv:2007.03690 [quant-ph]* (2020).
- [28] P. Forn-Díaz, J. García-Ripoll, B. Peropadre, J.-L. Orgiazzi, M. Yurtalan, R. Belyansky, C. Wilson, and A. Lupascu, Ultrastrong coupling of a single artificial atom to an electromagnetic continuum in the nonperturbative regime, *Nature Physics* **13**, 39 (2017).
- [29] L. Magazzù, P. Forn-Díaz, R. Belyansky, J.-L. Orgiazzi, M. A. Yurtalan, M. R. Otto, A. Lupascu, C. M. Wilson, and M. Grifoni, Probing the strongly driven spin-boson model in a superconducting quantum circuit, *Nature Communications* **9**, 1403 (2018).
- [30] R. Kuzmin, N. Mehta, N. Grabon, R. Mencia, and V. E. Manucharyan, Superstrong coupling in circuit quantum electrodynamics, *npj Quantum Information* **5**, 1 (2019).
- [31] J. Puertas Martínez, S. Léger, N. Gheeraert, R. Dassonneville, L. Planat, F. Foroughi, Y. Krupko, O. Buisson, C. Naud, W. Hasch-Guichard, S. Florens, I. Snyman, and N. Roch, A tunable Josephson platform to explore many-body quantum optics in circuit-QED, *npj Quantum Information* **5**, 19 (2019).
- [32] S. Indrajeet, H. Wang, M. D. Hutchings, B. G. Taketani, F. K. Wilhelm, M. D. LaHaye, and B. L. T. Plourde, Coupling a superconducting qubit to a left-handed metamaterial resonator, *arXiv:2007.10932 [quant-ph]* (2020).
- [33] J. Koch, T. M. Yu, J. Gambetta, A. A. Houck, D. I. Schuster, J. Majer, A. Blais, M. H. Devoret, S. M. Girvin, and R. J. Schoelkopf, Charge-insensitive qubit design derived from the Cooper pair box, *Phys. Rev. A* **76**, 042319 (2007).
- [34] V. E. Manucharyan, J. Koch, L. I. Glazman, and M. H. Devoret, Fluxonium: Single cooper-pair circuit free of charge offsets, *Science* **326**, 113 (2009).
- [35] By the dynamical Coulomb blockade [47], inelastic Cooper pair tunneling (dual to phase slips) could also induce photon emission [48, and references therein]. However, that process is driven by a dc voltage bias, akin (by the ac Josephson effect) to strong pumping by a microwave source in our setup, in marked distinction from the single photon excitation regime we consider.
- [36] See the supplemental material for further details of the derivations.
- [37] R. Kuzmin, N. Grabon, N. Mehta, A. Burshtein, M. Goldstein, M. Houzet, L. I. Glazman, and V. E. Manucharyan, Photon decay in circuit quantum electrodynamics, *arXiv:2010.02099 [cond-mat.supr-con]* (2020).
- [38] M. Abramowitz and I. A. Stegun, *Handbook of Mathematical Functions* (Dover, New York, 1965).
- [39] Corrections to the fluctuations contribution are subleading in Γ_0/ω_0 .
- [40] M. E. Peskin and D. V. Schroeder, *An Introduction to Quantum Field Theory* (CRC Press, Boca Raton, 2015).
- [41] J.-G. Zhou, J.-Q. Liang, J. Burzlaff, and H. Müller-Kirsten, Instanton induced tunneling amplitude at excited states with the LSZ method, *Physics Letters A* **224**, 142 (1996).
- [42] The sum is restricted to odd $N_{\text{out}} + N_{\text{in}} \geq 3$. However, in the thermodynamic limit one may discard this restriction and introduce the prefactor of half [36, Sec. SI.D].
- [43] A. O. Gogolin, A. A. Nersisyan, and A. M. Tsvelik, *Bosonization and strongly correlated systems* (Cambridge University Press, 2004).
- [44] M. Houzet and L. I. Glazman, Critical fluorescence of a transmon at the schmid transition, *Phys. Rev. Lett.* **125**, 267701 (2020).
- [45] C. L. Kane and M. P. A. Fisher, Transport in a one-channel luttinger liquid, *Phys. Rev. Lett.* **68**, 1220 (1992).
- [46] S. Krinner, D. Stadler, D. Husmann, J.-P. Brantut, and T. Esslinger, Observation of quantized conductance in neutral matter, *Nature* **517**, 64 (2015).
- [47] G. L. Ingold and Y. V. Nazarov, Charge tunneling rates in ultrasmall junctions, in *Single Charge Tunneling*, NATO ASI Series B, Vol. 294, edited by H. Grabert and M. H. Devoret (Plenum, New York, 1992) pp. 21–107.
- [48] A. Peugeot, G. Ménard, S. Dambach, M. Westig, B. Kubala, Y. Mukharsky, C. Altimiras, P. Joyez, D. Vion, P. Roche, D. Esteve, P. Milman, J. Leppäkangas, G. Johansson, M. Hofheinz, J. Ankerhold, and F. Portier, Generating two continuous entangled microwave beams using a dc-biased Josephson junction, *arXiv:2010.03376 [cond-mat.mes-hall]* (2020).

SUPPLEMENTAL MATERIAL FOR: “PHOTON-INSTANTON COLLIDER IMPLEMENTED BY A SUPERCONDUCTING CIRCUIT”

In this Supplemental Material we provide additional technical details and elaborate upon some of the derivations in the main text. In Sec. SI, we provide some intermediate steps in the derivation of the instanton inelastic rate which were omitted from the main text. In Sec. SII, we use a phenomenological “dual-cosine” approach to calculate the rate, and compare its results with those of the instanton approach. Finally, in Sec. SIII, we derive the inelastic rate due to the Josephson cosine quartic nonlinearity.

SI. ADDITIONAL DETAILS OF THE DERIVATION OF THE INSTANTON INELASTIC RATE

The main result of the paper is the inelastic rate due to the photon-instanton interaction, Eqs. (10)-(11) of the main text, which apply to incoming/outgoing photons with frequencies between λ_* and $3\omega_0$, assuming in addition that $\lambda_* \ll \max(\Gamma_0, T) \ll \omega_0$ and $E_C \ll E_J$ (all these parameters will be redefined below). In this section, we repeat the derivation while providing some additional details. We recite the Lagrangian of the system, Eq. (1) [describing the simplified circuit depicted in Fig. 1(b)] of the main text:

$$\mathcal{L} = \frac{C_0 \dot{\phi}_0^2}{2} + E_J \cos(2\phi_0) + \sum_{n=1}^N \frac{C_g \dot{\phi}_n^2}{2} - \frac{(\phi_n - \phi_{n-1})^2}{2L}, \quad (\text{S1})$$

where ϕ_n is the flux of node $n = 0 \cdots N$ in Fig. 1(b), L and C_g are the array effective Josephson inductance and ground capacitance, respectively, E_J and C_0 are the transmon Josephson energy and capacitance, respectively, and we employ units where $e = 1$ and $\hbar = 1$.

A. An isolated transmon

The Hamiltonian of an isolated Josephson junction [33] corresponds to the first two terms of the Lagrangian, Eq. (S1):

$$H_0 = E_C(Q_0 - q_g)^2 - E_J \cos(2\phi_0), \quad (\text{S2})$$

where $E_C = 1/2C_0$, ϕ_0 and Q_0 are the flux and charge variables of the transmon, obeying the canonical commutation relations, and q_g is its gate charge (which can be gauged away in the presence of an infinite transmission line, hence is ignored in later sections). This Hamiltonian may be solved exactly in the flux basis, where the energy of the m th level, or Bloch band, $E_m(q_g) = E_m(q_g \pm 2)$ ($m = 0, 1, \dots$), is given by the Mathieu characteristic values $a_\nu(E_J/2E_C)$ and $b_\nu(E_J/2E_C)$ [38], as summarized in Table ST1. The transmon resonance frequency ω_0 is defined by

$$\omega_0(q_g) = E_1(q_g) - E_0(q_g), \quad (\text{S3})$$

and generally depends on q_g . In the transmon limit, $E_J \gg E_C$, the effect of charge offset is negligible, and $\omega_0 \approx \sqrt{8E_J E_C}$ to leading order in E_C/E_J , which is also the resonance frequency which results from approximating the Josephson cosine potential in Eq. (S2) by a harmonic term, $2E_J \phi_0^2$. The lowest order correction may be calculated in perturbation theory due to the quartic term in the expansion of $\cos(2\phi_0)$, and yields $\omega_0 \approx \sqrt{8E_J E_C} - E_C$.

We define the charge dispersion λ_m as the half-bandwidth of the m th Bloch band, given by

$$\frac{\lambda_m}{E_C} = \frac{E_m(q_g = 1) - E_m(q_g = 0)}{2E_C} = \frac{(-1)^m}{2} \left[b_{m+1} \left(\frac{E_J}{2E_C} \right) - a_m \left(\frac{E_J}{2E_C} \right) \right] \approx \frac{2^{4m+9/2} (-1)^m}{m! \sqrt{\pi}} \left(\frac{E_J}{2E_C} \right)^{m/2+3/4} e^{-\sqrt{8E_J E_C}}, \quad (\text{S4})$$

The final form is the result of the WKB approximation [given also by Eq. (3) of the main text for $m = 0$]. In the imaginary-time path integral formalism it can be derived from the action of and quadratic fluctuations around the instanton solution, $\phi_0^{(0)}(\tau) = \pm 2 \tan^{-1}(e^{\omega_0 \tau})$, which interpolates between two adjacent minima of the cosine [1–3]. Its Fourier transform is $\phi_0^{(0)}(\omega) = \pm \pi / i\omega \cosh(\pi\omega/2\omega_0)$. Here and below, the plus and minus signs correspond to an instanton and an anti-instanton, respectively.

$E_m(q_g)/E_C$	$q_g = 0$		$0 < q_g < 1$		$ q_g = 1$
m even	$a_m(E_J/2E_C)$	$<$	$a_{m+ q_g }(E_J/2E_C) = b_{m+ q_g }(E_J/2E_C)$	$<$	$b_{m+1}(E_J/2E_C)$
m odd	$b_{m+1}(E_J/2E_C)$	$>$	$a_{m+1- q_g }(E_J/2E_C) = b_{m+1- q_g }(E_J/2E_C)$	$>$	$a_m(E_J/2E_C)$

TABLE ST1. The energy levels of an isolated transmon E_m ($m = 0, 1, \dots$) as function of the quasicharge q_g in the first Brillouin zone $-1 < q_g < 1$ in terms of the Mathieu characteristic values a_ν , b_ν [38].

B. The array modes and their effect on the instanton action

In the presence of the array, a phase slip in the transmon perturbs the array modes; the corresponding leading contribution to the action is given by Eq. (6) of the main text. Here we provide its derivation. To set the stage, let us first consider the limit where E_J/E_C is large enough for the Josephson cosine in Eq. (S1) to be approximated by a harmonic potential, so that

$$\mathcal{L} \approx \frac{C_0 \dot{\phi}_0^2}{2} - 2E_J \phi_0^2 + \sum_{n=1}^N \frac{C_g \dot{\phi}_n^2}{2} - \frac{(\phi_n - \phi_{n-1})^2}{2L}, \quad (\text{S5})$$

and the equations of motion are given by

$$\begin{aligned} -C_g \ddot{\phi}_n &= \frac{1}{L} (2\phi_n - \phi_{n-1} - \phi_{n+1}), & n \geq 1, \\ -C_0 \ddot{\phi}_0 &= 4E_J \phi_0 + \frac{1}{L} (\phi_0 - \phi_1), & n = 0. \end{aligned} \quad (\text{S6})$$

The solutions are of the form $\phi_n \propto \sin(kn + \delta_k)$. The equations for $n \geq 1$ yield the dispersion relation $\omega_k = 2v \sin(k/2) \approx vk$ (the approximation holds for $k \ll \pi$, that is, $\omega_k \ll v$), with $v = 1/\sqrt{LC_g}$. The mode spacing is $\Delta = \pi v/N$ (hence $\sum_k \rightarrow \int_0^\infty d\omega/\Delta$), while the wave impedance is $Z = \sqrt{L/C_g} \equiv z\pi/2$. The equation for $n = 0$ yields the phase shift:

$$\tan \delta_k = \frac{\Gamma_0 \omega_k \sqrt{1 - (\frac{\omega_k}{2v})^2}}{\omega_0^2 - \omega_k^2 (1 - \frac{\Gamma_0}{2v})} \approx \frac{\Gamma_0 \omega_k}{\omega_0^2 - \omega_k^2}, \quad (\text{S7})$$

where $\Gamma_0 = 1/ZC_0 = 4E_C/\pi z$ is the elastic resonance broadening. The approximate form corresponds to Eq. (2) of the main text. The $1 - \Gamma_0/2v$ factor in the denominator of the exact form only gives a slight shift of the resonance frequency, and may always be replaced by unity. The $\sqrt{1 - (\omega_k/2v)^2}$ factor in the numerator, however, should be retained when modes with $k \sim \pi$ contribute, as we discuss below.

Let us now return to $E_J \gtrsim E_C$, where instantons may appear. For $\omega_0/\Gamma_0 \gg 1$ we may expand the imaginary time dynamics around the classical isolated instanton solution, $\phi_0^{(0)}(\tau) = \pm 2 \tan^{-1}(e^{\omega_0 \tau})$ and $\phi_{n>0}^{(0)}(\tau) = 0$. We thus set $\phi_n(\tau) = \phi_n^{(0)}(\tau) + \delta\phi_n(\tau)$, and expand $\delta\phi_n = \sum_k \delta\phi_k \sin(kn + \delta_k)$. To second order in $\delta\phi_k$ we obtain the following action [Eq. (4) of the main text],

$$\begin{aligned} S = S_0 + \int \frac{d\omega}{2\pi} & \left[\frac{|\phi_0^{(0)}(\omega)|^2}{2L} + \sum_k \frac{C_k}{2} (\omega^2 + \omega_k^2) |\delta\phi_k(\omega)|^2 - \frac{\sin(k + \delta_k) - \sin(\delta_k)}{L} \phi_0^{(0)}(-\omega) \delta\phi_k(\omega) \right] \\ & - \int d\tau \frac{8E_J}{\cosh^2(\omega_0 \tau)} \left[\sum_k \sin(\delta_k) \delta\phi_k(\tau) \right]^2, \end{aligned} \quad (\text{S8})$$

where $S_0 = \sqrt{8E_J/E_C}$ is the classical action of an isolated instanton and $C_k \approx NC_g/2$ is the capacitance of mode k . The second row of Eq. (S8) yields subleading terms in Γ_0/ω_0 (as can be verified by plugging into it the solution we obtain below) and will be neglected henceforth. Solving the equation of motion for $\delta\phi_k(\omega)$ and using the $n = 0$ part of Eq. (S6), we find

$$\delta\phi_k(\omega) = \frac{2v^2}{N} \frac{\sin(k + \delta_k) - \sin(\delta_k)}{\omega^2 + \omega_k^2} \phi_0^{(0)}(\omega) = \frac{\sin(\delta_k)}{ZC_k \Gamma_0} \frac{\omega_0^2 - \omega_k^2}{\omega^2 + \omega_k^2} \phi_0^{(0)}(\omega) = \frac{\omega_k \cos(\delta_k) \sqrt{1 - (\frac{\omega_k}{2v})^2}}{ZC_k} \frac{\phi_0^{(0)}(\omega)}{\omega^2 + \omega_k^2}, \quad (\text{S9})$$

in correspondence with Eq. (5) of the main text, but with the additional factor $\sqrt{1 - (\omega_k/2v)^2}$ which is approximately unity for $\omega_k \ll v$. Plugging this back to Eq. (S8), the correction to the action $\delta S = S - S_0$ becomes

$$\delta S = \int \frac{d\omega}{2\pi} \frac{|\phi_0^{(0)}(\omega)|^2}{2L} \left[1 - \frac{2}{N} \sum_k (1 - (\omega_k/2v)^2) \cos^2(\delta_k) + \frac{2}{N} \sum_k \frac{\omega^2 (1 - (\omega_k/2v)^2) \cos^2(\delta_k)}{\omega^2 + \omega_k^2} \right]. \quad (\text{S10})$$

We note that in both of the sums over k in Eq. (S10) we may approximate $\cos^2(\delta_k) \approx 1$, since the deviation of the cosine from 1 occurs only in a frequency range of order Γ_0 around the resonance, and hence contributes subleading terms in Γ_0/ω_0 . Care must be taken in the evaluation of the first sum over k in Eq. (S10), since the argument does not decay for $k \sim \pi$, and therefore we must account for terms of order $\omega_k/2v$, including the Jacobian $d\omega_k/dk = \sqrt{1 - (\omega_k/2v)^2}$. This is not the case for the second sum, where the summand decays rapidly outside the regime $k \ll \pi$, and therefore we may drop all terms of order ω_k/v . Overall, we find:

$$\delta S = \frac{1}{2z} \int_{-\infty}^{\infty} \frac{d\omega}{|\omega| \cosh^2\left(\frac{\pi}{2} \frac{\omega}{\omega_0}\right)} = \frac{\Delta}{z} \sum_k \frac{1}{\omega_k \cosh^2\left(\frac{\pi}{2} \frac{\omega_k}{\omega_0}\right)} \equiv \frac{1}{2} \sum_k \tilde{f}_k^2, \quad (\text{S11})$$

where we have rewritten the ω integral as a k sum. We thus arrive at Eq. (6) of the main text. Combining δS with S_0 , and noting that to leading order in Γ_0/ω_0 Gaussian fluctuations around the classical solution we have just discussed can be approximated by their value for an isolated transmon, the overall amplitude of a single instanton is $(\lambda_0/2)e^{-\sum_k \tilde{f}_k^2/2}$. As discussed in the main text, for $z > 1$ instantons are a relevant perturbation, giving rise to an emergent scale, $\lambda_* \sim \lambda_0(\lambda_0/\omega_0)^{1/(z-1)}$ [2]. Below λ^* instanton effects are nonperturbative; in the following we concentrate on higher energies.

C. Calculation of the \mathcal{T} -matrix

To calculate the inelastic rate, we need the elements of the \mathcal{T} -matrix corresponding to all possible inelastic processes. According to the imaginary-frequency version of the Lehmann-Symanzik-Zimmermann (LSZ) reduction formula [40, 41], these matrix elements for multiple incoming and outgoing photons are determined by the multipoint correlation function of the involved photons, with the single-particle legs (Green functions) amputated:

$$\mathcal{T}_{k_1, k_2, \dots, k_{N_{\text{out}}}}^{k'_1, k'_2, \dots, k'_{N_{\text{in}}}} = \frac{\Delta}{2\pi} \frac{G_0^{-1}(\omega'_1, k'_1)}{\sqrt{2C_{k'_1}\omega_{k'_1}}} \dots \frac{G_0^{-1}(\omega'_{N_{\text{in}}}, k'_{N_{\text{in}}})}{\sqrt{2C_{k'_{N_{\text{in}}}}\omega_{k'_{N_{\text{in}}}}}} \frac{G_0^{-1}(\omega_1, k_1)}{\sqrt{2C_{k_1}\omega_{k_1}}} \dots \frac{G_0^{-1}(\omega_{N_{\text{out}}}, k_{N_{\text{out}}})}{\sqrt{2C_{k_{N_{\text{out}}}}\omega_{k_{N_{\text{out}}}}}} \times \\ \left\langle \phi_{k'_1}(\omega'_1) \dots \phi_{k'_{N_{\text{in}}}}(\omega'_{N_{\text{in}}}) \phi_{k_1}(\omega_1) \dots \phi_{k_{N_{\text{out}}}}(\omega_{N_{\text{out}}}) \right\rangle_{1\text{-instanton}} \Big|_{\substack{\omega'_1 \rightarrow i\omega_{k'_1}, \dots, \omega'_{N_{\text{in}}} \rightarrow i\omega_{k'_{N_{\text{in}}}} \\ \omega_1 \rightarrow -i\omega_{k_1}, \dots, \omega_{N_{\text{out}}} \rightarrow -i\omega_{k_{N_{\text{out}}}}}}, \quad (\text{S12})$$

with $G_0(\omega, k) = 1/C_k(\omega^2 + \omega_k^2)$ being the Green function of mode k . The $1/\sqrt{2C_k\omega_k}$ prefactors relate ϕ_k to a_k^\dagger and a_k , the creation and annihilation of operators of mode k , respectively. We thus recover the first line of Eq. (7) of the main text. The single-instanton propagator may be calculated using the path integral formalism. As mentioned above, each instanton contributes an amplitude $(\lambda_0/2)e^{-\sum_k \tilde{f}_k^2/2}$, which stems from the classical action $S_0 + \delta S$ together with Gaussian fluctuations around the classical path. To leading order in E_C/E_J and Γ_0/ω_0 we may replace the fields in the multipoint correlators by their values at the classical instanton path,

$$\langle \dots \rangle \Big|_{\substack{\omega'_1 \rightarrow i\omega_{k'_1}, \dots \\ \omega_1 \rightarrow -i\omega_{k_1}, \dots}} = (\pm 1)^{N_{\text{in}} + N_{\text{out}}} \frac{\lambda_0}{2} e^{-\sum_k \tilde{f}_k^2/2} \delta\phi_{k'_1}(\omega'_1) \dots \delta\phi_{k'_{N_{\text{in}}}}(\omega'_{N_{\text{in}}}) \delta\phi_{k_1}(\omega_1) \dots \delta\phi_{k_{N_{\text{out}}}}(\omega_{N_{\text{out}}}), \quad (\text{S13})$$

where, as mentioned above, the plus and minus signs correspond to instantons and anti-instantons, respectively. Plugging Eq. (S13) back into Eq. (S12) and taking the limits $\omega_j \rightarrow -i\omega_{k_j}, \omega'_j \rightarrow i\omega_{k'_j}$, one finds

$$\mathcal{T}_{k_1, k_2, \dots, k_{N_{\text{out}}}}^{k'_1, k'_2, \dots, k'_{N_{\text{in}}}} = (\mp 1)^{N_{\text{in}}} (\pm 1)^{N_{\text{out}}} f_{k'_1} f_{k'_2} \dots f_{k'_{N_{\text{in}}}} f_{k_1} f_{k_2} \dots f_{k_{N_{\text{out}}}} \frac{\lambda_0}{2} e^{-\sum_k \tilde{f}_k^2/2}, \quad (\text{S14})$$

with

$$f_k = \sqrt{\frac{2\Delta}{z\omega_k}} \frac{\omega_0^2 - \omega_k^2}{\sin\left(\frac{\pi}{2} \frac{\omega_0 - \omega_k}{\omega_0}\right) \sqrt{(\omega_0^2 - \omega_k^2)^2 + (\Gamma_0\omega_k)^2}}, \quad (\text{S15})$$

which are Eqs. (7)–(8) of the main text.

D. Calculation of the inelastic rate

The \mathcal{T} -matrix elements in Eq. (S14) allow us to calculate the inelastic rate using the Fermi golden rule. Before taking the squared absolute value, we have to sum over the contributions of instantons and anti-instantons in Eq. (S14). We see that the matrix elements vanish for odd $N_{\text{out}} + N_{\text{in}}$, and on the other hand are multiplied by 2 for even $N_{\text{out}} + N_{\text{in}}$; this reflects the symmetry of the Lagrangian, Eq. (S1) upon flipping all the phases. Let us now consider a process in which a photon at mode k collides with photons at $k'_1, k'_2, \dots, k'_{N_{\text{in}}}$ (so now there are $N_{\text{in}} + 1$ incoming photons) to produce photons at $k_1, k_2, \dots, k_{N_{\text{out}}}$, with odd $N_{\text{out}} + N_{\text{in}} \geq 3$; by the Fermi golden rule, the rate of such a process is

$$\Gamma_{k_1, k_2, \dots, k_{N_{\text{out}}}}^{k, k'_1, k'_2, \dots, k'_{N_{\text{in}}}} = \lambda_0^2 f_k^2 e^{-\sum_{k'} \tilde{f}_{k'}^2} f_{k_1}^2 \dots f_{k_{N_{\text{out}}}}^2 f_{k'_1}^2 \dots f_{k'_{N_{\text{in}}}}^2 2\pi \delta \left(\omega_k + \omega_{k'_1} + \dots + \omega_{k'_{N_{\text{in}}}} - \omega_{k_1} - \dots - \omega_{k_{N_{\text{out}}}} \right). \quad (\text{S16})$$

However, given a specific process, we note that we might add photons without changing the outcome. For instance, adding a single photon at mode k'' to both the incoming and outgoing photons would result in a process that is physically identical to the one without it, but with a \mathcal{T} -matrix element multiplied by $-f_{k''}^2$ [cf. Eq. (S14)]. Adding this amplitude to the amplitude excluding the photon at k'' we thus find that when such a photon is present in the system, the rate, Eq. (S16), would be multiplied by a factor $(1 - f_{k''}^2)^2$. Now, at finite temperature T the occupation of this mode is set by the Bose-Einstein distribution, $n_B(\omega_{k''})$, leading to a factor

$$1 + [(1 - f_{k''}^2)^2 - 1] n_B(\omega_{k''}) \approx 1 - 2f_{k''}^2 n_B(\omega_{k''}) \approx e^{-2f_{k''}^2 n_B(\omega_{k''})}, \quad (\text{S17})$$

where the approximations are based on the smallness of $f_{k''}^2 \sim 1/N$ [see Eq. (S15)] in the thermodynamic limit (similar considerations relieve us from the need to explicitly treat cases where some of the photon modes in the forthcoming equations coincide). Multiplying Eq. (S16) by this factor for all possible k'' , as well as by the appropriate Bose-Einstein factors for the photons at $k'_1, k'_2, \dots, k'_{N_{\text{in}}}$ and $k_1, k_2, \dots, k_{N_{\text{out}}}$, and subtracting the contribution of processes in which the photon at k is emitted rather than absorbed, we recover Eq. (9) of the main text:

$$\begin{aligned} \Gamma_k^{\text{in}} = & \lambda_0^2 f_k^2 e^{-\sum_{k'} \tilde{f}_{k'}^2 - 2 \sum_{k'} f_{k'}^2 n_B(\omega_{k'})} \sum_{N_{\text{out}}, N_{\text{in}}} \sum_{\substack{k_1 < \dots < k_{N_{\text{out}}}, \\ k'_1 < \dots < k'_{N_{\text{in}}}}} f_{k_1}^2 \dots f_{k_{N_{\text{out}}}}^2 f_{k'_1}^2 \dots f_{k'_{N_{\text{in}}}}^2 (1 + n_B(\omega_{k_1})) \dots (1 + n_B(\omega_{k_{N_{\text{out}}}})) \times \\ & n_B(\omega_{k'_1}) \dots n_B(\omega_{k'_{N_{\text{in}}}}) 2\pi \left[\delta \left(\omega_k + \omega_{k'_1} + \dots + \omega_{k'_{N_{\text{in}}}} - \omega_{k_1} - \dots - \omega_{k_{N_{\text{out}}}} \right) - \{\omega_k \rightarrow -\omega_k\} \right], \end{aligned} \quad (\text{S18})$$

where the sum is over odd $N_{\text{out}} + N_{\text{in}} \geq 3$.

We now move on to express Γ_k^{in} in terms of the retarded self energy $\Pi_R(\omega)$, given by Eq. (10) of the main text. First, we express the delta functions in terms of their Fourier representation, $2\pi\delta(\omega) = 2\Re \left\{ \int_0^\infty dt e^{i\omega t} \right\}$. Then we rearrange the sums over the momenta into a product (lifting the restrictions $k_1 < \dots < k_{N_{\text{out}}}$, $k'_1 < \dots < k'_{N_{\text{in}}}$ gives a factor $1/N_{\text{out}}!N_{\text{in}}!$):

$$\Gamma_k^{\text{in}} = 2\lambda_0^2 f_k^2 e^{-\sum_{k'} (\tilde{f}_{k'}^2 + 2f_{k'}^2 n_B(\omega_{k'}))} \Re \left\{ \int_0^\infty dt (e^{i\omega_k t} - e^{-i\omega_k t}) \sum_{N_{\text{out}}, N_{\text{in}}} \frac{\sigma_{\text{out}}^{N_{\text{out}}}(t) \sigma_{\text{in}}^{N_{\text{in}}}(t)}{N_{\text{out}}! N_{\text{in}}!} \right\}, \quad (\text{S19})$$

where we introduced the notation

$$\sigma_{\text{in}}(t) = \sum_{k'} f_{k'}^2 n_B(\omega_{k'}) e^{i\omega_{k'} t}, \quad \sigma_{\text{out}}(t) = \sum_{k'} f_{k'}^2 (1 + n_B(\omega_{k'})) e^{-i\omega_{k'} t}. \quad (\text{S20})$$

We recall that the sum involves only terms with odd $N_{\text{out}} + N_{\text{in}} \geq 3$. We decompose it to two sums — one with odd N_{out} and even N_{in} , and the other with even N_{out} and odd N_{in} :

$$\begin{aligned} \sum_{N_{\text{out}}, N_{\text{in}}} \frac{\sigma_{\text{out}}^{N_{\text{out}}}(t) \sigma_{\text{in}}^{N_{\text{in}}}(t)}{N_{\text{out}}! N_{\text{in}}!} &= \sum_{N_{\text{out}}=1,3,\dots} \frac{\sigma_{\text{out}}^{N_{\text{out}}}(t)}{N_{\text{out}}!} \sum_{N_{\text{in}}=2,4,\dots} \frac{\sigma_{\text{in}}^{N_{\text{in}}}(t)}{N_{\text{in}}!} + \sum_{N_{\text{out}}=3,5,\dots} \frac{\sigma_{\text{out}}^{N_{\text{out}}}(t)}{N_{\text{out}}!} \\ &+ \sum_{N_{\text{out}}=2,4,\dots} \frac{\sigma_{\text{out}}^{N_{\text{out}}}(t)}{N_{\text{out}}!} \sum_{N_{\text{in}}=1,3,\dots} \frac{\sigma_{\text{in}}^{N_{\text{in}}}(t)}{N_{\text{in}}!} + \sum_{N_{\text{in}}=3,5,\dots} \frac{\sigma_{\text{in}}^{N_{\text{in}}}(t)}{N_{\text{in}}!} \\ &= \sinh[\sigma_{\text{out}}(t) + \sigma_{\text{in}}(t)] - [\sigma_{\text{out}}(t) + \sigma_{\text{in}}(t)]. \end{aligned} \quad (\text{S21})$$

We now plug this back to (S19) and combine the exponential factor outside of the integral with (S21). For the hyperbolic sine term we have:

$$e^{-\sum_{k'}(\tilde{f}_{k'}^2 + 2f_{k'}^2 n_B(\omega_{k'}))} \sinh(\sigma_{\text{out}}(t) + \sigma_{\text{in}}(t)) = \frac{1}{2} \exp \left(- \sum_{k'} \left\{ f_{k'}^2 [(1 + n_B(\omega_{k'}))(1 - e^{-i\omega_{k'}t}) + n_B(\omega_{k'})(1 - e^{i\omega_{k'}t})] + \tilde{f}_{k'}^2 - f_{k'}^2 \right\} \right) - \frac{1}{2} \exp \left(- \sum_{k'} \left\{ f_{k'}^2 [(1 + n_B(\omega_{k'}))(1 + e^{-i\omega_{k'}t}) + n_B(\omega_{k'})(1 + e^{i\omega_{k'}t})] + \tilde{f}_{k'}^2 - f_{k'}^2 \right\} \right). \quad (\text{S22})$$

At low frequencies, one may approximate $f_q^2 \sim 2\Delta/z\omega_q$ [cf. Eq. (S15)]. The $1/\omega_q$ behavior leads to a logarithmic divergence of the sum over the modes, $\sum_{\omega_q < \omega_c} f_q^2 \sim (2/z) \log(\Delta/2\omega_c)$, since the first mode is located at $\omega_q = \Delta/2$ (assuming open circuit boundary conditions at the far end of the line [30]). Here ω_c is a cutoff frequency which satisfies $\omega_0 - \omega_c \gg \Gamma_0$ and $\omega_c \gg \Gamma_0$. This logarithmic divergence is avoided in the first term on the right hand side in Eq. (S22) due to the $(1 - e^{i\omega_{k'}t})$ factor, hence its contribution is finite. However, the second term goes to zero as a power law in the system size, $\sim \Delta^{2/z} \sim N^{-2/z}$. Thus, in the thermodynamic limit we may approximate the hyperbolic sine in (S21) as an exponential, $\sinh[\sigma_{\text{out}}(t) + \sigma_{\text{in}}(t)] \approx e^{\sigma_{\text{out}}(t) + \sigma_{\text{in}}(t)}/2$, and neglect the linear term. This leads to $\Gamma_k^{\text{in}} = 2f_k^2 \Im \Pi_R(\omega_k)$, with

$$\Pi_R(\omega) = -\lambda_0^2 \int_0^\infty dt \sin(\omega t) \exp \left(- \sum_{k'} \left\{ f_{k'}^2 [(1 + n_B(\omega_{k'}))(1 - e^{-i\omega_{k'}t}) + n_B(\omega_{k'})(1 - e^{i\omega_{k'}t})] + \tilde{f}_{k'}^2 - f_{k'}^2 \right\} \right), \quad (\text{S23})$$

which is Eq. (10) of the main text. The on-resonance inelastic rate decreases with increasing ω_0/Γ_0 due to the exponential decay of λ_0 ; dividing the rate by λ_0^2 reveals that the other factors in the last equation increase with increasing ω_0/Γ_0 , reflecting the increased phase space for inelastic processes, as depicted in Fig. SF1(a).

A similar procedure gives $\Gamma_{k'|k}^{\text{in}}$, the net rate of creation of photons at k' due to processes involving photons at k . Both k and k' could correspond to either incoming or outgoing photons, and therefore $\Gamma_{k'|k}^{\text{in}}$ includes four terms. Let us start with the processes in which the photon at k is absorbed and the photon at k' is emitted. Starting from Eq. (S18), we use the delta function with $+\omega_k$ and separate out a factor $f_{k'}^2(1 + n_B(\omega_{k'}))$ from the sum over the outgoing photons. We thus have

$$\Gamma_{k'|k}^{\text{in}(1)} = \lambda_0^2 f_k^2 f_{k'}^2 (1 + n_B(\omega_{k'})) e^{-\sum_{k'}(\tilde{f}_{k'}^2 + 2f_{k'}^2 n_B(\omega_{k'}))} \sum_{N_{\text{out}}, N_{\text{in}}} \sum_{\substack{k_1 < \dots < k_{N_{\text{out}}}, \\ k'_1 < \dots < k'_{N_{\text{in}}}}} f_{k_1}^2 \dots f_{k_{N_{\text{out}}}}^2 f_{k'_1}^2 \dots f_{k'_{N_{\text{in}}}}^2 n_B(\omega_{k'_1}) \dots n_B(\omega_{k'_{N_{\text{in}}}}) \times \\ (1 + n_B(\omega_{k_1})) \dots (1 + n_B(\omega_{k_{N_{\text{out}}}})) 2\pi \delta(\omega_k - \omega_{k'} + \omega_{k'_1} + \dots + \omega_{k'_{N_{\text{in}}}} - \omega_{k_1} - \dots - \omega_{k_{N_{\text{out}}}}), \quad (\text{S24})$$

where this time the sum is restricted to even $N_{\text{out}} + N_{\text{in}} \geq 2$. Repeating the same procedure as before, we find

$$\Gamma_{k'|k}^{\text{in}(1)} = \lambda_0^2 f_k^2 f_{k'}^2 (1 + n_B(\omega_{k'})) \Re \left\{ \int_0^\infty dt e^{i(\omega_k - \omega_{k'})t} \times \exp \left(- \sum_{k'} \left\{ f_{k'}^2 [(1 + n_B(\omega_{k'}))(1 - e^{-i\omega_{k'}t}) + n_B(\omega_{k'})(1 - e^{i\omega_{k'}t})] + \tilde{f}_{k'}^2 - f_{k'}^2 \right\} \right) \right\}. \quad (\text{S25})$$

The integral in Eq. (S25) is very similar to the integral appearing in the self energy $\Pi_R(\omega)$ [Eq. (S23)], but only accounts for absorption of a photon with energy $\omega_k - \omega_{k'}$, whereas $\Pi_R(\omega)$ accounts for both emission and absorption processes. However, the emission rate (which includes an exponential $e^{-i(\omega_k - \omega_{k'})t}$) is equal to the absorption rate times a factor $e^{-(\omega_k - \omega_{k'})/T}$, as one may infer from the corresponding Bose-Einstein factors in Eq. (S18). Therefore, we find $\Gamma_{k'|k}^{\text{in}(1)} = 2f_k^2 f_{k'}^2 (1 + n_B(\omega_{k'}))(1 + n_B(\omega_k - \omega_{k'})) \Im \Pi_R(\omega_k - \omega_{k'})$. The remaining three terms of $\Gamma_{k'|k}^{\text{in}}$ may be derived in a similar fashion. This leads to Eq. (11) of the main text:

$$\Gamma_{k'|k}^{\text{in}} = 2f_k^2 f_{k'}^2 \{ \Im \Pi_R(\omega_k - \omega_{k'}) [(1 + n_B(\omega_{k'}))(1 + n_B(\omega_k - \omega_{k'})) - n_B(\omega_{k'}) n_B(\omega_k - \omega_{k'})] + \Im \Pi_R(\omega_k + \omega_{k'}) [(1 + n_B(\omega_{k'})) n_B(\omega_k + \omega_{k'}) - n_B(\omega_{k'})(1 + n_B(\omega_k + \omega_{k'}))] \}. \quad (\text{S26})$$




FIG. SF1. (a) On-resonance (mode $k_0 = \omega_0/v$) total photon-instanton inelastic scattering probability $2\pi\Gamma_{k_0}^{\text{in}}/\Delta$ [Eq. (S23)] as function of ω_0/Γ_0 for several values of z at $T = 0$, with the prefactor λ_0^2 excluded. This shows the increased phase space for scattering with increasing ω_0/Γ_0 . (b) Ratio between the $T = 0$ on-resonance probabilities given by the instanton calculation, Eq. (S23), and either the dual cosine approximation, Eq. (S39) (continuous lines) or the first form of the limiting expression, Eq. (S32) (dashed lines).

The rates Γ_k^{in} and $\Gamma_{k'|k}^{\text{in}}$ satisfy an energy conservation sum rule, which may be verified by integration by parts over t in Eq. (S23) for the self energies:

$$\omega_k \Gamma_k^{\text{in}} = \sum_{k'} \omega_{k'} \Gamma_{k'|k}^{\text{in}}. \quad (\text{S27})$$

E. Limiting cases

To address limiting cases, it is useful to examine the behavior of $\Im\Pi_R(\omega)$ at low frequency, $\omega \ll \omega_0$. Here we may use $f_q \sim \sqrt{2\Delta/z\omega_q}$ for $\omega_q \ll \omega_0$ [cf. Eq. (S15)] in Eq. (S23) to obtain [43]

$$\begin{aligned} \Im\Pi_R(\omega) &\approx \frac{1}{2\Gamma(2/z)} \frac{\lambda_0^2}{\omega_c(z)} \left(\frac{2\pi T}{\omega_c(z)} \right)^{2/z-1} \sinh\left(\frac{\omega}{2T}\right) \left| \Gamma\left(\frac{1}{z} + i\frac{\omega}{2\pi T}\right) \right|^2 \\ &\approx \begin{cases} \frac{\pi}{2\Gamma(2/z)} \frac{\lambda_0^2}{\omega_c(z)} \left(\frac{\omega}{\omega_c(z)} \right)^{2/z-1}, & T \ll \omega \ll \omega_0, \\ \frac{\pi[\Gamma(1/z)]^2}{4\Gamma(2/z)} \frac{\lambda_0^2}{\omega_c(z)} \frac{\omega}{\omega_c(z)} \left(\frac{2\pi T}{\omega_c(z)} \right)^{2/z-2}, & \omega \ll T \ll \omega_0, \end{cases} \end{aligned} \quad (\text{S28})$$

where $\Gamma(x)$ is the gamma function [38], and the effective cutoff $\omega_c(z) \approx 0.9\omega_0$ is z independent for $z \lesssim 1$. The first case is Eq. (12) of the main text. We may thus immediately conclude that for $T = 0$ and $\omega_k \ll \omega_0$, using $\Gamma_k^{\text{in}} = 2f_k^2 \Im\Pi_R(\omega_k)$ with $f_k^2 \approx 2\Delta/z\omega_k$ [cf. Eq. (S15)] gives

$$\frac{2\pi\Gamma_{k \ll k_0}^{\text{in}}}{\Delta} \approx \frac{4\pi^2(\omega_0/\omega_c)^{2/z}}{z\Gamma(2/z)} \left(\frac{\lambda_0}{\omega_0} \right)^2 \left(\frac{\omega_0}{\omega_k} \right)^{2-2/z}. \quad (\text{S29})$$

Let us now examine different limiting cases for the inelastic rate for ω_k comparable to ω_0 and at $T = 0$, where Eq. (S26) reduces to $\Gamma_{k'|k}^{\text{in}} = 2f_k^2 f_{k'}^2 \Im\Pi_R(\omega_k - \omega_{k'})$ [extensions to finite $T \ll \omega_0$ are possible based on the general form of Eq. (S28)]. In the following, we assume $\Gamma_0/\omega_0 \rightarrow 0$ and $z > 1$.

When either $|\omega_k - \omega_0| \lesssim \Gamma_0$ or $\omega_0 \gg \omega_k - \omega_0 \gg \Gamma_0$, the main contribution to Eq. (S27) would come from a near-resonance photon at k' . We may then approximate it as $\Gamma_k^{\text{in}} = \sum_{k'} \Gamma_{k'|k}^{\text{in}}$, and note that $f_q^2 \approx \Delta/\pi(\lambda_1/\lambda_0)(\Gamma_0/2)/[(\omega_0 - \omega_q)^2 + (\Gamma_0/2)^2]$ near resonance [here we use the WKB expressions for λ_m , cf. Eq. (S4)]. Furthermore, we may use Eq. (S28) for $\Pi_R(\omega_k - \omega_{k'})$. In addition, we introduce a cutoff ω'_c [generally different than $\omega_c(z)$] which satisfies




FIG. SF2. The distribution of inelastically generated photons $\Gamma_{k'|k}^{\text{in}}/\Gamma_k^{\text{in}}$ at $T = 0$ for (a,b) $\omega_k = \omega_0 - \Gamma_0$; (c,d) $\omega_k = \omega_0$; (e,f) $\omega_k = \omega_0 + \Gamma_0$. In panels (a), (c), and (e) Γ_0/ω_0 varies at fixed $z = 2$, while in panels (b), and (d), (f) z varies at fixed $\Gamma_0/\omega_0 = 0.2$. Continuous lines represent the results of the full expressions, Eqs. (S26) and (S23); dashed lines correspond to the approximation in Eq. (S30), and show that it applies for very small Γ_0/ω_0 and/or large z .

$\omega'_c, \omega_0 - \omega'_c \gg \Gamma_0$ as the lower summation limit, and evaluate the sum over k' as an integral:

$$\frac{2\pi\Gamma_k^{\text{in}}}{\Delta} \approx \frac{2\lambda_1^2(\omega_0/\omega_c)^{2/z}}{\Gamma(2/z)} \frac{(\Gamma_0/2)}{(\omega_0 - \omega_k)^2 + (\Gamma_0/2)^2} \int_{\omega'_c}^{\omega_k} \frac{d\omega_{k'}}{\omega_0} \left(\frac{\omega_k - \omega_{k'}}{\omega_0} \right)^{2/z-1} \frac{(\Gamma_0/2)}{(\omega_0 - \omega_{k'})^2 + (\Gamma_0/2)^2}. \quad (\text{S30})$$

This is equivalent to Eq. (13) in the main text. As shown in Fig. SF2, this is a good approximation for very small Γ_0/ω_0 and/or large z .

For $|\omega_k - \omega_0| \lesssim \Gamma_0$ (k close to $k_0 = \omega_0/v$), we recognize that the leading ω_k dependence comes from the Lorentzian prefactor. Therefore, we set $\omega_k \approx \omega_0$ in the integrand, and replace the lower and upper integration limits by 0 and ω_0 , respectively. Evaluation of the integral then leads to

$$\frac{2\pi\Gamma_{k \sim k_0}^{\text{in}}}{\Delta} \approx \frac{2\pi\Gamma_{k_0}^{\text{in}}}{\Delta} \frac{(\Gamma_0/2)^2}{(\omega_0 - \omega_k)^2 + (\Gamma_0/2)^2}, \quad (\text{S31})$$

with

$$\frac{2\pi\Gamma_{k_0}^{\text{in}}}{\Delta} \approx \frac{2(\omega_0/\omega_c)^{2/z}}{\Gamma(1+2/z)} \frac{\lambda_1^2}{(\Gamma_0/2)^2} {}_2F_1\left(1, \frac{1}{z}, \frac{z+1}{z}; -\frac{4\omega_0^2}{\Gamma_0^2}\right) \approx \frac{\pi(\omega_0/\omega_c)^{2/z}}{\Gamma(2/z) \sin(\pi/z)} \frac{\lambda_1^2}{(\Gamma_0/2)^2} \left(\frac{\Gamma_0/2}{\omega_0}\right)^{2/z}, \quad (\text{S32})$$

where ${}_2F_1(a, b, c; x)$ is the hypergeometric function [38]. The last form relies again on $\Gamma_0/\omega_0 \ll 1$ and $z > 1$, and corresponds to Eq. (14) in the main text. The ratio between the on-resonance value of Γ_k^{in} evaluated using Eq. (S23) and using the first form of Eq. (S32) is displayed in Fig. SF1(b).

For $\omega_0 \gg \omega_k - \omega_0 \gg \Gamma_0$ we start again from Eq. (S30). The leading contribution to the integral comes from $|\omega_{k'} - \omega_0| \lesssim \Gamma_0$. Therefore, we set $\omega_{k'} \approx \omega_0$ in the power-law factor and extend the integration limits to $\pm\infty$. This yields:

$$\frac{2\pi\Gamma_k^{\text{in}}}{\Delta} \approx \frac{2\pi(\omega_0/\omega_c)^{2/z}}{\Gamma(2/z)} \frac{\lambda_1^2 \Gamma_0/2}{\omega_0^3} \left(\frac{\omega_0}{\omega_k - \omega_0} \right)^{3-2/z}. \quad (\text{S33})$$

When $\omega_0 \gg \omega_0 - \omega_k \gg \Gamma_0$, we return to Eq. (S27), drop the $(\Gamma_0 \omega_q)^2$ term in the denominator of f_q^2 , and approximate the sines as linear functions for both $q = k, k'$ [cf. Eq. (S15)]. We then use the low frequency approximation of $\Pi_R(\omega_k - \omega_{k'})$ [Eq. (S28)], extend the lower integration limit to $-\infty$, and approximate $\omega_k/\omega_0 \approx 1$. We then find

$$\frac{2\pi\Gamma_k^{\text{in}}}{\Delta} \approx \frac{2\pi(1-2/z)(\omega_0/\omega_c)^{2/z}}{\sin(2\pi/z)\Gamma(2/z)} \left(\frac{\lambda_1\Gamma_0/2}{\omega_0^2}\right)^2 \left(\frac{\omega_0}{\omega_0 - \omega_k}\right)^{4-2/z}. \quad (\text{S34})$$

Eqs. (S31), (S33), and (S33) are summarized by Eq. (15) in the main text.

SII. THE DUAL COSINE APPROACH

The instanton approach presented in the previous section accounts for the full imaginary time dynamics of the phases along the array during a phase slip. A common phenomenological approach is to approximate a phase slip as an instantaneous 2π shift of all the phases ($\Phi_0 = \pi$ shift of the fluxes) along the array. It has been successfully used in analyzing recent experiments on the system discussed [37]. Here we will review this approach and show that, despite its crudeness, it gives rise to a reasonable approximation for the inelastic decay rate obtained by the full instanton calculation.

In a Hamiltonian formalism, sudden phase slips could be accounted for by supplementing the quadratic Hamiltonian corresponding to the Lagrangian (S5) by a term [2, 3]

$$H^{PS} = \lambda^{PS} \cos\left(\pi \sum_{n=0}^N Q_n\right) = \lambda^{PS} \sum_{m=0}^{\infty} \frac{1}{(2m)!} \left[\sum_q f_q^{PS}(a_q - a_q^\dagger) \right]^{2m}, \quad (\text{S35})$$

where $Q_0 = C_0 \dot{\phi}_0$ and $Q_{n>0} = C_g \dot{\phi}_n$ denote the charge operators along the array, a_q^\dagger (a_q) is the creation (annihilation) operator of a single photon in the array mode q , and where

$$f_q^{PS} = -i \sqrt{\frac{\omega_q}{2C_q}} \left(C_0 \sin(\delta_q) + C_g \sum_{n=1}^N \sin(qn + \delta_q) \right) = \sqrt{\frac{2\Delta}{z\omega_q}} \frac{\omega_0^2}{[(\omega_q^2 - \omega_0^2)^2 + (\Gamma_0 \omega_q)^2]^{1/2}}. \quad (\text{S36})$$

Comparing with Eq. (S15) we can see that at low frequencies, $\omega_q \ll \omega_0$, $f_q^{PS} \approx f_q$, whereas near resonance they differ; at $k_0 = \omega_0/v$ we have $f_{k_0}^{PS}/f_{k_0} = \pi/4$.

The coefficient λ^{PS} needs to be set by the value of a known observable. For the study of nearly-resonant photon scattering it is natural to choose it so that H^{PS} reproduces the charge dispersion of the first excited level of an isolated transmon ($z \rightarrow \infty$ limit of our system), whose free Hamiltonian is $H_0 = \omega_0 a_0^\dagger a_0$. A phase slips operator corresponding to Eq. (S35) would be

$$H_{z \rightarrow \infty}^{PS}(q_g) = \lambda^{PS} \cos(\pi(Q_0 - q_g)), \quad (\text{S37})$$

where $Q_0 = (E_J/2E_C)^{1/4}(a_0 - a_0^\dagger)$ and q_g is the gate charge offset. The first-order correction in perturbation theory to the first excited level is $E_1^{(1)}(q_g) = \langle H_{z \rightarrow \infty}^{PS}(q_g) \rangle_1$, and the half-width of the corresponding Bloch band is given by

$$\lambda_1 = \frac{E_1^{(1)}(q_g = 1) - E_1^{(1)}(q_g = 0)}{2} = -\lambda^{PS} \langle \cos(\pi Q_0) \rangle_1 = \pi^2 \lambda^{PS} \sqrt{\frac{E_J}{2E_C}} e^{-\pi^2 \sqrt{E_J/8E_C}}. \quad (\text{S38})$$

Within the WKB approximation in Eq. (S4) we have $\lambda_1 = -\sqrt{2^7 E_J/E_C} \lambda_0$, hence $\lambda^{PS} = -(4/\pi)^2 e^{\pi^2 \sqrt{E_J/8E_C}} \lambda_0$.

Using the last form of Eq. (S35), it is straightforward to calculate the self energy of a photon at mode k to second order in λ^{PS} as a sum of the contributions of the second-order self energies of each term in the sum over m (including cross terms) [43]. One factor of $f_k^{PS}(a_k - a_k^\dagger)$ is pulled out as an external leg in each term. As usual, the calculation should be done in imaginary frequency space and analytically continued to real frequencies. We then find

$\Gamma_k^{\text{in}} = 2f_k^2 \Im \Pi_R^{PS}(\omega_k)$ with

$$\begin{aligned} \Pi_R^{PS}(\omega_k) &= \sum_{m,m'=0}^{\infty} \frac{i(\lambda^{PS})^2}{(2m+1)!(2m'+1)!} \int_0^{\infty} dt e^{i\omega t} \left\langle \left[\left\{ \sum_q f_q^{PS} (a_q e^{-i\omega_q t} - a_q^\dagger e^{i\omega_q t}) \right\}^{2m+1}, \left\{ \sum_q f_q^{PS} (a_q - a_q^\dagger) \right\}^{2m'+1} \right] \right\rangle \\ &= i(\lambda^{PS})^2 \int_0^{\infty} dt e^{i\omega t} \left\langle \left[\sin \left(\pi \sum_{n=0}^N Q_n(t) \right), \sin \left(\pi \sum_{n=0}^N Q_n(0) \right) \right] \right\rangle \\ &= -(\lambda^{PS})^2 \int_0^{\infty} dt \sin(\omega t) \exp \left(- \sum_{k'} \left\{ (f_{k'}^{PS})^2 [(1+n_B(\omega_{k'}))(1-e^{-i\omega_{k'} t}) + n_B(\omega_{k'})(1-e^{i\omega_{k'} t})] \right\} \right). \quad (\text{S39}) \end{aligned}$$

We see that the result is very similar to the instanton inelastic rate, Eq. (10) of the main text, with the replacements $\lambda_0 \rightarrow \lambda^{PS}$ and $f_k, \tilde{f}_k \rightarrow f_k^{PS}$. An analog of Eq. (11) may be derived as well, following similar steps to those in Sec. SID,

$$\begin{aligned} \Gamma_{k'|k}^{\text{in}} &= 2(f_k^{PS} f_{k'}^{PS})^2 \{ \Im \Pi_R^{PS}(\omega_k - \omega_{k'}) [(1+n_B(\omega_{k'}))(1+n_B(\omega_k - \omega_{k'})) - n_B(\omega_{k'}) n_B(\omega_k - \omega_{k'})] \\ &\quad + \Im \Pi_R^{PS}(\omega_k + \omega_{k'}) [(1+n_B(\omega_{k'})) n_B(\omega_k + \omega_{k'}) - n_B(\omega_{k'})(1+n_B(\omega_k + \omega_{k'}))] \}. \quad (\text{S40}) \end{aligned}$$

Interestingly, although f_q^{PS} differs from f_q, \tilde{f}_q near resonance, and λ^{PS} differs from λ_0 , the inelastic rates resulting from Eqs. (S26) and (S40) are similar. Indeed, for $\omega_k, \omega_{k'} \approx \omega_0$, when calculating $\Pi_R^{PS}(\omega_k - \omega_{k'})$ using Eq. (S23), only low-frequency modes contribute to the sum inside the exponent (see the discussion in Sec. SIE above). Similar considerations apply to the last line of Eq. (S39) in this regime, except for a relative factor $e^{\sum_{k''} (f_{k''}^{PS})^2 - \tilde{f}_{k''}^2}$, which is dominated by near resonance modes [at low frequencies $f_q^{PS} \approx f_q \approx \tilde{f}_q$, cf. Eqs. (S36), (S15), and (S11)]. Hence, collecting all the results of this section, the ratio of Eqs. (S40) and (S26) is

$$\begin{aligned} \frac{(f_k f_{k'})^2 \Im \Pi_R(\omega_k - \omega_{k'})}{(f_k^{PS} f_{k'}^{PS})^2 \Im \Pi_R^{PS}(\omega_k - \omega_{k'})} &\approx \left(\frac{f_{k_0} f_{k_0}}{f_{k_0}^{PS} f_{k_0}^{PS}} \frac{\lambda_0}{\lambda^{PS}} \right)^2 e^{\sum_{k''} (f_{k''}^{PS})^2 - \tilde{f}_{k''}^2} \\ &\approx \left(\frac{4}{\pi} \frac{4}{\pi} \frac{\pi^2}{16} e^{-\pi^2 \sqrt{E_J/8E_C}} \right)^2 \exp \left[\sum_{k''} \frac{\Delta \omega_0}{2z} \frac{1}{(\omega_0 - \omega_{k''})^2 + (\Gamma_0/2)^2} \right] \approx 1. \quad (\text{S41}) \end{aligned}$$

Correspondingly, the ratio between the on-resonance instanton total inelastic rate [Eq. (S23)] and the dual cosine total inelastic rate [Eq. (S39)] is close to unity, as shown in Fig. SF1(b).

III. DERIVATION OF THE QUARTIC NONLINEARITY INELASTIC RATE

In this section we give some additional details regarding the derivation of the quartic nonlinearity inelastic rate, given by Eq. (16) of the main text. Here the quadratic Hamiltonian corresponding to the Lagrangian (S5) is supplemented by the quartic term in the Taylor expansion of the transmon Josephson cosine, $H^{(4)} = -2E_J \phi_0^4/3$. The latter may be expressed in terms of the creation and annihilation operators of the eigenmodes (a_k^\dagger and a_k , respectively, for mode k):

$$H^{(4)} = -\frac{2E_J}{3} \sum_{k_1, k_2, k_3, k_4} \prod_{i=1}^4 f_{k_i}^{(4)} (a_{k_i} + a_{k_i}^\dagger), \quad (\text{S42})$$

where $f_k^{(4)} = \sin(\delta_k)/\sqrt{2C_k \omega_k}$ are the form factors. Expansion of Eq. (S42) yields terms with different numbers of creation and annihilation operators, which give rise to $1 \rightarrow 3$ (a single annihilation operator), $2 \rightarrow 2$ and $3 \rightarrow 1$ photon processes. The inelastic rate may then be calculated for each of these processes using the Fermi golden rule. Summing up the results gives

$$\begin{aligned} \Gamma_k^{\text{in}} &= \frac{4z^2}{3\pi} \frac{\omega_0^4 \Delta^4}{\Gamma_0^2} \frac{\sin^2(\delta_k)}{\omega_k} \sum_{k_1, k_2, k_3} \frac{\sin^2(\delta_{k_1})}{\omega_{k_1}} \frac{\sin^2(\delta_{k_2})}{\omega_{k_2}} \frac{\sin^2(\delta_{k_3})}{\omega_{k_3}} \delta(\omega_k + \omega_{k_1} - \omega_{k_2} - \omega_{k_3}) \times \\ &\quad [(1+n_B(\omega_{k_1}))(1+n_B(\omega_{k_2}))(1+n_B(\omega_{k_3})) + n_B(\omega_{k_1})(1+n_B(\omega_{k_2}))(1+n_B(\omega_{k_3})) + n_B(\omega_{k_1})n_B(\omega_{k_2})(1+n_B(\omega_{k_3}))], \quad (\text{S43}) \end{aligned}$$

where the three terms in the square brackets on the last line correspond to $1 \rightarrow 3$, $2 \rightarrow 2$ and $3 \rightarrow 1$ scattering, respectively. At $T = 0$ only the $1 \rightarrow 3$ process contributes,

$$\Gamma_k^{\text{in}} = \frac{4z^2}{3\pi} \frac{\omega_0^4 \Delta^4}{\Gamma_0^2} \frac{\sin^2(\delta_k)}{\omega_k} \sum_{k_1, k_2, k_3} \frac{\sin^2(\delta_{k_1})}{\omega_{k_1}} \frac{\sin^2(\delta_{k_2})}{\omega_{k_2}} \frac{\sin^2(\delta_{k_3})}{\omega_{k_3}} \delta(\omega_k - \omega_{k_1} - \omega_{k_2} - \omega_{k_3}), \quad (\text{S44})$$

which is Eq. (16) of the main text. Turning the sums into integrals, and accounting for the delta function, one finds

$$\Gamma_k^{\text{in}} = \frac{4\Delta z^2 \omega_0^4 \Gamma_0^6}{3\pi} \frac{\omega_k}{(\omega_0^2 - \omega_k^2)^2 + (\Gamma_0 \omega_k)^2} \int_0^{\omega_k} d\omega_1 \int_0^{\omega_k - \omega_1} d\omega_2 \frac{\omega_1}{(\omega_0^2 - \omega_1^2)^2 + (\Gamma_0 \omega_1)^2} \frac{\omega_2}{(\omega_0^2 - \omega_2^2)^2 + (\Gamma_0 \omega_2)^2} \frac{\omega_k - \omega_1 - \omega_2}{(\omega_0^2 - (\omega_k - \omega_1 - \omega_2)^2 + (\Gamma_0(\omega_k - \omega_1 - \omega_2))^2)^2}. \quad (\text{S45})$$

The inelastic rate may be evaluated explicitly for a nearly-resonant incoming photon, $|\omega_k - \omega_0| \lesssim \Gamma_0$ (k close to $k_0 = \omega_0/v$). In this case the outgoing photons are all far from resonance. Hence, we may approximate the form factors inside the integrals by dropping the terms proportional to Γ_0^2 in the denominators. The form factor of the incoming photon may be approximated by a Lorentzian with width $\Gamma_0/2$. The dominant part of the ω_k dependence is captured by this Lorentzian, hence we replace $\omega_k \approx \omega_0$ inside the integrals. The inelastic rate then becomes

$$\frac{2\pi \Gamma_{k \sim k_0}^{\text{in}}}{\Delta} \approx \frac{128c_0 z^2}{3} \left(\frac{\Gamma_0/2}{\omega_0} \right)^4 \frac{(\Gamma_0/2)^2}{(\omega_0 - \omega_k)^2 + (\Gamma_0/2)^2}, \quad (\text{S46})$$

with

$$c_0 = \int_0^1 dx_1 \int_0^{1-x_1} dx_2 \frac{x_1}{(1-x_1^2)^2} \frac{x_2}{(1-x_2^2)^2} \frac{1-x_1-x_2}{(1-(1-x_1-x_2)^2)^2} \approx 0.026. \quad (\text{S47})$$
