Nuclear two point correlation functions on a quantum computer

A. Baroni,¹ J. Carlson,¹ R. Gupta,¹ Andy C. Y. Li,² G. N. Perdue,² and A. Roggero^{3,4,5}

¹ Theoretical Division, Los Alamos National Laboratory, Los Alamos, NM 87545, USA

²Fermi National Accelerator Laboratory, Batavia, IL, 60510, USA

³Physics Department, University of Trento, Via Sommarive 14, I-38123 Trento, Italy

⁴INFN-TIFPA Trento Institute of Fundamental Physics and Applications, Trento, Italy

⁵InQubator for Quantum Simulation (IQuS), Department of Physics,

University of Washington, Seattle, WA 98195, USA

The calculation of dynamic response functions is expected to be an early application benefiting from rapidly developing quantum hardware resources. The ability to calculate real-time quantities of strongly-correlated quantum systems is one of the most exciting applications that can easily reach beyond the capabilities of traditional classical hardware. Response functions of fermionic systems at moderate momenta and energies corresponding roughly to the Fermi energy of the system are a potential early application because the relevant operators are nearly local and the energies can be resolved in moderately short real time, reducing the spatial resolution and gate depth required.

This is particularly the case in quasielastic electron and neutrino scattering from nuclei, a topic of great interest in the nuclear and particle physics communities and directly related to experiments designed to probe neutrino properties. In this work we use current quantum hardware and error mitigation protocols to calculate response functions for a highly simplified nuclear model through calculations of a 2-point real time correlation function for a modified Fermi-Hubbard model in two dimensions with three distinguishable nucleons on four lattice sites.

I. INTRODUCTION

Quantum computing holds the promise of enabling calculations of the real-time evolution of quantum systems, with a wide range of applications across many areas of physics including electronic many-body problems, condensed matter, cold atom, nuclear and particle physics. Quantum dynamics with more than a few particles easily exceeds the capabilities of traditional computers because of the extremely large number of basis states and the oscillatory nature of the path integrals involved in evaluating cross sections and transition rates. In specific cases such as low-energy resonance scattering and high-energy semi-classical approaches, valuable information can be gained with classical computers [1, 2]. Quantum computing, though, has the potential to perform calculations of quantum dynamics beyond the reach of classical computing.

The linear response of quantum systems is a promising candidate for early applications of quantum computers [3]. Linear response, as measured for example in neutron scattering from materials or electron and neutrino scattering from nuclei directly probes the structure and dynamics of the underlying system. By adjusting the momentum and energy transfer one can focus on different scales. Even seemingly simple cases, where the transfers are of the order of the Fermi momentum, can yield rich physics. While at larger momentum transfers the response is largely a function of the momentum distribution or spectral function of the target [4, 5], at more modest momenta two-nucleon physics including two-nucleon currents, correlations, and charge exchange can become quite important [2, 6-8]. These effects can play a role, for example, when trying to measure neutrino properties through neutrino-nucleus scattering in experiments including MiniBooNE, MicroBooNE, T2K and DUNE [7].

The linear response function for a specific quantum state (often the ground state) is defined as:

$$S(\omega, \mathbf{q}) = \sum_{f} |\langle \Psi_0 | O(\mathbf{q}) | f \rangle|^2 \delta(\omega - (E_f - E_0)) , \quad (1)$$

where $|\Psi_0\rangle$ describes the ground state with energy E_0 , the sum includes all final states $|f\rangle$ with energy E_f , ω and **q** denote respectively the energy and the threemomentum transfer injected in the system by the external probe, and the operator $O(\mathbf{q})$ describes the coupling of the system to the external probe. For electron scattering from nuclei there are two response functions describing the longitudinal (charge) and transverse (current) components of the response [9]. For neutrino scattering there are five response functions for a given momentum and energy transfer, the cross section is given by a linear combination of these response functions that depend upon geometry (e.g. the lepton scattering angle) and the particle (e.g. electron, neutrino, or anti-neutrino) being scattered [10]. The response functions govern the inclusive cross section where all final scattering states are summed over and only the lepton kinematics is specified.

Equivalent information is available from the Fourier transform of the relativistic two-point correlation function in real time τ :

$$S_M(q_0, \mathbf{q}) = \int d^4 x e^{iqx} \langle \Psi_0 | O^{\dagger}(\tau, \mathbf{x}) O(0, 0) | \Psi_0 \rangle , \quad (2)$$

which in the non-relativistic limit is the same as the real-time equivalent of Eq. (1), ie, $S_M(q_0, \mathbf{q}) \rightarrow S(\omega, \mathbf{q})$. Classical simulations in discrete Euclidean time τ_E , for example of lattice QCD, give an analogous two-point correlation function:

$$C_E(\tau_E, \mathbf{q}) = \sum_{\mathbf{x}} e^{i\mathbf{q}\cdot\mathbf{x}} \langle \Psi_0 | O^{\dagger}(\tau_E, \mathbf{x}) O(0, 0) | \Psi_0 \rangle, \quad (3)$$

where in both cases the operator O can be the electromagnetic current. We recall that C_E and S_M are related through the following Laplace transform $C_E(\tau_E, \mathbf{q}) =$ $\int d\tau_E e^{-q_0 \tau_E} S_M(q_0, \mathbf{q})$. The problem of obtaining S_M from C_E is in general an ill-posed problem. The lattice calculation can be done only at a finite number of discrete values of τ_E with the data having errors that typically grow very rapidly with τ_E . These errors get exponentially amplified by the inversion procedure. Various techniques have been developed in order to obtain good approximations of the frequency response S_M starting from euclidean data [11–15]. These approaches are often able to reconstruct signals with simple structure, such as a quasi elastic peaks which are composed of one broad peak [6], or observables that can be recast directly into euclidean time like transport coefficients dominated by zero frequency modes (see eg. [16]), but the systematic errors are difficult to assess reliably in the general case.

Quantum computers could perform simulations in realtime, however, a number of challenges needs to be solved such as the preparation of the ground state $|\Psi_0\rangle$, the application of the operator O, the evolution of the system for time τ long compared to the relevant energy scale, $1/q_0$, of the calculation while preserving coherence, and lastly transitioning back to the ground state through the second insertion of the excitation operator O. This work is a step in that direction.

In traditional approaches to the non-relativistic response, an integral transform of the response is calculated (such as Laplace, Lorentz or Gaussian, see e.g. [6, 17– 21]). The imaginary-time two point function is calculated in Quantum Monte Carlo approaches, and is equivalent to the non-relativistic limit of lattice QCD evalutations.

At high energy and momenta, the response can also be calculated through local properties of the initial state (momentum distribution or spectral function) [4, 5], short-time expansions of the nuclear propagation [2]. The single-particle Green's function yields information on this response, while the short-time approximation incorporates the coupling and propagation of pairs of nucleons in the final state. The short-time approach guarantees that the calculated response reproduces the energy independent and energy-weighted sum rules $E_0(\mathbf{q})$ and $E_{m>0}(\mathbf{q})$ defined as:

$$E_m(\mathbf{q}) = \langle \Psi_0 | O^{\dagger}(\mathbf{q}) H^m O(\mathbf{q}) | \Psi_0 \rangle, \qquad (4)$$

where H^m is the Hamiltonian to the mth power, and is available from a Taylor expansion of the real or imaginary-time response at short times. Including the two-particle ladders in the propagation reproduces reasonably well quasi-elastic scattering in simple test cases; it is equivalent to one sophisticated Trotter step in the real-time evolution as described in Ref. [2]. This approach provides a natural explanation for the scaling with momentum and nuclear system size observed in electron scattering [2]. Quantum computers, though, can, in principle, follow the real-time evolution of the system over larger distances and longer times, enabling reconstruction of the response at lower momenta and energies. They may also be used to calculate cross sections to explicit final states, a much more challenging task on even future quantum hardware [22].

In this paper we study two-point functions of a simple nuclear model, first introduced in Ref. [23], using current quantum hardware, and recently developed error mitigation strategies [24, 25].

II. LATTICE MODEL AND RESPONSE FUNCTION

We follow the approach originally developed in Ref. [23], where we considered a model for the triton nucleus on a two-dimensional lattice with periodic boundary conditions, with two dynamical nucleons and one static particle on a specific lattice site. The model considered is equivalent to a two species Hubbard model with two- and three- body interactions. At the leading order in pion-less Effective Field Theory [26], the Hamiltonian describing the low energy dynamics of a system of nucleons discretized on a lattice can be expressed as follows [23, 26, 27]

$$H = -t \sum_{f=1}^{N_f} \sum_{\langle i,j \rangle} c_{i,f}^{\dagger} c_{j,f} + U \sum_i \sum_{f < f'}^{N_f} n_{i,f} n_{i,f'} + V \sum_{f < f' < f''} \sum_i n_{i,f} n_{i,f'} n_{i,f''},$$
(5)

where the particle number operator $n_{i,f} = c_{if}^{\dagger} c_{if}$, with c_{if} the destruction operator at site *i* of species *f*. The kinetic energy (or hopping term) in the first line contains a sum $\langle i, j \rangle$ over nearest-neighbor sites on the lattice. This corresponds to a generalized Hubbard model with N_f fermionic species and the addition of an on-site repulsive three-body interaction. For applications in nuclear physics one typically considers $N_f = 4$ fermionic species corresponding to neutrons and protons in both spin projections. The numerical values of the couplings t, U and V are reported in table 1 of Ref. [23] (taken from [28]) and correspond to a lattice spacing of 1.4 fm.

Similarly to Ref. [23] we will also introduce an additional local term on site 1 of the lattice given by

$$H_{site} = U \sum_{f=1}^{N_f} n_{1,f} + V \sum_{f < f'} n_{1,f} n_{1,f'}, \qquad (6)$$

with the same V and U used in the general model of Eq. (5). As explained in Ref. [23], this additional interaction term mimics the presence of an additional particle at that spatial site that is treated statically. In order to describe scattering process with external probes, like neutrino-nucleus scattering, we now resort to linear response theory. We consider an interaction of the system described by the Hamiltonian in Eq. (5) with an external 'weak' probe injecting momentum

$$\mathbf{q}_k = \frac{\pi}{L} \left(x_k, y_k, z_k \right) \,, \tag{7}$$

with L the spatial length of the lattice in 3 dimensions and x_k, y_k, z_k positive integer numbers denoting the location of site k on the reciprocal lattice. In this initial exploration we seek to describe probes that couple to the nucleon density as in neutron scattering or a part of the nuclear longitudinal response and described by the following interacting Hamiltonian

$$H_I(\mathbf{q}_k) = \sum_{f=1}^{N_f} \rho_f(\mathbf{q}_i) = \sum_{f=1}^{N_f} e_f \sum_i e^{i\mathbf{q}_k \cdot \mathbf{r}_i} n_{i,f} \,, \quad (8)$$

where $\mathbf{r}_i = (x_i, y_i, z_i)$ denotes the location of site *i* on the spatial lattice, ρ_f and e_f denote respectively the charge density operator and the charge for the species *f*. We notice that from now on we will use the symbol H_I to represent what we denoted with *O* in Eq. (1) as the excitation operator. We consider the system to be initially in its ground state $|\Psi_0\rangle$ and, in the linear response regime, the probability to transition to all the final states $|n\rangle$ can be obtained using Fermi's golden rule

$$S(\omega, \mathbf{q}_k) = \sum_{n} \left| \langle \Psi_0 \right| H_I(\mathbf{q}_k) \left| n \right\rangle \right|^2 \delta(E_n + \omega - E_0), (9)$$

analogue of Eq. (1). We recall now the known identity

$$S(\omega, \mathbf{q}_k) = \int_{-\infty}^{\infty} \frac{d\tau}{2\pi} e^{i\omega\tau} \langle \Psi_0 | H_I(\tau, \mathbf{q}_k) H_I(\mathbf{q}_k) | \Psi_0 \rangle$$
$$= \int_{-\infty}^{\infty} \frac{d\tau}{2\pi} e^{i\omega\tau} C(\tau, \mathbf{q}_k) , \qquad (10)$$

relating the response function in frequency to a two-point time correlation function $C(\tau, \mathbf{q}_k)$. This definition uses $H_I(\tau, \mathbf{q}_k) = e^{iH\tau} H_I(\mathbf{q}_k) e^{-iH\tau}$ as the interacting Hamiltonian in the Heisenberg picture. One of the goals of the present work is to study the feasibility of reconstructing the frequency response $S(\omega, \mathbf{q}_k)$ from a (possibly noisy) estimate of the correlation function $C(\tau, \mathbf{q}_k)$ defined above. This is a classic problem in linear response theory and efficient quantum algorithms have been developed in the past for the calculation of the response function through both real-time simulations [29-31] and by direct sampling in frequency space [22, 32]. Recent work also proposed quantum algorithms to study directly Green's functions [33, 34]. In this work, we estimate the two-point function $C(\tau, \mathbf{q}_k)$ directly with a quantum simulation of a small system using current generation superconducting devices. We use an efficient algorithm originally proposed in Ref. [29] that requires one additional

ancilla qubit and the possibility to apply the interaction Hamiltonian $H_I(\mathbf{q}_k)$ controlled on the ancilla state. This requires $H_I(\mathbf{q}_k)$ to be unitary, but the scheme can be easily generalized to interactions that admit a short expansion into unitaries as we do for our example model described in the next section.

A. Real time correlation functions

The quantity that we will calculate in the following is the real time response function defined by the r.h.s. of Eq. (10) explicitly reported below in a compact notation

$$C(\tau, \mathbf{q}_k) = \langle \Psi_0 | U^{\dagger}(\tau) H_I(\mathbf{q}_k) U(\tau) H_I(\mathbf{q}_k) | \Psi_0 \rangle$$

= $\langle U^{\dagger}(\tau) H_I(\mathbf{q}_k) U(\tau) H_I(\mathbf{q}_k) \rangle$, (11)

with $U(\tau) = e^{-iH\tau}$ the real time evolution operator. We can express the interacting Hamiltonian, after a mapping to qubits, as a sum of Pauli operators

$$H_I(\mathbf{q}_k) = \sum_{i=1}^{L} \alpha_i(\mathbf{q}_k) P_i , \qquad (12)$$

with $P_i \in \{\mathbb{1}, X, Y, Z\}^{\otimes n}$ tensor products of Pauli matrices. The two point function can then be expressed as

$$C(\tau, \mathbf{q}_k) = \sum_{i,i'=1}^{L} \alpha_{i'}(\mathbf{q}_k) \alpha_i(\mathbf{q}_k) s_{i',i}(\tau), \qquad (13)$$

where, for convenience, we have defined the following matrix elements

$$s_{i',i}(\tau) \equiv \langle \Psi_0 | V_{i'i}(\tau) | \Psi_0 \rangle , \qquad (14)$$

with $V_{i'i}(\tau) = U^{\dagger}(\tau)P_{i'}U(\tau)P_i$. As explained in Ref. [29] the above quantity can be evaluated using the Hadamard test for the unitary operators $V_{i'i}$ and using gate identities we can write



where we have in principle two controlled and two anticontrolled unitary operations. Using the fact that a controlled and anti-controlled of the same unitary is equivalent to a single unitary acting only on the target qubits, as stated in Ref. [29], we have



The anti-controlled gate (i.e. a gate applied when the ancilla is in $|0\rangle$) may be expressed in terms of a controlled gate (i.e. a gate applied when the ancilla is in $|1\rangle$) used conjugation with the X gate



This modification is useful since it is often the case that gate libraries of current quantum devices have a controlled gate instead of an anti-controlled gate. In addition, the last X gate can be avoided by appropriately redefining the measurement operators.

As first noted in Ref. [29] the following quantum circuit allows us to compute $s_{i',i}(\tau)$ using only controlled Pauli operators and the application of one unitary transformation dependent on the time t, leading therefore to significantly shorter gate depths than a direct implementation of the circuit reported in Eq. (15). Measuring the ancillary qubit in the basis corresponding to the eigenstates of the three Pauli matrices leads to

$$\langle X \rangle = \mathcal{R}e\left(s_{i'i}(\tau)\right), \quad \langle Y \rangle = -\mathcal{I}m\left(s_{i'i}(\tau)\right), \quad (18)$$

and it is easy to see that $\langle Z \rangle = 0$. We notice that the total number of measurements necessary to obtain the above result with *statistical* precision ϵ is bounded by

$$N \leq \frac{L^2}{\epsilon^2} \max_k ||\overline{H_I(\mathbf{q}_k)}||_2^4 \leq \frac{L^4}{\epsilon^2} \max_k \max_i |\alpha_i(\mathbf{q}_k)|^4 (19)$$

where we have defined, similarly to Ref. [23], the following expression

$$||\overline{H_I(\mathbf{q}_k)}||_q = \left(\sum_{i=1}^L |\alpha_i(\mathbf{q}_k)|^q\right)^{1/q}, \quad \text{for } q \ge 1.$$
 (20)

A proof of this result may be found in Appendix C1. The strong scaling with the number of terms can be mitigated in a number of different ways. On a fault-tolerant quantum device one can obtain $\mathcal{O}(L/\epsilon)$ using amplitude estimation [35, 36] by trading the number of repetitions with a comparable increase in the gate depth. One can also completely remove the L dependence from the number of measurements by directly applying the interacting Hamiltonian H_I , controlled by the ancila qubit in the circuit diagrams above. Alternately, one can implement the sum in Eq. (12) using the "linear combination of unitaries (LCU)" algorithm [37] and performing the quantum control on the PREPARE unitary instead (see also [25]). Of course, these two techniques can be combined together to obtain the benefits of both. The quantity we actually calculate on a quantum computer is

$$\widetilde{C}(\tau, \mathbf{q}_k) = \langle \Psi | V^{\dagger}(\tau) H_I(\mathbf{q}_k) V(\tau) H_I(\mathbf{q}_k) | \Psi \rangle , \quad (21)$$

where $|\Psi\rangle$ is an approximation of the exact ground state $|\Psi_0\rangle$ with fidelity F and $V(\tau)$ is a generic approximation of the time evolution which can be chosen such that

$$\|U(\tau) - V(\tau)\| \le \frac{\epsilon(\tau)}{2}.$$
 (22)

We can therefore bound the difference between the ideal response function and the approximate one as

$$|C(\tau, \mathbf{q}_k) - \widetilde{C}(\tau, \mathbf{q}_k)| \le \|\overline{H_I(\mathbf{q}_k)}\|_1^2 \left(\epsilon(\tau) + \sqrt{1-F}\right), \quad (23)$$

where we have defined

$$F = |\langle \Psi | \Psi_0 \rangle|^2 , \qquad (24)$$

and a proof of this bound is provided in Appedix C2.

III. LATTICE MODEL MAPPED TO QUBITS

The model defined in Eq. (5) can be mapped to qubits in various ways as described in Ref. [23] (see also [38] for an alternative based on the Gray code). In the following we will consider the case of two flavors and four lattice sites, with the first quantization mapping already employed in Ref. [23] and that we report here for completeness

$$|1\rangle = |\uparrow\uparrow\rangle$$
, $|3\rangle = |\downarrow\uparrow\rangle$, $|3\rangle = |\uparrow\downarrow\rangle$, $|4\rangle = |\downarrow\downarrow\rangle$.

We notice that with the mapping above we use 2 qubits for each of the two particles to store their lattice site. Using this mapping in the 4 qubit Hilbert space, the Hamiltonian operator from Eq. (5) with the addition of the static contribution from Eq. (6) takes the form

$$H = 8t + \frac{U}{2} - 2t \sum_{k=1}^{4} X_k$$

- $\frac{U}{4} (Z_1 Z_4 + Z_2 Z_3) - \frac{U}{4} \sum_{i < j < k} Z_i Z_j Z_k,$ (25)

when mapped to qubits, the interacting Hamiltonian of interest from Eq. (8) becomes

$$H_{I}(\mathbf{q}_{k}) = \sum_{f \in \{A,B\}} e_{f} \left[a_{0}(\mathbf{q}_{k}) + a_{1}(\mathbf{q}_{k}) Z_{1} + a_{2}(\mathbf{q}_{k}) Z_{2} + a_{3}(\mathbf{q}_{k}) Z_{3} \right],$$
(26)

where explicit expressions of the coefficients $a_i(\mathbf{q}_k)$ are reported in Appendix A. The initial state preparation follows the approach in Ref. [23] and has a numerically exact fidelity relative to the exact ground state of 96.2% using the definition of fidelity reported in Eq.(24).

The calculation of Eq. (11) requires the implementation of approximations of the time evolution operator leading to the approximate two-point function reported in Eq. (21). In this work we will use first order Trotter-Suzuki approximations. We define the following three Hamiltonians (using *bd* as abbreviation for body)

$$H_{A}^{(1bd)} \equiv -2t \sum_{k=1}^{4} X_{k} ,$$

$$H_{A}^{(2bd)} \equiv -\frac{U}{4} (Z_{1}Z_{4} + Z_{2}Z_{3}) ,$$

$$H^{(3bd)} \equiv -\frac{U}{4} \sum_{i < j < k} Z_{i}Z_{j}Z_{k} .$$

(27)

We recall that the time evolution for each of these Hamiltonians can be decomposed exactly into one- and twoqubit gates using fundamental circuit identities [23] (see also [39] for general constructions). We can explicitly check that the total number of first-order Trotter-Suzuki splitting is four and we will group them in two categories



FIG. 1. Real and imaginary parts of the response function at different lattice sites using time orderings A1, A2, B1 and B2 compared against the numerically exact calculation, for the problem described in the text. The top panels are for $\mathbf{q} = (0, 1)$ while the bottom panels are for $\mathbf{q} = (1, 1)$.

called A and B and defined as following. We will indicate as A time orderings the following decompositions

$$U_{A1}(\tau) = e^{-iH_A^{(1bd)}\tau} e^{-iH_A^{(2bd)}\tau - iH^{(3bd)}\tau}, \qquad (28)$$

$$U_{A2}(\tau) = e^{-iH_A^{(2bd)}\tau - iH^{(3bd)}\tau} e^{-iH_A^{(1bd)}\tau}, \qquad (29)$$

and we note that the two-body and three-body part commute. For the remaining two time orderings, it is convenient to define the following Hamiltonians

$$H_B^{(i,j)} = -2t(X_i + X_j) - \frac{U}{4}Z_iZ_j, \qquad (30)$$

where $(i, j) \in \{(1, 4), (2, 3)\}$. The real time evolution operators for the *B* time orderings can be written as

$$U_{B1}(\tau) = e^{-iH_B^{(1,4)}\tau} e^{-iH_B^{(2,3)}\tau} e^{-iH^{(3bd)}\tau}, \qquad (31)$$

$$U_{B2}(\tau) = e^{-iH^{(3bd)}\tau} e^{-iH_B^{(1,4)}\tau} e^{-iH_B^{(2,3)}\tau} .$$
(32)

We notice that the commutator $[H^{(i,j)}, H^{(k,l)}]$ for $i \neq j \neq k \neq l$ is vanishing. We report in Fig. 1 the comparison between the exact and the approximate time evolutions for the problem considered at different lattice sites for the full response functions. We note that for small times all the time orderings seem to be quite close to the exact time evolution. The ordering B2 works better than the others for the imaginary parts of the response function for longer times. We also notice that sums rules are exact for the B-type propagators.

In order to implement the decomposition from Eq. (31) in the circuit shown in Eq. (17) we use the three-body operator derived in Ref. [23] and reported for completeness in Appendix B. We report in Fig. 2, as an example, the two circuits needed to calculate the correlator $\langle Z_1(\tau)Z_3 \rangle$ using the two different time evolutions $U_{B1}(\tau)$ and $U_{B2}(\tau)$. We can obtain similar expressions for the A orderings. The CNOT gate count for the various time orderings and correlators for one Trotter step is reported in Tab. I. We notice here that the fact that term B1 is much more expensive than term B2 can be easily understood looking at Fig. 2. As it can be seen for the ordering B2the diagonal three-body term commutes with the second controlled Z gate and can therefore be removed, while for the ordering B1 this simplification is not possible.

A more detailed example of the implementation of the above algorithm for the calculation of the two correlators $\langle Z_1(\tau)Z_3 \rangle$ and $\langle Z_4(\tau)Z_3(\tau)Z_2Z_1 \rangle$ is reported in Appendix B.

IV. RESULTS

We report here results for both the real and imaginary part of the approximate two point correlation functions $\widetilde{C}(\tau, \mathbf{q}_k)$ from Eq. (21) obtained using the IBM five qubit machine Ourense [40]. We used the IBM quantum programming language called Qiskit [41] to implement the above circuits. We applied to the results of the noisy quantum processing units error mitigation protocols developed in Refs. [23]. In particular we first used readout error mitigation with associated error propagation, and then the zero-noise-extrapolation (ZNE) as described in Ref. [23] (see also Refs. [24, 42–44] and the appendices of [25, 45] for more details on our implementation).

The final two point functions at two different values of the momentum transfer are shown in Figs. 3–4. We notice that for the real and imaginary part of the two point correlator at momentum transfer $\mathbf{q} = (0, 1)$, the bare results on current quantum hardware deviate only slightly from the numerical results, and the applied error mitigation procedure brings the machine results very close to the numerical ones. In particular we notice that the time ordering A2 and B2 lead to better agreement with the numerical calculations with respect to their counterparts A1 and B1. The higher infidelity could have been anticipated by noticing the different CNOT gate count (higher for the orderings A1 and B1 compared to the orderings A2 and B2, see Tab. I). We also notice that the first order Trotter approximation used here is a good approximation for the exact time evolution for times around 0.1 - 0.2 (see results in Fig. 1), however, in an actual calculation aimed at reproducing the exact time evolution higher order Trotter formulas should be

	A1	A2	B1	B2
$\langle Z_1(\tau)Z_1\rangle$	19	6	26	8
$\langle Z_1(\tau)Z_3\rangle$	25	9	28	11
$\langle Z_1(\tau)Z_2(\tau)Z_3Z_4\rangle$	25	15	28	15
$\langle Z_1(\tau)Z_2(\tau)Z_1Z_2\rangle$	30	9	29	13
$\langle Z_1(\tau)Z_2(\tau)Z_1Z_2\rangle$	30	9	29	13

TABLE I. CNOT gate count for the implementation of the two-point function calculation using different decompositions of the time evolution operator. Different rows correspond to different operator structures (see Appendix A for details).



FIG. 3. Real and imaginary parts of the response function wave-vector $\mathbf{q} = (0, 1)$ using time ordering A1, A2 (left panel) and B1, B2 (right panel) obtained from the five qubit machine Ourense [40]. For the Trotterized time evolution, black lines, green and red dots denote the numerically exact result, the bare estimate from the QPU and the error mitigated results, respectively. The dashed grey line represents the exact dynamics with no time step errors.

used. The calculation of the real response function at momentum transfer $\mathbf{q} = (1, 1)$ shows more discrepancies with numerically exact results, and in particular for the imaginary part the mitigated hardware results are significantly different from the exact ones. In order to asses the quality of the above runs, similarly to what has been done in Ref.[25], we introduce the following error metrics, the chi squared and the normalized sum of squared deviations (nssd), defined respectively as

$$\chi^{2}(\mathbf{q}_{k}) = \sum_{l=1}^{N} \frac{\left[C^{(t)}(\tau_{l}, \mathbf{q}_{k}) - C^{(e)}(\tau_{l}, \mathbf{q}_{k})\right]^{2}}{\left[\Delta C(\tau_{l}, \mathbf{q}_{k})\right]^{2}}, \quad (33)$$

$$\operatorname{nssd}(r, \mathbf{q}_{k}) = \sqrt{\frac{\sum_{l=1}^{N} \left[C^{(t)}(\tau_{l}, \mathbf{q}_{k}) - C^{(e)}(\tau_{l}, \mathbf{q}_{k})\right]^{2}}{\sum_{l=1}^{N} [rC^{(t)}(\tau_{l}, \mathbf{q}_{k})]^{2}}}, \quad (34)$$

where N is the number of time steps used, and $C^{(e)}(\tau_l, \mathbf{q}_k)$ and $C^{(t)}(\tau_l, \mathbf{q}_k)$ denote respectively the exact theoretical and the experimental results. These two error metrics serve two distinct purposes: the χ^2 is used as an indication that the error estimation is appropriate and large values indicate a residual component of unaccounted systematic error, the *nssd* metric instead is use-

ful to understand the performance of the error mitigation routine in reproducing the centroid of the distribution of the observables. In the following we use for nssd a value of r = 0.1 that denotes a 10% relative error. We first discuss the real and imaginary time correlation function at momentum transfer $\mathbf{q} = (0, 1)$ reported in Table II. The value of the error mitigated χ^2 is between 10 and 50 times smaller than the corresponding bare (unmitigated value). For the nssd metric instead the mitigated value is between > 1 and 5 times smaller than the unmitigated ones. This suggests that the error mitigation techniques in this case favors the improvement of the dispersion of the results. We also notice that the worst performing ordering, i.e. with corresponding higher error metrics, is B1 for both cases and that can be explained by the high gate depth of its implementation. We can now discuss the quality metrics for the real and imaginary part of the correlator at momentum transfer $\mathbf{q} = (1, 1)$. While the error mitigated values of both χ^2 and nssd experience a reduction with respect to the bare values similar to the previous case, the final mitigated numbers are much higher. We notice that the calculation of the two-point function at momentum transfer $\mathbf{q} = (1, 1)$ requires four controlled operations that lead to circuit depths in some



FIG. 4. Real and imaginary parts of the response function wave-vector $\mathbf{q}_1 = (1, 1)$ using time ordering A1, A2 (left panels) and B1, B2 (right panels) ran on the five qubit machine Ourense. Black lines, green and red dots denote respectively the expected result, the bare estimate from the QPU and the error mitigated results. The dashed grey line represents the exact dynamics with no time step errors.

cases slightly higher than the case where only two controlled operations were required. The imaginary part, in this case, shows the highest values for both the error metrics used. Similar results have been obtained using other five qubit machines such as Vigo. Also, these calculations were done over several months and the results did not change. The ordering A2 seems overall to provide an imaginary correlation function closer to the numerically exact one and this is related to the low gate count of the associated circuits used for the calculation. The second ordering that performs well for the calculation of the imaginary response is B2 (which corresponds to the circuits with the second smallest CNOT count). We finally arrive at the remaining orderings A1 and B1, that have comparably high CNOT gate counts and give considerably worse results. However, we notice that the gate count for circuits used to obtain the real and imaginary part differs only of a phase gate and therefore gate count alone cannot explain the fact that the real parts for orderings A1 and B1 show results much more in agreement with the exact calculations than their imaginary counterparts. It is possible that the final state produced by the implemented quantum circuit using gates with limited fidelity has a larger deviation in the Y direction (which we use to measure the imaginary part of the correlator) than in the X direction (used for the real part).

V. FROM THE TIME DOMAIN TO THE FREQUENCY DOMAIN

We consider a quantum circuit similar to the one displayed in Eq. (17) but with an initial time evolution on the target state $|\Psi\rangle$. This leads to the calculation of the following correlator depending on two time variables

$$C(\tau, t) = \langle \Psi | H_I(t) H_I(t+\tau) | \Psi \rangle$$
(35)

where H_I denotes a generic interacting Hamiltonian (where for convenience we left the possible dependence from the momentum transfer implicit, since it is of no interest in the following discussion) in the Heisenberg representation evolved with $U(t) = e^{-iHt}$. We notice that the correlation function of the previous sections is recovered whenever $t = -\tau$. Inserting a complete set of eigenstates $|n\rangle$ of H we get

$$C(\tau, t) = \sum_{n,k,m} \langle \Psi | m \rangle \langle m | H_I | n \rangle \langle n | H_I | k \rangle \langle k | \Psi \rangle$$
$$\times e^{i(E_n - E_k)\tau} e^{i(E_m - E_k)t}, \qquad (36)$$

which allows us to define the following frequency domain version of the correlator $C(\tau, t)$

$$S(\omega) \equiv \int_{-\infty}^{+\infty} \frac{dt}{2\pi} \int_{-\infty}^{+\infty} \frac{d\tau}{2\pi} e^{i\omega\tau} C(\tau, t)$$
(37)
$$= \sum_{n,k,m} \langle \Psi | m \rangle \langle m | H_I | n \rangle \langle n | H_I | k \rangle \langle k | \Psi \rangle$$
$$\times \delta(E_n - E_k + \omega) \delta(E_m - E_k) .$$
(38)

Using the second delta function in the line above we arrive at the following expression for the frequency domain response function

$$S(\omega) = \sum_{n,m} |\langle \Psi | m \rangle \langle m | H_I | n \rangle|^2 \,\delta(E_n - E_m + \omega) \,, \quad (39)$$

where we recall that the above derivation assumes that the delta function over the energies is the same delta function over the states and therefore the states are not degenerate in energy. We notice that in practice the integrals over t and τ are done for finite time and the frequency domain response function reads as

$$\widetilde{C}^{\text{finite}}(\widetilde{\tau}, T, \omega) = \frac{1}{4T\widetilde{\tau}} \int_{-T}^{T} dt \int_{-\widetilde{\tau}}^{\widetilde{\tau}} d\tau e^{i\omega\tau} C(\tau, T) \,. \tag{40}$$

		A1	A2	B1	B2
χ^2	bare	514.14 (472.05)	658.52(716.81)	343.41 (2456.35)	233.65(643.87)
	mit.	11.88(20.43)	64.82(51.19)	75.14(167.15)	30.80(60.96)
nssd	bare	1.36(4.28)	1.60(2.28)	1.71(5.48)	1.44(2.40)
	mit.	0.39(1.96)	0.66(0.94)	1.55(3.67)	1.25(1.39)

TABLE II. Quality metrics for the real and imaginary (in parenthesis) part of the response function with $\mathbf{q} = (0, 1)$ using different time orderings.

		A1	A2	<i>B</i> 1	B2
χ^2	bare	2885.02(13422.84)	3879.64 (5212.32)	11305.15 (11390.61)	9958.04 (9774.88)
	mit.	144.77(1547.30)	99.97(14.79)	320.89(1694.40)	270.56(303.41)
nssd	bare	3.16(15.93)	4.17(5.82)	8.45 (11.78)	7.03(7.05)
	mit.	2.61(12.17)	1.62(0.96)	4.91(9.16)	3.50(4.27)

TABLE III. Quality metrics for the real and imaginary (in parenthesis) part of the response function with $\mathbf{q} = (1, 1)$ using different time orderings.

We notice that in order to achieve a resolution $\Delta \omega$ we have $T \sim 1/\Delta \omega$. In order to perform the above integral we define a grid over times $T(\tau)$ with $(2N_T + 1)\Delta t = 2T$ $((2N_\tau + 1)\Delta \tau = 2\tau)$ time steps. We can then write

$$\widetilde{C}(\widetilde{\tau}, T, \omega) \equiv \frac{\Delta \tau \Delta t}{4T\widetilde{\tau}} \sum_{j=-N_{\tau}}^{N_{\tau}} \sum_{l=-N_{t}}^{N_{t}} e^{i\tau_{j}\omega} C(\tau_{j}, t_{l}), \quad (41)$$

where we used $\tau_j = j\Delta\tau$ and similarly $t_l = l\Delta T$. We also notice that we have the following upper bound using the midpoint rule in Riemann sums

$$|\widetilde{C}^{\text{finite}}(T,T,\omega) - \widetilde{C}(T,T,\omega)| \le \alpha \frac{T^3 \widetilde{\tau}^3}{N_T^2 N_{\widetilde{\tau}}^2}, \quad (42)$$

where $\alpha = M_2/24$, with M_2 maximum of the absolute value of the second derivative of the integrand on the interval of interest. Choosing $\Delta t = \Delta \tau = \Delta$ and $\tilde{\tau} = T$ we obtain

$$\widetilde{C}(T,T,\omega) = \frac{\Delta^2}{4T^2} \sum_{j=-N_t}^{N_t} \sum_{l=-N_t}^{N_t} e^{ij\Delta\,\omega} C(j\Delta,l\Delta)\,,$$
(43)

and in order to reach a precision $\Delta \omega$ in the response function in frequency domain we need to evaluate $N_t^2 = O(1/\Delta\omega^2)$ correlators. This is quadratically worse than the $O(1/\Delta\omega)$ cost (either in measurements or gate depth) required to compute the response function in frequency space using expansions in orthogonal polynomials [31, 32] or using Quantum Phase Estimation [22]. This suggests that, in situations where the frequency response is the observable of interest and when only approximations to the nuclear ground-state with low fidelity are available, these latter methods should be preferred. Future work in this direction will help elucidate the tradeoffs between the two approaches. A preliminary discussion of the effects of the excited contamination in the initial state is reported in Appendix C 3.

VI. CONCLUSIONS AND OUTLOOK

In this paper we performed a calculation of the real time two-point correlation function for a simple model of a triton using leading order pion-less EFT as first presented in Ref. [22]. In particula, we adopted for our problem an algorithm first presented in Ref. [29]. We performed a theoretical error analysis for the general version of the problem at hand investigating the required number of measurements as a function of the statistical precision and the error on the implementation of the time evolution. We performed calculations using current available IBM quantum hardware (five qubit machines, with T connectivity). Results have been error mitigated using readout error mitigation and zero-noise-extrapolation and are in agreement with the exact ones for the momentum transfer $\mathbf{q} = (0, 1)$ and for the real part at momentum transfer $\mathbf{q} = (1, 1)$. We noticed discrepancies with the exact results for two of the four time orderings for the error mitigated imaginary part of the response function at $\mathbf{q} = (1, 1)$. We can conclude that for almost all cases A2 leads to better error metrics than the ordering B2, which can be understood looking at the CNOT gate count reported in Tab. I. In the future we plan to explore the use of different error mitigation strategies and to perform calculations for a larger number of sites. Finally, we have also shown that techniques to reconstruct the frequency response starting from real-time data coming from two-point correlation function can require up to a quadratic increase in the number of experiments when the initial state is not the exact ground-state as compared with methods that work directly in frequency space. Besides applications where real time information is directly required, real time approaches might still be used efficiently in practice when either an approximation to the initial many-body ground state can be obtained with high-fidelity.

ACKNOWLEDGMENTS

We thank L. Cincio and Y. Subasi for useful discussions. This work was supported in part by the U.S. Department of Energy, Office of Science, Office of Nuclear Physics, Inqubator for Quantum Simulation (IQuS) under Award Number DOE (NP) Award DE-SC0020970, by the DOE HEP QuantISED grant KA2401032 and by the Institute for Nuclear Theory under U.S. Depart-

- [1] S. Pastore, A. Baroni, J. Carlson, S. Gandolfi, Steven C. Pieper, R. Schiavilla, and R. B. Wiringa, "Quantum monte carlo calculations of weak transitions in a = 6 10 nuclei," Phys. Rev. C **97**, 022501 (2018).
- [2] S. Pastore, J. Carlson, S. Gandolfi, R. Schiavilla, and R. B. Wiringa, "Quasielastic lepton scattering and back-to-back nucleons in the short-time approximation," Phys. Rev. C 101, 044612 (2020).
- [3] Maria Laura Baez, Marcel Goihl, Jonas Haferkamp, Juani Bermejo-Vega, Marek Gluza, and Jens Eisert, "Dynamical structure facsimulators," tors of dynamical quantum Proc. Natl. Acad. Sci. 117, 26123-26134 (2020).
- [4] Omar Benhar, Adelchi Fabrocini, and Stefano Fantoni, "The nucleon spectral function in nuclear matter," Nuclear Physics A 505, 267–299 (1989).
- [5] Noemi Rocco, Carlo Barbieri, Omar Benhar, Arturo De Pace, and Alessandro Lovato, "Neutrino-nucleus cross section within the extended factorization scheme," Phys. Rev. C 99, 025502 (2019).
- [6] A. Lovato, S. Gandolfi, J. Carlson, Steven C. Pieper, and R. Schiavilla, "Electromagnetic response of ¹²C: A first-principles calculation," Phys. Rev. Lett. **117**, 082501 (2016).
- [7] A. Lovato, J. Carlson, S. Gandolfi, N. Rocco, and R. Schiavilla, "Ab initio study of (ν_{ℓ}, ℓ^{-}) and $(\overline{\nu}_{\ell}, \ell^{+})$ inclusive scattering in ¹²C: Confronting the miniboone and t2k ccqe data," Phys. Rev. X 10, 031068 (2020).
- [8] P. Gysbers, G. Hagen, J. D. Holt, G. R. Jansen, T. D. Morris, P. Navrátil, T. Papenbrock, S. Quaglioni, A. Schwenk, S. R. Stroberg, and et al., "Discrepancy between experimental and theoretical beta-decay rates resolved from first principles," Nature Physics 15, 428–431 (2019).
- [9] J. Carlson and R. Schiavilla, "Structure and dynamics of few-nucleon systems," Rev. Mod. Phys. 70, 743–841 (1998).
- [10] G. Shen, L. E. Marcucci, J. Carlson, S. Gandolfi, and R. Schiavilla, "Inclusive neutrino scattering off the deuteron from threshold to gev energies," Phys. Rev. C 86, 035503 (2012).
- [11] R. N. Silver, D. S. Sivia, and J. E. Gubernatis, "Maximum-entropy method for analytic continuation of quantum monte carlo data," Phys. Rev. B 41, 2380–2389 (1990).
- [12] E. Vitali, M. Rossi, L. Reatto, and D. E. Galli, "Ab initio low-energy dynamics of superfluid and solid ⁴He," Phys. Rev. B 82, 174510 (2010).

ment of Energy grant No. DE-FG02-00ER41132. This manuscript has been authored in part by Fermi Research Alliance, LLC under Contract No. DE-AC02-07CH11359 with the U.S. Department of Energy, Office of Science, Office of High Energy Physics. This research used resources of the Oak Ridge Leadership Computing Facility, which is a DOE Office of Science User Facility supported under Contract DE-AC05-00OR22725.

- [13] Yannis Burnier and Alexander Rothkopf, "Bayesian approach to spectral function reconstruction for euclidean quantum field theories," Phys. Rev. Lett. 111, 182003 (2013).
- [14] Lukas Kades, Jan M. Pawlowski, Alexander Rothkopf, Manuel Scherzer, Julian M. Urban, Sebastian J. Wetzel, Nicolas Wink, and Felix P. G. Ziegler, "Spectral reconstruction with deep neural networks," Phys. Rev. D 102, 096001 (2020).
- [15] Krishnan Raghavan, Prasanna Balaprakash, Alessandro Lovato, Noemi Rocco, and Stefan M. Wild, "Machine-learning-based inversion of nuclear responses," Phys. Rev. C 103, 035502 (2021).
- [16] Alessandro Roggero and Sanjay Reddy, "Thermal conductivity and impurity scattering in the accreting neutron star crust," Phys. Rev. C 94, 015803 (2016).
- [17] J. Carlson and R. Schiavilla, "Euclidean proton response in light nuclei," Phys. Rev. Lett. 68, 3682–3685 (1992).
- [18] Alessandro Roggero, Francesco Pederiva, and Giuseppina Orlandini, "Dynamical structure functions from quantum monte carlo calculations of a proper integral transform," Phys. Rev. B 88, 094302 (2013).
- [19] V D Efros, W Leidemann, G Orlandini, and N Barnea, "The Lorentz integral transform (LIT) method and its applications to perturbation-induced reactions," 34, R459–R528 (2007).
- [20] J. E. Sobczyk, B. Acharya, S. Bacca, and G. Hagen, "Ab initio computation of the longitudinal response function in ⁴⁰Ca," Phys. Rev. Lett. **127**, 072501 (2021).
- [21] Joanna E. Sobczyk and Alessandro Roggero, "Spectral density reconstruction with chebyshev polynomials," (2021).
- [22] Alessandro Roggero and Joseph Carlson, "Dynamic linear response quantum algorithm," Phys. Rev. C 100, 034610 (2019).
- [23] Alessandro Roggero, Andy C. Y. Li, Joseph Carlson, Rajan Gupta, and Gabriel N. Perdue, "Quantum computing for neutrino-nucleus scattering," Phys. Rev. D 101, 074038 (2020).
- [24] Abhinav Kandala, Antonio Mezzacapo, Kristan Temme, Maika Takita, Markus Brink, Jerry M Chow, and Jay M Gambetta, "Hardware-efficient variational quantum eigensolver for small molecules and quantum magnets," Nature 549, 242–246 (2017).
- [25] Alessandro Roggero, Chenyi Gu, Alessandro Baroni, and Thomas Papenbrock, "Preparation of excited states for nuclear dynamics on a quantum computer," Phys. Rev. C 102, 064624 (2020).

- [26] Dean Lee, Bu gra Borasoy, and Thomas Schaefer, "Nuclear lattice simulations with chiral effective field theory," Phys. Rev. C 70, 014007 (2004).
- [27] B. Borasoy, H. Krebs, D. Lee, and U.-G. Meißner, "The triton and three-nucleon force in nuclear lattice simulations," Nuclear Physics A 768, 179–193 (2006).
- [28] A Rokash, E Epelbaum, H Krebs, D Lee, and U-G Meißner, "Finite volume effects in low-energy neutron-deuteron scattering," 41, 015105 (2013).
- [29] R. Somma, G. Ortiz, J. E. Gubernatis, E. Knill, and R. Laflamme, "Simulating physical phenomena by quantum networks," Phys. Rev. A 65, 042323 (2002).
- [30] Thomas E O'Brien, Brian Tarasinski, and Barbara M Terhal, "Quantum phase estimation of multiple eigenvalues for small-scale (noisy) experiments," New Journal of Physics 21, 023022 (2019).
- [31] Rolando D Somma, "Quantum eigenvalue estimation via time series analysis," New Journal of Physics 21, 123025 (2019).
- [32] A. Roggero, "Spectral-density estimation with the gaussian integral transform," Phys. Rev. A 102, 022409 (2020).
- [33] Suguru Endo, Iori Kurata, and Yuya O. Nakagawa, "Calculation of the green's function on near-term quantum computers," Phys. Rev. Research 2, 033281 (2020).
- [34] Anthony Ciavarella, "Algorithm for quantum computation of particle decays," Phys. Rev. D 102, 094505 (2020).
- [35] Gilles Brassard, Peter Høyer, Michele Alain Tapp, "Quantum Mosca, and amplitude amplification estimation." and Quantum Computation and Information, 53–74 (2002).
- [36] Emanuel Knill, Gerardo Ortiz, and Rolando D. Somma, "Optimal quantum measurements of expectation values of observables," Phys. Rev. A 75, 012328 (2007).
- [37] Andrew M. Childs and Nathan Wiebe,
 "Hamiltonian simulation using linear combinations of unitary operations,"
 Quantum Information and Computation 12, 0901–0924 (2012).
- [38] Olivia Di Matteo, Anna McCoy, Peter Gysbers, Takayuki Miyagi, R. M. Woloshyn, and Petr Navrátil, "Improving hamiltonian encodings with the gray code," Phys. Rev. A 103, 042405 (2021).
- [39] Adriano Barenco, Charles H. Bennett, Richard Cleve, David P. DiVincenzo, Norman Margolus, Peter Shor, Tycho Sleator, John A. Smolin, and Harald Weinfurter, "Elementary gates for quantum computation," Phys. Rev. A 52, 3457–3467 (1995).
- [40] 5qubit backed: IBM Q team, "IBM Ourense backend," (2020), retrieved from https://quantumcomputing.ibm.com.
- [41] MD SAJID ANIS and et al., "Qiskit: An open-source framework for quantum computing, (2021).
- [42] Ying Li and Simon C. Benjamin, "Efficient variational quantum simulator incorporating active error minimization," Phys. Rev. X 7, 021050 (2017).
- [43] E. F. Dumitrescu, A. J. McCaskey, G. Hagen, G. R. Jansen, T. D. Morris, T. Papenbrock, R. C. Pooser, D. J. Dean, and P. Lougovski, "Cloud Quantum Computing of an Atomic Nucleus," Phys. Rev. Lett. **120**, 210501 (2018).
- [44] Ying Li and Simon C. Benjamin, "Efficient variational quantum simulator incorporating active error minimiza-

tion," Phys. Rev. X 7, 021050 (2017).

[45] Benjamin Hall, Alessandro Roggero, Alessandro Baroni, and Joseph Carlson, "Simulation of collective neutrino oscillations on a quantum computer," Phys. Rev. D 104, 063009 (2021).

Appendix A: Exicitation operator and response function expansion

We can explicitly write the density excitation operator for one of the fermion species, denoted with the subscript A as

$$\rho_A(\mathbf{q}_k) = e_A \sum_{i=1}^4 e^{i\mathbf{q}_k \cdot \mathbf{x}_i} c_{i,A}^{\dagger} c_{i,A} , \qquad (A1)$$

where e_A is the charge. The total density operator for both fermion species is simply $\rho = \rho_A + \rho_B$. Using the mapping reported in Ref. [23] we can write the excitation operator for the specie A at site (m, n) as

$$\rho_A(\mathbf{q}_k) = e_A[|00\rangle\langle 00| + (-1)^m |01\rangle\langle 01| + (-1)^n |10\rangle\langle 10| + (-1)^{m+n} |11\rangle\langle 11|].$$

The expression of the total charge $\rho = \rho_A + \rho_B$ can be written as

$$\rho(\mathbf{q}_{0,0}) = e_A + e_B
\rho(\mathbf{q}_{0,1}) = e_A Z_1 + e_B Z_3
\rho(\mathbf{q}_{1,1}) = e_A Z_1 Z_2 + e_B Z_3 Z_4 .$$
(A2)

Therefore we can decompose the response function for site (0, 1) as

$$C(\tau, \mathbf{q}_{0,1}) = \langle U^{\dagger}(\tau)\rho(\mathbf{q}_{0,1})U(\tau)\rho(\mathbf{q}_{0,1})\rangle = e_A^2 \langle Z_1(\tau)Z_1 \rangle + e_A e_B \langle Z_1(\tau)Z_3 \rangle + e_A e_B \langle Z_3(\tau)Z_1 \rangle + e_B^2 \langle Z_3(\tau)Z_3 \rangle ,$$
(A3)

where $Z_k(\tau) = U^{\dagger}(\tau)Z_kU(\tau)$, and similarly for the site (1,0). For the site (1,1) we have

$$C(\tau, \mathbf{q}_{1,1}) = e_A^2 \langle Z_1(\tau) Z_2(\tau) Z_1 Z_2 \rangle + e_A e_B \left[\langle Z_1(\tau) Z_2(\tau) Z_3 Z_4 \rangle + \langle Z_3(\tau) Z_4(\tau) Z_1 Z_2 \rangle \right] + e_B^2 \langle Z_3(\tau) Z_4(\tau) Z_3 Z_4 \rangle .$$
(A4)

We recall here that both the initial state we consider and the Hamiltonian are symmetric respect to the exchanges

$$(1,4) \leftrightarrow (2,3) . \tag{A5}$$



FIG. 5. Circuit decomposition for the three-body propagator for $e^{-iH_M^{(3bd)}t}$. The angle in the single qubit rotations is $\theta = \tau U/2$.



FIG. 6. Circuit identities used in the synthesis of the full circuit for pair correlators as described in the text

Appendix B: Circuits

We preliminary discuss the three-body oracle reported in Fig. 2 that can be expressed as follows



where the full decomposition of the oracle for $e^{-iH_M^{(3bd)}t}$ first derived in Ref. [23], can be found in Fig. 5. We describe now how we implemented the circuit reported in the right hand side of the B1 decomposition in Fig. 2 (an similar construction applies to the B2 decomposition on the right). For ease of the present discussion, we temporarily remove the oracle gate that implements the time evolution $H_B^{(2,3)}$ given the fact that the second control is not acting on qubits T_3 and T_2 . Now in order to simplify the circuit further we use the identity chain reported in Fig. 6 where $|anc\rangle$ denotes a generic ancillary state, and in the first equality above we used the fact that $H_B^{(1,4)} = H_B^{(4,1)}$. The second equality in Fig. 6 follows from applying a swap gate to a controlled Z gate. Given the T connectivity of the machines used we want to apply the controlled gates over the same qubit. Starting from the final right hand side of Fig. 6 with the qubit T_3 added we can add an identity gate formed by two consecutive swap gates between qubits T_4 and T_3



and we can avoid executing the last two swaps between qubits T_1, T_4 and qubits T_4, T_3 .

We report here one of the circuits used to calculate the correlator $\langle Z_4(\tau)Z_3(\tau)Z_2Z_1 \rangle$. The implementation using the identities just described for the above mentioned correlator reads as



where we notice that the last two swaps between qubits 1, 4 and 3, 2, located after the two remaining controlled Z are not reported in the circuit since they will not affect the measurement result. The above circuit can be reduced to the following form using circuit identities for sequences of Hadamard and controlled Z gates (see e.g Ref [39])



Appendix C: Error bounds

We quantify the total error given by the difference of the estimator and the Trotter error as $\tilde{\epsilon}(t)$ and we require that the Trotter and the statistical error to be less than $\tilde{\epsilon}(t)/2 = \epsilon(t)$. In the following we analyze the two errors separately.

1. Measurement bounds

We estimate here the number of measurements needed to achieve the desired precision ϵ over the calculation of the real time response function $C(\tau, \mathbf{q}_k)$. We preliminary define the following estimator of the matrix element defined in the text in Eq. (14)

$$\overline{s}_{i',i}(\tau) = \frac{\sum_j s_{i',i}^j(\tau)}{M_{i',i}}, \qquad (C1)$$

where $s_{i',i}^{j}(\tau)$ denotes the outcomes of $M_{i',i}$ measurements for a fixed value of the time step τ . The estimator of the response function $C(\tau, \mathbf{q}_{k})$ can be written as

$$\overline{C}(\tau, \mathbf{q}_k) = \sum_{i,i'=1}^{L} \alpha_{i'}(\mathbf{q}_k) \alpha_i(\mathbf{q}_k) \overline{s}_{i',i}(\tau) , \qquad (C2)$$

where L the number of terms in the interaction Hamiltonian is simply equal to the product of the number of species with nonzero coupling to the charge operator. The corresponding variance of the estimator reads as

$$\operatorname{var}\left[\overline{C}(\tau, \mathbf{q}_{k})\right] = \sum_{i,i'=1}^{L} \alpha_{i'}^{2}(\mathbf{q}_{k}) \alpha_{i}^{2}(\mathbf{q}_{k}) \frac{1 - |\overline{s}_{i',i}(\tau)|^{2}}{M_{i',i}} .$$
$$\leq \sum_{i,i'=1}^{L} \alpha_{i'}^{2}(\mathbf{q}_{k}) \alpha_{i}^{2}(\mathbf{q}_{k}) \frac{1}{M_{i',i}}, \quad (C3)$$

where the expression in the first line comes from the fact that the average of s^2 is the identity since (c.f. definition of $s_{i',i}(\tau)$ in Eq. (14))

$$\langle \psi_0 | V_{i'i}^{\dagger}(\tau) V_{i'i}(\tau) | \psi_0 \rangle = 1.$$
 (C4)

We now require the variance in Eq. (C3) to be equal to ϵ^2 and we consider the case for which $\forall i, i' \ M_{i',i} = M = N/L^2$ where N is the total number of measurements done to estimate $\overline{C}(\tau, \mathbf{q}_k)$. We arrive at

$$N \le \frac{L^2}{\epsilon^2} \max_k \left[\sum_{i=1}^L \alpha_i^2(\mathbf{q}_k) \right]^2.$$
 (C5)

2. Trotter and state error bounds

We notice that the quantity that we want to calculate is $s_{k'k}(\tau)$ reported in Eq. (14) and the actual implementation contains two errors one coming from the initial state preparation and the other coming from the approximate implementation of the time evolution operator $V(\tau)$. We preliminary define the difference

$$\Delta_{k'k}(\tau) = Tr \left[V^{\dagger}(\tau) P_{k'} V(\tau) P_k \Pi \right] - Tr \left[U^{\dagger}(\tau) P_{k'} U(\tau) P_k \Pi_0 \right], \quad (C6)$$

where we have defined $\Pi_0 = |\Psi_0\rangle \langle \Psi_0|$ and $\Pi = |\Psi\rangle \langle \Psi|$. We can therefore write

$$\Delta_{k'k}(\tau) = \delta_{k'k}^{\text{Trott.}}(\tau) + \delta_{k'k}^{\text{state}}(\tau) , \qquad (C7)$$

where we have defined

$$\delta_{k'k}^{\text{Trott.}}(\tau) \equiv Tr\left[\left(V^{\dagger}(\tau)P_{k'}V(\tau) - U^{\dagger}(\tau)P_{k'}U(\tau)\right)P_{k}\Pi_{0}\right]$$

$$\delta_{k'k}^{\text{state}}(\tau) \equiv Tr\left[V^{\dagger}(\tau)P_{k'}V(\tau)P_{k}(\Pi - \Pi_{0})\right].$$
(C8)

we notice that

$$\begin{split} \delta_{k'k}^{\text{Trott.}}(\tau) &= \langle \Psi_0 | \left(V^{\dagger}(\tau) - U^{\dagger}(\tau) + U^{\dagger}(\tau) \right) P_{k'} V(\tau) P_k | \Psi_0 \rangle \\ &- \langle \Psi_0 | U^{\dagger}(\tau) P_{k'} (U(\tau) - V(\tau) + V(\tau)) P_k | \Psi_0 \rangle \\ &= \langle \Psi_0 | \left(V^{\dagger}(\tau) - U^{\dagger}(\tau) \right) P_k' V(\tau) P_k | \Psi_0 \rangle \\ &- \langle \Psi_0 | U^{\dagger}(\tau) P_{k'} (U(\tau) - V(\tau)) P_k | \Psi_0 \rangle , \end{split}$$
(C9)

taking the norm of the difference of the above quantity

$$\begin{aligned} |\delta_{k'k}^{\text{Trott.}}(\tau)| &\leq ||V^{\dagger}(\tau) - U^{\dagger}(\tau)|| \ ||P_{k'}V(\tau)P_k|| \\ &+ ||V(\tau) - U(\tau)|| \ ||P_kU^{\dagger}(\tau)P_{k'}|| \\ &= 2||V(\tau) - U(\tau)|| \ , \end{aligned}$$
(C10)

where we used the fact that the norm of the product of three unitaries is the unity. An extensive discussion for the case of Trotterizzation and qubitization is reported in Ref. [23]. We finally compute the difference $\delta_{k'k}^{\text{state}}(\tau)$ and using Eq. (B8) of ref. [25] we arrive at

$$\left|\delta_{k'k}^{\text{state}}(\tau)\right| \le \frac{1}{2}Tr|\Pi - \Pi_0| \le \sqrt{1-F}\,,\qquad(\text{C11})$$

where F is the fidelity defined in Eq. (24).

3. Excited state contamination in the initial state

The correlator that we want to calculate is the following

$$C(\tau, \mathbf{q}_k) = e^{iE_0\tau} \langle \Psi_0 | H_I(\mathbf{q}_k) U(\tau) H_I(\mathbf{q}_k) | \Psi_0 \rangle ,$$
(C12)

where $|\Psi_0\rangle$ denotes the exact ground state and $U(\tau) = e^{-iH\tau}$ the exact time evolution. We observe that using a set of eigenstates of H, denoted by $|i\rangle$, where $|i = 0\rangle = |\Psi_0\rangle$ we can write

$$H_{I}(\mathbf{q}_{k}) = \sum_{i,j} a_{i,j}(\mathbf{q}_{k}) \left| i \right\rangle \left\langle j \right| , \qquad (C13)$$

where $a_{i,j}(\mathbf{q}_k) = \langle i | H_I(\mathbf{q}_k) | j \rangle$. We, therefore, have

$$C(\tau, \mathbf{q}_k) = e^{iE_0\tau} \sum_l e^{-iE_l\tau} a_{0,l}(\mathbf{q}_k) a_{l,0}(\mathbf{q}_k) .$$
(C14)

The approximate ground state can be expressed as

$$|\Psi\rangle = c_0 |\Psi_0\rangle + \sum_{i=1}^{K} c_i |i\rangle , \qquad (C15)$$

and the approximate correlator is

$$C_{\Psi}(\tau, \mathbf{q}_k) = \sum_{i,j,m} a_{i,j}(\mathbf{q}_k) a_{j,m}(\mathbf{q}_k) e^{i(E_i - E_j)\tau} \left\langle \Psi \right| i \right\rangle \left\langle m \right| \Psi \right\rangle.$$
(C16)

We can now consider the case of imaginary time evolution in which the operator $U(\tau)$ is replaced by the operator $U_E(\tau_E) = e^{-H\tau_E}$. The euclidean version of the real time correlator is

$$C^{\rm E}(\tau_E, \mathbf{q}_k) = e^{-E_0 \tau_E} \sum_l e^{-E_l \tau_E} a_{0,l}(\mathbf{q}_k) a_{l,0}(\mathbf{q}_k) ,$$
(C17)

and expanding we obtain

$$C^{E}(\tau_{E}, \mathbf{q}_{k}) = e^{-2E_{0}\tau_{E}} a_{0,0}(\mathbf{q}_{k}) a_{0,0}(\mathbf{q}_{k}) + e^{-E_{0}\tau_{E}} \sum_{l \neq 0} e^{-E_{l}\tau_{E}} a_{0,l}(\mathbf{q}_{k}) a_{l,0}(\mathbf{q}_{k}) ,$$
(C18)

where the second term is subleading compared to the first term (if $E_0 < E_l \ \forall l \neq 0$). The approximate correlator in

euclidean time is

$$C_{\Psi}^{\rm E}(\tau_E, \mathbf{q}_k) = \sum_{i,j,m} a_{i,j}(\mathbf{q}_k) a_{j,m}(\mathbf{q}_k) e^{-(E_i + E_j)\tau_E} c_i^{\star} c_m \,.$$
(C19)

The exact euclidean correlator has the spectral decomposition

$$C_{\Psi}^{E}(\tau_{E}, \mathbf{q}_{k}) = \sum_{j,m} a_{0,j}(\mathbf{q}_{k})a_{j,m}(\mathbf{q}_{k})e^{-(E_{0}+E_{j})\tau_{E}}c_{0}^{\star}c_{m}$$
$$+ \sum_{i\neq 0,j,m} a_{i,j}(\mathbf{q}_{k})a_{j,m}(\mathbf{q}_{k})e^{-(E_{i}+E_{j})\tau_{E}}c_{i}^{\star}c_{m},$$
(C20)

where the leading terms, proportional to $e^{-2E_0\tau_E}$, are

$$C_{\Psi}^{\mathrm{E}}(\tau_{E}, \mathbf{q}_{k}) = |c_{0}|^{2} a_{0,0}(\mathbf{q}_{k}) a_{0,0}(\mathbf{q}_{k}) e^{-2E_{0}\tau_{E}} + \sum_{m \neq 0} a_{0,0}(\mathbf{q}_{k}) a_{0,m}(\mathbf{q}_{k}) e^{-2E_{0}\tau_{E}} c_{0}^{\star} c_{m} + \cdots .$$
(C21)

Terms represented by \cdots get contributions from the excited states that are exponentially suppressed by the respective mass gaps. However, the second term present in Eq. (C21) above, coming from the excited state contamination in the initial state $|\Psi\rangle$, is only suppressed by c_m/c_0 and not exponentially. It is therefore important to optimize the fidelity of $|\Psi\rangle$, ie, increase the overlap with $|\Psi_0\rangle$, in order to reduce the systematic bias in the results.