

Distributed Interval Observers for Bounded-Error LTI Systems

Mohammad Khajenejad*, Scott Brown*, and Sonia Martínez

Abstract—This paper proposes a novel distributed interval observer design for linear time-invariant (LTI) discrete-time systems subject to bounded disturbances. In the proposed observer algorithm, each agent in a networked group exchanges locally-computed framers or interval-valued state estimates with neighbors, and coordinates its update via an intersection operation. We show that the proposed framers are guaranteed to bound the true state trajectory of the system by construction, i.e., without imposing any additional assumptions or constraints. Moreover, we provide necessary and sufficient conditions for the collective stability of the distributed observer, i.e., to guarantee the uniform boundedness of the observer error sequence. In particular, we show that such conditions can be tractably satisfied through a constructive and distributed approach. Moreover, we provide an algorithm to verify some structural conditions for a given system, which guarantee the existence of the proposed observer. Finally, simulation results demonstrate the effectiveness of our proposed method compared to an existing distributed observer in the literature.

I. INTRODUCTION

Many large scale cyber-physical systems, such as electric power grids [1], intelligent transportation systems [2], and industrial infrastructures [3], are equipped with sensor networks, providing *in situ* and diverse measurements to monitor them. This makes possible the construction of system state estimates, which are essential to guarantee the safe and effective operation of these critical applications. Motivated by this, an intense research activity on the analysis and design of distributed estimation algorithms has ensued. In this way, each sensor, equipped with local communication and processing capabilities, interacts with neighboring nodes to compute joint estimates cooperatively.

A way to obtain such estimates is to use a *centralized observer*, by which a super node collects all measurements from the nodes and fuses them in an optimal way. The ubiquitous Kalman filter [4] and related approaches have been used extensively for this purpose. However, these algorithms do not scale well as the size of the network increases and are vulnerable to single-point failures. This spawned research on the design of *distributed estimation filters* (for systems subject to known stochastic disturbances) for sensor networks communicating only locally over a possibly time-varying network [5]. While these methods are more scalable and robust to communication failures than their centralized

counterparts, they generally have comparatively worse estimation error. An important class of algorithms that aim to approach the estimation performance of their Kalman filter counterparts, are Kalman-consensus filters, which combine a local Kalman-like update with average consensus to align agents' estimates [6], [7]. When stochastic characterization of disturbances is not available, however, other techniques that leverage alternative information should be considered.

In case the disturbances are known to be bounded, *interval observers* are a popular method for obtaining robust, guaranteed estimates of the state, due to their simplicity and computational efficiency [8]–[10]. Hence, various approaches to design centralized interval observers for various classes of dynamical systems have been proposed [11]–[17]. The main idea in most of the aforementioned designs is to synthesize appropriate centralized observer gains to obtain a robustly stable and positive observer error system for all realizations of the existing uncertainties [11], [14]. This strategy, which usually boils down to solving centralized semi-definite programs (SDP) subject to large numbers of constraints, leads to theoretical and computational difficulties, and thus infeasible solutions, especially for large-scale systems [15]–[17]. In addition to computational issues, the communication complexity of the centralized approach does not scale well as the size of the network increases. A recent study [18] proposes a distributed interval observer for *block-diagonalizable* linear time-invariant (LTI) systems, which requires a certain structure on the dynamics and the output of the system. Another work [19] designs an observer for LTI systems under denial-of-service attacks. In addition, [20] proposes an internally positive representation (IPR)-based robust distributed interval observer for continuous-time LTI systems. However, the proposed design relies on similarity transformations and the satisfaction of certain algebraic constraints, which could lead to moderately-performing results. Furthermore, all of the aforementioned works use average consensus to share estimates throughout the network, which limits the effectiveness of the proposed methods with respect to time of convergence and estimation quality.

Contributions. To overcome the aforementioned drawbacks, this work contributes to bridging the gap between interval observer design approaches and distributed estimation algorithms in the presence of distribution-free uncertainties. We introduce a novel method for synthesizing scalable distributed interval observers for discrete-time LTI systems subject to bounded additive disturbances. We provide necessary and sufficient conditions for the stability of our proposed observer. Our observer is correct by construc-

*Equal contribution. M. Khajenejad, S. Brown and S. Martínez are with the Mechanical and Aerospace Engineering Department of the Jacobs School of Engineering, University of California, San Diego, La Jolla, San Diego, CA, USA. (e-mail: {mkhajenejad, sab007, soniamd}@ucsd.edu.)

This work is partially funded by AFOSR and ONR grants FA9550-19-1-0235 and N00014-19-1-2471.

tion, and we leverage this correctness to intersect interval estimates between neighboring nodes, ensuring that the best possible (agent) estimate is adopted by consensus in a finite number of iterations. Furthermore, we introduce the intuitive notion of “collective positive detectability over neighborhoods” (CPDN) which, is sufficient to tractably compute gains that satisfy the aforementioned stability requirement in a distributed manner. This approach involves the solution to local and feasible linear programs (LP), which is potentially less conservative and computationally more efficient than SDP-based approaches. Finally, we provide an algorithm to verify if CPDN holds for a given system.

II. PRELIMINARIES

This section introduces basic notation, preliminary concepts and graph theory notions used throughout the paper.

Notation. Let \mathbb{R}^n , $\mathbb{R}^{n \times p}$, \mathbb{N} , $\mathbb{Z}_{\geq 0}$, and $\mathbb{R}_{\geq 0}$ denote the n -dimensional Euclidean space, the sets of n by p matrices, natural numbers, nonnegative integers, and nonnegative real numbers, respectively. For $M \in \mathbb{R}^{n \times p}$, let M_i and M_{ij} denote the i^{th} row of M , and the $(i, j)^{\text{th}}$ entry of M , respectively. Furthermore, for $M \in \mathbb{R}^{n \times p}$, we define $M^+ \in \mathbb{R}^{n \times p}$, such that $M_{ij}^+ \triangleq \max\{M_{ij}, 0\}$, $M^- \triangleq M^+ - M$, and $|M| \triangleq M^+ + M^-$. In addition, $M \succ 0$ (or, $M \succeq 0$, resp.) denote that M is positive definite (semi-definite, resp.), and $\rho(M)$ is used to denote the spectral radius of M . All the inequalities \leq, \geq are considered element-wise. As usual, e_i denotes the i^{th} vector of the standard basis of \mathbb{R}^n . Finally, for $A^1, \dots, A^N \in \mathbb{R}^{n \times n}$, $\text{diag}(A^1, \dots, A^N) \in \mathbb{R}^{nN \times nN}$ denotes the block-diagonal matrix with block-diagonal elements being $A^i, i \in \{1, \dots, N\}$.

Graph-theoretic Notions. Next, we recall some definitions from Graph Theory. A directed graph (digraph) \mathcal{G} is a set of nodes \mathcal{V} and a set of directed edges $\mathcal{E} \subseteq \mathcal{V} \times \mathcal{V}$. The set of neighbors of node i , denoted \mathcal{N}_i , is the set of all nodes j for which there is an edge $(i, j) \in \mathcal{E}$. We will assume that $i \in \mathcal{N}_i$. A path from node i to node j is a sequence of nodes starting with i and ending with j , such that any two consecutive nodes are joined by a directed edge. The d -hop neighbors of agent i , denoted \mathcal{N}_i^d , is the set of nodes connected to i by a path of length no more than d . The diameter of a graph is the largest distance between any two nodes, i.e. $\text{diam } \mathcal{G} \triangleq \max_{i,j} d(i, j)$, where $d(i, j)$ denotes the length of the shortest path between i and j .

Multi-dimensional Intervals. Finally, we introduce some definitions and results regarding multi-dimensional intervals. A (multi-dimensional) interval $\mathcal{I} \triangleq [\underline{s}, \overline{s}] \subset \mathbb{R}^n$ is the set of all vectors $x \in \mathbb{R}^n$ that satisfy $\underline{s} \leq x \leq \overline{s}$.

Proposition 1. [17, Lemma 1] *Let $A \in \mathbb{R}^{p \times n}$ and $\underline{x} \leq x \leq \overline{x} \in \mathbb{R}^n$. Then, $A^+ \underline{x} - A^- \overline{x} \leq Ax \leq A^+ \overline{x} - A^- \underline{x}$. As a corollary, if A is non-negative, $A \underline{x} \leq Ax \leq A \overline{x}$.*

III. PROBLEM FORMULATION

System Assumptions. Consider a multi-agent system (MAS) consisting of $\mathcal{V} \triangleq \{1, \dots, N\}$ agents, which interact over a time-invariant communication graph $\mathcal{G} = (\mathcal{V}, \mathcal{E})$. The agents

are able to obtain distributed measurements of a target as described by the following LTI dynamics:

$$\mathcal{P} : \begin{cases} x_{k+1} = Ax_k + Bw_k, \\ y_k^i = C^i x_k + D^i v_k^i, \quad i \in \mathcal{V}, \quad k \in \mathbb{Z}_{\geq 0}, \end{cases} \quad (1)$$

where $x_k \in \mathbb{R}^n$ is the continuous state of the target system and $w_k \in \mathcal{I}_w \triangleq [\underline{w}, \overline{w}] \subset \mathbb{R}^{n_w}$ is bounded process disturbance. Furthermore, at time step k , every agent $i \in \mathcal{V}$ takes a measurement $y_k^i \in \mathbb{R}^{n_i}$, known only to itself, which is perturbed by $v_k^i \in \mathcal{I}_v^i \triangleq [\underline{v}^i, \overline{v}^i] \subset \mathbb{R}^{n_v^i}$, a bounded sensor (measurement) noise signal. Finally, $A \in \mathbb{R}^{n \times n}$, $B \in \mathbb{R}^{n \times n_w}$, $C^i \in \mathbb{R}^{n_i \times n}$ and $D^i \in \mathbb{R}^{n_i \times n_v^i}$ are system matrices known to all agents. The MAS’s goal is to estimate the trajectories of (1) in a distributed manner, when they are initialized in an interval $\mathcal{I}_x \triangleq [\underline{x}_0, \overline{x}_0] \subset \mathbb{R}^n$, with $\underline{x}_0, \overline{x}_0$ known to all agents. Next, we define the notions of *framers*, *correctness*, and *stability*, used throughout the paper.

Definition 1 (Framers). *For an agent $i \in \mathcal{V}$, the sequences $\{\overline{x}_k^i\}_{k \geq 0}$ and $\{\underline{x}_k^i\}_{k \geq 0} \subseteq \mathbb{R}^n$ are called upper and lower individual framers for (the state of) \mathcal{P} if $\underline{x}_k^i \leq x_k \leq \overline{x}_k^i$, for all $k \geq 0$. Moreover, we define the individual lower and upper framer errors as follows:*

$$\underline{e}_k^i \triangleq x_k - \underline{x}_k^i, \quad \overline{e}_k^i \triangleq \overline{x}_k^i - x_k, \quad \forall k \geq 0. \quad (2)$$

Given an MAS with target system \mathcal{P} and communication graph \mathcal{G} , a distributed interval framer is a distributed algorithm over \mathcal{G} that allows each agent i to cooperatively compute upper and lower individual framers for \mathcal{P} . Finally,

$$e_k \triangleq [(\underline{e}_k^1)^\top \ (\overline{e}_k^1)^\top \ \dots \ (\underline{e}_k^N)^\top \ (\overline{e}_k^N)^\top]^\top \in \mathbb{R}^{2Nn}. \quad (3)$$

is called the collective framer error, which is the vector of all individual lower and upper framer errors.

Definition 2 (Distributed Interval Observer). *A distributed interval framer is input-to-state (ISS) stable if the collective framer error is bounded as follows:*

$$\|e_k\| \leq \beta(\|e_0\|, k) + \gamma \left(\max_{0 \leq l \leq k} |\Delta_l| \right), \quad \forall k \in \mathbb{Z}_{\geq 0},$$

where $\Delta_l \triangleq [w_l^\top \ (v_l^1)^\top \ \dots \ (v_l^N)^\top]^\top \in \mathbb{R}^{n_w + Nn_v}$, and β and γ are functions of classes \mathcal{KL} and \mathcal{K}_∞ , respectively. An ISS distributed interval framer is a distributed interval observer.

The observer design problem can be stated as follows:

Problem 1. *Given a multi-agent system and the LTI system in (1), design a distributed interval observer for \mathcal{P} .*

IV. PROPOSED DISTRIBUTED INTERVAL OBSERVER

In this section, we describe our novel distributed interval observer design, a necessary and sufficient condition for stability of the proposed observer, and an LP-based distributed procedure for computing stabilizing observer gains.

A. Distributed Observer and its Correctness

To address Problem 1, we propose a two-step distributed interval framer (cf. Definition 1) for \mathcal{P} . The DIO Algorithm 1 provides a pseudocode description of our observer, the details of which are further explained in this section as follows.

i) Propagation and Measurement Update: At every $k+1 \in \mathbb{Z}_{\geq 0}$, given $\underline{x}_k^i, \bar{x}_k^i, y_k^i$, and y_{k+1}^i , each agent $i \in \mathcal{V}$ performs a state propagation and a local measurement update step using observer gains $L^i, \Gamma^i \in \mathbb{R}^{n \times m_i}$ which will be designed to satisfy desired observer properties:

$$\begin{aligned} \underline{x}_{k+1}^{i,0} &= \tilde{A}^{i+} \underline{x}_k^i - \tilde{A}^{i-} \bar{x}_k^i + (T^i B)^+ \underline{w} - (T^i B)^- \bar{w} + L^i y_k^i + \Gamma^i y_{k+1}^i \\ &\quad + ((L^i D^i)^+ + (\Gamma^i D^i)^+) \underline{v} - ((L^i D^i)^- + (\Gamma^i D^i)^-) \bar{v}, \\ \bar{x}_{k+1}^{i,0} &= \tilde{A}^{i+} \bar{x}_k^i - \tilde{A}^{i-} \underline{x}_k^i + (T^i B)^+ \bar{w} - (T^i B)^- \underline{w} + L^i y_k^i + \Gamma^i y_{k+1}^i \\ &\quad + ((L^i D^i)^+ + (\Gamma^i D^i)^+) \bar{v} - ((L^i D^i)^- + (\Gamma^i D^i)^-) \underline{v}, \end{aligned} \quad (4)$$

where $T^i \triangleq I_n - \Gamma^i C^i$ and $\tilde{A}^i \triangleq T^i A - L^i C^i$. Further, $\underline{e}_k^{i,0} \triangleq x_k - \underline{x}_k^{i,0}$ and $\bar{e}_k^{i,0} \triangleq \bar{x}_k^{i,0} - x_k$ are the corresponding errors, and e_k^0 is the vector of all agents' errors, as in (3).

ii) Network Update: After the measurement update, each agent i iteratively shares its interval estimate with its neighbors in the network, and updates it by taking the tightest interval from all neighbors via intersection:

$$\begin{aligned} \underline{x}_k^{i,t} &= \max_{j \in \mathcal{N}_i} \underline{x}_k^{j,t-1}, & \underline{x}_k^i &= \underline{x}_k^{i,d}, \\ \bar{x}_k^{i,t} &= \min_{j \in \mathcal{N}_i} \bar{x}_k^{j,t-1}, & \bar{x}_k^i &= \bar{x}_k^{i,d}, \end{aligned} \quad (5)$$

$\forall t \in \{1, \dots, d\}$, where $d \in \mathbb{N}$ is the number of network-update iterations. Note that in case $d > 1$, this iterative procedure computes the intersection of intervals with the d -hop neighbors of each agent. Consequently, each agent i obtains the following information:

$$\underline{x}_k^i = \max_{j \in \mathcal{N}_i^d} \underline{x}_k^{j,0} \quad \text{and} \quad \bar{x}_k^i = \min_{j \in \mathcal{N}_i^d} \bar{x}_k^{j,0}.$$

We will use this fact as a compact representation of the network update (5). Next, we show that the proposed DIO algorithm constructs a distributed interval framer in the sense of Definition 1 for the plant \mathcal{P} .

Algorithm 1 Distributed Interval Observer (DIO) at node i .

Input: $\underline{x}_0^i, \bar{x}_0^i, d$; **Output:** $\{\underline{x}_k^i\}_{k \geq 0}, \{\bar{x}_k^i\}_{k \geq 0}$;

- 1: Compute L^i, Γ^i , and T^i using (12);
- 2: **loop**
- 3: Compute $\underline{x}_{k+1}^{i,0}$ and $\bar{x}_{k+1}^{i,0}$ using (4);
- 4: **for** $t = 1$ to d **do**
- 5: Send $\underline{x}_{k+1}^{i,t-1}$ and $\bar{x}_{k+1}^{i,t-1}$ to $j \in \mathcal{N}_i$;
- 6: $\underline{x}_{k+1}^{i,t} \leftarrow \max_{j \in \mathcal{N}_i} \underline{x}_{k+1}^{j,t-1}$; $\bar{x}_{k+1}^{i,t} \leftarrow \min_{j \in \mathcal{N}_i} \bar{x}_{k+1}^{j,t-1}$;
- 7: **end for**
- 8: $\underline{x}_{k+1}^i \leftarrow \underline{x}_{k+1}^{i,d}$; $\bar{x}_{k+1}^i \leftarrow \bar{x}_{k+1}^{i,d}$; $k \leftarrow k + 1$;
- 9: **end loop**
- 10: **return** $\{\underline{x}_k^i\}_{k \geq 0}, \{\bar{x}_k^i\}_{k \geq 0}$

Lemma 1 (Distributed Framer Construction). *The DIO algorithm is a distributed interval framer for (1).*

Proof. From (1) and the fact that $T^i = I_n - \Gamma^i C^i$, we have

$$x_{k+1} = (\Gamma^i C^i + T^i) x_{k+1} = T^i (A x_k + B w_k) + \Gamma^i C^i x_{k+1}. \quad (6)$$

Plugging $C^i x_{k+1} = y_{k+1}^i - D^i v_{k+1}^i$ into, as well as adding the zero term $L^i (y_k^i - C^i x_k - D^i v_k^i)$ to the right hand side of (6) results in

$$x_{k+1} = \tilde{A}^i x_k + T^i B w_k + \Gamma^i (y_{k+1}^i - D^i v_{k+1}^i) + L^i (y_k^i - D^i v_k^i). \quad (7)$$

Applying Proposition 1 to all the uncertain terms in the right hand side of (7) shows that for each $i \in \mathcal{V}$,

$$\underline{x}_k^i \leq x_k \leq \bar{x}_k^i \implies \underline{x}_{k+1}^{i,0} \leq x_{k+1} \leq \bar{x}_{k+1}^{i,0},$$

where $\underline{x}_{k+1}^{i,0}, \bar{x}_{k+1}^{i,0}$ are given in (4). This means that individual framers/interval estimates are correct. When the framer condition is satisfied for all nodes, the intersection of all the individual estimates of neighboring nodes (cf. (5)) also results in correct interval framers, i.e.

$$\underline{x}_k^{i,0} \leq x_k \leq \bar{x}_k^{i,0}, \forall i \in \mathcal{V} \implies \underline{x}_k^i \leq x_k \leq \bar{x}_k^i, \forall i \in \mathcal{V}.$$

Since the initial interval is known to all i , by induction (4)-(5) constructs a correct distributed interval framer for (1). ■

B. Collective Input-to-State Stability

In this subsection, we investigate conditions on the observer gains L^i, T^i , and Γ^i , as well as the communication graph \mathcal{G} , that lead to an ISS distributed observer (cf. Definition 2), which equivalently results in a uniformly bounded observer error sequence $\{e_k\}_{k \geq 0}$ (given in (2)–(3)), in the presence of bounded noise. For ease of exposition, in what follows, we ignore noise terms and focus on asymptotic stability of the noiseless error dynamics, which we will show implies collective input-to-state stability.

Switched System Perspective. We begin by stating a preliminary result that expresses the observer error dynamics in the form of a specific switched system.

Lemma 2. *The collective error e_k has dynamics*

$$e_{k+1} = H_k \hat{A} e_k, \quad (8)$$

where $\hat{A} \triangleq \text{diag}(\hat{A}^1, \dots, \hat{A}^N)$, $\hat{A}^i \triangleq \begin{bmatrix} (\tilde{A}^i)^+ & (\tilde{A}^i)^- \\ (\tilde{A}^i)^- & (\tilde{A}^i)^+ \end{bmatrix}$. $H_k \in \{0, 1\}^{2Nn \times 2Nn}$ is a binary matrix which selects a single minimizer or maximizer of the framers, i.e.,

$$\begin{aligned} (H_k)_{\text{id}(i,s), \text{id}(j^*,s)} &= 1 \Leftrightarrow j^* = \min(\arg\max_{j \in \mathcal{N}_i^d} (\underline{x}_k^{j,0})_s), \\ (H_k)_{\text{id}(i,s), \text{id}(j^*,s)} &= 1 \Leftrightarrow j^* = \min(\arg\min_{j \in \mathcal{N}_i^d} (\bar{x}_k^{j,0})_s), \end{aligned} \quad (9)$$

for $s \in \{1, \dots, n\}$ and $i \in \mathcal{V}$, where $\text{id}(i, s) = 2n(i-1) + s - 1$ and $\text{id}(i, s) = 2n(i-1) + s + n - 1$ encode the indices associated with the upper and lower framers of state s at node i . Furthermore, $H_k \hat{A} \in \mathcal{F} \subseteq \mathbb{R}^{2Nn \times 2Nn}$, where

$$\begin{aligned} \mathcal{F} &\triangleq \left\{ \begin{bmatrix} \underline{a}_{1,1}^\top & \bar{a}_{1,1}^\top & \underline{a}_{1,2}^\top & \bar{a}_{1,2}^\top & \dots & \underline{a}_{N,n}^\top & \bar{a}_{N,n}^\top \end{bmatrix}^\top \right. \\ &\quad \left. : \underline{a}_{i,s} \in \underline{\mathcal{F}}_s^i, \bar{a}_{i,s} \in \bar{\mathcal{F}}_s^i, s \in \{1, \dots, n\}, i \in \mathcal{V} \right\}, \\ \underline{\mathcal{F}}_s^i &\triangleq \left\{ e_j^\top \otimes [(\tilde{A}^j)^+ (\tilde{A}^j)^-]_s \in \mathbb{R}^{1 \times 2Nn} : j \in \mathcal{N}_i^d \right\}, \\ \bar{\mathcal{F}}_s^i &\triangleq \left\{ e_j^\top \otimes [(\tilde{A}^j)^- (\tilde{A}^j)^+]_s \in \mathbb{R}^{1 \times 2Nn} : j \in \mathcal{N}_i^d \right\}. \end{aligned}$$

Proof. Notice that $\tilde{A}^i = \tilde{A}^{i+} - \tilde{A}^{i-}$ in (7). Rewriting in terms of the error by adding (or subtracting) (7) to (4) and (5), then setting the noise to zero, we obtain $e_{k+1}^0 = \hat{A} e_k$ and $e_k = H_k e_k^0$. Combining these yields (8). ■

Recall that the switching in (8) depends on the state according to (9) and always creates the smallest possible

error. In order to take the advantage of this property note that the set \mathcal{F} has a specific structure known as *independent row uncertainty*, formally defined below.

Definition 3 (Independent Row Uncertainty [21]). *A set of matrices $\mathcal{M} \subset \mathbb{R}^{n \times n}$ has independent row uncertainties if*

$$\mathcal{M} = \left\{ [a_1^\top \cdots a_n^\top]^\top : a_i \in \mathcal{M}_i, i \in \{1, \dots, n\} \right\},$$

where all sets $\mathcal{M}_i \subset \mathbb{R}^{1 \times n}$ are compact.

Next, we restate the following lemma on the spectral properties of the sets with independent row uncertainties, that will be used later in our stability analysis of system (8).

Lemma 3. [21, Lemma 2] *Suppose $\mathcal{M} \subset \mathbb{R}^{n \times n}$ has independent row uncertainties. Then, there exists $M_* \in \mathcal{M}$ such that $\rho(M_*) = \min_{M \in \mathcal{M}} \rho(M) = \lim_{k \rightarrow \infty} \left(\min_{M_i \in \mathcal{M}, i \in \{1, \dots, k\}} \|M_1 \cdots M_k\|^{\frac{1}{k}} \right)$. The latter is known as the lower spectral radius of the set of matrices \mathcal{M} .*

We can now state our first main stability result.

Theorem 1 (Necessary and Sufficient Conditions for Stability). *The error system (8) is globally exponentially stable if and only if there exists $H_* \in \mathbb{R}^{2nN \times 2nN}$ which can be constructed according to (9) for some values of \underline{x} and \bar{x} , such that the matrix $H_* \hat{A}$ is Schur stable. Consequently, the DIO algorithm is ISS if and only if such an H_* exists.*

Proof. We first prove sufficiency and then necessity. Assume $H_* \hat{A}$ is Schur stable. Consider the comparison system $\tilde{e}_{k+1} = H_* \hat{A} \tilde{e}_k$ with initial condition $\tilde{e}_0 = e_0$. By the construction of H_k in (9), which implies $H_* \hat{A} e_k \geq H_k \hat{A} e_k$, $\tilde{e}_k \geq e_k \geq 0$ for all $k \geq 0$ by induction. Therefore, by comparison, (8) is globally exponentially stable. To prove necessity, note that (8) is asymptotically stable only if the lower spectral radius of \mathcal{F} is less than 1. By Lemma 3, this implies existence of a stable $F_* = H_* \hat{A}$. Finally, having studied stability of the noise-free system, we now study the ISS property of the noisy system:

$$e_{k+1} = H_k \hat{A} e_k + H_k (W_k + V_k), \quad \text{where} \quad (10)$$

$W_k \triangleq [(\Lambda_k^1)^\top \cdots (\Lambda_k^N)^\top]^\top$, $\Lambda_k^i \triangleq \begin{bmatrix} (T^i B)^+ \underline{s}_k + (T^i B)^- \bar{s}_k \\ (T^i B)^- \underline{s}_k + (T^i B)^+ \bar{s}_k \end{bmatrix}$, with $\underline{s}_k \triangleq w_k - \underline{w}$, $\bar{s}_k \triangleq \bar{w} - w_k$ and V_k is defined similarly to W_k , with $(L^i D^i)^* + (\Gamma^i D^i)^*$ replacing $(T^i B)^*$, for $*$ in $\{+, -\}$ and \underline{v}^i , \bar{v}^i , and v_k^i replacing \underline{w} , \bar{w} , and w_k respectively. As before, we can use the comparison system

$$\tilde{e}_{k+1} = H_* \hat{A} \tilde{e}_k + H_* (W_k + V_k), \quad \tilde{e}_0 = e_0 \quad (11)$$

It is well known that stable LTI systems are ISS [22]. Again, (9) guarantees $\tilde{e}_k \geq e_k \geq 0 \forall k \geq 0$ by induction, regardless of the values of W_k and V_k . By this comparison, the ISS property of the system (11) implies that (10) is ISS. ■

Theorem 1 is only an *existence* result. It does not provide a method for constructing H_* , which could be a difficult combinatorial problem. Therefore, in the next section we provide a tractable approach that allows for the computation of stabilizing gains and the corresponding H_* in Theorem 1.

C. Distributed Stabilizing of the Error Dynamics

In this subsection, we show that the ISS property formalized in Theorem 1 can be tractably verified in a constructive and distributed manner. The approach is motivated by the representation (8), in which H_k exchanges rows of \hat{A} to achieve the best possible estimate. The main idea is that each agent, depending on its observation of the system, contributes to stabilizing the state trajectory in *some*, not necessarily all, dimensions. To guarantee stability using our design approach, we will use the following assumption, which characterizes the interplay between the agents' local observations and their communication over the network.

Assumption 1 (Collective Positive Detectability over Neighborhoods (CPDN)). *There is a $d^* \in \mathbb{N}$ such that for every state $s \in \{1, \dots, n\}$ and every agent $i \in \mathcal{V}$, there is an agent $\ell(i, s) \in \mathcal{N}_i^{d^*}$ such that there exist gains $T^{\ell(i, s)}$, $L^{\ell(i, s)}$, and $\Gamma^{\ell(i, s)}$ satisfying $\|(T^{\ell(i, s)} A - L^{\ell(i, s)} C^{\ell(i, s)})_s\|_1 < 1$.*

Assumption 1 captures a broad range of conditions on the system and graph structure that can result in a stable observer. It is also different from the well-known notion of “collective observability” [20], which is not sufficient here due to the non-negativity of the error dynamics in the interval observer design. Furthermore, the conditions in Assumption 1, can be verified using a distributed procedure described in Algorithm 2, summarized here. First, each node $i \in \mathcal{V}$ independently solves the following linear program:

$$\begin{aligned} & \min_{\{E^i, L^i, T^i, \Gamma^i\}} \sum_{j=1}^n \sum_{t=1}^n E_{jt}^i \\ & \text{s.t.} \quad -E^i \leq T^i A - L^i C^i \leq E^i, T^i = I_n - \Gamma^i C^i. \end{aligned} \quad (12)$$

Then, nodes exchange their \tilde{A}^i matrices with increasingly larger neighborhoods until stabilizing agents are found for every state. The following lemma formalizes this result.

Algorithm 2 DIO initialization at node i .

Input: A, C^i, \mathcal{N}_i ; **Output:** L^i, T^i, Γ^i, d^*

- 1: Compute $L^{i,*}$, $\Gamma^{i,*}$, and $T^{i,*}$ by solving (12);
- 2: $\mathcal{Q}_i \leftarrow \{T^{i,*} A - L^{i,*} C^{i,*}\}$; $d^* \leftarrow 1$;
- 3: **while** $d^* \leq \text{diam } \mathcal{G}$ **do**
- 4: **if** $\forall s \in \{1, \dots, n\}, \exists P \in \mathcal{Q}_i$ s.t. $\|(P)_s\|_1 < 1$ **then**
- 5: **break**
- 6: **end if**
- 7: Send \mathcal{Q}_i to $j \in \mathcal{N}_i$ and receive \mathcal{Q}_j from $j \in \mathcal{N}_i$;
- 8: $\mathcal{Q}_i \leftarrow \bigcup_{j \in \mathcal{N}_i} \mathcal{Q}_j$; $d^* \leftarrow d^* + 1$;
- 9: **end while**
- 10: **for** $t = 1$ to $\text{diam } \mathcal{G}$ **do** $d_i^* \leftarrow \max_{j \in \mathcal{N}_i} d_j^*$ **end for**
- 11: **return** $L^{i,*}, T^{i,*}, \Gamma^{i,*}, d_i^*$

Lemma 4. *Assumption 1 holds if and only if Algorithm 2 returns $d^* \leq \text{diam } \mathcal{G}$.*

Proof. Assume Assumption 1 does not hold for some agent i . Then the condition in line 4 of Algorithm 2 will never be met, resulting in $d_i^* = \text{diam } \mathcal{G} + 1$. After the max consensus on line 10, all agents will return $d^* = \text{diam } \mathcal{G} + 1$. On the other hand, if Assumption 1 holds, the condition in line 4 will be met after less than $\text{diam } \mathcal{G}$ iterations for every node. ■

Finally, we show that the solutions to the LP in (12) are the corresponding stabilizing observer gains.

Theorem 2 (Distributed Interval Observer Design). *Suppose Assumption 1 holds. Then the DIO algorithm is ISS with $d = d^*$ and the corresponding observer gains $L^{*,i}$, $T^{*,i}$, and $\Gamma^{*,i}$ that are solutions to (12).*

Proof. We will construct H_* , which by Theorem 1 is sufficient for the ISS property to hold. For each node $i \in \mathcal{V}$ and state $s \in \{1, \dots, n\}$, using $\ell(i, s)$ from Assumption 1,

$$(H_*)_{\overline{\text{id}}(i,s), \overline{\text{id}}(\ell(i,s),s)} = 1, \quad (H_*)_{\underline{\text{id}}(i,s), \underline{\text{id}}(\ell(i,s),s)} = 1,$$

and all other entries are zero. Since $\ell(i, s) \in \mathcal{N}_i^{d^*}$, then H_* could be constructed according to (9) for some \underline{x} and \overline{x} . With H_* defined as such, rows $\underline{\text{id}}(i, s)$ and $\overline{\text{id}}(i, s)$ of $H_*\hat{A}$ are equal to rows $\underline{\text{id}}(\ell(i, s), s)$ and $\overline{\text{id}}(\ell(i, s), s)$ of \hat{A} , respectively (cf. Lemma 2). From the definition of \hat{A}^i , it is clear that $\|(\hat{A}^i)_s\|_1 = \|(\hat{A}^i)_{s+n}\|_1 = \|(\hat{A}^i)_{s+2n}\|_1$. Note that the gains T^i and L^i are computed by (12), which independently minimize the 1-norm of each row of \hat{A}^i , since the s^{th} rows of T^i and L^i only affect the s^{th} row of $\tilde{A}^i \triangleq T^i A - L^i C^i$. Moreover, Assumption 1 guarantees $\|(\tilde{A}^{\ell(i,s)})_s\|_1 < 1$ for each s . All of this implies $\|(H_*\hat{A})_{\underline{\text{id}}(i,s)}\|_1 = \|(H_*\hat{A})_{\overline{\text{id}}(i,s)}\|_1 < 1$. Since this holds for every row of the matrix $H_*\hat{A}$, then $\rho(H_*\hat{A}) \leq \|H_*\hat{A}\|_\infty \triangleq \max_{1 \leq i \leq 2nN} \sum_{s=1}^{2nN} |(H_*\hat{A})_{ij}| < 1$. ■

Even if Assumption 1 doesn't hold, or if the algorithm is run with $d < d^*$, it is possible that solving (12) will result in stabilizing gains which can be verified by Theorem 1.

V. NUMERICAL EXAMPLES

This section demonstrates the effectiveness of our distributed interval observer applied to two LTI target systems.

Example 1: Consider a system from [18] in the form of (1):

$$\begin{aligned} N &= 3, \\ n &= 4, \quad A = \begin{bmatrix} 1 & 0 & 1 & 0 \\ 0 & 1 & 0 & 1 \\ 0 & 0 & 1 & 0 \\ 0 & 0 & 0 & 1 \end{bmatrix}, \quad C^1 = [1 \ 0 \ 0 \ 0], \\ B &= I_4, \quad C^2 = [0 \ 1 \ 0 \ 0], \quad C^3 = [1 \ 1 \ 0 \ 0]. \end{aligned} \quad (13)$$

The network is fully connected, so $d = d^* = 1$. The initial state x_0 and the process noise w_k are bounded by $\underline{x}_0 = [-20 \ -15 \ -0.5 \ 0]^\top$, $\overline{x}_0 = [10 \ 25 \ 2 \ 3]^\top$, $\underline{w} = [-0.1 \ -0.1 \ -1 \ -1]^\top$ and $\overline{w} = [0.1 \ 0.1 \ 1 \ 1]^\top$, while v_k^i is bounded by $\underline{v}^i = -i$, $\overline{v}^i = i$, for $i = 1, 2, 3$. To show the advantage of including a network update in the observer design, we also implemented individual local observers for each agent i , i.e., using only (4) and local output y_k^i . The gains of the local observers are the same as in the distributed observer. Using CVX [23], [24] to solve the design LPs in (12), we obtained gains for each node:

$$\begin{aligned} L^1 &= [0 \ 0 \ -1 \ 0]^\top, L^2 = [0 \ 0 \ 0 \ -1]^\top, L^3 = -[0 \ 0 \ .5 \ .5]^\top, \\ \Gamma^1 &= [1 \ 0 \ 1 \ 0]^\top, \Gamma^2 = [0 \ 1 \ 0 \ 1]^\top, \Gamma^3 = [.5 \ .5 \ .5 \ .5]^\top, \\ T^1 &= \begin{bmatrix} 0 & 0 & 0 & 0 \\ 0 & 1 & 0 & 0 \\ -1 & 0 & 1 & 0 \\ 0 & 0 & 0 & 1 \end{bmatrix}, T^2 = \begin{bmatrix} 1 & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 \\ 0 & 0 & 1 & 0 \\ 0 & -1 & 0 & 1 \end{bmatrix}, T^3 = \begin{bmatrix} .5 & -.5 & 0 & 0 \\ -.5 & .5 & 0 & 0 \\ -.5 & -.5 & 1 & 0 \\ -.5 & -.5 & 0 & 1 \end{bmatrix}. \end{aligned}$$

Figure 1 shows the resulting framer trajectories and interval widths for each observer. All observers maintain a *correct* interval estimate, but some framers of the individual observers are clearly unstable. On the other hand, the distributed observer is able to maintain a tight interval around the true state trajectory, despite the unstable individual observers.

Example 2: Consider the following multi-agent system (a discretized version of the example from [20], with $\Delta_t = 0.01$) in the form of (1) with $N = 6$, $n = 12$, $A = I_6 \otimes \begin{bmatrix} 1 & 0.01 \\ 0 & 1 \end{bmatrix}$, $B = I_6 \otimes \begin{bmatrix} 0.01 & 0.0001 \\ 0 & .01 \end{bmatrix}$, and $C^i = \mathbf{e}_i \otimes [1 \ 0]$. The communication graph \mathcal{G} is a directed ring with nodes $\mathcal{V} = \{1, \dots, 6\}$ and edges $\mathcal{E} = \{(i, (i + 1 \bmod 6)) : i \in \mathcal{V}\}$. Moreover, the initial state is $x_0 = \mathbf{1}_6 \otimes [0.7032 \ 0.0457]^\top$ and the process noise is given by $w_k = \mathbf{1}_4 \otimes [\frac{1}{2} \sin(0.01k) \ 0 \ \frac{1}{5} \cos(0.01k)]^\top$, $\overline{w} = \mathbf{1}_4 \otimes [\frac{1}{2} \ 0 \ \frac{1}{5}]^\top$, $\underline{w} = \mathbf{1}_4 \otimes [-\frac{1}{2} \ 0 \ -\frac{1}{5}]^\top$. The measurement noise is given by $v_k^1 = v_k^4 = \frac{1}{5} \sin^2(0.01k)$, $v_k^2 = v_k^5 = 0$, and $v_k^3 = v_k^6 = \frac{1}{3} \cos(0.02k)$, with bounds $\overline{v}^1 = \overline{v}^4 = \frac{1}{5}$, $\overline{v}^2 = \overline{v}^5 = 0$, $\overline{v}^3 = \overline{v}^6 = \frac{1}{3}$, $\underline{v}^1 = \underline{v}^2 = \underline{v}^4 = \underline{v}^5 = 0$, and $\underline{v}^3 = \underline{v}^6 = -\frac{1}{3}$. The DIO gains for each node $i \in \mathcal{V}$ are $L^i = \mathbf{e}_i \otimes [0 \ -100]^\top$, $\Gamma^i = \mathbf{e}_i \otimes [1 \ 100]^\top$, $T^i = I_{12} + \mathbf{e}_i \mathbf{e}_i^\top \otimes \begin{bmatrix} -1 & 0 \\ -100 & 0 \end{bmatrix}$. Assumption 1 is satisfied with $d^* = 5$, but $d = 1$ still results in a stable observer. Figure 2 shows the state trajectories and interval widths from the DIO algorithm with $d = 1$. For comparison, we also plot the results of the continuous time distributed observer proposed in the work in [20]. As can be seen, our observer is able to maintain tighter intervals around the true states, which can be due to the advantage of using the equivalent system representation (7), solving LPs instead of SDPs and/or leveraging a more general observer structure.

VI. CONCLUSION AND FUTURE WORK

In this paper, a novel distributed interval observer synthesis was introduced for linear time-invariant discrete-time systems that are subject to bounded noise. At each time step, agents first individually compute upper and lower framers for the system state, based on their own observation of the system. Then, they communicate to their neighbors, exchanging and updating their estimates iteratively by selecting the tightest intervals among their agents' estimates. The true state trajectory of the system was guaranteed to be bounded by the updated framers. Furthermore, necessary and sufficient conditions assuring collective stability were provided. Such conditions were shown to be collectively achievable by contribution of all agents through solving tractable linear programs in a distributed manner. In addition, we provided an algorithm to verify if such sufficient conditions hold for a given system. Finally, the advantage of the proposed distributed design compared to its centralized version and also versus a benchmark observer in the literature was demonstrated through simulation examples. In future work, extension to nonlinear settings with time-varying networks, and the effect of adversarial agents and communication and measurement failures will be considered.




Fig. 1: States x_1 through x_3 (black), along with the upper (red) and lower (blue) framers (left) and interval widths $\delta_i \triangleq \bar{x}_i - \underline{x}_i$ (right) from the observers, for system (13). Superscripts 1–3 denote framers from individual agents 1–3, respectively, while the green marker (left) denotes the resulting estimate by DIO.




Fig. 2: State framers and interval widths from all agents for Example 2, from DIO (red) and the observer from [20] (blue).

REFERENCES

- [1] J. Zhao, A. Gomez-Exposito, M. Netto, L. Mili, A. Abur, V. Terzija, I. Kamwa, B. Pal, A.K. Singh, J. Qi, Z. Huang, and A.P. Meliopoulos. Power system dynamic state estimation: Motivations, definitions, methodologies and future work. *IEEE Transactions on Power Systems*, 34:3188–3198, 07 2019.
- [2] Y. Sun and H. Song. *Secure and trustworthy transportation cyber-physical systems*. Springer, 2017.
- [3] B. Cheng, J. Zhang, G.P. Hancke, S. Karnouskos, and A.W. Colombo. Industrial cyber-physical systems: Realizing cloud-based big data infrastructures. *IEEE Industrial Electronics Magazine*, 12(1):25–35, 2018.
- [4] R.E. Kalman. A new approach to linear filtering and prediction problems. *Transactions of the ASME—Journal of Basic Engineering*, 82(Series D):35–45, 1960.
- [5] F.F.C. Rego, A. M. Pascoal, A. P. Aguiar, and C. N. Jones. Distributed state estimation for discrete-time linear time invariant systems: A survey. *Annual Reviews in Control*, 48:36–56, 2019.
- [6] R. Olfati-Saber. Kalman-consensus filter: Optimality, stability, and performance. In *Proceedings of the 48th IEEE Conference on Decision and Control (CDC) held jointly with 2009 28th Chinese Control Conference*, pages 7036–7042, 2009.
- [7] A. T. Kamal, J. A. Farrell, and A. K. Roy-Chowdhury. Information weighted consensus filters and their application in distributed camera networks. *IEEE Transactions on Automatic Control*, 58(12):3112–3125, 2013.
- [8] Y. Wang, D.M. Bevly, and R. Rajamani. Interval observer design for LPV systems with parametric uncertainty. *Automatica*, 60:79–85, 2015.
- [9] F. Mazenc, T-N. Dinh, and S-I. Niculescu. Robust interval observers and stabilization design for discrete-time systems with input and output. *Automatica*, 49(11):3490–3497, 2013.
- [10] M. Khajenejad, F. Shoaib, and S.Z. Yong. Interval observer synthesis for locally Lipschitz nonlinear dynamical systems via mixed-monotone decompositions. In *American control Conference (ACC)*, accepted, <https://arxiv.org/pdf/2202.11689.pdf>, 2022.
- [11] A.M. Tahir and B. Açikmeşe. Synthesis of interval observers for bounded Jacobian nonlinear discrete-time systems. *IEEE Control Systems Letters*, 2021.
- [12] M. Khajenejad, Z. Jin, and S.Z. Yong. Interval observers for simultaneous state and model estimation of partially known nonlinear systems. In *American Control Conference (ACC)*, pages 2848–2854, 2021.
- [13] M. Khajenejad and S.Z. Yong. Simultaneous input and state interval observers for nonlinear systems with full-rank direct feedthrough. In *IEEE Conference on Decision and Control*, pages 5443–5448, 2020.
- [14] F. Mazenc and O. Bernard. Interval observers for linear time-invariant systems with disturbances. *Automatica*, 47(1):140–147, 2011.
- [15] E. Chambon, L. Burlion, and P. Apkarian. Overview of linear time-invariant interval observer design: towards a non-smooth optimisation-based approach. *IET Control Theory & Applications*, 10(11):1258–1268, 2016.
- [16] F. Cacace, A. Germani, and C. Manes. A new approach to design interval observers for linear systems. *IEEE Transactions on Automatic Control*, 60(6):1665–1670, 2014.
- [17] D. Efimov, T. Raïssi, S. Chebotarev, and A. Zolghadri. Interval state observer for nonlinear time varying systems. *Automatica*, 49(1):200–205, 2013.
- [18] D. Li, J. Chang, W. Chen, and T. Raïssi. IPR-based distributed interval observers design for uncertain LTI systems. *ISA Transactions*, 121, 03 2021.
- [19] X. Li, G. Wei, and D. Ding. Distributed resilient interval estimation for sensor networks under aperiodic denial-of-service attacks and adaptive event-triggered protocols. *Applied Mathematics and Computation*, 409:126371, 2021.
- [20] X. Wang, H. Su, F. Zhang, and G. Chen. A robust distributed interval observer for LTI systems. *IEEE Transactions on Automatic Control*, 2022.
- [21] V. D. Blondel and Y. Nesterov. Polynomial-time computation of the joint spectral radius for some sets of nonnegative matrices. *SIAM Journal on Matrix Analysis and Applications*, 31(3):865–876, 2010.
- [22] E.D. Sontag. Input to state stability: Basic concepts and results. In *Nonlinear and optimal control theory*, pages 163–220. Springer, 2008.
- [23] CVX Research, Inc. CVX: Matlab software for disciplined convex programming, version 2.0. <http://cvxr.com/cvx>, August 2012.
- [24] M. Grant and S. Boyd. Graph implementations for nonsmooth convex programs. In V. Blondel, S. Boyd, and H. Kimura, editors, *Recent Advances in Learning and Control*, Lecture Notes in Control and Information Sciences, pages 95–110. Springer-Verlag Limited, 2008.