

OPTIMAL CONTROL FOR PORT-HAMILTONIAN SYSTEMS AND A NEW PERSPECTIVE ON DYNAMIC NETWORK FLOW PROBLEMS

ONUR TANIL DOGANAY*, KATHRIN KLAMROTH*, BRUNO LANG*,
MICHAEL STIGLMAYR*, AND CLAUDIA TOTZECK*

Abstract. We formulate open-loop optimal control problems for general port-Hamiltonian systems with possibly state-dependent system matrices and prove their well-posedness. The optimal controls are characterized by the first-order optimality system, which is the starting point for the derivation of an adjoint-based gradient descent algorithm. Moreover, we discuss the relationship of port-Hamiltonian dynamics and minimum cost network flow problems. Our analysis is underpinned by a proof of concept, where we apply the proposed algorithm to static minimum cost flow problems and dynamic minimum cost flow problems with a simple directed acyclic graph. The numerical results validate the approach.

Key words. port Hamiltonian systems • ordinary differential equations • optimal control • minimum cost network flow • dynamic network flow.

AMS subject classifications. 93B70 • 49J15

1. Introduction. Port-Hamiltonian systems (PHS) were introduced in 1992 by Arjan van der Schaft and Bernhard Maschke in order to formalize the power-conserving coupling of dynamical systems on different domains [32]. By now, the PHS framework for modelling is well-established in the engineering community, in particular, the inherent features of energy conservation, elegant (de)coupling into sub-modules and PHS preserving control approaches using system theory are appreciated [42]. Initially, the main focus was on physical systems, but the abstract framework of Dirac structures [8] allows for straightforward generalizations attracting the interest of mathematicians. In the recent years, linear PHS with finite and infinite dimensional states became well-understood [22]. However, there are many open problems concerning nonlinear systems, differential-algebraic PH structures, stochastic PHS and optimization of PHS.

Concerning the optimization of PHS most approaches in the literature use closed-loop controllers, for example, by constructing a feedback that, in combination with the original system, yields again a PHS structure, see for example [5, 44], [28] for a variant based on Control-Lyapunov functions and the survey [33]. Open loop approaches are very recent [13, 31, 39, 23] and so far focused on minimizing the energy supply, which naturally leads to solutions with turnpike properties.

In this article we focus on the optimal control of general cost functionals constrained by nonlinear ODE-PHS. We introduce a general class of optimal control problems constrained by nonlinear ordinary differential equations (ODE) with PHS structure and analyze the well-posedness. In order to derive a gradient-descent algorithm we compute the first-order optimality system that characterizes the optimal control. As a first application of the general framework we consider dynamic minimum cost flow problems. Here, we exploit the intrinsic flow conservation property of PHS and recall the relation of the incidence matrix of the network and the skew-symmetric system matrix which is well-known in the context of PHS on graphs [42].

Network flow problems occur in a variety of applications, including routing prob-

*University of Wuppertal, Institute of Mathematical Modelling, Analysis and Computational Mathematics (doganay@uni-wuppertal.de, klamroth@uni-wuppertal.de, lang@uni-wuppertal.de, stiglmayr@uni-wuppertal.de, totzeck@uni-wuppertal.de)

blems, supply chain management applications, and combinatorial optimization problems like matching and assignment problems. We refer to [1] for a comprehensive introduction. Characteristic for network flow problems are the flow conservation constraints that guarantee that no flow is added or lost at any node and that the (external) supplies and demands are satisfied. Due to this flow conserving property, network flow problems lend themselves towards a port-Hamiltonian formulation. This is reported for example in [43] and will be further explored in this paper. As we shall see, PHS provide a general framework that can be used to model classical (static) flow conservation constraints as well as a wide range of dynamic network flow formulations, including flow dependent costs and constraints.

In this paper, we focus on minimum cost flow problems. They have several important special cases as, for example, shortest path problems, assignment problems, and maximum flow problems. In the static and linear case, minimum cost flow problems seek to send a constant amount of flow from a finite set of supply nodes to a finite set of demand nodes through a directed graph at minimum cost, obeying of course the flow conservation constraints. The edges of the graph usually have some upper and lower capacities limiting the amount of flow, and each unit of flow induces a fixed cost on every edge. Static minimum cost flow problems can be solved efficiently, for example, by the network simplex algorithm or by specific algorithms tailored, e.g., for sparse or dense networks. We refer again to [1] for a comprehensive introduction to the field, and to [27] for a numerical comparison of a variety of solution methods.

In many practical applications, static flows are not appropriate to model transportation processes, e.g., when considering flows of gas or liquids in pipes, or flows of cars, bicycles or pedestrians on streets that are subject to rush hour traffic and congestion. This is caused by the fact that supplies and demands as well as flow costs and travel times may vary over time and may depend on the (dynamic) flow values, hence requiring dynamic network flow models. These can also be characterized by a set of flow conservation constraints, that typically have to be satisfied at all points in time. See, for example, [3, 26, 35, 37, 40] for introductory surveys on dynamic network flow problems and for an array of potential applications.

An established way to handle flows over time is based on time-discretization and on the construction of so-called time-expanded networks, see, for example, [14, 17, 40]. By generating a copy of the (static) network for each time step and introducing arcs that reflect travel times between nodes by spanning over different time steps, dynamic network flows can be approximated by static network flows that can be computed using classical methods. However, this comes at the cost of a largely increased network complexity – and hence computational time – and becomes impractical for large real-world applications. Moreover, it is difficult to incorporate non-linear and flow dependent edge costs into the framework of time-expanded networks. One possible but rather rough approximation of flow dependent edge costs consists in introducing several (parallel) arcs with limited capacity and increasing costs, so that larger flow amounts are forced to use more expensive edges [25].

Alternatively, dynamic and non-linear network flows can be modelled by using differential equations on the individual edges and, if necessary, also in the nodes of the network. This is particularly well-suited whenever a high accuracy is needed, for example, when modelling gas or water networks. Due to the large computational complexity, however, these models are often limited to smaller instances. We refer to [7, 16, 20, 30] for exemplary results and applications.

The port-Hamiltonian flows that are considered in this paper can be viewed as a compromise between (cheap and inaccurate) discretized linear and static flows and (ac-

curate and complex) flow dynamics based on differential equations. Port-Hamiltonian flows cover static and dynamic models and allow for a wide range of further modelling options through the system matrices and via potential ports. We formulate tailored optimal control problems for PHS as the basis for gradient-based optimization approaches that are then applied to static and dynamic flow settings.

This paper is organized as follows. In Section 2 we formulate a general class of optimal control problems constrained by ODE systems with PHS structure. As we aim to derive a gradient-descent algorithm we assume that the control space admits a Hilbert structure and prove well-posedness of the state system as well as continuous dependence on the data in Carathéodory sense. These results are exploited in the proof of well-posedness of the optimal control problem. Then we derive the first-order optimality conditions which lay the ground for the gradient-descent algorithm. In Section 3 we discuss the relationship of the general PHS setting, especially PHS on graphs, and the special case of minimum cost network flow problems. As first application, we solve static minimum cost flow problems with the proposed framework. A proof of concept for dynamic minimum cost flow problems is given in Section 4. Then we draw our conclusion.

2. Optimal control of ODE with PHS structure. Let us assume to have a Hamiltonian $\mathcal{H}: \mathbb{R}^n \rightarrow \mathbb{R}$ of the form

$$(2.1) \quad \mathcal{H}(z(t)) = \frac{1}{2} z(t)^\top Q z(t), \quad Q \in \mathbb{R}^{n \times n} > 0$$

and the corresponding port-Hamiltonian system given by

$$(2.2a) \quad \frac{d}{dt} z = (J(z) - R(z)) Q z + B(z) u, \quad z(0) = \hat{z},$$

$$(2.2b) \quad y = B(z)^\top Q z,$$

where $J, R \in \text{Lip}_{\text{loc}}(\mathbb{R}^n, \mathbb{R}^{n \times n})$ with $J(z)^\top = -J(z)$ for all $z \in \mathbb{R}^n$, $R(z) \geq 0$ for all $z \in \mathbb{R}^n$ and the input matrix $B \in \text{Lip}_{\text{loc}}(\mathbb{R}^n, \mathbb{R}^{n \times m})$. Note that the output equation (2.2b) is just passive, that means once we obtained z , we can easily compute y .

2.1. The optimal control problem. We consider the task of finding an initial condition \hat{z} or input $u \in L^2(0, T; \mathbb{R}^m)$ (or both) that allows us to drive the dynamics either as close as possible to a desired state $z_{\text{des}} \in H^1(0, T; \mathbb{R}^n)$ or to find a dynamic that satisfies, for example, given supplies and demands at minimum cost in a network flow sense. To this end, we let $w = (u, \hat{z})$ and propose an optimal control problem given by

$$(P) \quad \min_{(z, w) \in Z \times W_{\text{ad}}} \mathcal{J}(z, w) \quad \text{subject to the dynamics (2.2),}$$

where

$$\mathcal{J}(z, w) := \int_0^T c(z(t), z_{\text{des}}(t)) dt + c_T(z(T), z_{\text{des}}(T)) + \frac{\lambda}{2} \|w\|^2$$

with cost functions $c, c_T : \mathbb{R}^n \times \mathbb{R}^n \rightarrow \mathbb{R}$. Z is the state space (see below for a specification), and W_{ad} is the set of admissible controls, which needs to be specified individually for each problem at hand. The first two terms of the cost functional allow us to define the main objective of the problem by penalizing undesired states over time or at time T , while the third term is optional. It is needed in case the set of admissible controls is unbounded.

For the derivation of the first order optimality system and the gradient, it is useful to have Riesz representation theorem, which requires controls from a Hilbert space. We therefore choose $u \in L^2(0, T; \mathbb{R}^m)$ in the following and consider solutions to the state system in Carathéodory sense.

Let $u \in L^2(0, T; \mathbb{R}^m)$ and $\hat{z} \in \mathbb{R}^n$. Then the right-hand side of (2.2a) given by

$$f(t, z) = (J(z) - R(z)) Q z + B(z) u(t)$$

is defined on the rectangle $\Omega = \{(t, z) : 0 \leq t \leq T, |z - \hat{z}| \leq b\}$ for $b > 0$. Moreover, it is a Carathéodory function, i.e., it holds

- (a) $f(t, z)$ is continuous in z for each fixed t ,
- (b) $f(t, z)$ is measurable in t for each fixed z ,
- (c) there is a Lebesgue-integrable function $m_\Omega : [0, T] \rightarrow [0, \infty)$ such that

$$|f(t, z)| \leq m_\Omega(t) \text{ for all } (t, z) \in \Omega.$$

Indeed, (a) holds by the assumptions on J, R, Q and B ; and (b) holds by the assumption on u . To show (c) we note that it holds

$$|f(t, z)| \leq \max_{z: |z-\hat{z}| \leq b} \left(\|J(z)\| + \|R(z)\| \right) \|Q\| |z| + \max_{z: |z-\hat{z}| \leq b} \|B(z)\| |u(t)| =: m_\Omega(t).$$

Furthermore, the assumptions on the system matrices yield the existence of a function $k_\Omega(t)$ such that

$$|f(t, z) - f(t, \tilde{z})| \leq k_\Omega(t) |z - \tilde{z}|, \quad (t, z), (t, \tilde{z}) \in \Omega.$$

Altogether we obtain the well-posedness of the state equation, see [19] for details.

THEOREM 2.1. *Let J, R, Q, B and u as above. Then for any \hat{z} there exists a unique absolutely continuous solution z satisfying (2.2) except on a set of Lebesgue measure zero and $z(0) = \hat{z}$.*

In particular, Theorem 2.1 yields $z \in H^1(0, T; \mathbb{R}^n)$. Hence, we define the state space $Z = H^1(0, T; \mathbb{R}^n)$. Let $W := L^2(0, T; \mathbb{R}^m) \times \mathbb{R}^n$, then we define the *control-to-state map*

$$S: W \rightarrow Z, \quad w = (u, \hat{z}) \mapsto z.$$

Furthermore, we use S to define the reduced cost functional

$$\hat{\mathcal{J}}(w) := \mathcal{J}(S(w), w).$$

We emphasize that using $\hat{\mathcal{J}}$ we treat the state constraint of the optimization problem (P) implicitly. In fact, we will derive an optimization algorithm based on the reduced form and only update the controls w to drive the dynamics to reduce the objective.

The next theorem shows the boundedness of the states with respect to the controls.

THEOREM 2.2. *Let J, R, Q, B and u as above. Then the state solution z to (2.2) is bounded by the control w . In more detail, there exists a constant $C > 0$ such that*

$$\|z\|_{H^1(0, T; \mathbb{R}^n)} \leq C \|w\|_W.$$

Proof. First, we bound the L^2 -norm of z . Note that the regularity of z shown in Theorem 2.1 implies the embedding $z \in C([0, T], \mathbb{R}^n)$ and in particular yields the existence of a constant $C_0 > 0$ such that

$$\max_{s \in [0, T]} (|J(z(s))| + |R(z(s))| + |B(z(s))|) \leq C_0.$$

Using the Young inequality and the Jensen inequality [2] we find

$$\begin{aligned} |z(t)|^2 &= 2|\hat{z}|^2 + 2 \left| \int_0^t (J(z(s)) - R(z(s))) Q z(s) + B(z(s)) u(s) \, ds \right|^2, \\ &\leq 2|\hat{z}|^2 + 4T \int_0^t |(J(z(s)) - R(z(s))) Q z(s)|^2 + |B(z(s)) u(s)|^2 \, ds \\ &\leq 2|\hat{z}|^2 + 4TC_0^2 \left(|Q|^2 \int_0^t |z(s)|^2 \, ds + \int_0^T |u(s)|^2 \, ds \right) \end{aligned}$$

for all $t \in [0, T]$. An application of the Gronwall inequality [12] gives us

$$|z(t)|^2 \leq \alpha e^{4TC_0^2|Q|^2t}$$

where

$$\alpha = 2|\hat{z}|^2 + 4TC_0^2 \int_0^T |u(s)|^2 \, ds.$$

Integration over $[0, T]$ yields the existence of $C_1 > 0$ such that

$$\|z\|_{L^2(0, T; \mathbb{R}^n)}^2 \leq C_1 (|\hat{z}|^2 + \|u\|_{L^2(0, T; \mathbb{R}^m)}^2).$$

Analogously, we obtain for the derivative

$$\begin{aligned} \left| \frac{d}{dt} z(t) \right|^2 &= |(J(z) - R(z)) Q z + B(z) u(t)|^2 \\ &\leq 2C_0^2 |Q|^2 |z(t)|^2 + 2C_0^2 |u(t)|^2 \\ &= 2C_0^2 |Q|^2 \left| \int_0^t \frac{d}{ds} z(s) \, ds \right|^2 + 2C_0^2 |u(t)|^2 \\ &\leq 2C_0^2 |Q|^2 T \int_0^t \left| \frac{d}{ds} z(s) \right|^2 \, ds + 2C_0^2 |u(t)|^2. \end{aligned}$$

Again, with Gronwall we obtain a constant $C_2 > 0$ such that

$$\left\| \frac{d}{dt} z \right\|_{L^2(0, T; \mathbb{R}^n)}^2 \leq C_2 \|w\|_W^2.$$

Adding the two bounds and taking the square root on both sides yields the desired result. \square

Before we begin with the theorem on the existence of optimal controls, we note that $\lambda > 0$ implies that the cost functional is coercive with respect to w and thus a minimizing sequence is bounded. Moreover, we introduce the state operator

$$e: H^1(0, T; \mathbb{R}^n) \times W \rightarrow X^* \times \mathbb{R}^n$$

implicitly as

$$\langle e(z, w), (\varphi_0) \rangle_{X^* \times \mathbb{R}^n, X \times \mathbb{R}^n} = \int_0^T \left(\frac{d}{dt} z - (J(z) - R(z)) Q z - B(z) u \right) \cdot \varphi dt + (z(0) - \hat{z}) \cdot \varphi_0$$

where $\varphi \in X = L^2(0, T; \mathbb{R}^n)$ and $\varphi_0 \in \mathbb{R}^n$.

THEOREM 2.3. *Let $\lambda > 0$ or $W_{ad} \subset W$ closed and bounded. Further, let J, R, B be weakly continuous and $c(z, z_{des})$ continuous and convex w.r.t. z and $c_T(z, z_{des})$ continuous and convex w.r.t. $z(T)$. Then there exists a solution to (P).*

Proof. We follow the lines of [21, 41] and consider a minimizing sequence $\{w_n\}_n \subset W_{ad}$, that means $w_n = (u_n, \hat{z}_n)$ with

$$\inf_w \hat{\mathcal{J}}(w) = \lim_{n \rightarrow \infty} \hat{\mathcal{J}}(w_n).$$

Either $\lambda > 0$ or the boundedness of W_{ad} ensures the boundedness of $\{w_n\}_n$. Note that W is a reflexive Hilbert space, hence there exists a weakly convergent subsequence $\{w_{n_k}\}_{n_k}$ with $w_{n_k} \rightharpoonup \bar{w} \in W$ as $k \rightarrow \infty$. We denote $\bar{w} = (\bar{u}, \bar{z})$ in the following. Theorem 2.2 yields the boundedness of

$$\{S(w_{n_k})\} \subset H^1(0, T; \mathbb{R}^n)$$

and by reflexivity of the space we obtain the existence of \bar{z} such that $S(w_{n_k}) =: z_{n_k} \rightharpoonup \bar{z}$ as $k \rightarrow \infty$. We emphasize that at this stage it is not clear that \bar{z} is the state solution for the control \bar{w} . We prove this in the following. Indeed, the weak continuity of J, R and B and the weak convergence of z_{n_k} in $H^1(0, T; \mathbb{R}^n)$ allow us to obtain

$$\begin{aligned} \int_0^T \varphi(t) \frac{d}{dt} (z_{n_k}(t) - \bar{z}(t)) dt &\longrightarrow 0, \\ \int_0^T \varphi(t) (J(z_{n_k}(t)) - J(\bar{z}(t)) - (R(z_{n_k}(t)) - R(\bar{z}(t)))) Q z_{n_k}(t) dt &\longrightarrow 0, \\ \int_0^T \varphi(t) (J(\bar{z}(t)) - R(\bar{z}(t))) (z_{n_k}(t) - \bar{z}(t)) dt &\longrightarrow 0, \\ \int_0^T \varphi(t) B(z_{n_k}(t)) (w_{n_k}(t) - \bar{w}(t)) + (B(z_{n_k}(t)) - B(\bar{z}(t))) \bar{w}(t) dt &\longrightarrow 0, \end{aligned}$$

for all test functions $\varphi \in L^2(0, T; \mathbb{R}^n)$, which implies the weak continuity of the state operator e , i.e. $e(z_{n_k}, w_{n_k}) \rightharpoonup e(\bar{z}, \bar{w})$. By the weak lower semi-continuity of the norm we find

$$0 \leq \|e(\bar{z}, \bar{w})\| = \liminf_{k \rightarrow \infty} \|e(z_{n_k}, w_{n_k})\| = 0,$$

which proves that $\lim_{k \rightarrow \infty} S(w_{n_k}) = \lim_{k \rightarrow \infty} z_{n_k} = \bar{z}$.

We note that the continuity and convexity of $c(z, z_{des})$ and $c_T(z(T), z_{des}(T))$ imply the weak-lower semicontinuity of \mathcal{J} and moreover of $\hat{\mathcal{J}}$. This allows to conclude that

$$\hat{\mathcal{J}}(\bar{w}) \leq \liminf_{k \rightarrow \infty} \hat{\mathcal{J}}(w_{n_k}) = \inf_w \hat{\mathcal{J}}(w),$$

which proves that \bar{w} is an optimal control. \square

In the following, we formally compute the optimality system that allows us to characterize candidates for optimal controls. We remark that more regularity of the system matrices is required to make the following results rigorous.

2.2. First-order optimality system. We use a Lagrangian approach to derive the first-order optimality system formally. We therefore introduce the Lagrangian corresponding to (P) as

$$\mathcal{L}(z, w, \varphi) = \mathcal{J}(z, w) - \langle e(z, u), (\varphi_0) \rangle_{X^* \times \mathbb{R}^n, X \times \mathbb{R}^n}.$$

The first-order optimality system is now characterized by the solution of $d\mathcal{L} = 0$. In more detail,

$$d_\varphi \mathcal{L} = \frac{d}{dt} z - (J(z) - R(z)) Q z - B(z) u = 0, \quad d_{\varphi_0} \mathcal{L} = z(0) - \hat{z} = 0,$$

which is the state equation. For the adjoint equation we compute for an arbitrary direction $h \in Z$

$$\begin{aligned} d_z \mathcal{L}(z, w, \varphi)[h] &= \int_0^T c'(z, z_{\text{des}}) \cdot h \, dt + c'_T(z(T), z_{\text{des}}(T)) \cdot h(T) - h(0) \cdot \varphi_0 \\ &\quad - \int_0^T \frac{d}{dt} h \cdot \varphi - (J'(z)[h] - R'(z)[h]) Q z \cdot \varphi \, dt \\ &\quad - \int_0^T (J(z) - R(z)) Q h \cdot \varphi - B'(z)[h] u \cdot \varphi \, dt \end{aligned}$$

Assuming $\varphi \in Z$ we integrate by parts to obtain

$$\begin{aligned} d_z \mathcal{L}(z, w, \varphi)[h] &= -h(0) \cdot \varphi_0 - [h \cdot \varphi]_0^T \\ &\quad + \int_0^T c'(z, z_{\text{des}}) \cdot h \, dt + c'_T(z(T), z_{\text{des}}(T)) \cdot h(T) \\ &\quad - \int_0^T \left(-\frac{d}{dt} \varphi - (J'(z)^*[\varphi \otimes Qz] - R'(z)^*[\varphi \otimes Qz]) \right. \\ &\quad \left. - Q^\top (J(z) - R(z))^\top \varphi + B'(z)^*[\varphi \otimes u] \right) \cdot h \, dt \end{aligned}$$

Since h is arbitrary we can choose $h(0) = 0$ and $h(T) = 0$ to identify the adjoint equation with the help of the variational lemma

$$\begin{aligned} -\frac{d}{dt} \varphi &= c'(z, z_{\text{des}}) + (J'(z)^*[\varphi \otimes Qz] + R'(z)^*[\varphi \otimes Qz]) \\ &\quad + Q^\top (J(z) - R(z))^\top \varphi - B'(z)^*[\varphi \otimes u], \\ \varphi(T) &= c'_T(z(T), z_{\text{des}}(T)). \end{aligned}$$

The optimality condition is an inequality as W_{ad} is possibly bounded. Hence an optimal control \bar{w} satisfies

$$\langle d_w \mathcal{L}(z, w, \varphi), w - \bar{w} \rangle \geq 0 \quad \text{for all } w \in W_{\text{ad}}.$$

Following the same steps as above, we obtain

$$(2.3) \quad (\lambda \bar{z} + \varphi(0)) \cdot (\hat{z} - \bar{z}) + \int_0^T \lambda \bar{u}(t) + B(\bar{z})^\top \varphi \cdot (u(t) - \bar{u}(t)) \, dt \geq 0$$

for all $w = (u, \hat{z},) \in W_{\text{ad}}$.

To derive the gradient of the reduced cost functional $\hat{\mathcal{J}}(w)$ we first compute the Gâteaux derivative in direction h which yields

$$\begin{aligned} d_w \hat{\mathcal{J}}(w)[h] &= \int_0^T d_z \mathcal{J}(z, w) \cdot S'(w)h + d_w \mathcal{J}(z, w) \cdot h \, dt \\ &= \int_0^T (S'(w)^* d_z \mathcal{J}(z, w) + d_w \mathcal{J}(z, w)) \cdot h \, dt \\ &= \int_0^T d_w \mathcal{L}(z, w, \varphi) \cdot h \, dt. \end{aligned}$$

Together with (2.3) this allows us to identify the gradient as

$$\nabla \hat{\mathcal{J}}(w) = \begin{pmatrix} \lambda u(t) + B(z)^\top \varphi \\ \lambda \hat{z} + \varphi(0) \end{pmatrix}.$$

We employ this to propose a projected gradient descent algorithm for the optimal control problem [21].

Algorithm 2.1 Gradient descent algorithm for (P)

- 1: **initialize:** feasible initial guess w , PHS functions $J(z), R(z), B(z), Q$, and other algorithmic parameters
 - 2: solve state problem to get $S(w)$
 - 3: solve adjoint problem to get φ for given $S(w)$ and w
 - 4: identify the gradient and project to \mathcal{W}_{ad} to obtain $P_{\mathcal{W}_{\text{ad}}}(\nabla \hat{\mathcal{J}}(w))$
 - 5: **while** $|P_{\mathcal{W}_{\text{ad}}}(\nabla \hat{\mathcal{J}}(w))| \geq \epsilon_{\text{stop}}$ **do**
 - 6: choose appropriate step size σ with Armijo rule
 - 7: $w \leftarrow w - \sigma P_{\mathcal{W}_{\text{ad}}}(\nabla \hat{\mathcal{J}}(w))$
 - 8: solve state problem to get $S(w)$
 - 9: solve adjoint problem to get φ for given $S(w)$ and w
 - 10: identify the gradient and project to \mathcal{W}_{ad} to obtain $P_{\mathcal{W}_{\text{ad}}}(\nabla \hat{\mathcal{J}}(w))$
 - 11: **end while**
 - 12: **return** optimized control w
-

In the following, we focus on PHS that model dynamic network flows. One important feature is flow conservation. In particular, this will constrain the set of admissible controls and lead to interesting projection operators. Before we go into the details and numerical results for static network flow problems, we establish the relationship of the general optimal control for ODEs with PH structure and static and dynamic network flow problems.

3. Port-Hamiltonian formulation of network flows. In this section we reinterpret a standard static network flow problem as a special case of a PHS constrained optimal control problem as introduced in Section 2. While this can not be expected to lead to competitive solution approaches as compared to well-established network optimization algorithms (see, e.g., [1]), the PHS perspective offers a wide array of modelling options that go far beyond static network flows. This will be exemplified with time dynamic network flow problems in Section 4.

Minimum cost flow problems have an array of applications in operations research and thus have been extensively investigated since the 1960s, see, e.g., [1, 6, 9, 15]. While the original formulation considers a static situation and constant flow costs,

there are extensions to the dynamic case with flow dependent costs. However, linear network flow models require extensive reformulation and linearization techniques to approximate time dynamics and/or non-linearity of flow costs. To avoid these reformulations which generally lead to a dramatic increase of the network size (in terms of the number of nodes and edges) we suggest a port-Hamiltonian formulation of network flows which intrinsically covers non-linear costs and time-dynamic flows.

Towards this end, let $G = (V, E)$ be a finite directed and connected graph with node set $V = \{1, \dots, N_v\}$ and edge set $E \subset V \times V$, with $|V| = N_v$ and $|E| = N_e$. An edge $e \in E$ from node i to node j , $i \neq j$, is denoted by $e = (i, j)$. The node arc incidence matrix $A \in \{-1, 0, 1\}^{N_v \times N_e}$ contains one column for every edge $e = (i, j) \in E$ such that $a_{ie} = 1$, $a_{je} = -1$, and $a_{ke} = 0$ for all $k \in V \setminus \{i, j\}$. Note that the rows of A sum to the zero vector since each column contains exactly one entry equal to $+1$ and one entry equal to -1 . Hence, A is not of full rank. Whenever a full-rank matrix is required in the following, we will omit an arbitrary but fixed row of A (e.g., its last row) which yields the so-called full-rank node arc incidence matrix that still contains the same information as A .

In a static network flow problem we usually assume that finite supplies and demands $b_i \in \mathbb{R}$ are associated with every node $i \in V$, satisfying $\sum_{i \in V} b_i = 0$ (i.e., the sum of all demands equals the sum of all supplies), and that non-negative costs $c_e \in \mathbb{R}_+$ are associated with all edges $e \in E$. Moreover, all edges $e \in E$ have associated flow bound constraints x_e^ℓ (lower bounds) and x_e^u (upper bounds), with $x_e^\ell \leq x_e^u$ for all $e \in E$. If not stated otherwise, we assume that $x_e^\ell = 0$ for all $e \in E$. The goal is then to identify a minimum cost flow solution $x \in \mathbb{R}^{N_e}$ that satisfies the flow bound constraints on all edges and the flow conservation constraints in all nodes in the sense that the difference between inflow and outflow at every node equals the supplies and demands at the respective nodes. Comprising all data for supplies and demands, costs, and capacities by $b \in \mathbb{R}^{N_v}$ and $c, x^\ell, x^u \in \mathbb{R}_+^{N_e}$, respectively, the static *minimum cost flow problem* (**MCFP**) can be formulated as

$$\begin{aligned}
 \text{(MCFP)} \quad & \min \quad c^\top x \\
 & \text{s. t.} \quad Ax = b \\
 & \quad \quad x^\ell \leq x \leq x^u.
 \end{aligned}$$

We will assume throughout this paper that (**MCFP**) is feasible. An example problem with one supply node (node 1) and four demand nodes (nodes 2 to 5) is illustrated in Figure 1.

In principle, any optimization algorithm for linear programs can be used to solve (**MCFP**). However, the specific structure of network flow problems can be exploited to significantly improve the computational performance. The network simplex algorithm and its variants (see again [1]) rely on highly efficient updates in the residual network and have become state-of-the-art solution techniques over the years.

3.1. Static flows as a special case of dynamic flows. In order to cast static network flow problems in the port-Hamiltonian framework (2.2), we interpret a static flow $\hat{x} \in \mathbb{R}^{N_e}$ as a special case of a dynamic flow $x \in H^1(0, T; \mathbb{R}^{N_e})$, where $x(t) = \hat{x}$ for all $t \in [0, T]$ is desired to be constant over time. Motivated by [43], we apply the optimal control of port-Hamiltonian systems to the optimal control of (static) network flows, see also [11]. We hence consider flow not only on the edges of the network G , but also consider associated potentials, or pressure, in the nodes which are now interpreted as reservoirs. Let $\hat{\rho}_v \in \mathbb{R}$ denote a (static) potential (or pressure) in node $v \in V$, and let $\hat{\rho} \in \mathbb{R}^{N_v}$ denote the vector of node potentials. Similar to the




Fig. 1: Illustrative example of a network flow problem with five nodes, i.e., $V = \{1, \dots, 5\}$, seven edges $E = \{(1, 2), (1, 4), (2, 3), (3, 1), (3, 4), (4, 5), (5, 1)\}$, and node arc incidence matrix A . The supplies and demands b_i , $i = \{1, \dots, 5\}$ are indicated next to the nodes, and the upper capacity bounds and costs (x_e^u, c_e) are indicated next to the edges. We assume that all lower bounds are equal to zero ($x^\ell = 0$). Note that one possible (non-optimal) feasible flow with cost 20 is given by $x = (4, 2, 3, 2, 0, 1, 0)^\top$.

flow values on the edges, these could be interpreted as a special case of dynamic node potentials $\rho \in H^1(0, T; \mathbb{R}^{N_v})$, where again $\rho(t) = \hat{\rho}$ for all $t \in [0, T]$ is desired in the static case. The flow conservation constraints (over time) can then be generalized to the system

$$(3.1a) \quad \frac{d}{dt} \rho = A x + u^\rho, \quad \rho(0) = \hat{\rho},$$

$$(3.1b) \quad \frac{d}{dt} x = -A^\top \rho, \quad x(0) = \hat{x},$$

where $u^\rho \in H^1(0, T; \mathbb{R}^{N_v})$ denotes external inputs (i.e., supplies and demands) at the nodes. Note that (3.1a) ensures that the rate of change of the potential in any node v equals the sum of in- and outflows on the incident edges, possibly plus some (external) input u_v^ρ . Similarly, (3.1b) guarantees that the rate at which the flow changes in any edge $e = (i, j)$ is equal to the difference $\rho_j - \rho_i$ of the potentials (or pressure) at the respective end nodes. Note that the node potentials ρ from (3.1) are somewhat related to the dual variables of (MCFP) that are also called node potentials in the network flow context (see, e.g., [1]). Similarly, potential-based flow networks (see, e.g., [4, 10, 38]) use node potentials to constrain the flow on the edges through physically motivated constraints.

In the static case, i.e., when $\rho = \hat{\rho}$ and $x = \hat{x}$ are constant over time, we recover the flow conservation constraints $A x = b$ of (MCFP) from (3.1a), where we set $u^\rho = -b$. In addition, (3.1b) then yields for $u^x = 0$ that $-A^\top \rho = 0$, which is satisfied for $\rho = \hat{\rho} = 0$, i.e., with zero potentials in the nodes.

Now set $n = N_v + N_e$ and let $z = (\rho, x)^\top \in H^1(0, T; \mathbb{R}^n)$. For completeness, we define $u^x \in H^1(0, T; \mathbb{R}^{N_e})$ as possible external inputs (i.e., inflows or leaks) at the edges and set $u = (u^\rho, u^x)^\top \in H^1(0, T; \mathbb{R}^n)$. Then the system (3.1) can be rewritten as the port-Hamiltonian system

$$(3.2) \quad \frac{d}{dt} z = J(z) Q z + B(z) u, \quad z(0) = \hat{z},$$

where

$$J(z) = J = \begin{pmatrix} 0 & A \\ -A^\top & 0 \end{pmatrix}, \quad Q = I \in \mathbb{R}^{n \times n}, \quad \text{and} \quad B(z) = B = \begin{pmatrix} I & 0 \\ 0 & 0 \end{pmatrix} \in \mathbb{R}^{n \times n}.$$

This is a special case of the port-Hamiltonian system (2.2) with $R(z) = 0 \in \mathbb{R}^{n \times n}$. When a solution z of the system (3.2) is known, then the output of the system can be easily computed as $y = B^\top z = (\rho, 0)^\top \in \mathbb{R}^n$.

In the following, we first utilize a linear program based on the KKT conditions of (3.1) as the projection applied in Algorithm 2.1, which is an equivalent way to formulate the static problem (MCFP). Next, we apply a projection on the space of circulations, i.e., $\{x \in \mathbb{R}^{N_e} : Ax = 0\}$, paired with a barrier function to achieve results that satisfy the (ε -relaxed) capacity constraints, i.e., $x_e^\ell - \varepsilon \leq x_e \leq x_e^u + \varepsilon$, $\varepsilon > 0$, to also solve the static problem (MCFP). Finally, we move toward dynamic time-dependent problems and investigate a small instance with two different time-dependent cost functions.

3.2. Static flows using projections and KKT conditions. We now consider the static case and set $u^\rho = -b$ as discussed above. Note that u^ρ is thus fixed and no longer a control variable. We hence optimize only over the initial condition $\hat{z} = (0, \hat{x})$, where the cost functional of the control problem is given by

$$\mathcal{J}(z, w) = \frac{1}{T} \int_0^T c^\top x(t) dt = c^\top \hat{x}.$$

In the following, we consider $\hat{\mathcal{J}}$ as defined in Section 2.

As stated above, in our first approach we utilize the KKT conditions of our formulation for the projection of the gradient $\nabla \hat{\mathcal{J}}(w)$. Recall that an optimal control \bar{w} satisfies

$$(3.3) \quad \langle \nabla \hat{\mathcal{J}}(w), w - \bar{w} \rangle \geq 0 \quad \text{for all } w \in W_{\text{ad}},$$

where, for simplicity, we consider only the controllable variables \hat{x} and hence set $W_{\text{ad}} = \{\hat{x} \in \mathbb{R}^{N_e} : A\hat{x} = b, x^\ell \leq \hat{x} \leq x^u\}$. In an iteration of the gradient descent Algorithm 2.1 we are interested in a direction $h = w - \bar{w}$ such that we achieve equality in (3.3). Towards this end, we investigate the linear program

$$(3.4) \quad \begin{aligned} \min_h \quad & \nabla \hat{\mathcal{J}}(w)^\top h \\ \text{s.t.} \quad & Ah = 0, \\ & x^\ell - \hat{x} \leq h \leq x^u - \hat{x}, \end{aligned}$$

Note that the constraints of (3.4) ensure that h is a circulation in the static network flow problem (MCFP), i.e., that in Algorithm 2.1 the control updated via the projected gradient $P_{W_{\text{ad}}}(\nabla \hat{\mathcal{J}}(w))$ is still feasible. Moreover, for an optimal direction \bar{h} of the linear program (3.4), i.e., $P_{W_{\text{ad}}}(\nabla \hat{\mathcal{J}}(w)) = \bar{h}$, it holds that $\bar{w} = w - \bar{h}$. Thus, solving (3.4), i.e., computing the path from w to \bar{w} , is equivalent to solving (MCFP), i.e., computing \bar{w} directly.

We test the presented approach on the same test cases as in [29] which are generated via NETGEN, see [24]. We acquired the files containing the test instances on the 23rd of November 2022 from the electronic library of *Zuse Institute Berlin*¹ which are

¹<http://elib.zib.de/pub/mp-testdata/mincost/netg/index.html>

unfortunately not available anymore but are reproducible via [29, 24]. Furthermore, since the test cases in [29] are rather large, we also include three small exemplary networks (ep1-3) on which we test our approach, see, Figure 2. The numerical experiments are implemented in *Python* (version 3.8.15) using *Anaconda* (version 4.12.0). For the numerical integration of the ordinary differential equations we apply the symplectic Euler scheme, see, e.g., [18]. Furthermore, all linear programs are solved with *IBM ILOG CPLEX* (version 20.1.0.0), since we experienced some issues with the open-source linear program solvers of the Python packages “*networkx*”, which returns correct optimal objective function values but, surprisingly, infeasible solutions, and “*scipy.optimize*” where some optimal objective values were incorrect. To compare our approach, we compute relative errors of the optimized solutions of the static minimal cost network flow problem (MCFP) to the ones resulting from *CPLEX*. We emphasize that for all test cases of [29] and ep1-3 only one gradient step is needed to achieved a relative error of 0.0 with Algorithm 2.1. This is due to the fact that (MCFP) is actually an equivalent reformulation of the static minimal cost network flow problem.

3.3. Static flows using orthogonal projections and barrier terms. We use the same problem formulation for static network flows as in Section 3.2. Instead of including the capacity constraints into the projection, one can use penalty or barrier methods to obtain feasible flows. In this case, a projection is only required to map the flows to the affine-linear space of flows satisfying the flow conservation constraints, i.e., $\{x \in \mathbb{R}^{N_e} : Ax = b\}$. Penalty and barrier methods both relax (some or all) constraints and penalize constraint violations in the objective function. In the penalty method a penalization term is added to the objective function that is zero if the constraints are satisfied and goes to infinity for increasing constraint violation. On the other hand, in the barrier method a barrier term is added to the objective function that tends to infinity when approaching the boundary of feasible set from the inside. A comprehensive discussion of penalty and barrier methods is, for example, given in [34]. To satisfy the flow conservation constraints after a gradient step, we project the gradient $\nabla \hat{\mathcal{J}}(w)$ to the space of circulations, i.e., $\{x \in \mathbb{R}^{N_e} : Ax = 0\}$. Towards this end, we utilize the following orthogonal projection, see, e.g., [36],


$$(3.5) \quad P_{\text{Wad}}(\nabla \hat{\mathcal{J}}(w)) = (I - A^\top (A A^\top)^{-1} A) \nabla \hat{\mathcal{J}}(w),$$

where I is the identity matrix of the same dimension as $A^\top A$. Furthermore, in order to achieve results that do not violate the (ε -relaxed) capacity constraints we use logarithmic functions as a barrier term in our numerical tests, i.e.,


$$\Theta(x) := \Theta(x, \alpha, \varepsilon) := -\alpha \left(\sum_{e \in E} (\ln((x_e^u - x_e + \varepsilon)) + \ln((x_e - x_e^\ell + \varepsilon))) \right),$$

where $\alpha > 0$ is a penalization parameter and $\varepsilon > 0$ is a small constant. If the flow value x_e on an edge $e \in E$ reaches one of the flow bounds x_e^u or x_e^ℓ then $\Theta(x)$ becomes large. Since the feasible set of network flow problems has a specific polyhedral structure, optimal flow solutions often have flow values that are on the boundary of the feasible set, i.e., that satisfy flow bound constraints with equality on many edges. This is also the case for standard choices for the starting solution. Therefore, we relax the flow bound constraints to $x^\ell - \varepsilon \leq x \leq x^u + \varepsilon$ in the barrier function $\Theta(x)$ since otherwise already the starting solution would lead to unbounded cost values. The cost functional including the barrier term now reads


$$\mathcal{J}_\Theta(z, w) := \mathcal{J}(z, w) + \int_0^T \Theta(x(t)) dt.$$



(a) Exemplary problem 1 (ep1) with 8 nodes and 15 edges.



(b) Exemplary problem 2 (ep2) with 6 nodes and 9 edges.



(c) Exemplary problem 3 (ep3) with 10 nodes and 20 edges.

Fig. 2: Exemplary minimum cost network flow problems (ep1-3). In all cases we assume $x_e^l = 0$ and $x_e^u = 20$ for each edge, and the values next to the edges denote the cost of the edges.


Name	α_0	ε_0	Relative Error w.r.t. (MCFP) solution
ep1	0.7	1.3	0.0392
ep2	1.0	2.0	0.0277
ep3	0.7	1.1	0.0430

Table 1: Results after 300 iterations with 20 Armijo steps for test instances (ep1-3) with geometrically decreasing α and ε .


For the implementation of Algorithm 2.1 we normalize the cost vector $c = (c_e)_{e \in E}$ with the maximum cost of the edges, i.e., $\bar{c} = (c_e / \max c)_{e \in E}$, to ensure that for each test instance the value of α can be chosen from a comparable range. During the optimization process we decrease the values of α and ε after each gradient step in Algorithm 2.1, thus decreasing the influence of the barrier term and the relaxation. We remark that the parameter tuning for this problem is not straightforward since it is unfortunately instance dependent. Further, note that Θ , due to the logarithmic terms, favours flow values in the middle of the intervals $[x^\ell - \varepsilon, x^u + \varepsilon]$. Thus, this approach has problems computing solutions that are on the boundaries, and hence it is not likely to find optimal flow solutions which are usually extreme points of the polyhedral feasible set. Nevertheless, the combination of the projection (3.5) and the barrier function Θ allows us to extend this approach for dynamic time-dependent network flow problems, as investigated in the following section.

Due to the required instance dependent parameter tuning we narrow our numerical experiment to the exemplary problems (ep1-3). As initial flows for Algorithm 2.1 we select the optimal solutions of the maximization problem with the same objective function and constraints as (MCFP), i.e., the worst case solutions. The results after 300 iterations and a maximum of 20 Armijo iterations in Algorithm 2.1 with a geometric decrease of α and ε after each gradient step k , where we applied the update scheme $\alpha_{k+1} = 0.9 \alpha_k$ until $\alpha_k = 0.01$ is reached and $\varepsilon_{k+1} = 0.99 \varepsilon_k$, are shown in Table 1. Here, we choose $\sum_{e \in E} |P_{\mathcal{W}_{\text{ad}}}(\nabla \hat{\mathcal{J}}(w))_e| < 10^{-6}$ as a stopping condition which was not satisfied during the 300 iterations, i.e., the approaches did not converge and stopped after the maximum number of iterations. However, we observe that for all problems ep1-3 there are no significant changes to the costs of the solutions after approximately 150 iterations, see Figure 3. Furthermore, for all three problems we achieved a relative error of below 5% where graphs with a larger number of edges led to larger relative errors w.r.t. the solutions of (MCFP). The reason is that the barrier term Θ pushes the flow value away from the boundaries towards the middle of the interval $[x_e^\ell - \varepsilon, x_e^u + \varepsilon]$ for each edge, and hence for a larger number of edges the deviation from the optimal solution, which is an extreme point, may grow, accumulating in a potentially larger relative error.


4. Time-dependent network flow problems. In this section, we extend our approach to dynamic time-dependent problems and show a proof-of-concept with two different time-dependent cost functions. We consider time-dependent network flow



(a) Exemplary problem 1 (ep1) – cost wrt. gradient steps



(b) Exemplary problem 2 (ep2) – cost wrt. gradient steps



(c) Exemplary problem 3 (ep3) – cost wrt. gradient steps

Fig. 3: Cost for 300 gradient steps with 20 Armijo iterations for exemplary problems (ep1–3). The red lines show the optimal costs of (MCFP) for these problems.

problems with relaxed flow bound constraints

$$\begin{aligned}
 (4.1) \quad \min \quad & \mathcal{J}(z, w), \quad \mathcal{J}(z, w) = \int_0^T \sum_{e \in E} c_e(t) x_e(t) + \frac{\lambda}{2} \left| \frac{d}{dt} u^x(t) \right|^2 dt \\
 \text{s.t.} \quad & \frac{d}{dt} \rho = A x, & \rho(0) = \hat{\rho}, \\
 & \frac{d}{dt} x = -A^\top \rho + u^x, & x(0) = \hat{x}, \\
 & x^\ell - \varepsilon \leq x \leq x^u + \varepsilon,
 \end{aligned}$$

where, using the notation from (P), $w = (u, \hat{z})$, and $\varepsilon > 0$.

We now assume that $u^\rho = 0$ and \hat{z} are given and fixed (and not part of the optimization). In the following, we omit the fixed components u^ρ and \hat{z} of w and identify w with u^x for better readability. In particular, we allow only to vary the flow on circulations in the network which leads us to the admissible set given by

$$W_{\text{ad}} = \left\{ u^x \in H^1((0, T); \mathbb{R}^{N_e}) : u^x(0) = 0, \quad A u^x(t) = 0 \quad \text{a.e. in } (0, T) \right\}.$$

In addition to ensuring that the flow conservation constraints are satisfied a.e. in $(0, T)$, this admissible set guarantees that the control does not change the initial condition \hat{x} . Note that the cost functional penalizes $\|\frac{d}{dt}u^x\|^2$ which corresponds to the assumption that adjusting the redirection of flow is expensive.

Remark 4.1. We note that in $W = \{u^x \in H^1((0, T); \mathbb{R}^{N_e}) : u^x(0) = 0\}$ the norms $\|\frac{d}{dt}u^x\|_{L^2}$ and $\|u^x\|_{H^1}$ are equivalent. In particular, there exist $c_1, c_2 > 0$ such that $c_1\|u^x\|_2^2 \leq \|\frac{d}{dt}u^x\|_2^2 \leq c_2\|u^x\|_2^2$ for each $u^x \in W$. Hence, for $\lambda > 0$ the cost function $\mathcal{J}(z, w)$ from (4.1) is coercive and the result on the existence of optimal controls can be directly applied.

We use the barrier approach from Section 3.3 to ensure the ε -relaxed capacity constraints analogous to Section 3.3. The derivative of this barrier term appears also in the adjoint system and is given by

$$\begin{aligned} -\frac{d}{dt}\nu &= -A^\top p + c_\rho(t), & \nu(T) &= 0, \\ -\frac{d}{dt}p &= A\nu + c_x(t) + \nabla\Theta(x(t)), & p(T) &= 0. \end{aligned}$$

The computation of the gradient is a bit more involved, since we consider $W_{\text{ad}} \subset H^1((0, T); \mathbb{R}^{N_e})$ here. We therefore first compute the linearization of $\hat{\mathcal{J}}(w)$ and then solve an additional problem to identify the gradient using the Riesz representation theorem. Numerical tests indicate that it is favourable to employ an equivalent H^1 -norm weighted by λ . Indeed, for $\lambda > 0$ we use

$$\|u^x\|_\lambda^2 := \|u^x\|_{L^2}^2 + \lambda \left\| \frac{d}{dt}u^x \right\|_{L^2}^2.$$

This leads to

$$d_{u^x}\mathcal{J}((z, u^x))[h] = \int_0^T \lambda \frac{d}{dt}u^x \cdot \frac{d}{dt}h + p \cdot h \, dt.$$

Afterwards, the gradient g_{u^x} is identified by solving

$$\int_0^T g_{u^x} \cdot h + \lambda \frac{d}{dt}g_{u^x} \cdot \frac{d}{dt}h \, dt = \int_0^T \lambda \frac{d}{dt}u^x \cdot \frac{d}{dt}h + p \cdot h \, dt \quad \text{for all } h$$


for g_{u^x} . Numerically, we solve the problem in strong formulation, i.e.,

$$g_{u^x} - \lambda \frac{d^2}{dt^2}g_{u^x} = \lambda \frac{d^2}{dt^2}u^x + p,$$

with finite differences, where we incorporate the boundary conditions $u^x(0) = 0$, $\frac{d}{dt}u^x(0) = 0 = \frac{d}{dt}u^x(T)$ in the difference operator. The gradient g_{u^x} is then projected to the feasible set to satisfy the flow conservation constraints. For the projection of $g_{u^x}(t)$ we again utilize the orthogonal projection

$$(4.2) \quad P_{W_{\text{ad}}}(g_{u^x}(t)) = (I - A^\top(AA^\top)^{-1}A)g_{u^x}(t)$$

for each time $t \in [0, T]$ and apply the barrier function $\Theta(x(t), \alpha, \varepsilon)$ to achieve (ε -relaxed) feasible solutions. For our numerical experiments we investigate a small directed acyclic time-dependent network flow problem with 4 nodes and 4 edges and consider two different time-dependent cost functions on the edges for the time interval $[0, 1]$. This problem and the two different time-dependent cost functions, $c_e^q(t)$ for all edges $e \in E$, $t \in [0, 1]$, and $q \in \{1, 2\}$, are illustrated in Figure 4.



Linear cost function Cost of edges for $t \in [0, 1]$	Hat-type cost function Cost of edges for $t \in [0, 1]$
$c_{(1,2)}^1(t) = c_{(2,4)}^1(t) = 100(1+t)$	$c_{(1,2)}^2(t) = c_{(2,4)}^2(t) = \begin{cases} 100(1+2t), & t < 0.5, \\ 100(1+2(1-t)), & t \geq 0.5 \end{cases}$
$c_{(1,3)}^1(t) = c_{(3,4)}^1(t) = 100(2-t)$	$c_{(1,3)}^2(t) = c_{(3,4)}^2(t) = \begin{cases} 100(2-2t), & t < 0.5, \\ 100(2-2(1-t)), & t \geq 0.5 \end{cases}$

Fig. 4: Time-dependent example problem – minimum cost network flow problem with 4 nodes and 4 edges, where $x^\ell = 0$ and $x^u = 4$ for each edge. We consider two different time-dependent cost functions $c_e^q = c_{(i,j)}^q : [0, 1] \rightarrow \mathbb{R}$ with $q \in \{1, 2\}$. For these simple examples the optimal cost (1000) can be computed explicitly.


Example with linear cost function. By construction, the upper path, i.e., from node 1 to 4 through node 2, has smaller cost than the lower path, i.e., from node 1 to 4 through node 3 for $t \in [0, \frac{1}{2})$, while for $t \in (\frac{1}{2}, 1]$ the lower path is preferable, and at $t = \frac{1}{2}$ both paths are indistinguishable w.r.t. the cost. For the barrier function Θ we normalize the costs as above and set the parameters as $\alpha_0 = 1$ and $\varepsilon_0 = 0.001$ while applying the same geometric decrease in α and ε as in the previous section. For the dynamics (4.1) we choose $\lambda = 0.001$, i.e. the penalization w.r.t. u^x is small. For the optimization approach we allow a maximum of 50 gradient steps and 20 Armijo iterations with an initial step length of 1000 while stopping the scheme if $\sum_{i=1}^4 |P_{\mathcal{W}^{\text{ad}}}(\nabla \hat{\mathcal{J}}(u^x))_i| < 10^{-6}$ or if the maximum number of iterations is reached. Furthermore, we discretize the time interval $[0, 1]$ by 1000 equidistant time steps. As the initial flow we choose the flow that only uses the upper path, $x(0) = (x_{(1,2)}(0), x_{(1,3)}(0), x_{(2,4)}(0), x_{(3,4)}(0))^\top = (4, 0, 4, 0)^\top$, i.e., the cost optimal path at time $t = 0$, and expect that the optimizer redirects the flow over time to the lower path $x = (0, 4, 0, 4)^\top$ that is optimal at time $t = 1$. We actually observe this in our numerical tests. After 25 gradient steps the optimizer updates the control u^x such that, after starting in $x(0) = (4, 0, 4, 0)^\top$, the flow at time $t = 1$, i.e., after 1000 time steps, has the value of $x(1) \approx (0.0213, 3.9787, 0.0213, 3.9787)^\top$ which lies in the precision of the applied Euler scheme and the barrier function Θ . In Figure 5d, the total cost over time for each gradient step in Algorithm 2.1 is shown, where the red line at 1000 depicts the optimal costs that is attained for a flow that switches from

the upper path to the lower path at time $t = \frac{1}{2}$. Note that we can not expect to reach this optimum value, due to the smoothness constraints imposed on our control $u^x(t)$. We observe a descent in total cost over time in 25 gradient iterations until the optimizer can not find a feasible Armijo step length anymore, i.e., reaches the maximum number of Armijo iterations. We expect this behaviour due to the barrier approach.


The course of each component of the control u^x after the first update and of the optimized control \bar{u}^x over time are shown in Figure 5a and Figure 5b, respectively. Note that we have a two-fold symmetry in these figures. The u_i^x values for edges from the same path, i.e., edges (1, 2) and (2, 4) of the upper path (cyan, dotted) and edges (1, 3) and (3, 4) of the lower path (magenta), are identical and change with the same ratio, and u_i^x values of different paths have the same absolute values but differing signs, i.e., edges from the upper path lose flow over time while edges from the lower path gain the same amount over time. One can observe that more and more flow is redirected via u^x during the optimization process. Furthermore, this is also visible in the course of the optimal flow values over time, see Figure 5c. This nicely captures the expected behaviour of the optimizer for this simple time-dependent network flow problem with a linear cost function.

Example with hat-type cost function. The hat-type cost function, see Figure 4, is similar to the linear cost function in the sense that for $t \in [0, \frac{1}{4})$, the upper path has smaller cost than the lower path for $t \in [0, \frac{1}{4})$, at $t = \frac{1}{4}$ the paths are indistinguishable w.r.t. the cost, and for $t \in (\frac{1}{4}, \frac{1}{2})$ the lower path is preferable. However, for $t \in [\frac{1}{2}, 1]$ the roles reverse, i.e., the lower path is superior w.r.t. the cost for $t \in [\frac{1}{2}, \frac{3}{4})$, the paths are indistinguishable at $t = \frac{3}{4}$, and the upper path has again smaller cost for $t \in [\frac{3}{4}, 1]$. Hence, starting with the initial flow $x(0) = (x_{(1,2)}(0), x_{(1,3)}(0), x_{(2,4)}(0), x_{(3,4)}(0))^\top = (4, 0, 4, 0)^\top$ that only uses the upper path one would expect that until $t = \frac{1}{2}$ the approach would shift the flow to the lower path, i.e., $x(\frac{1}{2}) = (0, 4, 0, 4)^\top$, and then redirect it back to the upper path for $t \in [\frac{1}{2}, 1]$, i.e., $x(1) = (4, 0, 4, 0)^\top$. As for the linear cost function, the same setting for the barrier function Θ is applied, i.e., $\alpha_0 = 1$ and $\varepsilon_0 = 0.001$ with the same geometric decrease. We also allow a maximum of 50 gradient steps and 20 Armijo iterations with the same initial step length of 1000 and stopping condition $\sum_{i=1}^4 |P_{\mathcal{W}_{\text{ad}}}(\nabla \hat{\mathcal{J}}(u^x))_i| < 10^{-6}$. Furthermore, the time interval $[0, 1]$ is again discretized by 1000 equidistant time steps. For the dynamics (4.1) we choose $\lambda = 0.001$. The optimization approach used all 50 gradient iterations, i.e., it did not converge, which we expect due to the barrier term. However, there are no significant changes to the cost after around 25 iterations, see Figure 6d. Note that the red line at 1000 in Figure 6d corresponds to the optimal costs. The control u^x after the first iteration is depicted in Figure 6a. We observe that in this first iteration the optimizer redirects flow from the upper path (cyan, dotted) to the lower path (magenta) without taking into account that after $t = \frac{1}{2}$, i.e., 500 time steps, the flow should be redirected back to the upper path. This is not the case for the optimized control \bar{u}^x , where the control shifts the flow back to the upper path after initially redirecting it to the lower path, see Figure 6b. Moreover, the optimized flow values \bar{x} for the times $t \in \{\frac{1}{2}, 1\}$ are as expected, i.e., $\bar{x}(\frac{1}{2}) \approx (0.0011, 3.9989, 0.0011, 3.9989)^\top$ and $\bar{x}(1) \approx (3.9984, 0.0016, 3.9984, 0.0016)^\top$, see also Figure 6c. This nicely captures the expected behaviour for this hat-type cost functional.


To summarize, the presented approach yields satisfactory results for small, time-dependent network flow problems for both cost functions.




(a) Control u^x after the first update over time where the values w.r.t. the edges (1,2) and (2,4) are dotted and in cyan and the values w.r.t. the edges (1,3) and (3,4) are in magenta.



(b) Optimized control \bar{u}^x over time.



(c) Optimized flow values \bar{x} over time. Here, the \bar{x} components w.r.t. the edges (1,2) and (2,4) are dotted and in cyan and the values w.r.t. the edges (1,3) and (3,4) are in magenta.




(d) Cost (over time) w.r.t. the gradient iterations. The red line depicts the optimal cost of 1000.


Fig. 5: Time-dependent problem with linear cost function

5. Conclusion. In this article we discuss an optimal control framework for general nonlinear port-Hamiltonian systems of ODE-type and an application to (dynamic) minimum cost flow problems. The well-posedness of optimal control problems constrained by PHS is established and the first-order optimality system is derived. Based on this, a gradient descent algorithm exploiting the adjoint formulation is proposed. A special case of the discussed framework is given by minimum cost flow problems. Here the skew-symmetric matrix contains the information of the incidence matrix which defines the network at hand. We validate the approach with the help of simple static and dynamic network flow problems.


In future work, we plan to extend the concept to more involved network flow problems and gain a deeper understanding of the relationship of optimal control for PHS on graphs and dynamic network flow problems. Intrinsic features of PHS, such as the decomposition into subnetworks will be exploited to speed up the algorithms.




(a) Control u^x after the first update over time where the values w.r.t. the edges (1,2) and (2,4) are dotted and in cyan and the values w.r.t. the edges (1,3) and (3,4) are in magenta.



(b) Optimized control \bar{u}^x over time.



(c) Optimized flow values \bar{x} over time. Here, the \bar{x} components w.r.t. the edges (1,2) and (2,4) are dotted and in cyan and the values w.r.t. the edges (1,3) and (3,4) are in magenta.



(d) Cost (over time) w.r.t. the gradient iterations. The red line depicts the non-continuous optimal cost of 1000.

Fig. 6: Time-dependent problem with hat-type cost function

REFERENCES

- [1] R. K. AHUJA, T. L. MAGNANTI, AND J. B. ORLIN, *Network Flows: Theory, Algorithms, and Applications*, Prentice-Hall, 1993.
- [2] H. W. ALT, *Linear functional analysis*, Springer, 2016.
- [3] J. ARONSON, *A survey of dynamic network flows*, *Annals of Operations Research*, 20 (1989), pp. 1–66.
- [4] G. BIRKHOFF AND J. DIAZ, *Non-linear network problems*, *Quarterly of Applied Mathematics*, 13 (1956), pp. 431–443.
- [5] T. BREITEN AND A. KARSAI, *Structure preserving H_∞ control for port-Hamiltonian systems*, arXiv:2206.08706, (2022).
- [6] L. CHEN, R. KYNG, Y. P. LIU, R. PENG, M. P. GUTENBERG, AND S. SACHDEVA, *Maximum flow and minimum-cost flow in almost-linear time*, 2022, <https://doi.org/10.48550/ARXIV.2203.00671>. arXiv:2203.00671v2.
- [7] R. COMINETTI, T. HARKS, C. OSORIO, AND B. PEIS, *Dynamic Traffic Models in Transportation Science (Dagstuhl Seminar 18102)*, *Dagstuhl Reports*, 8 (2018), pp. 21–38, <https://doi.org/10.4230/DagRep.8.3.21>, <http://drops.dagstuhl.de/opus/volltexte/2018/9295>.

- [8] T. J. COURANT, *Dirac manifolds*, Transactions of the American Mathematical Society, 319 (1990), pp. 631–661.
- [9] O. CRUZ-MEJÍA AND A. N. LETCHFORD, *A survey on exact algorithms for the maximum flow and minimum-cost flow problems*, tech. report, Lancaster University, 2022. <https://www.lancaster.ac.uk/staff/letchfoa/articles/flow-survey.pdf>.
- [10] D. DE WOLF AND Y. SMEERS, *The gas transmission problem solved by an extension of the simplex algorithm*, Management Science, 46 (2000), pp. 1454–1465.
- [11] O. T. DOGANAY, K. KLAMROTH, B. LANG, M. STIGLMAYR, AND C. TOTZECK, *Modeling minimum cost network flows with port-Hamiltonian systems*, 2023, <https://arxiv.org/abs/2303.13196>.
- [12] L. EVANS, *Partial Differential Equations*, American Mathematical Society, Providence, 1998.
- [13] T. FAULWASSER, B. MASCHKE, F. PHILIPP, M. SCHALLER, AND K. WORTHMANN, *Optimal control of port-Hamiltonian descriptor systems with minimal energy supply*, SIAM Journal on Control and Optimization, 60 (2022), pp. 2132–2158, <https://doi.org/10.1137/21M1427723>.
- [14] L. FLEISCHER AND M. SKUTELLA, *Quickest flows over time*, SIAM Journal on Computing, 36 (2007), pp. 1600–1630, <https://doi.org/10.1137/s0097539703427215>.
- [15] L. R. FORD AND D. R. FULKERSON, *Flows in networks*, Princeton University Press, 1962.
- [16] S. GÖTTLICH, S. KÜHN, J. P. OHST, AND S. RUZIKA, *Evacuation modeling: A case study on linear and nonlinear network flow models*, EURO J. Computat. Optim., 4 (2016), pp. 219–239, <https://doi.org/10.1007/s13675-015-0055-6>.
- [17] M. GROSS, *Approximation Algorithms for Complex Network Flow Over Time Problems*, phd thesis, Technische Universität Berlin, Fakultät II - Mathematik und Naturwissenschaften, Berlin, 2014, <https://doi.org/10.14279/depositonce-3966>.
- [18] E. HAIRER, C. LUBICH, AND G. WANNER, *Geometric Numerical Integration*, Springer Series in Computational Mathematics, Springer-Verlag, 2006, <https://doi.org/https://doi.org/10.1007/3-540-30666-8>.
- [19] J. K. HALE, *Ordinary Differential Equations*, Dover Books, 2009.
- [20] M. HERTY, J. MOHRING, AND V. SACHERS, *A new model for gas flow in pipe networks*, Mathematical Methods in the Applied Sciences, 33 (2010), pp. 845–855.
- [21] M. HINZE, R. PINNAU, AND S. ULBRICH, *Optimization with PDE Constraints*, Springer Netherlands, 2009, <https://doi.org/10.1007/978-1-4020-8839-1>.
- [22] B. JACOB AND H. J. ZWART, *Linear port-Hamiltonian systems on infinite-dimensional spaces*, vol. 223, Springer Science & Business Media, 2012.
- [23] A. KARSAI, *Manifold turnpikes of nonlinear port-Hamiltonian descriptor systems under minimal energy supply*, arXiv:2301.09094, (2023).
- [24] D. D. KLINGMAN, A. NAPIER, AND J. D. STUTZ, *Netgen: A program for generating large scale capacitated assignment, transportation, and minimum cost flow network problems*, Management Science, 20 (1974), pp. 814–821.
- [25] E. KÖHLER AND M. SKUTELLA, *Flows over time with load-dependent transit times.*, SIAM Journal on Optimization, 15 (2005), pp. 1185–1202.
- [26] B. KOTNYEK, *An annotated overview of dynamic network flows*, Tech. Report RR-4936, INRIA, Sept. 2003, <https://hal.inria.fr/inria-00071643>.
- [27] P. KOVÁCS, *Minimum-cost flow algorithms: an experimental evaluation*, Optimization Methods and Software, 30 (2015), pp. 94–127, <https://doi.org/10.1080/10556788.2014.895828>.
- [28] L. KÖLSCH, P. J. SONEIRA, F. STREHLE, AND S. HOHMANN, *Optimal control of port-Hamiltonian systems: A continuous-time learning approach*, Automatica, 130 (2021), p. 109725.
- [29] A. LÖBEL, *Solving large-scale real-world minimum-cost flow problems by a network simplex method*, Tech. Report SC-96-07, ZIB, Takustr. 7, 14195 Berlin, 1996.
- [30] A. MARTIN, K. KLAMROTH, J. LANG, G. LEUGERING, A. MORSI, M. OBERLACK, M. OSTROWSKI, AND R. ROSEN, eds., *Mathematical Optimization of Water Networks*, Springer, Basel, 2012.
- [31] B. MASCHKE, F. PHILIPP, M. SCHALLER, K. WORTHMANN, AND T. FAULWASSER, *Optimal control of thermodynamic port-Hamiltonian systems*, 2022, <https://arxiv.org/abs/2202.09086>.
- [32] B. MASCHKE AND A. VAN DER SCHAFT, *Port-controlled Hamiltonian systems: Modelling origins and systemtheoretic properties*, IFAC Proceedings Volumes, 25 (1992), pp. 359–365, [https://doi.org/https://doi.org/10.1016/S1474-6670\(17\)52308-3](https://doi.org/https://doi.org/10.1016/S1474-6670(17)52308-3).
- [33] S. P. NAGESHRAO, G. A. D. LOPES, D. JELTSEMA, AND R. BABUŠKA, *Port-Hamiltonian systems in adaptive and learning control: A survey*, IEEE Transactions on Automatic Control, 61 (2016), pp. 1223–1238, <https://doi.org/10.1109/TAC.2015.2458491>.

- [34] J. NOCEDAL AND S. J. WRIGHT, *Numerical optimization*, Springer, New York, 2 ed., 2006.
- [35] B. PANGENI AND T. DHAMALA, *A brief survey on dynamic network flows in continuous-time model*, Journal of Mathematical Sciences & Computational Mathematics, 2 (2021), pp. 467–477, <https://doi.org/10.15864/jmscm.2401>.
- [36] P. PETERSEN, *Linear Algebra*, Springer New York, 2012, <https://doi.org/10.1007/978-1-4614-3612-6>.
- [37] U. PYAKUREL AND S. DEMPE, *Network flow with intermediate storage: Models and algorithms*, SN Operations Research Forum, 1 (2020), <https://doi.org/10.1007/s43069-020-00033-0>.
- [38] R. ROCKAFELLAR, *Network Flows and Monotropic Optimization*, Wiley-Interscience, Hoboken, 1984.
- [39] M. SCHALLER, F. PHILIPP, T. FAULWASSER, K. WORTHMANN, AND B. MASCHKE, *Control of port-Hamiltonian systems with minimal energy supply*, European Journal of Control, 62 (2021), pp. 33–40, <https://doi.org/https://doi.org/10.1016/j.ejcon.2021.06.017>. 2021 European Control Conference Special Issue.
- [40] M. SKUTELLA, *An introduction to network flows over time*, in Research Trends in Combinatorial Optimization, Springer, 2009, pp. 451–482.
- [41] F. TRÖLTZSCH, *Optimal control of partial differential equations : Theory, methods, and applications*, American Mathematical Society, Providence, Rhode Island, 2010.
- [42] A. VAN DER SCHAFT AND D. JELTSEMA, *Port-Hamiltonian Systems Theory: An Introductory Overview*, vol. 1 of Foundations and Trends in Systems and Control, now Publishers, Inc., Hanover, MA, 2014.
- [43] A. J. VAN DER SCHAFT AND B. M. MASCHKE, *Port-Hamiltonian systems on graphs*, SIAM Journal on Control and Optimization, 51 (2013), pp. 906–937, <https://doi.org/10.1137/110840091>.
- [44] Y. WU, B. HAMROUN, Y. LE GORREC, AND B. MASCHKE, *Reduced order LQG control design for infinite dimensional port Hamiltonian systems*, IEEE Transactions on Automatic Control, 66 (2020), pp. 865–871.