

Nonlinear Stationary Waves with Transport Current in Superconductors

N. T. Taylanov

Department of Theoretical Physics,
Institute of Applied Physics,
National University of Uzbekistan,
Vuzgorodok, 800174, Tashkent, Uzbekistan
e-mail: taylanov@iaph.tkt.uz

Abstract

The profile of a nonlinear stationary thermomagnetic wave in the resistive state of superconductors is studied at different transport currents. It is proved that the thermomagnetic wave has an oscillating profile at relatively high values of the transport current in the sample. A shock wave with a monotonic structure corresponds to comparatively weak transport currents. The wave propagation velocity and the wave front width in a superconductor are estimated.

The problem of thermal suppression of the superconducting state in the presence of transport current is topical in the practical use of superconducting magnetic systems (see [1]). External perturbations of various physical natures (thermal, magnetic, mechanical, etc.) can lead to the formation of resistive-phase regions in a superconductor. The ohmic heating of these regions under a transport current with density j_x can bring about an increase in the temperature T above the critical point ($T > T_c$) and, hence, the emergence of a vortex electric field E in the sample. It was shown earlier [2] that, together with dispersive and nonlinear effects, the dissipative processes induced under ohmic heating in a superconductor lead to the formation of stable structures, thermoelectromagnetic E and H waves, depending on the condition at the sample surface. In the present work, we studied the qualitative pattern of the dynamics of nonlinear thermomagnetic dissipative structures in the resistive state of a superconductor. The dynamics of thermomagnetic waves, which move at a constant velocity v along the x axis in a superconductor, is described in terms of self-simulated variables $(x;t) = x - vt$ by the nonlinear heat conduction equation [2-4]

$$v \frac{dT}{dx} = \frac{d}{dx} \left(\kappa \frac{dT}{dx} \right) + jE; \quad (1)$$

a set of Maxwell equations

$$\frac{dE}{dx} = -\frac{4\pi v}{c^2} j; \quad (2)$$

$$E = -\frac{v}{c} H \quad (3)$$

and their related equation of the critical state

$$j = j_c(T; H) + j_r(E) + j_{tr} \quad (4)$$

Here, κ and λ are the heat capacity and thermal conductivity coefficients, respectively; $j_c(T) = j_0 [1 - a(T - T_0)]$ is the critical current density in the Bean model $\frac{dj_c}{dH} = 0$ [5] (where T_0 and T_c are the initial and critical temperatures of the superconductor, respectively, and the quantity $a = \frac{dj_c}{dT}|_{T=T_0}$ describes the thermally activated weakening of the Abrikosov vortex pinning by lattice defects); $j_r(E)$ is the resistive current density; and j_{tr} is the transport current density. In the weak-heating approximation $(T - T_0) \ll (T_c - T_0)$ for the viscous flow region ($E > E_f$, where E_f is the boundary of the linear section in the current-voltage characteristics of hard superconductors [6]), the dependence of the resistive current density j_r on the electric field E is linear; i.e., $j_r = \sigma_f E$ (σ_f is the effective conductivity). In weak fields ($E < E_f$) the dependence $j_r(E)$ is essentially nonlinear and is most likely determined by the thermally activated motion of the magnetic flux (flux creep [6]). Here, we will consider a perturbation with a sufficiently high amplitude ($E > E_f$) and use the linear dependence $j_r(E)$. The appropriate thermal and electrodynamical boundary conditions for Eqs. (1)–(4) have the form

$$T(x=0) = T_0; \quad \frac{dT}{dx}(x=0) = 0; \quad (5)$$

$$E(x=0) = 0; \quad E(x=L) = E_e;$$

where E_e is the external electric field.

By solving the set of Eqs. (1)–(4) with boundary conditions (5), we obtain the following equation for the distribution of the nonlinear E wave:

$$\frac{d^3 E}{dz^3} + (1 + \gamma) \frac{d^2 E}{dz^2} + \gamma^2 \frac{dE}{dz} + \frac{E_j}{E} E = 0; \quad (6)$$

Here, $z = \frac{x}{L}$, $\gamma = \frac{vt}{L}$, $E_j = \frac{j_{tr}}{\sigma_f}$, $\gamma^2 = \frac{4}{c^2} \sigma_f E = \frac{4}{aL^2}$, $L = \frac{dH_e}{4j_0}$ is the depth of the magnetic field penetration into the bulk of the superconductor, $t = \frac{L^2}{\kappa}$ is the thermal time of the problem, and H_e is the external magnetic field.

By analyzing the roots of the characteristic equation [7]

$$(\lambda + \gamma)(\lambda + \gamma + \frac{E_j}{E}) = 0; \quad (7)$$

we can easily verify that the problem considered has solution that oscillate about the origin of the coordinates ($E_0 = 0$) of the phase diagram with decreasing and increasing amplitudes. The oscillations appear at $E_j > \frac{E}{2(1 + \gamma)}$, attenuate at $(1 + \gamma)E > E_j > \frac{E}{2(1 + \gamma)}$, and increase at $(1 + \gamma)E < E_j$. This means that, at a sufficiently high transport current j_{tr} , the roots of the characteristic equation (7) are complex, the integral curves are helical,

and the origin $E_0 = 0$ is a singular point (focus). If the coefficients α and β are assumed to be universally positive, the representative point approaches the origin of coordinates, which is a stable equilibrium position. In the opposite case, when $(1 + \alpha)E_0 < E_j$, the focus becomes unstable and the representative point goes to infinity. Note that the final value of the transport current j_{tr} leads to a displacement of singular points and, correspondingly, of the boundary conditions.

At sufficiently weak transport currents, when the condition $\frac{dE}{dz} \gg \alpha^2 E_j$ is satisfied (high-amplitude waves), Eq. (6) is an integrable equation and the corresponding model can be considered a damped linear oscillator owing to the friction force, that is,

$$F_t = - (1 + \alpha) \frac{dE}{dz}; \quad (8)$$

where z is an analogue of time and E is the coordinate of the "material" point. The potential well equation has the form

$$U(E) = \frac{E^3}{6E_j} + \frac{\alpha^2}{2} \frac{E^2}{2}; \quad (9)$$

A analysis of the phase plane $(\frac{dE}{dz}; E)$ described by Eq. (6) shows that it has two equilibrium points: E_0 is a stable node and $E_1 = \alpha^2 E_j$ is a saddle. The two equilibrium states $(E_0; E_1)$ are separated by the separatrix AB in the phase plane (Fig.1). The material point is located at the point E_1 at $z = 0$ and goes over into the point E_0 at $z \rightarrow \infty$. The change-over from one equilibrium state to other occurs only monotonically.

Within the approximation $\alpha \ll 1$, the solution of Eq. (6) is represented as

$$E(z) = \frac{E_1}{2} \left[1 - \tanh\left(\frac{\alpha}{2}(z - z_0)\right) \right] \quad (10)$$

The condition $\frac{D_t}{D_m} \ll 1$ means that the magnetic flux is redistributed much faster than the heat is transferred. Here, $D_t = -\frac{c^2}{4\pi\sigma}$ and $D_m = \frac{c^2}{4\pi\sigma_f}$ are the thermal and magnetic diffusion coefficients, respectively [6]. Hence, the spatial scale L_E for the magnetic flux penetration is substantially greater than the corresponding thermal scale L_T . Therefore, the spatial derivatives $\frac{d^n E}{dz^n}$ will contain a small parameter $\frac{L_T}{L_E} \ll 1$. We can easily check the validity of this approximation by the direct differentiation of Eq. (6), that is,

$$\frac{d^2 E}{dz^2} \sim \frac{dE}{dz} \frac{1}{L_E} \ll 1 \quad (11)$$

The maximum error of this approximation is of the order $\frac{1}{(1 + \alpha)^2}$. For example, the error is equal to 25% in the limiting case $\alpha \rightarrow 0$. Relationship (10) describes the profile of a shock thermomagnetic wave propagating into the bulk of the superconductor. The wave

structure is shown in Fig 2. At the boundary condition $(E(z \rightarrow 1) = E_e)$, we can easily determine the velocity v_E of the wave with an amplitude E_e in the form

$$v_E = \frac{L}{t} \frac{E_e^{1=2}}{2 E} ; \quad (12)$$

and the wave front width z

$$z = 16 \frac{1 + \frac{E}{E_e}^{1=2}}{1=2} : \quad (13)$$

The numerical estimates yield the values $v_E = 1 \cdot 10^2$ and $z = 10^{-1} \cdot 10^{-2}$ for $\beta = 1$.

In conclusion, we note that the results obtained make it possible to describe the nonlinear stage of evolution of the thermomagnetic instability in the resistive state of superconductors. In the initial stage, we observe an exponential increase in the perturbations of T , E , and H with the increment determined from the linear theory (see [8]). The linear stage of the instability evolution lasts for the period $t_j = \frac{t}{\beta}$. In the latter stage of the instability evolution, the stationary E' or H' wave (depending on whether the E' or H' quantity is fixed on the sample surface during the wave motion) propagates into the bulk of the sample. The velocity of the wave is determined by formula (12), and the time of its motion in the sample with thickness $2l$ is given by

$$t = \frac{1}{v_E}$$

Hence, it follows that the transition from the superconducting to the normal state can occur through the propagation of a stationary thermomagnetic wave whose structure essentially depends on dispersive and dissipative effects.

REFERENCES

1. V R Rom anovskii, Dokl. Akad. Nauk 365, (1) 44 (1999) [Dokl. Phys. 44, 137 (1999)].
2. I L Maksim ov, Yu N M astakov, and N A Taylanov. Fiz. Tverd. Tela (Leningrad) 28 (8), 2323 (1986) [Sov. Phys. Solid State 28, 1300 (1986)].
3. N A Taylanov, Metallo fizika (Kiev) 13 (9), 713 (1991).
4. N A Taylanov Superconduct. Science and Technology, 14, 326 (2001).
5. Bean C P. Phys. Rev. Lett. 8, 6. 250 (1962).
6. R G Mints and A L Rakhmanov, Instability in Superconductors (Nauka, Moscow, 1984).
7. V I Karpman, Non-linear Waves in Dispersive Media (Nauka, Moscow, 1973; Pergamon, Oxford, 1975).
8. V A A l'tov, V B Zenkevich, M G Krem lev, and V V Sychev, Stabilization of Superconducting Magnetic Systems (Energoatom izdat, Moscow, 1984).




Рис.1.

