

Onset of Delocalization in Quasi-1D Waveguides with Correlated Surface Disorder

F. M. Izrailev

*Instituto de Física, Universidad Autónoma de Puebla,
Apartado Postal J-48, Puebla, Pue., 72570, México*

N. M. Makarov

*Instituto de Ciencias, Universidad Autónoma de Puebla,
Priv. 17 Norte No 3417, Col. San Miguel Hueyotlipan, Puebla, Pue., 72050, México
(March 22, 2022)*

We present first analytical results on transport properties of many-mode waveguides with rough surfaces having long-range correlations. We show that propagation of waves through such waveguides reveals a quite unexpected phenomena of a complete transparency for a subset of propagating modes. These modes do not interact with each other and effectively can be described by the theory of 1D transport with correlated disorder. We also found that with a proper choice of model parameters one can arrange a perfect transparency of waveguides inside a given window of energy of incoming waves. The results may be important in view of experimental realizations of a selective transport in application to both waveguides and electron/optic nanodevices.

During last few years there is a burst of interest to solid state models with correlated disorder (see, e.g., [1] and references therein). This fact is mainly due to the possibility to observe an anomalous transport in 1D models with random correlated potentials. In particular, it was shown [2] that specific long-range correlations in potentials give rise to a complete transparency of electron waves for given energy windows. Experimental realization of such potentials for single-mode waveguides with delta-like scatters [3] has confirmed theoretical predictions.

The subject of wave propagation through surface-disordered waveguides (see, e.g., [4,5,6,7,8,9] and references therein) is important both from the theoretical viewpoint and for experimental applications such as optic fibers, remote sensing, radio wave propagation, shallow water waves, etc. On the other hand, it describes electronic transport in mesoscopic conducting channels as well. So far, main results in this field are obtained for random surfaces with *fast-decaying* correlations along a scattering surface. It is now of great importance to understand main properties of multiple scattering from rough surfaces with *long-range* correlations.

In this contribution we theoretically analyze transport properties of quasi-1D waveguides with rough surfaces. Our main interest is in exploring the possibility of constructing such surface profiles that result in frequency windows of a perfect propagation of waves.

In what follows we consider a plane waveguide (or conducting wire) of average width d and length L , stretched along the x -axis. One (lower) surface of the waveguide is a rough profile $z = \xi(x)$, and the other (upper) surface, for simplicity, is taken to be flat, $z = d$. The function $\xi(x)$ describes the boundary roughness and is assumed to be statistically homogeneous and isotropic, with stan-

dard statistical properties,

$$\langle \xi(x) \rangle = 0, \quad \langle \xi(x)\xi(x') \rangle = \sigma^2 \mathcal{W}(|x - x'|). \quad (1)$$

Here the angular brackets stand for a statistical average over different realizations of a profile $\xi(x)$. The binary correlator $\mathcal{W}(|x - x'|)$ is assumed to decrease on a characteristic scale k_0^{-1} , and is normalized to its maximal value, $\mathcal{W}(0) = 1$.

Both the *amplitude* and *gradient* roughness of the corrugated surface is taken to be small, $\sigma \ll d$ and $k_0\sigma \ll 1$. These limitations are common in surface scattering theories that are based on an appropriate *perturbative approach*, see for example, [4]. We should also add that zero (Dirichlet) boundary conditions are applied at both surfaces of the waveguide.

Let us first consider a single-mode waveguide in which only one normal mode (*channel*) has real lengthwise wave number $k_1 = \sqrt{k^2 - (\pi/d)^2}$ (for details see [10]). It is known [11] that in this case the problem of surface scattering is reduced to a purely 1D model with the potential determined by the random profile $\xi(x)$. The corresponding wave equation takes the form,

$$\left(\frac{d^2}{dx^2} + k_1^2 \right) \Psi(x) - \frac{2}{\pi} \left(\frac{\pi}{d} \right)^3 \xi(x) \Psi(x) = 0. \quad (2)$$

Since one channel case corresponds to inequality $1 < kd/\pi < 2$, the value of k_1 is restricted by the relation $0 < k_1 d/\pi < \sqrt{3}$. Note also that the weak scattering assumption $\sigma \ll d$ leads to the condition, $k_1\sigma \ll 1$.

The above equation (2) demonstrates an exact correspondence between the surface scattering in one-mode waveguides, and bulk scattering for electrons in 1D models of the Anderson (or Kronig-Penney) type. Specifically, the wave number k is equal to ω/c for a classical

wave of frequency ω , and to the Fermi wave number for electrons.

In order to solve the wave equation (2) and to find the averaged *transmittance*, or, the same, the dimensionless *conductance* (in units of $e^2/\pi\hbar$), one can use methods developed in the transport theory of one-dimensional disordered systems, such as the perturbative diagrammatic method of Berezinski [12], invariant imbedding method [13], or the two-scale approach [9]. All the methods allow to take adequately into account the effects of coherent multiple scattering of waves (electrons) from the corrugated surface.

Main theoretical result is that the average transmittance $\langle T \rangle$ is described by a universal expression which depends on one parameter $\Lambda = L_{loc}/L$ only (*one-parameter scaling*). Here the quantity $L_{loc}/4$ is the backscattering length in a 1D disordered system. Its inverse value L_{loc}^{-1} is equal to the Lyapunov exponent that can be found in the transfer matrix approach, so that the quantity L_{loc} is known as the *localization length* [14].

The expression for $\langle T \rangle$ is fully consistent with the theory of 1D *Anderson localization*. Specifically, the transmittance $\langle T \rangle$ exhibits the ballistic behavior for large localization length, $L_{loc}/L \gg 1$,

$$\langle T(L/L_{loc}) \rangle \approx 1 - 4L/L_{loc}, \quad (3)$$

therefore, in this case the waveguide is practically transparent. On the contrary, the transmittance is exponentially small when the localization length is much less than the length of the waveguide, $L_{loc}/L \ll 1$,

$$\langle T(L/L_{loc}) \rangle \approx \frac{\pi^{5/2}}{16} (L/L_{loc})^{-3/2} \exp(-L/L_{loc}). \quad (4)$$

This implies strong wave localization. Since in this case the transmittance is not a self-averaged quantity, for completeness of presentation one should refer to the expression for its logarithm, $\langle \ln T(L/L_{loc}) \rangle = -4L/L_{loc}$.

Thus, in order to describe transport properties of a disordered waveguide, one needs to know the value of the localization length L_{loc} . The latter is entirely determined by the type of disorder. For the surface disorder, from the solution of the equation (2) one can obtain [11],

$$\frac{1}{L_{loc}} = \frac{\sigma^2}{\pi^2} \left(\frac{\pi}{d} \right)^6 \frac{W(2k_1)}{(2k_1)^2}. \quad (5)$$

This formula contains the Fourier transform $W(k_x)$ of the binary correlator $\mathcal{W}(|x - x'|)$, which is called the *roughness power spectrum*,

$$\mathcal{W}(|x - x'|) = \int_{-\infty}^{\infty} \frac{dk_x}{2\pi} \exp\{ik_x(x - x')\} W(k_x). \quad (6)$$

One can see that the localization length and, correspondingly, transport properties of a single-mode waveguide are completely defined by the dependence $W(k_x)$. In particular, if $W(2k_1)$ abruptly vanishes within some

interval of wave number k_1 , then the localization length L_{loc} diverges and the waveguide of any length will be fully transparent. Therefore, an interesting problem arises: how to construct such (random) surface profiles that result in a complete transparency of waveguides within a predefined part of the allowed region for the wave vector k_1 ? The answer to this question was done in Ref. [10] where the results obtained for discrete Anderson-like disordered models [2] have been extended to the surface scattering.

The recipe is as follows [10]. Having a desirable dependence for the Fourier transform $W(k_x)$, one obtains the function $\beta(x)$,

$$\beta(x) = \int_{-\infty}^{\infty} \frac{dk_x}{2\pi} \exp(ik_x x) W^{1/2}(k_x). \quad (7)$$

Then, the surface profile can be constructed by the convolution of the delta-correlated random process (white noise $Z(x)$) with the function $\beta(x)$,

$$\xi(x) = \sigma \int_{-\infty}^{\infty} dx' Z(x - x') \beta(x'). \quad (8)$$

The proposed method allows us to practically solve the inverse scattering problem of a reconstruction of rough surfaces from their power spectrum. We would like to emphasize that by a proper choice of the binary correlator, the transition between localized and delocalized wave/electron transport can occur abruptly at a given point inside the allowed interval for the wave number k_1 (see details and examples in [10]). This means that the roughness power spectrum $W(k_x)$ is discontinuous at this point. Consequently, the correlator $\mathcal{W}(|x - x'|)$ of the corrugated surface $\xi(x)$ should be of *specific* form with *long-range correlations* along the waveguide.

It is important to stress that surfaces with the above discussed properties (when $W(k_x)$ vanishes in some regions of k_x) are not exotic. They have been recently fabricated in experimental studies of an *enhanced backscattering* [15].

Let us now consider *many-mode* waveguides with correlated surface disorder. In the spirit of the Landauer's concept [16], the *total transmittance* $\langle T \rangle$ of any quasi-1D structure is expressed as a sum of *partial transmittances* T_n that describe the transport for every n -th propagating normal mode, $\langle T \rangle = \sum_{n=1}^{N_d} T_n$. Here $N_d = [kd/\pi]$ is the total number of propagating modes (*open channels*) determined by the integer part [...] of the ratio kd/π .

From general theory of scattering systems [4] it follows that the wave propagation through any n -th open channel is determined by two *attenuation lengths*, the length $L_n^{(f)}$ of forward scattering and the backscattering length $L_n^{(b)}$. For quasi-1D waveguides with surface disorder the inverse scattering lengths are given by,

$$\frac{1}{L_n^{(f)}} = \sigma^2 \frac{(\pi n/d)^2}{k_n d} \sum_{n'=1}^{N_d} \frac{(\pi n'/d)^2}{k_{n'} d} W(k_n - k_{n'}), \quad (9)$$

$$\frac{1}{L_n^{(b)}} = \sigma^2 \frac{(\pi n/d)^2}{k_n d} \sum_{n'=1}^{N_d} \frac{(\pi n'/d)^2}{k_{n'} d} W(k_n + k_{n'}), \quad (10)$$

where $k_n = \sqrt{k^2 - (\pi n/d)^2}$.

The results (9) and (10) can be obtained by the diagrammatic Green's function approach [4] as well as with the use of the technique developed in Ref. [17]. Also, these expressions directly follow from the invariant imbedding method extended to quasi-1D structures (see Ref. [6]). Note that in a single-mode waveguide with $N_d = 1$ the sum over n' contains only one term with $n' = n = 1$. Therefore, the backscattering length $L_1^{(b)}$ is four times less than the 1D localization length L_{loc} , see Eq. (5).

The expressions (9) and (10) manifest that, in general, both attenuation lengths are formed by scattering of a given n -th propagating mode into all other modes. This is the case when, for example, a surface profile is either delta-correlated random function ("white noise") with constant power spectrum $W(k_x)$, or the function with fast decreasing binary correlator (or, the same, with a slow decrease of its Fourier components).

One can see that the larger the mode number n is, the stronger is the scattering of this mode into others. As was shown in Ref. [6], in this case a very interesting phenomenon of the coexistence of *ballistic*, *diffusive*, and *localized* transport arises, which seems to be generic for propagation through waveguides with random surfaces. Specifically, while lowest modes can be in the ballistic regime, the intermediate and highest modes exhibit the diffusive and localized behavior, respectively.

Now we are ready to show that the situation is fundamentally different when the surface disorder has specific long-range correlations. To demonstrate this, let us take the surface profile $\xi(x)$ with the binary correlator in the following form, $\mathcal{W}(|x - x'|) = \sin\{k_0(x - x')\}/k_0(x - x')$. In this case the Fourier transform $W(k_x)$ is a "window function",

$$W(k_x) = (\pi/k_0) \Theta(k_0 - |k_x|), \quad k_0 > 0, \quad (11)$$

where $\Theta(z)$ stands for the unit-step function.

In accordance with Eqs. (7), (8) rough surfaces that have such correlation properties can be constructed as follows,

$$\xi(x) = \frac{\sigma}{\sqrt{\pi k_0}} \int_{-\infty}^{\infty} dx' Z(x - x') \frac{\sin(k_0 x')}{x'}. \quad (12)$$

Now one can see that in the case under consideration the number of modes into which a given n -th mode is scattered, is entirely determined by the width k_0 of the rectangular spectrum (11). It is clear that if the distance $|k_n - k_{n\pm 1}|$ between neighboring values of k_n is larger than the width k_0 ,

$$|k_n - k_{n\pm 1}| > k_0, \quad (13)$$

then the transitions *between* all modes are forbidden. In this case the sum over n' in Eq. (9) contains only one term with $n' = n$ which describes scattering *inside* the channels. Moreover, each term in the sum of Eq. (10) is equal to zero, and the scattering lengths are,

$$\frac{1}{L_n^{(f)}} = \frac{\pi \sigma^2}{k_0} \frac{(\pi n/d)^4}{(k_n d)^2}, \quad \frac{1}{L_n^{(b)}} = 0. \quad (14)$$

The above analysis shows that a remarkable phenomenon can arise. Specifically, all the propagating modes with index n , that satisfy the condition (13), are independent of other waveguide modes, in spite of the interaction with a rough surface. In other words, they represent a coset of *non-interacting* channels. Since the transport of any 1D disordered system is determined by the backscattering length only, and the latter is infinite according to Eq. (14), the transmittance for such channels is $T_n = 1$. This means that according to the Landauer's formula for $\langle T \rangle$, the transmittance of the coset of such *independent transparent* waveguide modes is simply equal to their total number.

As for other propagating modes with index n , that do not satisfy the condition (13), they remain to be mixed by surface scattering because the roughness power spectrum (11) is non-zero, $W(k_n - k_{n'}) = \pi/k_0$. Since these *mixed modes* have finite backscattering lengths, for large enough size L they do not contribute in the total transmittance and the latter is equal to the number of *independent transparent* modes.

For large number $N_d \gg 1$ of open channels one can perform further analytical analysis. In this case the inequality (13) is analogous to the requirement $|\partial k_n / \partial n| > k_0$ which can be written in the following form,

$$n > N_{k_0} \equiv \left\lceil \frac{(kd/\pi)}{\sqrt{1 + (k_0 d/\pi)^{-2}}} \right\rceil. \quad (15)$$

We remind again that square brackets stand for the integer part of the inner expression.

The expression (15) determines the total number N_{k_0} of mixed non-transparent modes, total number $N_t = N_d - N_{k_0}$ of independent transparent modes, and the critical value of n that divides these two groups. All propagating modes with $n > N_{k_0}$ are independent and fully transparent, otherwise, they are mixed and characterized by finite backscattering lengths $L_n^{(b)}$.

The numbers N_{k_0} and N_t of mixed non-transparent and independent transparent modes are determined by two parameters, kd/π and $k_0 d/\pi$. In the case of "weak" correlations, $k_0 d/\pi \gg 1$, the number of mixed modes N_{k_0} is of the order of N_d ,

$$N_{k_0} \approx \left\lceil \left(\frac{kd}{\pi} \right) - \frac{1}{2} \left(\frac{kd}{\pi} \right) \left(\frac{k_0 d}{\pi} \right)^{-2} \right\rceil. \quad (16)$$

Consequently, in this case the number of independent modes $N_d - N_{k_0}$ is small, or there are no such modes at

all. If the parameter $k_0 d/\pi$ tends to infinity, $k_0 d/\pi \rightarrow \infty$, the rough surface profile becomes white-noise-like and, naturally, $N_{k_0} \rightarrow N_d$.

The most interesting case is when surface profiles are strongly correlated, which is specified by the condition $k_0 d/\pi \ll 1$. Then the characteristic integer N_{k_0} is much less than the total number of modes N_d ,

$$N_{k_0} \approx \left[\left(\frac{kd}{\pi} \right) \left(\frac{k_0 d}{\pi} \right) \right] \ll N_d, \quad (17)$$

and the number of transparent modes N_t is large. When $k_0 d/\pi$ decreases and becomes small, $k_0 d/\pi < (kd/\pi)^{-1} \ll 1$, the number N_{k_0} vanishes and *all modes* become independent and fully transparent. Evidently, if $k_0 d/\pi$ tends to zero, the roughness power spectrum $W(k_x)$, see (11), becomes delta-function-like and, as a consequence, $N_{k_0} = 0$. In this case the correlated disorder results in a perfect transmission of waves, in spite of their scattering from a rough surface.

We also would like to note that the scattering through many-mode waveguides with correlated surfaces of the above kind reveals a step-wise dependence of the transmittance on the value of the parameter $\gamma_k = kd/\pi$. This is clear from the explicit expression for the transmittance,

$$\langle T \rangle = [\gamma_k] - [\alpha \gamma_k], \quad \alpha = \{1 + (k_0 d/\pi)^{-2}\}^{-1/2}. \quad (18)$$

The effect is similar to that known to occur for the conductance of quasi-1D ballistic structures (see, e.g., [18]). Interesting enough, in our model the step-wise dependence of the transmittance arises both for integer and *non-integer* values of γ_k , due to the presence of the second term in Eq.(18).

In conclusion, we have studied transport properties of quasi-1D waveguides with random correlated surfaces. It was analytically shown that for a specific choice of long-range correlations a subset of propagating modes emerges that are *independent* and fully *transparent*. These modes do not interact with each other and the theory of 1D transport can be rigorously applied for them. The rest of propagating modes creates the second set of *mixed* and *non-transparent* modes. With a proper choice of model parameters, one can construct such waveguides for which *all* modes turn out to be completely delocalized. This means a perfect transparency of waveguides in spite of random character of surface scattering. These results may be used for experimental fabrication of waveguides and superlattices with selective windows of a complete transparency in dependence of the wave number of incoming waves.

This research was supported by Consejo Nacional de Ciencia y Tecnología (CONACYT, México) grant 34668-E, and by the Universidad Autónoma de Puebla (BUAP, México) under the grant II-63G01.

- [1] P. Carpena, P. Bernaola-Galván, P. Ch. Ivanov, and H. E. Stanley, *Nature*, **418**, 955 (2002); F. A. B. F. de Moura, M. D. Coutinho-Filho, E. P. Raposo, and M. L. Lyra, cond-mat/0209304.
- [2] F. M. Izrailev and A. Krokhin, *Phys. Rev. Lett.* **82**, 4062 (1999); A. A. Krokhin and F. M. Izrailev, *Ann. Phys. (Leipzig)* **8**, 153 (1999); F. M. Izrailev, A. A. Krokhin, and S. E. Ulloa, *Phys. Rev. B* **63**, 041102(R) (2001).
- [3] U. Kuhl, F. M. Izrailev, A. A. Krokhin, and H.-J. Stoeckmann, *Appl. Phys. Lett.* **77**, 633 (2000).
- [4] F. G. Bass, I. M. Fuks, *Wave Scattering from Statistically Rough Surfaces* (Pergamon, New York, 1979).
- [5] N. M. Makarov, A. V. Moroz, and V. A. Yampol'skii, *Phys. Rev. B* **52**, 6087 (1995).
- [6] J. A. Sánchez-Gil, V. Freilikher, I. V. Yurkevich, and A. A. Maradudin, *Phys. Rev. Lett.* **80**, 948 (1998); J. A. Sánchez-Gil, V. Freilikher, A. A. Maradudin, and I. V. Yurkevich, *Phys. Rev. B* **59**, 5915 (1999).
- [7] M. Leadbeater, V. I. Fal'ko, and C. J. Lambert, *Phys. Rev. Lett.* **81**, 1274 (1998).
- [8] A. García-Martín, J. A. Torres, and J. J. Sáenz, *Phys. Rev. Lett.* **80**, 4165 (1998).
- [9] N. M. Makarov and Yu. V. Tarasov, *J. Phys.: Condens. Matter* **10**, 1523 (1998); N. M. Makarov, lectures on *Spectral and Transport Properties of One-Dimensional Disordered Conductors*, www.ifuap.buap.mx/virtual/page_vir.html.
- [10] F. M. Izrailev and N. M. Makarov, *Opt. Lett.* **26**, 1604 (2001).
- [11] N. M. Makarov and I. V. Yurkevich, *Zh. Eksp. Teor. Fiz* **96**, 1106 (1989) [*Sov. Phys. JETP* **69**, 628 (1989)]; V. Freilikher, N. M. Makarov, and I. V. Yurkevich, *Phys. Rev. B* **41**, 8033 (1990).
- [12] V. L. Berezinski, *Zh. Eksp. Teor. Fiz.* **65**, 1251 (1973) [*Sov. Phys.-JETP* **38**, 620 (1974)]; A. A. Abrikosov and I. A. Ryzhkin, *Adv. Phys.* **27**, 147 (1978).
- [13] R. Bellman and G. M. Wing, *An Introduction to Invariant Imbedding* (N.Y.: Wiley, 1975); V. I. Klyatskin, *The Invariant Imbedding Method in a Theory of Wave Propagation* (Moscow: Nauka, 1986) (*in Russian*).
- [14] I. M. Lifshits, S. A. Gredeskul, and L. A. Pastur, *Introduction to the Theory of Disordered Systems* (Wiley, New York, 1988).
- [15] C. S. West and K. A. O'Donnell, *J. Opt. Soc. Am. A* **12**, 390 (1995).
- [16] R. Landauer, *Physica Scripta* **T42**, 110 (1992).
- [17] A. R. McGurn and A. A. Maradudin, *Phys. Rev. B* **30**, 3136 (1984).
- [18] B. J. van Wees, H. van Houten, C. W. J. Beenakker, *et al.*, *Phys. Rev. Lett.* **60**, 848 (1988).