

Wave Propagation in Generalized Gyrotropic Media

Jian-Qi Shen^{1,2,*}

¹ Centre for Optical and Electromagnetic Research, State Key Laboratory of Modern Optical Instrumentation

² Zhejiang Institute of Modern Physics and Department of Physics

Zhejiang University, Spring Jade, Hangzhou 310027, P.R. China

(February 19, 2022)

Wave propagation inside generalized gyrotropic media is considered in the present Letter. It is shown that in this type of materials, the left- and right-handed circularly polarized light can be coupled to each other, which may possess some potential applications to quantum information.

Gyrotropic media whose electric permittivity and magnetic permeability are tensors has peculiar optical and electromagnetic properties [1,2]. Recently we proposed an experimentally feasible scheme of testing the so-called quantum vacuum geometric phases of zero-point electromagnetic fields in the helically curved optical fibre by using the gyrotropic medium fibre [3]. In this Letter, we investigate the wave propagation in a generalized gyrotropic medium with the following permittivity and permeability

$$(\epsilon)_{ik} = \begin{pmatrix} \epsilon_0 & \epsilon_1 & \epsilon_2 & \epsilon_3 \\ \epsilon_1 & \epsilon_0 & \epsilon_2 & \epsilon_3 \\ \epsilon_2 & \epsilon_2 & \epsilon_0 & \epsilon_3 \\ \epsilon_3 & \epsilon_3 & \epsilon_3 & \epsilon_0 \end{pmatrix}; \quad (\mu)_{ik} = \begin{pmatrix} \mu_0 & \mu_1 & \mu_2 & \mu_3 \\ \mu_1 & \mu_0 & \mu_2 & \mu_3 \\ \mu_2 & \mu_2 & \mu_0 & \mu_3 \\ \mu_3 & \mu_3 & \mu_3 & \mu_0 \end{pmatrix} \quad (1)$$

This type of materials is a generalization of the ordinary gyrotropic medium with [1,2]

$$(\epsilon)_{ik} = \begin{pmatrix} \epsilon_0 & \epsilon_1 & \epsilon_2 & 0 \\ \epsilon_1 & \epsilon_0 & 0 & 0 \\ \epsilon_2 & 0 & \epsilon_0 & 0 \\ 0 & 0 & 0 & \epsilon_3 \end{pmatrix}; \quad (\mu)_{ik} = \begin{pmatrix} \mu_0 & \mu_1 & \mu_2 & 0 \\ \mu_1 & \mu_0 & 0 & 0 \\ \mu_2 & 0 & \mu_0 & 0 \\ 0 & 0 & 0 & \mu_3 \end{pmatrix} \quad (2)$$

and can encompass the electromagnetic parameters of ϵ_{ik} and μ_{ik} in (1) material responses experimentally obtained.

Assume that the wave vector k of electromagnetic wave propagating inside this medium is parallel to the the third component of the Cartesian coordinate system. According to Maxwellian Equations, one can arrive at

$$\nabla^2 E_1 = \epsilon_0 \frac{\partial^2}{\partial t^2} D_2 - \epsilon_2 \frac{\partial^2}{\partial t^2} D_1; \quad \nabla^2 E_2 = \epsilon_0 \frac{\partial^2}{\partial t^2} D_2 - \epsilon_2 \frac{\partial^2}{\partial t^2} D_1; \quad (3)$$

where the electric displacement vector D_1 and D_2 are of the form

$$D_1 = \epsilon_0 (\epsilon_1 E_1 + \epsilon_2 E_2); \quad D_2 = \epsilon_0 (\epsilon_2 E_1 + \epsilon_0 E_2); \quad (4)$$

Due to the transverse nature of planar electromagnetic wave, the following acquirements are satisfied

$$E_3 = 0; \quad H_3 = 0; \quad k \cdot E = 0; \quad k \cdot H = 0; \quad k \cdot D = 0; \quad k \cdot B = 0; \quad (5)$$

Thus with the help of above equations, it is verified that

$$\nabla^2 E_1 = \epsilon_0 \left(\epsilon_1 \epsilon_1 - \epsilon_2 \epsilon_1 \right) \frac{\partial^2}{\partial t^2} E_1 + \left(\epsilon_1 \epsilon_2 - \epsilon_2 \epsilon_2 \right) \frac{\partial^2}{\partial t^2} E_2; \quad (6)$$

$$\nabla^2 E_2 = \epsilon_0 \left(\epsilon_1 \epsilon_1 - \epsilon_2 \epsilon_1 \right) \frac{\partial^2}{\partial t^2} E_1 + \left(\epsilon_1 \epsilon_2 - \epsilon_2 \epsilon_2 \right) \frac{\partial^2}{\partial t^2} E_2;$$

So,

It will be submitted nowhere else for the publication, just uploaded at the e-print archives.

*E-mail address: jqshen@coer.zju.edu.cn

$$\begin{aligned} r^2 \frac{E_1}{P} \frac{\partial E_2}{\partial t} &= \frac{1}{P} \begin{pmatrix} 0 & 0 \\ 0 & 0 \end{pmatrix} \left[\begin{pmatrix} 22 & 11 \\ 21 & 21 \end{pmatrix} - i \begin{pmatrix} 11 & 21 \\ 12 & 11 \end{pmatrix} \right] \frac{\partial^2}{\partial t^2} E_1 \\ &+ \frac{1}{P} \begin{pmatrix} 0 & 0 \\ 0 & 0 \end{pmatrix} \left[\begin{pmatrix} 22 & 12 \\ 21 & 22 \end{pmatrix} - i \begin{pmatrix} 11 & 22 \\ 12 & 12 \end{pmatrix} \right] \frac{\partial^2}{\partial t^2} E_2; \end{aligned} \quad (7)$$

It follows from (1) that

$$\begin{aligned} \begin{pmatrix} 22 & 11 \\ 21 & 21 \end{pmatrix} + i \begin{pmatrix} 11 & 21 \\ 12 & 11 \end{pmatrix} &= A_+ + iB_+; \\ \begin{pmatrix} 22 & 12 \\ 21 & 22 \end{pmatrix} + i \begin{pmatrix} 11 & 22 \\ 12 & 12 \end{pmatrix} &= iA_+ + B_+; \end{aligned} \quad (8)$$

where

$$\begin{aligned} A_+ &= a_e a_h - a_e c_h - d_e d_h - i d_e b_h - b_e b_h + i b_e d_h + c_e c_h - c_e a_h; \\ B_+ &= a_e b_h - i d_e a_h + i d_e c_h - b_e c_h + b_e a_h - c_e b_h + i c_e d_h + i a_e d_h; \end{aligned} \quad (9)$$

In the same fashion, one can arrive at

$$\begin{aligned} \begin{pmatrix} 22 & 11 \\ 21 & 21 \end{pmatrix} - i \begin{pmatrix} 11 & 21 \\ 12 & 11 \end{pmatrix} &= A_- + iB_-; \\ \begin{pmatrix} 22 & 12 \\ 21 & 22 \end{pmatrix} - i \begin{pmatrix} 11 & 22 \\ 12 & 12 \end{pmatrix} &= iA_- - B_-; \end{aligned} \quad (10)$$

where

$$\begin{aligned} A_- &= a_e a_h + a_e c_h - d_e d_h + i d_e b_h - b_e b_h - i b_e d_h + c_e c_h + c_e a_h; \\ B_- &= a_e b_h - i d_e a_h - i d_e c_h - b_e c_h - b_e a_h - c_e b_h - i c_e d_h + i a_e d_h; \end{aligned} \quad (11)$$

Hence, the wave equations of left- and right-handed circularly polarized light¹ is written

$$\begin{aligned} r^2 \frac{E_1}{P} \frac{\partial E_2}{\partial t} &= \begin{pmatrix} 0 & 0 \\ 0 & 0 \end{pmatrix} A_+ \frac{\partial^2}{\partial t^2} \frac{E_1}{P} \frac{\partial E_2}{\partial t} + i \begin{pmatrix} 0 & 0 \\ 0 & 0 \end{pmatrix} B_+ \frac{\partial^2}{\partial t^2} \frac{E_1 + iE_2}{P} \frac{\partial E_2}{\partial t}; \\ r^2 \frac{E_1 + iE_2}{P} \frac{\partial E_2}{\partial t} &= \begin{pmatrix} 0 & 0 \\ 0 & 0 \end{pmatrix} A_+ \frac{\partial^2}{\partial t^2} \frac{E_1 + iE_2}{P} \frac{\partial E_2}{\partial t} + i \begin{pmatrix} 0 & 0 \\ 0 & 0 \end{pmatrix} B_+ \frac{\partial^2}{\partial t^2} \frac{E_1}{P} \frac{\partial E_2}{\partial t}; \end{aligned} \quad (13)$$

It should be pointed out that the interaction between left- and right-handed polarized light arises in Eq.(13), which is analogous to the Josephson's effect and may therefore be of physical interest.

The coupling of left-handed polarized light to the right-handed one can be characterized by the frequency shift ω_L and ω_R , namely, the amplitudes of left- and right-handed circularly polarized light propagating along the z -direction are written as follows

$$E_L = \exp \left[\frac{1}{i} (\omega_L + \omega_L) t \right] \exp \left[\frac{1}{c} z + \frac{i}{L} \right]; \quad E_R = \exp \left[\frac{1}{i} (\omega_R + \omega_R) t \right] \exp \left[\frac{1}{c} z + \frac{i}{R} \right]; \quad (14)$$

Insertion of Eq.(14) into Eq.(13) yields

$$A_+ \omega_L^2 E_L = A_+ (\omega_L + \omega_L)^2 E_L + iB_+ (\omega_L + \omega_R)^2 E_R; \quad A_+ \omega_R^2 E_R = A_+ (\omega_R + \omega_R)^2 E_R + iB_+ (\omega_L + \omega_L)^2 E_L; \quad (15)$$

¹For simplicity, without loss of generality, it is assumed that the two mutually perpendicular real unit polarization vectors $\mathbf{u}(k;1)$ and $\mathbf{u}(k;2)$ can be taken to be as follows: $\mathbf{u}_1(k;1) = \mathbf{u}_2(k;2) = 1$, $\mathbf{u}_1(k;2) = \mathbf{u}_2(k;1) = 0$ and $\mathbf{u}_3(k;1) = \mathbf{u}_3(k;2) = 0$. Thus by the aid of the formula $E = \frac{\partial A}{\partial t}$ for the electric field strength, in the second-quantization framework one can arrive at [3]

$$\begin{aligned} E_R &= \frac{E_1 + iE_2}{P} = i \int d^3k \frac{1}{2(2\pi)^3} [\mathbf{a}_L(k) \exp(ik \cdot \mathbf{x}) - \mathbf{a}_R(k) \exp(ik \cdot \mathbf{x})]; \\ E_L &= \frac{E_1}{P} \frac{\partial E_2}{\partial t} = i \int d^3k \frac{1}{2(2\pi)^3} [\mathbf{a}_R(k) \exp(ik \cdot \mathbf{x}) - \mathbf{a}_L(k) \exp(ik \cdot \mathbf{x})]; \end{aligned} \quad (12)$$

