

Compensation of decoherence from telegraph noise by means of bang-bang control

Henryk Gutmann and Frank K. Wilhelm

Sektion Physik and CeNS, Ludwig-Maximilians-Universität, 80333 München, Germany

William M. Kaminsky

Department of Physics, Massachusetts Institute of Technology, Cambridge, Massachusetts 02139

Seth Lloyd

Department of Mechanical Engineering, Massachusetts Institute of Technology, Cambridge, Massachusetts 02139

With the growing efforts in isolating solid-state qubits from external decoherence sources, the origins of noise inherent to the material start to play a relevant role. One representative example are charged impurities in the device material or substrate, which typically produce telegraph noise and can hence be modelled as bistable actuators. In order to demonstrate the possibility of the active suppression of the disturbance from a single actuator, we theoretically implement an elementary bang-bang control protocol. We numerically simulate the random walk of the qubit state on the Bloch sphere with and without bang-bang compensation by means of the stochastic Schrödinger equation and compare it with an analytical saddle point solution of the corresponding Langevin equation in the long-time limit. We find that the deviation with respect to the noiseless case is significantly reduced when bang-bang pulses are applied, being scaled down approximately by the ratio of the bang-bang period to the typical flipping time of the bistable actuation. Our analysis gives not only the effect of bang-bang control on the variance of these deviations, but also their entire distribution. As a result, we expect that bang-bang control works as a high-pass filter on the spectrum of noise sources. This indicates how the influence of $1=f$ noise ubiquitous to the solid state world can be reduced.

PACS numbers: 03.65.Yz, 03.67.Lx, 05.40.-a

In order to implement solid-state quantum information processing devices, the decoherence acting on the quantum states has to be carefully understood, controlled and eliminated. So far, research has concentrated on decoupling from external noise sources (like thermal heat baths and electromagnetic noise). With the success of this effort, noise sources intrinsic to the material such as defect states increase in importance and have to be controlled in order to improve coherence even further.

Most external noise sources are composed of extended modes in the thermodynamic limit close to equilibrium such that their fluctuations are purely Gaussian. Thus, their influence can be modelled by an oscillator bath, see e.g. [1]. However, there are physical situations when this assumption fails [2, 3, 5]. In particular, this is true for localized noise sources with bounded spectra as they occur in disordered systems for hopping defect states [4]. Physical examples for this situation are background charges in charge qubits [5, 6, 7] or traps in the oxide layers of Josephson tunnel junctions [8]. Such localized noise sources are more realistically represented by a collection of bistable actuators [5, 9] (henceforth abbreviated *b*), as their noise spectrum is considerably non-Gaussian. If many of these noise sources with different flipping times are appropriately superimposed, they lead to $1=f$ noise [4, 10, 11]. With the progress of fabrication technology and miniaturization of qubits, we expect however that there might only be a few actuators in a qubit [8].

We analyze the impact of a single actuator in the

semiclassical limit, where it acts as a source of telegraph noise. We apply an open loop quantum control technique, namely quantum bang-bang [12, 13, 14], which is designed suitably for slowly fluctuating noise sources. We simulate the noise-influenced qubit dynamics with and without bang-bang correction by integrating the time-dependent Schrödinger equation for each specific realization of the noise. We present the resulting random walks around the unperturbed signal on the Bloch sphere and analyze the quality of this suppression by an comparison of the ensemble averaged deviations of these random walks with and without bang-bang correction.

We describe our system by the effective Hamiltonian

$$H_q^e(t) = H_q + H_{qb}^{\text{noise}}(t) \quad (1)$$

$$H_q = \tilde{\omega}_q \hat{z}^q + \tilde{\omega}_q \hat{x}^q \quad H_{qb}^{\text{noise}}(t) = \tilde{\omega}_b(t) \hat{z}^q \quad (2)$$

where $\tilde{\omega}_q$ denotes the coupling strength between the actuator and the qubit and $\tilde{\omega}_b(t)$ represents a symmetric telegraph process that is flipping between ± 1 , whose switching events are Poisson distributed with a mean separation τ_b between two flips.

On a microscopic level, such noise is typically generated by coupling the qubit to a two-state impurity, which is in turn coupled to a heat bath causing the two-state system to flip randomly and incoherently. Our model corresponds to the semiclassical limit and should be accurate whenever the coupling of the impurity to the bath is much stronger than its coupling to the qubit [2, 5] such that the qubit does not act back on the noise source.

The assumption of a symmetrical telegraph process corresponds to a high bath temperature compared to the impurity level spacing. This restriction is not essential for the following investigations, for an asymmetric noise signal would only produce an additional constant drift.

We describe the resulting evolution of the noise in unenclosed qubit by a stochastic Schrödinger equation [15, 16] with the time-dependent Hamiltonian (2). For any initial state of the qubit, we numerically integrate

$$|\psi(t)\rangle = T \exp \left[-i \int_0^t H_q^{(e)}(t') dt' \right] |\psi(0)\rangle \quad (3)$$

with T the time-ordering operator and $|\psi\rangle$ the state vector of the two-state system. The result is a random walk on the Bloch sphere, which is centered around the free precession corresponding to ω_q and ω_q .

We implement the following idealized open quantum control scheme: apply an infinite train of π -pulses on the qubit with negligibly short pulse durations and a constant separation time t_{bb} between neighboring pulses. In doing so, we intend to average out the $\hat{\sigma}_z$ parts of the effective Hamiltonian (and thereby in particular the noise term) on time scales large compared to t_{bb} . This is accomplished by iteratively spin-flipping the qubit and thus effectively switching the sign of the noisy part of the Hamiltonian. This mechanism thus works analogously to the well-known spin-echo procedure, specially the Carr-Purcell procedure of NMR [17]. We expect to compensate a fraction of the telegraph noise effects: the size of the random walk induced by the noise is determined by the typical time separation of the fluctuations in unenclosed between two flips t_{bb} and its coupling strength and scales roughly with t_{bb} [5]. Using bang-bang, the bias in unenclosed remains uncompensated for at most a single bang-bang period. Thus, we reduce the in unenclosed of the bias randomly by an average factor of $t_{bb} = t_{bb}$.

As generic conditions of the system dynamics we consider for the numerical simulations $\omega_q = \omega_q = 0$. Without loss of generality, we assume $\langle \hat{\sigma}_z^q \rangle = +1$ as an initial state. If there were no noise, the spin would precess on the Bloch sphere around the rotation axis $\hat{\sigma}_x^q + \hat{\sigma}_z^q$. So we expect for not too large an interaction strength ($\gamma \ll 1$) a slight deviation of the individual quantum trajectory from the free evolution case. We take $\gamma = 0.1$ for our coupling strength. All the following time and energy measures are given in units of the unperturbed system Hamiltonian: our time unit is $\tau_{sys} = 1/\omega_0$ and our energy unit is $E = \frac{\omega_q^2}{2} + \frac{\omega_q^2}{2} = \frac{\omega_0^2}{2}$. Note that in these units, a period lasts $\tau_{sys} = 2$. We have integrated Equ. (3) and averaged over $N = 1000$ realizations. The time scale ratio $t_{bb} = t_{bb} = 10$ if not denoted otherwise. We characterize our results by the root-mean-square de-

viation from the unperturbed signal

$$\sigma_{rms}(t) = \sqrt{\frac{1}{N} \sum_j \left(\tilde{x}_j^q(t) - \tilde{x}_{noisy,j}^q(t) \right)^2} \quad (4)$$

In order to characterize the degree of noise suppression by means of bang-bang control, we define the suppression factors for a given time t_0

$$S_{t_0}(b = bb) = \frac{\sigma_{rms}^b(t_0)}{\sigma_{rms}^{bb}(t_0)} \quad (5)$$

The deviation as a function of time is plotted in Fig. (1).




FIG. 1: Time evolution of the mean deviations for b-induced random walks with and without bang-bang. The straight lines are square-roots of the analytical derived random walk model variances (plotted as triangles). Inset: Transverse and perpendicular components of bang-bang suppressed noise.

We recognize that the total deviations on intermediate time scales are suppressed by a ratio of ~ 10 . Detailed analysis shows that the tangential and the orthogonal deviation, corresponding respectively to dephasing and relaxation, are of the same size for the uncompensated case. In contrast, the bang-bang modulation mostly compensates the dephasing-type deviation, as shown in the inset of Fig. (1).

We now develop analytical random walk models for our system. Although the random walk on the Bloch sphere is in general two-dimensional, bang-bang control effectively reduces it to a one-dimensional model, representing the relevant perpendicular part. We restrict ourselves to the long-time limit.

For simplicity, we replace the fluctuating number of random walk steps for a given time t of noisy evolution by its expectation value t/t_{bb} [18]. This allows to use the number of random walk steps as time parameter. We encounter different one-step-distributions, depending on whether the number of steps is odd or even, corresponding to an "up" or "down" state of the b [22]. The

step-size distribution of the b model in our small deviation regime is given from Poisson statistics

$$b_{\text{odd=even}}(x) = \frac{e^{-x} x^{\lfloor x \rfloor}}{\lfloor x \rfloor!} \quad (6)$$

with $x = \frac{b}{b_{\text{unit}}}$ as a typical random walk one-step deviation. b_{unit} is a time unit, corresponding to a discrete step length $x_{\text{unit}} = \frac{b}{b_{\text{unit}}}$ of the random walk. $\lfloor x \rfloor$ denotes the Heaviside step function. We neglect the correlations between transverse and perpendicular deviations as they average out in the long-time limit.

For the bang-bang suppressed random walk, the flipping positions of the b-noise sign in the bang-bang time-slots are essentially randomly distributed as long as $b_{\text{bb}} \ll b$. We find a homogeneous step-size distribution between zero deviation and a maximum $x = \frac{b}{b_{\text{bb}}}$,

$$b_{\text{odd=even}}^{\text{bb}}(x) = \frac{\lfloor x \rfloor! \lfloor \frac{b}{b_{\text{bb}}} - x \rfloor!}{\lfloor \frac{b}{b_{\text{bb}}} \rfloor!} \quad (7)$$

The ubiquitous $\frac{1}{2}$ occurs, because the bang-bang sequence also averages over the static q -term and hence slows down the free evolution.

By means of these one-step probability distributions, we are able to calculate via convolution the distributions for $2N$ -step random walks. Specifically, they are the inverse Fourier transforms of the N -fold products of the Fourier transforms of the two-step distribution [18]. For the uncompensated case, we find

$$b_{2N}(x) = \int_{-\infty}^{\infty} \frac{dk}{2} e^{ikx} \frac{1}{1 - 2\cos(k)e^{i\frac{b}{b_{\text{unit}}}} + e^{i\frac{2b}{b_{\text{unit}}}}} \quad (8)$$

whereas for the compensated case

$$b_{2N}^{\text{bb}}(x) = \int_{-\infty}^{\infty} \frac{dk}{2} e^{ikx} \frac{[1 - \cos((\frac{b}{b_{\text{bb}}} + 1)k)]^N}{[1 - \cos(k)]^N} \quad (9)$$

Already for random walk step-numbers in the order of ten, the resulting distributions are almost Gaussian. Their standard deviations give the rms deviations of the random walk models plotted in Fig. (1). As expected, they grow as a square-root of the number of steps.

The above integrals can be evaluated analytically using the saddle point approximation. We find variances of

$$b(N) = \frac{b}{2N} \quad (10)$$

for the pure b random walk and

$$b_{\text{bb}}(N) = \frac{b}{3} \quad (11)$$

for the compensated one. In the large- N limit, this model shows excellent agreement with the simulation.

Beyond predicting the variance, our analysis also allows evaluation of the full distribution. We compared

evolution with and without bang-bang compensation via simulations with 10^4 realizations and calculated the full distribution function for a evolution time $t_0 = \frac{b}{b_{\text{sys}}}$. The numerical histograms of the deviation with their respective one- and two-dimensional Gaussian fits are shown in Fig.(2).




FIG. 2: Histograms of the deviation from free evolution with and without bang-bang and fits to the expected two- (pure b case), respectively one-dimensional (bang-bang corrected evolution) random walk statistics. Numerical data collected over 10000 realizations at a fixed time $t_0 = \frac{b}{b_{\text{sys}}}$. With $b = 0.01 b_{\text{sys}}$ the random walk distributions are calculated for $N = \frac{b}{b_{\text{sys}}} = 100$ steps. (NB: The x-axis scale of the right graph is 15 times smaller than that of the left graph.)

We observe that not only the bang-bang compensated distribution is much narrower than the uncompensated distribution, but also that its shape is qualitatively different: its maximum is at zero error whereas the uncompensated distribution has its maximum at a finite error $j \approx 0.01$ and zero probability of zero error.

We have systematically studied suppression factors for different ratios of the switching time $b_{\text{bb}} = b_{\text{bb}}$ at a constant actuator flipping rate $b_{\text{bb}} = 10^{-2} b_{\text{sys}}$ and evolution time $t_0 = \frac{b}{b_{\text{sys}}}$. The numerical data in Fig. (3) show that the suppression efficiency is linear in the bang-bang repetition rate, $S = \frac{b}{b_{\text{bb}}} = \frac{b}{b_{\text{bb}}}$. The numerically derived value of the coefficient, $\frac{1.679}{3}$, is in excellent agreement with our analytical result $\frac{1.679}{3}$, $\frac{1.732}{3}$ from the saddle point approximation, Eqs. (10) and (11). This small discrepancy reflects the correlations between the transverse and longitudinal random walk in the uncompensated case, see Fig. (2).

We have demonstrated the ability of a bang-bang protocol to compensate environmental fluctuations with frequency $\omega = \frac{1}{b_{\text{bb}}}$. Thus, bang-bang is acting as a "high pass filter" for noise with a roll-off frequency of $\omega = \frac{1}{b_{\text{bb}}}$. Evidently, the bang-bang correction is suitable for suppressing the impact of telegraph noise on qubits and can enhance the coherence by orders of magnitude. The application of the scheme which we outlined requires a relatively strict separation of time scales: One has to be able to flip the spin very rapidly, typically two orders of magnitude faster than b_{bb} . It remains to be investigated how this scheme works with pulse durations that are finite rather than infinitesimal. Moreover, we have assumed that the environment produces symmetric tele-




FIG. 3: The suppression factor $S_{t_0}(t_b = t_{bb}) = \frac{\gamma_{\text{eff}}^{\text{bfl}}(t_0)}{\gamma_{\text{eff}}^{\text{bb}}(t_0)}$ evaluated for $t_0 = t_{\text{sys}}$ as a function of the ratio of the hopping time t_b and the bang-bang pulse separation t_{bb} .

graph noise regardless of the qubit dynamics. Clearly, the issue of when one may neglect feedback effects between the qubit and bath must be critically revisited in the low-temperature limit. We speculate that the setup is promising for 1=f-noise, as in particular the most harmful and predominantly low-frequency fraction of a corresponding ensemble of actuators would be compensated most strongly. Finally, one has to be aware that also the static term of the Hamiltonian is averaged out, and this generally reduces the degree of control on the qubit. This is only a technical constraint, however, as one could imagine interchanging two different types of bang-bang pulses to admit corresponding quantum gate operations.

Another approach for decoupling from slow noise is to choose an appropriate working point with a dominant term x in the static Hamiltonian. The action of this term can be understood as a rapid flipping of the spin, similar to our bang-bang protocol. Using a Gaussian approximation the noise from the bath with standard rate expressions (e.g., [19]), it can be shown that the dephasing rate reads $\gamma_x = \gamma_b^2$ instead of $\gamma_x = \gamma_b$, which corresponds to the same amount of reduction as in our case. This scheme has been implemented in superconducting qubits [20]. In that case, it turned out that because the x term was limited by fabrication, this consideration led to a major redesign. Our compensation scheme purely relies on external control and thus keeps the hardware design flexible.

A related problem has been addressed in Ref. [21], which deals with bang-bang suppression of Gaussian 1=f-noise, i.e., a bosonic bath with an appropriate sub-Ohmic spectrum. That system is treated in the weak-coupling approximation, i.e. it assumes $S(!) \approx 1$ at low frequencies where $S(!)$ is the noise spectral function. Both assumptions are serious constraints in the 1=f-case [4, 5]. Our work is not constrained to weak coupling, takes the full non-Gaussian statistics of telegraph noise into account, and gives the full resulting distribution of errors.

In summary, we examined the decoherence of a sin-

gle qubit from a single symmetric telegraph noise source and proposed an adequate open quantum control compensation protocol for suppressing its impact. We simulated the qubit's dynamics using a stochastic Schrödinger equation and analyzed its deviation from free evolution. We formulated analytically solvable one- and two-dimensional random walk models, which are in excellent agreement with the simulations in the long time limit. Specially, we show quantitatively, how the degree of noise compensation is controlled by the ratio between hopping time scale and bang-bang pulse length. We give the full statistics of deviations in both cases.

We thank T.P. Orlando, I. Goychuk, J. von Delft and especially A. Kack for helpful and insights deepening discussions. HG and FKW are also indebted to T.P. Orlando for his great hospitality at MIT. WMK gratefully acknowledges fellowship support from the Fannie and John Hertz Foundation. This work was supported by a DAAD NSF travel grant, by ARO project P-43385-PH-QC and the DFG through SFB 631.

-
- [1] U. Weiss, Quantum Dissipative Systems (World Scientific, Singapore, 2001).
 - [2] H. Gassmann, F. Marquardt, and C. Bruder, Phys. Rev. E 66, 041111 (2002).
 - [3] N. P. Rokov'ef and P. Stamp, Rep. Prog. Phys. 63, 669 (2000).
 - [4] P. Dutta and P. M. Hom, Rev. Mod. Phys. 53, 497 (1981).
 - [5] E. Paladino, L. Faoro, G. Falci, and R. Fazio, Phys. Rev. Lett. 88, 228304 (2002).
 - [6] H. Müller, M. Fulam, T. Heinzel, and K. Ensslin, Europhys. Lett. 55, 253 (2001).
 - [7] A. Zorin et al., Phys. Rev. B 53, 13682 (1996).
 - [8] R. Waki and D. van Harlingen, Phys. Rev. Lett. 58, 1687 (1987).
 - [9] T. Y. Takura and Y. Tokura, cond-mat/0303412 (2003).
 - [10] M. B. Weissmann, Rev. Mod. Phys. 60, 537 (1988).
 - [11] J. M. Martinis et al., Phys. Rev. B 67, 094510 (2003).
 - [12] S. Lloyd and L. Viola, Phys. Rev. A 58, 2733 (1998).
 - [13] S. Lloyd, E. Knill, and L. Viola, Phys. Rev. Lett. 82, 2417 (1999).
 - [14] S. Lloyd, E. Knill, and L. Viola, Phys. Rev. Lett. 83, 4888 (1999).
 - [15] N. G. van Kampen, Stochastic processes in physics and chemistry (Elsevier, Amsterdam, 1997).
 - [16] L. Arnold, stochastische Differentialgleichungen (Okinbourg, München, 1973).
 - [17] H. Carr and E. Purcell, Phys. Rev. 94, 630 (1954).
 - [18] G. H. Weiss, Aspects and Applications of the Random Walk (North-Holland, Amsterdam, 1994).
 - [19] C. van der Wal, F. Wilhelm, C. Hamers, and J. Mooij, Eur. Phys. J. B 31, 111 (2003).
 - [20] D. Vion et al., Science 296, 886 (2002).
 - [21] K. Shiozawa and D. Lidar, quant-ph/0211081 (unpublished).
 - [22] We assume the bath being initially in its "upper" state. This restriction is of no relevance for the long time limit.

